

Title: Early UE discussions. Technically endorsed R'99 and Rel-4/Rel-5 category A CRs to TS 25.331.

Source: TSG-RAN WG2

Agenda item: 8.7.11

Doc-1st-	Status-1st-	Spec	CR	Rev	Phase	Subject	Cat	Version	Version
R2-023239	Technically endorsed	25.331	1758	2	R'99	Early UE Specific Behaviour Information in RRC Connection Request / inter RAT info	F	3.12.0	3.13.0
R2-023240	Technically endorsed	25.331	1759	2	Rel-4	Early UE Specific Behaviour Information in RRC Connection Request / inter RAT info	A	4.7.0	4.8.0
R2-023241	Technically endorsed	25.331	1760	2	Rel-5	Early UE Specific Behaviour Information in RRC Connection Request / inter RAT info	A	5.2.0	5.3.0
R2-023242	Technically endorsed	25.331	1761	1	R'99	Early UE Specific Behaviour Information in Handover Complete / Setup Complete	F	3.12.0	3.13.0
R2-023243	Technically endorsed	25.331	1762	1	Rel-4	Early UE Specific Behaviour Information in Handover Complete / Setup Complete	A	4.7.0	4.8.0
R2-023244	Technically endorsed	25.331	1763	1	Rel-5	Early UE Specific Behaviour Information in Handover Complete / Setup Complete	A	5.2.0	5.3.0
R2-023236	Technically endorsed	25.331	1788	1	R'99	Compact IMEI-SV transfer across Uu and within RRC containers	F	3.12.0	3.13.0
R2-023237	Technically endorsed	25.331	1789	1	Rel-4	Compact IMEI-SV transfer across Uu and within RRC containers	A	4.7.0	4.8.0
R2-023238	Technically endorsed	25.331	1790	1	Rel-5	Compact IMEI-SV transfer across Uu and within RRC containers	A	5.2.0	5.3.0

## CHANGE REQUEST

⌘ 25.331 CR 1758 ⌘ rev 2 ⌘ Current version: 3.12.0 ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

**Proposed change affects:** UICC apps ⌘ ME  Radio Access Network  Core Network ⌘

<b>Title:</b>	⌘ Early UE Specific Behaviour Information in RRC Connection Request / inter RAT info
<b>Source:</b>	⌘ Alcatel, Fujitsu, Motorola, NEC, Orange, Siemens
<b>Work item code:</b>	⌘ TEI
	<b>Date:</b> ⌘ 05/11/2002
<b>Category:</b>	<b>⌘ B</b> Use <u>one of the following categories:</u> <b>F</b> (correction) <b>A</b> (corresponds to a correction in an earlier release) <b>B</b> (addition of feature), <b>C</b> (functional modification of feature) <b>D</b> (editorial modification) Detailed explanations of the above categories can be found in 3GPP <a href="#">TR 21.900</a> .
	<b>Release:</b> ⌘ R99 Use <u>one of the following releases:</u> 2 (GSM Phase 2) R96 (Release 1996) R97 (Release 1997) R98 (Release 1998) R99 (Release 1999) Rel-4 (Release 4) Rel-5 (Release 5) Rel-6 (Release 6)

**Reason for change:** ⌘ It is currently not possible to identify and handle faulty UE implementations

<b>Summary of change:</b>	Two transparent containers “UE Specific Behaviour Information 1 idle” (current assumption 4bits, tbc) and “UE Specific Behaviour Information 1 interRAT” (8bits) are added to the early messages at call setup and to the appropriate messages for SRNS relocation and inter rat handover, i.e. to the following messages:  RRC Connection Request, Inter RAT Handover Info, Inter RAT Handover Info with Inter RAT Capabilities, SRNS Relocation Info,  If UTRAN implements the CR but UE doesn't: - No impact. The RNC might not be able to adapt to specific UE behavior.  If UE implements the CR but UTRAN doesn't: - No impact. UTRAN will ignore the unknown extension and treat all UEs in the same way  If neither UE nor UTRAN implement the CR: - No impact.
---------------------------	---

**Consequences if not approved:** ⌘ Errors discovered in UEs can not be handled appropriately

<b>Clauses affected:</b>	⌘ 8.1.3.3, 8.1.16.3, 10.2.16b, 10.2.39, 10.3.3.51 (new), 10.3.3.52 (new), 11.2, 11.3, 11.5, 14.12.4.1, 14.12.4.2				
<b>Other specs</b>	<table border="1" style="display: inline-table; vertical-align: middle;"> <tr> <td style="text-align: center;">Y</td> <td style="text-align: center;">N</td> </tr> <tr> <td style="text-align: center;">X</td> <td></td> </tr> </table> Other core specifications ⌘	Y	N	X	
Y	N				
X					

<b>affected:</b>	<table border="1" style="display: inline-table; vertical-align: middle;"> <tr><td></td><td>X</td></tr> <tr><td>X</td><td></td></tr> </table>		X	X		Test specifications	
	X						
X							
<b>Other comments:</b>	⌘						

### How to create CRs using this form:

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>.

Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/>. For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

### 8.1.3.3 RRC CONNECTION REQUEST message contents to set

The UE shall, in the transmitted RRC CONNECTION REQUEST message:

- 1> set the IE "Establishment cause" to the value of the variable ESTABLISHMENT\_CAUSE;
- 1> set the IE "Initial UE identity" to the value of the variable INITIAL\_UE\_IDENTITY;
- 1> set the IE "Protocol error indicator" to the value of the variable PROTOCOL\_ERROR\_INDICATOR;
- 1> include a measurement report in the IE "Measured results on RACH", as specified in the IE "Intra-frequency reporting quantity for RACH reporting" and the IE "Maximum number of reported cells on RACH" in System Information Block type 11; and
- 1> include in the IE "Measured results on RACH" all requested reporting quantities for cells for which measurements are reported; and
- 1> take care that the maximum allowed message size is not exceeded when forming the IE "Measured results on RACH".

[The UE shall not include the IE "UE Specific Behaviour Information 1 idle".](#)

### 8.1.16.3 INTER RAT HANDOVER INFO message contents to set

The UE shall:

- 1> include the IE "Predefined configuration status information" and the IE "UE security information";
- 1> include the IE "UE capability container", containing the IE "UE radio access capability" and the IE "UE radio access capability extension", in accordance with the following:
  - 2> if the UE supports multiple UTRA FDD Frequency Bands; or
  - 2> if the UE supports a single UTRA FDD Frequency Band different from 2100 MHz:
    - 3> include the IE "UE radio access capability", excluding IEs "RF capability FDD" and "Measurement capability";
    - 3> include the IE "UE radio access capability extension", including the IEs "RF capability FDD extension" and the "Measurement capability extension" associated with each supported UTRA FDD frequency band indicated in the IE "Frequency band".
  - 2> else:
    - 3> include the IE "UE radio access capability", including the IEs "RF capability FDD" and "Measurement capability" associated with the 2100 MHz UTRA FDD frequency band;
    - 3> include the IE "UE radio access capability extension", including the IEs "RF capability FDD extension" and the "Measurement capability extension" associated with each supported UTRA FDD frequency band indicated in the IE "Frequency band".

[1> The UE shall not include the IE "UE Specific Behaviour Information 1 interRAT".](#)

- 1> initiate the transfer of the INTER RAT HANDOVER INFO message via the other radio access technology, using radio access technology-specific procedures;
- 1> store the IE "Predefined configuration status information", the IE "UE security information", the IE "UE radio access capability" and the IE "UE radio access capability extension", if included in the INTER RAT HANDOVER MESSAGE, in variable INTER\_RAT\_HANDOVER\_INFO\_TRANSFERRED;
- 1> and the procedure ends.

## 10.2.16d INTER RAT HANDOVER INFO

This message is sent by the UE via another radio access technology to provide information to the target RNC when preparing for a handover to UTRAN.

RLC-SAP: N/A (Sent through a different RAT)

Logical channel: N/A (Sent through a different RAT)

Direction: UE → UTRAN

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
<b>Radio Bearer IEs</b>				
Predefined configuration status information	OP		Predefined configuration status information 10.3.4.5a	
<b>UE Information elements</b>				
UE security information	OP		UE security information 10.3.3.42b	
> <a href="#">UE Specific Behaviour Information 1 interRAT</a>	<a href="#">OP</a>		<a href="#">UE Specific Behaviour Information 1 interRAT 10.3.3.52</a>	<a href="#">This IE shall not be included in this version of the protocol</a>
UE capability container	OP			
>UE radio access capability	MP		UE radio access capability 10.3.3.42	
>UE radio access capability extension	MP		UE radio access capability extension 10.3.3.42a	Although this IE is not always required, the need has been set to MP to align with the ASN.1

## 10.2.39 RRC CONNECTION REQUEST

RRC Connection Request is the first message transmitted by the UE when setting up an RRC Connection to the network.

RLC-SAP: TM

Logical channel: CCCH

Direction: UE → UTRAN

<u>Information Element/Group name</u>	<u>Need</u>	<u>Multi</u>	<u>Type and reference</u>	<u>Semantics description</u>
Message Type	MP		Message Type	
<b>UE information elements</b>				
Initial UE identity	MP		Initial UE identity 10.3.3.15	
Establishment cause	MP		Establishment cause 10.3.3.11	
Protocol error indicator	MD		Protocol error indicator 10.3.3.27	Default value is FALSE
<a href="#"><u>&gt;UE Specific Behaviour Information 1 idle</u></a>	<a href="#"><u>OP</u></a>		<a href="#"><u>UE Specific Behaviour Information 1 idle</u></a> <a href="#"><u>10.3.3.51</u></a>	<a href="#"><u>This IE shall not be included in this version of the protocol</u></a>
<b>Measurement information elements</b>				
Measured results on RACH	OP		Measured results on RACH 10.3.7.45	

If the encoded message does not fill a transport block, the RRC layer shall insert padding according to subclause 12.1.

### [10.3.3.51 UE Specific Behaviour Information 1 idle](#)

[This IE indicates the UE conformance typically for RRC connection establishment from idle mode.](#)

<u>Information Element/Group name</u>	<u>Need</u>	<u>Multi</u>	<u>Type and Reference</u>	<u>Semantics description</u>
<a href="#"><u>UE Specific Behaviour Information 1 idle</u></a>	<a href="#"><u>MP</u></a>		<a href="#"><u>bit string(14)</u></a>	

### [10.3.3.52 UE Specific Behaviour Information 1 interRAT](#)

[This IE indicates the UE conformance typically for RRC connection establishment from another RAT.](#)

<u>Information Element/Group name</u>	<u>Need</u>	<u>Multi</u>	<u>Type and Reference</u>	<u>Semantics description</u>
<a href="#"><u>UE Specific Behaviour Information 1 interRAT</u></a>	<a href="#"><u>MP</u></a>		<a href="#"><u>bit string(8)</u></a>	

## 11.2 PDU definitions

```
--*****
-- TABULAR: The message type and integrity check info are not
-- visible in this module as they are defined in the class module.
-- Also, all FDD/TDD specific choices have the FDD option first
-- and TDD second, just for consistency.
--*****
```

PDU-definitions DEFINITIONS AUTOMATIC TAGS ::=

BEGIN

```
--*****
-- IE parameter types from other modules
--*****
```

```

--***** IMPORTS *****

IMPORTS

-- Core Network IEs :
CN-DomainIdentity,
CN-InformationInfo,
CN-InformationInfoFull,
NAS-Message,
PagingRecordTypeID,
-- UTRAN Mobility IEs :
URA-Identity,
-- User Equipment IEs :
ActivationTime,
C-RNTI,
CapabilityUpdateRequirement,
CellUpdateCause,
CipheringAlgorithm,
CipheringModeInfo,
DSCH-RNTI,
EstablishmentCause,
FailureCauseWithProtErr,
FailureCauseWithProtErrTrId,
UESpecificBehaviourInformationInterRAT,
UESpecificBehaviourInformationIdle,
InitialUE-Identity,
IntegrityProtActivationInfo,
IntegrityProtectionModeInfo,
N-308,
PagingCause,
PagingRecordList,
ProtocolErrorIndicator,
ProtocolErrorIndicatorWithMoreInfo,
Rb-timer-indicator,
RedirectionInfo,
RejectionCause,
ReleaseCause,
RRC-StateIndicator,
RRC-TransactionIdentifier,
SecurityCapability,
START-Value,
STARTList,
U-RNTI,
U-RNTI-Short,
UE-RadioAccessCapability,
UE-RadioAccessCapability-v370ext,
UE-RadioAccessCapability-v380ext,
UE-RadioAccessCapability-v3a0ext,
DL-PhysChCapabilityFDD-v380ext,
UE-ConnTimersAndConstants,
UE-ConnTimersAndConstants-v3a0ext,
UE-SecurityInformation,
URA-UpdateCause,
UTRAN-DRX-CycleLengthCoefficient,
WaitTime,
-- Radio Bearer IEs :
DefaultConfigIdentity,
DefaultConfigMode,
DL-CounterSynchronisationInfo,
PredefinedConfigIdentity,
PredefinedConfigStatusList,
RAB-Info,
RAB-Info-Post,
RAB-InformationList,
RAB-InformationReconfigList,
RAB-InformationSetupList,
RB-ActivationTimeInfoList,
RB-COUNT-C-InformationList,
RB-COUNT-C-MSB-InformationList,
RB-IdentityList,
RB-InformationAffectedList,
RB-InformationReconfigList,
RB-InformationReleaseList,
SRB-InformationSetupList,
SRB-InformationSetupList2,
UL-CounterSynchronisationInfo,
-- Transport Channel IEs:
CPCH-SetID,
DL-AddReconfTransChInfo2List,

```

```

DL-AddReconfTransChInfoList,
DL-CommonTransChInfo,
DL-DeletedTransChInfoList,
DRAC-StaticInformationList,
TFC-Subset,
TFCS-Identity,
UL-AddReconfTransChInfoList,
UL-CommonTransChInfo,
UL-DeletedTransChInfoList,
-- Physical Channel IEs :
Alpha,
CCTrCH-PowerControlInfo,
ConstantValue,
ConstantValueTdd,
CPCH-SetInfo,
DL-CommonInformation,
DL-CommonInformationPost,
DL-InformationPerRL,
DL-InformationPerRL-List,
DL-InformationPerRL-ListPostFDD,
DL-InformationPerRL-PostTDD,
DL-PDSCH-Information,
DPCH-CompressedModeStatusInfo,
FrequencyInfo,
FrequencyInfoFDD,
FrequencyInfoTDD,
MaxAllowedUL-TX-Power,
PDSCH-CapacityAllocationInfo,
PDSCH-Identity,
PrimaryCCPCH-TX-Power,
PUSCH-CapacityAllocationInfo,
PUSCH-Identity,
RL-AdditionInformationList,
RL-RemovalInformationList,
SpecialBurstScheduling,
SSDT-Information,
TFC-ControlDuration,
TimeslotList,
TX-DiversityMode,
UL-ChannelRequirement,
UL-ChannelRequirementWithCPCH-SetID,
UL-DPCH-Info,
UL-DPCH-InfoPostFDD,
UL-DPCH-InfoPostTDD,
UL-TimingAdvance,
UL-TimingAdvanceControl,
-- Measurement IEs :
AdditionalMeasurementID-List,
Frequency-Band,
EventResults,
InterRAT-TargetCellDescription,
MeasuredResults,
MeasuredResults-v390ext,
MeasuredResultsList,
MeasuredResultsOnRACH,
MeasurementCommand,
MeasurementIdentity,
MeasurementReportingMode,
PrimaryCCPCH-RSCP,
SFN-Offset-Validity,
TimeslotListWithISCP,
TrafficVolumeMeasuredResultsList,
UE-Positioning-GPS-AssistanceData,
UE-Positioning-Measurement-v390ext,
UE-Positioning-OTDOA-AssistanceData,
UE-Positioning-OTDOA-AssistanceData-UEB,
-- Other IEs :
BCCH-ModificationInfo,
CDMA2000-MessageList,
GSM-MessageList,
InterRAT-ChangeFailureCause,
InterRAT-HO-FailureCause,
InterRAT-UE-RadioAccessCapabilityList,
InterRAT-UE-SecurityCapList,
IntraDomainNasNodeSelector,
ProtocolErrorMoreInformation,
Rplmn-Information,
SegCount,
SegmentIndex,
SFN-Prime,

```

```

SIB-Data-fixed,
SIB-Data-variable,
SIB-Type
FROM InformationElements

maxSIBperMsg
FROM Constant-definitions;

-- ****
-- 
-- HANOVER TO UTRAN COMPLETE
-- 
-- ****

HandoverToUTRANComplete ::= SEQUENCE {
    --TABULAR: Integrity protection shall not be performed on this message.
    -- User equipment IEs
        -- TABULAR: startList is conditional on history.
        startList                      STARTList                  OPTIONAL,
    -- Radio bearer IEs
        count-C-ActivationTime         ActivationTime          OPTIONAL,
    -- Extension mechanism for non- release99 information
        nonCriticalExtensions        SEQUENCE {}           OPTIONAL
}
}

-- ****
-- 
-- INTER RAT HANOVER INFO
-- 
-- ****

InterRATHandoverInfo ::= SEQUENCE {
    -- This structure is defined for historical reasons, backward compatibility with 04.18
    predefinedConfigStatusList      CHOICE {
        absent                     NULL,
        present                    PredefinedConfigStatusList
    },
    uE-SecurityInformation         CHOICE {
        absent                     NULL,
        present                    UE-SecurityInformation
    },
    ue-CapabilityContainer         CHOICE {
        absent                     NULL,
        -- present is an octet aligned string containing IE UE-RadioAccessCapabilityInfo
        present                   OCTET STRING (SIZE (0..63))
    },
    -- Non critical extensions
    v390NonCriticalExtensions     CHOICE {
        absent                     NULL,
        present                    SEQUENCE {
            interRATHandoverInfo-v390ext   InterRATHandoverInfo-v390ext-IES,
            -- Reserved for future non critical extension
            v3a0NonCriticalExtensions    SEQUENCE {
                interRATHandoverInfo-v3a0ext   InterRATHandoverInfo-v3a0ext-IES,
                v3d0NonCriticalExtensions    SEQUENCE {
                    interRATHandoverInfo-v3d0ext   InterRATHandoverInfo-v3d0ext-IES,
                    -- Reserved for future non critical extension
                    nonCriticalExtensions       SEQUENCE {} OPTIONAL
                } OPTIONAL
            } OPTIONAL
        }
    }
}

InterRATHandoverInfo-v390ext-IES ::= SEQUENCE {
    -- User equipment IEs
        ue-RadioAccessCapability-v380ext    UE-RadioAccessCapability-v380ext          OPTIONAL,
        dl-PhysChCapabilityFDD-v380ext     DL-PhysChCapabilityFDD-v380ext
}

InterRATHandoverInfo-v3a0ext-IES ::= SEQUENCE {
    -- User equipment IEs
        ue-RadioAccessCapability-v3a0ext    UE-RadioAccessCapability-v3a0ext          OPTIONAL
}

InterRATHandoverInfo-v3d0ext-IES ::= SEQUENCE {

```

```

-- User equipment IEs
    uESpecificBehaviourInformationlnterRAT      UESpecificBehaviourInformationlnterRAT
OPTIONAL
}

-- ****
-- RRC CONNECTION REQUEST
-- ****

RRCConnectionRequest ::= SEQUENCE {
    -- TABULAR: Integrity protection shall not be performed on this message.
    -- User equipment IEs
        initialUE-Identity          InitialUE-Identity,
        establishmentCause           EstablishmentCause,
        -- protocolErrorIndicator is MD, but for compactness reasons no default value
        -- has been assigned to it.
        protocolErrorIndicator       ProtocolErrorIndicator,
    -- Measurement IEs
        measuredResultsOnRACH       MeasuredResultsOnRACH
                                         OPTIONAL,
    -- Non critical Extensions
        v3d0NonCriticalExtensions   SEQUENCE {
            rRCCconnectionRequest-v3d0ext   RRCConnectionRequest-v3d0ext-IES,
            -- Reserved for future non critical extensionExtension mechanism for non release99
information
            nonCriticalExtensions        SEQUENCE {}      OPTIONAL
        }                                OPTIONAL
    }

RRCConnectionRequest-v3d0ext-IES ::= SEQUENCE {
    -- User equipment IEs
        uESpecificBehaviourInformationlidle      UESpecificBehaviourInformationlidle
                                         OPTIONAL
    }

-- ****
-- RRC CONNECTION SETUP COMPLETE
-- ****

RRCConnectionSetupComplete ::= SEQUENCE {
    -- TABULAR: Integrity protection shall not be performed on this message.
    -- User equipment
        rrc-TransactionIdentifier      RRC-TransactionIdentifier,
        startList                      STARTList,
        ue-RadioAccessCapability       UE-RadioAccessCapability
                                         OPTIONAL,
    -- Other IEs
        ue-RATSpecificCapability      InterRAT-UE-RadioAccessCapabilityList  OPTIONAL,
    -- Non critical extensions
        v370NonCriticalExtensions     SEQUENCE {
            rrcConnectionSetupComplete-v370ext   RRCConnectionSetupComplete-v370ext,
            v380NonCriticalExtensions          SEQUENCE {
                rrcConnectionSetupComplete-v380ext   RRCConnectionSetupComplete-v380ext-IES,
                -- Reserved for future non critical extension
                v3a0NonCriticalExtensions         SEQUENCE {
                    rrcConnectionSetupComplete-v3a0ext   RRCConnectionSetupComplete-v3a0ext-IES,
                    nonCriticalExtensions           SEQUENCE {}      OPTIONAL
                }                                OPTIONAL
            }                                OPTIONAL
        }                                OPTIONAL
    }

RRCConnectionSetupComplete-v370ext ::= SEQUENCE {
    -- User equipment IEs
        ue-RadioAccessCapability-v370ext     UE-RadioAccessCapability-v370ext
                                         OPTIONAL
}

RRCConnectionSetupComplete-v380ext-IES ::= SEQUENCE {
    -- User equipment IEs
        ue-RadioAccessCapability-v380ext     UE-RadioAccessCapability-v380ext
                                         OPTIONAL,
        dl-PhysChCapabilityFDD-v380ext      DL-PhysChCapabilityFDD-v380ext
    }

RRCConnectionSetupComplete-v3a0ext-IES ::= SEQUENCE {
    -- User equipment IEs
        ue-RadioAccessCapability-v3a0ext     UE-RadioAccessCapability-v3a0ext
                                         OPTIONAL
}

```

## 11.3 Information element definitions

```

-- ****
-- USER EQUIPMENT INFORMATION ELEMENTS (10.3.3)
-- ****

-- TABULAR : for ActivationTime, value 'now' always appears as default, and is encoded
-- by absence of the field
ActivationTime ::= INTEGER (0..255)

BackoffControlParams ::= SEQUENCE {
    n-AP-RetransMax,
    n-AccessFails,
    nf-BO-NoAICH,
    ns-BO-Busy,
    nf-BO-AllBusy,
    nf-BO-Mismatch,
    t-CPCH
}

C-RNTI ::= BIT STRING (SIZE (16))

CapabilityUpdateRequirement ::= SEQUENCE {
    ue-RadioCapabilityFDDUpdateRequirement BOOLEAN,
    ue-RadioCapabilityTDDUpdateRequirement BOOLEAN,
    systemSpecificCapUpdateReqList SystemSpecificCapUpdateReqList OPTIONAL
}

CellUpdateCause ::= ENUMERATED {
    cellReselection,
    periodicalCellUpdate,
    uplinkDataTransmission,
    utran-pagingResponse,
    re-enteredServiceArea,
    radiolinkFailure,
    rlc-unrecoverableError,
    spare1
}

ChipRateCapability ::= ENUMERATED {
    mcps3-84, mcps1-28 }

CipheringAlgorithm ::= ENUMERATED {
    uea0, uea1 }

CipheringModeCommand ::= CHOICE {
    startRestart CipheringAlgorithm,
    dummy NULL
}

CipheringModeInfo ::= SEQUENCE {
    -- TABULAR: The ciphering algorithm is included in the CipheringModeCommand.
    cipheringModeCommand CipheringModeCommand,
    activationTimeForDPCH ActivationTime OPTIONAL,
    rb-DL-CiphActivationTimeInfo RB-ActivationTimeInfoList OPTIONAL
}

CN-DRX-CycleLengthCoefficient ::= INTEGER (6..9)

CN-PagedUE-Identity ::= CHOICE {
    imsi-GSM-MAP,
    tmsi-GSM-MAP,
    p-TMSI-GSM-MAP,
    imsi-DS-41,
    tmsi-DS-41,
    spare3,
    spare2,
    spare1
}

CompressedModeMeasCapability ::= SEQUENCE {
    fdd-Measurements BOOLEAN,
    -- TABULAR: The IEs tdd-Measurements, gsm-Measurements and multiCarrierMeasurements
    -- are made optional since they are conditional based on another information element.
    -- Their absence corresponds to the case where the condition is not true.
    tdd-Measurements BOOLEAN OPTIONAL,
}

```

```

gsm-Measurements          GSM-Measurements           OPTIONAL,
multiCarrierMeasurements   BOOLEAN                  OPTIONAL
}

CompressedModeMeasCapabFDDList ::= SEQUENCE (SIZE (1..maxFreqBandsFDD)) OF
                                    CompressedModeMeasCapabFDD

CompressedModeMeasCapabFDD ::= SEQUENCE {
                                radioFrequencyBandFDD    OPTIONAL,
                                dl-MeasurementsFDD       BOOLEAN,
                                ul-MeasurementsFDD       BOOLEAN
}
}

CompressedModeMeasCapabTDDList ::= SEQUENCE (SIZE (1..maxFreqBandsTDD)) OF
                                    CompressedModeMeasCapabTDD

CompressedModeMeasCapabTDD ::= SEQUENCE {
                                radioFrequencyBandTDD,
                                dl-MeasurementsTDD       BOOLEAN,
                                ul-MeasurementsTDD       BOOLEAN
}
}

CompressedModeMeasCapabGSMList ::= SEQUENCE (SIZE (1..maxFreqBandsGSM)) OF
                                    CompressedModeMeasCapabGSM

CompressedModeMeasCapabGSM ::= SEQUENCE {
                                radioFrequencyBandGSM,
                                dl-MeasurementsGSM       BOOLEAN,
                                ul-MeasurementsGSM       BOOLEAN
}
}

CompressedModeMeasCapabMC ::= SEQUENCE {
                                dl-MeasurementsMC        BOOLEAN,
                                ul-MeasurementsMC        BOOLEAN
}
}

CPCH-Parameters ::= SEQUENCE {
                      initialPriorityDelayList      InitialPriorityDelayList      OPTIONAL,
                      backoffControlParams          BackoffControlParams,
-- TABULAR: TPC step size nested inside PowerControlAlgorithm
                      powerControlAlgorithm         PowerControlAlgorithm,
                      dl-DPCCH-BER                 DL-DPCCH-BER
}
}

DL-DPCCH-BER ::= INTEGER (0..63)

DL-PhysChCapabilityFDD ::= SEQUENCE {
                            maxNoDPCH-PDSCH-Codes      INTEGER (1..8),
                            maxNoPhysChBitsReceived     MaxNoPhysChBitsReceived,
                            supportForSF-512             BOOLEAN,
                            supportOfPDSCH              BOOLEAN,
                            simultaneousSCCPCH-DPCH-Reception SimultaneousSCCPCH-DPCH-Reception
}
}

DL-PhysChCapabilityFDD-v380ext ::= SEQUENCE {
                                    supportOfDedicatedPilotsForChEstimation SupportOfDedicatedPilotsForChEstimation      OPTIONAL
}
}

SupportOfDedicatedPilotsForChEstimation ::= ENUMERATED { true }

DL-PhysChCapabilityTDD ::= SEQUENCE {
                            maxTS-PerFrame               MaxTS-PerFrame,
                            maxPhysChPerFrame            MaxPhysChPerFrame,
                            minimumSF                     MinimumSF-DL,
                            supportOfPDSCH               BOOLEAN,
                            maxPhysChPerTS               MaxPhysChPerTS
}
}

DL-TransChCapability ::= SEQUENCE {
                            maxNoBitsReceived            MaxNoBits,
                            maxConvCodeBitsReceived       MaxNoBits,
                            turboDecodingSupport         TurboSupport,
                            maxSimultaneousTransChs     MaxSimultaneousTransChsDL,
                            maxSimultaneousCCTrCH-Count MaxSimultaneousCCTrCH-Count,
                            maxReceivedTransportBlocks   MaxTransportBlocksDL,
                            maxNumberoftFC                MaxNumberoftFC-DL,
                            maxNumberoftTF                MaxNumberoftTF
}
}

```

```

DRAC-SysInfo ::= SEQUENCE {
    transmissionProbability,
    maximumBitRate
}

DRAC-SysInfoList ::= SEQUENCE (SIZE (1..maxDRACclasses)) OF
    DRAC-SysInfo

DSCH-RNTI ::= BIT STRING (SIZE (16))

ESN-DS-41 ::= BIT STRING (SIZE (32))

EstablishmentCause ::= ENUMERATED {
    originatingConversationalCall,
    originatingStreamingCall,
    originatingInteractiveCall,
    originatingBackgroundCall,
    originatingSubscribedTrafficCall,
    terminatingConversationalCall,
    terminatingStreamingCall,
    terminatingInteractiveCall,
    terminatingBackgroundCall,
    emergencyCall,
    interRAT-CellReselection,
    interRAT-CellChangeOrder,
    registration,
    detach,
    originatingHighPrioritySignalling,
    originatingLowPrioritySignalling,
    callRe-establishment,
    terminatingHighPrioritySignalling,
    terminatingLowPrioritySignalling,
    terminatingCauseUnknown,
    spare12,
    spare11,
    spare10,
    spare9,
    spare8,
    spare7,
    spare6,
    spare5,
    spare4,
    spare3,
    spare2,
    spare1
}

FailureCauseWithProtErr ::= CHOICE {
    configurationUnsupported      NULL,
    physicalChannelFailure       NULL,
    incompatibleSimultaneousReconfiguration   NULL,
    compressedModeRuntimeError   TGPSI,
    protocolError                ProtocolErrorInformation,
    cellUpdateOccurred           NULL,
    invalidConfiguration          NULL,
    configurationIncomplete      NULL,
    unsupportedMeasurement        NULL,
    spare7                      NULL,
    spare6                      NULL,
    spare5                      NULL,
    spare4                      NULL,
    spare3                      NULL,
    spare2                      NULL,
    spare1                      NULL
}

FailureCauseWithProtErrTrId ::= SEQUENCE {
    rrc-TransactionIdentifier   RRC-TransactionIdentifier,
    failureCause                FailureCauseWithProtErr
}

GSM-Measurements ::= SEQUENCE {
    gsm900                      BOOLEAN,
    dcs1800                      BOOLEAN,
    gsm1900                      BOOLEAN
}

AccessStratumReleaseIndicator ::= ENUMERATED {

```

```

        r99 }

UESpecificBehaviourInformationIdle ::= BIT STRING (SIZE ([4]))
UESpecificBehaviourInformationInterRAT ::= BIT STRING (SIZE (8))

```

```

IMSI-and-ESN-DS-41 ::=          SEQUENCE {
    imsi-DS-41           IMSI-DS-41,
    esn-DS-41            ESN-DS-41
}

IMSI-DS-41 ::=                  OCTET STRING (SIZE (5..7))

InitialPriorityDelayList ::=     SEQUENCE (SIZE (1..maxASC)) OF
                                NS-IP

InitialUE-Identity ::=          CHOICE {
    imsi                 IMSI-GSM-MAP,
    tmsi-and-LAI         TMSI-and-LAI-GSM-MAP,
    p-TMSI-and-RAI       P-TMSI-and-RAI-GSM-MAP,
    imei                IMEI,
    esn-DS-41           ESN-DS-41,
    imsi-DS-41          IMSI-DS-41,
    imsi-and-ESN-DS-41  IMSI-and-ESN-DS-41,
    tmsi-DS-41          TMSI-DS-41
}

IntegrityCheckInfo ::=          SEQUENCE {
    messageAuthenticationCode  MessageAuthenticationCode,
    rrc-MessageSequenceNumber RRC-MessageSequenceNumber
}

IntegrityProtActivationInfo ::=   SEQUENCE {
    rrc-MessageSequenceNumberList RRC-MessageSequenceNumberList
}

IntegrityProtectionAlgorithm ::= ENUMERATED {
                                uial
}

```

## 11.5 RRC information between network nodes

```

-- ****
-- Handover to UTRAN information
--
-- ****

InterRATHandoverInfoWithInterRATCapabilities ::= CHOICE {
    r3           SEQUENCE {
        -- IE InterRATHandoverInfoWithInterRATCapabilities-r3-IEs also
        -- includes non critical extensions
        interRATHandoverInfo-r3      InterRATHandoverInfoWithInterRATCapabilities-r3-IEs,
        v390NonCriticalExtensions   SEQUENCE {
            interRATHandoverInfoWithInterRATCapabilities-v390ext
        }
        InterRATHandoverInfoWithInterRATCapabilities-v390ext-IEs,
        -- Reserved for future non critical extension
        nonCriticalExtensions       SEQUENCE {} OPTIONAL
    }
    OPTIONAL
},
criticalExtensions          SEQUENCE {}
}

InterRATHandoverInfoWithInterRATCapabilities-r3-IEs ::= SEQUENCE {
    -- The order of the IE's may not reflect the tabular format
    -- but has been chosen to simplify the handling of the information in the BSC
    -- Other IE's
    ue-RATSpecificCapability     InterRAT-UE-RadioAccessCapabilityList OPTIONAL,
    -- interRATHandoverInfo, Octet string is used to obtain 8 bit length field prior to
    -- actual information. This makes it possible for BSS to transparently handle information
    -- received via GSM air interface even when it includes non critical extensions.
    -- The octet string shall include the InterRATHandoverInfo information
}

```

```

-- The BSS can re-use the 04.18 length field received from the MS
interRATHandoverInfo          OCTET STRING (SIZE (0..255))
}

-- ****
-- SRNC Relocation information
-- ****

SRNC-RelocationInfo ::= CHOICE {
    r3           SEQUENCE {
        SRNC-RelocationInfo-r3      SRNC-RelocationInfo-r3-IEs,
        v380NonCriticalExtensions   SEQUENCE {
            sRNC-RelocationInfo-v380ext SRNC-RelocationInfo-v380ext-IEs,
            -- Reserved for future non critical extension
            v390NonCriticalExtensions   SEQUENCE {
                sRNC-RelocationInfo-v390ext      SRNC-RelocationInfo-v390ext-IEs,
                v3a0NonCriticalExtensions       SEQUENCE {
                    sRNC-RelocationInfo-v3a0ext      SRNC-RelocationInfo-v3a0ext-IEs,
                    v3b0NonCriticalExtensions       SEQUENCE {
                        sRNC-RelocationInfo-v3b0ext      SRNC-RelocationInfo-v3b0ext-IEs,
                        v3c0NonCriticalExtensions       SEQUENCE {
                            sRNC-RelocationInfo-v3c0ext      SRNC-RelocationInfo-v3c0ext-IEs,
                            v3d0NonCriticalExtensions     SEQUENCE {
                                SRNC-RelocationInfo-v3d0ext      SRNC-RelocationInfo-v3d0ext-IEs,
                                -- Reserved for future non critical extension
                                nonCriticalExtensions        SEQUENCE {} OPTIONAL
                            }
                        }
                    }
                }
            }
        }
    },
    criticalExtensions          SEQUENCE {}
}

SRNC-RelocationInfo-r3-IEs ::= SEQUENCE {
    -- Non-RRC IEs
    stateOfRRC                  StateOfRRC,
    stateOfRRC-Procedure         StateOfRRC-Procedure,
    -- Ciphering related information IEs
    -- If the extension v380 is included use the extension for the ciphering status per CN domain
    cipheringStatus              CipheringStatus,
    calculationTimeForCiphering  CalculationTimeForCiphering OPTIONAL,
    -- The order of occurrence in the IE cipheringInfoPerRB-List is the
    -- same as the RBs in the IE "Signalling RB information list" and in the
    -- IE "RAB information list". The signalling RBs are supposed to be listed
    -- first. Only UM and AM RBs that are ciphered are listed here
    cipheringInfoPerRB-List      CipheringInfoPerRB-List OPTIONAL,
    count-C-List                 COUNT-C-List OPTIONAL,
    integrityProtectionStatus    IntegrityProtectionStatus,
    srb-SpecificIntegrityProtInfo SRB-SpecificIntegrityProtInfoList,
    implementationSpecificParams ImplementationSpecificParams OPTIONAL,
    -- User equipment IEs
    u-RNTI                      U-RNTI,
    c-RNTI                      C-RNTI OPTIONAL,
    ue-RadioAccessCapability     UE-RadioAccessCapability,
    ue-Positioning-LastKnownPos  UE-Positioning-LastKnownPos OPTIONAL,
    -- Other IEs
    ue-RATSpecificCapability    InterRAT-UE-RadioAccessCapabilityList OPTIONAL,
    -- UTRAN mobility IEs
    ura-Identity                 URA-Identity OPTIONAL,
    -- Core network IEs
    cn-CommonGSM-MAP-NAS-SysInfo NAS-SystemInformationGSM-MAP,
    cn-DomainInformationList     CN-DomainInformationList OPTIONAL,
    -- Measurement IEs
    ongoingMeasRepList          OngoingMeasRepList OPTIONAL,
    -- Radio bearer IEs
    predefinedConfigStatusList   PredefinedConfigStatusList,
    srb-InformationList          SRB-InformationSetupList,
    rab-InformationList          RAB-InformationSetupList OPTIONAL,
    -- Transport channel IEs
    ul-CommonTransChInfo         UL-CommonTransChInfo OPTIONAL,
    ul-TransChInfoList           UL-AddReconfTransChInfoList OPTIONAL,
    modeSpecificInfo             CHOICE {
        fdd                         SEQUENCE {
    }
}

```

```

        cpch-SetID          CPCH-SetID           OPTIONAL,
        transChDRAC-Info   DRAC-StaticInformationList OPTIONAL
    },
    tdd                  NULL
},
dl-CommonTransChInfo DL-CommonTransChInfo   OPTIONAL,
dl-TransChInfoList   DL-AddReconfTransChInfoList OPTIONAL,
-- Measurement report
measurementReport     MeasurementReport      OPTIONAL
}

SRNC-RelocationInfo-v380ext-IEs ::= SEQUENCE {
-- Ciphering related information IEs
    cn-DomainIdentity          CN-DomainIdentity,
    cipheringStatusList         CipheringStatusList
}

SRNC-RelocationInfo-v390ext-IEs ::= SEQUENCE {
    cn-DomainInformationList-v390ext  CN-DomainInformationList-v390ext   OPTIONAL,
    ue-RadioAccessCapability-v370ext  UE-RadioAccessCapability-v370ext   OPTIONAL,
    ue-RadioAccessCapability-v380ext  UE-RadioAccessCapability-v380ext   OPTIONAL,
    dl-PhysChCapabilityFDD-v380ext   DL-PhysChCapabilityFDD-v380ext,    FailureCauseWithProtErr
    failureCauseWithProtErr         FailureCauseWithProtErr           OPTIONAL
}

SRNC-RelocationInfo-v3a0ext-IEs ::= SEQUENCE {
    cipheringInfoForSRB1-v3a0ext   CipheringInfoPerRB-List-v3a0ext,
    ue-RadioAccessCapability-v3a0ext UE-RadioAccessCapability-v3a0ext   OPTIONAL,
    -- cn-domain identity for IE startValueForCiphering-v3a0ext is specified
    -- in subsequent extension (SRNC-RelocationInfo-v3b0ext-IEs)
    startValueForCiphering-v3a0ext START-Value
}

SRNC-RelocationInfo-v3b0ext-IEs ::= SEQUENCE {
    -- cn-domain identity for IE startValueForCiphering-v3a0ext included in previous extension
    cn-DomainIdentity          CN-DomainIdentity,
    -- the remaining start values are contained in IE startValueForCiphering-v3b0ext
    startValueForCiphering-v3b0ext STARTList2           OPTIONAL
}

SRNC-RelocationInfo-v3c0ext-IEs ::= SEQUENCE {
    -- IE rb-IdentityForHOMessage includes the identity of the RB used by the source SRNC
    -- to send the message contained in the IE "TargetRNC-ToSourceRNC-Container".
    -- Only included if type is "UE involved"
    rb-IdentityForHOMessage     RB-Identity           OPTIONAL
}

SRNC-RelocationInfo-v3d0ext-IEs ::= SEQUENCE {
    -- User equipment IE
    uESpecificBehaviourInformationlidle   UESpecificBehaviourInformationlidle   OPTIONAL,
    uESpecificBehaviourInformationlinterRAT UESpecificBehaviourInformationlinterRAT
    OPTIONAL
}

```

#### 14.12.4.1 INTER RAT HANDOVER INFO WITH INTER RAT CAPABILITIES

This RRC message is sent between network nodes when preparing for an inter RAT handover to UTRAN.

Direction: source RAT→target RNC

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
<b>UE Information elements</b>				
UE security information	OP		UE security information 10.3.3.42b	
UE capability container	OP			
>UE radio access capability	MP		UE radio access capability 10.3.3.42	
>UE radio access capability extension	MP		UE radio access	Although this IE is not always required, the need has been

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
			capability extension 10.3.3.42a	set to MP to align with the ASN.1
<a href="#">&gt;UE Specific Behaviour Information 1 interRAT</a>	<a href="#">OP</a>		<a href="#">UE Specific Behaviour Information 1 interRAT</a> 10.3.3.51	<a href="#">This IE shall not be included in this version of the protocol</a>
<b>Non RRC IEs</b>				
<b>Radio Bearer IEs</b>				
Predefined configuration status information	OP		Predefined configuration status information 10.3.4.5a	
<b>Other Information elements</b>				
UE system specific capability	OP	1 to <maxSystemCapability>		
>Inter-RAT UE radio access capability	MP		Inter-RAT UE radio access capability 10.3.8.7	
Failure cause	OP		Failure cause 10.3.3.13	Diagnostics information related to an earlier handover to UTRAN request
Protocol error information	CV-ProtErr		Protocol error information 10.3.8.12	

Condition	Explanation
ProtErr	This IE is mandatory present if the IE "Protocol error indicator" is included and has the value "TRUE". Otherwise it is not needed.

NOTE: The above table does not need to reflect the order of the information elements in the actual encoded message. The order, that is reflected in the ASN.1, should be chosen in a manner that avoids that network nodes need to perform reordering of information elements.

#### 14.12.4.2 SRNS RELOCATION INFO

This RRC message is sent between network nodes when preparing for an SRNS relocation.

With the presence or absence of the IE "RB identity for Hard Handover message" the source RNC indicates to the target SRNC whether the source RNC expects to receive the choice "DL DCCH message" in the IE "RRC information, target RNC to source RNC" in case the SRNS relocation is of type "UE involved". Furthermore the target RNC uses this information for the calculation of the MAC-I.

Direction: source RNC→target RNC

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
<b>Non RRC IEs</b>				
RB identity for Handover message	OP		RB identity 10.3.4.16	Gives the id of the radio bearer on which the source RNC will transmit the RRC message in the case the relocation is of type "UE involved".
>State of RRC	MP		RRC state indicator, 10.3.3.35a	
>State of RRC procedure	MP		Enumerated	

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
			(await no RRC message, await RB Release Complete, await RB Setup Complete, await RB Reconfiguration Complete, await Transport CH Reconfiguration Complete, await Physical CH Reconfiguration Complete, await Active Set Update Complete, await Handover Complete, send Cell Update Confirm, send URA Update Confirm, , others)	
<b>Ciphering related information</b>				
>Ciphering status for each CN domain	MP	<1 to maxCNDomains>		
>>CN domain identity	MP		CN domain identity 10.3.1.1	
>>Ciphering status	MP		Enumerated( Not started, Started)	
>>START	MP		START 10.3.3.38	START value to be used in this CN domain.
>Latest configured CN domain	MP		CN domain identity 10.3.1.1	Value contained in the variable of the same name. In case this variable is empty, the source RNC can set any CN domain identity. In that case, the Ciphering status and the Integrity protection status should be Not started and the target RNC should not initialise the variable Latest configured CN domain.
>Calculation time for ciphering related information	CV-Ciphering			Time when the ciphering information of the message were calculated, relative to a cell of the target RNC
>>Cell Identity	MP		Cell Identity 10.3.2.2	Identity of one of the cells under the target RNC and included in the active set of the

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
				current call
>>SFN	MP		Integer(0..4095)	
>COUNT-C list	OP	1 to <maxCNdomains>		COUNT-C values for radio bearers using transparent mode RLC
>>CN domain identity	MP		CN domain identity 10.3.1.1	
>>COUNT-C	MP		Bit string(32)	
>Ciphering info per radio bearer	OP	1 to <maxRB>		For signalling radio bearers this IE is mandatory.
>>RB identity	MP		RB identity 10.3.4.16	
>>Downlink HFN	MP		Bit string(20..25)	This IE is either RLC AM HFN (20 bits) or RLC UM HFN (25 bits)
>>Downlink SN	CV-SRB1		Bit String(7)	VT(US) of RLC UM
>>Uplink HFN	MP		Bit string(20..25)	This IE is either RLC AM HFN (20 bits) or RLC UM HFN (25 bits)
<b>Integrity protection related information</b>				
>Integrity protection status	MP		Enumerated(Not started, Started)	
>Signalling radio bearer specific integrity protection information	CV-IP	4 to <maxSRBs etup>		
>>Uplink RRC HFN	MP		Bit string (28)	For each SRB, this IE corresponds to the last value used.
>>Downlink RRC HFN	MP		Bit string (28)	For each SRB, this IE corresponds to the last value used. In particular, for SRB2, this IE should not take into account the RRC message that will trigger the relocation.
>>Uplink RRC Message sequence number	MP		Integer (0..15)	For each SRB, this IE corresponds to the last value used.
>>Downlink RRC Message sequence number	MP		Integer (0..15)	For each SRB, this IE corresponds to the last value used. In particular, for SRB2, this IE should not take into account the RRC message that will trigger the relocation.
>Implementation specific parameters	OP		Bit string (1..512)	
<b>RRC IEs</b>				
<b>UE Information elements</b>				
>U-RNTI	MP		U-RNTI 10.3.3.47	
>C-RNTI	OP		C-RNTI 10.3.3.8	
>UE radio access Capability	MP		UE radio access capability 10.3.3.42	
>UE radio access capability extension	OP		UE radio access capability extension 10.3.3.42a	
>Last known UE position	OP			
>>SFN	MP		Integer	Time when position was

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
			(0..4095)	estimated
>>Cell ID	MP		Cell identity; 10.3.2.2	Indicates the cell, the SFN is valid for.
>>CHOICE Position estimate	MP			
>>>Ellipsoid Point			Ellipsoid Point; 10.3.8.4a	
>>>Ellipsoid point with uncertainty circle			Ellipsoid point with uncertainty circle 10.3.8.4d	
>>>Ellipsoid point with uncertainty ellipse			Ellipsoid point with uncertainty ellipse 10.3.8.4e	
>>>Ellipsoid point with altitude			Ellipsoid point with altitude 10.3.8.4b	
>>>Ellipsoid point with altitude and uncertainty ellipsoid			Ellipsoid point with altitude and uncertainty ellipsoid 10.3.8.4c	
<a href="#">&gt;UE Specific Behaviour Information 1 idle</a>	<a href="#">OP</a>		<a href="#">UE Specific Behaviour Information 1</a> <a href="#">10.3.3.51</a>	<a href="#">This IE should be included if received via the "INTER RAT HANDOVER INFO" or the "RRC CONNECTION REQUEST" or the IE "SRNS RELOCATION INFO" or the "Inter RAT Handover Info with Inter RAT Capabilities"</a>
<a href="#">&gt;UE Specific Behaviour Information 1 interRAT</a>	<a href="#">OP</a>		<a href="#">UE Specific Behaviour Information 1</a> <a href="#">interRAT</a> <a href="#">10.3.3.52</a>	<a href="#">This IE should be included if received via the "INTER RAT HANDOVER INFO" or the "RRC CONNECTION REQUEST" or the IE "SRNS RELOCATION INFO" or the "Inter RAT Handover Info with Inter RAT Capabilities"</a>
<b>Other Information elements</b>				
>UE system specific capability	OP	1 to <maxSystemCapability>		
>>Inter-RAT UE radio access capability	MP		Inter-RAT UE radio access capability 10.3.8.7	
<b>UTRAN Mobility Information elements</b>				
>URA Identifier	OP		URA identity 10.3.2.6	
<b>CN Information Elements</b>				
>CN common GSM-MAP NAS system information	MP		NAS system information (GSM-MAP) 10.3.1.9	
>CN domain related information	OP	1 to <MaxCNdomains>		CN related information to be provided for each CN domain
>>CN domain identity	MP			

<b>Information Element/Group Name</b>	<b>Need</b>	<b>Multi</b>	<b>Type and reference</b>	<b>Semantics description</b>
>>CN domain specific GSM-MAP NAS system info	MP		NAS system information (GSM-MAP) 10.3.1.9	
>>CN domain specific DRX cycle length coefficient	MP		CN domain specific DRX cycle length coefficient, 10.3.3.6	
<b>Measurement Related Information elements</b>				
>For each ongoing measurement reporting	OP	1 to <MaxNoOf Meas>		
>>Measurement Identity	MP		Measuremen t identity 10.3.7.48	
>>Measurement Command	MP		Measuremen t command 10.3.7.46	
>>Measurement Type	CV-Setup		Measuremen t type 10.3.7.50	
>>Measurement Reporting Mode	OP		Measuremen t reporting mode 10.3.7.49	
>>Additional Measurements list	OP		Additional measuremen ts list 10.3.7.1	
>>CHOICE Measurement	OP			
>>>Intra-frequency				
>>>>Intra-frequency cell info	OP		Intra-frequency cell info list 10.3.7.33	
>>>>Intra-frequency measurement quantity	OP		Intra-frequency measuremen t quantity 10.3.7.38	
>>>>Intra-frequency reporting quantity	OP		Intra-frequency reporting quantity 10.3.7.41	
>>>>Reporting cell status	OP		Reporting cell status 10.3.7.61	
>>>>Measurement validity	OP		Measuremen t validity 10.3.7.51	
>>>>CHOICE report criteria	OP			
>>>>>Intra-frequency measurement reporting criteria			Intra-frequency measuremen t reporting criteria 10.3.7.39	
>>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>>No reporting			NULL	
>>>>Inter-frequency				

<b>Information Element/Group Name</b>	<b>Need</b>	<b>Multi</b>	<b>Type and reference</b>	<b>Semantics description</b>
>>>>Inter-frequency cell info	OP		Inter-frequency cell info list 10.3.7.13	
>>>>Inter-frequency measurement quantity	OP		Inter-frequency measurement quantity 10.3.7.18	
>>>>Inter-frequency reporting quantity	OP		Inter-frequency reporting quantity 10.3.7.21	
>>>>Reporting cell status	OP		Reporting cell status 10.3.7.61	
>>>>Measurement validity	OP		Measurement validity 10.3.7.51	
>>>>CHOICE report criteria	OP			
>>>>>Inter-frequency measurement reporting criteria			Inter-frequency measurement reporting criteria 10.3.7.19	
>>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>>No reporting			NULL	
>>>>>Inter-RAT				
>>>>Inter-RAT cell info	OP		Inter-RAT cell info list 10.3.7.23	
>>>>Inter-RAT measurement quantity	OP		Inter-RAT measurement quantity 10.3.7.29	
>>>>Inter-RAT reporting quantity	OP		Inter-RAT reporting quantity 10.3.7.32	
>>>>Reporting cell status	OP		Reporting cell status 10.3.7.61	
>>>>Measurement validity	OP		Measurement validity 10.3.7.51	
>>>>CHOICE report criteria	OP			
>>>>>Inter-RAT measurement reporting criteria			Inter-RAT measurement reporting criteria 10.3.7.30	
>>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>>No reporting			NULL	
>>>>>Traffic Volume				

<b>Information Element/Group Name</b>	<b>Need</b>	<b>Multi</b>	<b>Type and reference</b>	<b>Semantics description</b>
>>>Traffic volume measurement Object	OP		Traffic volume measurement object 10.3.7.70	
>>>Traffic volume measurement quantity	OP		Traffic volume measurement quantity 10.3.7.71	
>>>Traffic volume reporting quantity	OP		Traffic volume reporting quantity 10.3.7.74	
>>>CHOICE report criteria	OP			
>>>>Traffic volume measurement reporting criteria			Traffic volume measurement reporting criteria 10.3.7.72	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting			NULL	
>>>Quality				
>>>Quality measurement Object	OP		Quality measurement object	
>>>CHOICE report criteria	OP			
>>>>Quality measurement reporting criteria			Quality measurement reporting criteria 10.3.7.58	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting			NULL	
>>>UE internal				
>>>UE internal measurement quantity	OP		UE internal measurement quantity 10.3.7.79	
>>>UE internal reporting quantity	OP		UE internal reporting quantity 10.3.7.82	
>>>CHOICE report criteria	OP			
>>>>UE internal measurement reporting criteria			UE internal measurement reporting criteria 10.3.7.80	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting			NULL	
>>>UE positioning				

<b>Information Element/Group Name</b>	<b>Need</b>	<b>Multi</b>	<b>Type and reference</b>	<b>Semantics description</b>
>>>LCS reporting quantity	OP		LCS reporting quantity 10.3.7.111	
>>>CHOICE report criteria	OP			
>>>>LCS reporting criteria			LCS reporting criteria 10.3.7.110	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting				
<b>Radio Bearer Information Elements</b>				
>Predefined configuration status information	OP		Predefined configuration status information 10.3.4.5a	
>Signalling RB information list	MP	1 to <maxSRBs etup>		For each signalling radio bearer
>>Signalling RB information	MP		Signalling RB information to setup 10.3.4.24	
>RAB information list	OP	1 to <maxRABs etup>		Information for each RAB
>>RAB information	MP		RAB information to setup 10.3.4.10	
<b>Transport Channel Information Elements</b>				
<b>Uplink transport channels</b>				
>UL Transport channel information common for all transport channels	OP		UL Transport channel information common for all transport channels 10.3.5.24	
>UL transport channel information list	OP	1 to <MaxTrCH >		
>>UL transport channel information	MP		Added or reconfigured UL TrCH information 10.3.5.2	
>CHOICE mode	OP			
>>FDD				
>>>CPCH set ID	OP		CPCH set ID 10.3.5.5	
>>>Transport channel information for DRAC list	OP	1 to <MaxTrCH >		
>>>>DRAC static information	MP		DRAC static information 10.3.5.7	
>>TDD				(no data)

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
<b>Downlink transport channels</b>				
>DL Transport channel information common for all transport channels	OP		DL Transport channel information common for all transport channels 10.3.5.6	
>DL transport channel information list	OP	1 to <MaxTrCH>		
>>DL transport channel information	MP		Added or reconfigured DL TrCH information 10.3.5.1	
>Measurement report	OP		MEASUREMENT REPORT 10.2.17	
<b>Other Information elements</b>				
Failure cause	OP		Failure cause 10.3.3.13	Diagnostics information related to an earlier SRNC Relocation request (see NOTE 2 in 14.12.0a)
Protocol error information	CV-ProtErr		Protocol error information 10.3.8.12	

Multi Bound	Explanation
MaxNoOfMeas	Maximum number of active measurements, upper limit 16

Condition	Explanation
Setup	The IE is mandatory present when the IE Measurement command has the value "Setup", otherwise the IE is not needed.
Ciphering	The IE is mandatory present when the IE Ciphering Status has the value "started" and the ciphering counters need not be reinitialised, otherwise the IE is not needed.
IP	The IE is mandatory present when the IE Integrity protection status has the value "started" and the integrity protection counters need not be reinitialised, otherwise the IE is not needed.
ProtErr	This IE is mandatory present if the IE "Protocol error indicator" is included and has the value "TRUE". Otherwise it is not needed.
SRB1	The IE is mandatory present for RB1. Otherwise it is not needed.

## CHANGE REQUEST

⌘ 25.331 CR 1759 ⌘ rev 2 ⌘ Current version: 4.7.0 ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

**Proposed change affects:** UICC apps ⌘ ME  Radio Access Network  Core Network ⌘

<b>Title:</b>	⌘ Early UE Specific Behaviour Information in RRC Connection Request / inter RAT info
<b>Source:</b>	⌘ Alcatel, Fujitsu, Motorola, NEC, Orange, Siemens
<b>Work item code:</b>	⌘ TEI
	<b>Date:</b> ⌘ 05/11/2002
<b>Category:</b>	<b>⌘ B</b> Use <u>one of the following categories:</u> <b>F</b> (correction) <b>A</b> (corresponds to a correction in an earlier release) <b>B</b> (addition of feature), <b>C</b> (functional modification of feature) <b>D</b> (editorial modification) Detailed explanations of the above categories can be found in 3GPP <a href="#">TR 21.900</a> .
	<b>Release:</b> ⌘ Rel-4 Use <u>one of the following releases:</u> 2 (GSM Phase 2) R96 (Release 1996) R97 (Release 1997) R98 (Release 1998) R99 (Release 1999) Rel-4 (Release 4) Rel-5 (Release 5) Rel-6 (Release 6)

**Reason for change:** ⌘ It is currently not possible to identify and handle faulty UE implementations

<b>Summary of change:</b>	Two transparent containers “UE Specific Behaviour Information 1 idle” (current assumption 4bits, tbc) and “UE Specific Behaviour Information 1 interRAT” (8bits) are added to the early messages at call setup and to the appropriate messages for SRNS relocation and inter rat handover, i.e. to the following messages:  RRC Connection Request, Inter RAT Handover Info, Inter RAT Handover Info with Inter RAT Capabilities, SRNS Relocation Info,  If UTRAN implements the CR but UE doesn't: - No impact. The RNC might not be able to adapt to specific UE behavior.  If UE implements the CR but UTRAN doesn't: - No impact. UTRAN will ignore the unknown extension and treat all UEs in the same way  If neither UE nor UTRAN implement the CR: - No impact.
<b>Consequences if not approved:</b>	⌘ Errors discovered in UEs can not be handled appropriately

<b>Clauses affected:</b>	⌘ 8.1.3.3, 8.1.16.3, 10.2.16b, 10.2.39, 10.3.3.51 (new), 10.3.3.52 (new), 11.2, 11.3, 11.5, 14.12.4.1, 14.12.4.2				
<b>Other specs</b>	<table border="1" style="display: inline-table; vertical-align: middle;"> <tr> <td style="text-align: center;">Y</td> <td style="text-align: center;">N</td> </tr> <tr> <td style="text-align: center;">X</td> <td></td> </tr> </table> Other core specifications ⌘	Y	N	X	
Y	N				
X					

<b>affected:</b>	<table border="1" style="display: inline-table; vertical-align: middle;"> <tr><td></td><td>X</td></tr> <tr><td>X</td><td></td></tr> </table>		X	X		Test specifications	
	X						
X							
<b>Other comments:</b>	⌘						

### How to create CRs using this form:

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>.

Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/>. For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

### 8.1.3.3 RRC CONNECTION REQUEST message contents to set

The UE shall, in the transmitted RRC CONNECTION REQUEST message:

- 1> set the IE "Establishment cause" to the value of the variable ESTABLISHMENT\_CAUSE;
- 1> set the IE "Initial UE identity" to the value of the variable INITIAL\_UE\_IDENTITY;
- 1> set the IE "Protocol error indicator" to the value of the variable PROTOCOL\_ERROR\_INDICATOR;
- 1> include a measurement report in the IE "Measured results on RACH", as specified in the IE "Intra-frequency reporting quantity for RACH reporting" and the IE "Maximum number of reported cells on RACH" in System Information Block type 11; and
- 1> include in the IE "Measured results on RACH" all requested reporting quantities for cells for which measurements are reported; and
- 1> take care that the maximum allowed message size is not exceeded when forming the IE "Measured results on RACH".

The UE shall not include the IE "UE Specific Behaviour Information 1 idle".

### 8.1.16.3 INTER RAT HANDOVER INFO message contents to set

The UE shall:

- 1> include the IE "Predefined configuration status information" and the IE "UE security information";
- 1> include the IE "UE capability container", containing the IE "UE radio access capability" and the IE "UE radio access capability extension", in accordance with the following:
  - 2> if the UE supports multiple UTRA FDD Frequency Bands; or
  - 2> if the UE supports a single UTRA FDD Frequency Band different from 2100 MHz:
    - 3> include the IE "UE radio access capability", excluding IEs "RF capability FDD" and "Measurement capability";
    - 3> include the IE "UE radio access capability extension", including the IEs "RF capability FDD extension" and the "Measurement capability extension" associated with each supported UTRA FDD frequency band indicated in the IE "Frequency band".
  - 2> else:
    - 3> include the IE "UE radio access capability", including the IEs "RF capability FDD" and "Measurement capability" associated with the 2100 MHz UTRA FDD frequency band;
    - 3> include the IE "UE radio access capability extension", including the IEs "RF capability FDD extension" and the "Measurement capability extension" associated with each supported UTRA FDD frequency band indicated in the IE "Frequency band".

1> The UE shall not include the IE "UE Specific Behaviour Information 1 interRAT".

- 1> initiate the transfer of the INTER RAT HANDOVER INFO message via the other radio access technology, using radio access technology-specific procedures;
- 1> store the IE "Predefined configuration status information", the IE "UE security information", the IE "UE radio access capability" and the IE "UE radio access capability extension", if included in the INTER RAT HANDOVER MESSAGE, in variable INTER\_RAT\_HANDOVER\_INFO\_TRANSFERRED;
- 1> and the procedure ends.

## 10.2.16d INTER RAT HANDOVER INFO

This message is sent by the UE via another radio access technology to provide information to the target RNC when preparing for a handover to UTRAN.

RLC-SAP: N/A (Sent through a different RAT)

Logical channel: N/A (Sent through a different RAT)

Direction: UE → UTRAN

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
<b>Radio Bearer IEs</b>				
Predefined configuration status information	OP		Predefined configuration status information 10.3.4.5a	
<b>UE Information elements</b>				
UE security information	OP		UE security information 10.3.3.42b	
>UE Specific Behaviour Information 1 interRAT	OP		UE Specific Behaviour Information 1 interRAT 10.3.3.52	<a href="#">This IE shall not be included in this version of the protocol</a>
UE capability container	OP			
>UE radio access capability	MP		UE radio access capability 10.3.3.42	
>UE radio access capability extension	MP		UE radio access capability extension 10.3.3.42a	Although this IE is not always required, the need has been set to MP to align with the ASN.1

## 10.2.39 RRC CONNECTION REQUEST

RRC Connection Request is the first message transmitted by the UE when setting up an RRC Connection to the network.

RLC-SAP: TM

Logical channel: CCCH

Direction: UE → UTRAN

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
Message Type	MP		Message Type		
<b>UE information elements</b>					
Initial UE identity	MP		Initial UE identity 10.3.3.15		
Establishment cause	MP		Establishment cause 10.3.3.11		
Protocol error indicator	MD		Protocol error indicator 10.3.3.27	Default value is FALSE	
>UE Specific Behaviour Information 1 idle	OP		UE Specific Behaviour Information 1	<a href="#">This IE shall not be included in this version of the protocol</a>	

			<a href="#">idle</a> <a href="#">10.3.3.51</a>		
<b>Measurement information elements</b>					
Measured results on RACH	OP		Measured results on RACH 10.3.7.45		
Access stratum release indicator	MP		Enumerated( REL-4)	Absence of the IE implies R99. The IE also indicates the release of the RRC transfer syntax supported by the UE 15 spare values are needed	REL-4

If the encoded message does not fill a transport block, the RRC layer shall insert padding according to subclause 12.1.

### [10.3.3.51 UE Specific Behaviour Information 1 idle](#)

This IE indicates the UE conformance typically for RRC connection establishment from idle mode.

<a href="#">Information Element/Group name</a>	<a href="#">Need</a>	<a href="#">Multi</a>	<a href="#">Type and Reference</a>	<a href="#">Semantics description</a>
<a href="#">UE Specific Behaviour Information 1</a>	<a href="#">MP</a>		<a href="#">bit string(14)</a>	

### [10.3.3.52 UE Specific Behaviour Information 1 interRAT](#)

This IE indicates the UE conformance typically for RRC connection establishment from another RAT.

<a href="#">Information Element/Group name</a>	<a href="#">Need</a>	<a href="#">Multi</a>	<a href="#">Type and Reference</a>	<a href="#">Semantics description</a>
<a href="#">UE Specific Behaviour Information 1 interRAT</a>	<a href="#">MP</a>		<a href="#">bit string(8)</a>	

## 11.2 PDU definitions

```
--*****
-- TABULAR: The message type and integrity check info are not
-- visible in this module as they are defined in the class module.
-- Also, all FDD/TDD specific choices have the FDD option first
-- and TDD second, just for consistency.
--*****
```

```
PDU-definitions DEFINITIONS AUTOMATIC TAGS ::=
```

```
BEGIN
```

```
--*****
-- IE parameter types from other modules
--*****
```

```
IMPORTS
```

```
-- Core Network IEs :
  CN-DomainIdentity,
```

```

CN-InformationInfo,
CN-InformationInfoFull,
NAS-Message,
PagingRecordTypeID,
-- UTRAN Mobility IEs :
CellIdentity,
CellIdentity-PerRL-List,
URA-Identity,
-- User Equipment IEs :
ActivationTime,
C-RNTI,
CapabilityUpdateRequirement,
CapabilityUpdateRequirement-r4,
CapabilityUpdateRequirement-r4-ext,
CellUpdateCause,
CipheringAlgorithm,
CipheringModeInfo,
DSCH-RNTI,
EstablishmentCause,
FailureCauseWithProtErr,
FailureCauseWithProtErrTrId,
UESpecificBehaviourInformationIdle,
UESpecificBehaviourInformationInterRAT,
InitialUE-Identity,
IntegrityProtActivationInfo,
IntegrityProtectionModeInfo,
N-308,
PagingCause,
PagingRecordList,
ProtocolErrorIndicator,
ProtocolErrorIndicatorWithMoreInfo,
Rb-timer-indicator,
RedirectionInfo,
RejectionCause,
ReleaseCause,
RRC-StateIndicator,
RRC-TransactionIdentifier,
SecurityCapability,
START-Value,
STARTList,
U-RNTI,
U-RNTI-Short,
UE-RadioAccessCapability,
UE-RadioAccessCapability-r4-ext,
UE-RadioAccessCapability-v370ext,
UE-RadioAccessCapability-v380ext,
UE-RadioAccessCapability-v3a0ext,
UE-RadioAccessCapability-v4xyext,
DL-PhysChCapabilityFDD-v380ext,
UE-ConnTimersAndConstants,
UE-ConnTimersAndConstants-v3a0ext,
UE-SecurityInformation,
URA-UpdateCause,
UTRAN-DRX-CycleLengthCoefficient,
WaitTime,
-- Radio Bearer IEs :
DefaultConfigIdentity,
DefaultConfigIdentity-r4,
DefaultConfigMode,
DL-CounterSynchronisationInfo,
PredefinedConfigIdentity,
PredefinedConfigStatusList,
RAB-Info,
RAB-Info-Post,
RAB-InformationList,
RAB-InformationReconfigList,
RAB-InformationSetupList,
RAB-InformationSetupList-r4,
RB-ActivationTimeInfoList,
RB-COUNT-C-InformationList,
RB-COUNT-C-MSB-InformationList,
RB-IdentityList,
RB-InformationAffectedList,
RB-InformationReconfigList,
RB-InformationReconfigList-r4,
RB-InformationReleaseList,
SRB-InformationSetupList,
SRB-InformationSetupList2,
UL-CounterSynchronisationInfo,

```

```

-- Transport Channel IEs:
CPCH-SetID,
DL-AddReconfTransChInfo2List,
DL-AddReconfTransChInfoList,
DL-AddReconfTransChInfoList-r4,
DL-CommonTransChInfo,
DL-CommonTransChInfo-r4,
DL-DeletedTransChInfoList,
DRAC-StaticInformationList,
TFC-Subset,
TFCS-Identity,
UL-AddReconfTransChInfoList,
UL-CommonTransChInfo,
UL-CommonTransChInfo-r4,
UL-DeletedTransChInfoList,
-- Physical Channel IEs :
Alpha,
CCTrCH-PowerControlInfo,
CCTrCH-PowerControlInfo-r4,
ConstantValue,
ConstantValueTdd,
CPCH-SetInfo,
DL-CommonInformation,
DL-CommonInformation-r4,
DL-CommonInformationPost,
DL-InformationPerRL,
DL-InformationPerRL-List,
DL-InformationPerRL-List-r4,
DL-InformationPerRL-ListPostFDD,
DL-InformationPerRL-PostTDD,
DL-InformationPerRL-PostTDD-LCR-r4,
DL-PDSCH-Information,
DPCH-CompressedModeStatusInfo,
FrequencyInfo,
FrequencyInfoFDD,
FrequencyInfoTDD,
MaxAllowedUL-TX-Power,
OpenLoopPowerControl-IPDL-TDD-r4,
PDSCH-CapacityAllocationInfo,
PDSCH-CapacityAllocationInfo-r4,
PDSCH-Identity,
PrimaryCCPCH-TX-Power,
PUSCH-CapacityAllocationInfo,
PUSCH-CapacityAllocationInfo-r4,
PUSCH-Identity,
RL-AdditionInformationList,
RL-RemovalInformationList,
SpecialBurstScheduling,
SSDT-Information,
TFC-ControlDuration,
SSDT-UL-r4,
TimeslotList,
TimeslotList-r4,
TX-DiversityMode,
UL-ChannelRequirement,
UL-ChannelRequirement-r4,
UL-ChannelRequirementWithCPCH-SetID,
UL-ChannelRequirementWithCPCH-SetID-r4,
UL-DPCH-Info,
UL-DPCH-Info-r4,
UL-DPCH-InfoPostFDD,
UL-DPCH-InfoPostTDD,
UL-DPCH-InfoPostTDD-LCR-r4,
UL-SynchronisationParameters-r4,
UL-TimingAdvance,
UL-TimingAdvanceControl,
UL-TimingAdvanceControl-r4,
-- Measurement IEs :
AdditionalMeasurementID-List,
Frequency-Band,
EventResults,
InterFreqEventResults-LCR-r4-ext,
InterRAT-TargetCellDescription,
MeasuredResults,
MeasuredResults-v390ext,
MeasuredResultsList,
MeasuredResultsList-LCR-r4-ext,
MeasuredResultsOnRACH,
MeasurementCommand,

```

```

MeasurementCommand-r4,
MeasurementIdentity,
MeasurementReportingMode,
PrimaryCCPCH-RSCP,
SFN-Offset-Validity,
TimeslotListWithISCP,
TrafficVolumeMeasuredResultsList,
UE-Positioning-GPS-AssistanceData,
UE-Positioning-Measurement-v390ext,
UE-Positioning-OTDOA-AssistanceData,
UE-Positioning-OTDOA-AssistanceData-r4ext,
UE-Positioning-OTDOA-AssistanceData-UEB,
UE-Positioning-IPDL-Parameters-TDD-r4-ext,
-- Other IEs :
BCCH-ModificationInfo,
CDMA2000-MessageList,
GSM-MessageList,
InterRAT-ChangeFailureCause,
InterRAT-HO-FailureCause,
InterRAT-UE-RadioAccessCapabilityList,
InterRAT-UE-SecurityCapList,
IntraDomainNasNodeSelector,
ProtocolErrorMoreInformation,
Rplmn-Information,
Rplmn-Information-r4,
SegCount,
SegmentIndex,
SFN-Prime,
SIB-Data-fixed,
SIB-Data-variable,
SIB-Type
FROM InformationElements

maxSIBperMsg
FROM Constant-definitions;

-- *****
-- HANOVER TO UTRAN COMPLETE
--
-- *****

HandoverToUTRANComplete ::= SEQUENCE {
    --TABULAR: Integrity protection shall not be performed on this message.
    -- User equipment IEs
    -- TABULAR: startList is conditional on history.
    startList                      STARTList           OPTIONAL,
    -- Radio bearer IEs
    count-C-ActivationTime          ActivationTime      OPTIONAL,
    -- Extension mechanism for non- release99 information
    nonCriticalExtensions          SEQUENCE {}        OPTIONAL
}

-- *****
-- INITIAL DIRECT TRANSFER
--
-- *****

InitialDirectTransfer ::= SEQUENCE {
    -- Core network IEs
    cn-DomainIdentity              CN-DomainIdentity,
    intraDomainNasNodeSelector     IntraDomainNasNodeSelector,
    nas-Message                     NAS-Message,
    -- Measurement IEs
    measuredResultsOnRACH          MeasuredResultsOnRACH      OPTIONAL,
    v3a0NonCriticalExtensions      SEQUENCE {
        initialDirectTransfer-v3a0ext  InitialDirectTransfer-v3a0ext,
        -- Extension mechanism for non- release99 information
        nonCriticalExtensions         SEQUENCE {}        OPTIONAL
    }                                OPTIONAL
}

InitialDirectTransfer-v3a0ext ::= SEQUENCE {
    -- start-value shall always be included in this version of the protocol
    start-Value                     START-Value        OPTIONAL
}

```

```

-- ****
-- HANOVER FROM UTRAN COMMAND
--
-- ****

HandoverFromUTRANCommand-GSM ::= CHOICE {
    r3           SEQUENCE {
        handoverFromUTRANCommand-GSM-r3
            HandoverFromUTRANCommand-GSM-r3-IEs,
            -- UTRAN should not include the IE nonCriticalExtensions when it sets
            -- the IE gsm-message included in handoverFromUTRANCommand-GSM-r3 to single-GSM-Message
            -- The UE behaviour upon receiving a message including this combination of IE values is
            -- not specified
            nonCriticalExtensions      SEQUENCE {} OPTIONAL
    },
    later-than-r3      SEQUENCE {
        rrc-TransactionIdentifier   RRC-TransactionIdentifier,
        criticalExtensions         SEQUENCE {}
    }
}

HandoverFromUTRANCommand-GSM-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier   RRC-TransactionIdentifier,
    activationTime               ActivationTime                   OPTIONAL,
    -- Radio bearer IEs
    toHandover-Info              RAB-Info                     OPTIONAL,
    -- Measurement IEs
    frequency-band                Frequency-Band,
    -- Other IEs
    gsm-message                  CHOICE {
        -- In the single-GSM-Message case the following rules apply:
        -- 1> the GSM message directly follows the basic production; the final padding that
        -- results when PER encoding the abstract syntax value is removed prior to appending
        -- the GSM message.
        -- 2> the RRC message excluding the GSM part, does not contain a length determinant;
        -- there is no explicit parameter indicating the size of the included GSM message.
        -- 3> depending on need, final padding (all "0"s) is added to ensure the final result
        -- comprises a full number of octets
        single-GSM-Message          SEQUENCE {},
        gsm-MessageList             SEQUENCE {
            gsm-Messages            GSM-MessageList
        }
    }
}

HandoverFromUTRANCommand-CDMA2000 ::= CHOICE {
    r3           SEQUENCE {
        handoverFromUTRANCommand-CDMA2000-r3
            HandoverFromUTRANCommand-CDMA2000-r3-IEs,
            nonCriticalExtensions      SEQUENCE {} OPTIONAL
    },
    later-than-r3      SEQUENCE {
        rrc-TransactionIdentifier   RRC-TransactionIdentifier,
        criticalExtensions         SEQUENCE {}
    }
}

HandoverFromUTRANCommand-CDMA2000-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier   RRC-TransactionIdentifier,
    activationTime               ActivationTime                   OPTIONAL,
    -- Radio bearer IEs
    toHandover-Info              RAB-Info                     OPTIONAL,
    -- Other IEs
    cdma2000-MessageList        CDMA2000-MessageList
}

-- ****
-- HANOVER FROM UTRAN FAILURE
--
-- ****

HandoverFromUTRANFailure ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier   RRC-TransactionIdentifier,

```

```

-- Other IEs
    interRAT-HO-FailureCause      InterRAT-HO-FailureCause          OPTIONAL,
    interRATMessage                CHOICE {
        gsm                      SEQUENCE {
            gsm-MessageList           GSM-MessageList
        },
        cdma2000                  SEQUENCE {
            cdma2000-MessageList     CDMA2000-MessageList
        }
    }                                OPTIONAL,
-- Extension mechanism for non- release99 information
    nonCriticalExtensions         SEQUENCE {}           OPTIONAL
}

-- ****
-- 
-- INTER RAT HANDOVER INFO
-- 
-- ****

InterRATHandoverInfo ::= SEQUENCE {
    -- This structure is defined for historical reasons, backward compatibility with 04.18
    predefinedConfigStatusList   CHOICE {
        absent                 NULL,
        present                PredefinedConfigStatusList
    },
    uE-SecurityInformation       CHOICE {
        absent                 NULL,
        present                UE-SecurityInformation
    },
    ue-CapabilityContainer       CHOICE {
        absent                 NULL,
        -- present is an octet aligned string containing IE UE-RadioAccessCapabilityInfo
        present                OCTET STRING (SIZE (0..63))
    },
    -- Non critical extensions
    v390NonCriticalExtensions   CHOICE {
        absent                 NULL,
        present                SEQUENCE {
            interRATHandoverInfo-v390ext   InterRATHandoverInfo-v390ext-IEs,
            v3a0NonCriticalExtensions    SEQUENCE {
                interRATHandoverInfo-v3a0ext   InterRATHandoverInfo-v3a0ext,
                v3d0NonCriticalExtensions    SEQUENCE {
                    interRATHandoverInfo-v3d0ext   InterRATHandoverInfo-v3d0ext-IEs,
                    v4xyNonCriticalExtensions    SEQUENCE {
                        interRATHandoverInfo-v4xyext   InterRATHandoverInfo-v4xyext-IEs,
                        -- Reserved for future non critical extension
                        nonCriticalExtensions        SEQUENCE {} OPTIONAL
                    } OPTIONAL
                } OPTIONAL
            } OPTIONAL
        } OPTIONAL
    }
}

InterRATHandoverInfo-v390ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v380ext   UE-RadioAccessCapability-v380ext          OPTIONAL,
    dl-PhysChCapabilityFDD-v380ext    DL-PhysChCapabilityFDD-v380ext
}

InterRATHandoverInfo-v3a0ext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v3a0ext   UE-RadioAccessCapability-v3a0ext          OPTIONAL
}

InterRATHandoverInfo-v3d0ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ueSpecificBehaviourInformationlinterRAT   UESpecificBehaviourInformationlinterRAT
}

InterRATHandoverInfo-v4xyext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v4xyext   UE-RadioAccessCapability-v4xyext
}

```

```

-- ****
-- 
-- RRC CONNECTION REQUEST
-- 
-- ****

RRCConnectionRequest ::= SEQUENCE {
    -- TABULAR: Integrity protection shall not be performed on this message.
    -- User equipment IEs
    initialUE-Identity           InitialUE-Identity,
    establishmentCause            EstablishmentCause,
    -- protocolErrorIndicator is MD, but for compactness reasons no default value
    -- has been assigned to it.
    protocolErrorIndicator        ProtocolErrorIndicator,
    -- Measurement IEs
    measuredResultsOnRACH        MeasuredResultsOnRACH
                                    OPTIONAL,
    -- Non critical Extensions
    v3d0NonCriticalExtensions    SEQUENCE {
        rRCCconnectionRequest-v3d0ext   RRCConnectionRequest-v3d0ext-IEs,
        -- Reserved for future non critical extension
        v4xyNonCriticalExtensions     SEQUENCE {
            rrcConnectionRequest-v4xyext   RRCConnectionRequest-v4xyext-IEs,
            -- Reserved for future non critical extension
            nonCriticalExtensions       SEQUENCE {}      OPTIONAL
        } OPTIONAL
    } OPTIONAL
}

RRCConnectionRequest-v3d0ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    uESpecificBehaviourInformationIidle   UESpecificBehaviourInformationIidle
                                    OPTIONAL
}

RRCConnectionRequest-v4xyext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v4xyext   UE-RadioAccessCapability-v4xyext
}

-- ****
-- 
-- RRC CONNECTION SETUP
-- 
-- ****

RRCConnectionSetup ::= CHOICE {
    r3                         SEQUENCE {
        rrcConnectionSetup-r3          RRCConnectionSetup-r3-IEs,
        v4xyNonCriticalExtensions    SEQUENCE {
            rrcConnectionSetup-v4xyext   RRCConnectionSetup-v4xyext-IEs,
            -- Extension mechanism for non- release99 information
            nonCriticalExtensions      SEQUENCE {}      OPTIONAL
        } OPTIONAL
    },
    later-than-r3                SEQUENCE {
        initialUE-Identity           InitialUE-Identity,
        rrc-TransactionIdentifier   RRC-TransactionIdentifier,
        criticalExtensions          CHOICE {
            r4                         SEQUENCE {
                rrcConnectionSetup-r4      RRCConnectionSetup-r4-IEs,
                nonCriticalExtensions    SEQUENCE {}      OPTIONAL
            },
            criticalExtensions         SEQUENCE {}
        }
    }
}

RRCConnectionSetup-r3-IEs ::= SEQUENCE {
    -- TABULAR: Integrity protection shall not be performed on this message.
    -- User equipment IEs
    initialUE-Identity           InitialUE-Identity,
    rrc-TransactionIdentifier   RRC-TransactionIdentifier,
    activationTime               ActivationTime
                                    OPTIONAL,
    new-U-RNTI                  U-RNTI,
    new-c-RNTI                  C-RNTI
                                    OPTIONAL,
    rrc-StateIndicator          RRC-StateIndicator,
    utran-DRX-CycleLengthCoeff  UTRAN-DRX-CycleLengthCoefficient,
    -- TABULAR: If capacityUpdateRequest is not present, the default value
    -- defined in 10.3.3.2 shall be used.
    capabilityUpdateRequirement  CapabilityUpdateRequirement
                                    OPTIONAL,
}

```

```

-- Radio bearer IEs
    srb-InformationSetupList      SRB-InformationSetupList2,
-- Transport channel IEs
    ul-CommonTransChInfo         UL-CommonTransChInfo          OPTIONAL,
    -- NOTE: ul-AddReconfTransChInfoList should be optional in later versions of
    -- this message
    ul-AddReconfTransChInfoList   UL-AddReconfTransChInfoList,
    dl-CommonTransChInfo         DL-CommonTransChInfo          OPTIONAL,
    -- NOTE: dl-AddReconfTransChInfoList should be optional in later versions
    -- of this message
    dl-AddReconfTransChInfoList   DL-AddReconfTransChInfoList,
-- Physical channel IEs
    frequencyInfo                FrequencyInfo               OPTIONAL,
    maxAllowedUL-TX-Power        MaxAllowedUL-TX-Power     OPTIONAL,
    ul-ChannelRequirement        UL-ChannelRequirement       OPTIONAL,
    dl-CommonInformation         DL-CommonInformation       OPTIONAL,
    dl-InformationPerRL-List     DL-InformationPerRL-List  OPTIONAL
}

RRCConnectionSetup-v4xyext-IEs ::= SEQUENCE {
    capabilityUpdateRequirement-r4-ext CapabilityUpdateRequirement-r4-ext OPTIONAL,
-- Physical channel IEs
    -- ssdt-UL extends SSDT-Information, which is included in
    -- DL-CommonInformation. FDD only.
    ssdt-UL                      SSDT-UL-r4                  OPTIONAL,
    -- The order of the RLs in IE cell-id-PerRL-List is the same as
    -- in IE DL-InformationPerRL-List included in this message
    cell-id-PerRL-List            CellIdentity-PerRL-List  OPTIONAL
}

RRCConnectionSetup-r4-IEs ::= SEQUENCE {
-- TABULAR: Integrity protection shall not be performed on this message.
    activationTime                ActivationTime             OPTIONAL,
    new-U-RNTI                   U-RNTI,
    new-c-RNTI                  C-RNTI                  OPTIONAL,
    rrc-StateIndicator           RRC-StateIndicator,
    utran-DRX-CycleLengthCoeff  UTRAN-DRX-CycleLengthCoefficient,
    -- TABULAR: If capabilityUpdateRequirements is not present, the default value
    -- defined in 10.3.3.2 shall be used.
    capabilityUpdateRequirement   CapabilityUpdateRequirement-r4  OPTIONAL,
-- Radio bearer IEs
    srb-InformationSetupList      SRB-InformationSetupList2,
-- Transport channel IEs
    ul-CommonTransChInfo         UL-CommonTransChInfo          OPTIONAL,
    ul-AddReconfTransChInfoList   UL-AddReconfTransChInfoList,
    dl-CommonTransChInfo         DL-CommonTransChInfo-r4      OPTIONAL,
    dl-AddReconfTransChInfoList   DL-AddReconfTransChInfoList,
-- Physical channel IEs
    frequencyInfo                FrequencyInfo               OPTIONAL,
    maxAllowedUL-TX-Power        MaxAllowedUL-TX-Power     OPTIONAL,
    ul-ChannelRequirement        UL-ChannelRequirement-r4    OPTIONAL,
    dl-CommonInformation         DL-CommonInformation-r4    OPTIONAL,
    dl-InformationPerRL-List     DL-InformationPerRL-List-r4  OPTIONAL
}

-- ****
-- 
-- RRC CONNECTION SETUP COMPLETE
-- 
-- ****

RRCConnectionSetupComplete ::= SEQUENCE {
-- TABULAR: Integrity protection shall not be performed on this message.
-- User equipment IEs
    rrc-TransactionIdentifier    RRC-TransactionIdentifier,
    startList                    STARTList,
    ue-RadioAccessCapability    UE-RadioAccessCapability      OPTIONAL,
-- Other IEs
    ue-RATSpecificCapability   InterRAT-UE-RadioAccessCapabilityList  OPTIONAL,
-- Non critical extensions
    v370NonCriticalExtensions   SEQUENCE {
        rrcConnectionSetupComplete-v370ext RRCConnectionSetupComplete-v370ext,
        v380NonCriticalExtensions        SEQUENCE {
            rrcConnectionSetupComplete-v380ext RRCConnectionSetupComplete-v380ext-IEs,
            -- Reserved for future non critical extension
            v3a0NonCriticalExtensions       SEQUENCE {
                rrcConnectionSetupComplete-v3a0ext RRCConnectionSetupComplete-v3a0ext,
                v4xyNonCriticalExtensions     SEQUENCE {
                    rrcConnectionSetupComplete-v4xyext RRCConnectionSetupComplete-v4xyext-IEs,

```

```

        nonCriticalExtensions           SEQUENCE {}      OPTIONAL
    } } OPTIONAL
} } OPTIONAL
}

RRCConnectionSetupComplete-v370ext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v370ext     UE-RadioAccessCapability-v370ext     OPTIONAL
}

RRCConnectionSetupComplete-v380ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v380ext     UE-RadioAccessCapability-v380ext     OPTIONAL,
    dl-PhysChCapabilityFDD-v380ext       DL-PhysChCapabilityFDD-v380ext
}

RRCConnectionSetupComplete-v3a0ext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v3a0ext     UE-RadioAccessCapability-v3a0ext     OPTIONAL
}

RRCConnectionSetupComplete-v4xyext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-r4-ext     UE-RadioAccessCapability-r4-ext     OPTIONAL
}

-- *****
-- 
-- RRC FAILURE INFO
-- 
-- *****

RRC-FailureInfo ::= CHOICE {
    r3                               SEQUENCE {
        rRC-FailureInfo-r3
        nonCriticalExtensions
    },
    criticalExtensions               SEQUENCE {}
}

RRC-FailureInfo-r3-IEs ::= SEQUENCE {
    -- Non-RRC IEs
    failureCauseWithProtErr         FailureCauseWithProtErr
}

END

```

## 11.3 Information element definitions

```

InformationElements DEFINITIONS AUTOMATIC TAGS ::=
-- *****
-- 
-- CORE NETWORK INFORMATION ELEMENTS (10.3.1)
-- 
-- *****

BEGIN

IMPORTS

    hiPDSCHidentities,
    hiPUSCHidentities,
    hiRM,
    maxAC,
    maxAdditionalMeas,
    maxASC,
    maxASCmap,
    maxASCpersist,
    maxCCTrCH,
    maxCellMeas,
    maxCellMeas-1,
    maxCNdomains,
    maxCPCHsets,
    maxDPCH-DLchan,

```

```

maxDPDCH-UL,
maxDRACclasses,
maxFACHPCH,
maxFreq,
maxFreqBandsFDD,
maxFreqBandsTDD,
maxFreqBandsGSM,
maxInterSysMessages,
maxLoCHperRLC,
maxMeasEvent,
maxMeasIntervals,
maxMeasParEvent,
maxNumCDMA2000Freqs,
maxNumFDDFreqs,
maxNumGSMFreqRanges,
maxNumTDDFreqs,
maxOtherRAT,
maxOtherRAT-16,
maxPage1,
maxPCPCH-APsig,
maxPCPCH-APsubCh,
maxPCPCH-CDsig,
maxPCPCH-CDsubCh,
maxPCPCH-SF,
maxPCPCHs,
maxPDCPAlgoType,
maxPDSCH,
maxPDSCH-TFCIgroups,
maxPRACH,
maxPRACH-FPACH,
maxPredefConfig,
maxPUSCH,
maxRABsetup,
maxRAT,
maxRB,
maxRBallRABs,
maxRBMsgOptions,
maxRBperRAB,
maxReportedGSMCells,
maxSRBsetup,
maxRL,
maxRL-1,
maxROHC-PacketSizes-r4,
maxROHC-Profile-r4,
maxSCCPCH,
maxSat,
maxSIB,
maxSIB-FACH,
maxSystemCapability,
maxTF,
maxTF-CPCH,
maxTFC,
maxTFCsub,
maxTFCI-2-Combs,
maxTGPS,
maxTrCH,
maxTrCHpreconf,
maxTS,
maxTS-1,
maxTS-LCR,
maxTS-LCR-1,
maxURA
FROM Constant-definitions;

FailureCauseWithProtErrTrId ::=      SEQUENCE {
    rrc-TransactionIdentifier,
    failureCause
    FailureCauseWithProtErr
}

GSM-Measurements ::=                  SEQUENCE {
    gsm900
    BOOLEAN,
    dcs1800
    BOOLEAN,
    gsm1900
    BOOLEAN
}

UESpecificBehaviourInformation1idle ::= BIT STRING (SIZE ([4]))
UESpecificBehaviourInformation1interRAT ::= BIT STRING (SIZE (8))

```

```

IMSI-and-ESN-DS-41 ::=          SEQUENCE {
    imsi-DS-41                  IMSI-DS-41,
    esn-DS-41                   ESN-DS-41
}

IMSI-DS-41 ::=                  OCTET STRING (SIZE (5..7))

InitialPriorityDelayList ::=      SEQUENCE (SIZE (1..maxASC)) OF
                                    NS-IP

```

END

## 11.5 RRC information between network nodes

```
Internode-definitions DEFINITIONS AUTOMATIC TAGS ::=
```

BEGIN

IMPORTS

```

HandoverToUTRANCommand,
MeasurementReport,
PhysicalChannelReconfiguration,
RadioBearerReconfiguration,
RadioBearerRelease,
RadioBearerSetup,
RRC-FailureInfo-r3-IEs,
TransportChannelReconfiguration
FROM PDU-definitions

```

```

-- Core Network IEs :
CN-DomainIdentity,
CN-DomainInformationList,
CN-DomainInformationListFull,
CN-DRX-CycleLengthCoefficient,
NAS-SystemInformationGSM-MAP,
-- UTRAN Mobility IEs :
CellIdentity,
URA-Identity,
-- User Equipment IEs :
AccessStratumReleaseIndicator,
C-RNTI,
ChipRateCapability,
DL-PhysChCapabilityFDD-v380ext,
DL-PhysChCapabilityTDD,
DL-PhysChCapabilityTDD-LCR-r4,
GSM-Measurements,
FailureCauseWithProtErr,
MaxHcContextSpace,
MaxNoPhysChBitsReceived,
MaxROHC-ContextSessions-r4,
NetworkAssistedGPS-Supported,
RadioFrequencyBandTDDList,
RLC-Capability,
RRC-MessageSequenceNumber,
SecurityCapability,
SimultaneousSCCPCH-DPCH-Reception,
STARTList,
STARTSingle,
START-Value,
SupportOfDedicatedPilotsForChEstimation,
TransportChannelCapability,
TxRxFrequencySeparation,
U-RNTI,
UE-MultiModeRAT-Capability,
UE-PowerClass-v370,
UE-RadioAccessCapabBandFDDList,
UE-RadioAccessCapability,
UE-RadioAccessCapability-v370ext,
UE-RadioAccessCapability-v380ext,
UE-RadioAccessCapability-v3a0ext,
UE-RadioAccessCapability-v4xyext,
UL-PhysChCapabilityFDD,
UL-PhysChCapabilityTDD,
UL-PhysChCapabilityTDD-LCR-r4,

```

```

-- Radio Bearer IEs :
    PredefinedConfigStatusList,
    PredefinedConfigValueTag,
    RAB-InformationSetupList,
    RAB-InformationSetupList-r4,
    RAB-Identity,
    RB-Identity,
    SRB-InformationSetupList,
-- Transport Channel IEs :
    CPCH-SetID,
    DL-CommonTransChInfo,
    DL-CommonTransChInfo-r4,
    DL-AddReconfTransChInfoList,
    DL-AddReconfTransChInfoList-r4,
    DRAC-StaticInformationList,
    UL-CommonTransChInfo,
    UL-CommonTransChInfo-r4,
    UL-AddReconfTransChInfoList,
-- Measurement IEs :
    MeasurementIdentity,
    MeasurementReportingMode,
    MeasurementType,
    MeasurementType-r4,
    AdditionalMeasurementID-List,
    PositionEstimate,
    UE-Positioning-IPDL-Parameters-TDD-r4-ext,
-- Other IEs :
    InterRAT-UE-RadioAccessCapabilityList

FROM InformationElements

maxCNdomains,
maxNoOfMeas,

maxRB,
maxSRBsetup
FROM Constant-definitions
;

-- Part 1: Class definitions similar to what has been defined in 11.1 for RRC messages
-- Information that is transferred in the same direction and across the same path is grouped

-- ****
-- 
-- RRC information, to target RNC
-- 
-- ****
-- RRC Information to target RNC sent either from source RNC or from another RAT

ToTargetRNC-Container ::= CHOICE {
    interRATHandoverInfo           InterRATHandoverInfoWithInterRATCapabilities-r3,
    srncRelocation                 SRNC-RelocationInfo-r3,
    extension                      NULL
}

-- ****
-- 
-- RRC information, target RNC to source RNC
-- 
-- ****

Target-RNC-ToSourceRNC-Container ::= CHOICE {
    radioBearerSetup                RadioBearerSetup,
    radioBearerReconfiguration      RadioBearerReconfiguration,
    radioBearerRelease              RadioBearerRelease,
    transportChannelReconfiguration TransportChannelReconfiguration,
    physicalChannelReconfiguration PhysicalChannelReconfiguration,
    rrcFailureInfo                 RRC-FailureInfo-r3-IEs,
    -- IE dl-DCCHmessage consists of an octet string that includes
    -- the IE DL-DCCH-Message
    dL-DCCHmessage                 OCTET STRING,
    extension                       NULL
}

-- Part 2: Container definitions, similar to the PDU definitions in 11.2 for RRC messages
-- In alphabetical order

```

```

-- ****
-- Handover to UTRAN information
-- ****

InterRATHandoverInfoWithInterRATCapabilities-r3 ::= CHOICE {
    r3           SEQUENCE {
        -- IE InterRATHandoverInfoWithInterRATCapabilities-r3-IEs also
        -- includes non critical extensions
        interRATHandoverInfo-r3      InterRATHandoverInfoWithInterRATCapabilities-r3-IEs,
        v390NonCriticalExtensions   SEQUENCE {
            interRATHandoverInfoWithInterRATCapabilities-v390ext
        },
        InterRATHandoverInfoWithInterRATCapabilities-v390ext-IEs,
        -- Reserved for future non critical extension
        nonCriticalExtensions       SEQUENCE {} OPTIONAL
    }           OPTIONAL
},
criticalExtensions          SEQUENCE {}
}

InterRATHandoverInfoWithInterRATCapabilities-r3-IEs ::= SEQUENCE {
    -- The order of the IE's may not reflect the tabular format
    -- but has been chosen to simplify the handling of the information in the BSC
    -- Other IE's
    ue-RATSpecificCapability     InterRAT-UE-RadioAccessCapabilityList OPTIONAL,
    -- interRATHandoverInfo, Octet string is used to obtain 8 bit length field prior to
    -- actual information. This makes it possible for BSS to transparently handle information
    -- received via GSM air interface even when it includes non critical extensions.
    -- The octet string shall include the InterRATHandoverInfo information
    -- The BSS can re-use the 04.18 length field received from the MS
    interRATHandoverInfo         OCTET STRING (SIZE (0..255))
}
}

InterRATHandoverInfoWithInterRATCapabilities-v390ext-IEs ::= SEQUENCE {
    -- User equipment IE's
    failureCauseWithProtErr      FailureCauseWithProtErr
                                OPTIONAL
}
}

-- ****
-- SRNC Relocation information
-- ****

SRNC-RelocationInfo-r3 ::= CHOICE {
    r3           SEQUENCE {
        SRNC-RelocationInfo-r3      SRNC-RelocationInfo-r3-IEs,
        v380NonCriticalExtensions   SEQUENCE {
            SRNC-RelocationInfo-v380ext SRNC-RelocationInfo-v380ext-IEs,
            -- Reserved for future non critical extension
            v390NonCriticalExtensions   SEQUENCE {
                SRNC-RelocationInfo-v390ext      SRNC-RelocationInfo-v390ext-IEs,
                v3a0NonCriticalExtensions       SEQUENCE {
                    SRNC-RelocationInfo-v3a0ext      SRNC-RelocationInfo-v3a0ext-IEs,
                    v3b0NonCriticalExtensions       SEQUENCE {
                        SRNC-RelocationInfo-v3b0ext      SRNC-RelocationInfo-v3b0ext-IEs,
                        v3c0NonCriticalExtensions       SEQUENCE {
                            SRNC-RelocationInfo-v3c0ext      SRNC-RelocationInfo-v3c0ext-IEs,
                            v3d0NonCriticalExtensions       SEQUENCE {
                                SRNC-RelocationInfo-v3d0ext      SRNC-RelocationInfo-v3d0ext-IEs,
                                v4xyNonCriticalExtensions     SEQUENCE {
                                    SRNC-RelocationInfo-v4xyext      SRNC-RelocationInfo-
v4xyext-IEs,
                                    -- Reserved for future non critical extension
                                    nonCriticalExtensions        SEQUENCE {} OPTIONAL
                                }           OPTIONAL
                            }           OPTIONAL
                        }           OPTIONAL
                    }           OPTIONAL
                }           OPTIONAL
            }           OPTIONAL
        }           OPTIONAL
    }           OPTIONAL
},
later-than-r3                 CHOICE {
    r4           SEQUENCE {
        SRNC-RelocationInfo-r4      SRNC-RelocationInfo-r4-IEs,
        nonCriticalExtensions       SEQUENCE {} OPTIONAL
    },
}

```

```

        criticalExtensions          SEQUENCE {}
    }

SRNC-RelocationInfo-r3-IEs ::= SEQUENCE {
    -- Non-RRC IEs
    stateOfRRC                  StateOfRRC,
    stateOfRRC-Procedure         StateOfRRC-Procedure,
    -- Ciphering related information IEs
    -- If the extension v380 is included use the extension for the ciphering status per CN domain
    cipheringStatus              CipheringStatus,
    calculationTimeForCiphering  CalculationTimeForCiphering OPTIONAL,
    -- The order of occurrence in the IE cipheringInfoPerRB-List is the
    -- same as the RBs in the IE "Signalling RB information list" and in the
    -- IE "RAB information list". The signalling RBs are supposed to be listed
    -- first. Only UM and AM RBs that are ciphered are listed here
    cipheringInfoPerRB-List      CipheringInfoPerRB-List OPTIONAL,
    count-C-List                 COUNT-C-List OPTIONAL,
    integrityProtectionStatus    IntegrityProtectionStatus,
    srb-SpecificIntegrityProtInfo SRB-SpecificIntegrityProtInfoList,
    implementationSpecificParams ImplementationSpecificParams OPTIONAL,
    -- User equipment IEs
    u-RNTI                      U-RNTI,
    c-RNTI                      C-RNTI OPTIONAL,
    ue-RadioAccessCapability     UE-RadioAccessCapability,
    ue-Positioning-LastKnownPos  UE-Positioning-LastKnownPos OPTIONAL,
    -- Other IEs
    ue-RATSpecificCapability    InterRAT-UE-RadioAccessCapabilityList OPTIONAL,
    -- UTRAN mobility IEs
    ura-Identity                 URA-Identity OPTIONAL,
    -- Core network IEs
    cn-CommonGSM-MAP-NAS-SysInfo NAS-SystemInformationGSM-MAP,
    cn-DomainInformationList     CN-DomainInformationList OPTIONAL,
    -- Measurement IEs
    ongoingMeasRepList           OngoingMeasRepList OPTIONAL,
    -- Radio bearer IEs
    predefinedConfigStatusList   PredefinedConfigStatusList,
    srb-InformationList          SRB-InformationSetupList,
    rab-InformationList          RAB-InformationSetupList OPTIONAL,
    -- Transport channel IEs
    ul-CommonTransChInfo         UL-CommonTransChInfo OPTIONAL,
    ul-TransChInfoList           UL-AddReconfTransChInfoList OPTIONAL,
    modeSpecificInfo {
        fdd {
            cpch-SetID             CPCH-SetID OPTIONAL,
            transChDRAC-Info       DRAC-StaticInformationList OPTIONAL
        },
        tdd {
            NULL
        },
        dl-CommonTransChInfo      DL-CommonTransChInfo OPTIONAL,
        dl-TransChInfoList        DL-AddReconfTransChInfoList OPTIONAL,
    -- Measurement report
    measurementReport             MeasurementReport OPTIONAL ,
    nonCriticalExtensions {
        -- In case of TDD only up-Ipd1-Parameters-TDD is present, otherwise
        -- this IE is absent
        up-Ipd1-Parameters-TDD    UE-Positioning-IPDL-Parameters-TDD-r4-ext OPTIONAL,
        -- Extension mechanism for non- release4 information
        nonCriticalExtensions    SEQUENCE {} OPTIONAL
    }
}
}

SRNC-RelocationInfo-v380ext-IEs ::= SEQUENCE {
    -- Ciphering related information IEs
    cn-DomainIdentity            CN-DomainIdentity,
    cipheringStatusList          CipheringStatusList
}

SRNC-RelocationInfo-v390ext-IEs ::= SEQUENCE {
    cn-DomainInformationList-v390ext CN-DomainInformationList-v390ext OPTIONAL,
    ue-RadioAccessCapability-v370ext UE-RadioAccessCapability-v370ext OPTIONAL,
    ue-RadioAccessCapability-v380ext UE-RadioAccessCapability-v380ext OPTIONAL,
    dl-PhysChCapabilityFDD-v380ext DL-PhysChCapabilityFDD-v380ext,
    failureCauseWithProtErr      FailureCauseWithProtErr OPTIONAL
}

SRNC-RelocationInfo-v3a0ext-IEs ::= SEQUENCE {
    -- cn-domain identity for IE startValueForCiphering-v3a0ext is specified
    -- in subsequent extension (SRNC-RelocationInfo-v3b0ext-IEs)
}

```

```

        startValueForCIphering-v3a0ext      START-Value,
        cipheringInfoForSRB1-v3a0ext       CipheringInfoForSRB1-v3a0ext,
        ue-RadioAccessCapability-v3a0ext   UE-RadioAccessCapability-v3a0ext      OPTIONAL
    }

SRNC-RelocationInfo-v3b0ext-IEs ::= SEQUENCE {
    -- cn-domain identity for IE startValueForCIphering-v3a0ext included in previous extension
    cn-DomainIdentity          CN-DomainIdentity,
    -- the remaining start values are contained in IE startValueForCIphering-v3b0ext
    startValueForCIphering-v3b0ext     STARTList2           OPTIONAL
}

SRNC-RelocationInfo-v3c0ext-IEs ::= SEQUENCE {
    -- IE rb-IdentityForHOMessage includes the identity of the RB used by the source SRNC
    -- to send the message contained in the IE "TargetRNC-ToSourceRNC-Container".
    -- Only included if type is "UE involved"
    rb-IdentityForHOMessage      RB-Identity           OPTIONAL
}

SRNC-RelocationInfo-v3d0ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    uESpecificBehaviourInformationlidle   UESpecificBehaviourInformationlidle   OPTIONAL,
    uESpecificBehaviourInformationlinterRAT UESpecificBehaviourInformationlinterRAT
    OPTIONAL
}

STARTList2 ::= SEQUENCE (SIZE (2..maxCNdomains)) OF
                STARTSingle

SRNC-RelocationInfo-v4xyext-IEs ::= SEQUENCE {
    ue-RadioAccessCapability-v4xyext     UE-RadioAccessCapability-v4xyext
}

CipheringInfoForSRB1-v3a0ext ::= SEQUENCE {
    dl-UM-SN                      BIT STRING (SIZE (7))
}

CipheringStatusList ::= SEQUENCE (SIZE (1..maxCNdomains)) OF
                        CipheringStatusCNdomain

CipheringStatusCNdomain ::= SEQUENCE {
    cn-DomainIdentity          CN-DomainIdentity,
    cipheringStatus            CipheringStatus
}

SRNC-RelocationInfo-r4-IEs ::= SEQUENCE {
    -- Non-RRC IEs
    -- IE rb-IdentityForHOMessage includes the identity of the RB used by the source SRNC
    -- to send the message contained in the IE "TargetRNC-ToSourceRNC-Container".
    -- Only included if type is "UE involved"
    rb-IdentityForHOMessage      RB-Identity           OPTIONAL,
    stateOfRRC                  StateOfRRC,
    stateOfRRC-Procedure        StateOfRRC-Procedure,
    -- Ciphering related information IEs
    cipheringStatusList         CipheringStatusList-r4,
    latestConfiguredCN-Domain   CN-DomainIdentity,
    calculationTimeForCiphering CalculationTimeForCiphering   OPTIONAL,
    count-C-List                COUNT-C-List          OPTIONAL,
    cipheringInfoPerRB-List     CipheringInfoPerRB-List-r4   OPTIONAL,
    -- Integrity protection related information IEs
    integrityProtectionStatus   IntegrityProtectionStatus,
    srb-SpecificIntegrityProtInfo SRB-SpecificIntegrityProtInfoList,
    implementationSpecificParams ImplementationSpecificParams   OPTIONAL,
    -- User equipment IEs
    u-RNTI                      U-RNTI,
    c-RNTI                      C-RNTI           OPTIONAL,
    ue-RadioAccessCapability     UE-RadioAccessCapability-r4,
    ue-RadioAccessCapability-ext UE-RadioAccessCapabBandFDDList   OPTIONAL,
    ue-Positioning-LastKnownPos  UE-Positioning-LastKnownPos   OPTIONAL,
    uESpecificBehaviourInformationlidle   UESpecificBehaviourInformationlidle   OPTIONAL,
    uESpecificBehaviourInformationlinterRAT UESpecificBehaviourInformationlinterRAT
    OPTIONAL,
    -- Other IEs
    ue-RATSpecificCapability    InterRAT-UE-RadioAccessCapabilityList   OPTIONAL,
    -- UTRAN mobility IEs
    ura-Identity                 URA-Identity           OPTIONAL,
    -- Core network IEs
    cn-CommonGSM-MAP-NAS-SysInfo NAS-SystemInformationGSM-MAP,
}

```

```

    cn-DomainInformationListFull          OPTIONAL,
-- Measurement IEs
    ongoingMeasRepList                 OPTIONAL,
-- Radio bearer IEs
    predefinedConfigStatusList         PredefinedConfigStatusList,
    srb-InformationList               SRB-InformationSetupList,
    rab-InformationList               RAB-InformationSetupList-r4   OPTIONAL,
-- Transport channel IEs
    ul-CommonTransChInfo              UL-CommonTransChInfo-r4      OPTIONAL,
    ul-TransChInfoList                UL-AddReconfTransChInfoList  OPTIONAL,
    modeSpecificInfo
        fdd                           CHOICE {
            cpch-SetID                  SEQUENCE {
                CPCH-SetID                OPTIONAL,
                transChDRAC-Info           DRAC-StaticInformationList  OPTIONAL
            },
            tdd                           NULL
        }
        dl-CommonTransChInfo          DL-CommonTransChInfo-r4      OPTIONAL,
        dl-TransChInfoList            DL-AddReconfTransChInfoList  OPTIONAL,
-- Measurement report
    measurementReport                 MeasurementReport           OPTIONAL,
    failureCause                     FailureCauseWithProtErr    OPTIONAL
}

-- IE definitions

CalculationTimeForCiphering ::= SEQUENCE {
    cell-Id                         CellIdentity,
    sfn                             INTEGER (0..4095)
}

CipheringInfoPerRB ::= SEQUENCE {
    dl-HFN                          BIT STRING (SIZE (20..25)),
    ul-HFN                          BIT STRING (SIZE (20..25))
}

CipheringInfoPerRB-r4 ::= SEQUENCE {
    rb-Identity                      RB-Identity,
    dl-HFN                          BIT STRING (SIZE (20..25)),
    dl-UM-SN                         BIT STRING (SIZE (7))           OPTIONAL,
    ul-HFN                          BIT STRING (SIZE (20..25))
}

-- TABULAR: CipheringInfoPerRB-List, multiplicity value numberOfRadioBearers
-- has been replaced with maxRB.
CipheringInfoPerRB-List ::= SEQUENCE (SIZE (1..maxRB)) OF
    CipheringInfoPerRB

CipheringInfoPerRB-List-r4 ::= SEQUENCE (SIZE (1..maxRB)) OF
    CipheringInfoPerRB-r4

CipheringStatus ::= ENUMERATED {
    started, notStarted
}

CipheringStatusList-r4 ::= SEQUENCE (SIZE (1..maxCNdomains)) OF
    CipheringStatusCNdomain-r4

CipheringStatusCNdomain-r4 ::= SEQUENCE {
    cn-DomainIdentity               CN-DomainIdentity,
    cipheringStatus                 CipheringStatus,
    start-Value                     START-Value
}

CN-DomainInformation-v390ext ::= SEQUENCE {
    cn-DRX-CycleLengthCoeff         CN-DRX-CycleLengthCoefficient
}

CN-DomainInformationList-v390ext ::= SEQUENCE (SIZE (1..maxCNdomains)) OF
    CN-DomainInformation-v390ext

CompressedModeMeasCapability-r4 ::= SEQUENCE {
    fdd-Measurements                BOOLEAN,
    -- TABULAR: The IEs tdd-Measurements, gsm-Measurements and multiCarrierMeasurements
    -- are made optional since they are conditional based on another information element.
    -- Their absence corresponds to the case where the condition is not true.
    tdd384-Measurements              BOOLEAN                   OPTIONAL,
    tdd128-Measurements              BOOLEAN                   OPTIONAL,
    gsm-Measurements                 GSM-Measurements        OPTIONAL,
    multiCarrierMeasurements         BOOLEAN                   OPTIONAL
}

```

```

}

COUNT-C-List ::= SEQUENCE (SIZE (1..maxCNdomains)) OF COUNT-CSingle

COUNT-CSingle ::= SEQUENCE {
    cn-DomainIdentity,
    count-C
}

DL-PhysChCapabilityFDD-r4 ::= SEQUENCE {
    maxNoDPCH-PDSCH-Codes INTEGER (1..8),
    maxNoPhysChBitsReceived MaxNoPhysChBitsReceived,
    supportForSF-512 BOOLEAN,
    supportOfPDSCH BOOLEAN,
    simultaneousSCCPCH-DPCH-Reception SimultaneousSCCPCH-DPCH-Reception,
    supportOfDedicatedPilotsForChEstimation SupportOfDedicatedPilotsForChEstimation OPTIONAL
}

ImplementationSpecificParams ::= BIT STRING (SIZE (1..512))

IntegrityProtectionStatus ::= ENUMERATED {
    started, notStarted }

MeasurementCapability-r4 ::= SEQUENCE {
    downlinkCompressedMode CompressedModeMeasCapability-r4,
    uplinkCompressedMode CompressedModeMeasCapability-r4 }

MeasurementCommandWithType ::= CHOICE {
    setup MeasurementType,
    modify NULL,
    release NULL }

MeasurementCommandWithType-r4 ::= CHOICE {
    setup MeasurementType-r4,
    modify NULL,
    release NULL }

OngoingMeasRep ::= SEQUENCE {
    measurementIdentity MeasurementIdentity,
    -- TABULAR: The CHOICE Measurement in the tabular description is included
    -- in MeasurementCommandWithType
    measurementCommandWithType MeasurementCommandWithType,
    measurementReportingMode MeasurementReportingMode OPTIONAL,
    additionalMeasurementID-List AdditionalMeasurementID-List OPTIONAL }

OngoingMeasRep-r4 ::= SEQUENCE {
    measurementIdentity MeasurementIdentity,
    -- TABULAR: The CHOICE Measurement in the tabular description is included
    -- in MeasurementCommandWithType-r4.
    measurementCommandWithType MeasurementCommandWithType-r4,
    measurementReportingMode MeasurementReportingMode OPTIONAL,
    additionalMeasurementID-List AdditionalMeasurementID-List OPTIONAL }

OngoingMeasRepList ::= SEQUENCE (SIZE (1..maxNoOfMeas)) OF OngoingMeasRep

OngoingMeasRepList-r4 ::= SEQUENCE (SIZE (1..maxNoOfMeas)) OF OngoingMeasRep-r4

PDCP-Capability-r4 ::= SEQUENCE {
    losslessSRNS-RelocationSupport BOOLEAN,
    supportForRfc2507 CHOICE {
        notSupported NULL,
        supported MaxHcContextSpace
    },
    supportForRfc3095 CHOICE {
        notSupported NULL,
        supported SEQUENCE {
            maxROHC-ContextSessions MaxROHC-ContextSessions-r4 DEFAULT s16,
            reverseCompressionDepth INTEGER (0..65535) DEFAULT 0
        }
    }
}

```

```

}

PhysicalChannelCapability-r4 ::= SEQUENCE {
    fddPhysChCapability      SEQUENCE {
        downlinkPhysChCapability
        uplinkPhysChCapability
    }
    tdd384-PhysChCapability  SEQUENCE {
        downlinkPhysChCapability
        uplinkPhysChCapability
    }
    tdd128-PhysChCapability  SEQUENCE {
        downlinkPhysChCapability
        uplinkPhysChCapability
    }
}

RF-Capability-r4 ::= SEQUENCE {
    fddRF-Capability         SEQUENCE {
        ue-PowerClass
        txRxFrequencySeparation
    }
    tdd384-RF-Capability     SEQUENCE {
        ue-PowerClass
        radioFrequencyBandTDDList
        chipRateCapability
    }
    tdd128-RF-Capability     SEQUENCE {
        ue-PowerClass
        radioFrequencyBandTDDList
        chipRateCapability
    }
}

SRB-SpecificIntegrityProtInfo ::= SEQUENCE {
    ul-RRC-HFN               BIT STRING (SIZE (28)),
    dl-RRC-HFN               BIT STRING (SIZE (28)),
    ul-RRC-SequenceNumber     RRC-MessageSequenceNumber,
    dl-RRC-SequenceNumber     RRC-MessageSequenceNumber
}

SRB-SpecificIntegrityProtInfoList ::= SEQUENCE (SIZE (4..maxSRBsetup)) OF
    SRB-SpecificIntegrityProtInfo

StateOfRRC ::= ENUMERATED {
    cell-DCH, cell-FACH,
    cell-PCH, ura-PCH }

StateOfRRC-Procedure ::= ENUMERATED {
    awaitNoRRC-Message,
    awaitRB-ReleaseComplete,
    awaitRB-SetupComplete,
    awaitRB-ReconfigurationComplete,
    awaitTransportCH-ReconfigurationComplete,
    awaitPhysicalCH-ReconfigurationComplete,
    awaitActiveSetUpdateComplete,
    awaitHandoverComplete,
    sendCellUpdateConfirm,
    sendUraUpdateConfirm,
    -- dummy is not used in this version of specification
    -- It should not be sent
    dummy,
    otherStates
}

UE-Positioning-LastKnownPos ::= SEQUENCE {
    sfn                      INTEGER (0..4095),
    cell-id                  CellIdentity,
    positionEstimate          PositionEstimate
}

UE-Positioning-Capability-r4 ::= SEQUENCE {
    standaloneLocMethodsSupported BOOLEAN,
    ue-BasedOTDOA-Supported      BOOLEAN,
    networkAssistedGPS-Supported BOOLEAN,
    supportForUE-GPS-TimingOfCellFrames BOOLEAN,
    supportForIPDL                BOOLEAN,
    rx-tx-TimeDifferenceType2Capable BOOLEAN,
    validity-CellPCH-UraPCH       ENUMERATED { true (0) } OPTIONAL
}

```

```

}

UE-RadioAccessCapability-r4 ::= SEQUENCE {
    accessStratumReleaseIndicator,
    pdcp-Capability,
    rlc-Capability,
    transportChannelCapability,
    rf-Capability,
    physicalChannelCapability,
    ue-MultiModeRAT-Capability,
    securityCapability,
    ue-positioning-Capability,
    measurementCapability
} OPTIONAL
}

```

END

#### 14.12.4.1 INTER RAT HANDOVER INFO WITH INTER RAT CAPABILITIES

This RRC message is sent between network nodes when preparing for an inter RAT handover to UTRAN.

Direction: source RAT→target RNC

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
<b>UE Information elements</b>				
UE security information	OP		UE security information 10.3.3.42b	
UE capability container	OP			
>UE radio access capability	MP		UE radio access capability 10.3.3.42	
>UE radio access capability extension	MP		UE radio access capability extension 10.3.3.42a	Although this IE is not always required, the need has been set to MP to align with the ASN.1
<a href="#"><u>&gt;UE Specific Behaviour Information 1 interRAT</u></a>	<a href="#"><u>OP</u></a>		<a href="#"><u>UE Specific Behaviour Information 1 interRAT 10.3.3.52</u></a>	<a href="#"><u>This IE shall not be included in this version of the protocol</u></a>

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
<b>Non RRC IEs</b>				
<b>Radio Bearer IEs</b>				
Predefined configuration status information	OP		Predefined configuration status information 10.3.4.5a	
<b>Other Information elements</b>				
UE system specific capability	OP	1 to <maxSystemCapability>		
>Inter-RAT UE radio access capability	MP		Inter-RAT UE radio access capability 10.3.8.7	
Failure cause	OP		Failure cause 10.3.3.13	Diagnostics information related to an earlier handover to UTRAN request
Protocol error information	CV-ProtErr		Protocol error information 10.3.8.12	

Condition	Explanation
ProtErr	This IE is mandatory present if the IE "Protocol error indicator" is included and has the value "TRUE". Otherwise it is not needed.

NOTE: The above table does not need to reflect the order of the information elements in the actual encoded message. The order, that is reflected in the ASN.1, should be chosen in a manner that avoids that network nodes need to perform reordering of information elements.

#### 14.12.4.2 SRNS RELOCATION INFO

This RRC message is sent between network nodes when preparing for an SRNS relocation.

With the presence or absence of the IE "RB identity for Hard Handover message" the source RNC indicates to the target SRNC whether the source RNC expects to receive the choice "DL DCCH message" in the IE "RRC information, target RNC to source RNC" in case the SRNS relocation is of type "UE involved". Furthermore the target RNC uses this information for the calculation of the MAC-I.

Direction: source RNC→target RNC

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
<b>Non RRC IEs</b>				
RB identity for Handover message	OP		RB identity 10.3.4.16	Gives the id of the radio bearer on which the source RNC will transmit the RRC message in the case the relocation is of type "UE involved".
>State of RRC	MP		RRC state indicator, 10.3.3.35a	
>State of RRC procedure	MP		Enumerated (await no RRC message, await RB Release Complete, await RB Setup)	

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
			Complete, await RB Reconfiguration Complete, await Transport CH Reconfiguration Complete, await Physical CH Reconfiguration Complete, await Active Set Update Complete, await Handover Complete, send Cell Update Confirm, send URA Update Confirm, , others)	
<b>Ciphering related information</b>				
>Ciphering status for each CN domain	MP	<1 to maxCNDo mains>		
>>CN domain identity	MP		CN domain identity 10.3.1.1	
>>Ciphering status	MP		Enumerated( Not started, Started)	
>>START	MP		START 10.3.3.38	START value to be used in this CN domain.
>Latest configured CN domain	MP		CN domain identity 10.3.1.1	Value contained in the variable of the same name. In case this variable is empty, the source RNC can set any CN domain identity. In that case, the Ciphering status and the Integrity protection status should be Not started and the target RNC should not initialise the variable Latest configured CN domain.
>Calculation time for ciphering related information	CV-Ciphering			Time when the ciphering information of the message were calculated, relative to a cell of the target RNC
>>Cell Identity	MP		Cell Identity 10.3.2.2	Identity of one of the cells under the target RNC and included in the active set of the current call
>>SFN	MP		Integer(0..4095)	
>COUNT-C list	OP	1 to <maxCNDo mains>		COUNT-C values for radio bearers using transparent mode RLC
>>CN domain identity	MP		CN domain	

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
			identity 10.3.1.1	
>>COUNT-C	MP		Bit string(32)	
>Ciphering info per radio bearer	OP	1 to <maxRBs>		For signalling radio bearers this IE is mandatory.
>>RB identity	MP		RB identity 10.3.4.16	
>>Downlink HFN	MP		Bit string(20..25 )	This IE is either RLC AM HFN (20 bits) or RLC UM HFN (25 bits)
>>Downlink SN	CV-SRB1		Bit String(7)	VT(US) of RLC UM
>>Uplink HFN	MP		Bit string(20..25 )	This IE is either RLC AM HFN (20 bits) or RLC UM HFN (25 bits)
<b>Integrity protection related information</b>				
>Integrity protection status	MP		Enumerated( Not started, Started)	
>Signalling radio bearer specific integrity protection information	CV-IP	4 to <maxSRBs etup>		
>>Uplink RRC HFN	MP		Bit string (28)	For each SRB, this IE corresponds to the last value used.
>>Downlink RRC HFN	MP		Bit string (28)	For each SRB, this IE corresponds to the last value used. In particular, for SRB2, this IE should not take into account the RRC message that will trigger the relocation.
>>Uplink RRC Message sequence number	MP		Integer (0.. 15)	For each SRB, this IE corresponds to the last value used.
>>Downlink RRC Message sequence number	MP		Integer (0.. 15)	For each SRB, this IE corresponds to the last value used. In particular, for SRB2, this IE should not take into account the RRC message that will trigger the relocation.
>Implementation specific parameters	OP		Bit string (1..512)	
<b>RRC IEs</b>				
<b>UE Information elements</b>				
>U-RNTI	MP		U-RNTI 10.3.3.47	
>C-RNTI	OP		C-RNTI 10.3.3.8	
>UE radio access Capability	MP		UE radio access capability 10.3.3.42	
>UE radio access capability extension	OP		UE radio access capability extension 10.3.3.42a	
>Last known UE position	OP			
>>SFN	MP		Integer (0..4095)	Time when position was estimated
>>Cell ID	MP		Cell identity; 10.3.2.2	Indicates the cell, the SFN is valid for.
>>CHOICE Position estimate	MP			
>>>Ellipsoid Point			Ellipsoid Point; 10.3.8.4a	

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
>>>Ellipsoid point with uncertainty circle			Ellipsoid point with uncertainty circle 10.3.8.4d	
>>>Ellipsoid point with uncertainty ellipse			Ellipsoid point with uncertainty ellipse 10.3.8.4e	
>>>Ellipsoid point with altitude			Ellipsoid point with altitude 10.3.8.4b	
>>>Ellipsoid point with altitude and uncertainty ellipsoid			Ellipsoid point with altitude and uncertainty ellipsoid 10.3.8.4c	
<a href="#"><u>&gt;UE Specific Behaviour Information 1 idle</u></a>	<a href="#"><u>OP</u></a>		<a href="#"><u>UE Specific Behaviour Information idle 1</u></a> <a href="#"><u>10.3.3.51</u></a>	This IE should be included if received via the "INTER RAT HANDOVER INFO" or the "RRC CONNECTION REQUEST" or the IE "SRNS RELOCATION INFO" or the "Inter RAT Handover Info with Inter RAT Capabilities"
<a href="#"><u>&gt;UE Specific Behaviour Information 1 interRAT</u></a>	<a href="#"><u>OP</u></a>		<a href="#"><u>UE Specific Behaviour Information 1 interRAT</u></a> <a href="#"><u>10.3.3.52</u></a>	This IE should be included if received via the "INTER RAT HANDOVER INFO" or the "RRC CONNECTION REQUEST" or the IE "SRNS RELOCATION INFO" or the "Inter RAT Handover Info with Inter RAT Capabilities"
<b>Other Information elements</b>				
>UE system specific capability	OP	1 to <maxSystemCapability>		
>>Inter-RAT UE radio access capability	MP		Inter-RAT UE radio access capability 10.3.8.7	
<b>UTRAN Mobility Information elements</b>				
>URA Identifier	OP		URA identity 10.3.2.6	
<b>CN Information Elements</b>				
>CN common GSM-MAP NAS system information	MP		NAS system information (GSM-MAP) 10.3.1.9	
>CN domain related information	OP	1 to <MaxCNdomains>		CN related information to be provided for each CN domain
>>CN domain identity	MP			
>>CN domain specific GSM-MAP NAS system info	MP		NAS system information (GSM-MAP) 10.3.1.9	
>>CN domain specific DRX cycle length coefficient	MP		CN domain specific DRX cycle length	

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
			coefficient, 10.3.3.6	
<b>Measurement Related Information elements</b>				
>For each ongoing measurement reporting	OP	1 to <MaxNoOf Meas>		
>>Measurement Identity	MP		Measuremen t identity 10.3.7.48	
>>Measurement Command	MP		Measuremen t command 10.3.7.46	
>>Measurement Type	CV-Setup		Measuremen t type 10.3.7.50	
>>Measurement Reporting Mode	OP		Measuremen t reporting mode 10.3.7.49	
>>Additional Measurements list	OP		Additional measurements list 10.3.7.1	
>>CHOICE Measurement	OP			
>>>Intra-frequency				
>>>>Intra-frequency cell info	OP		Intra-frequency cell info list 10.3.7.33	
>>>>Intra-frequency measurement quantity	OP		Intra-frequency measurement quantity 10.3.7.38	
>>>>Intra-frequency reporting quantity	OP		Intra-frequency reporting quantity 10.3.7.41	
>>>>Reporting cell status	OP		Reporting cell status 10.3.7.61	
>>>>Measurement validity	OP		Measuremen t validity 10.3.7.51	
>>>>CHOICE report criteria	OP			
>>>>>Intra-frequency measurement reporting criteria			Intra-frequency measurement reporting criteria 10.3.7.39	
>>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>>No reporting			NULL	
>>>>Inter-frequency				
>>>>>Inter-frequency cell info	OP		Inter-frequency cell info list 10.3.7.13	
>>>>>Inter-frequency measurement quantity	OP		Inter-frequency measuremen	

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
			t quantity 10.3.7.18	
>>>Inter-frequency reporting quantity	OP		Inter-frequency reporting quantity 10.3.7.21	
>>>Reporting cell status	OP		Reporting cell status 10.3.7.61	
>>>Measurement validity	OP		Measuremen t validity 10.3.7.51	
>>>CHOICE report criteria	OP			
>>>>Inter-frequency measurement reporting criteria			Inter-frequency measurement reporting criteria 10.3.7.19	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting			NULL	
>>>Inter-RAT				
>>>Inter-RAT cell info	OP		Inter-RAT cell info list 10.3.7.23	
>>>Inter-RAT measurement quantity	OP		Inter-RAT measuremen t quantity 10.3.7.29	
>>>Inter-RAT reporting quantity	OP		Inter-RAT reporting quantity 10.3.7.32	
>>>Reporting cell status	OP		Reporting cell status 10.3.7.61	
>>>Measurement validity	OP		Measuremen t validity 10.3.7.51	
>>>CHOICE report criteria	OP			
>>>>Inter-RAT measurement reporting criteria			Inter-RAT measurement reporting criteria 10.3.7.30	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting			NULL	
>>>Traffic Volume				
>>>Traffic volume measurement Object	OP		Traffic volume measurement object 10.3.7.70	
>>>Traffic volume measurement quantity	OP		Traffic volume measurement quantity 10.3.7.71	
>>>Traffic volume reporting	OP		Traffic	

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
quantity			volume reporting quantity 10.3.7.74	
>>>CHOICE report criteria	OP			
>>>>Traffic volume measurement reporting criteria			Traffic volume measurement reporting criteria 10.3.7.72	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting			NULL	
>>>Quality				
>>>>Quality measurement Object	OP		Quality measurement object	
>>>CHOICE report criteria	OP			
>>>>Quality measurement reporting criteria			Quality measurement reporting criteria 10.3.7.58	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting			NULL	
>>>UE internal				
>>>>UE internal measurement quantity	OP		UE internal measurement quantity 10.3.7.79	
>>>>UE internal reporting quantity	OP		UE internal reporting quantity 10.3.7.82	
>>>CHOICE report criteria	OP			
>>>>UE internal measurement reporting criteria			UE internal measurement reporting criteria 10.3.7.80	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting			NULL	
>>>UE positioning				
>>>>LCS reporting quantity	OP		LCS reporting quantity 10.3.7.111	
>>>CHOICE report criteria	OP			
>>>>LCS reporting criteria			LCS reporting criteria 10.3.7.110	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting				

<b>Information Element/Group Name</b>	<b>Need</b>	<b>Multi</b>	<b>Type and reference</b>	<b>Semantics description</b>
<b>Radio Bearer Information Elements</b>				
>Predefined configuration status information	OP		Predefined configuration status information 10.3.4.5a	
>Signalling RB information list	MP	1 to <maxSRBs etup>		For each signalling radio bearer
>>Signalling RB information	MP		Signalling RB information to setup 10.3.4.24	
>RAB information list	OP	1 to <maxRABs etup>		Information for each RAB
>>RAB information	MP		RAB information to setup 10.3.4.10	
<b>Transport Channel Information Elements</b>				
<b>Uplink transport channels</b>				
>UL Transport channel information common for all transport channels	OP		UL Transport channel information common for all transport channels 10.3.5.24	
>UL transport channel information list	OP	1 to <MaxTrCH >		
>>UL transport channel information	MP		Added or reconfigured UL TrCH information 10.3.5.2	
>CHOICE mode	OP			
>>FDD				
>>>CPCH set ID	OP		CPCH set ID 10.3.5.5	
>>>Transport channel information for DRAC list	OP	1 to <MaxTrCH >		
>>>>DRAC static information	MP		DRAC static information 10.3.5.7	
>>TDD				(no data)
<b>Downlink transport channels</b>				
>DL Transport channel information common for all transport channels	OP		DL Transport channel information common for all transport channels 10.3.5.6	
>DL transport channel information list	OP	1 to <MaxTrCH >		
>>DL transport channel information	MP		Added or reconfigured DL TrCH information	

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
			10.3.5.1	
>Measurement report	OP		MEASUREMENT REPORT 10.2.17	
<b>Other Information elements</b>				
Failure cause	OP		Failure cause 10.3.3.13	Diagnostics information related to an earlier SRNC Relocation request (see NOTE 2 in 14.12.0a)
Protocol error information	CV-ProtErr		Protocol error information 10.3.8.12	

Multi Bound	Explanation
MaxNumberOfMeas	Maximum number of active measurements, upper limit 16

Condition	Explanation
Setup	The IE is mandatory present when the IE Measurement command has the value "Setup", otherwise the IE is not needed.
Ciphering	The IE is mandatory present when the IE Ciphering Status has the value "started" and the ciphering counters need not be reinitialised, otherwise the IE is not needed.
IP	The IE is mandatory present when the IE Integrity protection status has the value "started" and the integrity protection counters need not be reinitialised, otherwise the IE is not needed.
ProtErr	This IE is mandatory present if the IE "Protocol error indicator" is included and has the value "TRUE". Otherwise it is not needed.
SRB1	The IE is mandatory present for RB1. Otherwise it is not needed.

## CHANGE REQUEST

⌘ 25.331 CR 1760 ⌘ rev 2 ⌘ Current version: 5.2.0 ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

**Proposed change affects:** UICC apps ⌘ ME  Radio Access Network  Core Network ⌘

<b>Title:</b>	⌘ Early UE Specific Behaviour Information in RRC Connection Request / inter RAT info
<b>Source:</b>	⌘ Alcatel, Fujitsu, Motorola, NEC, Orange, Siemens
<b>Work item code:</b>	⌘ TEI
	<b>Date:</b> ⌘ 05/11/2002
<b>Category:</b>	<b>⌘ B</b> Use <u>one of the following categories:</u> <b>F</b> (correction) <b>A</b> (corresponds to a correction in an earlier release) <b>B</b> (addition of feature), <b>C</b> (functional modification of feature) <b>D</b> (editorial modification) Detailed explanations of the above categories can be found in 3GPP <a href="#">TR 21.900</a> .
	<b>Release:</b> ⌘ Rel-5 Use <u>one of the following releases:</u> 2 (GSM Phase 2) R96 (Release 1996) R97 (Release 1997) R98 (Release 1998) R99 (Release 1999) Rel-4 (Release 4) Rel-5 (Release 5) Rel-6 (Release 6)

**Reason for change:** ⌘ It is currently not possible to identify and handle faulty UE implementations

<b>Summary of change:</b>	Two transparent containers “UE Specific Behaviour Information 1 idle” (current assumption 4bits, tbc) and “UE Specific Behaviour Information 1 interRAT” (8bits) are added to the early messages at call setup and to the appropriate messages for SRNS relocation and inter rat handover, i.e. to the following messages:  RRC Connection Request, Inter RAT Handover Info, Inter RAT Handover Info with Inter RAT Capabilities, SRNS Relocation Info,  If UTRAN implements the CR but UE doesn't: - No impact. The RNC might not be able to adapt to specific UE behavior.  If UE implements the CR but UTRAN doesn't: - No impact. UTRAN will ignore the unknown extension and treat all UEs in the same way  If neither UE nor UTRAN implement the CR: - No impact.
---------------------------	---

**Consequences if not approved:** ⌘ Errors discovered in UEs can not be handled appropriately

<b>Clauses affected:</b>	⌘ 8.1.3.3, 8.1.16.3, 10.2.16b, 10.2.39, 10.3.3.51 (new), 10.3.3.52 (new), 11.2, 11.3, 11.5, 14.12.4.1, 14.12.4.2				
<b>Other specs</b>	<table border="1" style="display: inline-table; vertical-align: middle;"> <tr> <td style="text-align: center;">Y</td> <td style="text-align: center;">N</td> </tr> <tr> <td style="text-align: center;">X</td> <td></td> </tr> </table> Other core specifications ⌘	Y	N	X	
Y	N				
X					

<b>affected:</b>	<table border="1" style="display: inline-table; vertical-align: middle;"> <tr><td></td><td>X</td></tr> <tr><td></td><td>X</td></tr> </table>		X		X	Test specifications O&M Specifications	
	X						
	X						
<b>Other comments:</b> 86							

### How to create CRs using this form:

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>.

Below is a brief summary:

- 1) Fill out the above form. The symbols above marked contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/>. For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

### 8.1.3.3 RRC CONNECTION REQUEST message contents to set

The UE shall, in the transmitted RRC CONNECTION REQUEST message:

- 1> set the IE "Establishment cause" to the value of the variable ESTABLISHMENT\_CAUSE;
- 1> set the IE "Initial UE identity" to the value of the variable INITIAL\_UE\_IDENTITY;
- 1> set the IE "Protocol error indicator" to the value of the variable PROTOCOL\_ERROR\_INDICATOR;
- 1> include a measurement report in the IE "Measured results on RACH", as specified in the IE "Intra-frequency reporting quantity for RACH reporting" and the IE "Maximum number of reported cells on RACH" in System Information Block type 11; and
- 1> include in the IE "Measured results on RACH" all requested reporting quantities for cells for which measurements are reported; and
- 1> take care that the maximum allowed message size is not exceeded when forming the IE "Measured results on RACH".

The UE shall not include the IE "UE Specific Behaviour Information 1 idle".

### 10.2.16d INTER RAT HANDOVER INFO

This message is sent by the UE via another radio access technology to provide information to the target RNC when preparing for a handover to UTRAN.

RLC-SAP: N/A (Sent through a different RAT)

Logical channel: N/A (Sent through a different RAT)

Direction: UE → UTRAN

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
<b>Radio Bearer IEs</b>				
Predefined configuration status information	OP		Predefined configuration status information 10.3.4.5a	
<b>UE Information elements</b>				
UE security information	OP		UE security information 10.3.3.42b	
<a href="#"><u>&gt;UE Specific Behaviour Information 1 interRAT</u></a>	<a href="#"><u>OP</u></a>		<a href="#"><u>UE Specific Behaviour Information 1 interRAT 10.3.3.52</u></a>	<a href="#"><u>This IE shall not be included in this version of the protocol</u></a>
UE capability container	OP			
>UE radio access capability	MP		UE radio access capability 10.3.3.42	
>UE radio access capability extension	MP		UE radio access capability extension 10.3.3.42a	Although this IE is not always required, the need has been set to MP to align with the ASN.1

## 10.2.39 RRC CONNECTION REQUEST

RRC Connection Request is the first message transmitted by the UE when setting up an RRC Connection to the network.

RLC-SAP: TM

Logical channel: CCCH

Direction: UE → UTRAN

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
Message Type	MP		Message Type		
<b>UE information elements</b>					
Initial UE identity	MP		Initial UE identity 10.3.3.15		
Establishment cause	MP		Establishment cause 10.3.3.11		
Protocol error indicator	MD		Protocol error indicator 10.3.3.27	Default value is FALSE	
<a href="#">UE Specific Behaviour Information 1 idle</a>	OP		<a href="#">UE Specific Behaviour Information 1 idle</a> 10.3.3.51	<a href="#">This IE shall not be included in this version of the protocol</a>	
<b>Measurement information elements</b>					
Measured results on RACH	OP		Measured results on RACH 10.3.7.45		
Access stratum release indicator	MP		Enumerated( REL-4)	Absence of the IE implies R99. The IE also indicates the release of the RRC transfer syntax supported by the UE 15 spare values are needed	REL-4

If the encoded message does not fill a transport block, the RRC layer shall insert padding according to subclause 12.1.

### 10.3.3.51 UE Specific Behaviour Information 1 idle

[This IE indicates the UE conformance typically for RRC connection establishment from idle mode.](#)

Information Element/Group name	Need	Multi	Type and Reference	Semantics description
<a href="#">UE Specific Behaviour Information 1 idle</a>	MP		<a href="#">bit string(4)</a>	

### 10.3.3.52 UE Specific Behaviour Information 1 interRAT

[This IE indicates the UE conformance typically for RRC connection establishment from another RAT.](#)

Information Element/Group name	Need	Multi	Type and Reference	Semantics description
<a href="#">UE Specific Behaviour</a>	MP		<a href="#">bit string(8)</a>	

<u>Information Element/Group name</u>	<u>Need</u>	<u>Multi</u>	<u>Type and Reference</u>	<u>Semantics description</u>
Information 1 interRAT				

## 11.2 PDU definitions

```
--*****
-- TABULAR: The message type and integrity check info are not
-- visible in this module as they are defined in the class module.
-- Also, all FDD/TDD specific choices have the FDD option first
-- and TDD second, just for consistency.
--*****
PDU-definitions DEFINITIONS AUTOMATIC TAGS ::=
BEGIN
--*****
-- IE parameter types from other modules
--*****
IMPORTS
-- Core Network IEs :
CN-DomainIdentity,
CN-InformationInfo,
CN-InformationInfoFull,
NAS-Message,
PagingRecordTypeID,
-- UTRAN Mobility IEs :
CellIdentity,
CellIdentity-PerRL-List,
URA-Identity,
-- User Equipment IEs :
ActivationTime,
C-RNTI,
CapabilityUpdateRequirement,
CapabilityUpdateRequirement-r4,
CapabilityUpdateRequirement-r4-ext,
CellUpdateCause,
CipheringAlgorithm,
CipheringModeInfo,
DSCH-RNTI,
EstablishmentCause,
FailureCauseWithProtErr,
FailureCauseWithProtErrTrId,
H-RNTI,
UESpecificBehaviourInformationIdle,
UESpecificBehaviourInformationinterRAT,
InitialUE-Identity,
IntegrityProtActivationInfo,
IntegrityProtectionModeInfo,
N-308,
PagingCause,
PagingRecordList,
ProtocolErrorIndicator,
ProtocolErrorIndicatorWithMoreInfo,
Rb-timer-indicator,
RedirectionInfo,
RejectionCause,
ReleaseCause,
RRC-StateIndicator,
RRC-TransactionIdentifier,
SecurityCapability,
START-Value,
STARTList,
U-RNTI,
U-RNTI-Short,
UE-RadioAccessCapability,
```

```

UE-RadioAccessCapability-r4-ext,
UE-RadioAccessCapability-r5-ext,
UE-RadioAccessCapability-v370ext,
UE-RadioAccessCapability-v380ext,
UE-RadioAccessCapability-v3a0ext,
UE-RadioAccessCapability-v4xyext,
DL-PhysChCapabilityFDD-v380ext,
UE-ConnTimersAndConstants,
UE-ConnTimersAndConstants-v3a0ext,
UE-ConnTimersAndConstants-r5,
UE-SecurityInformation,
URA-UpdateCause,
UTRAN-DRX-CycleLengthCoefficient,
WaitTime,
-- Radio Bearer IEs :
DefaultConfigIdentity,
DefaultConfigIdentity-r4,
DefaultConfigMode,
DL-CounterSynchronisationInfo,
DL-CounterSynchronisationInfo-r5,
PredefinedConfigIdentity,
PredefinedConfigStatusList,
RAB-Info,
RAB-Info-Post,
RAB-InformationList,
RAB-InformationReconfigList,
RAB-InformationSetupList,
RAB-InformationSetupList-r4,
RB-ActivationTimeInfoList,
RB-COUNT-C-InformationList,
RB-COUNT-C-MSB-InformationList,
RB-IdentityList,
RB-InformationAffectedList,
RB-InformationAffectedList-r5,
RB-InformationReconfigList,
RB-InformationReconfigList-r4,
RB-InformationReconfigList-r5,
RB-InformationReleaseList,
RB-PDCPContextRelocationList,
SRB-InformationSetupList,
SRB-InformationSetupList2,
UL-CounterSynchronisationInfo,
-- Transport Channel IEs:
CPCH-SetID,
DL-AddReconfTransChInfo2List,
DL-AddReconfTransChInfoList,
DL-AddReconfTransChInfoList-r4,
DL-AddReconfTransChInfoList-r5,
DL-CommonTransChInfo,
DL-CommonTransChInfo-r4,
DL-DeletedTransChInfoList,
DL-DeletedTransChInfoList-r5,
DRAC-StaticInformationList,
TFC-Subset,
TFCS-Identity,
UL-AddReconfTransChInfoList,
UL-CommonTransChInfo,
UL-CommonTransChInfo-r4,
UL-DeletedTransChInfoList,
-- Physical Channel IEs :
Alpha,
CCTrCH-PowerControlInfo,
CCTrCH-PowerControlInfo-r4,
ConstantValue,
ConstantValueTdd,
CPCH-SetInfo,
DL-CommonInformation,
DL-CommonInformation-r4,
DL-CommonInformationPost,
DL-HSPDSCH-Information,
DL-InformationPerRL,
DL-InformationPerRL-List,
DL-InformationPerRL-List-r4,
DL-InformationPerRL-List-r5,
DL-InformationPerRL-ListPostFDD,
DL-InformationPerRL-PostTDD,
DL-InformationPerRL-PostTDD-LCR-r4,
DL-PDSCH-Information,
DPCH-CompressedModeStatusInfo,

```

```

FrequencyInfo,
FrequencyInfoFDD,
FrequencyInfoTDD,
MaxAllowedUL-TX-Power,
OpenLoopPowerControl-IPDL-TDD-r4,
PDSCH-CapacityAllocationInfo,
PDSCH-CapacityAllocationInfo-r4,
PDSCH-Identity,
PrimaryCCPCH-TX-Power,
PUSCH-CapacityAllocationInfo,
PUSCH-CapacityAllocationInfo-r4,
PUSCH-Identity,
RL-AdditionInformationList,
RL-RemovalInformationList,
SpecialBurstsScheduling,
SSDT-Information,
TFC-ControlDuration,
SSDT-UL-r4,
TimeslotList,
TimeslotList-r4,
TX-DiversityMode,
UL-ChannelRequirement,
UL-ChannelRequirement-r4,
UL-ChannelRequirement-r5,
UL-ChannelRequirementWithCPCH-SetID,
UL-ChannelRequirementWithCPCH-SetID-r4,
UL-ChannelRequirementWithCPCH-SetID-r5,
UL-DPCH-Info,
UL-DPCH-Info-r4,
UL-DPCH-InfoPostFDD,
UL-DPCH-InfoPostTDD,
UL-DPCH-InfoPostTDD-LCR-r4,
UL-SynchronisationParameters-r4,
UL-TimingAdvance,
UL-TimingAdvanceControl,
UL-TimingAdvanceControl-r4,
-- Measurement IEs :
AdditionalMeasurementID-List,
Frequency-Band,
EventResults,
InterFreqEventResults-LCR-r4-ext,
InterRAT-TargetCellDescription,
MeasuredResults,
MeasuredResults-v390ext,
MeasuredResultsList,
MeasuredResultsList-LCR-r4-ext,
MeasuredResultsOnRACH,
MeasurementCommand,
MeasurementCommand-r4,
MeasurementIdentity,
MeasurementReportingMode,
PrimaryCCPCH-RSCP,
SFN-Offset-Validity,
TimeslotListWithISCP,
TrafficVolumeMeasuredResultsList,
UE-Positioning-GPS-AssistanceData,
UE-Positioning-Measurement-v390ext,
UE-Positioning-OTDOA-AssistanceData,
UE-Positioning-OTDOA-AssistanceData-r4ext,
UE-Positioning-OTDOA-AssistanceData-UEB,
UE-Positioning-IPDL-Parameters-TDD-r4-ext,
-- Other IEs :
BCCH-ModificationInfo,
CDMA2000-MessageList,
GSM-MessageList,
InterRAT-ChangeFailureCause,
InterRAT-HO-FailureCause,
InterRAT-UE-RadioAccessCapabilityList,
InterRAT-UE-SecurityCapList,
IntraDomainNasNodeSelector,
ProtocolErrorMoreInformation,
Rplmn-Information,
Rplmn-Information-r4,
SegCount,
SegmentIndex,
SFN-Prime,
SIB-Data-fixed,
SIB-Data-variable,
SIB-Type
FROM InformationElements

```

```

maxSIBperMsg
FROM Constant-definitions;

-- ****
-- 
-- HANOVER TO UTRAN COMPLETE
-- 
-- ****

HandoverToUTRANComplete ::= SEQUENCE {
    --TABULAR: Integrity protection shall not be performed on this message.
    -- User equipment IEs
    -- TABULAR: startList is conditional on history.
    startList                      STARTList                                OPTIONAL,
    -- Radio bearer IEs
    count-C-ActivationTime          ActivationTime                         OPTIONAL,
    -- Extension mechanism for non- release99 information
    nonCriticalExtensions          SEQUENCE {}                           OPTIONAL
}

-- ****
-- 
-- INITIAL DIRECT TRANSFER
-- 
-- ****

InitialDirectTransfer ::= SEQUENCE {
    -- Core network IEs
    cn-DomainIdentity              CN-DomainIdentity,
    intraDomainNasNodeSelector     IntraDomainNasNodeSelector,
    nas-Message                     NAS-Message,
    -- Measurement IEs
    measuredResultsOnRACH          MeasuredResultsOnRACH                         OPTIONAL,
    v3a0NonCriticalExtensions      SEQUENCE {
        initialDirectTransfer-v3a0ext   InitialDirectTransfer-v3a0ext,
        -- Extension mechanism for non- release99 information
        nonCriticalExtensions         SEQUENCE {}                           OPTIONAL
    }                                OPTIONAL
}

InitialDirectTransfer-v3a0ext ::= SEQUENCE {
    -- start-value shall always be included in this version of the protocol
    start-Value                    START-Value                            OPTIONAL
}

-- ****
-- 
-- HANOVER FROM UTRAN COMMAND
-- 
-- ****

HandoverFromUTRANCommand-GSM ::= CHOICE {
    r3                           SEQUENCE {
        handoverFromUTRANCommand-GSM-r3
            HandoverFromUTRANCommand-GSM-r3-IEs,
            -- UTRAN should not include the IE nonCriticalExtensions when it sets
            -- the IE gsm-message included in handoverFromUTRANCommand-GSM-r3 to single-GSM-Message
            -- The UE behaviour upon receiving a message including this combination of IE values is
            -- not specified
            nonCriticalExtensions        SEQUENCE {} OPTIONAL
    },
    later-than-r3                 SEQUENCE {
        rrc-TransactionIdentifier   RRC-TransactionIdentifier,
        criticalExtensions          SEQUENCE {}
    }
}

HandoverFromUTRANCommand-GSM-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier     RRC-TransactionIdentifier,
    activationTime                ActivationTime                         OPTIONAL,
    -- Radio bearer IEs
    toHandover-Info               RAB-Info                               OPTIONAL,
    -- Measurement IEs
    frequency-band                Frequency-Band,
    -- Other IEs
    gsm-message                   CHOICE {

```

```

-- In the single-GSM-Message case the following rules apply:
-- 1> the GSM message directly follows the basic production; the final padding that
--    results when PER encoding the abstract syntax value is removed prior to appending
--    the GSM message.
-- 2> the RRC message excluding the GSM part, does not contain a length determinant;
--    there is no explicit parameter indicating the size of the included GSM message.
-- 3> depending on need, final padding (all "0"s) is added to ensure the final result
--    comprises a full number of octets
single-GSM-Message           SEQUENCE {},
gsm-MessageList              SEQUENCE {
    gsm-Messages          GSM-MessageList
}
}

}

HandoverFromUTRANCommand-CDMA2000 ::= CHOICE {
    r3                   SEQUENCE {
        handoverFromUTRANCommand-CDMA2000-r3
            HandoverFromUTRANCommand-CDMA2000-r3-IEs,
            nonCriticalExtensions      SEQUENCE {} OPTIONAL
    },
    later-than-r3         SEQUENCE {
        rrc-TransactionIdentifier   RRC-TransactionIdentifier,
        criticalExtensions         SEQUENCE {}
    }
}

HandoverFromUTRANCommand-CDMA2000-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier   RRC-TransactionIdentifier,
    activationTime               ActivationTime             OPTIONAL,
    -- Radio bearer IEs
    toHandover-Info              RAB-Info                 OPTIONAL,
    -- Other IEs
    cdma2000-MessageList         CDMA2000-MessageList
}

-- ****
-- HANOVER FROM UTRAN FAILURE
--
-- ****

HandoverFromUTRANFailure ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier   RRC-TransactionIdentifier,
    -- Other IEs
    interRAT-HO-FailureCause    InterRAT-HO-FailureCause      OPTIONAL,
    interRATMessage              CHOICE {
        gsm                  SEQUENCE {
            gsm-MessageList      GSM-MessageList
        },
        cdma2000              SEQUENCE {
            cdma2000-MessageList CDMA2000-MessageList
        }
    }                           OPTIONAL,
    -- Extension mechanism for non- release99 information
    nonCriticalExtensions        SEQUENCE {}             OPTIONAL
}

-- ****
-- INTER RAT HANDOVER INFO
--
-- ****

InterRATHandoverInfo ::= SEQUENCE {
    -- This structure is defined for historical reasons, backward compatibility with 04.18
    predefinedConfigStatusList   CHOICE {
        absent                NULL,
        present               PredefinedConfigStatusList
    },
    uE-SecurityInformation       CHOICE {
        absent                NULL,
        present               UE-SecurityInformation
    },
    ue-CapabilityContainer       CHOICE {
        absent                NULL,
        -- present is an octet aligned string containing IE UE-RadioAccessCapabilityInfo
    }
}

```

```

        present          OCTET STRING (SIZE (0..63))
    },
-- Non critical extensions
v390NonCriticalExtensions CHOICE {
    absent           NULL,
    present          SEQUENCE {
        interRATHandoverInfo-v390ext   InterRATHandoverInfo-v390ext-IEs,
        v3a0NonCriticalExtensions     SEQUENCE {
            interRATHandoverInfo-v3a0ext   InterRATHandoverInfo-v3a0ext,
            v3d0NonCriticalExtensions   SEQUENCE {
                interRATHandoverInfo-v3d0ext   InterRATHandoverInfo-v3d0ext-IEs,
                v4xyNonCriticalExtensions   SEQUENCE {
                    interRATHandoverInfo-v4xyext   InterRATHandoverInfo-v4xyext-IEs,
                    -- Reserved for future non critical extension
                }
            }
        }
    }
}

nonCriticalExtensions      SEQUENCE {} OPTIONAL
OPTIONAL
} Optional
} OPTIONAL
}

InterRATHandoverInfo-v390ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v380ext     UE-RadioAccessCapability-v380ext      OPTIONAL,
    dl-PhysChCapabilityFDD-v380ext       DL-PhysChCapabilityFDD-v380ext
}

InterRATHandoverInfo-v3a0ext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v3a0ext     UE-RadioAccessCapability-v3a0ext      OPTIONAL
}

InterRATHandoverInfo-v3d0ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    uESpecificBehaviourInformationInterRAT     UESpecificBehaviourInformationInterRAT
    OPTIONAL
}

InterRATHandoverInfo-v4xyext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v4xyext     UE-RadioAccessCapability-v4xyext
}

-- ****
-- 
-- MEASUREMENT CONTROL
-- 
-- ****

MeasurementControl ::= CHOICE {
    r3                  SEQUENCE {
        measurementControl-r3      MeasurementControl-r3-IEs,
        v390nonCriticalExtensions SEQUENCE {
            measurementControl-v390ext   MeasurementControl-v390ext,
            v3a0NonCriticalExtensions   SEQUENCE {
                measurementControl-v3a0ext   MeasurementControl-v3a0ext,
                v4xyNonCriticalExtensions   SEQUENCE {
                    measurementControl-v4xyext   MeasurementControl-v4xyext-IEs,
                    nonCriticalExtensions      SEQUENCE {} OPTIONAL
                }
            }
        }
    }
    OPTIONAL
    OPTIONAL
},
later-than-r3             SEQUENCE {
    rrc-TransactionIdentifier   RRC-TransactionIdentifier,
    criticalExtensions          CHOICE {
        r4                  SEQUENCE {
            measurementControl-r4      MeasurementControl-r4-IEs,
            nonCriticalExtensions     SEQUENCE {} OPTIONAL
        }
        criticalExtensions         SEQUENCE {}
    }
}
}

MeasurementControl-r3-IEs ::= SEQUENCE {

```

```

-- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
-- Measurement IEs
    measurementIdentity      MeasurementIdentity,
    -- TABULAR: The measurement type is included in MeasurementCommand.
    measurementCommand      MeasurementCommand,
    measurementReportingMode     MeasurementReportingMode      OPTIONAL,
    additionalMeasurementList   AdditionalMeasurementID-List      OPTIONAL,
-- Physical channel IEs
    dpch-CompressedModeStatusInfo DPCH-CompressedModeStatusInfo      OPTIONAL
}

MeasurementControl-v4xyext-IEs ::= SEQUENCE {
    ue-Positioning-OTDOA-AssistanceData-r4ext    UE-Positioning-OTDOA-AssistanceData-r4ext      OPTIONAL
}

MeasurementControl-v390ext ::= SEQUENCE {
    ue-Positioning-Measurement-v390ext        UE-Positioning-Measurement-v390ext      OPTIONAL
}

MeasurementControl-v3a0ext ::= SEQUENCE {
    sfn-Offset-Validity          SFN-Offset-Validity      OPTIONAL
}

MeasurementControl-r4-IEs ::= SEQUENCE {
    -- Measurement IEs
    measurementIdentity      MeasurementIdentity,
    -- TABULAR: The measurement type is included in measurementCommand.
    measurementCommand      MeasurementCommand-r4,
    measurementReportingMode     MeasurementReportingMode      OPTIONAL,
    additionalMeasurementList   AdditionalMeasurementID-List      OPTIONAL,
    -- Physical channel IEs
    dpch-CompressedModeStatusInfo DPCH-CompressedModeStatusInfo      OPTIONAL
}

-- *****
-- 
-- MEASUREMENT CONTROL FAILURE
-- 
-- *****

MeasurementControlFailure ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    failureCause                  FailureCauseWithProtErr,
    -- Extension mechanism for non- release99 information
    nonCriticalExtensions       SEQUENCE {}      OPTIONAL
}

-- *****
-- 
-- RRC CONNECTION REQUEST
-- 
-- *****

RRCConnectionRequest ::= SEQUENCE {
    -- TABULAR: Integrity protection shall not be performed on this message.
    -- User equipment IEs
    initialUE-Identity      InitialUE-Identity,
    establishmentCause        EstablishmentCause,
    -- protocolErrorIndicator is MD, but for compactness reasons no default value
    -- has been assigned to it.
    protocolErrorIndicator    ProtocolErrorIndicator,
    -- Measurement IEs
    measuredResultsOnRACH     MeasuredResultsOnRACH      OPTIONAL,
    -- Non critical Extensions
    v3d0NonCriticalExtensions SEQUENCE {
        rRCCconnectionRequest-v3d0ext    RRCConnectionRequest-v3d0ext-IEs,
        -- Reserved for future non critical extension
        v4xyNonCriticalExtensions      SEQUENCE {
            rrcConnectionRequest-v4xyext    RRCConnectionRequest-v4xyext-IEs,
            -- Reserved for future non critical extension
            nonCriticalExtensions       SEQUENCE {}      OPTIONAL
        }      OPTIONAL
    }      OPTIONAL
}

RRCConnectionRequest-v3d0ext-IEs ::= SEQUENCE {
    -- User equipment IEs

```

<pre>     ueSpecificBehaviourInformation1Ie          UE-Specific-Behaviour-Information1Ie      OPTIONAL } </pre>		
--	--	--

```

RRCConnectionRequest-v4xyext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v4xyext     UE-RadioAccessCapability-v4xyext
}

-- ****
-- 
-- RRC CONNECTION SETUP COMPLETE
-- 
-- ****

RRCConnectionSetupComplete ::= SEQUENCE {
    -- TABULAR: Integrity protection shall not be performed on this message.
    -- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    startList                      STARTList,
    ue-RadioAccessCapability       UE-RadioAccessCapability           OPTIONAL,
    -- Other IEs
    ue-RATSpecificCapability      InterRAT-UE-RadioAccessCapabilityList   OPTIONAL,
    -- Non critical extensions
    v370NonCriticalExtensions     SEQUENCE {
        rrcConnectionSetupComplete-v370ext  RRCConnectionSetupComplete-v370ext,
        v380NonCriticalExtensions         SEQUENCE {
            rrcConnectionSetupComplete-v380ext  RRCConnectionSetupComplete-v380ext-IEs,
            -- Reserved for future non critical extension
            v3a0NonCriticalExtensions       SEQUENCE {
                rrcConnectionSetupComplete-v3a0ext  RRCConnectionSetupComplete-v3a0ext,
                v4xyNonCriticalExtensions     SEQUENCE {
                    rrcConnectionSetupComplete-v4xyext  RRCConnectionSetupComplete-v4xyext-IEs,
                    nonCriticalExtensions       SEQUENCE {}           OPTIONAL
                }
                OPTIONAL
            }
            OPTIONAL
        }
        OPTIONAL
    }
}

RRCConnectionSetupComplete-v370ext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v370ext     UE-RadioAccessCapability-v370ext      OPTIONAL
}

RRCConnectionSetupComplete-v380ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v380ext     UE-RadioAccessCapability-v380ext           OPTIONAL,
    dl-PhysChCapabilityFDD-v380ext      DL-PhysChCapabilityFDD-v380ext
}

RRCConnectionSetupComplete-v3a0ext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v3a0ext     UE-RadioAccessCapability-v3a0ext      OPTIONAL
}

RRCConnectionSetupComplete-v4xyext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-r4-ext     UE-RadioAccessCapability-r4-ext      OPTIONAL
}

-- ****
-- 
-- RRC FAILURE INFO
-- 
-- ****

RRC-FailureInfo ::= CHOICE {
    r3                                SEQUENCE {
        rRC-FailureInfo-r3-IEs,
        nonCriticalExtensions       SEQUENCE {}           OPTIONAL
    },
    criticalExtensions                  SEQUENCE {}
}

RRC-FailureInfo-r3-IEs ::= SEQUENCE {
    -- Non-RRC IEs
    failureCauseWithProtErr          FailureCauseWithProtErr
}

```

```
-- ****
-- RRC STATUS
-- ****
```

END

## 11.3 Information element definitions

```
InformationElements DEFINITIONS AUTOMATIC TAGS ::=
```

```
-- ****
-- CORE NETWORK INFORMATION ELEMENTS (10.3.1)
-- ****
```

BEGIN

IMPORTS

```
    hiPDSCHidentities,
    hiPUSCHidentities,
    hiRM,
    maxAC,
    maxAdditionalMeas,
    maxASC,
    maxASCmap,
    maxASCpersist,
    maxCCTrCH,
    maxCellMeas,
    maxCellMeas-1,
    maxCNdomains,
    maxCPCHsets,
    maxDPCH-DLchan,
    maxDPDCH-UL,
    maxDRACclasses,
    maxFACHPCH,
    maxFreq,
    maxFreqBandsFDD,
    maxFreqBandsTDD,
    maxFreqBandsGSM,
    maxHProcesses,
    maxHSDSCHTBIndex,
    maxHSDSCHTBIndex-tdd384,
    maxHSSCCHs,
    maxInterSysMessages,
    maxLoCHperRLC,
    maxMAC-d-PDUsizes,
    maxMeasEvent,
    maxMeasIntervals,
    maxMeasParEvent,
    maxNumCDMA2000Freqs,
    maxNumFDDFreqs,
    maxNumGSMFreqRanges,
    maxNumTDDFreqs,
    maxOtherRAT,
    maxOtherRAT-16,
    maxPagel,
    maxPCPCH-APsig,
    maxPCPCH-APsubCh,
    maxPCPCH-CDsig,
    maxPCPCH-CDsubCh,
    maxPCPCH-SF,
    maxPCPCHs,
    maxPDCPAlgoType,
    maxPDSCH,
    maxPDSCH-TFCIgroups,
    maxPRACH,
    maxPRACH-FPACH,
    maxPredefConfig,
    maxPUSCH,
    maxQueueIDs,
    maxRABsetup,
    maxRAT,
```

```

maxRB,
maxRBallRABs,
maxRBMaxOptions,
maxRBperRAB,
maxReportedGSMCells,
maxSRBsetup,
maxRL,
maxRL-1,
maxROHC-PacketSizes-r4,
maxROHC-Profile-r4,
maxSCCPCH,
maxSat,
maxSIB,
maxSIB-FACH,
maxSystemCapability,
maxTF,
maxTF-CPCH,
maxTFC,
maxTFCsub,
maxTFCI-2-Combs,
maxGPS,
maxTrCH,
maxTrCHpreconf,
maxTS,
maxTS-1,
maxTS-LCR,
maxTS-LCR-1,
maxURA
FROM Constant-definitions;

Ansi-41-IDNNS ::= BIT STRING (SIZE (14))

CN-DomainIdentity ::= ENUMERATED {
    cs-domain,
    ps-domain }

CN-DomainInformation ::= SEQUENCE {
    CN-DomainIdentity,
    NAS-SystemInformationGSM-MAP
}

CN-DomainInformationFull ::= SEQUENCE {
    CN-DomainIdentity,
    NAS-SystemInformationGSM-MAP,
    CN-DRX-CycleLengthCoeff
}

CN-DomainInformationList ::= SEQUENCE (SIZE (1..maxCNdomains)) OF
    CN-DomainInformation

CN-DomainInformationListFull ::= SEQUENCE (SIZE (1..maxCNdomains)) OF
    CN-DomainInformationFull

CN-DomainSysInfo ::= SEQUENCE {
    cn-DomainIdentity,
    cn-Type {
        gsm-MAP
        ansi-41
    },
    cn-DRX-CycleLengthCoeff
}

CN-DomainSysInfoList ::= SEQUENCE (SIZE (1..maxCNdomains)) OF
    CN-DomainSysInfo

CN-InformationInfo ::= SEQUENCE {
    plmn-Identity OPTIONAL,
    cn-CommonGSM-MAP-NAS-SysInfo OPTIONAL,
    cn-DomainInformationList OPTIONAL
}

CN-InformationInfoFull ::= SEQUENCE {
    plmn-Identity OPTIONAL,
    cn-CommonGSM-MAP-NAS-SysInfo OPTIONAL,
    cn-DomainInformationListFull OPTIONAL
}

Digit ::= INTEGER (0..9)

```

```

Gsm-map-IDNNS ::= SEQUENCE {
    routingbasis CHOICE {
        localPTMSI SEQUENCE {
            routingparameter
        },
        tMSIofsamePLMN SEQUENCE {
            routingparameter
        },
        tMSIofdifferentPLMN SEQUENCE {
            routingparameter
        },
        iMSIresponsetopaging SEQUENCE {
            routingparameter
        },
        iMSIUEinitiatedEvent SEQUENCE {
            routingparameter
        },
        iMEI SEQUENCE {
            routingparameter
        },
        spare1 SEQUENCE {
            routingparameter
        },
        spare2 SEQUENCE {
            routingparameter
        }
    },
    enteredparameter BOOLEAN
}

IMEI ::= SEQUENCE (SIZE (15)) OF IMEI-Digit

IMEI-Digit ::= INTEGER (0..15)

IMSI-GSM-MAP ::= SEQUENCE (SIZE (6..15)) OF Digit

IntraDomainNasNodeSelector ::= SEQUENCE {
    version CHOICE {
        release99 SEQUENCE {
            cn-Type CHOICE {
                gsm-Map-IDNNS,
                ansi-41-IDNNS
            }
        },
        later SEQUENCE {
            futurecoding
        }
    }
}

LAI ::= SEQUENCE {
    plmn-Identity,
    lac BIT STRING (SIZE (16))
}

MCC ::= SEQUENCE (SIZE (3)) OF Digit

MNC ::= SEQUENCE (SIZE (2..3)) OF Digit

NAS-Message ::= OCTET STRING (SIZE (1..4095))

NAS-Synchronisation-Indicator ::= BIT STRING(SIZE(4))

NAS-SystemInformationGSM-MAP ::= OCTET STRING (SIZE (1..8))

P-TMSI-GSM-MAP ::= BIT STRING (SIZE (32))

PagingRecordTypeID ::= ENUMERATED {
    imsi-GSM-MAP,
    tmsi-GSM-MAP-P-TMSI,
    imsi-DS-41,
    tmsi-DS-41 }

PLMN-Identity ::= SEQUENCE {
    mcc
}

```

```

        mnc                                MNC
    }

PLMN-Type ::= CHOICE {
    gsm-MAP
        plmn-Identity
    },
    ansi-41
        p-REV
        min-P-REV
        sid
        nid
    },
    gsm-MAP-and-ANSI-41
        plmn-Identity
        p-REV
        min-P-REV
        sid
        nid
    },
    spare
}

RAB-Identity ::= CHOICE {
    gsm-MAP-RAB-Identity
    ansi-41-RAB-Identity
}

RAI ::= SEQUENCE {
    lai
    rac
}

RoutingAreaCode ::= BIT STRING (SIZE (8))

RoutingParameter ::= BIT STRING (SIZE (10))

TMSI-GSM-MAP ::= BIT STRING (SIZE (32))

-- *****
-- UTRAN MOBILITY INFORMATION ELEMENTS (10.3.2)
-- *****

AccessClassBarred ::= ENUMERATED {
    barred, notBarred }

AccessClassBarredList ::= SEQUENCE (SIZE (maxAC)) OF AccessClassBarred

AllowedIndicator ::= ENUMERATED {
    allowed, notAllowed }

CellAccessRestriction ::= SEQUENCE {
    cellBarred
        CellBarred,
    cellReservedForOperatorUse
        ReservedIndicator,
    cellReservationExtension
        ReservedIndicator,
    -- NOTE: IE accessClassBarredList should not be included if the IE CellAccessRestriction
    -- is included in the IE SysInfoType4
    accessClassBarredList
        AccessClassBarredList
    OPTIONAL
}

CellBarred ::= CHOICE {
    barred
        SEQUENCE {
            intraFreqCellReselectionInd
                AllowedIndicator,
            t-Barred
        },
    notBarred
        NULL
}

CellIdentity ::= BIT STRING (SIZE (28))

CellIdentity-PerRL-List ::= SEQUENCE (SIZE (1..maxRL)) OF CellIdentity

CellSelectReselectInfoSIB-3-4 ::= SEQUENCE {
    mappingInfo
        MappingInfo
    cellSelectQualityMeasure
        CHOICE {
            cpich-Ec-N0
                SEQUENCE {

```

```

-- Default value for q-HYST-2-S is q-HYST-1-S
q-HYST-2-S                               Q-Hyst-S                                OPTIONAL
-- Default value for q-HYST-2-S is q-HYST-1-S
},
cpich-RSCP                               NULL
},
modeSpecificInfo
fdd
CHOICE {
SEQUENCE {
S-Intrasearch
S-Intersearch
S-SearchHCS
rat-List
q-QualMin
q-RxlevMin
},
tdd
SEQUENCE {
S-Intrasearch
S-Intersearch
S-SearchHCS
rat-List
q-RxlevMin
}
},
q-Hyst-1-S
T-Reselection-S
HCS-ServingCellInformation
maxAllowedUL-TX-Power
OPTIONAL,
},
MapParameter ::= INTEGER (0..99)

Mapping ::= SEQUENCE {
rat
mappingFunctionParameterList
}

Mapping-LCR-r4 ::= SEQUENCE {
mappingFunctionParameterList
}

MappingFunctionParameter ::= SEQUENCE {
functionType
MappingFunctionType,
mapParameter1
MapParameter
OPTIONAL,
mapParameter2
MapParameter,
-- The presence of upperLimit is conditional on the number of repetition
upperLimit
UpperLimit
OPTIONAL
}

MappingFunctionParameterList ::= SEQUENCE (SIZE (1..maxMeasIntervals)) OF
MappingFunctionParameter

MappingFunctionType ::= ENUMERATED {
linear,
functionType2,
functionType3,
functionType4
}

-- In MappingInfo list, mapping for FDD and 3.84Mcps TDD is defined.
-- For 1.28Mcps TDD, Mapping-LCR-r4 is used instead.
MappingInfo ::= SEQUENCE (SIZE (1..maxRAT)) OF
Mapping

-- Actual value Q-Hyst-S = IE value * 2
Q-Hyst-S ::= INTEGER (0..20)

RAT ::= ENUMERATED {
utra-FDD,
utra-TDD,
gsm,
cdma2000
}

RAT-FDD-Info ::= SEQUENCE {
rat-Identifier
RAT-Identifier,
S-SearchRAT
S-SearchQual,
S-HCS-RAT
S-SearchRXLEV
S-SearchQual
OPTIONAL,
S-Limit-SearchRAT
}
}

RAT-FDD-InfoList ::= SEQUENCE (SIZE (1..maxOtherRAT)) OF

```

```

RAT-FDD-Info

RAT-Identifier ::= ENUMERATED {
    gsm, cdma2000 }

RAT-TDD-Info ::= SEQUENCE {
    rat-Identifier,
    S-SearchRAT,
    S-HCS-RAT,
    S-Limit-SearchRAT
} OPTIONAL,

RAT-TDD-InfoList ::= SEQUENCE (SIZE (1..maxOtherRAT)) OF
    RAT-TDD-Info

ReservedIndicator ::= ENUMERATED {
    reserved,
    notReserved }

-- Actual value S-SearchedQual = IE value * 2
S-SearchQual ::= INTEGER (-16..10)

-- Actual value S-SearchRXLEV = (IE value * 2) + 1
S-SearchRXLEV ::= INTEGER (-53..45)

T-Barred ::= ENUMERATED {
    s10, s20, s40, s80,
    s160, s320, s640, s1280 }

T-Reselection-S ::= INTEGER (0..31)

-- For UpperLimit, the used range depends on the RAT used.
UpperLimit ::= INTEGER (1..91)

URA-Identity ::= BIT STRING (SIZE (16))

URA-IdentityList ::= SEQUENCE (SIZE (1..maxURA)) OF
    URA-Identity

-- *****
-- USER EQUIPMENT INFORMATION ELEMENTS (10.3.3)
-- *****

AccessStratumReleaseIndicator ::= ENUMERATED {
    rel-4, spare15, spare14, spare13,
    spare12, spare11, spare10, spare9, spare8,
    spare7, spare6, spare5, spare4, spare3,
    spare2, spare1 }

-- TABULAR : for ActivationTime, value 'now' always appear as default, and is encoded
-- by absence of the field
ActivationTime ::= INTEGER (0..255)

BackoffControlParams ::= SEQUENCE {
    n-AP-RetransMax,
    n-AccessFails,
    nf-BO-NoAICH,
    ns-BO-Busy,
    nf-BO-AllBusy,
    nf-BO-Mismatch,
    t-CPCH
}

C-RNTI ::= BIT STRING (SIZE (16))

CapabilityUpdateRequirement ::= SEQUENCE {
    ue-RadioCapabilityFDDUpdateRequirement-FDD BOOLEAN,
    -- ue-RadioCapabilityTDDUpdateRequirement-TDD is for 3.84Mcps TDD update requirement
    ue-RadioCapabilityTDDUpdateRequirement-TDD BOOLEAN,
    systemSpecificCapUpdateReqList SystemSpecificCapUpdateReqList OPTIONAL
}

CapabilityUpdateRequirement-r4-ext ::= SEQUENCE {
    ue-RadioCapabilityUpdateRequirement-TDD128 BOOLEAN
}

CapabilityUpdateRequirement-r4 ::= SEQUENCE {

```

```

ue-RadioCapabilityFDDUpdateRequirement-FDD    BOOLEAN,
ue-RadioCapabilityTDDUpdateRequirement-TDD384   BOOLEAN,
ue-RadioCapabilityTDDUpdateRequirement-TDD128   BOOLEAN,
systemSpecificCapUpdateReqList      SystemSpecificCapUpdateReqList      OPTIONAL
}

CellUpdateCause ::=           ENUMERATED {
                           cellReselection,
                           periodicalCellUpdate,
                           uplinkDataTransmission,
                           utran-pagingResponse,
                           re-enteredServiceArea,
                           radiolinkFailure,
                           rlc-unrecoverableError,
                           spare1 }

ChipRateCapability ::=        ENUMERATED {
                           mcps3-84, mcps1-28 }

CipheringAlgorithm ::=        ENUMERATED {
                           uea0, uea1 }

CipheringModeCommand ::=      CHOICE {
                           startRestart,
                           dummy
                           NULL }

CipheringModeInfo ::=         SEQUENCE {
-- TABULAR: The ciphering algorithm is included in the CipheringModeCommand.
                           cipheringModeCommand     CipheringModeCommand,
                           activationTimeForDPCH   ActivationTime
                           OPTIONAL,
                           rb-DL-CiphActivationTimeInfo RB-ActivationTimeInfoList
                           OPTIONAL
}

CN-DRX-CycleLengthCoefficient ::=   INTEGER (6..9)

CN-PagedUE-Identity ::=       CHOICE {
                           imsi-GSM-MAP
                           IMSI-GSM-MAP,
                           tmsi-GSM-MAP
                           TMSI-GSM-MAP,
                           p-TMSI-GSM-MAP
                           P-TMSI-GSM-MAP ,
                           imsi-DS-41
                           IMSI-DS-41,
                           tmsi-DS-41
                           TMSI-DS-41,
                           spare3
                           NULL,
                           spare2
                           NULL,
                           spare1
                           NULL
}

CompressedModeMeasCapability ::=  SEQUENCE {
                           fdd-Measurements
                           BOOLEAN,
-- TABULAR: The IEs tdd-Measurements, gsm-Measurements and multiCarrierMeasurements
-- are made optional since they are conditional based on another information element.
-- Their absence corresponds to the case where the condition is not true.
                           tdd-Measurements
                           BOOLEAN
                           OPTIONAL,
                           gsm-Measurements
                           GSM-Measurements
                           OPTIONAL,
                           multiCarrierMeasurements
                           BOOLEAN
                           OPTIONAL
}

CompressedModeMeasCapability-LCR-r4 ::= SEQUENCE {
                           tdd128-Measurements
                           BOOLEAN
                           OPTIONAL
}

CompressedModeMeasCapabFDDList ::= SEQUENCE (SIZE (1..maxFreqBandsFDD)) OF
                           CompressedModeMeasCapabFDD

CompressedModeMeasCapabFDD ::=    SEQUENCE {
                           radioFrequencyBandFDD
                           RadioFrequencyBandFDD
                           OPTIONAL,
                           dl-MeasurementsFDD
                           BOOLEAN,
                           ul-MeasurementsFDD
                           BOOLEAN
}

CompressedModeMeasCapabTDDList ::= SEQUENCE (SIZE (1..maxFreqBandsTDD)) OF
                           CompressedModeMeasCapabTDD

CompressedModeMeasCapabTDD ::=    SEQUENCE {
                           radioFrequencyBandTDD
                           RadioFrequencyBandTDD,
                           BOOLEAN,
                           dl-MeasurementsTDD
                           BOOLEAN,
                           ul-MeasurementsTDD
                           BOOLEAN
}

```

```

CompressedModeMeasCapabGSMList ::= SEQUENCE (SIZE (1..maxFreqBandsGSM)) OF
    CompressedModeMeasCapabGSM

CompressedModeMeasCapabGSM ::= SEQUENCE {
    radioFrequencyBandGSM,
    dl-MeasurementsGSM,
    ul-MeasurementsGSM
}

CompressedModeMeasCapabMC ::= SEQUENCE {
    dl-MeasurementsMC,
    ul-MeasurementsMC
}

CPCH-Parameters ::= SEQUENCE {
    initialPriorityDelayList           InitialPriorityDelayList          OPTIONAL,
    backoffControlParams              BackoffControlParams,
    -- TABULAR: TPC step size nested inside PowerControlAlgorithm
    powerControlAlgorithm             PowerControlAlgorithm,
    dl-DPCCH-BER                      DL-DPCCH-BER
}

DL-CapabilityWithSimultaneousHS-DSCHConfig ::= ENUMERATED{kbps32, kbps64, kbps128, kbps384}

DL-DPCCH-BER ::= INTEGER (0..63)

DL-PhysChCapabilityFDD ::= SEQUENCE {
    maxNoDPCH-PDSCH-Codes           INTEGER (1..8),
    maxNoPhysChBitsReceived         MaxNoPhysChBitsReceived,
    supportForSF-512                 BOOLEAN,
    supportOfPDSCH                  BOOLEAN,
    simultaneousSCCPCH-DPCH-Reception SimultaneousSCCPCH-DPCH-Reception
}

DL-PhysChCapabilityFDD-v380ext ::= SEQUENCE {
    supportOfDedicatedPilotsForChEstimation SupportOfDedicatedPilotsForChEstimation OPTIONAL
}

SupportOfDedicatedPilotsForChEstimation ::= ENUMERATED { true }

DL-PhysChCapabilityTDD ::= SEQUENCE {
    maxTS-PerFrame                  MaxTS-PerFrame,
    maxPhysChPerFrame               MaxPhysChPerFrame,
    minimumSF                        MinimumSF-DL,
    supportOfPDSCH                  BOOLEAN,
    maxPhysChPerTS                  MaxPhysChPerTS
}

DL-PhysChCapabilityTDD-LCR-r4 ::= SEQUENCE {
    maxTS-PerSubFrame               MaxTS-PerSubFrame-r4,
    maxPhysChPerFrame               MaxPhysChPerSubFrame-r4,
    minimumSF                        MinimumSF-DL,
    supportOfPDSCH                  BOOLEAN,
    maxPhysChPerTS                  MaxPhysChPerTS,
    supportOf8PSK                    BOOLEAN
}

DL-TransChCapability ::= SEQUENCE {
    maxNoBitsReceived               MaxNoBits,
    maxConvCodeBitsReceived         MaxNoBits,
    turboDecodingSupport            TurboSupport,
    maxSimultaneousTransChs        MaxSimultaneousTransChsDL,
    maxSimultaneousCCTrCH-Count    MaxSimultaneousCCTrCH-Count,
    maxReceivedTransportBlocks      MaxTransportBlocksDL,
    maxNumberoftFC                  MaxNumberoftFC-DL,
    maxNumberoftTF                  MaxNumberoftTF
}

DRAC-SysInfo ::= SEQUENCE {
    transmissionProbability          TransmissionProbability,
    maximumBitRate                   MaximumBitRate
}

DRAC-SysInfoList ::= SEQUENCE (SIZE (1..maxDRACclasses)) OF
    DRAC-SysInfo

DSCH-RNTI ::= BIT STRING (SIZE (16))

ESN-DS-41 ::= BIT STRING (SIZE (32))

```

```

EstablishmentCause ::= ENUMERATED {
    originatingConversationalCall,
    originatingStreamingCall,
    originatingInteractiveCall,
    originatingBackgroundCall,
    originatingSubscribedTrafficCall,
    terminatingConversationalCall,
    terminatingStreamingCall,
    terminatingInteractiveCall,
    terminatingBackgroundCall,
    emergencyCall,
    interRAT-CellReselection,
    interRAT-CellChangeOrder,
    registration,
    detach,
    originatingHighPrioritySignalling,
    originatingLowPrioritySignalling,
    callRe-establishment,
    terminatingHighPrioritySignalling,
    terminatingLowPrioritySignalling,
    terminatingCauseUnknown,
    spare12,
    spare11,
    spare10,
    spare9,
    spare8,
    spare7,
    spare6,
    spare5,
    spare4,
    spare3,
    spare2,
    spare1 }

FailureCauseWithProtErr ::= CHOICE {
    configurationUnsupported           NULL,
    physicalChannelFailure           NULL,
    incompatibleSimultaneousReconfiguration   NULL,
    compressedModeRuntimeError        TGSI,
    protocolError                    ProtocolErrorInformation,
    cellUpdateOccurred               NULL,
    invalidConfiguration             NULL,
    configurationIncomplete          NULL,
    unsupportedMeasurement           NULL,
    spare7                           NULL,
    spare6                           NULL,
    spare5                           NULL,
    spare4                           NULL,
    spare3                           NULL,
    spare2                           NULL,
    spare1                           NULL
}

FailureCauseWithProtErrTrId ::= SEQUENCE {
    rrc-TransactionIdentifier        RRC-TransactionIdentifier,
    failureCause                    FailureCauseWithProtErr
}

GSM-Measurements ::= SEQUENCE {
    gsm900                          BOOLEAN,
    dcs1800                         BOOLEAN,
    gsm1900                         BOOLEAN
}

H-RNTI ::= BIT STRING (SIZE (16))

HSDSCH-capability-class ::= INTEGER (0..63)

UESpecificBehaviourInformationlidle ::= BIT STRING (SIZE ([4]))  

UESpecificBehaviourInformationlinterRAT ::= BIT STRING (SIZE (8))

IMSI-and-ESN-DS-41 ::= SEQUENCE {
    imsi-DS-41                      IMSI-DS-41,
    esn-DS-41                        ESN-DS-41
}

```

```

IMSI-DS-41 ::= OCTET STRING (SIZE (5..7))

InitialPriorityDelayList ::= SEQUENCE (SIZE (1..maxASC)) OF
                           NS-IP

```

END

## 11.5 RRC information between network nodes

```
Internode-definitions DEFINITIONS AUTOMATIC TAGS ::=
```

BEGIN

IMPORTS

```

HandoverToUTRANCommand,
MeasurementReport,
PhysicalChannelReconfiguration,
RadioBearerReconfiguration,
RadioBearerRelease,
RadioBearerSetup,
RRC-FailureInfo-r3-IEs,
TransportChannelReconfiguration
FROM PDU-definitions

```

```

-- Core Network IEs :
CN-DomainIdentity,
CN-DomainInformationList,
CN-DomainInformationListFull,
CN-DRX-CycleLengthCoefficient,
NAS-SystemInformationGSM-MAP,
-- UTRAN Mobility IEs :
CellIdentity,
URA-Identity,
-- User Equipment IEs :
AccessStratumReleaseIndicator,
C-RNTI,
ChipRateCapability,
DL-PhysChCapabilityFDD-v380ext,
DL-PhysChCapabilityTDD,
DL-PhysChCapabilityTDD-LCR-r4,
GSM-Measurements,
FailureCauseWithProtErr,
MaxHcContextSpace,
MaxNoPhysChBitsReceived,
MaxROHC-ContextSessions-r4,
NetworkAssistedGPS-Supported,
RadioFrequencyBandTDDList,
RLC-Capability,
RRC-MessageSequenceNumber,
SecurityCapability,
SimultaneousSCCPCH-DPCH-Reception,
STARTList,
STARTSingle,
START-Value,
SupportOfDedicatedPilotsForChEstimation,
TransportChannelCapability,
TxRxFrequencySeparation,
U-RNTI,
UE-MultiModeRAT-Capability,
UE-PowerClass-v370,
UE-RadioAccessCapabBandFDDList,
UE-RadioAccessCapability,
UE-RadioAccessCapability-v370ext,
UE-RadioAccessCapability-v380ext,
UE-RadioAccessCapability-v3a0ext,
UE-RadioAccessCapability-v4xyext,
UL-PhysChCapabilityFDD,
UL-PhysChCapabilityTDD,
UL-PhysChCapabilityTDD-LCR-r4,
-- Radio Bearer IEs :
PredefinedConfigStatusList,
PredefinedConfigValueTag,
RAB-InformationSetupList,
RAB-InformationSetupList-r4,
RAB-Identity,

```

```

RB-Identity,
RB-Identity,
SRB-InformationSetupList,
-- Transport Channel IEs :
CPCH-SetID,
DL-CommonTransChInfo,
DL-CommonTransChInfo-r4,
DL-AddReconfTransChInfoList,
DL-AddReconfTransChInfoList-r4,
DRAC-StaticInformationList,
UL-CommonTransChInfo,
UL-CommonTransChInfo-r4,
UL-AddReconfTransChInfoList,
-- Measurement IEs :
MeasurementIdentity,
MeasurementReportingMode,
MeasurementType,
MeasurementType-r4,
AdditionalMeasurementID-List,
PositionEstimate,
UE-Positioning-IPDL-Parameters-TDD-r4-ext,
-- Other IEs :
InterRAT-UE-RadioAccessCapabilityList
FROM InformationElements

maxCNdomains,
maxNoOfMeas,

maxRB,
maxRBallRABs,
maxRFC3095-CID,
maxSRBsetup
FROM Constant-definitions
;

-- Part 1: Class definitions similar to what has been defined in 11.1 for RRC messages
-- Information that is transferred in the same direction and across the same path is grouped

-- ****
-- 
-- RRC information, to target RNC
-- 
-- ****
-- RRC Information to target RNC sent either from source RNC or from another RAT

ToTargetRNC-Container ::= CHOICE {
    interRATHandoverInfo           InterRATHandoverInfoWithInterRATCapabilities-r3,
    srncRelocation                 SRNC-RelocationInfo-r3,
    rfc3095-ContextInfo            RFC3095-ContextInfo-r5,
    extension                       NULL
}

-- ****
-- 
-- RRC information, target RNC to source RNC
-- 
-- ****

Target-RNC-ToSourceRNC-Container ::= CHOICE {
    radioBearerSetup                RadioBearerSetup,
    radioBearerReconfiguration      RadioBearerReconfiguration,
    radioBearerRelease              RadioBearerRelease,
    transportChannelReconfiguration TransportChannelReconfiguration,
    physicalChannelReconfiguration PhysicalChannelReconfiguration,
    rrc-FailureInfo                RRC-FailureInfo-r3-IEs,
    dL-DCCHmessage                 OCTET STRING,
    extension                       NULL
}

-- Part 2: Container definitions, similar to the PDU definitions in 11.2 for RRC messages
-- In alphabetical order

-- ****
-- 
-- Handover to UTRAN information
-- 
-- ****

```

```

InterRATHandoverInfoWithInterRATCapabilities-r3 ::= CHOICE {
    r3
        SEQUENCE {
            -- IE InterRATHandoverInfoWithInterRATCapabilities-r3-IEs also
            -- includes non critical extensions
            interRATHandoverInfo-r3           InterRATHandoverInfoWithInterRATCapabilities-r3-IEs,
            v390NonCriticalExtensions        SEQUENCE {
                interRATHandoverInfoWithInterRATCapabilities-v390ext
            },
            InterRATHandoverInfoWithInterRATCapabilities-v390ext-IEs,
                -- Reserved for future non critical extension
                nonCriticalExtensions      SEQUENCE {} OPTIONAL
            },
            OPTIONAL
        },
        criticalExtensions             SEQUENCE {}
    }

InterRATHandoverInfoWithInterRATCapabilities-r3-IEs ::= SEQUENCE {
    -- The order of the IEs may not reflect the tabular format
    -- but has been chosen to simplify the handling of the information in the BSC
    -- Other IEs
    ue-RATSpecificCapability     InterRAT-UE-RadioAccessCapabilityList   OPTIONAL,
    -- interRATHandoverInfo, Octet string is used to obtain 8 bit length field prior to
    -- actual information. This makes it possible for BSS to transparently handle information
    -- received via GSM air interface even when it includes non critical extensions.
    -- The octet string shall include the InterRATHandoverInfo information
    -- The BSS can re-use the 04.18 length field received from the MS
    interRATHandoverInfo         OCTET STRING (SIZE (0..255))
}

InterRATHandoverInfoWithInterRATCapabilities-v390ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    failureCauseWithProtErr       FailureCauseWithProtErr
        OPTIONAL
}

-- *****
-- 
-- RFC3095 context, source RNC to target RNC
-- 
-- *****

RFC3095-ContextInfo-r5 ::= CHOICE {
    r5
        SEQUENCE {
            rFC3095-ContextInfoList-r5      RFC3095-ContextInfoList-r5,
            -- Reserved for future non critical extension
            nonCriticalExtensions        SEQUENCE {} OPTIONAL
        },
        criticalExtensions             SEQUENCE {}
    }

RFC3095-ContextInfoList-r5 ::= SEQUENCE (SIZE (1..maxRBallRABs)) OF
    RFC3095-ContextInfo

-- *****
-- 
-- SRNC Relocation information
-- 
-- *****

SRNC-RelocationInfo-r3 ::= CHOICE {
    r3
        SEQUENCE {
            SRNC-RelocationInfo-r3          SRNC-RelocationInfo-r3-IEs,
            v380NonCriticalExtensions      SEQUENCE {
                SRNC-RelocationInfo-v380ext  SRNC-RelocationInfo-v380ext-IEs,
                -- Reserved for future non critical extension
            },
            v390NonCriticalExtensions      SEQUENCE {
                SRNC-RelocationInfo-v390ext  SRNC-RelocationInfo-v390ext-IEs,
                v3a0NonCriticalExtensions    SEQUENCE {
                    SRNC-RelocationInfo-v3a0ext  SRNC-RelocationInfo-v3a0ext-IEs,
                    v3b0NonCriticalExtensions  SEQUENCE {
                        SRNC-RelocationInfo-v3b0ext  SRNC-RelocationInfo-v3b0ext-IEs,
                        v3c0NonCriticalExtensions  SEQUENCE {
                            SRNC-RelocationInfo-v3c0ext  SRNC-RelocationInfo-v3c0ext-IEs,
                            v3d0NonCriticalExtensions  SEQUENCE {
                                SRNC-RelocationInfo-v3d0ext  SRNC-RelocationInfo-v3d0ext-IEs,
                                v4xyNonCriticalExtensions SEQUENCE {
                                    SRNC-RelocationInfo-v4xyext  SRNC-RelocationInfo-v4xyext-IEs,
                                    -- Reserved for future non critical extension
                                }
                            }
                        }
                    }
                }
            }
        }
    }
}

```

```

        nonCriticalExtensions
    } OPTIONAL
    } OPTIONAL
    } OPTIONAL
    } OPTIONAL
    } OPTIONAL
},
later-than-r3 CHOICE {
r4
    SRNC-RelocationInfo-r4
    nonCriticalExtensions
    },
    criticalExtensions
}
}

SRNC-RelocationInfo-r3-IEs ::= SEQUENCE {
-- Non-RRC IEs
    stateOfRRC
    stateOfRRC-Procedure
-- Ciphering related information IEs
-- If the extension v380 is included use the extension for the ciphering status per CN domain
    cipheringStatus
    calculationTimeForCiphering
-- The order of occurrence in the IE cipheringInfoPerRB-List is the
-- same as the RBs in the IE "Signalling RB information list" and in the
-- IE "RAB information list". The signalling RBs are supposed to be listed
-- first. Only UM and AM RBs that are ciphered are listed here
    cipheringInfoPerRB-List
    count-C-List
    integrityProtectionStatus
    srb-SpecificIntegrityProtInfo
    implementationSpecificParams
-- User equipment IEs
    u-RNTI
    c-RNTI
    ue-RadioAccessCapability
    ue-Positioning-LastKnownPos
-- Other IEs
    ue-RATSpecificCapability
-- UTRAN mobility IEs
    ura-Identity
-- Core network IEs
    cn-CommonGSM-MAP-NAS-SysInfo
    cn-DomainInformationList
-- Measurement IEs
    ongoingMeasRepList
-- Radio bearer IEs
    predefinedConfigStatusList
    srb-InformationList
    rab-InformationList
-- Transport channel IEs
    ul-CommonTransChInfo
    ul-TransChInfoList
    modeSpecificInfo
        fdd
            cpch-SetID
            transChDRAC-Info
        },
        tdd
    },
    dl-CommonTransChInfo
    dl-TransChInfoList
-- Measurement report
    measurementReport
    nonCriticalExtensions
        -- In case of TDD only up-Ipd1-Parameters-TDD is present, otherwise
        -- this IE is absent
        up-Ipd1-Parameters-TDD
        UE-Positioning-IPD1-Parameters-TDD-r4-ext
-- Extension mechanism for non- release4 information
        nonCriticalExtensions
    }
}

SRNC-RelocationInfo-v380ext-IEs ::= SEQUENCE {
-- Ciphering related information IEs
    cn-DomainIdentity
}

```

```

        cipheringStatusList          CipheringStatusList
    }

SRNC-RelocationInfo-v390ext-IEs ::= SEQUENCE {
    cn-DomainInformationList-v390ext   CN-DomainInformationList-v390ext      OPTIONAL,
    ue-RadioAccessCapability-v370ext   UE-RadioAccessCapability-v370ext      OPTIONAL,
    ue-RadioAccessCapability-v380ext   UE-RadioAccessCapability-v380ext      OPTIONAL,
    dl-PhysChCapabilityFDD-v380ext    DL-PhysChCapabilityFDD-v380ext,       FailureCauseWithProtErr
    failureCauseWithProtErr           FailureCauseWithProtErr            OPTIONAL
}

SRNC-RelocationInfo-v3a0ext-IEs ::= SEQUENCE {
    -- cn-domain identity for IE startValueForCiphering-v3a0ext is specified
    -- in subsequent extension (SRNC-RelocationInfo-v3b0ext-IEs)
    startValueForCIphering-v3a0ext     START-Value,
    cipheringInfoForSRB1-v3a0ext      CipheringInfoForSRB1-v3a0ext,
    ue-RadioAccessCapability-v3a0ext   UE-RadioAccessCapability-v3a0ext      OPTIONAL
}

SRNC-RelocationInfo-v3b0ext-IEs ::= SEQUENCE {
    -- cn-domain identity for IE startValueForCiphering-v3a0ext included in previous extension
    cn-DomainIdentity                 CN-DomainIdentity,
    -- the remaining start values are contained in IE startValueForCiphering-v3b0ext
    startValueForCiphering-v3b0ext     STARTList2                         OPTIONAL
}

SRNC-RelocationInfo-v3c0ext-IEs ::= SEQUENCE {
    -- IE rb-IdentityForHOMessage includes the identity of the RB used by the source SRNC
    -- to send the message contained in the IE "TargetRNC-ToSourceRNC-Container".
    -- Only included if type is "UE involved"
    rb-IdentityForHOMessage          RB-Identity             OPTIONAL
}

SRNC-RelocationInfo-v3d0ext-IEs ::= SEQUENCE {
    -- User equipment IEs
        uESpecificBehaviourInformationlidle    UESpecificBehaviourInformationlidle    OPTIONAL,
        uESpecificBehaviourInformationlinterRAT    UESpecificBehaviourInformationlinterRAT
    OPTIONAL
}

STARTList2 ::= SEQUENCE (SIZE (2..maxCNdomains)) OF
                STARTSingle

SRNC-RelocationInfo-v4xyext-IEs ::= SEQUENCE {
    ue-RadioAccessCapability-v4xyext   UE-RadioAccessCapability-v4xyext
}

CipheringInfoForSRB1-v3a0ext ::= SEQUENCE {
    dl-UM-SN                      BIT STRING (SIZE (7))
}

CipheringStatusList ::= SEQUENCE (SIZE (1..maxCNdomains)) OF
                        CipheringStatusCNdomain

CipheringStatusCNdomain ::= SEQUENCE {
    cn-DomainIdentity               CN-DomainIdentity,
    cipheringStatus                 CipheringStatus
}

SRNC-RelocationInfo-r4-IEs ::= SEQUENCE {
    -- Non-RRC IEs
    -- IE rb-IdentityForHOMessage includes the identity of the RB used by the source SRNC
    -- to send the message contained in the IE "TargetRNC-ToSourceRNC-Container".
    -- Only included if type is "UE involved"
    rb-IdentityForHOMessage          RB-Identity             OPTIONAL,
    stateOfRRC                       StateOfRRC,
    stateOfRRC-Procedure              StateOfRRC-Procedure,
    -- Ciphering related information IEs
    cipheringStatusList              CipheringStatusList-r4,
    latestConfiguredCN-Domain        CN-DomainIdentity,
    calculationTimeForCiphering      CalculationTimeForCiphering      OPTIONAL,
    count-C-List                     COUNT-C-List           OPTIONAL,
    cipheringInfoPerRB-List          CipheringInfoPerRB-List-r4    OPTIONAL,
    -- Integrity protection related information IEs
    integrityProtectionStatus        IntegrityProtectionStatus,
    srb-SpecificIntegrityProtInfo   SRB-SpecificIntegrityProtInfoList,
    implementationSpecificParams     ImplementationSpecificParams    OPTIONAL,
    -- User equipment IEs
    u-RNTI                          U-RNTI
}

```

```

c-RNTI C-RNTI OPTIONAL,
ue-RadioAccessCapability UE-RadioAccessCapability-r4, OPTIONAL,
ue-RadioAccessCapability-ext UE-RadioAccessCapabBandFDDList OPTIONAL,
ue-Positioning-LastKnownPos UE-Positioning-LastKnownPos OPTIONAL,
UESpecificBehaviourInformationidle UESpecificBehaviourInformationidle OPTIONAL,
UESpecificBehaviourInformationinterRAT UESpecificBehaviourInformationinterRAT OPTIONAL,
-- Other IEs
ue-RATSpecificCapability InterRAT-UE-RadioAccessCapabilityList OPTIONAL,
-- UTRAN mobility IEs
ura-Identity URA-Identity OPTIONAL,
-- Core network IEs
cn-CommonGSM-MAP-NAS-SysInfo NAS-SystemInformationGSM-MAP, OPTIONAL,
cn-DomainInformationList CN-DomainInformationListFull OPTIONAL,
-- Measurement IEs
ongoingMeasRepList OngoingMeasRepList-r4 OPTIONAL,
-- Radio bearer IEs
predefinedConfigStatusList PredefinedConfigStatusList, OPTIONAL,
srb-InformationList SRB-InformationSetupList, OPTIONAL,
rab-InformationList RAB-InformationSetupList-r4 OPTIONAL,
-- Transport channel IEs
ul-CommonTransChInfo UL-CommonTransChInfo-r4 OPTIONAL,
ul-TransChInfoList UL-AddReconfTransChInfoList OPTIONAL,
modeSpecificInfo CHOICE {
    fdd SEQUENCE {
        cpch-SetID CPCH-SetID OPTIONAL,
        transChDRAC-Info DRAC-StaticInformationList OPTIONAL
    },
    tdd NULL OPTIONAL,
}
dl-CommonTransChInfo DL-CommonTransChInfo-r4 OPTIONAL,
dl-TransChInfoList DL-AddReconfTransChInfoList-r4 OPTIONAL,
-- Measurement report
measurementReport MeasurementReport OPTIONAL,
failureCause FailureCauseWithProtErr OPTIONAL
}

-- IE definitions

CalculationTimeForCiphering ::= SEQUENCE {
    cell-Id CellIdentity,
    sfn INTEGER (0..4095)
}

CipheringInfoPerRB ::= SEQUENCE {
    dl-HFN BIT STRING (SIZE (20..25)),
    ul-HFN BIT STRING (SIZE (20..25))
}

CipheringInfoPerRB-r4 ::= SEQUENCE {
    rb-Identity,
    dl-HFN BIT STRING (SIZE (20..25)),
    dl-UM-SN BIT STRING (SIZE (7)) OPTIONAL,
    ul-HFN BIT STRING (SIZE (20..25))
}

-- TABULAR: CipheringInfoPerRB-List, multiplicity value numberOfRadioBearers
-- has been replaced with maxRB.
CipheringInfoPerRB-List ::= SEQUENCE (SIZE (1..maxRB)) OF
    CipheringInfoPerRB

CipheringInfoPerRB-List-r4 ::= SEQUENCE (SIZE (1..maxRB)) OF
    CipheringInfoPerRB-r4

CipheringStatus ::= ENUMERATED {
    started, notStarted }

CipheringStatusList-r4 ::= SEQUENCE (SIZE (1..maxCNdomains)) OF
    CipheringStatusCNdomain-r4

CipheringStatusCNdomain-r4 ::= SEQUENCE {
    cn-DomainIdentity,
    cipheringStatus,
    start-Value }

CN-DomainInformation-v390ext ::= SEQUENCE {
    cn-DRX-CycleLengthCoeff

```

```

}

CN-DomainInformationList-v390ext ::= SEQUENCE (SIZE (1..maxCNdomains)) OF
                                    CN-DomainInformation-v390ext

CompressedModeMeasCapability-r4 ::= SEQUENCE {
    fdd-Measurements                  BOOLEAN,
    -- TABULAR: The IEs tdd-Measurements, gsm-Measurements and multiCarrierMeasurements
    -- are made optional since they are conditional based on another information element.
    -- Their absence corresponds to the case where the condition is not true.
    tdd384-Measurements               OPTIONAL,
    tdd128-Measurements               OPTIONAL,
    gsm-Measurements                 OPTIONAL,
    multiCarrierMeasurements         OPTIONAL
}

COUNT-C-List ::= SEQUENCE (SIZE (1..maxCNdomains)) OF
                  COUNT-CSingle

COUNT-CSingle ::= SEQUENCE {
    cn-DomainIdentity,
    count-C                      BIT STRING (SIZE (32))
}

DL-PhysChCapabilityFDD-r4 ::= SEQUENCE {
    maxNoDPCH-PDSCH-Codes          INTEGER (1..8),
    maxNoPhysChBitsReceived        MaxNoPhysChBitsReceived,
    supportForSF-512                BOOLEAN,
    supportOfPDSCH                 BOOLEAN,
    simultaneousSSCPCH-DPCH-Reception SimultaneousSSCPCH-DPCH-Reception,
    supportOfDedicatedPilotsForChEstimation SupportOfDedicatedPilotsForChEstimation OPTIONAL
}

-- The structure of DL-RFC3095-Context is FFS
DL-RFC3095-Context ::= SEQUENCE {
    rfc3095-Context-Identity        INTEGER (0..16383),
    dl-mode                         ENUMERATED {u, o, r}
}

ImplementationSpecificParams ::= BIT STRING (SIZE (1..512))

IntegrityProtectionStatus ::= ENUMERATED {
                            started, notStarted }

MeasurementCapability-r4 ::= SEQUENCE {
    downlinkCompressedMode,
    uplinkCompressedMode
}

MeasurementCommandWithType ::= CHOICE {
    setup                           MeasurementType,
    modify                          NULL,
    release                         NULL
}

MeasurementCommandWithType-r4 ::= CHOICE {
    setup                           MeasurementType-r4,
    modify                          NULL,
    release                         NULL
}

OngoingMeasRep ::= SEQUENCE {
    measurementIdentity             MeasurementIdentity,
    -- TABULAR: The CHOICE Measurement in the tabular description is included
    -- in MeasurementCommandWithType
    measurementCommandWithType      MeasurementCommandWithType,
    measurementReportingMode       MeasurementReportingMode OPTIONAL,
    additionalMeasurementID-List   AdditionalMeasurementID-List OPTIONAL
}

OngoingMeasRep-r4 ::= SEQUENCE {
    measurementIdentity             MeasurementIdentity,
    -- TABULAR: The CHOICE Measurement in the tabular description is included
    -- in MeasurementCommandWithType-r4.
    measurementCommandWithType      MeasurementCommandWithType-r4,
    measurementReportingMode       MeasurementReportingMode OPTIONAL,
    additionalMeasurementID-List   AdditionalMeasurementID-List OPTIONAL
}

```

```

OngoingMeasRepList ::= SEQUENCE (SIZE (1..maxNoOfMeas)) OF
                         OngoingMeasRep

OngoingMeasRepList-r4 ::= SEQUENCE (SIZE (1..maxNoOfMeas)) OF
                           OngoingMeasRep-r4

PDCP-Capability-r4 ::= SEQUENCE {
    losslessSRNS-RelocationSupport BOOLEAN,
    supportForRfc2507 CHOICE {
        notSupported NULL,
        supported      MaxHcContextSpace
    },
    supportForRfc3095 CHOICE {
        notSupported NULL,
        supported      SEQUENCE {
            maxROHC-ContextSessions MaxROHC-ContextSessions-r4 DEFAULT s16,
            reverseCompressionDepth INTEGER (0..65535)      DEFAULT 0
        }
    }
}

PhysicalChannelCapability-r4 ::= SEQUENCE {
    fddPhysChCapability SEQUENCE {
        downlinkPhysChCapability DL-PhysChCapabilityFDD-r4,
        uplinkPhysChCapability UL-PhysChCapabilityFDD
    OPTIONAL,
    tdd384-PhysChCapability SEQUENCE {
        downlinkPhysChCapability DL-PhysChCapabilityTDD,
        uplinkPhysChCapability UL-PhysChCapabilityTDD
    OPTIONAL,
    tdd128-PhysChCapability SEQUENCE {
        downlinkPhysChCapability DL-PhysChCapabilityTDD-LCR-r4,
        uplinkPhysChCapability UL-PhysChCapabilityTDD-LCR-r4
    OPTIONAL
}
}

RF-Capability-r4 ::= SEQUENCE {
    fddRF-Capability SEQUENCE {
        ue-PowerClass UE-PowerClass-v370,
        txRxFrequencySeparation TxRxFrequencySeparation
    OPTIONAL,
    tdd384-RF-Capability SEQUENCE {
        ue-PowerClass UE-PowerClass-v370,
        radioFrequencyBandTDDList RadioFrequencyBandTDDList,
        chipRateCapability ChipRateCapability
    OPTIONAL,
    tdd128-RF-Capability SEQUENCE {
        ue-PowerClass UE-PowerClass-v370,
        radioFrequencyBandTDDList RadioFrequencyBandTDDList,
        chipRateCapability ChipRateCapability
    OPTIONAL
}
}

RFC3095-ContextInfo ::= SEQUENCE {
    rb-Identity RB-Identity,
    rfc3095-Context-List RFC3095-Context-List
}

RFC3095-Context-List ::= SEQUENCE (SIZE (1..maxRFC3095-CID)) OF SEQUENCE {
    dl-RFC3095-Context OPTIONAL,
    ul-RFC3095-Context OPTIONAL
}

SRB-SpecificIntegrityProtInfo ::= SEQUENCE {
    ul-RRC-HFN BIT STRING (SIZE (28)),
    dl-RRC-HFN BIT STRING (SIZE (28)),
    ul-RRC-SequenceNumber RRC-MessageSequenceNumber,
    dl-RRC-SequenceNumber RRC-MessageSequenceNumber
}

SRB-SpecificIntegrityProtInfoList ::= SEQUENCE (SIZE (4..maxSRBsetup)) OF
                                         SRB-SpecificIntegrityProtInfo

StateOfRRC ::= ENUMERATED {
    cell-DCH, cell-FACH,
    cell-PCH, ura-PCH }

StateOfRRC-Procedure ::= ENUMERATED {

```

```

        awaitNoRRC-Message,
        awaitRB-ReleaseComplete,
        awaitRB-SetupComplete,
        awaitRB-ReconfigurationComplete,
        awaitTransportCH-ReconfigurationComplete,
        awaitPhysicalCH-ReconfigurationComplete,
        awaitActiveSetUpdateComplete,
        awaitHandoverComplete,
        sendCellUpdateConfirm,
        sendUraUpdateConfirm,
        -- dummy is not used in this version of specification
        -- It should not be sent
        dummy,
        otherStates
    }

UE-Positioning-Capability-r4 ::= SEQUENCE {
    standaloneLocMethodsSupported      BOOLEAN,
    ue-BasedOTDOA-Supported           BOOLEAN,
    networkAssistedGPS-Supported      NetworkAssistedGPS-Supported,
    supportForUE-GPS-TimingOfCellFrames BOOLEAN,
    supportForIPDL                     BOOLEAN,
    rx-tx-TimeDifferenceType2Capable  BOOLEAN,
    validity-CellPCH-UraPCH           ENUMERATED { true (0) }      OPTIONAL
}

UE-Positioning-LastKnownPos ::= SEQUENCE {
    sfn                           INTEGER (0..4095),
    cell-id                      CellIdentity,
    positionEstimate              PositionEstimate
}

UE-RadioAccessCapability-r4 ::= SEQUENCE {
    accessStratumReleaseIndicator   AccessStratumReleaseIndicator,
    pdcp-Capability                PDCP-Capability-r4,
    rlc-Capability                 RLC-Capability,
    transportChannelCapability     TransportChannelCapability,
    rf-Capability                  RF-Capability-r4,
    physicalChannelCapability      PhysicalChannelCapability-r4,
    ue-MultiModeRAT-Capability    UE-MultiModeRAT-Capability,
    securityCapability             SecurityCapability,
    ue-positioning-Capability     UE-Positioning-Capability-r4,
    measurementCapability          MeasurementCapability-r4      OPTIONAL
}

-- The structure of UL-RFC3095-Context is FFS
UL-RFC3095-Context ::= SEQUENCE {
    rfc3095-Context-Identity       INTEGER (0..16383),
    ul-mode                        ENUMERATED {u, o, r}
}

END

```

#### 14.12.4.1 INTER RAT HANDOVER INFO WITH INTER RAT CAPABILITIES

This RRC message is sent between network nodes when preparing for an inter RAT handover to UTRAN.  
Direction: source RAT→target RNC

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
<b>UE Information elements</b>				
UE security information	OP		UE security information 10.3.3.42b	
UE capability container	OP			
>UE radio access capability	MP		UE radio access capability 10.3.3.42	
>UE radio access capability extension	MP		UE radio access capability extension	Although this IE is not always required, the need has been set to MP to align with the ASN.1

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
			10.3.3.42a	
>UE Specific Behaviour Information 1 interRAT	OP		UE Specific Behaviour Information 1 interRAT 10.3.3.52	This IE shall not be included in this version of the protocol
<b>Non RRC IEs</b>				
<b>Radio Bearer IEs</b>				
Predefined configuration status information	OP		Predefined configuration status information 10.3.4.5a	
<b>Other Information elements</b>				
UE system specific capability	OP	1 to <maxSystemCapability>		
>Inter-RAT UE radio access capability	MP		Inter-RAT UE radio access capability 10.3.8.7	
Failure cause	OP		Failure cause 10.3.3.13	Diagnostics information related to an earlier handover to UTRAN request
Protocol error information	CV-ProtErr		Protocol error information 10.3.8.12	

Condition	Explanation
ProtErr	This IE is mandatory present if the IE "Protocol error indicator" is included and has the value "TRUE". Otherwise it is not needed.

NOTE: The above table does not need to reflect the order of the information elements in the actual encoded message. The order, that is reflected in the ASN.1, should be chosen in a manner that avoids that network nodes need to perform reordering of information elements.

#### 14.12.4.2 SRNS RELOCATION INFO

This RRC message is sent between network nodes when preparing for an SRNS relocation.

With the presence or absence of the IE "RB identity for Hard Handover message" the source RNC indicates to the target SRNC whether the source RNC expects to receive the choice "DL DCCH message" in the IE "RRC information, target RNC to source RNC" in case the SRNS relocation is of type "UE involved". Furthermore the target RNC uses this information for the calculation of the MAC-I.

Direction: source RNC→target RNC

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
<b>Non RRC IEs</b>				
RB identity for Handover message	OP		RB identity 10.3.4.16	Gives the id of the radio bearer on which the source RNC will transmit the RRC message in the case the relocation is of type "UE involved".
>State of RRC	MP		RRC state indicator, 10.3.3.35a	
>State of RRC procedure	MP		Enumerated (await no RRC	

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
			message, await RB Release Complete, await RB Setup Complete, await RB Reconfigurat ion Complete, await Transport CH Reconfigurat ion Complete, await Physical CH Reconfigurat ion Complete, await Active Set Update Complete, await Handover Complete, send Cell Update Confirm, send URA Update Confirm, , others)	
<b>Ciphering related information</b>				
>Ciphering status for each CN domain	MP	<1 to maxCNDomains>		
>>CN domain identity	MP		CN domain identity 10.3.1.1	
>>Ciphering status	MP		Enumerated( Not started, Started)	
>>START	MP		START 10.3.3.38	START value to be used in this CN domain.
>Latest configured CN domain	MP		CN domain identity 10.3.1.1	Value contained in the variable of the same name. In case this variable is empty, the source RNC can set any CN domain identity. In that case, the Ciphering status and the Integrity protection status should be Not started and the target RNC should not initialise the variable Latest configured CN domain.
>Calculation time for ciphering related information	CV-Ciphering			Time when the ciphering information of the message were calculated, relative to a cell of the target RNC
>>Cell Identity	MP		Cell Identity 10.3.2.2	Identity of one of the cells under the target RNC and included in the active set of the current call
>>SFN	MP		Integer(0..40)	

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
			95)	
>COUNT-C list	OP	1 to <maxCNdomains>		COUNT-C values for radio bearers using transparent mode RLC
>>CN domain identity	MP		CN domain identity 10.3.1.1	
>>COUNT-C	MP		Bit string(32)	
>Ciphering info per radio bearer	OP	1 to <maxRBs>		For signalling radio bearers this IE is mandatory.
>>RB identity	MP		RB identity 10.3.4.16	
>>Downlink HFN	MP		Bit string(20..25 )	This IE is either RLC AM HFN (20 bits) or RLC UM HFN (25 bits)
>>Downlink SN	CV-SRB1		Bit String(7)	VT(US) of RLC UM
>>Uplink HFN	MP		Bit string(20..25 )	This IE is either RLC AM HFN (20 bits) or RLC UM HFN (25 bits)
<b>Integrity protection related information</b>				
>Integrity protection status	MP		Enumerated( Not started, Started)	
>Signalling radio bearer specific integrity protection information	CV-IP	4 to <maxSRBs etup>		
>>Uplink RRC HFN	MP		Bit string (28)	For each SRB, this IE corresponds to the last value used.
>>Downlink RRC HFN	MP		Bit string (28)	For each SRB, this IE corresponds to the last value used. In particular, for SRB2, this IE should not take into account the RRC message that will trigger the relocation.
>>Uplink RRC Message sequence number	MP		Integer (0.. 15)	For each SRB, this IE corresponds to the last value used.
>>Downlink RRC Message sequence number	MP		Integer (0.. 15)	For each SRB, this IE corresponds to the last value used. In particular, for SRB2, this IE should not take into account the RRC message that will trigger the relocation.
>Implementation specific parameters	OP		Bit string (1..512)	
<b>RRC IEs</b>				
<b>UE Information elements</b>				
>U-RNTI	MP		U-RNTI 10.3.3.47	
>C-RNTI	OP		C-RNTI 10.3.3.8	
>UE radio access Capability	MP		UE radio access capability 10.3.3.42	
>UE radio access capability extension	OP		UE radio access capability extension 10.3.3.42a	
>Last known UE position	OP			
>>SFN	MP		Integer (0..4095)	Time when position was estimated
>>Cell ID	MP		Cell identity;	Indicates the cell, the SFN is

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
>>CHOICE Position estimate	MP		10.3.2.2	valid for.
>>>Ellipsoid Point			Ellipsoid Point; 10.3.8.4a	
>>>Ellipsoid point with uncertainty circle			Ellipsoid point with uncertainty circle 10.3.8.4d	
>>>Ellipsoid point with uncertainty ellipse			Ellipsoid point with uncertainty ellipse 10.3.8.4e	
>>>Ellipsoid point with altitude			Ellipsoid point with altitude 10.3.8.4b	
>>Ellipsoid point with altitude and uncertainty ellipsoid			Ellipsoid point with altitude and uncertainty ellipsoid 10.3.8.4c	
>UE Specific Behaviour Information 1 idle	OP		<a href="#">UE Specific Behaviour Information 1</a> <a href="#">10.3.3.51</a>	This IE should be included if received via the "INTER RAT HANDOVER INFO" or the "RRC CONNECTION REQUEST" or the IE "SRNS RELOCATION INFO" or the "Inter RAT Handover Info with Inter RAT Capabilities"
>UE Specific Behaviour Information 1 interRAT	OP		<a href="#">UE Specific Behaviour Information 1</a> <a href="#">interRAT</a> <a href="#">10.3.3.52</a>	This IE should be included if received via the "INTER RAT HANDOVER INFO" or the "RRC CONNECTION REQUEST" or the IE "SRNS RELOCATION INFO" or the "Inter RAT Handover Info with Inter RAT Capabilities"
<b>Other Information elements</b>				
>UE system specific capability	OP	1 to <maxSystemCapability>		
>>Inter-RAT UE radio access capability	MP		Inter-RAT UE radio access capability 10.3.8.7	
<b>UTRAN Mobility Information elements</b>				
>URA Identifier	OP		URA identity 10.3.2.6	
<b>CN Information Elements</b>				
>CN common GSM-MAP NAS system information	MP		NAS system information (GSM-MAP) 10.3.1.9	
>CN domain related information	OP	1 to <MaxCNdomains>		CN related information to be provided for each CN domain
>>CN domain identity	MP			
>>CN domain specific GSM-MAP NAS system info	MP		NAS system information	

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
			(GSM-MAP) 10.3.1.9	
>>CN domain specific DRX cycle length coefficient	MP		CN domain specific DRX cycle length coefficient, 10.3.3.6	
<b>Measurement Related Information elements</b>				
>For each ongoing measurement reporting	OP	1 to <MaxNoOf Meas>		
>>Measurement Identity	MP		Measuremen t identity 10.3.7.48	
>>Measurement Command	MP		Measuremen t command 10.3.7.46	
>>Measurement Type	CV-Setup		Measuremen t type 10.3.7.50	
>>Measurement Reporting Mode	OP		Measuremen t reporting mode 10.3.7.49	
>>Additional Measurements list	OP		Additional measuremen ts list 10.3.7.1	
>>CHOICE Measurement	OP			
>>>Intra-frequency				
>>>>Intra-frequency cell info	OP		Intra- frequency cell info list 10.3.7.33	
>>>>Intra-frequency measurement quantity	OP		Intra- frequency measuremen t quantity 10.3.7.38	
>>>>Intra-frequency reporting quantity	OP		Intra- frequency reporting quantity 10.3.7.41	
>>>>Reporting cell status	OP		Reporting cell status 10.3.7.61	
>>>>Measurement validity	OP		Measuremen t validity 10.3.7.51	
>>>>CHOICE report criteria	OP			
>>>>>Intra-frequency measurement reporting criteria			Intra- frequency measuremen t reporting criteria 10.3.7.39	
>>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>>No reporting			NULL	
>>>>Inter-frequency				

<b>Information Element/Group Name</b>	<b>Need</b>	<b>Multi</b>	<b>Type and reference</b>	<b>Semantics description</b>
>>>>Inter-frequency cell info	OP		Inter-frequency cell info list 10.3.7.13	
>>>>Inter-frequency measurement quantity	OP		Inter-frequency measurement quantity 10.3.7.18	
>>>>Inter-frequency reporting quantity	OP		Inter-frequency reporting quantity 10.3.7.21	
>>>>Reporting cell status	OP		Reporting cell status 10.3.7.61	
>>>>Measurement validity	OP		Measurement validity 10.3.7.51	
>>>>CHOICE report criteria	OP			
>>>>>Inter-frequency measurement reporting criteria			Inter-frequency measurement reporting criteria 10.3.7.19	
>>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>>No reporting			NULL	
>>>>>Inter-RAT				
>>>>Inter-RAT cell info	OP		Inter-RAT cell info list 10.3.7.23	
>>>>Inter-RAT measurement quantity	OP		Inter-RAT measurement quantity 10.3.7.29	
>>>>Inter-RAT reporting quantity	OP		Inter-RAT reporting quantity 10.3.7.32	
>>>>Reporting cell status	OP		Reporting cell status 10.3.7.61	
>>>>Measurement validity	OP		Measurement validity 10.3.7.51	
>>>>CHOICE report criteria	OP			
>>>>>Inter-RAT measurement reporting criteria			Inter-RAT measurement reporting criteria 10.3.7.30	
>>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>>No reporting			NULL	
>>>>>Traffic Volume				

<b>Information Element/Group Name</b>	<b>Need</b>	<b>Multi</b>	<b>Type and reference</b>	<b>Semantics description</b>
>>>Traffic volume measurement Object	OP		Traffic volume measurement object 10.3.7.70	
>>>Traffic volume measurement quantity	OP		Traffic volume measurement quantity 10.3.7.71	
>>>Traffic volume reporting quantity	OP		Traffic volume reporting quantity 10.3.7.74	
>>>CHOICE report criteria	OP			
>>>>Traffic volume measurement reporting criteria			Traffic volume measurement reporting criteria 10.3.7.72	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting			NULL	
>>>Quality				
>>>Quality measurement Object	OP		Quality measurement object	
>>>CHOICE report criteria	OP			
>>>>Quality measurement reporting criteria			Quality measurement reporting criteria 10.3.7.58	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting			NULL	
>>>UE internal				
>>>UE internal measurement quantity	OP		UE internal measurement quantity 10.3.7.79	
>>>UE internal reporting quantity	OP		UE internal reporting quantity 10.3.7.82	
>>>CHOICE report criteria	OP			
>>>>UE internal measurement reporting criteria			UE internal measurement reporting criteria 10.3.7.80	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting			NULL	
>>>UE positioning				

<b>Information Element/Group Name</b>	<b>Need</b>	<b>Multi</b>	<b>Type and reference</b>	<b>Semantics description</b>
>>>LCS reporting quantity	OP		LCS reporting quantity 10.3.7.111	
>>>CHOICE report criteria	OP			
>>>>LCS reporting criteria			LCS reporting criteria 10.3.7.110	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting				
<b>Radio Bearer Information Elements</b>				
>Predefined configuration status information	OP		Predefined configuration status information 10.3.4.5a	
>Signalling RB information list	MP	1 to <maxSRBs etup>		For each signalling radio bearer
>>Signalling RB information	MP		Signalling RB information to setup 10.3.4.24	
>RAB information list	OP	1 to <maxRABs etup>		Information for each RAB
>>RAB information	MP		RAB information to setup 10.3.4.10	
<b>Transport Channel Information Elements</b>				
<b>Uplink transport channels</b>				
>UL Transport channel information common for all transport channels	OP		UL Transport channel information common for all transport channels 10.3.5.24	
>UL transport channel information list	OP	1 to <MaxTrCH >		
>>UL transport channel information	MP		Added or reconfigured UL TrCH information 10.3.5.2	
>CHOICE mode	OP			
>>FDD				
>>>CPCH set ID	OP		CPCH set ID 10.3.5.5	
>>>Transport channel information for DRAC list	OP	1 to <MaxTrCH >		
>>>>DRAC static information	MP		DRAC static information 10.3.5.7	
>>TDD				(no data)

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
<b>Downlink transport channels</b>				
>DL Transport channel information common for all transport channels	OP		DL Transport channel information common for all transport channels 10.3.5.6	
>DL transport channel information list	OP	1 to <MaxTrCH>		
>>DL transport channel information	MP		Added or reconfigured DL TrCH information 10.3.5.1	
>Measurement report	OP		MEASUREMENT REPORT 10.2.17	
<b>Other Information elements</b>				
Failure cause	OP		Failure cause 10.3.3.13	Diagnostics information related to an earlier SRNC Relocation request (see NOTE 2 in 14.12.0a)
Protocol error information	CV-ProtErr		Protocol error information 10.3.8.12	

Multi Bound	Explanation
MaxNoOfMeas	Maximum number of active measurements, upper limit 16

Condition	Explanation
Setup	The IE is mandatory present when the IE Measurement command has the value "Setup", otherwise the IE is not needed.
Ciphering	The IE is mandatory present when the IE Ciphering Status has the value "started" and the ciphering counters need not be reinitialised, otherwise the IE is not needed.
IP	The IE is mandatory present when the IE Integrity protection status has the value "started" and the integrity protection counters need not be reinitialised, otherwise the IE is not needed.
ProtErr	This IE is mandatory present if the IE "Protocol error indicator" is included and has the value "TRUE". Otherwise it is not needed.
SRB1	The IE is mandatory present for RB1. Otherwise it is not needed.

## CHANGE REQUEST

⌘ 25.331 CR 1761 ⌘ rev 1 ⌘ Current version: 3.12.0 ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

**Proposed change affects:** UICC apps ⌘ ME  Radio Access Network  Core Network ⌘

<b>Title:</b>	⌘ Early UE Specific Behaviour Information in Handover Complete / Setup Complete	
<b>Source:</b>	⌘ Alcatel, Fujitsu, Motorola, NEC, Orange, Siemens	
<b>Work item code:</b> ⌘ TEI	<b>Date:</b> ⌘ 05/11/2002	
<b>Category:</b> ⌘ <b>B</b>	<i>Use one of the following categories:</i>	<b>Release:</b> ⌘ R99
<i>F (correction)</i> <i>A (corresponds to a correction in an earlier release)</i> <i>B (addition of feature)</i> , <i>C (functional modification of feature)</i> <i>D (editorial modification)</i> Detailed explanations of the above categories can be found in 3GPP <a href="#">TR 21.900</a> .		<i>Use one of the following releases:</i>
		2 (GSM Phase 2) R96 (Release 1996) R97 (Release 1997) R98 (Release 1998) R99 (Release 1999) Rel-4 (Release 4) Rel-5 (Release 5) Rel-6 (Release 6)

<b>Reason for change:</b>	⌘ It is currently not possible to identify and handle faulty UE implementations
<b>Summary of change:</b>	⌘ A transparent container "UE Specific Behaviour Information 2" is added to early messages at call setup and to the appropriate messages for SRNS relocation, i.e. to the following messages:  RRC Connection Setup Complete, Handover to UTRAN Complete, SRNS Relocation Info,  If UTRAN implements the CR but UE doesn't: - No impact. The RNC might not be able to adapt to specific UE behavior.  If UE implements the CR but UTRAN doesn't: - No impact. UTRAN will ignore the unknown extension and treat all UEs in the same way  If neither UE nor UTRAN implement the CR: - No impact.
<b>Consequences if not approved:</b>	⌘ Errors discovered in UEs can not be handled appropriately

<b>Clauses affected:</b>	⌘ 8.1.3.6, 8.3.6.3, 10.2.16b, 10.2.41, 10.3.3.53 (new), 11.2, 11.3, 11.5, 14.12.4.2								
<b>Other specs affected:</b>	<table border="1" style="display: inline-table; vertical-align: middle;"> <tr> <td style="text-align: center;">Y</td> <td style="text-align: center;">N</td> </tr> <tr> <td style="text-align: center;"><input checked="" type="checkbox"/></td> <td style="text-align: center;">Other core specifications</td> </tr> <tr> <td style="text-align: center;"><input checked="" type="checkbox"/></td> <td style="text-align: center;">Test specifications</td> </tr> <tr> <td style="text-align: center;"><input checked="" type="checkbox"/></td> <td style="text-align: center;">O&amp;M Specifications</td> </tr> </table>	Y	N	<input checked="" type="checkbox"/>	Other core specifications	<input checked="" type="checkbox"/>	Test specifications	<input checked="" type="checkbox"/>	O&M Specifications
Y	N								
<input checked="" type="checkbox"/>	Other core specifications								
<input checked="" type="checkbox"/>	Test specifications								
<input checked="" type="checkbox"/>	O&M Specifications								

**Other comments:** ☰

**How to create CRs using this form:**

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>. Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ☰ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

### 8.1.3.6 Reception of an RRC CONNECTION SETUP message by the UE

The UE shall compare the value of the IE "Initial UE identity" in the received RRC CONNECTION SETUP message with the value of the variable INITIAL\_UE\_IDENTITY.

If the values are different, the UE shall:

- 1> ignore the rest of the message.

If the values are identical, the UE shall:

- 1> stop timer T300, and act upon all received information elements as specified in subclause 8.6, unless specified otherwise in the following:

- 2> if the UE will be in the CELL\_FACH state at the conclusion of this procedure:

- 3> if the IE "Frequency info" is included:

- 4> select a suitable UTRA cell according to [4] on that frequency;

- 3> select PRACH according to subclause 8.5.17;

- 3> select Secondary CCPCH according to subclause 8.5.19;

- 3> ignore the IE "UTRAN DRX cycle length coefficient" and stop using DRX.

- 1> if the UE will be in the CELL\_DCH state at the conclusion of this procedure:

- 2> perform the physical layer synchronisation procedure A as specified in [29] (FDD only).

- 1> enter UTRA RRC connected mode, in a state according to subclause 8.6.3.3;

- 1> submit an RRC CONNECTION SETUP COMPLETE message to the lower layers on the uplink DCCH after successful state transition per subclause 8.6.3.3, with the contents set as specified below:

- 2> set the IE "RRC transaction identifier" to:

- 3> the value of "RRC transaction identifier" in the entry for the RRC CONNECTION SETUP message in the table "Accepted transactions" in the variable TRANSACTIONS; and

- 3> clear that entry.

#### 2> set IE "UE Specific Behaviour Information 2" to "No UE Specific Behaviour Information 2";

- 2> if the USIM or SIM is present:

- 3> set the "START" for each CN domain in the IE "START list" in the RRC CONNECTION SETUP COMPLETE message with the corresponding START value that is stored in the USIM [50] if present, or as stored in the UE if the SIM is present; and then

- 3> set the START value stored in the USIM [50] if present, and as stored in the UE if the SIM is present for any CN domain to the value "THRESHOLD" of the variable START\_THRESHOLD.

- 2> if neither the USIM nor SIM is present:

- 3> set the "START" for each CN domain in the IE "START list" in the RRC CONNECTION SETUP COMPLETE message to zero;

- 3> set the value of "THRESHOLD" in the variable "START\_THRESHOLD" to the default value [40].

- 2> retrieve its UTRA UE radio access capability information elements from variable UE\_CAPABILITY\_REQUESTED; and then

- 2> include this in IE "UE radio access capability" and IE "UE radio access capability extension", provided this IE is included in variable UE\_CAPABILITY\_REQUESTED;
- 2> retrieve its inter-RAT-specific UE radio access capability information elements from variable UE\_CAPABILITY\_REQUESTED; and then
- 2> include this in IE "UE system specific capability".

When the RRC CONNECTION SETUP COMPLETE message has been submitted to lower layers for transmission the UE shall:

- 1> if the UE has entered CELL\_FACH state:
  - 2> start timer T305 using its initial value if periodical update has been configured by T305 in the IE "UE Timers and constants in connected mode" set to any other value than "infinity" in the variable TIMERS\_AND\_CONSTANTS.
- 1> store the contents of the variable UE\_CAPABILITY\_REQUESTED in the variable UE\_CAPABILITY\_TRANSFERRED;
- 1> initialise variables upon entering UTRA RRC connected mode as specified in subclause 13.4;
- 1> consider the procedure to be successful;

And the procedure ends.

### 8.3.6.3 Reception of HANDOVER TO UTRAN COMMAND message by the UE

The UE shall be able to receive a HANDOVER TO UTRAN COMMAND message and perform an inter-RAT handover, even if no prior UE measurements have been performed on the target UTRAN cell and/or frequency.

The UE shall act upon all received information elements as specified in subclause 8.6, unless specified otherwise in the following. The UE shall:

- 1> store a U-RNTI value (32 bits), which is derived by the IEs "SRNC identity" (12 bits) and "S-RNTI 2" (10 bits) included in IE "U-RNTI-short". In order to produce a full size U-RNTI value, a full size "S-RNTI" (20 bits) shall be derived by padding the IE "S-RNTI 2" with 10 zero bits in the most significant positions; and
- 1> initialise the variable ESTABLISHED\_SIGNALLING\_CONNECTIONS with the signalling connections that remains after the handover according to the specifications of the source RAT;
- 1> initialise the variable UE\_CAPABILITIES\_TRANSFERRED with the UE capabilities that have been transferred to the network up to the point prior to the handover, if any;
- 1> initialise the variable TIMERS\_AND\_CONSTANTS to the default values and start to use those timer and constants values;
- 1> if IE "Specification mode" is set to "Preconfiguration" and IE "Preconfiguration mode" is set to "Predefined configuration":
  - 2> initiate the radio bearer and transport channel configuration in accordance with the predefined parameters identified by the IE "Predefined configuration identity";
  - 2> initiate the physical channels in accordance with the predefined parameters identified by the IE "Predefined radio configuration identity" and the received physical channel information elements;
  - 2> store information about the established radio access bearers and radio bearers according to the IE "Predefined configuration identity"; and
  - 2> set the IE "RAB Info Post" in the variable ESTABLISHED\_RABS and the IE "Re-establishment timer" in the IE "RAB Info" in the variable ESTABLISHED\_RABS to "useT314".

- 1> if IE "Specification mode" is set to "Preconfiguration" and IE "Preconfiguration mode" is set to "Default configuration":
- 2> initiate the radio bearer and transport channel configuration in accordance with the default parameters identified by the IE "Default configuration mode" and IE "Default configuration identity";
- 2> initiate the physical channels in accordance with the default parameters identified by the IE "Default configuration mode" and IE "Default configuration identity" and the received physical channel information elements;

NOTE IE "Default configuration mode" specifies whether the FDD or TDD version of the default configuration shall be used

- 2> set the IE "RAB Info Post" in the variable ESTABLISHED\_RABS and the IE "Re-establishment timer" in the IE "RAB Info" in the variable ESTABLISHED\_RABS to "useT314".
- 1> if IE "Specification mode" is set to "Preconfiguration":

2> use the following values for parameters that are neither signalled within the HANOVER TO UTRAN COMMAND message nor included within pre-defined or default configuration:

3> 0 dB for the power offset  $P_{\text{Pilot-DPDCH}}$  bearer in FDD;

3> calculate the Default DPCH Offset Value using the following formula:

3> in FDD:

$$\text{Default DPCH Offset Value} = (\text{SRNTI } 2 \bmod 600) * 512$$

3> in TDD:

$$\text{Default DPCH Offset Value} = (\text{SRNTI } 2 \bmod 7)$$

3> handle the above Default DPCH Offset Value as if an IE with that value was included in the message, as specified in subclause 8.6.6.21.

- 1> if IE "Specification mode" is set to "Complete specification":

2> initiate the radio bearer, transport channel and physical channel configuration in accordance with the received radio bearer, transport channel and physical channel information elements.

- 1> perform an open loop estimation to determine the UL transmission power according to subclause 8.5.3;

- 1> set the IE "START" for each CN domain, in the IE "START list" in the HANOVER TO UTRAN COMPLETE message equal to the START value for each CN domain stored in the USIM if the USIM is present, or as stored in the UE for each CN domain if the SIM is present;

- 1> if ciphering has been activated and ongoing in the radio access technology from which inter- RAT handover is performed:

2> for the CN domain included in the IE "CN domain identity" which is included in the IE "RAB info" of the IE "RAB information to setup", or the CS domain when these IEs are not present:

3> set the variable LATEST\_CONFIGURED\_CN\_DOMAIN to the value indicated in the IE "CN domain identity", or to the CS domain when this IE is not present;

3> set the 20 MSB of the HFN component of the COUNT-C variable for all radio bearers using RLC-TM and all signalling radio bearers to the "START" value included in the IE "UE security information" in the variable "INTER\_RAT\_HANOVER\_INFO\_TRANSFERRED";

3> set the remaining LSBs of the HFN component of COUNT-C for all radio bearers using RLC-TM and all signalling radio bearers to zero;

3> not increment the HFN component of COUNT-C for radio bearers using RLC-TM, i.e. keep the HFN value fixed without incrementing every CFN cycle;

3> set the CFN component of the COUNT-C variable to the value of the CFN as calculated in subclause 8.5.15;

- 3> set the IE "Status" in the variable CIPHERING\_STATUS to "Started";
- 3> apply the algorithm according to IE "Ciphering Algorithm" and apply ciphering immediately upon reception of the HANDOVER TO UTRAN COMMAND.

1> if ciphering has not been activated and ongoing in the radio access technology from which inter-RAT handover is performed:

- 2> for the CN domain included in the IE "CN domain identity" which is included in the IE "RAB info" of the IE "RAB information to setup", or the CS domain when these IEs are not present:
  - 3> set the IE "Status" in the variable CIPHERING\_STATUS to "Not Started".

If the UE succeeds in establishing the connection to UTRAN, it shall:

- 1> if the IE "Status" in the variable CIPHERING\_STATUS of a CN domain is set to "Started" and transparent mode radio bearers have been established by this procedure for that CN domain:
  - 2> include the IE "COUNT-C activation time" in the response message and specify a CFN value other than the default, "Now" for this IE;
  - 2> at the CFN value as indicated in the response message in the IE "COUNT-C activation time" for radio bearers using RLC-TM:
    - 3> set the 20 MSB of the HFN component of the COUNT-C variable common for all transparent mode radio bearers of this CN domain to the START value as indicated in the IE "START list" of the response message for the relevant CN domain; and
    - 3> set the remaining LSBs of the HFN component of COUNT-C to zero;
    - 3> increment the HFN component of the COUNT-C variable by one;
    - 3> set the CFN component of the COUNT-C to the value of the IE "COUNT-C activation time" of the response message. The HFN component and the CFN component completely initialise the COUNT-C variable;
    - 3> step the COUNT-C variable, as normal, at each CFN value. The HFN component is no longer fixed in value but incremented at each CFN cycle.

- 1> if the IE "Status" in the variable CIPHERING\_STATUS of a CN domain is set to "Not Started" and transparent mode radio bearers have been established by this procedure for that CN domain:
  - 2> initialise the 20 MSB of the HFN component of COUNT-C common for all transparent mode radio bearers of this CN domain with the START value as indicated in the IE "START list" of the response message for the relevant CN domain;
  - 2> set the remaining LSBs of the HFN component of COUNT-C to zero;
  - 2> do not increment the COUNT-C value common for all transparent mode radio bearers for this CN domain.

1> transmit a HANDOVER TO UTRAN COMPLETE message on the uplink DCCH, using, if ciphering has been started, the new ciphering configuration; and

[1> set IE "UE Specific Behaviour Information 2" to "No UE Specific Behaviour Information 2";](#)

- 1> when the HANDOVER TO UTRAN COMPLETE message has been submitted to lower layers for transmission:
  - 2> enter UTRA RRC connected mode in state CELL\_DCH;
  - 2> initialise variables upon entering UTRA RRC connected mode as specified in subclause 13.4;
  - 2> for all radio bearers using RLC-AM or RLC-UM:
    - 3> set the 20 MSB of the HFN component of the uplink and downlink COUNT-C variable to the START value indicated in the IE "START list" of the response message for the relevant CN domain; and
    - 3> set the remaining LSBs of the HFN component of COUNT-C to zero;
    - 3> increment the HFN component of the COUNT-C variable by one;

3> start incrementing the COUNT-C values.

1> and the procedure ends.

## 10.2.16b HANDOVER TO UTRAN COMPLETE

This message is sent by the UE when a handover to UTRAN has been completed.

RLC-SAP: AM

Logical channel: DCCH

Direction: UE → UTRAN

Information Element/Group name	Need	Multi	Type and reference	Semantics description
Message Type	MP		Message Type	
<b>UE Information elements</b>				
START list	CH	1 to <maxCNdomains>		START [40] values for all CN domains.
>CN domain identity	MP		CN domain identity 10.3.1.1	
>START	MP		START 10.3.3.38	
<a href="#">&gt;UE Specific Behaviour Information 2</a>	<a href="#">MP</a>		<a href="#">UE Specific Behaviour Information 2</a> <a href="#">10.3.3.53</a>	
<b>RB Information elements</b>				
COUNT-C activation time	OP		Activation time 10.3.3.1	Used for radio bearers mapped on RLC-TM.

## 10.2.41 RRC CONNECTION SETUP COMPLETE

This message confirms the establishment of the RRC Connection by the UE.

RLC-SAP: AM

Logical channel: DCCH

Direction: UE → UTRAN

Information Element/Group name	Need	Multi	Type and reference	Semantics description
Message Type	MP		Message Type	
<b>UE Information Elements</b>				
RRC transaction identifier	MP		RRC transaction identifier 10.3.3.36	
START list	MP	1 to <maxCNdomains>		START [40] values for all CN domains.
>CN domain identity	MP		CN domain identity 10.3.1.1	
>START	MP		START 10.3.3.38	START value to be used in this CN domain.
UE radio access capability	OP		UE radio	

<b>Information Element/Group name</b>	<b>Need</b>	<b>Multi</b>	<b>Type and reference</b>	<b>Semantics description</b>
			access capability 10.3.3.42	
UE radio access capability extension	OP		UE radio access capability extension 10.3.3.42a	
<a href="#">&gt;UE Specific Behaviour Information 2</a>	<a href="#">MP</a>		<a href="#">UE Specific Behaviour Information 2</a> 10.3.3.53	
<b>Other information elements</b>				
UE system specific capability	OP	1 to <maxInter SysMessages>		
>Inter-RAT UE radio access capability	MP		Inter-RAT UE radio access capability 10.3.8.7	

### 10.3.3.53 UE Specific Behaviour Information 2

This IE indicates the UE conformance.

<b>Information Element/Group name</b>	<b>Need</b>	<b>Multi</b>	<b>Type and Reference</b>	<b>Semantics description</b>
<a href="#">CHOICE UE Specific Behaviour Information 2</a>	<a href="#">MP</a>			<a href="#">In this version of the specification the UE should set this IE to "No UE Specific Behaviour Information 2"</a>
<a href="#">&gt;No UE Specific Behaviour Information 2</a>	<a href="#">MP</a>			(no data)
<a href="#">&gt;UE Specific Behaviour Information 2 fixed</a>	<a href="#">MP</a>		<a href="#">bit string(16)</a>	
<a href="#">&gt; UE Specific Behaviour Information 2 variable</a>	<a href="#">MP</a>		<a href="#">bit string(1..256)</a>	

## 11.2 PDU definitions

```
-- ****
-- TABULAR: The message type and integrity check info are not
-- visible in this module as they are defined in the class module.
-- Also, all FDD/TDD specific choices have the FDD option first
-- and TDD second, just for consistency.
-- ****
```

PDU-definitions DEFINITIONS AUTOMATIC TAGS ::=

BEGIN

```
-- ****
-- IE parameter types from other modules
-- ****
```

IMPORTS

```

-- Core Network IEs :
CN-DomainIdentity,
CN-InformationInfo,
CN-InformationInfoFull,
NAS-Message,
PagingRecordTypeID,
-- UTRAN Mobility IEs :
URA-Identity,
-- User Equipment IEs :
ActivationTime,
C-RNTI,
CapabilityUpdateRequirement,
CellUpdateCause,
CipheringAlgorithm,
CipheringModeInfo,
DSCH-RNTI,
EstablishmentCause,
FailureCauseWithProtErr,
FailureCauseWithProtErrTrId,
UESpecificBehaviourInformation2,
InitialUE-Identity,
IntegrityProtActivationInfo,
IntegrityProtectionModeInfo,
N-308,
PagingCause,
PagingRecordList,
ProtocolErrorIndicator,
ProtocolErrorIndicatorWithMoreInfo,
Rb-timer-indicator,
RedirectionInfo,
RejectionCause,
ReleaseCause,
RRC-StateIndicator,
RRC-TransactionIdentifier,
SecurityCapability,
START-Value,
STARTList,
U-RNTI,
U-RNTI-Short,
UE-RadioAccessCapability,
UE-RadioAccessCapability-v370ext,
UE-RadioAccessCapability-v380ext,
UE-RadioAccessCapability-v3a0ext,
DL-PhysChCapabilityFDD-v380ext,
UE-ConnTimersAndConstants,
UE-ConnTimersAndConstants-v3a0ext,
UE-SecurityInformation,
URA-UpdateCause,
UTRAN-DRX-CycleLengthCoefficient,
WaitTime,
-- Radio Bearer IEs :
DefaultConfigIdentity,
DefaultConfigMode,
DL-CounterSynchronisationInfo,
PredefinedConfigIdentity,
PredefinedConfigStatusList,
RAB-Info,
RAB-Info-Post,
RAB-InformationList,
RAB-InformationReconfigList,
RAB-InformationSetupList,
RB-ActivationTimeInfoList,
RB-COUNT-C-InformationList,
RB-COUNT-C-MSB-InformationList,
RB-IdentityList,
RB-InformationAffectedList,
RB-InformationReconfigList,
RB-InformationReleaseList,
SRB-InformationSetupList,
SRB-InformationSetupList2,
UL-CounterSynchronisationInfo,
-- Transport Channel IEs:
CPCH-SetID,
DL-AddReconfTransChInfo2List,
DL-AddReconfTransChInfoList,
DL-CommonTransChInfo,
DL-DeletedTransChInfoList,
DRAC-StaticInformationList,
TFC-Subset,

```

```

TFCS-Identity,
UL-AddReconfTransChInfoList,
UL-CommonTransChInfo,
UL-DeletedTransChInfoList,
-- Physical Channel IEs :
Alpha,
CCTrCH-PowerControlInfo,
ConstantValue,
ConstantValueTdd,
CPCH-SetInfo,
DL-CommonInformation,
DL-CommonInformationPost,
DL-InformationPerRL,
DL-InformationPerRL-List,
DL-InformationPerRL-ListPostFDD,
DL-InformationPerRL-PostTDD,
DL-PDSCH-Information,
DPCH-CompressedModeStatusInfo,
FrequencyInfo,
FrequencyInfoFDD,
FrequencyInfoTDD,
MaxAllowedUL-TX-Power,
PDSCH-CapacityAllocationInfo,
PDSCH-Identity,
PrimaryCCPCH-TX-Power,
PUSCH-CapacityAllocationInfo,
PUSCH-Identity,
RL-AdditionInformationList,
RL-RemovalInformationList,
SpecialBurstsScheduling,
SSDT-Information,
TFC-ControlDuration,
TimeslotList,
TX-DiversityMode,
UL-ChannelRequirement,
UL-ChannelRequirementWithCPCH-SetID,
UL-DPCH-Info,
UL-DPCH-InfoPostFDD,
UL-DPCH-InfoPostTDD,
UL-TimingAdvance,
UL-TimingAdvanceControl,
-- Measurement IEs :
AdditionalMeasurementID-List,
Frequency-Band,
EventResults,
InterRAT-TargetCellDescription,
MeasuredResults,
MeasuredResults-v390ext,
MeasuredResultsList,
MeasuredResultsOnRACH,
MeasurementCommand,
MeasurementIdentity,
MeasurementReportingMode,
PrimaryCCPCH-RSCP,
SFN-Offset-Validity,
TimeslotListWithISCP,
TrafficVolumeMeasuredResultsList,
UE-Positioning-GPS-AssistanceData,
UE-Positioning-Measurement-v390ext,
UE-Positioning-OTDOA-AssistanceData,
UE-Positioning-OTDOA-AssistanceData-UEB,
-- Other IEs :
BCCH-ModificationInfo,
CDMA2000-MessageList,
GSM-MessageList,
InterRAT-ChangeFailureCause,
InterRAT-HO-FailureCause,
InterRAT-UE-RadioAccessCapabilityList,
InterRAT-UE-SecurityCapList,
IntraDomainNasNodeSelector,
ProtocolErrorMoreInformation,
Rplmn-Information,
SegCount,
SegmentIndex,
SFN-Prime,
SIB-Data-fixed,
SIB-Data-variable,
SIB-Type
FROM InformationElements

```

```

maxSIBperMsg
FROM Constant-definitions;

-- ****
-- 
-- HANOVER TO UTRAN COMPLETE
-- 
-- ****

HandoverToUTRANComplete ::= SEQUENCE {
    --TABULAR: Integrity protection shall not be performed on this message.
    -- User equipment IEs
        -- TABULAR: startList is conditional on history.
        startList                      STARTList                                OPTIONAL,
    -- Radio bearer IEs
        count-C-ActivationTime          ActivationTime                OPTIONAL,
    -- Non critical Extensions
        v3d0NonCriticalExtensions     SEQUENCE {
            handoverToUTRANComplete-v3d0ext HandoverToUTRANComplete-v3d0ext-IES,
            -- Reserved for future non critical extension
            nonCriticalExtensions       SEQUENCE {} OPTIONAL
        } OPTIONAL
    -- Extension mechanism for non-release99 information
    -- nonCriticalExtensions       SEQUENCE {} OPTIONAL
}

HandoverToUTRANComplete-v3d0ext-IES ::= SEQUENCE {
    -- User equipment IEs
        uESpecificBehaviourInformation2 UESpecificBehaviourInformation2
}

-- ****
-- 
-- INTER RAT HANOVER INFO
-- 
-- ****

InterRATHandoverInfo ::= SEQUENCE {
    -- This structure is defined for historical reasons, backward compatibility with 04.18
    predefinedConfigStatusList      CHOICE {
        absent                     NULL,
        present                    PredefinedConfigStatusList
    },
    uE-SecurityInformation         CHOICE {
        absent                     NULL,
        present                    UE-SecurityInformation
    },
    ue-CapabilityContainer         CHOICE {
        absent                     NULL,
        -- present is an octet aligned string containing IE UE-RadioAccessCapabilityInfo
        present                   OCTET STRING (SIZE (0..63))
    },
    -- Non critical extensions
    v390NonCriticalExtensions     CHOICE {
        absent                     NULL,
        present                    SEQUENCE {
            interRATHandoverInfo-v390ext InterRATHandoverInfo-v390ext-IES,
            -- Reserved for future non critical extension
            v3a0NonCriticalExtensions   SEQUENCE {
                interRATHandoverInfo-v3a0ext InterRATHandoverInfo-v3a0ext-IES,
                -- Reserved for future non critical extension
                nonCriticalExtensions     SEQUENCE {} OPTIONAL
            } OPTIONAL
        }
    }
}

InterRATHandoverInfo-v390ext-IES ::= SEQUENCE {
    -- User equipment IEs
        ue-RadioAccessCapability-v380ext    UE-RadioAccessCapability-v380ext      OPTIONAL,
        dl-PhysChCapabilityFDD-v380ext     DL-PhysChCapabilityFDD-v380ext
}

InterRATHandoverInfo-v3a0ext-IES ::= SEQUENCE {
    -- User equipment IEs
        ue-RadioAccessCapability-v3a0ext    UE-RadioAccessCapability-v3a0ext      OPTIONAL
}

```

```

-- ****
-- RRC CONNECTION REQUEST
--
-- ****

RRCConnectionRequest ::= SEQUENCE {
    -- TABULAR: Integrity protection shall not be performed on this message.
    -- User equipment IEs
    initialUE-Identity           InitialUE-Identity,
    establishmentCause            EstablishmentCause,
    -- protocolErrorIndicator is MD, but for compactness reasons no default value
    -- has been assigned to it.
    protocolErrorIndicator        ProtocolErrorIndicator,
    -- Measurement IEs
    measuredResultsOnRACH         MeasuredResultsOnRACH
                                    OPTIONAL,
    -- Extension mechanism for non- release99 information
    nonCriticalExtensions         SEQUENCE {}      OPTIONAL
}

-- ****
-- RRC CONNECTION SETUP COMPLETE
--
-- ****

RRCConnectionSetupComplete ::= SEQUENCE {
    -- TABULAR: Integrity protection shall not be performed on this message.
    -- User equipment IEs
    rrc-TransactionIdentifier     RRC-TransactionIdentifier,
    startList                     STARTList,
    ue-RadioAccessCapability      UE-RadioAccessCapability
                                    OPTIONAL,
    -- Other IEs
    ue-RATSpecificCapability     InterRAT-UE-RadioAccessCapabilityList OPTIONAL,
    -- Non critical extensions
    v370NonCriticalExtensions    SEQUENCE {
        rrcConnectionSetupComplete-v370ext  RRCConnectionSetupComplete-v370ext,
        v380NonCriticalExtensions          SEQUENCE {
            rrcConnectionSetupComplete-v380ext  RRCConnectionSetupComplete-v380ext-IEs,
            -- Reserved for future non critical extension
            v3a0NonCriticalExtensions        SEQUENCE {
                rrcConnectionSetupComplete-v3a0ext  RRCConnectionSetupComplete-v3a0ext-IEs,
                v3d0NonCriticalExtensions      SEQUENCE {
                    rRCConnectionSetupComplete-v3d0ext-IEs RRCConnectionSetupComplete-v3d0ext-IEs,
                    -- Reserved for future non critical extension
                    nonCriticalExtensions        SEQUENCE {}      OPTIONAL
                }
                OPTIONAL
            }
            OPTIONAL
        }
        OPTIONAL
    }
}

RRCConnectionSetupComplete-v370ext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v370ext  UE-RadioAccessCapability-v370ext
                                    OPTIONAL
}

RRCConnectionSetupComplete-v380ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v380ext  UE-RadioAccessCapability-v380ext
                                    OPTIONAL,
    dl-PhysChCapabilityFDD-v380ext  DL-PhysChCapabilityFDD-v380ext
}

RRCConnectionSetupComplete-v3a0ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v3a0ext  UE-RadioAccessCapability-v3a0ext
                                    OPTIONAL
}

RRCConnectionSetupComplete-v3d0ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    uESpecificBehaviourInformation2  UESpecificBehaviourInformation2
}

```

## 11.3 Information element definitions

```

-- ****
-- 
--   USER EQUIPMENT INFORMATION ELEMENTS (10.3.3)
-- 
-- ****

-- TABULAR : for ActivationTime, value 'now' always appears as default, and is encoded
-- by absence of the field
ActivationTime ::= INTEGER (0..255)

BackoffControlParams ::= SEQUENCE {
    n-AP-RetransMax,
    n-AccessFails,
    nf-BO-NoAICH,
    ns-BO-Busy,
    nf-BO-AllBusy,
    nf-BO-Mismatch,
    t-CPCH
}

C-RNTI ::= BIT STRING (SIZE (16))

CapabilityUpdateRequirement ::= SEQUENCE {
    ue-RadioCapabilityFDDUpdateRequirement BOOLEAN,
    ue-RadioCapabilityTDDUpdateRequirement BOOLEAN,
    systemSpecificCapUpdateReqList SystemSpecificCapUpdateReqList OPTIONAL
}

CellUpdateCause ::= ENUMERATED {
    cellReselection,
    periodicalCellUpdate,
    uplinkDataTransmission,
    utran-pagingResponse,
    re-enteredServiceArea,
    radiolinkFailure,
    rlc-unrecoverableError,
    spare1
}

ChipRateCapability ::= ENUMERATED {
    mcps3-84, mcps1-28
}

CipheringAlgorithm ::= ENUMERATED {
    uea0, uea1
}

CipheringModeCommand ::= CHOICE {
    startRestart,
    dummy
    NULL
}

CipheringModeInfo ::= SEQUENCE {
    -- TABULAR: The ciphering algorithm is included in the CipheringModeCommand.
    cipheringModeCommand CipheringModeCommand,
    activationTimeForDPCH ActivationTime OPTIONAL,
    rb-DL-CiphActivationTimeInfo RB-ActivationTimeInfoList OPTIONAL
}

CN-DRX-CycleLengthCoefficient ::= INTEGER (6..9)

CN-PagedUE-Identity ::= CHOICE {
    imsi-GSM-MAP,
    tmsi-GSM-MAP,
    p-TMSI-GSM-MAP,
    imsi-DS-41,
    tmsi-DS-41,
    spare3,
    spare2,
    spare1
}

CompressedModeMeasCapability ::= SEQUENCE {
    fdd-Measurements BOOLEAN,
    -- TABULAR: The IEs tdd-Measurements, gsm-Measurements and multiCarrierMeasurements
    -- are made optional since they are conditional based on another information element.
    -- Their absence corresponds to the case where the condition is not true.
    tdd-Measurements BOOLEAN OPTIONAL,
    gsm-Measurements GSM-Measurements OPTIONAL,
    multiCarrierMeasurements BOOLEAN OPTIONAL
}

```

```

CompressedModeMeasCapabFDDList ::= SEQUENCE (SIZE (1..maxFreqBandsFDD)) OF
    CompressedModeMeasCapabFDD

CompressedModeMeasCapabFDD ::= SEQUENCE {
    radioFrequencyBandFDD OPTIONAL,
    dl-MeasurementsFDD BOOLEAN,
    ul-MeasurementsFDD BOOLEAN
}

CompressedModeMeasCapabTDDList ::= SEQUENCE (SIZE (1..maxFreqBandsTDD)) OF
    CompressedModeMeasCapabTDD

CompressedModeMeasCapabTDD ::= SEQUENCE {
    radioFrequencyBandTDD,
    dl-MeasurementsTDD BOOLEAN,
    ul-MeasurementsTDD BOOLEAN
}

CompressedModeMeasCapabGSMList ::= SEQUENCE (SIZE (1..maxFreqBandsGSM)) OF
    CompressedModeMeasCapabGSM

CompressedModeMeasCapabGSM ::= SEQUENCE {
    radioFrequencyBandGSM,
    dl-MeasurementsGSM BOOLEAN,
    ul-MeasurementsGSM BOOLEAN
}

CompressedModeMeasCapabMC ::= SEQUENCE {
    dl-MeasurementsMC BOOLEAN,
    ul-MeasurementsMC BOOLEAN
}

CPCH-Parameters ::= SEQUENCE {
    initialPriorityDelayList InitialPriorityDelayList OPTIONAL,
    backoffControlParams BackoffControlParams,
    -- TABULAR: TPC step size nested inside PowerControlAlgorithm
    powerControlAlgorithm PowerControlAlgorithm,
    dl-DPCCH-BER
}

DL-DPCCH-BER ::= INTEGER (0..63)

DL-PhysChCapabilityFDD ::= SEQUENCE {
    maxNoDPCH-PDSCH-Codes INTEGER (1..8),
    maxNoPhysChBitsReceived MaxNoPhysChBitsReceived,
    supportForSF-512 BOOLEAN,
    supportOfPDSCH BOOLEAN,
    simultaneousSCCPCH-DPCH-Reception SimultaneousSCCPCH-DPCH-Reception
}

DL-PhysChCapabilityFDD-v380ext ::= SEQUENCE {
    supportOfDedicatedPilotsForChEstimation SupportOfDedicatedPilotsForChEstimation OPTIONAL
}

SupportOfDedicatedPilotsForChEstimation ::= ENUMERATED { true }

DL-PhysChCapabilityTDD ::= SEQUENCE {
    maxTS-PerFrame MaxTS-PerFrame,
    maxPhysChPerFrame MaxPhysChPerFrame,
    minimumSF MinimumSF-DL,
    supportOfPDSCH BOOLEAN,
    maxPhysChPerTS MaxPhysChPerTS
}

DL-TransChCapability ::= SEQUENCE {
    maxNoBitsReceived MaxNoBits,
    maxConvCodeBitsReceived MaxNoBits,
    turboDecodingSupport TurboSupport,
    maxSimultaneousTransChs MaxSimultaneousTransChsDL,
    maxSimultaneousCCTrCH-Count MaxSimultaneousCCTrCH-Count,
    maxReceivedTransportBlocks MaxTransportBlocksDL,
    maxNumberOfTFC MaxNumberOfTFC-DL,
    maxNumberOfTF MaxNumberOfTF
}

DRAC-SysInfo ::= SEQUENCE {
    transmissionProbability TransmissionProbability,
    maximumBitRate MaximumBitRate
}

```

```

DRAC-SysInfoList ::= SEQUENCE (SIZE (1..maxDRACclasses)) OF DRAC-SysInfo

DSCH-RNTI ::= BIT STRING (SIZE (16))

ESN-DS-41 ::= BIT STRING (SIZE (32))

EstablishmentCause ::= ENUMERATED {
    originatingConversationalCall,
    originatingStreamingCall,
    originatingInteractiveCall,
    originatingBackgroundCall,
    originatingSubscribedTrafficCall,
    terminatingConversationalCall,
    terminatingStreamingCall,
    terminatingInteractiveCall,
    terminatingBackgroundCall,
    emergencyCall,
    interRAT-CellReselection,
    interRAT-CellChangeOrder,
    registration,
    detach,
    originatingHighPrioritySignalling,
    originatingLowPrioritySignalling,
    callRe-establishment,
    terminatingHighPrioritySignalling,
    terminatingLowPrioritySignalling,
    terminatingCauseUnknown,
    spare12,
    spare11,
    spare10,
    spare9,
    spare8,
    spare7,
    spare6,
    spare5,
    spare4,
    spare3,
    spare2,
    spare1 }

FailureCauseWithProtErr ::= CHOICE {
    configurationUnsupported      NULL,
    physicalChannelFailure       NULL,
    incompatibleSimultaneousReconfiguration   NULL,
    compressedModeRuntimeError   TGPSI,
    protocolError                ProtocolErrorInformation,
    cellUpdateOccurred           NULL,
    invalidConfiguration          NULL,
    configurationIncomplete      NULL,
    unsupportedMeasurement       NULL,
    spare7                      NULL,
    spare6                      NULL,
    spare5                      NULL,
    spare4                      NULL,
    spare3                      NULL,
    spare2                      NULL,
    spare1                      NULL
}

FailureCauseWithProtErrTrId ::= SEQUENCE {
    rrc-TransactionIdentifier   RRC-TransactionIdentifier,
    failureCause                FailureCauseWithProtErr
}

GSM-Measurements ::= SEQUENCE {
    gsm900                      BOOLEAN,
    dcs1800                      BOOLEAN,
    gsm1900                      BOOLEAN
}

AccessStratumReleaseIndicator ::= ENUMERATED {
    r99
}

UESpecificBehaviourInformation2 ::= CHOICE {
    uESpecificBehaviourInformation2fixednotavailable   NULL,
    uESpecificBehaviourInformation2fixed               UESpecificBehaviourInformation2fixed,
}

```

```

UESpecificBehaviourInformation2variable          UESpecificBehaviourInformation2variable,
spare                                         NULL
}

UESpecificBehaviourInformation2fixed ::= = BIT STRING (SIZE (16))
UESpecificBehaviourInformation2variable ::= = BIT STRING (SIZE (1..256))

IMSI-and-ESN-DS-41 ::=          SEQUENCE {
    imsi-DS-41           IMSI-DS-41,
    esn-DS-41            ESN-DS-41
}

IMSI-DS-41 ::=                  OCTET STRING (SIZE (5..7))

InitialPriorityDelayList ::=      SEQUENCE (SIZE (1..maxASC)) OF
                                    NS-IP

InitialUE-Identity ::=          CHOICE {
    imsi
    tmsi-and-LAI
    p-TMSI-and-RAI
    imei
    esn-DS-41
    imsi-DS-41
    imsi-and-ESN-DS-41
    tmsi-DS-41
}

IntegrityCheckInfo ::=          SEQUENCE {
    messageAuthenticationCode
    rrc-MessageSequenceNumber
}

IntegrityProtActivationInfo ::=   SEQUENCE {
    rrc-MessageSequenceNumberList
}

IntegrityProtectionAlgorithm ::= ENUMERATED {
                                uial
}

```

## 11.5 RRC information between network nodes

```

-- ****
-- Handover to UTRAN information
--
-- ****

InterRATHandoverInfoWithInterRATCapabilities ::= CHOICE {
    r3          SEQUENCE {
        -- IE InterRATHandoverInfoWithInterRATCapabilities-r3-IEs also
        -- includes non critical extensions
        interRATHandoverInfo-r3          InterRATHandoverInfoWithInterRATCapabilities-r3-IEs,
        v390NonCriticalExtensions       SEQUENCE {
            interRATHandoverInfoWithInterRATCapabilities-v390ext
        }
        InterRATHandoverInfoWithInterRATCapabilities-v390ext-IEs,
        -- Reserved for future non critical extension
        nonCriticalExtensions          SEQUENCE {} OPTIONAL
    },
    criticalExtensions             SEQUENCE {}
}

InterRATHandoverInfoWithInterRATCapabilities-r3-IEs ::= SEQUENCE {
    -- The order of the IEs may not reflect the tabular format
    -- but has been chosen to simplify the handling of the information in the BSC
    -- Other IEs
    ue-RATSpecificCapability       InterRAT-UE-RadioAccessCapabilityList OPTIONAL,
    -- interRATHandoverInfo, Octet string is used to obtain 8 bit length field prior to
    -- actual information. This makes it possible for BSS to transparently handle information
    -- received via GSM air interface even when it includes non critical extensions.
    -- The octet string shall include the InterRATHandoverInfo information
    -- The BSS can re-use the 04.18 length field received from the MS
}

```

```

        interRATHandoverInfo          OCTET STRING (SIZE (0..255))
    }

-- ****
-- SRNC Relocation information
-- ****

SRNC-RelocationInfo ::= CHOICE {
    r3                      SEQUENCE {
        SRNC-RelocationInfo-r3      SRNC-RelocationInfo-r3-IEs,
        v380NonCriticalExtensions   SEQUENCE {
            SRNC-RelocationInfo-v380ext SRNC-RelocationInfo-v380ext-IEs,
            -- Reserved for future non critical extension
            v390NonCriticalExtensions   SEQUENCE {
                SRNC-RelocationInfo-v390ext      SRNC-RelocationInfo-v390ext-IEs,
                v3a0NonCriticalExtensions       SEQUENCE {
                    SRNC-RelocationInfo-v3a0ext      SRNC-RelocationInfo-v3a0ext-IEs,
                    v3b0NonCriticalExtensions       SEQUENCE {
                        SRNC-RelocationInfo-v3b0ext      SRNC-RelocationInfo-v3b0ext-IEs,
                        v3c0NonCriticalExtensions       SEQUENCE {
                            SRNC-RelocationInfo-v3c0ext      SRNC-RelocationInfo-v3c0ext-IEs,
                            v3d0NonCriticalExtensions     SEQUENCE {
                                SRNC-RelocationInfo-v3d0ext      SRNC-RelocationInfo-v3d0ext-IEs,
                                -- Reserved for future non critical extension
                                nonCriticalExtensions         SEQUENCE {} OPTIONAL
                            } OPTIONAL
                        } OPTIONAL
                    } OPTIONAL
                } OPTIONAL
            } OPTIONAL
        } OPTIONAL
    }, criticalExtensions      SEQUENCE {}
}

SRNC-RelocationInfo-r3-IEs ::= SEQUENCE {
    -- Non-RRC IEs
    stateOfRRC                  StateOfRRC,
    stateOfRRC-Procedure         StateOfRRC-Procedure,
    -- Ciphering related information IEs
    -- If the extension v380 is included use the extension for the ciphering status per CN domain
    cipheringStatus              CipheringStatus,
    calculationTimeForCiphering  CalculationTimeForCiphering OPTIONAL,
    -- The order of occurrence in the IE cipheringInfoPerRB-List is the
    -- same as the RBs in the IE "Signalling RB information list" and in the
    -- IE "RAB information list". The signalling RBs are supposed to be listed
    -- first. Only UM and AM RBs that are ciphered are listed here
    cipheringInfoPerRB-List      CipheringInfoPerRB-List OPTIONAL,
    count-C-List                 COUNT-C-List OPTIONAL,
    integrityProtectionStatus    IntegrityProtectionStatus,
    srb-SpecificIntegrityProtInfo SRB-SpecificIntegrityProtInfoList,
    implementationSpecificParams ImplementationSpecificParams OPTIONAL,
    -- User equipment IEs
    u-RNTI                      U-RNTI,
    c-RNTI                      C-RNTI OPTIONAL,
    ue-RadioAccessCapability     UE-RadioAccessCapability,
    ue-Positioning-LastKnownPos  UE-Positioning-LastKnownPos OPTIONAL,
    -- Other IEs
    ue-RATSpecificCapability    InterRAT-UE-RadioAccessCapabilityList OPTIONAL,
    -- UTRAN mobility IEs
    ura-Identity                 URA-Identity OPTIONAL,
    -- Core network IEs
    cn-CommonGSM-MAP-NAS-SysInfo NAS-SystemInformationGSM-MAP,
    cn-DomainInformationList     CN-DomainInformationList OPTIONAL,
    -- Measurement IEs
    ongoingMeasRepList           OngoingMeasRepList OPTIONAL,
    -- Radio bearer IEs
    predefinedConfigStatusList   PredefinedConfigStatusList,
    srb-InformationList          SRB-InformationSetupList,
    rab-InformationList          RAB-InformationSetupList OPTIONAL,
    -- Transport channel IEs
    ul-CommonTransChInfo         UL-CommonTransChInfo OPTIONAL,
    ul-TransChInfoList           UL-AddReconfTransChInfoList OPTIONAL,
    modeSpecificInfo              CHOICE {
        fdd                         SEQUENCE {
            cpch-SetID                 CPCH-SetID OPTIONAL,
        }
    }
}

```

```

        transChDRAC-Info           DRAC-StaticInformationList  OPTIONAL
    },
    tdd                         NULL
},
dl-CommonTransChInfo          DL-CommonTransChInfo          OPTIONAL,
dl-TransChInfoList            DL-AddReconfTransChInfoList  OPTIONAL,
-- Measurement report         MeasurementReport           OPTIONAL
measurementReport

}

SRNC-RelocationInfo-v380ext-IEs ::= SEQUENCE {
    -- Ciphering related information IEs
    cn-DomainIdentity           CN-DomainIdentity,
    cipheringStatusList          CipheringStatusList
}

SRNC-RelocationInfo-v390ext-IEs ::= SEQUENCE {
    cn-DomainInformationList-v390ext   CN-DomainInformationList-v390ext  OPTIONAL,
    ue-RadioAccessCapability-v370ext   UE-RadioAccessCapability-v370ext  OPTIONAL,
    ue-RadioAccessCapability-v380ext   UE-RadioAccessCapability-v380ext  OPTIONAL,
    dl-PhysChCapabilityFDD-v380ext    DL-PhysChCapabilityFDD-v380ext,
    failureCauseWithProtErr         FailureCauseWithProtErr      OPTIONAL
}

SRNC-RelocationInfo-v3a0ext-IEs ::= SEQUENCE {
    cipheringInfoForSRB1-v3a0ext     CipheringInfoPerRB-List-v3a0ext,
    ue-RadioAccessCapability-v3a0ext  UE-RadioAccessCapability-v3a0ext  OPTIONAL,
    -- cn-domain identity for IE startValueForCiphering-v3a0ext is specified
    -- in subsequent extension (SRNC-RelocationInfo-v3b0ext-IEs)
    startValueForCiphering-v3a0ext    START-Value
}

SRNC-RelocationInfo-v3b0ext-IEs ::= SEQUENCE {
    -- cn-domain identity for IE startValueForCiphering-v3a0ext included in previous extension
    cn-DomainIdentity               CN-DomainIdentity,
    -- the remaining start values are contained in IE startValueForCiphering-v3b0ext
    startValueForCiphering-v3b0ext    STARTList2                  OPTIONAL
}

SRNC-RelocationInfo-v3c0ext-IEs ::= SEQUENCE {
    -- IE rb-IdentityForHOMessage includes the identity of the RB used by the source SRNC
    -- to send the message contained in the IE "TargetRNC-ToSourceRNC-Container".
    -- Only included if type is "UE involved"
    rb-IdentityForHOMessage         RB-Identity                OPTIONAL
}

}

SRNC-RelocationInfo-v3d0ext-IEs ::= SEQUENCE {
    -- User equipment IEs
        uESpecificBehaviourInformation2    UESpecificBehaviourInformation2    OPTIONAL
}

```

#### 14.12.4.2 SRNS RELOCATION INFO

This RRC message is sent between network nodes when preparing for an SRNS relocation.

With the presence or absence of the IE "RB identity for Hard Handover message" the source RNC indicates to the target SRNC whether the source RNC expects to receive the choice "DL DCCH message" in the IE "RRC information, target RNC to source RNC" in case the SRNS relocation is of type "UE involved". Furthermore the target RNC uses this information for the calculation of the MAC-I.

Direction: source RNC→target RNC

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
<b>Non RRC IEs</b>				
RB identity for Handover message	OP		RB identity 10.3.4.16	Gives the id of the radio bearer on which the source RNC will transmit the RRC message in the case the relocation is of type "UE involved".
>State of RRC	MP		RRC state indicator,	

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
			10.3.3.35a	
>State of RRC procedure	MP		Enumerated (await no RRC message, await RB Release Complete, await RB Setup Complete, await RB Reconfiguration Complete, await Transport CH Reconfiguration Complete, await Physical CH Reconfiguration Complete, await Active Set Update Complete, await Handover Complete, send Cell Update Confirm, send URA Update Confirm, , others)	
<b>Ciphering related information</b>				
>Ciphering status for each CN domain	MP	<1 to maxCNDomains>		
>>CN domain identity	MP		CN domain identity 10.3.1.1	
>>Ciphering status	MP		Enumerated( Not started, Started)	
>>START	MP		START 10.3.3.38	START value to be used in this CN domain.
>Latest configured CN domain	MP		CN domain identity 10.3.1.1	Value contained in the variable of the same name. In case this variable is empty, the source RNC can set any CN domain identity. In that case, the Ciphering status and the Integrity protection status should be Not started and the target RNC should not initialise the variable Latest configured CN domain.
>Calculation time for ciphering related information	CV-Ciphering			Time when the ciphering information of the message were calculated, relative to a cell of the target RNC
>>Cell Identity	MP		Cell Identity	Identity of one of the cells

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
			10.3.2.2	under the target RNC and included in the active set of the current call
>>SFN	MP		Integer(0..4095)	
>COUNT-C list	OP	1 to <maxCNdomains>		COUNT-C values for radio bearers using transparent mode RLC
>>CN domain identity	MP		CN domain identity 10.3.1.1	
>>COUNT-C	MP		Bit string(32)	
>Ciphering info per radio bearer	OP	1 to <maxRB>		For signalling radio bearers this IE is mandatory.
>>RB identity	MP		RB identity 10.3.4.16	
>>Downlink HFN	MP		Bit string(20..25)	This IE is either RLC AM HFN (20 bits) or RLC UM HFN (25 bits)
>>Downlink SN	CV-SRB1		Bit String(7)	VT(US) of RLC UM
>>Uplink HFN	MP		Bit string(20..25)	This IE is either RLC AM HFN (20 bits) or RLC UM HFN (25 bits)
<b>Integrity protection related information</b>				
>Integrity protection status	MP		Enumerated(Not started, Started)	
>Signalling radio bearer specific integrity protection information	CV-IP	4 to <maxSRBs etup>		
>>Uplink RRC HFN	MP		Bit string (28)	For each SRB, this IE corresponds to the last value used.
>>Downlink RRC HFN	MP		Bit string (28)	For each SRB, this IE corresponds to the last value used. In particular, for SRB2, this IE should not take into account the RRC message that will trigger the relocation.
>>Uplink RRC Message sequence number	MP		Integer (0..15)	For each SRB, this IE corresponds to the last value used.
>>Downlink RRC Message sequence number	MP		Integer (0..15)	For each SRB, this IE corresponds to the last value used. In particular, for SRB2, this IE should not take into account the RRC message that will trigger the relocation.
>Implementation specific parameters	OP		Bit string (1..512)	
<b>RRC IEs</b>				
<b>UE Information elements</b>				
>U-RNTI	MP		U-RNTI 10.3.3.47	
>C-RNTI	OP		C-RNTI 10.3.3.8	
>UE radio access Capability	MP		UE radio access capability 10.3.3.42	
>UE radio access capability extension	OP		UE radio access capability extension 10.3.3.42a	

<b>Information Element/Group Name</b>	<b>Need</b>	<b>Multi</b>	<b>Type and reference</b>	<b>Semantics description</b>
>Last known UE position	OP			
>>SFN	MP		Integer (0..4095)	Time when position was estimated
>>Cell ID	MP		Cell identity; 10.3.2.2	Indicates the cell, the SFN is valid for.
>>CHOICE Position estimate	MP			
>>>Ellipsoid Point			Ellipsoid Point; 10.3.8.4a	
>>>Ellipsoid point with uncertainty circle			Ellipsoid point with uncertainty circle 10.3.8.4d	
>>>Ellipsoid point with uncertainty ellipse			Ellipsoid point with uncertainty ellipse 10.3.8.4e	
>>>Ellipsoid point with altitude			Ellipsoid point with altitude 10.3.8.4b	
>>>Ellipsoid point with altitude and uncertainty ellipsoid			Ellipsoid point with altitude and uncertainty ellipsoid 10.3.8.4c	
<a href="#"><u>&gt;UE Specific Behaviour Information 2</u></a>	<a href="#"><u>OP</u></a>		<a href="#"><u>UE Specific Behaviour Information 2</u></a> <a href="#"><u>10.3.3.53</u></a>	<a href="#"><u>This IE should be included if received via the "HANDOVER TO UTRAN COMPLETE" or the "RRC CONNECTION SETUP COMPLETE" or the IE "SRNS RELOCATION INFO"</u></a>
<b>Other Information elements</b>				
>UE system specific capability	OP	1 to <maxSystemCapability>		
>>Inter-RAT UE radio access capability	MP		Inter-RAT UE radio access capability 10.3.8.7	
<b>UTRAN Mobility Information elements</b>				
>URA Identifier	OP		URA identity 10.3.2.6	
<b>CN Information Elements</b>				
>CN common GSM-MAP NAS system information	MP		NAS system information (GSM-MAP) 10.3.1.9	
>CN domain related information	OP	1 to <MaxCNdomains>		CN related information to be provided for each CN domain
>>CN domain identity	MP			
>>CN domain specific GSM-MAP NAS system info	MP		NAS system information (GSM-MAP) 10.3.1.9	
>>CN domain specific DRX cycle length coefficient	MP		CN domain specific DRX cycle length coefficient,	

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
			10.3.3.6	
<b>Measurement Related Information elements</b>				
>For each ongoing measurement reporting	OP	1 to <MaxNoOf Meas>		
>>Measurement Identity	MP		Measuremen t identity 10.3.7.48	
>>Measurement Command	MP		Measuremen t command 10.3.7.46	
>>Measurement Type	CV-Setup		Measuremen t type 10.3.7.50	
>>Measurement Reporting Mode	OP		Measuremen t reporting mode 10.3.7.49	
>>Additional Measurements list	OP		Additional measuremen ts list 10.3.7.1	
>>CHOICE Measurement	OP			
>>>Intra-frequency				
>>>>Intra-frequency cell info	OP		Intra-frequency cell info list 10.3.7.33	
>>>>Intra-frequency measurement quantity	OP		Intra-frequency measurement quantity 10.3.7.38	
>>>>Intra-frequency reporting quantity	OP		Intra-frequency reporting quantity 10.3.7.41	
>>>>Reporting cell status	OP		Reporting cell status 10.3.7.61	
>>>>Measurement validity	OP		Measuremen t validity 10.3.7.51	
>>>>CHOICE report criteria	OP			
>>>>>Intra-frequency measurement reporting criteria			Intra-frequency measurement reporting criteria 10.3.7.39	
>>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>>No reporting			NULL	
>>>>Inter-frequency				
>>>>>Inter-frequency cell info	OP		Inter-frequency cell info list 10.3.7.13	
>>>>>Inter-frequency measurement quantity	OP		Inter-frequency measurement quantity	

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
			10.3.7.18	
>>>Inter-frequency reporting quantity	OP		Inter-frequency reporting quantity 10.3.7.21	
>>>Reporting cell status	OP		Reporting cell status 10.3.7.61	
>>>Measurement validity	OP		Measurement validity 10.3.7.51	
>>>CHOICE report criteria	OP			
>>>>Inter-frequency measurement reporting criteria			Inter-frequency measurement reporting criteria 10.3.7.19	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting			NULL	
>>>Inter-RAT				
>>>Inter-RAT cell info	OP		Inter-RAT cell info list 10.3.7.23	
>>>Inter-RAT measurement quantity	OP		Inter-RAT measurement quantity 10.3.7.29	
>>>Inter-RAT reporting quantity	OP		Inter-RAT reporting quantity 10.3.7.32	
>>>Reporting cell status	OP		Reporting cell status 10.3.7.61	
>>>Measurement validity	OP		Measurement validity 10.3.7.51	
>>>CHOICE report criteria	OP			
>>>>Inter-RAT measurement reporting criteria			Inter-RAT measurement reporting criteria 10.3.7.30	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting			NULL	
>>>Traffic Volume				
>>>Traffic volume measurement Object	OP		Traffic volume measurement object 10.3.7.70	
>>>Traffic volume measurement quantity	OP		Traffic volume measurement quantity 10.3.7.71	
>>>Traffic volume reporting quantity	OP		Traffic volume	

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
			reporting quantity 10.3.7.74	
>>>CHOICE report criteria	OP			
>>>>Traffic volume measurement reporting criteria			Traffic volume measurement reporting criteria 10.3.7.72	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting			NULL	
>>>Quality				
>>>>Quality measurement Object	OP		Quality measurement object	
>>>CHOICE report criteria	OP			
>>>>Quality measurement reporting criteria			Quality measurement reporting criteria 10.3.7.58	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting			NULL	
>>>UE internal				
>>>>UE internal measurement quantity	OP		UE internal measurement quantity 10.3.7.79	
>>>>UE internal reporting quantity	OP		UE internal reporting quantity 10.3.7.82	
>>>CHOICE report criteria	OP			
>>>>UE internal measurement reporting criteria			UE internal measurement reporting criteria 10.3.7.80	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting			NULL	
>>>UE positioning				
>>>>LCS reporting quantity	OP		LCS reporting quantity 10.3.7.111	
>>>CHOICE report criteria	OP			
>>>>LCS reporting criteria			LCS reporting criteria 10.3.7.110	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting				

<b>Information Element/Group Name</b>	<b>Need</b>	<b>Multi</b>	<b>Type and reference</b>	<b>Semantics description</b>
<b>Radio Bearer Information Elements</b>				
>Predefined configuration status information	OP		Predefined configuration status information 10.3.4.5a	
>Signalling RB information list	MP	1 to <maxSRBs etup>		For each signalling radio bearer
>>Signalling RB information	MP		Signalling RB information to setup 10.3.4.24	
>RAB information list	OP	1 to <maxRABs etup>		Information for each RAB
>>RAB information	MP		RAB information to setup 10.3.4.10	
<b>Transport Channel Information Elements</b>				
<b>Uplink transport channels</b>				
>UL Transport channel information common for all transport channels	OP		UL Transport channel information common for all transport channels 10.3.5.24	
>UL transport channel information list	OP	1 to <MaxTrCH >		
>>UL transport channel information	MP		Added or reconfigured UL TrCH information 10.3.5.2	
>CHOICE mode	OP			
>>FDD				
>>>CPCH set ID	OP		CPCH set ID 10.3.5.5	
>>>Transport channel information for DRAC list	OP	1 to <MaxTrCH >		
>>>>DRAC static information	MP		DRAC static information 10.3.5.7	
>>TDD				(no data)
<b>Downlink transport channels</b>				
>DL Transport channel information common for all transport channels	OP		DL Transport channel information common for all transport channels 10.3.5.6	
>DL transport channel information list	OP	1 to <MaxTrCH >		
>>DL transport channel information	MP		Added or reconfigured DL TrCH information	

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
			10.3.5.1	
>Measurement report	OP		MEASUREMENT REPORT 10.2.17	
<b>Other Information elements</b>				
Failure cause	OP		Failure cause 10.3.3.13	Diagnostics information related to an earlier SRNC Relocation request (see NOTE 2 in 14.12.0a)
Protocol error information	CV-ProtErr		Protocol error information 10.3.8.12	

Multi Bound	Explanation
MaxNumberOfMeas	Maximum number of active measurements, upper limit 16

Condition	Explanation
Setup	The IE is mandatory present when the IE Measurement command has the value "Setup", otherwise the IE is not needed.
Ciphering	The IE is mandatory present when the IE Ciphering Status has the value "started" and the ciphering counters need not be reinitialised, otherwise the IE is not needed.
IP	The IE is mandatory present when the IE Integrity protection status has the value "started" and the integrity protection counters need not be reinitialised, otherwise the IE is not needed.
ProtErr	This IE is mandatory present if the IE "Protocol error indicator" is included and has the value "TRUE". Otherwise it is not needed.
SRB1	The IE is mandatory present for RB1. Otherwise it is not needed.

## CHANGE REQUEST

⌘ 25.331 CR 1762 ⌘ rev 1 ⌘ Current version: 4.7.0 ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

**Proposed change affects:** UICC apps ⌘ ME  Radio Access Network  Core Network ⌘

<b>Title:</b>	⌘ Early UE Specific Behaviour Information in Handover Complete / Setup Complete	
<b>Source:</b>	⌘ Alcatel, Fujitsu, Motorola, NEC, Orange, Siemens	
<b>Work item code:</b>	⌘ TEI	<b>Date:</b> ⌘ 05/11/2002
<b>Category:</b>	⌘ <b>B</b> Use one of the following categories: <b>F</b> (correction) <b>A</b> (corresponds to a correction in an earlier release) <b>B</b> (addition of feature), <b>C</b> (functional modification of feature) <b>D</b> (editorial modification) Detailed explanations of the above categories can be found in 3GPP <a href="#">TR 21.900</a> .	<b>Release:</b> ⌘ Rel-4 Use one of the following releases: 2 (GSM Phase 2) R96 (Release 1996) R97 (Release 1997) R98 (Release 1998) R99 (Release 1999) Rel-4 (Release 4) Rel-5 (Release 5) Rel-6 (Release 6)

<b>Reason for change:</b>	⌘ It is currently not possible to identify and handle faulty UE implementations
<b>Summary of change:</b>	⌘ A transparent container “UE Specific Behaviour Information 2” is added to early messages at call setup and to the appropriate messages for SRNS relocation, i.e. to the following messages:  RRC Connection Setup Complete, Handover to UTRAN Complete, SRNS Relocation Info,  If UTRAN implements the CR but UE doesn't: - No impact. The RNC might not be able to adapt to specific UE behavior.  If UE implements the CR but UTRAN doesn't: - No impact. UTRAN will ignore the unknown extension and treat all UEs in the same way  If neither UE nor UTRAN implement the CR: - No impact.
<b>Consequences if not approved:</b>	⌘ Errors discovered in UEs can not be handled appropriately

<b>Clauses affected:</b>	⌘ 8.1.3.6, 8.3.6.3, 10.2.16b, 10.2.41, 10.3.3.53 (new), 11.2, 11.3, 11.5, 14.12.4.2										
<b>Other specs affected:</b>	⌘ <table border="1" style="display: inline-table; vertical-align: middle;"><tr><td>Y</td><td>N</td></tr><tr><td>X</td><td></td></tr><tr><td>X</td><td>Other core specifications</td></tr><tr><td>X</td><td>Test specifications</td></tr><tr><td>X</td><td>O&amp;M Specifications</td></tr></table>	Y	N	X		X	Other core specifications	X	Test specifications	X	O&M Specifications
Y	N										
X											
X	Other core specifications										
X	Test specifications										
X	O&M Specifications										

**Other comments:** ☰

**How to create CRs using this form:**

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>. Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ☰ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

### 8.1.3.6 Reception of an RRC CONNECTION SETUP message by the UE

The UE shall compare the value of the IE "Initial UE identity" in the received RRC CONNECTION SETUP message with the value of the variable INITIAL\_UE\_IDENTITY.

If the values are different, the UE shall:

- 1> ignore the rest of the message.

If the values are identical, the UE shall:

- 1> stop timer T300, and act upon all received information elements as specified in subclause 8.6, unless specified otherwise in the following:

- 2> if the UE will be in the CELL\_FACH state at the conclusion of this procedure:

- 3> if the IE "Frequency info" is included:

- 4> select a suitable UTRA cell according to [4] on that frequency;

- 3> select PRACH according to subclause 8.5.17;

- 3> select Secondary CCPCH according to subclause 8.5.19;

- 3> ignore the IE "UTRAN DRX cycle length coefficient" and stop using DRX.

- 1> if the UE will be in the CELL\_DCH state at the conclusion of this procedure:

- 2> perform the physical layer synchronisation procedure A as specified in [29] (FDD only).

- 1> enter UTRA RRC connected mode, in a state according to subclause 8.6.3.3;

- 1> submit an RRC CONNECTION SETUP COMPLETE message to the lower layers on the uplink DCCH after successful state transition per subclause 8.6.3.3, with the contents set as specified below:

- 2> set the IE "RRC transaction identifier" to:

- 3> the value of "RRC transaction identifier" in the entry for the RRC CONNECTION SETUP message in the table "Accepted transactions" in the variable TRANSACTIONS; and

- 3> clear that entry.

#### [2> set IE "UE Specific Behaviour Information 2" to "No UE Specific Behaviour Information 2";](#)

- 2> if the USIM or SIM is present:

- 3> set the "START" for each CN domain in the IE "START list" in the RRC CONNECTION SETUP COMPLETE message with the corresponding START value that is stored in the USIM [50] if present, or as stored in the UE if the SIM is present; and then

- 3> set the START value stored in the USIM [50] if present, and as stored in the UE if the SIM is present for any CN domain to the value "THRESHOLD" of the variable START\_THRESHOLD.

- 2> if neither the USIM nor SIM is present:

- 3> set the "START" for each CN domain in the IE "START list" in the RRC CONNECTION SETUP COMPLETE message to zero;

- 3> set the value of "THRESHOLD" in the variable "START\_THRESHOLD" to the default value [40].

- 2> retrieve its UTRA UE radio access capability information elements from variable UE\_CAPABILITY\_REQUESTED; and then

- 2> include this in IE "UE radio access capability" and IE "UE radio access capability extension", provided this IE is included in variable UE\_CAPABILITY\_REQUESTED;

- 2> retrieve its inter-RAT-specific UE radio access capability information elements from variable UE\_CAPABILITY\_REQUESTED; and then

2> include this in IE "UE system specific capability".

When the RRC CONNECTION SETUP COMPLETE message has been submitted to lower layers for transmission the UE shall:

1> if the UE has entered CELL\_FACH state:

2> start timer T305 using its initial value if periodical update has been configured by T305 in the IE "UE Timers and constants in connected mode" set to any other value than "infinity" in the variable TIMERS\_AND\_CONSTANTS.

1> store the contents of the variable UE\_CAPABILITY\_REQUESTED in the variable UE\_CAPABILITY\_TRANSFERRED;

1> initialise variables upon entering UTRA RRC connected mode as specified in subclause 13.4;

1> consider the procedure to be successful;

And the procedure ends.

### 8.3.6.3 Reception of HANOVER TO UTRAN COMMAND message by the UE

The UE shall be able to receive a HANOVER TO UTRAN COMMAND message and perform an inter-RAT handover, even if no prior UE measurements have been performed on the target UTRAN cell and/or frequency.

The UE shall act upon all received information elements as specified in subclause 8.6, unless specified otherwise in the following.

The UE may:

1> maintain a list of the set of cells to which the UE has Radio Links if the IE "Cell ID" is present.

The UE shall:

1> store a U-RNTI value (32 bits), which is derived by the IEs "SRNC identity" (12 bits) and "S-RNTI 2" (10 bits) included in IE "U-RNTI-short". In order to produce a full size U-RNTI value, a full size "S-RNTI" (20 bits) shall be derived by padding the IE "S-RNTI 2" with 10 zero bits in the most significant positions; and

1> initialise the variable ESTABLISHED\_SIGNALLING\_CONNECTIONS with the signalling connections that remains after the handover according to the specifications of the source RAT;

1> initialise the variable UE\_CAPABILITIES\_TRANSFERRED with the UE capabilities that have been transferred to the network up to the point prior to the handover, if any;

1> initialise the variable TIMERS\_AND\_CONSTANTS to the default values and start to use those timer and constants values;

1> if IE "Specification mode" is set to "Preconfiguration" and IE "Preconfiguration mode" is set to "Predefined configuration":

2> initiate the radio bearer and transport channel configuration in accordance with the predefined parameters identified by the IE "Predefined configuration identity";

2> initiate the physical channels in accordance with the predefined parameters identified by the IE "Predefined radio configuration identity" and the received physical channel information elements;

2> store information about the established radio access bearers and radio bearers according to the IE "Predefined configuration identity"; and

2> set the IE "RAB Info Post" in the variable ESTABLISHED\_RABS and the IE "Re-establishment timer" in the IE "RAB Info" in the variable ESTABLISHED\_RABS to "useT314".

1> if IE "Specification mode" is set to "Preconfiguration" and IE "Preconfiguration mode" is set to "Default configuration":

- 2> initiate the radio bearer and transport channel configuration in accordance with the default parameters identified by the IE "Default configuration mode" and IE "Default configuration identity";
- 2> initiate the physical channels in accordance with the default parameters identified by the IE "Default configuration mode" and IE "Default configuration identity" and the received physical channel information elements;

NOTE: IE "Default configuration mode" specifies whether the FDD or TDD version of the default configuration shall be used.

- 2> set the IE "RAB Info Post" in the variable ESTABLISHED\_RABS and the IE "Re-establishment timer" in the IE "RAB Info" in the variable ESTABLISHED\_RABS to "useT314".

1> if IE "Specification mode" is set to "Preconfiguration":

- 2> use the following values for parameters that are neither signalled within the HANOVER TO UTRAN COMMAND message nor included within pre-defined or default configuration:

3> 0 dB for the power offset  $P_{\text{Pilot-DPDCH}}$  bearer in FDD;

3> calculate the Default DPCH Offset Value using the following formula:

3> in FDD:

$$\text{Default DPCH Offset Value} = (\text{SRNTI } 2 \bmod 600) * 512$$

3> in TDD:

$$\text{Default DPCH Offset Value} = (\text{SRNTI } 2 \bmod 7)$$

3> handle the above Default DPCH Offset Value as if an IE with that value was included in the message, as specified in subclause 8.6.6.21.

1> if IE "Specification mode" is set to "Complete specification":

- 2> initiate the radio bearer, transport channel and physical channel configuration in accordance with the received radio bearer, transport channel and physical channel information elements.

1> perform an open loop estimation to determine the UL transmission power according to subclause 8.5.3;

1> set the IE "START" for each CN domain, in the IE "START list" in the HANOVER TO UTRAN COMPLETE message equal to the START value for each CN domain stored in the USIM if the USIM is present, or as stored in the UE for each CN domain if the SIM is present;

1> if ciphering has been activated and ongoing in the radio access technology from which inter-RAT handover is performed:

- 2> for the CN domain included in the IE "CN domain identity" which is included in the IE "RAB info" of the IE "RAB information to setup", or the CS domain when these IEs are not present:

3> set the variable LATEST\_CONFIGURED\_CN\_DOMAIN to the value indicated in the IE "CN domain identity", or to the CS domain when this IE is not present;

3> set the 20 MSB of the HFN component of the COUNT-C variable for all radio bearers using RLC-TM and all signalling radio bearers to the "START" value included in the IE "UE security information" in the variable "INTER\_RAT\_HANOVER\_INFO\_TRANSFERRED";

3> set the remaining LSBs of the HFN component of COUNT-C for all radio bearers using RLC-TM and all signalling radio bearers to zero;

3> not increment the HFN component of COUNT-C for radio bearers using RLC-TM, i.e. keep the HFN value fixed without incrementing every CFN cycle;

3> set the CFN component of the COUNT-C variable to the value of the CFN as calculated in subclause 8.5.15;

3> set the IE "Status" in the variable CIPHERING\_STATUS to "Started";

3> apply the algorithm according to IE "Ciphering Algorithm" and apply ciphering immediately upon reception of the HANOVER TO UTRAN COMMAND.

1> if ciphering has not been activated and ongoing in the radio access technology from which inter-RAT handover is performed:

2> for the CN domain included in the IE "CN domain identity" which is included in the IE "RAB info" of the IE "RAB information to setup", or the CS domain when these IEs are not present:

3> set the IE "Status" in the variable CIPHERING\_STATUS to "Not Started".

If the UE succeeds in establishing the connection to UTRAN, it shall:

1> if the IE "Status" in the variable CIPHERING\_STATUS of a CN domain is set to "Started" and transparent mode radio bearers have been established by this procedure for that CN domain:

2> include the IE "COUNT-C activation time" in the response message and specify a CFN value other than the default, "Now" for this IE;

2> at the CFN value as indicated in the response message in the IE "COUNT-C activation time" for radio bearers using RLC-TM:

3> set the 20 MSB of the HFN component of the COUNT-C variable common for all transparent mode radio bearers of this CN domain to the START value as indicated in the IE "START list" of the response message for the relevant CN domain; and

3> set the remaining LSBs of the HFN component of COUNT-C to zero;

3> increment the HFN component of the COUNT-C variable by one;

3> set the CFN component of the COUNT-C to the value of the IE "COUNT-C activation time" of the response message. The HFN component and the CFN component completely initialise the COUNT-C variable;

3> step the COUNT-C variable, as normal, at each CFN value. The HFN component is no longer fixed in value but incremented at each CFN cycle.

1> if the IE "Status" in the variable CIPHERING\_STATUS of a CN domain is set to "Not Started" and transparent mode radio bearers have been established by this procedure for that CN domain:

2> initialise the 20 MSB of the HFN component of COUNT-C common for all transparent mode radio bearers of this CN domain with the START value as indicated in the IE "START list" of the response message for the relevant CN domain;

2> set the remaining LSBs of the HFN component of COUNT-C to zero;

2> do not increment the COUNT-C value common for all transparent mode radio bearers for this CN domain.

1> transmit a HANOVER TO UTRAN COMPLETE message on the uplink DCCH, using, if ciphering has been started, the new ciphering configuration; and

1> set IE "UE Specific Behaviour Information 2" to "No UE Specific Behaviour Information 2";

1> when the HANOVER TO UTRAN COMPLETE message has been submitted to lower layers for transmission:

2> enter UTRA RRC connected mode in state CELL\_DCH;

2> initialise variables upon entering UTRA RRC connected mode as specified in subclause 13.4;

2> for all radio bearers using RLC-AM or RLC-UM:

3> set the 20 MSB of the HFN component of the uplink and downlink COUNT-C variable to the START value indicated in the IE "START list" of the response message for the relevant CN domain; and

3> set the remaining LSBs of the HFN component of COUNT-C to zero;

3> increment the HFN component of the COUNT-C variable by one;

3> start incrementing the COUNT-C values.

1> and the procedure ends.

## 10.2.16b HANDOVER TO UTRAN COMPLETE

This message is sent by the UE when a handover to UTRAN has been completed.

RLC-SAP: AM

Logical channel: DCCH

Direction: UE → UTRAN

Information Element/Group name	Need	Multi	Type and reference	Semantics description
Message Type	MP		Message Type	
<b>UE Information elements</b>				
START list	CH	1 to <maxCNdomains>		START [40] values for all CN domains.
>CN domain identity	MP		CN domain identity 10.3.1.1	
>START	MP		START 10.3.3.38	
<a href="#"><u>&gt;UE Specific Behaviour Information 2</u></a>	<a href="#"><u>MP</u></a>		<a href="#"><u>UE Specific Behaviour Information 2</u></a> 10.3.3.53	
<b>RB Information elements</b>				
COUNT-C activation time	OP		Activation time 10.3.3.1	Used for radio bearers mapped on RLC-TM.

## 10.2.41 RRC CONNECTION SETUP COMPLETE

This message confirms the establishment of the RRC Connection by the UE.

RLC-SAP: AM

Logical channel: DCCH

Direction: UE → UTRAN

Information Element/Group name	Need	Multi	Type and reference	Semantics description
Message Type	MP		Message Type	
<b>UE Information Elements</b>				
RRC transaction identifier	MP		RRC transaction identifier 10.3.3.36	
START list	MP	1 to <maxCNdomains>		START [40] values for all CN domains.
>CN domain identity	MP		CN domain identity 10.3.1.1	
>START	MP		START 10.3.3.38	START value to be used in this CN domain.
UE radio access capability	OP		UE radio access capability	

<b>Information Element/Group name</b>	<b>Need</b>	<b>Multi</b>	<b>Type and reference</b>	<b>Semantics description</b>
			10.3.3.42	
UE radio access capability extension	OP		UE radio access capability extension 10.3.3.42a	
<a href="#">&gt;UE Specific Behaviour Information 2</a>	<a href="#">MP</a>		<a href="#">UE Specific Behaviour Information 2</a> <a href="#">10.3.3.53</a>	
<b>Other information elements</b>				
UE system specific capability	OP	1 to <maxInter SysMessages>		
>Inter-RAT UE radio access capability	MP		Inter-RAT UE radio access capability 10.3.8.7	

### [10.3.3.53 UE Specific Behaviour Information 2](#)

This IE indicates the UE conformance.

<b>Information Element/Group name</b>	<b>Need</b>	<b>Multi</b>	<b>Type and Reference</b>	<b>Semantics description</b>
<a href="#">CHOICE UE Specific Behaviour Information 2</a>	<a href="#">MP</a>			<a href="#">In this version of the specification the UE should set this IE to "No UE Specific Behaviour Information 2"</a>
<a href="#">&gt;No UE Specific Behaviour Information 2</a>	<a href="#">MP</a>			<a href="#">(no data)</a>
<a href="#">&gt;UE Specific Behaviour Information 2 fixed</a>	<a href="#">MP</a>		<a href="#">bit string(16)</a>	
<a href="#">&gt;UE Specific Behaviour Information 2 variable</a>	<a href="#">MP</a>		<a href="#">bit string(1..256)</a>	

## 11.2 PDU definitions

```
--*****
-- TABULAR: The message type and integrity check info are not
-- visible in this module as they are defined in the class module.
-- Also, all FDD/TDD specific choices have the FDD option first
-- and TDD second, just for consistency.
--*****
```

PDU-definitions DEFINITIONS AUTOMATIC TAGS ::=

BEGIN

```
--*****
-- IE parameter types from other modules
--*****
```

IMPORTS

```
-- Core Network IEs :
CN-DomainIdentity,
CN-InformationInfo,
CN-InformationInfoFull,
```

```

NAS-Message,
PagingRecordTypeID,
-- UTRAN Mobility IEs :
CellIdentity,
CellIdentity-PerRL-List,
URA-Identity,
-- User Equipment IEs :
ActivationTime,
C-RNTI,
CapabilityUpdateRequirement,
CapabilityUpdateRequirement-r4,
CapabilityUpdateRequirement-r4-ext,
CellUpdateCause,
CipheringAlgorithm,
CipheringModeInfo,
DSCH-RNTI,
EstablishmentCause,
FailureCauseWithProtErr,
FailureCauseWithProtErrTrId,
UESpecificBehaviourInformation2,
InitialUE-Identity,
IntegrityProtActivationInfo,
IntegrityProtectionModeInfo,
N-308,
PagingCause,
PagingRecordList,
ProtocolErrorIndicator,
ProtocolErrorIndicatorWithMoreInfo,
Rb-timer-indicator,
RedirectionInfo,
RejectionCause,
ReleaseCause,
RRC-StateIndicator,
RRC-TransactionIdentifier,
SecurityCapability,
START-Value,
STARTList,
U-RNTI,
U-RNTI-Short,
UE-RadioAccessCapability,
UE-RadioAccessCapability-r4-ext,
UE-RadioAccessCapability-v370ext,
UE-RadioAccessCapability-v380ext,
UE-RadioAccessCapability-v3a0ext,
UE-RadioAccessCapability-v4xyext,
DL-PhysChCapabilityFDD-v380ext,
UE-ConnTimersAndConstants,
UE-ConnTimersAndConstants-v3a0ext,
UE-SecurityInformation,
URA-UpdateCause,
UTRAN-DRX-CycleLengthCoefficient,
WaitTime,
-- Radio Bearer IEs :
DefaultConfigIdentity,
DefaultConfigIdentity-r4,
DefaultConfigMode,
DL-CounterSynchronisationInfo,
PredefinedConfigIdentity,
PredefinedConfigStatusList,
RAB-Info,
RAB-Info-Post,
RAB-InformationList,
RAB-InformationReconfigList,
RAB-InformationSetupList,
RAB-InformationSetupList-r4,
RB-ActivationTimeInfoList,
RB-COUNT-C-InformationList,
RB-COUNT-C-MSB-InformationList,
RB-IdentityList,
RB-InformationAffectedList,
RB-InformationReconfigList,
RB-InformationReconfigList-r4,
RB-InformationReleaseList,
SRB-InformationSetupList,
SRB-InformationSetupList2,
UL-CounterSynchronisationInfo,
-- Transport Channel IEs:
CPCH-SetID,
DL-AddReconfTransChInfo2List,

```

```

DL-AddReconfTransChInfoList,
DL-AddReconfTransChInfoList-r4,
DL-CommonTransChInfo,
DL-CommonTransChInfo-r4,
DL-DeletedTransChInfoList,
DRAC-StaticInformationList,
TFC-Subset,
TFCS-Identity,
UL-AddReconfTransChInfoList,
UL-CommonTransChInfo,
UL-CommonTransChInfo-r4,
UL-DeletedTransChInfoList,
-- Physical Channel IEs :
Alpha,
CCTrCH-PowerControlInfo,
CCTrCH-PowerControlInfo-r4,
ConstantValue,
ConstantValueTdd,
CPCH-SetInfo,
DL-CommonInformation,
DL-CommonInformation-r4,
DL-CommonInformationPost,
DL-InformationPerRL,
DL-InformationPerRL-List,
DL-InformationPerRL-List-r4,
DL-InformationPerRL-ListPostFDD,
DL-InformationPerRL-PostTDD,
DL-InformationPerRL-PostTDD-LCR-r4,
DL-PDSCH-Information,
DPCH-CompressedModeStatusInfo,
FrequencyInfo,
FrequencyInfoFDD,
FrequencyInfoTDD,
MaxAllowedUL-TX-Power,
OpenLoopPowerControl-IPDL-TDD-r4,
PDSCH-CapacityAllocationInfo,
PDSCH-CapacityAllocationInfo-r4,
PDSCH-Identity,
PrimaryCCPCH-TX-Power,
PUSCH-CapacityAllocationInfo,
PUSCH-CapacityAllocationInfo-r4,
PUSCH-Identity,
RL-AdditionInformationList,
RL-RemovalInformationList,
SpecialBurstScheduling,
SSDT-Information,
TFC-ControlDuration,
SSDT-UL-r4,
TimeslotList,
TimeslotList-r4,
TX-DiversityMode,
UL-ChannelRequirement,
UL-ChannelRequirement-r4,
UL-ChannelRequirementWithCPCH-SetID,
UL-ChannelRequirementWithCPCH-SetID-r4,
UL-DPCH-Info,
UL-DPCH-Info-r4,
UL-DPCH-InfoPostFDD,
UL-DPCH-InfoPostTDD,
UL-DPCH-InfoPostTDD-LCR-r4,
UL-SynchronisationParameters-r4,
UL-TimingAdvance,
UL-TimingAdvanceControl,
UL-TimingAdvanceControl-r4,
-- Measurement IEs :
AdditionalMeasurementID-List,
Frequency-Band,
EventResults,
InterFreqEventResults-LCR-r4-ext,
InterRAT-TargetCellDescription,
MeasuredResults,
MeasuredResults-v390ext,
MeasuredResultsList,
MeasuredResultsList-LCR-r4-ext,
MeasuredResultsOnRACH,
MeasurementCommand,
MeasurementCommand-r4,
MeasurementIdentity,
MeasurementReportingMode,

```

```

PrimaryCCPCH-RSCP,
SFN-Offset-Validity,
TimeslotListWithISCP,
TrafficVolumeMeasuredResultsList,
UE-Positioning-GPS-AssistanceData,
UE-Positioning-Measurement-v390ext,
UE-Positioning-OTDOA-AssistanceData,
UE-Positioning-OTDOA-AssistanceData-r4ext,
UE-Positioning-OTDOA-AssistanceData-UEB,
UE-Positioning-IPDL-Parameters-TDD-r4-ext,
-- Other IEs :
BCCH-ModificationInfo,
CDMA2000-MessageList,
GSM-MessageList,
InterRAT-ChangeFailureCause,
InterRAT-HO-FailureCause,
InterRAT-UE-RadioAccessCapabilityList,
InterRAT-UE-SecurityCapList,
IntraDomainNasNodeSelector,
ProtocolErrorMoreInformation,
Rplmn-Information,
Rplmn-Information-r4,
SegCount,
SegmentIndex,
SFN-Prime,
SIB-Data-fixed,
SIB-Data-variable,
SIB-Type
FROM InformationElements

maxSIBperMsg
FROM Constant-definitions;

-- *****
-- 
-- HANOVER TO UTRAN COMPLETE
-- 
-- *****

HandoverToUTRANComplete ::= SEQUENCE {
    --TABULAR: Integrity protection shall not be performed on this message.
    -- User equipment IEs
    -- TABULAR: startList is conditional on history.
        startList                      STARTList                  OPTIONAL,
    -- Radio bearer IEs
        count-C-ActivationTime          ActivationTime           OPTIONAL,
    -- Non critical Extensions
        v480NonCriticalExtensions     SEQUENCE {
            handoverToUTRANComplete-v480ext HandoverToUTRANComplete-v480ext-IEs,
            -- Reserved for future non critical extension
            nonCriticalExtensions       SEQUENCE {} OPTIONAL
        } OPTIONAL
    -- Extension mechanism for non release99 information
    -- nonCriticalExtensions        SEQUENCE {} OPTIONAL
}

HandoverToUTRANComplete-v480ext-IEs ::= SEQUENCE {
    -- User equipment IEs
        uESpecificBehaviourInformation2 UESpecificBehaviourInformation2
}

-- *****
-- 
-- INITIAL DIRECT TRANSFER
-- 
-- *****

InitialDirectTransfer ::= SEQUENCE {
    -- Core network IEs
        cn-DomainIdentity,           CN-DomainIdentity,
        intraDomainNasNodeSelector   IntraDomainNasNodeSelector,
        nas-Message                 NAS-Message,
    -- Measurement IEs
        measuredResultsOnRACH        MeasuredResultsOnRACH      OPTIONAL,
        v3a0NonCriticalExtensions   SEQUENCE {
            initialDirectTransfer-v3a0ext InitialDirectTransfer-v3a0ext,
            -- Extension mechanism for non- release99 information

```

```

        nonCriticalExtensions           SEQUENCE {}      OPTIONAL
    }
}

InitialDirectTransfer-v3a0ext ::= SEQUENCE {
    -- start-value shall always be included in this version of the protocol
    start-Value                      START-Value      OPTIONAL
}

-- ****
-- 
-- HANOVER FROM UTRAN COMMAND
-- 
-- ****

HandoverFromUTRANCommand-GSM ::= CHOICE {
    r3      SEQUENCE {
        handoverFromUTRANCommand-GSM-r3
            HandoverFromUTRANCommand-GSM-r3-IEs,
            -- UTRAN should not include the IE nonCriticalExtensions when it sets
            -- the IE gsm-message included in handoverFromUTRANCommand-GSM-r3 to single-GSM-Message
            -- The UE behaviour upon receiving a message including this combination of IE values is
            -- not specified
        nonCriticalExtensions       SEQUENCE {} OPTIONAL
    },
    later-than-r3        SEQUENCE {
        rrc-TransactionIdentifier   RRC-TransactionIdentifier,
        criticalExtensions         SEQUENCE {}
    }
}

HandoverFromUTRANCommand-GSM-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
        rrc-TransactionIdentifier   RRC-TransactionIdentifier,
        activationTime               ActivationTime      OPTIONAL,
    -- Radio bearer IEs
        toHandover-Info             RAB-Info          OPTIONAL,
    -- Measurement IEs
        frequency-band              Frequency-Band,
    -- Other IEs
        gsm-message                 CHOICE {
            -- In the single-GSM-Message case the following rules apply:
            -- 1> the GSM message directly follows the basic production; the final padding that
            -- results when PER encoding the abstract syntax value is removed prior to appending
            -- the GSM message.
            -- 2> the RRC message excluding the GSM part, does not contain a length determinant;
            -- there is no explicit parameter indicating the size of the included GSM message.
            -- 3> depending on need, final padding (all "0"s) is added to ensure the final result
            -- comprises a full number of octets
            single-GSM-Message          SEQUENCE {},
            gsm-MessageList             SEQUENCE {
                gsm-Messages             GSM-MessageList
            }
        }
}

HandoverFromUTRANCommand-CDMA2000 ::= CHOICE {
    r3      SEQUENCE {
        handoverFromUTRANCommand-CDMA2000-r3
            HandoverFromUTRANCommand-CDMA2000-r3-IEs,
        nonCriticalExtensions       SEQUENCE {} OPTIONAL
    },
    later-than-r3        SEQUENCE {
        rrc-TransactionIdentifier   RRC-TransactionIdentifier,
        criticalExtensions         SEQUENCE {}
    }
}

HandoverFromUTRANCommand-CDMA2000-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
        rrc-TransactionIdentifier   RRC-TransactionIdentifier,
        activationTime               ActivationTime      OPTIONAL,
    -- Radio bearer IEs
        toHandover-Info             RAB-Info          OPTIONAL,
    -- Other IEs
        cdma2000-MessageList        CDMA2000-MessageList
}

```

```

-- ****
-- 
-- HANOVER FROM UTRAN FAILURE
-- 
-- ****

HandoverFromUTRANFailure ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    -- Other IEs
    interRAT-HO-FailureCause      InterRAT-HO-FailureCause          OPTIONAL,
    interRATMessage                CHOICE {
        gsm                      SEQUENCE {
            gsm-MessageList           GSM-MessageList
        },
        cdma2000                  SEQUENCE {
            cdma2000-MessageList     CDMA2000-MessageList
        }
    }                                OPTIONAL,
    -- Extension mechanism for non- release99 information
    nonCriticalExtensions         SEQUENCE {}          OPTIONAL
}

-- ****
-- 
-- INTER RAT HANOVER INFO
-- 
-- ****

InterRATHandoverInfo ::= SEQUENCE {
    -- This structure is defined for historical reasons, backward compatibility with 04.18
    predefinedConfigStatusList    CHOICE {
        absent                 NULL,
        present                PredefinedConfigStatusList
    },
    ue-SecurityInformation        CHOICE {
        absent                 NULL,
        present               UE-SecurityInformation
    },
    ue-CapabilityContainer        CHOICE {
        absent                 NULL,
        -- present is an octet aligned string containing IE UE-RadioAccessCapabilityInfo
        present               OCTET STRING (SIZE (0..63))
    },
    -- Non critical extensions
    v390NonCriticalExtensions    CHOICE {
        absent                 NULL,
        present                SEQUENCE {
            interRATHandoverInfo-v390ext   InterRATHandoverInfo-v390ext-IEs,
            v3a0NonCriticalExtensions   SEQUENCE {
                interRATHandoverInfo-v3a0ext   InterRATHandoverInfo-v3a0ext,
                v4xyNonCriticalExtensions   SEQUENCE {
                    interRATHandoverInfo-v4xyext   InterRATHandoverInfo-v4xyext-IEs,
                    -- Reserved for future non critical extension
                    nonCriticalExtensions       SEQUENCE {} OPTIONAL
                } OPTIONAL
            } OPTIONAL
        } OPTIONAL
    }
}

InterRATHandoverInfo-v390ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v380ext   UE-RadioAccessCapability-v380ext          OPTIONAL,
    dl-PhysChCapabilityFDD-v380ext    DL-PhysChCapabilityFDD-v380ext
}

InterRATHandoverInfo-v3a0ext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v3a0ext   UE-RadioAccessCapability-v3a0ext          OPTIONAL
}

InterRATHandoverInfo-v4xyext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v4xyext   UE-RadioAccessCapability-v4xyext
}

-- ****

```

```

-- RRC CONNECTION REQUEST
-- ****
RRCConnectionRequest ::= SEQUENCE {
    -- TABULAR: Integrity protection shall not be performed on this message.
    -- User equipment IEs
    initialUE-Identity           InitialUE-Identity,
    establishmentCause            EstablishmentCause,
    -- protocolErrorIndicator is MD, but for compactness reasons no default value
    -- has been assigned to it.
    protocolErrorIndicator        ProtocolErrorIndicator,
    -- Measurement IEs
    measuredResultsOnRACH         MeasuredResultsOnRACH           OPTIONAL,
    v4xyNonCriticalExtensions     SEQUENCE {
        rrcConnectionRequest-v4xyext   RRCConnectionRequest-v4xyext-IEs,
        -- Reserved for future non critical extension
        nonCriticalExtensions          SEQUENCE {}           OPTIONAL
    } OPTIONAL
}

RRCConnectionRequest-v4xyext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v4xyext   UE-RadioAccessCapability-v4xyext
}

-- ****
-- RRC CONNECTION SETUP
-- ****

RRCConnectionSetup ::= CHOICE {
    r3           SEQUENCE {
        rrcConnectionSetup-r3      RRCConnectionSetup-r3-IEs,
        v4xyNonCriticalExtensions SEQUENCE {
            rrcConnectionSetup-v4xyext   RRCConnectionSetup-v4xyext-IEs,
            -- Extension mechanism for non- release99 information
            nonCriticalExtensions       SEQUENCE {}           OPTIONAL
        } OPTIONAL
    },
    later-than-r3           SEQUENCE {
        initialUE-Identity         InitialUE-Identity,
        rrc-TransactionIdentifier  RRC-TransactionIdentifier,
        criticalExtensions         CHOICE {
            r4           SEQUENCE {
                rrcConnectionSetup-r4      RRCConnectionSetup-r4-IEs,
                nonCriticalExtensions     SEQUENCE {}           OPTIONAL
            },
            criticalExtensions        SEQUENCE {}
        }
    }
}

RRCConnectionSetup-r3-IEs ::= SEQUENCE {
    -- TABULAR: Integrity protection shall not be performed on this message.
    -- User equipment IEs
    initialUE-Identity           InitialUE-Identity,
    rrc-TransactionIdentifier    RRC-TransactionIdentifier,
    activationTime                ActivationTime           OPTIONAL,
    new-U-RNTI                   U-RNTI,
    new-c-RNTI                   C-RNTI                 OPTIONAL,
    rrc-StateIndicator           RRC-StateIndicator,
    utran-DRX-CycleLengthCoeff   UTRAN-DRX-CycleLengthCoefficient,
    -- TABULAR: If capacityUpdateRequest is not present, the default value
    -- defined in 10.3.3.2 shall be used.
    capabilityUpdateRequirement   CapabilityUpdateRequirement OPTIONAL,
    -- Radio bearer IEs
    srb-InformationSetupList     SRB-InformationSetupList2,
    -- Transport channel IEs
    ul-CommonTransChInfo         UL-CommonTransChInfo       OPTIONAL,
    -- NOTE: ul-AddReconfTransChInfoList should be optional in later versions of
    -- this message
    ul-AddReconfTransChInfoList   UL-AddReconfTransChInfoList,
    dl-CommonTransChInfo         DL-CommonTransChInfo       OPTIONAL,
    -- NOTE: dl-AddReconfTransChInfoList should be optional in later versions
    -- of this message
}

```

```

        dl-AddReconfTransChInfoList      DL-AddReconfTransChInfoList,
-- Physical channel IEs
        frequencyInfo                  FrequencyInfo
        maxAllowedUL-TX-Power        MaxAllowedUL-TX-Power
        ul-ChannelRequirement        UL-ChannelRequirement
        dl-CommonInformation         DL-CommonInformation
        dl-InformationPerRL-List     DL-InformationPerRL-List
    }

RRCConnectionSetup-v4xyext-IEs ::= SEQUENCE {
    capabilityUpdateRequirement-r4-ext  CapabilityUpdateRequirement-r4-ext  OPTIONAL,
-- Physical channel IEs
    -- ssdt-UL extends SSDT-Information, which is included in
    -- DL-CommonInformation. FDD only.
    ssdt-UL                         SSDT-UL-r4
    -- The order of the RLs in IE cell-id-PerRL-List is the same as
    -- in IE DL-InformationPerRL-List included in this message
    cell-id-PerRL-List                CellIdentity-PerRL-List
}
}

RRCConnectionSetup-r4-IEs ::= SEQUENCE {
    -- TABULAR: Integrity protection shall not be performed on this message.
    activationTime                   ActivationTime
    new-U-RNTI                      U-RNTI
    new-c-RNTI                      C-RNTI
    rrc-StateIndicator               RRC-StateIndicator
    utran-DRX-CycleLengthCoef       UTRAN-DRX-CycleLengthCoefficient
    -- TABULAR: If capabilityUpdateRequirements is not present, the default value
    -- defined in 10.3.3.2 shall be used.
    capabilityUpdateRequirement      CapabilityUpdateRequirement-r4
    -- Radio bearer IEs
    srb-InformationSetupList        SRB-InformationSetupList2,
-- Transport channel IEs
    ul-CommonTransChInfo            UL-CommonTransChInfo
    ul-AddReconfTransChInfoList     UL-AddReconfTransChInfoList
    dl-CommonTransChInfo            DL-CommonTransChInfo-r4
    dl-AddReconfTransChInfoList     DL-AddReconfTransChInfoList
-- Physical channel IEs
    frequencyInfo                  FrequencyInfo
    maxAllowedUL-TX-Power          MaxAllowedUL-TX-Power
    ul-ChannelRequirement          UL-ChannelRequirement-r4
    dl-CommonInformation           DL-CommonInformation-r4
    dl-InformationPerRL-List        DL-InformationPerRL-List-r4
}

-- ****
-- RRC CONNECTION SETUP COMPLETE
-- ****

RRCConnectionSetupComplete ::= SEQUENCE {
    -- TABULAR: Integrity protection shall not be performed on this message.
    -- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    startList                      STARTList,
    ue-RadioAccessCapability       UE-RadioAccessCapability
    -- Other IEs
    ue-RATSpecificCapability      InterRAT-UE-RadioAccessCapabilityList
    -- Non critical extensions
    v370NonCriticalExtensions     SEQUENCE {
        rrcConnectionSetupComplete-v370ext  RRCConnectionSetupComplete-v370ext,
        v380NonCriticalExtensions          SEQUENCE {
            rrcConnectionSetupComplete-v380ext  RRCConnectionSetupComplete-v380ext-IEs,
            -- Reserved for future non critical extension
            v3a0NonCriticalExtensions        SEQUENCE {
                rrcConnectionSetupComplete-v3a0ext  RRCConnectionSetupComplete-v3a0ext,
                v3d0NonCriticalExtensions        SEQUENCE {
                    rRCConnectionSetupComplete-v3d0ext-IEs  RRCConnectionSetupComplete-v3d0ext-IEs,
                    v4xyNonCriticalExtensions      SEQUENCE {
                        rrcConnectionSetupComplete-v4xyext  RRCConnectionSetupComplete-v4xyext-
IES,
                        -- Reserved for future non critical extension
                        nonCriticalExtensions          SEQUENCE {}  OPTIONAL
                    }
                }
            }
        }
    }
}

```

```

}

RRCConnectionSetupComplete-v370ext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v370ext     UE-RadioAccessCapability-v370ext     OPTIONAL
}

RRCConnectionSetupComplete-v380ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v380ext     UE-RadioAccessCapability-v380ext     OPTIONAL,
    dl-PhysChCapabilityFDD-v380ext      DL-PhysChCapabilityFDD-v380ext
}

RRCConnectionSetupComplete-v3a0ext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v3a0ext     UE-RadioAccessCapability-v3a0ext     OPTIONAL
}

RRCConnectionSetupComplete-v3d0ext-IEs ::= SEQUENCE {
    -- User equipment IEs
        uESpecificBehaviourInformation2     UESpecificBehaviourInformation2
}

RRCConnectionSetupComplete-v4xyext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-r4-ext     UE-RadioAccessCapability-r4-ext     OPTIONAL
}

-- ****
-- 
-- RRC FAILURE INFO
-- 
-- ****

RRC-FailureInfo ::= CHOICE {
    r3                               SEQUENCE {
        rRC-FailureInfo-r3
        nonCriticalExtensions
    },
    criticalExtensions               SEQUENCE {}
}

RRC-FailureInfo-r3-IEs ::= SEQUENCE {
    -- Non-RRC IEs
    failureCauseWithProtErr         FailureCauseWithProtErr
}

END

```

## 11.3 Information element definitions

```

InformationElements DEFINITIONS AUTOMATIC TAGS ::=

-- ****
-- 
-- CORE NETWORK INFORMATION ELEMENTS (10.3.1)
-- 
-- ****

BEGIN

IMPORTS

    hiPDSCHidentities,
    hiPUSCHidentities,
    hiRM,
    maxAC,
    maxAdditionalMeas,
    maxASC,
    maxASCmap,
    maxASCpersist,
    maxCCTrCH,
    maxCellMeas,
    maxCellMeas-1,
    maxCNdomains,
    maxCPCHsets,
    maxDPCH-DLchan,

```

```

maxDPDCH-UL,
maxDRACclasses,
maxFACHPCH,
maxFreq,
maxFreqBandsFDD,
maxFreqBandsTDD,
maxFreqBandsGSM,
maxInterSysMessages,
maxLoCHperRLC,
maxMeasEvent,
maxMeasIntervals,
maxMeasParEvent,
maxNumCDMA2000Freqs,
maxNumFDDFreqs,
maxNumGSMFreqRanges,
maxNumTDDFreqs,
maxOtherRAT,
maxOtherRAT-16,
maxPage1,
maxPCPCH-APsig,
maxPCPCH-APsubCh,
maxPCPCH-CDsig,
maxPCPCH-CDsubCh,
maxPCPCH-SF,
maxPCPCHs,
maxPDCPAlgoType,
maxPDSCH,
maxPDSCH-TFCIgroups,
maxPRACH,
maxPRACH-FPACH,
maxPredefConfig,
maxPUSCH,
maxRABsetup,
maxRAT,
maxRB,
maxRBallRABs,
maxRBMsgOptions,
maxRBperRAB,
maxReportedGSMCells,
maxSRBsetup,
maxRL,
maxRL-1,
maxROHC-PacketSizes-r4,
maxROHC-Profile-r4,
maxSCCPCH,
maxSat,
maxSIB,
maxSIB-FACH,
maxSystemCapability,
maxTF,
maxTF-CPCH,
maxTFC,
maxTFCsub,
maxTFCI-2-Combs,
maxTGPS,
maxTrCH,
maxTrCHpreconf,
maxTS,
maxTS-1,
maxTS-LCR,
maxTS-LCR-1,
maxURA
FROM Constant-definitions;

FailureCauseWithProtErrTrId ::=      SEQUENCE {
    rrc-TransactionIdentifier,
    failureCause
    FailureCauseWithProtErr
}

GSM-Measurements ::=                  SEQUENCE {
    gsm900
    dcs1800
    gsm1900
    BOOLEAN,
    BOOLEAN,
    BOOLEAN
}

UESpecificBehaviourInformation2 ::= CHOICE {
    uESpecificBehaviourInformation2fixednotavailable      NULL,
    uESpecificBehaviourInformation2fixed                 UESpecificBehaviourInformation2fixed,
}

```

```

UESpecificBehaviourInformation2variable          UESpecificBehaviourInformation2variable,
spare                                         NULL
}

UESpecificBehaviourInformation2fixed ::= = BIT STRING (SIZE (16))
UESpecificBehaviourInformation2variable ::= = BIT STRING (SIZE (1..256))

IMSI-and-ESN-DS-41 ::=          SEQUENCE {
  imsi-DS-41           IMSI-DS-41,
  esn-DS-41            ESN-DS-41
}

IMSI-DS-41 ::=                  OCTET STRING (SIZE (5..7))

InitialPriorityDelayList ::=      SEQUENCE (SIZE (1..maxASC)) OF
                                  NS-IP

END

```

## 11.5 RRC information between network nodes

```
Internode-definitions DEFINITIONS AUTOMATIC TAGS ::=
```

```
BEGIN
```

```
IMPORTS
```

```

HandoverToUTRANCommand,
MeasurementReport,
PhysicalChannelReconfiguration,
RadioBearerReconfiguration,
RadioBearerRelease,
RadioBearerSetup,
RRC-FailureInfo-r3-IEs,
TransportChannelReconfiguration
FROM PDU-definitions

```

```

-- Core Network IEs :
CN-DomainIdentity,
CN-DomainInformationList,
CN-DomainInformationListFull,
CN-DRX-CycleLengthCoefficient,
NAS-SystemInformationGSM-MAP,
-- UTRAN Mobility IEs :
CellIdentity,
URA-Identity,
-- User Equipment IEs :
AccessStratumReleaseIndicator,
C-RNTI,
ChipRateCapability,
DL-PhysChCapabilityFDD-v380ext,
DL-PhysChCapabilityTDD,
DL-PhysChCapabilityTDD-LCR-r4,
GSM-Measurements,
FailureCauseWithProtErr,
MaxHcContextSpace,
MaxNoPhysChBitsReceived,
MaxROHC-ContextSessions-r4,
NetworkAssistedGPS-Supported,
RadioFrequencyBandTDDList,
RLC-Capability,
RRC-MessageSequenceNumber,
SecurityCapability,
SimultaneousSCCPCH-DPCH-Reception,
STARTList,
STARTSingle,
START-Value,
SupportOfDedicatedPilotsForChEstimation,
TransportChannelCapability,
TxRxFrequencySeparation,
U-RNTI,
UE-MultiModeRAT-Capability,
UE-PowerClass-v370,
UE-RadioAccessCapabBandFDDList,
UE-RadioAccessCapability,
UE-RadioAccessCapability-v370ext,

```

```

UE-RadioAccessCapability-v380ext,
UE-RadioAccessCapability-v3a0ext,
UE-RadioAccessCapability-v4xyext,
UL-PhysChCapabilityFDD,
UL-PhysChCapabilityTDD,
UL-PhysChCapabilityTDD-LCR-r4,
-- Radio Bearer IEs :
PredefinedConfigStatusList,
PredefinedConfigValueTag,
RAB-InformationSetupList,
RAB-InformationSetupList-r4,
RAB-Identity,
RB-Identity,
SRB-InformationSetupList,
-- Transport Channel IEs :
CPCH-SetID,
DL-CommonTransChInfo,
DL-CommonTransChInfo-r4,
DL-AddReconfTransChInfoList,
DL-AddReconfTransChInfoList-r4,
DRAC-StaticInformationList,
UL-CommonTransChInfo,
UL-CommonTransChInfo-r4,
UL-AddReconfTransChInfoList,
-- Measurement IEs :
MeasurementIdentity,
MeasurementReportingMode,
MeasurementType,
MeasurementType-r4,
AdditionalMeasurementID-List,
PositionEstimate,
UE-Positioning-IPDL-Parameters-TDD-r4-ext,
-- Other IEs :
InterRAT-UE-RadioAccessCapabilityList

FROM InformationElements

maxCNdomains,
maxNoOfMeas,

maxRB,
maxSRBsetup
FROM Constant-definitions
;

-- Part 1: Class definitions similar to what has been defined in 11.1 for RRC messages
-- Information that is transferred in the same direction and across the same path is grouped

-- ****
-- RRC information, to target RNC
-- ****
-- RRC Information to target RNC sent either from source RNC or from another RAT

ToTargetRNC-Container ::= CHOICE {
    interRATHandoverInfo           InterRATHandoverInfoWithInterRATCapabilities-r3,
    srncRelocation                 SRNC-RelocationInfo-r3,
    extension                      NULL
}

-- ****
-- RRC information, target RNC to source RNC
-- ****

Target-RNC-ToSourceRNC-Container ::= CHOICE {
    radioBearerSetup                RadioBearerSetup,
    radioBearerReconfiguration      RadioBearerReconfiguration,
    radioBearerRelease              RadioBearerRelease,
    transportChannelReconfiguration TransportChannelReconfiguration,
    physicalChannelReconfiguration PhysicalChannelReconfiguration,
    rrcFailureInfo                 RRC-FailureInfo-r3-IEs,
    -- IE dl-DCCHmessage consists of an octet string that includes
    -- the IE DL-DCCH-Message
    dl-DCCHmessage                 OCTET STRING,
    extension                      NULL
}

```

```

}

-- Part 2: Container definitions, similar to the PDU definitions in 11.2 for RRC messages
-- In alphabetical order

-- ****
-- Handover to UTRAN information
--
-- ****

InterRATHandoverInfoWithInterRATCapabilities-r3 ::= CHOICE {
    r3
        SEQUENCE {
            -- IE InterRATHandoverInfoWithInterRATCapabilities-r3-IEs also
            -- includes non critical extensions
            interRATHandoverInfo-r3           InterRATHandoverInfoWithInterRATCapabilities-r3-IEs,
            v390NonCriticalExtensions       SEQUENCE {
                interRATHandoverInfoWithInterRATCapabilities-v390ext
            InterRATHandoverInfoWithInterRATCapabilities-v390ext-IEs,
                -- Reserved for future non critical extension
                nonCriticalExtensions     SEQUENCE {} OPTIONAL
            }
        OPTIONAL
    },
    criticalExtensions      SEQUENCE {}
}

InterRATHandoverInfoWithInterRATCapabilities-r3-IEs ::= SEQUENCE {
    -- The order of the IEs may not reflect the tabular format
    -- but has been chosen to simplify the handling of the information in the BSC
    -- Other IEs
    ue-RATSpecificCapability      InterRAT-UE-RadioAccessCapabilityList OPTIONAL,
    -- interRATHandoverInfo, Octet string is used to obtain 8 bit length field prior to
    -- actual information. This makes it possible for BSS to transparently handle information
    -- received via GSM air interface even when it includes non critical extensions.
    -- The octet string shall include the InterRATHandoverInfo information
    -- The BSS can re-use the 04.18 length field received from the MS
    interRATHandoverInfo          OCTET STRING (SIZE (0..255))
}

InterRATHandoverInfoWithInterRATCapabilities-v390ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    failureCauseWithProtErr      FailureCauseWithProtErr
    OPTIONAL
}

-- ****
-- SRNC Relocation information
--
-- ****

SRNC-RelocationInfo-r3 ::= CHOICE {
    r3
        SEQUENCE {
            SRNC-RelocationInfo-r3           SRNC-RelocationInfo-r3-IEs,
            v380NonCriticalExtensions       SEQUENCE {
                SRNC-RelocationInfo-v380ext SRNC-RelocationInfo-v380ext-IEs,
                -- Reserved for future non critical extension
                v390NonCriticalExtensions   SEQUENCE {
                    SRNC-RelocationInfo-v390ext      SRNC-RelocationInfo-v390ext-IEs,
                    v3a0NonCriticalExtensions     SEQUENCE {
                        SRNC-RelocationInfo-v3a0ext      SRNC-RelocationInfo-v3a0ext-IEs,
                        v3b0NonCriticalExtensions   SEQUENCE {
                            SRNC-RelocationInfo-v3b0ext      SRNC-RelocationInfo-v3b0ext-IEs,
                            v3c0NonCriticalExtensions   SEQUENCE {
                                SRNC-RelocationInfo-v3c0ext      SRNC-RelocationInfo-v3c0ext-IEs,
                                v3d0NonCriticalExtensions   SEQUENCE {
                                    SRNC-RelocationInfo-v3d0ext      SRNC-RelocationInfo-v3d0ext-IEs,
                                    v4xyNonCriticalExtensions     SEQUENCE {
                                        SRNC-RelocationInfo-v4xyext      SRNC-RelocationInfo-
                                    v4xyext-IEs,
                                        -- Reserved for future non critical extension
                                        nonCriticalExtensions     SEQUENCE {} OPTIONAL
                                    }
                                }
                            }
                        }
                    }
                }
            }
        }
    }
}

```

```

},
later-than-r3
r4
    CHOICE {
        SEQUENCE {
            SRNC-RelocationInfo-r4-IES,
            SEQUENCE {} OPTIONAL
        },
        criticalExtensions
    }
}

SRNC-RelocationInfo-r3-IES ::= SEQUENCE {
    -- Non-RRC IEs
    stateOfRRC StateOfRRC,
    stateOfRRC-Procedure StateOfRRC-Procedure,
    -- Ciphering related information IEs
    -- If the extension v380 is included use the extension for the ciphering status per CN domain
    cipheringStatus CipheringStatus,
    calculationTimeForCiphering CalculationTimeForCiphering OPTIONAL,
    -- The order of occurrence in the IE cipheringInfoPerRB-List is the
    -- same as the RBs in the IE "Signalling RB information list" and in the
    -- IE "RAB information list". The signalling RBs are supposed to be listed
    -- first. Only UM and AM RBs that are ciphered are listed here
    cipheringInfoPerRB-List CipheringInfoPerRB-List OPTIONAL,
    count-C-List COUNT-C-List OPTIONAL,
    integrityProtectionStatus IntegrityProtectionStatus,
    srb-SpecificIntegrityProtInfo SRB-SpecificIntegrityProtInfoList,
    implementationSpecificParams ImplementationSpecificParams OPTIONAL,
    -- User equipment IEs
    u-RNTI U-RNTI,
    c-RNTI C-RNTI OPTIONAL,
    ue-RadioAccessCapability UE-RadioAccessCapability,
    ue-Positioning-LastKnownPos UE-Positioning-LastKnownPos OPTIONAL,
    -- Other IEs
    ue-RATSpecificCapability InterRAT-UE-RadioAccessCapabilityList OPTIONAL,
    -- UTRAN mobility IEs
    ura-Identity URA-Identity OPTIONAL,
    -- Core network IEs
    cn-CommonGSM-MAP-NAS-SysInfo NAS-SystemInformationGSM-MAP,
    cn-DomainInformationList CN-DomainInformationList OPTIONAL,
    -- Measurement IEs
    ongoingMeasRepList OngoingMeasRepList OPTIONAL,
    -- Radio bearer IEs
    predefinedConfigStatusList PredefinedConfigStatusList,
    srb-InformationList SRB-InformationSetupList,
    rab-InformationList RAB-InformationSetupList OPTIONAL,
    -- Transport channel IEs
    ul-CommonTransChInfo UL-CommonTransChInfo OPTIONAL,
    ul-TransChInfoList UL-AddReconfTransChInfoList OPTIONAL,
    modeSpecificInfo CHOICE {
        fdd SEQUENCE {
            cpch-SetID CPCH-SetID OPTIONAL,
            transChDRAC-Info DRAC-StaticInformationList OPTIONAL
        },
        tdd NULL
    },
    dl-CommonTransChInfo DL-CommonTransChInfo OPTIONAL,
    dl-TransChInfoList DL-AddReconfTransChInfoList OPTIONAL,
    -- Measurement report
    measurementReport MeasurementReport OPTIONAL ,
    nonCriticalExtensions SEQUENCE {
        -- In case of TDD only up-Ipd1-Parameters-TDD is present, otherwise
        -- this IE is absent
        up-Ipd1-Parameters-TDD UE-Positioning-IPDL-Parameters-TDD-r4-ext OPTIONAL,
        -- Extension mechanism for non- release4 information
        nonCriticalExtensions SEQUENCE {}
    }
} OPTIONAL

SRNC-RelocationInfo-v380ext-IES ::= SEQUENCE {
    -- Ciphering related information IEs
    cn-DomainIdentity CN-DomainIdentity,
    cipheringStatusList CipheringStatusList
}

SRNC-RelocationInfo-v390ext-IES ::= SEQUENCE {
    cn-DomainInformationList-v390ext CN-DomainInformationList-v390ext OPTIONAL,
    ue-RadioAccessCapability-v370ext UE-RadioAccessCapability-v370ext OPTIONAL,
    ue-RadioAccessCapability-v380ext UE-RadioAccessCapability-v380ext OPTIONAL,
    dl-PhysChCapabilityFDD-v380ext DL-PhysChCapabiliyFDD-v380ext,
}

```

```

        failureCauseWithProtErr           FailureCauseWithProtErr          OPTIONAL
    }

SRNC-RelocationInfo-v3a0ext-IEs ::= SEQUENCE {
    -- cn-domain identity for IE startValueForCiphering-v3a0ext is specified
    -- in subsequent extension (SRNC-RelocationInfo-v3b0ext-IEs)
    startValueForCIphering-v3a0ext      START-Value,
    cipheringInfoForSRB1-v3a0ext       CipheringInfoForSRB1-v3a0ext,
    ue-RadioAccessCapability-v3a0ext   UE-RadioAccessCapability-v3a0ext          OPTIONAL
}

SRNC-RelocationInfo-v3b0ext-IEs ::= SEQUENCE {
    -- cn-domain identity for IE startValueForCiphering-v3a0ext included in previous extension
    cn-DomainIdentity                 CN-DomainIdentity,
    -- the remaining start values are contained in IE startValueForCiphering-v3b0ext
    startValueForCiphering-v3b0ext     STARTList2          OPTIONAL
}

SRNC-RelocationInfo-v3c0ext-IEs ::= SEQUENCE {
    -- IE rb-IdentityForHOMessage includes the identity of the RB used by the source SRNC
    -- to send the message contained in the IE "TargetRNC-ToSourceRNC-Container".
    -- Only included if type is "UE involved"
    rb-IdentityForHOMessage           RB-Identity          OPTIONAL
}

SRNC-RelocationInfo-v3d0ext-IEs ::= SEQUENCE {
    -- User equipment IEs
        uESpecificBehaviourInformation2     UESpecificBehaviourInformation2      OPTIONAL
}

STARTList2 ::=           SEQUENCE (SIZE (2..maxCNdomains)) OF
                        STARTSingle

SRNC-RelocationInfo-v4xyext-IEs ::= SEQUENCE {
    ue-RadioAccessCapability-v4xyext   UE-RadioAccessCapability-v4xyext
}

CipheringInfoForSRB1-v3a0ext ::= SEQUENCE {
    dl-UM-SN                         BIT STRING (SIZE (7))
}

CipheringStatusList ::=           SEQUENCE (SIZE (1..maxCNdomains)) OF
                                    CipheringStatusCNdomain

CipheringStatusCNdomain ::=           SEQUENCE {
    cn-DomainIdentity                 CN-DomainIdentity,
    cipheringStatus                  CipheringStatus
}

SRNC-RelocationInfo-r4-IEs ::=           SEQUENCE {
    -- Non-RRC IEs
    -- IE rb-IdentityForHOMessage includes the identity of the RB used by the source SRNC
    -- to send the message contained in the IE "TargetRNC-ToSourceRNC-Container".
    -- Only included if type is "UE involved"
    rb-IdentityForHOMessage           RB-Identity          OPTIONAL,
    stateOfRRC                        StateOfRRC,
    stateOfRRC-Procedure              StateOfRRC-Procedure,
    -- Ciphering related information IEs
    cipheringStatusList               CipheringStatusList-r4,
    latestConfiguredCN-Domain         CN-DomainIdentity,
    calculationTimeForCiphering       CalculationTimeForCiphering          OPTIONAL,
    count-C-List                      COUNT-C-List          OPTIONAL,
    cipheringInfoPerRB-List           CipheringInfoPerRB-List-r4          OPTIONAL,
    -- Integrity protection related information IEs
    integrityProtectionStatus         IntegrityProtectionStatus,
    srb-SpecificIntegrityProtInfo   SRB-SpecificIntegrityProtInfoList,
    implementationSpecificParams      ImplementationSpecificParams          OPTIONAL,
    -- User equipment IEs
    u-RNTI                           U-RNTI,
    c-RNTI                           C-RNTI          OPTIONAL,
    ue-RadioAccessCapability          UE-RadioAccessCapability-r4,
    ue-RadioAccessCapability-ext     UE-RadioAccessCapabBandFDDList          OPTIONAL,
    ue-Positioning-LastKnownPos      UE-Positioning-LastKnownPos          OPTIONAL,
        uESpecificBehaviourInformation2     UESpecificBehaviourInformation2      OPTIONAL,
    -- Other IEs
    ue-RATSpecificCapability         InterRAT-UE-RadioAccessCapabilityList    OPTIONAL,
    -- UTRAN mobility IEs
    ura-Identity                     URA-Identity          OPTIONAL,
}

```

```

-- Core network IEs
cn-CommonGSM-MAP-NAS-SysInfo      NAS-SystemInformationGSM-MAP,
cn-DomainInformationList           CN-DomainInformationListFull          OPTIONAL,
-- Measurement IEs
ongoingMeasRepList                OngoingMeasRepList-r4                  OPTIONAL,
-- Radio bearer IEs
predefinedConfigStatusList         PredefinedConfigStatusList,
srb-InformationList               SRB-InformationSetupList,
rab-InformationList               RAB-InformationSetupList-r4          OPTIONAL,
-- Transport channel IEs
ul-CommonTransChInfo              UL-CommonTransChInfo-r4            OPTIONAL,
ul-TransChInfoList                UL-AddReconfTransChInfoList        OPTIONAL,
modeSpecificInfo
    fdd                           CHOICE {
        cpch-SetID                 SEQUENCE {
            CPCH-SetID             OPTIONAL,
            transChDRAC-Info       DRAC-StaticInformationList   OPTIONAL
        },
        tdd                           NULL
    }
dl-CommonTransChInfo              DL-CommonTransChInfo-r4            OPTIONAL,
dl-TransChInfoList                DL-AddReconfTransChInfoList        OPTIONAL,
-- Measurement report
measurementReport                 MeasurementReport                  OPTIONAL,
failureCause                      FailureCauseWithProtErr        OPTIONAL
}

-- IE definitions

CalculationTimeForCiphering ::=      SEQUENCE {
    cell-Id                     CellIdentity,
    sfn                          INTEGER (0..4095)
}

CipheringInfoPerRB ::=              SEQUENCE {
    dl-HFN                       BIT STRING (SIZE (20..25)),
    ul-HFN                       BIT STRING (SIZE (20..25))
}

CipheringInfoPerRB-r4 ::=           SEQUENCE {
    rb-Identity                  RB-Identity,
    dl-HFN                       BIT STRING (SIZE (20..25)),
    dl-UM-SN                     BIT STRING (SIZE (7))          OPTIONAL,
    ul-HFN                       BIT STRING (SIZE (20..25))
}

-- TABULAR: CipheringInfoPerRB-List, multiplicity value numberOfRadioBearers
-- has been replaced with maxRB.
CipheringInfoPerRB-List ::=         SEQUENCE (SIZE (1..maxRB)) OF
                                         CipheringInfoPerRB

CipheringInfoPerRB-List-r4 ::=       SEQUENCE (SIZE (1..maxRB)) OF
                                         CipheringInfoPerRB-r4

CipheringStatus ::=                 ENUMERATED {
    started,
    notStarted
}

CipheringStatusList-r4 ::=          SEQUENCE (SIZE (1..maxCNdomains)) OF
                                         CipheringStatusCNdomain-r4

CipheringStatusCNdomain-r4 ::=       SEQUENCE {
    cn-DomainIdentity            CN-DomainIdentity,
    cipheringStatus              CipheringStatus,
    start-Value                  START-Value
}

CN-DomainInformation-v390ext ::=     SEQUENCE {
    cn-DRX-CycleLengthCoeff     CN-DRX-CycleLengthCoefficient
}

CN-DomainInformationList-v390ext ::= SEQUENCE (SIZE (1..maxCNdomains)) OF
                                         CN-DomainInformation-v390ext

CompressedModeMeasCapability-r4 ::= SEQUENCE {
    fdd-Measurements             BOOLEAN,
    -- TABULAR: The IEs tdd-Measurements, gsm-Measurements and multiCarrierMeasurements
    -- are made optional since they are conditional based on another information element.
    -- Their absence corresponds to the case where the condition is not true.
    tdd384-Measurements          BOOLEAN                         OPTIONAL,
    tdd128-Measurements          BOOLEAN                         OPTIONAL,

```

```

gsm-Measurements          GSM-Measurements           OPTIONAL,
multiCarrierMeasurements   BOOLEAN                  OPTIONAL
}

COUNT-C-List ::=          SEQUENCE (SIZE (1..maxCNdomains)) OF
                           COUNT-CSingle

COUNT-CSingle ::=          SEQUENCE {
                           cn-DomainIdentity,
                           count-C
                           }

DL-PhysChCapabilityFDD-r4 ::= SEQUENCE {
                           maxNoDPCH-PDSCH-Codes
                           maxNoPhysChBitsReceived
                           supportForSF-512
                           supportOfPDSCH
                           simultaneousSCCPCH-DPCH-Reception
                           supportOfDedicatedPilotsForChEstimation
                           supportOfDedicatedPilotsForChEstimation
                           }
                           OPTIONAL

ImplementationSpecificParams ::= BIT STRING (SIZE (1..512))

IntegrityProtectionStatus ::= ENUMERATED {
                           started, notStarted
                           }

MeasurementCapability-r4 ::= SEQUENCE {
                           downlinkCompressedMode
                           uplinkCompressedMode
                           }

MeasurementCommandWithType ::= CHOICE {
                           setup
                           modify
                           release
                           }

MeasurementCommandWithType-r4 ::= CHOICE {
                           setup
                           modify
                           release
                           }

OngoingMeasRep ::=          SEQUENCE {
                           measurementIdentity
                           MeasurementIdentity,
                           -- TABULAR: The CHOICE Measurement in the tabular description is included
                           -- in MeasurementCommandWithType
                           measurementCommandWithType
                           MeasurementCommandWithType,
                           measurementReportingMode
                           MeasurementReportingMode
                           additionalMeasurementID-List
                           AdditionalMeasurementID-List
                           }
                           OPTIONAL,
                           OPTIONAL
}

OngoingMeasRep-r4 ::=          SEQUENCE {
                           measurementIdentity
                           MeasurementIdentity,
                           -- TABULAR: The CHOICE Measurement in the tabular description is included
                           -- in MeasurementCommandWithType-r4.
                           measurementCommandWithType
                           MeasurementCommandWithType-r4,
                           measurementReportingMode
                           MeasurementReportingMode
                           additionalMeasurementID-List
                           AdditionalMeasurementID-List
                           }
                           OPTIONAL,
                           OPTIONAL
}

OngoingMeasRepList ::=          SEQUENCE (SIZE (1..maxNoOfMeas)) OF
                           OngoingMeasRep

OngoingMeasRepList-r4 ::=          SEQUENCE (SIZE (1..maxNoOfMeas)) OF
                           OngoingMeasRep-r4

PDCP-Capability-r4 ::=          SEQUENCE {
                           losslessSRNS-RelocationSupport
                           BOOLEAN,
                           supportForRfc2507
                           CHOICE {
                           notSupported
                           NULL,
                           supported
                           MaxHcContextSpace
                           },
                           supportForRfc3095
                           CHOICE {
                           notSupported
                           NULL,
                           supported
                           SEQUENCE {
                           maxROHC-ContextSessions
                           MaxROHC-ContextSessions-r4 DEFAULT s16,
                           reverseCompressionDepth
                           INTEGER (0..65535) DEFAULT 0
                           }
                           }
                           }
                           
```

```

        }
    }

PhysicalChannelCapability-r4 ::=      SEQUENCE {
    fddPhysChCapability           SEQUENCE {
        downlinkPhysChCapability   DL-PhysChCapabilityFDD-r4,
        uplinkPhysChCapability     UL-PhysChCapabilityFDD
                                    OPTIONAL,
    }
    tdd384-PhysChCapability       SEQUENCE {
        downlinkPhysChCapability   DL-PhysChCapabilityTDD,
        uplinkPhysChCapability     UL-PhysChCapabilityTDD
                                    OPTIONAL,
    }
    tdd128-PhysChCapability       SEQUENCE {
        downlinkPhysChCapability   DL-PhysChCapabilityTDD-LCR-r4,
        uplinkPhysChCapability     UL-PhysChCapabilityTDD-LCR-r4
                                    OPTIONAL
    }
}

RF-Capability-r4 ::=                  SEQUENCE {
    fddRF-Capability            SEQUENCE {
        ue-PowerClass             UE-PowerClass-v370,
        txRxFrequencySeparation   TxRxFrequencySeparation
                                    OPTIONAL,
    }
    tdd384-RF-Capability        SEQUENCE {
        ue-PowerClass             UE-PowerClass-v370,
        radioFrequencyBandTDDList RadioFrequencyBandTDDList,
        chipRateCapability         ChipRateCapability
                                    OPTIONAL,
    }
    tdd128-RF-Capability        SEQUENCE {
        ue-PowerClass             UE-PowerClass-v370,
        radioFrequencyBandTDDList RadioFrequencyBandTDDList,
        chipRateCapability         ChipRateCapability
                                    OPTIONAL
    }
}

SRB-SpecificIntegrityProtInfo ::=    SEQUENCE {
    ul-RRC-HFN                 BIT STRING (SIZE (28)),
    dl-RRC-HFN                 BIT STRING (SIZE (28)),
    ul-RRC-SequenceNumber       RRC-MessageSequenceNumber,
    dl-RRC-SequenceNumber       RRC-MessageSequenceNumber
}

SRB-SpecificIntegrityProtInfoList ::= SEQUENCE (SIZE (4..maxSRBsetup)) OF
                                         SRB-SpecificIntegrityProtInfo

StateOfRRC ::=                      ENUMERATED {
    cell-DCH, cell-FACH,
    cell-PCH, ura-PCH }

StateOfRRC-Procedure ::=             ENUMERATED {
    awaitNoRRC-Message,
    awaitRB-ReleaseComplete,
    awaitRB-SetupComplete,
    awaitRB-ReconfigurationComplete,
    awaitTransportCH-ReconfigurationComplete,
    awaitPhysicalCH-ReconfigurationComplete,
    awaitActiveSetUpdateComplete,
    awaitHandoverComplete,
    sendCellUpdateConfirm,
    sendUraUpdateConfirm,
    -- dummy is not used in this version of specification
    -- It should not be sent
    dummy,
    otherStates
}

UE-Positioning-LastKnownPos ::=     SEQUENCE {
    sfn                         INTEGER (0..4095),
    cell-id                     CellIdentity,
    positionEstimate            PositionEstimate
}

UE-Positioning-Capability-r4 ::=    SEQUENCE {
    standaloneLocMethodsSupported BOOLEAN,
    ue-BasedOTDOA-Supported       BOOLEAN,
    networkAssistedGPS-Supported NetworkAssistedGPS-Supported,
    supportForUE-GPS-TimingOfCellFrames BOOLEAN,
    supportForIPDL                BOOLEAN,
}

```

```

rx-tx-TimeDifferenceType2Capable           BOOLEAN,
validity-CellPCH-UrapCH                   ENUMERATED { true (0) }   OPTIONAL
}

UE-RadioAccessCapability-r4 ::= SEQUENCE {
accessStratumReleaseIndicator,
pdcp-Capability,
rlc-Capability,
transportChannelCapability,
rf-Capability,
physicalChannelCapability,
ue-MultiModeRAT-Capability,
securityCapability,
ue-positioning-Capability,
measurementCapability
}
}

END

```

#### 14.12.4.2 SRNS RELOCATION INFO

This RRC message is sent between network nodes when preparing for an SRNS relocation.

With the presence or absence of the IE "RB identity for Hard Handover message" the source RNC indicates to the target SRNC whether the source RNC expects to receive the choice "DL DCCH message" in the IE "RRC information, target RNC to source RNC" in case the SRNS relocation is of type "UE involved". Furthermore the target RNC uses this information for the calculation of the MAC-I.

Direction: source RNC→target RNC

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
<b>Non RRC IEs</b>				
RB identity for Handover message	OP		RB identity 10.3.4.16	Gives the id of the radio bearer on which the source RNC will transmit the RRC message in the case the relocation is of type "UE involved".
>State of RRC	MP		RRC state indicator, 10.3.3.35a	
>State of RRC procedure	MP		Enumerated (await no RRC message, await RB Release Complete, await RB Setup Complete, await RB Reconfiguration Complete, await Transport CH Reconfiguration Complete, await Physical CH Reconfiguration Complete, await Active Set Update Complete,	

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
			await Handover Complete, send Cell Update Confirm, send URA Update Confirm, , others)	
<b>Ciphering related information</b>				
>Ciphering status for each CN domain	MP	<1 to maxCNDomains>		
>>CN domain identity	MP		CN domain identity 10.3.1.1	
>>Ciphering status	MP		Enumerated( Not started, Started)	
>>START	MP		START 10.3.3.38	START value to be used in this CN domain.
>Latest configured CN domain	MP		CN domain identity 10.3.1.1	Value contained in the variable of the same name. In case this variable is empty, the source RNC can set any CN domain identity. In that case, the Ciphering status and the Integrity protection status should be Not started and the target RNC should not initialise the variable Latest configured CN domain.
>Calculation time for ciphering related information	CV-Ciphering			Time when the ciphering information of the message were calculated, relative to a cell of the target RNC
>>Cell Identity	MP		Cell Identity 10.3.2.2	Identity of one of the cells under the target RNC and included in the active set of the current call
>>SFN	MP		Integer(0..4095)	
>COUNT-C list	OP	1 to <maxCNdomains>		COUNT-C values for radio bearers using transparent mode RLC
>>CN domain identity	MP		CN domain identity 10.3.1.1	
>>COUNT-C	MP		Bit string(32)	
>Ciphering info per radio bearer	OP	1 to <maxRB>		For signalling radio bearers this IE is mandatory.
>>RB identity	MP		RB identity 10.3.4.16	
>>Downlink HFN	MP		Bit string(20..25 )	This IE is either RLC AM HFN (20 bits) or RLC UM HFN (25 bits)
>>Downlink SN	CV-SRB1		Bit String(7)	VT(US) of RLC UM
>>Uplink HFN	MP		Bit string(20..25 )	This IE is either RLC AM HFN (20 bits) or RLC UM HFN (25 bits)
<b>Integrity protection related information</b>				
>Integrity protection status	MP		Enumerated( Not started, Started)	

<b>Information Element/Group Name</b>	<b>Need</b>	<b>Multi</b>	<b>Type and reference</b>	<b>Semantics description</b>
>Signalling radio bearer specific integrity protection information	CV-/P	4 to <maxSRBs etup>		
>>Uplink RRC HFN	MP		Bit string (28)	For each SRB, this IE corresponds to the last value used.
>>Downlink RRC HFN	MP		Bit string (28)	For each SRB, this IE corresponds to the last value used. In particular, for SRB2, this IE should not take into account the RRC message that will trigger the relocation.
>>Uplink RRC Message sequence number	MP		Integer (0..15)	For each SRB, this IE corresponds to the last value used.
>>Downlink RRC Message sequence number	MP		Integer (0..15)	For each SRB, this IE corresponds to the last value used. In particular, for SRB2, this IE should not take into account the RRC message that will trigger the relocation.
>Implementation specific parameters	OP		Bit string (1..512)	
<b>RRC IEs</b>				
<b>UE Information elements</b>				
>U-RNTI	MP		U-RNTI 10.3.3.47	
>C-RNTI	OP		C-RNTI 10.3.3.8	
>UE radio access Capability	MP		UE radio access capability 10.3.3.42	
>UE radio access capability extension	OP		UE radio access capability extension 10.3.3.42a	
>Last known UE position	OP			
>>SFN	MP		Integer (0..4095)	Time when position was estimated
>>Cell ID	MP		Cell identity; 10.3.2.2	Indicates the cell, the SFN is valid for.
>>CHOICE Position estimate	MP			
>>>Ellipsoid Point			Ellipsoid Point; 10.3.8.4a	
>>>Ellipsoid point with uncertainty circle			Ellipsoid point with uncertainty circle 10.3.8.4d	
>>>Ellipsoid point with uncertainty ellipse			Ellipsoid point with uncertainty ellipse 10.3.8.4e	
>>>Ellipsoid point with altitude			Ellipsoid point with altitude 10.3.8.4b	
>>>Ellipsoid point with altitude and uncertainty ellipsoid			Ellipsoid point with altitude and uncertainty ellipsoid	

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
			10.3.8.4c	
>UE Specific Behaviour Information 2	OP		<a href="#">UE Specific Behaviour Information 2</a> <a href="#">10.3.3.53</a>	This IE should be included if received via the "HANDOVER TO UTRAN COMPLETE" or the "RRC CONNECTION SETUP COMPLETE" or the IE "SRNS RELOCATION INFO"
<b>Other Information elements</b>				
>UE system specific capability	OP	1 to <maxSystemCapability>		
>>Inter-RAT UE radio access capability	MP		Inter-RAT UE radio access capability 10.3.8.7	
<b>UTRAN Mobility Information elements</b>				
>URA Identifier	OP		URA identity 10.3.2.6	
<b>CN Information Elements</b>				
>CN common GSM-MAP NAS system information	MP		NAS system information (GSM-MAP) 10.3.1.9	
>CN domain related information	OP	1 to <MaxCnDomains>		CN related information to be provided for each CN domain
>>CN domain identity	MP			
>>CN domain specific GSM-MAP NAS system info	MP		NAS system information (GSM-MAP) 10.3.1.9	
>>CN domain specific DRX cycle length coefficient	MP		CN domain specific DRX cycle length coefficient, 10.3.3.6	
<b>Measurement Related Information elements</b>				
>For each ongoing measurement reporting	OP	1 to <MaxNoOf Meas>		
>>Measurement Identity	MP		Measurement identity 10.3.7.48	
>>Measurement Command	MP		Measurement command 10.3.7.46	
>>Measurement Type	CV-Setup		Measurement type 10.3.7.50	
>>Measurement Reporting Mode	OP		Measurement reporting mode 10.3.7.49	
>>Additional Measurements list	OP		Additional measurements list 10.3.7.1	
>>CHOICE Measurement	OP			
>>>Intra-frequency				
>>>>Intra-frequency cell info	OP		Intra-frequency cell info list	

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
			10.3.7.33	
>>>Intra-frequency measurement quantity	OP		Intra-frequency measurement quantity 10.3.7.38	
>>>Intra-frequency reporting quantity	OP		Intra-frequency reporting quantity 10.3.7.41	
>>>Reporting cell status	OP		Reporting cell status 10.3.7.61	
>>>Measurement validity	OP		Measurement validity 10.3.7.51	
>>>CHOICE report criteria	OP			
>>>>Intra-frequency measurement reporting criteria			Intra-frequency measurement reporting criteria 10.3.7.39	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting			NULL	
>>>>Inter-frequency				
>>>>Inter-frequency cell info	OP		Inter-frequency cell info list 10.3.7.13	
>>>>Inter-frequency measurement quantity	OP		Inter-frequency measurement quantity 10.3.7.18	
>>>>Inter-frequency reporting quantity	OP		Inter-frequency reporting quantity 10.3.7.21	
>>>>Reporting cell status	OP		Reporting cell status 10.3.7.61	
>>>>Measurement validity	OP		Measurement validity 10.3.7.51	
>>>>CHOICE report criteria	OP			
>>>>Inter-frequency measurement reporting criteria			Inter-frequency measurement reporting criteria 10.3.7.19	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting			NULL	
>>>>Inter-RAT				
>>>>Inter-RAT cell info	OP		Inter-RAT cell info list 10.3.7.23	

<b>Information Element/Group Name</b>	<b>Need</b>	<b>Multi</b>	<b>Type and reference</b>	<b>Semantics description</b>
>>>Inter-RAT measurement quantity	OP		Inter-RAT measurement quantity 10.3.7.29	
>>>Inter-RAT reporting quantity	OP		Inter-RAT reporting quantity 10.3.7.32	
>>>Reporting cell status	OP		Reporting cell status 10.3.7.61	
>>>Measurement validity	OP		Measurement validity 10.3.7.51	
>>>CHOICE report criteria	OP			
>>>>Inter-RAT measurement reporting criteria			Inter-RAT measurement reporting criteria 10.3.7.30	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting			NULL	
>>>Traffic Volume				
>>>Traffic volume measurement Object	OP		Traffic volume measurement object 10.3.7.70	
>>>Traffic volume measurement quantity	OP		Traffic volume measurement quantity 10.3.7.71	
>>>Traffic volume reporting quantity	OP		Traffic volume reporting quantity 10.3.7.74	
>>>CHOICE report criteria	OP			
>>>>Traffic volume measurement reporting criteria			Traffic volume measurement reporting criteria 10.3.7.72	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting			NULL	
>>>Quality				
>>>Quality measurement Object	OP		Quality measurement object	
>>>CHOICE report criteria	OP			
>>>>Quality measurement reporting criteria			Quality measurement reporting criteria 10.3.7.58	
>>>>Periodical reporting			Periodical reporting criteria	

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
			10.3.7.53	
>>>>No reporting			NULL	
>>>UE internal				
>>>>UE internal measurement quantity	OP		UE internal measurement quantity 10.3.7.79	
>>>>UE internal reporting quantity	OP		UE internal reporting quantity 10.3.7.82	
>>>>CHOICE report criteria	OP			
>>>>UE internal measurement reporting criteria			UE internal measurement reporting criteria 10.3.7.80	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting			NULL	
>>>UE positioning				
>>>>LCS reporting quantity	OP		LCS reporting quantity 10.3.7.111	
>>>>CHOICE report criteria	OP			
>>>>LCS reporting criteria			LCS reporting criteria 10.3.7.110	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting				
<b>Radio Bearer Information Elements</b>				
>Predefined configuration status information	OP		Predefined configuration status information 10.3.4.5a	
>Signalling RB information list	MP	1 to <maxSRBs etup>		For each signalling radio bearer
>>Signalling RB information	MP		Signalling RB information to setup 10.3.4.24	
>RAB information list	OP	1 to <maxRABs etup>		Information for each RAB
>>RAB information	MP		RAB information to setup 10.3.4.10	
<b>Transport Channel Information Elements</b>				
<b>Uplink transport channels</b>				
>UL Transport channel information common for all transport channels	OP		UL Transport channel information common for	

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
			all transport channels 10.3.5.24	
>UL transport channel information list	OP	1 to <MaxTrCH >		
>>UL transport channel information	MP		Added or reconfigured UL TrCH information 10.3.5.2	
>CHOICE mode	OP			
>>FDD				
>>>CPCH set ID	OP		CPCH set ID 10.3.5.5	
>>>Transport channel information for DRAC list	OP	1 to <MaxTrCH >		
>>>>DRAC static information	MP		DRAC static information 10.3.5.7	
>>TDD				(no data)
<b>Downlink transport channels</b>				
>DL Transport channel information common for all transport channels	OP		DL Transport channel information common for all transport channels 10.3.5.6	
>DL transport channel information list	OP	1 to <MaxTrCH >		
>>DL transport channel information	MP		Added or reconfigured DL TrCH information 10.3.5.1	
>Measurement report	OP		MEASUREMENT REPORT 10.2.17	
<b>Other Information elements</b>				
Failure cause	OP		Failure cause 10.3.3.13	Diagnostics information related to an earlier SRNC Relocation request (see NOTE 2 in 14.12.0a)
Protocol error information	CV-ProtErr		Protocol error information 10.3.8.12	

Multi Bound	Explanation
MaxNoOfMeas	Maximum number of active measurements, upper limit 16

<b>Condition</b>	<b>Explanation</b>
<i>Setup</i>	The IE is mandatory present when the IE Measurement command has the value "Setup", otherwise the IE is not needed.
<i>Ciphering</i>	The IE is mandatory present when the IE Ciphering Status has the value "started" and the ciphering counters need not be reinitialised, otherwise the IE is not needed.
<i>IP</i>	The IE is mandatory present when the IE Integrity protection status has the value "started" and the integrity protection counters need not be reinitialised, otherwise the IE is not needed.
<i>ProtErr</i>	This IE is mandatory present if the IE "Protocol error indicator" is included and has the value "TRUE". Otherwise it is not needed.
<i>SRB1</i>	The IE is mandatory present for RB1. Otherwise it is not needed.

## CHANGE REQUEST

⌘ 25.331 CR 1763 ⌘ rev 1 ⌘ Current version: 5.2.0 ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

**Proposed change affects:** UICC apps ⌘ ME  Radio Access Network  Core Network ⌘

<b>Title:</b>	⌘ Early UE Specific Behaviour Information in Handover Complete / Setup Complete	
<b>Source:</b>	⌘ Alcatel, Fujitsu, Motorola, NEC, Orange, Siemens	
<b>Work item code:</b>	⌘ TEI	<b>Date:</b> ⌘ 05/11/2002
<b>Category:</b>	⌘ <b>B</b> Use one of the following categories: <b>F</b> (correction) <b>A</b> (corresponds to a correction in an earlier release) <b>B</b> (addition of feature), <b>C</b> (functional modification of feature) <b>D</b> (editorial modification) Detailed explanations of the above categories can be found in 3GPP <a href="#">TR 21.900</a> .	<b>Release:</b> ⌘ Rel-5 Use one of the following releases: 2 (GSM Phase 2) R96 (Release 1996) R97 (Release 1997) R98 (Release 1998) R99 (Release 1999) Rel-4 (Release 4) Rel-5 (Release 5) Rel-6 (Release 6)

<b>Reason for change:</b>	⌘ It is currently not possible to identify and handle faulty UE implementations
<b>Summary of change:</b>	⌘ A transparent container “UE Specific Behaviour Information 2” is added to early messages at call setup and to the appropriate messages for SRNS relocation, i.e. to the following messages:  RRC Connection Setup Complete, Handover to UTRAN Complete, SRNS Relocation Info,  If UTRAN implements the CR but UE doesn't: - No impact. The RNC might not be able to adapt to specific UE behavior.  If UE implements the CR but UTRAN doesn't: - No impact. UTRAN will ignore the unknown extension and treat all UEs in the same way  If neither UE nor UTRAN implement the CR: - No impact.
<b>Consequences if not approved:</b>	⌘ Errors discovered in UEs can not be handled appropriately

<b>Clauses affected:</b>	⌘ 8.1.3.6, 8.3.6.3, 10.2.16b, 10.2.41, 10.3.3.53 (new), 11.2, 11.3, 11.5, 14.12.4.2										
<b>Other specs affected:</b>	⌘ <table border="1" style="display: inline-table; vertical-align: middle;"><tr><td>Y</td><td>N</td></tr><tr><td>X</td><td></td></tr><tr><td>X</td><td>Other core specifications</td></tr><tr><td>X</td><td>Test specifications</td></tr><tr><td>X</td><td>O&amp;M Specifications</td></tr></table>	Y	N	X		X	Other core specifications	X	Test specifications	X	O&M Specifications
Y	N										
X											
X	Other core specifications										
X	Test specifications										
X	O&M Specifications										

**Other comments:** ☰

**How to create CRs using this form:**

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>. Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ☰ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

### 8.1.3.6 Reception of an RRC CONNECTION SETUP message by the UE

The UE shall compare the value of the IE "Initial UE identity" in the received RRC CONNECTION SETUP message with the value of the variable INITIAL\_UE\_IDENTITY.

If the values are different, the UE shall:

- 1> ignore the rest of the message.

If the values are identical, the UE shall:

- 1> stop timer T300, and act upon all received information elements as specified in subclause 8.6, unless specified otherwise in the following:

- 2> if the UE will be in the CELL\_FACH state at the conclusion of this procedure:

- 3> if the IE "Frequency info" is included:

- 4> select a suitable UTRA cell according to [4] on that frequency;

- 3> select PRACH according to subclause 8.5.17;

- 3> select Secondary CCPCH according to subclause 8.5.19;

- 3> ignore the IE "UTRAN DRX cycle length coefficient" and stop using DRX.

- 1> if the UE will be in the CELL\_DCH state at the conclusion of this procedure:

- 2> perform the physical layer synchronisation procedure A as specified in [29] (FDD only).

- 1> enter UTRA RRC connected mode, in a state according to subclause 8.6.3.3;

- 1> submit an RRC CONNECTION SETUP COMPLETE message to the lower layers on the uplink DCCH after successful state transition per subclause 8.6.3.3, with the contents set as specified below:

- 2> set the IE "RRC transaction identifier" to:

- 3> the value of "RRC transaction identifier" in the entry for the RRC CONNECTION SETUP message in the table "Accepted transactions" in the variable TRANSACTIONS; and

- 3> clear that entry.

[2> set IE "UE Specific Behaviour Information 2" to "No UE Specific Behaviour Information 2";](#)

- 2> if the USIM or SIM is present:

- 3> set the "START" for each CN domain in the IE "START list" in the RRC CONNECTION SETUP COMPLETE message with the corresponding START value that is stored in the USIM [50] if present, or as stored in the UE if the SIM is present; and then

- 3> set the START value stored in the USIM [50] if present, and as stored in the UE if the SIM is present for any CN domain to the value "THRESHOLD" of the variable START\_THRESHOLD.

- 2> if neither the USIM nor SIM is present:

- 3> set the "START" for each CN domain in the IE "START list" in the RRC CONNECTION SETUP COMPLETE message to zero;

- 3> set the value of "THRESHOLD" in the variable "START\_THRESHOLD" to the default value [40].

- 2> retrieve its UTRA UE radio access capability information elements from variable UE\_CAPABILITY\_REQUESTED; and then

- 2> include this in IE "UE radio access capability" and IE "UE radio access capability extension", provided this IE is included in variable UE\_CAPABILITY\_REQUESTED;

- 2> retrieve its inter-RAT-specific UE radio access capability information elements from variable UE\_CAPABILITY\_REQUESTED; and then

2> include this in IE "UE system specific capability".

When the RRC CONNECTION SETUP COMPLETE message has been submitted to lower layers for transmission the UE shall:

1> if the UE has entered CELL\_FACH state:

2> start timer T305 using its initial value if periodical update has been configured by T305 in the IE "UE Timers and constants in connected mode" set to any other value than "infinity" in the variable TIMERS\_AND\_CONSTANTS.

1> store the contents of the variable UE\_CAPABILITY\_REQUESTED in the variable UE\_CAPABILITY\_TRANSFERRED;

1> initialise variables upon entering UTRA RRC connected mode as specified in subclause 13.4;

1> consider the procedure to be successful;

And the procedure ends.

### 8.3.6.3 Reception of HANDOVER TO UTRAN COMMAND message by the UE

The UE shall be able to receive a HANDOVER TO UTRAN COMMAND message and perform an inter-RAT handover, even if no prior UE measurements have been performed on the target UTRAN cell and/or frequency.

The UE shall act upon all received information elements as specified in subclause 8.6, unless specified otherwise in the following.

The UE may:

1> maintain a list of the set of cells to which the UE has Radio Links if the IE "Cell ID" is present.

The UE shall:

1> store a U-RNTI value (32 bits), which is derived by the IEs "SRNC identity" (12 bits) and "S-RNTI 2" (10 bits) included in IE "U-RNTI-short". In order to produce a full size U-RNTI value, a full size "S-RNTI" (20 bits) shall be derived by padding the IE "S-RNTI 2" with 10 zero bits in the most significant positions; and

1> initialise the variable ESTABLISHED\_SIGNALLING\_CONNECTIONS with the signalling connections that remains after the handover according to the specifications of the source RAT;

1> initialise the variable UE\_CAPABILITIES\_TRANSFERRED with the UE capabilities that have been transferred to the network up to the point prior to the handover, if any;

1> initialise the variable TIMERS\_AND\_CONSTANTS to the default values and start to use those timer and constants values;

1> if IE "Specification mode" is set to "Preconfiguration" and IE "Preconfiguration mode" is set to "Predefined configuration":

2> initiate the radio bearer and transport channel configuration in accordance with the predefined parameters identified by the IE "Predefined configuration identity";

2> initiate the physical channels in accordance with the predefined parameters identified by the IE "Predefined radio configuration identity" and the received physical channel information elements;

2> store information about the established radio access bearers and radio bearers according to the IE "Predefined configuration identity"; and

2> set the IE "RAB Info Post" in the variable ESTABLISHED\_RABS and the IE "Re-establishment timer" in the IE "RAB Info" in the variable ESTABLISHED\_RABS to "useT314".

1> if IE "Specification mode" is set to "Preconfiguration" and IE "Preconfiguration mode" is set to "Default configuration":

2> initiate the radio bearer and transport channel configuration in accordance with the default parameters identified by the IE "Default configuration mode" and IE "Default configuration identity";

- 2> initiate the physical channels in accordance with the default parameters identified by the IE "Default configuration mode" and IE "Default configuration identity" and the received physical channel information elements;

NOTE: IE "Default configuration mode" specifies whether the FDD or TDD version of the default configuration shall be used.

- 2> set the IE "RAB Info Post" in the variable ESTABLISHED\_RABS and the IE "Re-establishment timer" in the IE "RAB Info" in the variable ESTABLISHED\_RABS to "useT314".

1> if IE "Specification mode" is set to "Preconfiguration":

- 2> use the following values for parameters that are neither signalled within the HANOVER TO UTRAN COMMAND message nor included within pre-defined or default configuration:

3> 0 dB for the power offset  $P_{\text{Pilot-DPDCH}}$  bearer in FDD;

3> calculate the Default DPCH Offset Value using the following formula:

3> in FDD:

$$\text{Default DPCH Offset Value} = (\text{SRNTI } 2 \bmod 600) * 512$$

3> in TDD:

$$\text{Default DPCH Offset Value} = (\text{SRNTI } 2 \bmod 7)$$

3> handle the above Default DPCH Offset Value as if an IE with that value was included in the message, as specified in subclause 8.6.6.21.

1> if IE "Specification mode" is set to "Complete specification":

- 2> initiate the radio bearer, transport channel and physical channel configuration in accordance with the received radio bearer, transport channel and physical channel information elements.

1> perform an open loop estimation to determine the UL transmission power according to subclause 8.5.3;

1> set the IE "START" for each CN domain, in the IE "START list" in the HANOVER TO UTRAN COMPLETE message equal to the START value for each CN domain stored in the USIM if the USIM is present, or as stored in the UE for each CN domain if the SIM is present;

1> if ciphering has been activated and ongoing in the radio access technology from which inter-RAT handover is performed:

- 2> for the CN domain included in the IE "CN domain identity" which is included in the IE "RAB info" of the IE "RAB information to setup", or the CS domain when these IEs are not present:

3> set the variable LATEST\_CONFIGURED\_CN\_DOMAIN to the value indicated in the IE "CN domain identity", or to the CS domain when this IE is not present;

3> set the 20 MSB of the HFN component of the COUNT-C variable for all radio bearers using RLC-TM and all signalling radio bearers to the "START" value included in the IE "UE security information" in the variable "INTER\_RAT\_HANOVER\_INFO\_TRANSFERRED";

3> set the remaining LSBs of the HFN component of COUNT-C for all radio bearers using RLC-TM and all signalling radio bearers to zero;

3> not increment the HFN component of COUNT-C for radio bearers using RLC-TM, i.e. keep the HFN value fixed without incrementing every CFN cycle;

3> set the CFN component of the COUNT-C variable to the value of the CFN as calculated in subclause 8.5.15;

3> set the IE "Status" in the variable CIPHERING\_STATUS to "Started";

3> apply the algorithm according to IE "Ciphering Algorithm" and apply ciphering immediately upon reception of the HANOVER TO UTRAN COMMAND.

- 1> if ciphering has not been activated and ongoing in the radio access technology from which inter-RAT handover is performed:
- 2> for the CN domain included in the IE "CN domain identity" which is included in the IE "RAB info" of the IE "RAB information to setup", or the CS domain when these IEs are not present:
  - 3> set the IE "Status" in the variable CIPHERING\_STATUS to "Not Started".

If the UE succeeds in establishing the connection to UTRAN, it shall:

- 1> if the IE "Status" in the variable CIPHERING\_STATUS of a CN domain is set to "Started" and transparent mode radio bearers have been established by this procedure for that CN domain:
  - 2> include the IE "COUNT-C activation time" in the response message and specify a CFN value other than the default, "Now" for this IE;
  - 2> at the CFN value as indicated in the response message in the IE "COUNT-C activation time" for radio bearers using RLC-TM:
    - 3> set the 20 MSB of the HFN component of the COUNT-C variable common for all transparent mode radio bearers of this CN domain to the START value as indicated in the IE "START list" of the response message for the relevant CN domain; and
    - 3> set the remaining LSBs of the HFN component of COUNT-C to zero;
    - 3> increment the HFN component of the COUNT-C variable by one;
    - 3> set the CFN component of the COUNT-C to the value of the IE "COUNT-C activation time" of the response message. The HFN component and the CFN component completely initialise the COUNT-C variable;
    - 3> step the COUNT-C variable, as normal, at each CFN value. The HFN component is no longer fixed in value but incremented at each CFN cycle.

- 1> if the IE "Status" in the variable CIPHERING\_STATUS of a CN domain is set to "Not Started" and transparent mode radio bearers have been established by this procedure for that CN domain:
  - 2> initialise the 20 MSB of the HFN component of COUNT-C common for all transparent mode radio bearers of this CN domain with the START value as indicated in the IE "START list" of the response message for the relevant CN domain;
  - 2> set the remaining LSBs of the HFN component of COUNT-C to zero;
  - 2> do not increment the COUNT-C value common for all transparent mode radio bearers for this CN domain.

- 1> transmit a HANDOVER TO UTRAN COMPLETE message on the uplink DCCH, using, if ciphering has been started, the new ciphering configuration; and

**1> set IE "UE Specific Behaviour Information 2" to "No UE Specific Behaviour Information 2";**

- 1> when the HANDOVER TO UTRAN COMPLETE message has been submitted to lower layers for transmission:
  - 2> enter UTRA RRC connected mode in state CELL\_DCH;
  - 2> initialise variables upon entering UTRA RRC connected mode as specified in subclause 13.4;
  - 2> for all radio bearers using RLC-AM or RLC-UM:
    - 3> set the 20 MSB of the HFN component of the uplink and downlink COUNT-C variable to the START value indicated in the IE "START list" of the response message for the relevant CN domain; and
    - 3> set the remaining LSBs of the HFN component of COUNT-C to zero;
    - 3> increment the HFN component of the COUNT-C variable by one;
    - 3> start incrementing the COUNT-C values.
- 1> and the procedure ends.

## 10.2.16b HANDOVER TO UTRAN COMPLETE

This message is sent by the UE when a handover to UTRAN has been completed.

RLC-SAP: AM

Logical channel: DCCH

Direction: UE → UTRAN

Information Element/Group name	Need	Multi	Type and reference	Semantics description
Message Type	MP		Message Type	
<b>UE Information elements</b>				
START list	CH	1 to <maxCNdomains>		START [40] values for all CN domains.
>CN domain identity	MP		CN domain identity 10.3.1.1	
>START	MP		START 10.3.3.38	
<a href="#"><u>&gt;UE Specific Behaviour Information 2</u></a>	<a href="#"><u>MP</u></a>		<a href="#"><u>UE Specific Behaviour Information 2</u></a> <a href="#"><u>10.3.3.53</u></a>	
<b>RB Information elements</b>				
COUNT-C activation time	OP		Activation time 10.3.3.1	Used for radio bearers mapped on RLC-TM.

## 10.2.41 RRC CONNECTION SETUP COMPLETE

This message confirms the establishment of the RRC Connection by the UE.

RLC-SAP: AM

Logical channel: DCCH

Direction: UE → UTRAN

Information Element/Group name	Need	Multi	Type and reference	Semantics description
Message Type	MP		Message Type	
<b>UE Information Elements</b>				
RRC transaction identifier	MP		RRC transaction identifier 10.3.3.36	
START list	MP	1 to <maxCNdomains>		START [40] values for all CN domains.
>CN domain identity	MP		CN domain identity 10.3.1.1	
>START	MP		START 10.3.3.38	START value to be used in this CN domain.
UE radio access capability	OP		UE radio access capability 10.3.3.42	

<u>Information Element/Group name</u>	<u>Need</u>	<u>Multi</u>	<u>Type and reference</u>	<u>Semantics description</u>
UE radio access capability extension	OP		UE radio access capability extension 10.3.3.42a	
<a href="#">&gt;UE Specific Behaviour Information 2</a>	<a href="#">MP</a>		<a href="#">UE Specific Behaviour Information 2</a> 10.3.3.53	
<b>Other information elements</b>				
UE system specific capability	OP	1 to <maxInter SysMessages>		
>Inter-RAT UE radio access capability	MP		Inter-RAT UE radio access capability 10.3.8.7	

### [10.3.3.53 UE Specific Behaviour Information 2](#)

This IE indicates the UE conformance.

<u>Information Element/Group name</u>	<u>Need</u>	<u>Multi</u>	<u>Type and Reference</u>	<u>Semantics description</u>
<a href="#">CHOICE UE Specific Behaviour Information 2</a>	<a href="#">MP</a>			<a href="#">In this version of the specification the UE should set this IE to "No UE Specific Behaviour Information 2"</a>
<a href="#">&gt;No UE Specific Behaviour Information 2</a>	<a href="#">MP</a>			(no data)
<a href="#">&gt;UE Specific Behaviour Information 2 fixed</a>	<a href="#">MP</a>		<a href="#">bit string(16)</a>	
<a href="#">&gt;UE Specific Behaviour Information 2 variable</a>	<a href="#">MP</a>		<a href="#">bit string(1..256)</a>	

## 11.2 PDU definitions

```
--*****
-- TABULAR: The message type and integrity check info are not
-- visible in this module as they are defined in the class module.
-- Also, all FDD/TDD specific choices have the FDD option first
-- and TDD second, just for consistency.
--*****
```

PDU-definitions DEFINITIONS AUTOMATIC TAGS ::=

BEGIN

```
--*****
-- IE parameter types from other modules
--*****
```

IMPORTS

```
-- Core Network IEs :
CN-DomainIdentity,
CN-InformationInfo,
CN-InformationInfoFull,
NAS-Message,
```

```

PagingRecordTypeID,
-- UTRAN Mobility IEs :
CellIdentity,
CellIdentity-PerRL-List,
URA-Identity,
-- User Equipment IEs :
ActivationTime,
C-RNTI,
CapabilityUpdateRequirement,
CapabilityUpdateRequirement-r4,
CapabilityUpdateRequirement-r4-ext,
CellUpdateCause,
CipheringAlgorithm,
CipheringModeInfo,
DSCH-RNTI,
EstablishmentCause,
FailureCauseWithProtErr,
FailureCauseWithProtErrTrId,
H-RNTI,
| UESpecificBehaviourInformation2,
InitialUE-Identity,
IntegrityProtActivationInfo,
IntegrityProtectionModeInfo,
N-308,
PagingCause,
PagingRecordList,
ProtocolErrorIndicator,
ProtocolErrorIndicatorWithMoreInfo,
Rb-timer-indicator,
RedirectionInfo,
RejectionCause,
ReleaseCause,
RRC-StateIndicator,
RRC-TransactionIdentifier,
SecurityCapability,
START-Value,
STARTList,
U-RNTI,
U-RNTI-Short,
UE-RadioAccessCapability,
UE-RadioAccessCapability-r4-ext,
UE-RadioAccessCapability-r5-ext,
UE-RadioAccessCapability-v370ext,
UE-RadioAccessCapability-v380ext,
UE-RadioAccessCapability-v3a0ext,
UE-RadioAccessCapability-v4xyext,
DL-PhysChCapabilityFDD-v380ext,
UE-ConnTimersAndConstants,
UE-ConnTimersAndConstants-v3a0ext,
UE-ConnTimersAndConstants-r5,
UE-SecurityInformation,
URA-UpdateCause,
UTRAN-DRX-CycleLengthCoefficient,
WaitTime,
-- Radio Bearer IEs :
DefaultConfigIdentity,
DefaultConfigIdentity-r4,
DefaultConfigMode,
DL-CounterSynchronisationInfo,
DL-CounterSynchronisationInfo-r5,
PredefinedConfigIdentity,
PredefinedConfigStatusList,
RAB-Info,
RAB-Info-Post,
RAB-InformationList,
RAB-InformationReconfigList,
RAB-InformationSetupList,
RAB-InformationSetupList-r4,
RB-ActivationTimeInfoList,
RB-COUNT-C-InformationList,
RB-COUNT-C-MSB-InformationList,
RB-IdentityList,
RB-InformationAffectedList,
RB-InformationAffectedList-r5,
RB-InformationReconfigList,
RB-InformationReconfigList-r4,
RB-InformationReconfigList-r5,
RB-InformationReleaseList,
RB-PDCPContextRelocationList,

```

```

SRB-InformationSetupList,
SRB-InformationSetupList2,
UL-CounterSynchronisationInfo,
-- Transport Channel IEs:
CPCH-SetID,
DL-AddReconfTransChInfo2List,
DL-AddReconfTransChInfoList,
DL-AddReconfTransChInfoList-r4,
DL-AddReconfTransChInfoList-r5,
DL-CommonTransChInfo,
DL-CommonTransChInfo-r4,
DL-DeletedTransChInfoList,
DL-DeletedTransChInfoList-r5,
DRAC-StaticInformationList,
TFC-Subset,
TFCS-Identity,
UL-AddReconfTransChInfoList,
UL-CommonTransChInfo,
UL-CommonTransChInfo-r4,
UL-DeletedTransChInfoList,
-- Physical Channel IEs :
Alpha,
CCTrCH-PowerControlInfo,
CCTrCH-PowerControlInfo-r4,
ConstantValue,
ConstantValueTdd,
CPCH-SetInfo,
DL-CommonInformation,
DL-CommonInformation-r4,
DL-CommonInformationPost,
DL-HSPDSCH-Information,
DL-InformationPerRL,
DL-InformationPerRL-List,
DL-InformationPerRL-List-r4,
DL-InformationPerRL-List-r5,
DL-InformationPerRL-ListPostFDD,
DL-InformationPerRL-PostTDD,
DL-InformationPerRL-PostTDD-LCR-r4,
DL-PDSCH-Information,
DPCH-CompressedModeStatusInfo,
FrequencyInfo,
FrequencyInfoFDD,
FrequencyInfoTDD,
MaxAllowedUL-TX-Power,
OpenLoopPowerControl-IPDL-TDD-r4,
PDSCH-CapacityAllocationInfo,
PDSCH-CapacityAllocationInfo-r4,
PDSCH-Identity,
PrimaryCCPCH-TX-Power,
PUSCH-CapacityAllocationInfo,
PUSCH-CapacityAllocationInfo-r4,
PUSCH-Identity,
RL-AdditionInformationList,
RL-RemovalInformationList,
SpecialBurstScheduling,
SSDT-Information,
TFC-ControlDuration,
SSDT-UL-r4,
TimeslotList,
TimeslotList-r4,
TX-DiversityMode,
UL-ChannelRequirement,
UL-ChannelRequirement-r4,
UL-ChannelRequirement-r5,
UL-ChannelRequirementWithCPCH-SetID,
UL-ChannelRequirementWithCPCH-SetID-r4,
UL-ChannelRequirementWithCPCH-SetID-r5,
UL-DPCH-Info,
UL-DPCH-Info-r4,
UL-DPCH-InfoPostFDD,
UL-DPCH-InfoPostTDD,
UL-DPCH-InfoPostTDD-LCR-r4,
UL-SynchronisationParameters-r4,
UL-TimingAdvance,
UL-TimingAdvanceControl,
UL-TimingAdvanceControl-r4,
-- Measurement IEs :
AdditionalMeasurementID-List,
Frequency-Band,

```

```

EventResults,
InterFreqEventResults-LCR-r4-ext,
InterRAT-TargetCellDescription,
MeasuredResults,
MeasuredResults-v390ext,
MeasuredResultsList,
MeasuredResultsList-LCR-r4-ext,
MeasuredResultsOnRACH,
MeasurementCommand,
MeasurementCommand-r4,
MeasurementIdentity,
MeasurementReportingMode,
PrimaryCCPCH-RSCP,
SFN-Offset-Validity,
TimeslotListWithISCP,
TrafficVolumeMeasuredResultsList,
UE-Positioning-GPS-AssistanceData,
UE-Positioning-Measurement-v390ext,
UE-Positioning-OTDOA-AssistanceData,
UE-Positioning-OTDOA-AssistanceData-r4ext,
UE-Positioning-OTDOA-AssistanceData-UEB,
UE-Positioning-IPDL-Parameters-TDD-r4-ext,
-- Other IEs :
BCCH-ModificationInfo,
CDMA2000-MessageList,
GSM-MessageList,
InterRAT-ChangeFailureCause,
InterRAT-HO-FailureCause,
InterRAT-UE-RadioAccessCapabilityList,
InterRAT-UE-SecurityCapList,
IntraDomainNasNodeSelector,
ProtocolErrorMoreInformation,
Rplmn-Information,
Rplmn-Information-r4,
SegCount,
SegmentIndex,
SFN-Prime,
SIB-Data-fixed,
SIB-Data-variable,
SIB-Type
FROM InformationElements

maxSIBperMsg
FROM Constant-definitions;

-- *****
-- HANOVER TO UTRAN COMPLETE
--
-- *****

HandoverToUTRANComplete ::= SEQUENCE {
    --TABULAR: Integrity protection shall not be performed on this message.
    -- User equipment IEs
    -- TABULAR: startList is conditional on history.
    startList                  STARTList                      OPTIONAL,
    -- Radio bearer IEs
    count-C-ActivationTime     ActivationTime                OPTIONAL,
    -- Non critical Extensions
    v520NonCriticalExtensions SEQUENCE {
        handoverToUTRANComplete-v520ext HandoverToUTRANComplete-v520ext-IEs,
        -- Reserved for future non critical extension
        nonCriticalExtensions      SEQUENCE {} OPTIONAL
    } OPTIONAL
    -- Extension mechanism for non-release99 information
    nonCriticalExtensions      SEQUENCE {} OPTIONAL
}
HandoverToUTRANComplete-v520ext-IEs ::= = SEQUENCE {
    -- User equipment IEs
    uESpecificBehaviourInformation2 UESpecificBehaviourInformation2
}

-- *****
-- INITIAL DIRECT TRANSFER
--
-- *****

```

```

InitialDirectTransfer ::= SEQUENCE {
    -- Core network IEs
    cn-DomainIdentity           CN-DomainIdentity,
    intraDomainNasNodeSelector  IntraDomainNasNodeSelector,
    nas-Message                  NAS-Message,
    -- Measurement IEs
    measuredResultsOnRACH       MeasuredResultsOnRACH
    v3a0NonCriticalExtensions   SEQUENCE {
        initialDirectTransfer-v3a0ext InitialDirectTransfer-v3a0ext,
    }
    -- Extension mechanism for non-release99 information
    nonCriticalExtensions       SEQUENCE {} OPTIONAL
}
} OPTIONAL

InitialDirectTransfer-v3a0ext ::= SEQUENCE {
    -- start-value shall always be included in this version of the protocol
    start-Value                 START-Value OPTIONAL
}

-- ****
-- HANOVER FROM UTRAN COMMAND
-- ****

HandoverFromUTRANCommand-GSM ::= CHOICE {
    r3                         SEQUENCE {
        handoverFromUTRANCommand-GSM-r3
            HandoverFromUTRANCommand-GSM-r3-IES,
            -- UTRAN should not include the IE nonCriticalExtensions when it sets
            -- the IE gsm-message included in handoverFromUTRANCommand-GSM-r3 to single-GSM-Message
            -- The UE behaviour upon receiving a message including this combination of IE values is
            -- not specified
            nonCriticalExtensions      SEQUENCE {} OPTIONAL
    },
    later-than-r3                SEQUENCE {
        rrc-TransactionIdentifier RRC-TransactionIdentifier,
        criticalExtensions        SEQUENCE {}
    }
}

HandoverFromUTRANCommand-GSM-r3-IES ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier   RRC-TransactionIdentifier,
    activationTime               ActivationTime OPTIONAL,
    -- Radio bearer IEs
    toHandover-Info             RAB-Info OPTIONAL,
    -- Measurement IEs
    frequency-band               Frequency-Band,
    -- Other IEs
    gsm-message                 CHOICE {
        -- In the single-GSM-Message case the following rules apply:
        -- 1> the GSM message directly follows the basic production; the final padding that
        -- results when PER encoding the abstract syntax value is removed prior to appending
        -- the GSM message.
        -- 2> the RRC message excluding the GSM part, does not contain a length determinant;
        -- there is no explicit parameter indicating the size of the included GSM message.
        -- 3> depending on need, final padding (all "0"s) is added to ensure the final result
        -- comprises a full number of octets
        single-GSM-Message          SEQUENCE {},
        gsm-MessageList              SEQUENCE {
            gsm-Messages             GSM-MessageList
        }
    }
}

HandoverFromUTRANCommand-CDMA2000 ::= CHOICE {
    r3                         SEQUENCE {
        handoverFromUTRANCommand-CDMA2000-r3
            HandoverFromUTRANCommand-CDMA2000-r3-IES,
        nonCriticalExtensions      SEQUENCE {} OPTIONAL
    },
    later-than-r3                SEQUENCE {
        rrc-TransactionIdentifier RRC-TransactionIdentifier,
        criticalExtensions        SEQUENCE {}
    }
}

```

```

HandoverFromUTRANCommand-CDMA2000-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    activationTime                 ActivationTime
    OPTIONAL,
    -- Radio bearer IEs
    toHandover-Info                RAB-Info
    OPTIONAL,
    -- Other IEs
    cdma2000-MessageList          CDMA2000-MessageList
}

-- ****
-- 
-- HANOVER FROM UTRAN FAILURE
-- 
-- ****

HandoverFromUTRANFailure ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    -- Other IEs
    interRAT-HO-FailureCause      InterRAT-HO-FailureCause
    OPTIONAL,
    interRATMessage                CHOICE {
        gsm                      SEQUENCE {
            gsm-MessageList        GSM-MessageList
        },
        cdma2000                  SEQUENCE {
            cdma2000-MessageList   CDMA2000-MessageList
        }
    }                                OPTIONAL,
    -- Extension mechanism for non- release99 information
    nonCriticalExtensions          SEQUENCE {}     OPTIONAL
}

-- ****
-- 
-- INTER RAT HANDOVER INFO
-- 
-- ****

InterRATHandoverInfo ::= SEQUENCE {
    -- This structure is defined for historical reasons, backward compatibility with 04.18
    predefinedConfigStatusList      CHOICE {
        absent                   NULL,
        present                  PredefinedConfigStatusList
    },
    uE-SecurityInformation          CHOICE {
        absent                   NULL,
        present                  UE-SecurityInformation
    },
    ue-CapabilityContainer          CHOICE {
        absent                   NULL,
        -- present is an octet aligned string containing IE UE-RadioAccessCapabilityInfo
        present                  OCTET STRING (SIZE (0..63))
    },
    -- Non critical extensions
    v390NonCriticalExtensions      CHOICE {
        absent                   NULL,
        present                  SEQUENCE {
            interRATHandoverInfo-v390ext  InterRATHandoverInfo-v390ext-IEs,
            v3a0NonCriticalExtensions   SEQUENCE {
                interRATHandoverInfo-v3a0ext  InterRATHandoverInfo-v3a0ext,
                v4xyNonCriticalExtensions   SEQUENCE {
                    interRATHandoverInfo-v4xyext  InterRATHandoverInfo-v4xyext-IEs,
                    -- Reserved for future non critical extension
                    nonCriticalExtensions       SEQUENCE {} OPTIONAL
                }                                OPTIONAL
            }                                OPTIONAL
        }                                OPTIONAL
    }
}

InterRATHandoverInfo-v390ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v380ext  UE-RadioAccessCapability-v380ext
    dl-PhysChCapabilityFDD-v380ext   DL-PhysChCapabilityFDD-v380ext
    OPTIONAL,
}

InterRATHandoverInfo-v3a0ext ::= SEQUENCE {
    -- User equipment IEs
}

```

```

        ue-RadioAccessCapability-v3a0ext      UE-RadioAccessCapability-v3a0ext      OPTIONAL
    }

InterRATHandoverInfo-v4xyext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v4xyext      UE-RadioAccessCapability-v4xyext
}

-- ****
-- 
-- MEASUREMENT CONTROL
-- 
-- ****

MeasurementControl ::= CHOICE {
    r3                               SEQUENCE {
        measurementControl-r3            MeasurementControl-r3-IEs,
        v390nonCriticalExtensions       SEQUENCE {
            measurementControl-v390ext   MeasurementControl-v390ext,
            v3a0NonCriticalExtensions    SEQUENCE {
                measurementControl-v3a0ext   MeasurementControl-v3a0ext,
                v4xyNonCriticalExtensions   SEQUENCE {
                    measurementControl-v4xyext   MeasurementControl-v4xyext-IEs,
                    nonCriticalExtensions     SEQUENCE {}           OPTIONAL
                }
            }
        }
    },
    later-than-r3                     SEQUENCE {
        rrc-TransactionIdentifier      RRC-TransactionIdentifier,
        criticalExtensions             CHOICE {
            r4                           SEQUENCE {
                measurementControl-r4      MeasurementControl-r4-IEs,
                nonCriticalExtensions     SEQUENCE {}           OPTIONAL
            },
            criticalExtensions          SEQUENCE {}
        }
    }
}

MeasurementControl-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier,
    -- Measurement IEs
    measurementIdentity            MeasurementIdentity,
    -- TABULAR: The measurement type is included in MeasurementCommand.
    measurementCommand              MeasurementCommand,
    measurementReportingMode       MeasurementReportingMode           OPTIONAL,
    additionalMeasurementList      AdditionalMeasurementID-List    OPTIONAL,
    -- Physical channel IEs
    dpch-CompressedModeStatusInfo DPCH-CompressedModeStatusInfo    OPTIONAL
}

MeasurementControl-v4xyext-IEs ::= SEQUENCE {
    ue-Positioning-OTDOA-AssistanceData-r4ext  UE-Positioning-OTDOA-AssistanceData-r4ext    OPTIONAL
}

MeasurementControl-v390ext ::= SEQUENCE {
    ue-Positioning-Measurement-v390ext        UE-Positioning-Measurement-v390ext    OPTIONAL
}

MeasurementControl-v3a0ext ::= SEQUENCE {
    sfn-Offset-Validity                  SFN-Offset-Validity    OPTIONAL
}

MeasurementControl-r4-IEs ::= SEQUENCE {
    -- Measurement IEs
    measurementIdentity            MeasurementIdentity,
    -- TABULAR: The measurement type is included in measurementCommand.
    measurementCommand              MeasurementCommand-r4,
    measurementReportingMode       MeasurementReportingMode           OPTIONAL,
    additionalMeasurementList      AdditionalMeasurementID-List    OPTIONAL,
    -- Physical channel IEs
    dpch-CompressedModeStatusInfo DPCH-CompressedModeStatusInfo    OPTIONAL
}

-- ****
-- 
-- MEASUREMENT CONTROL FAILURE
-- 
```

```

-- ****
-- MeasurementControlFailure ::= SEQUENCE {
    -- User equipment IEs
        rrc-TransactionIdentifier      RRC-TransactionIdentifier,
        failureCause                  FailureCauseWithProtErr,
    -- Extension mechanism for non- release99 information
        nonCriticalExtensions        SEQUENCE {}           OPTIONAL
}

-- ****
-- RRC CONNECTION SETUP COMPLETE
-- ****

RRCConnectionSetupComplete ::= SEQUENCE {
    -- TABULAR: Integrity protection shall not be performed on this message.
    -- User equipment IEs
        rrc-TransactionIdentifier      RRC-TransactionIdentifier,
        startList                      STARTList,
        ue-RadioAccessCapability       UE-RadioAccessCapability           OPTIONAL,
    -- Other IEs
        ue-RATSpecificCapability      InterRAT-UE-RadioAccessCapabilityList   OPTIONAL,
    -- Non critical extensions
        v370NonCriticalExtensions     SEQUENCE {
            rrcConnectionSetupComplete-v370ext  RRCConnectionSetupComplete-v370ext,
            v380NonCriticalExtensions         SEQUENCE {
                rrcConnectionSetupComplete-v380ext  RRCConnectionSetupComplete-v380ext-IEs,
                ----- Reserved for future non critical extension -----
                v3a0NonCriticalExtensions       SEQUENCE {
                    rrcConnectionSetupComplete-v3a0ext  RRCConnectionSetupComplete-v3a0ext,
                    v3d0NonCriticalExtensions        SEQUENCE {
                        rrcConnectionSetupComplete-v3d0ext-IEs  RRCConnectionSetupComplete-v3d0ext-IEs,
                        ----- Reserved for future non critical extension -----
                        v4xyNonCriticalExtensions       SEQUENCE {
                            rrcConnectionSetupComplete-v4xyext  RRCConnectionSetupComplete-v4xyext-IEs,
                            ----- Reserved for future non critical extension -----
                            nonCriticalExtensions          SEQUENCE {}           OPTIONAL
                        }                               OPTIONAL
                    }                               OPTIONAL
                }                               OPTIONAL
            }                               OPTIONAL
        }                               OPTIONAL
    }

RRCConnectionSetupComplete-v370ext ::= SEQUENCE {
    -- User equipment IEs
        ue-RadioAccessCapability-v370ext  UE-RadioAccessCapability-v370ext   OPTIONAL
}

RRCConnectionSetupComplete-v380ext-IEs ::= SEQUENCE {
    -- User equipment IEs
        ue-RadioAccessCapability-v380ext  UE-RadioAccessCapability-v380ext   OPTIONAL,
        dl-PhysChCapabilityFDD-v380ext  DL-PhysChCapabilityFDD-v380ext
}

RRCConnectionSetupComplete-v3a0ext ::= SEQUENCE {
    -- User equipment IEs
        ue-RadioAccessCapability-v3a0ext  UE-RadioAccessCapability-v3a0ext   OPTIONAL
}

RRCConnectionSetupComplete-v3d0ext-IEs ::= SEQUENCE {
    -- User equipment IEs
        uESpecificBehaviourInformation2  UESpecificBehaviourInformation2
}

RRCConnectionSetupComplete-v4xyext-IEs ::= SEQUENCE {
    -- User equipment IEs
        ue-RadioAccessCapability-r4-ext  UE-RadioAccessCapability-r4-ext   OPTIONAL
}

-- ****
-- RRC FAILURE INFO
-- ****

```

```

RRC-FailureInfo ::= CHOICE {
    r3
        RRC-FailureInfo-r3
        nonCriticalExtensions
    },
    criticalExtensions
}

RRC-FailureInfo-r3-IEs ::= SEQUENCE {
    -- Non-RRC IE
        failureCauseWithProtErr
    }

-- *****
-- 
-- RRC STATUS
-- 
-- *****

END

```

## 11.3 Information element definitions

```

InformationElements DEFINITIONS AUTOMATIC TAGS ::=

-- *****
-- 
-- CORE NETWORK INFORMATION ELEMENTS (10.3.1)
-- 
-- *****

BEGIN

IMPORTS

    hiPDSCHidentities,
    hiPUSCHidentities,
    hiRM,
    maxAC,
    maxAdditionalMeas,
    maxASC,
    maxASCmap,
    maxASCpersist,
    maxCCTrCH,
    maxCellMeas,
    maxCellMeas-1,
    maxCNdomains,
    maxCPCHsets,
    maxDPCH-DLchan,
    maxDPDCH-UL,
    maxDRACclasses,
    maxFACHPCH,
    maxFreq,
    maxFreqBandsFDD,
    maxFreqBandSTDD,
    maxFreqBandsGSM,
    maxHProcesses,
    maxHSDSCHTBIndex,
    maxHSDSCHTBIndex-tdd384,
    maxHSSCCHs,
    maxInterSysMessages,
    maxLoCHperRLC,
    maxMAC-d-PDUsizes,
    maxMeasEvent,
    maxMeasIntervals,
    maxMeasParEvent,
    maxNumCDMA2000Freqs,
    maxNumFDDFreqs,
    maxNumGSMFreqRanges,
    maxNumTDDFreqs,
    maxOtherRAT,
    maxOtherRAT-16,
    maxPage1,
    maxPCPCH-APsig,
    maxPCPCH-APsubCh,
    maxPCPCH-CDsig,

```

```

maxPCPCH-CDsubCh,
maxPCPCH-SF,
maxPCPCHs,
maxPDCPAalgoType,
maxPDSCH,
maxPDSCH-TFCIgroups,
maxPRACH,
maxPRACH-FPACH,
maxPredefConfig,
maxPUSCH,
maxQueueIDs,
maxRABsetup,
maxRAT,
maxRB,
maxRBallRABs,
maxRBmuxOptions,
maxRBperRAB,
maxReportedGSMCells,
maxSRBsetup,
maxRL,
maxRL-1,
maxROHC-PacketSizes-r4,
maxROHC-Profile-r4,
maxSCCPCH,
maxSat,
maxSIB,
maxSIB-FACH,
maxSystemCapability,
maxTF,
maxTF-CPCH,
maxTFC,
maxTFCsub,
maxTFCI-2-Combs,
maxTGPS,
maxTrCH,
maxTrCHpreconf,
maxTS,
maxTS-1,
maxTS-LCR,
maxTS-LCR-1,
maxURA
FROM Constant-definitions;

Ansi-41-IDNNS ::= BIT STRING (SIZE (14))

CN-DomainIdentity ::= ENUMERATED {
    cs-domain,
    ps-domain }

CN-DomainInformation ::= SEQUENCE {
    cn-DomainIdentity,
    cn-DomainSpecificNAS-Info
}

CN-DomainInformationFull ::= SEQUENCE {
    cn-DomainIdentity,
    cn-DomainSpecificNAS-Info
    cn-DRX-CycleLengthCoeff
}

CN-DomainInformationList ::= SEQUENCE (SIZE (1..maxCNdomains)) OF
    CN-DomainInformation

CN-DomainInformationListFull ::= SEQUENCE (SIZE (1..maxCNdomains)) OF
    CN-DomainInformationFull

CN-DomainSysInfo ::= SEQUENCE {
    cn-DomainIdentity,
    cn-Type {
        gsm-MAP
        ansi-41
    },
    cn-DRX-CycleLengthCoeff
}

CN-DomainSysInfoList ::= SEQUENCE (SIZE (1..maxCNdomains)) OF
    CN-DomainSysInfo

CN-InformationInfo ::= SEQUENCE {

```

```

plmn-Identity          PLMN-Identity          OPTIONAL,
cn-CommonGSM-MAP-NAS-SysInfo   NAS-SystemInformationGSM-MAP    OPTIONAL,
cn-DomainInformationList   CN-DomainInformationList    OPTIONAL
}

CN-InformationInfoFull ::= SEQUENCE {
    plmn-Identity          PLMN-Identity          OPTIONAL,
    cn-CommonGSM-MAP-NAS-SysInfo   NAS-SystemInformationGSM-MAP    OPTIONAL,
    cn-DomainInformationListFull  CN-DomainInformationListFull    OPTIONAL
}

Digit ::= INTEGER (0..9)

Gsm-map-IDNNS ::= SEQUENCE {
    routingbasis           CHOICE {
        localPTMSI          SEQUENCE {
            routingparameter RoutingParameter
        },
        tMSIofsamePLMN       SEQUENCE {
            routingparameter RoutingParameter
        },
        tMSIoffifferentPLMN SEQUENCE {
            routingparameter RoutingParameter
        },
        iMSIresponsetopaging SEQUENCE {
            routingparameter RoutingParameter
        },
        iMSIUEinitiatedEvent SEQUENCE {
            routingparameter RoutingParameter
        },
        iMEI                  SEQUENCE {
            routingparameter RoutingParameter
        },
        spare1               SEQUENCE {
            routingparameter RoutingParameter
        },
        spare2               SEQUENCE {
            routingparameter RoutingParameter
        }
    },
    enteredparameter        BOOLEAN
}

IMEI ::= SEQUENCE (SIZE (15)) OF
    IMEI-Digit

IMEI-Digit ::= INTEGER (0..15)

IMSI-GSM-MAP ::= SEQUENCE (SIZE (6..15)) OF
    Digit

IntraDomainNasNodeSelector ::= SEQUENCE {
    version               CHOICE {
        release99           SEQUENCE {
            cn-Type             CHOICE {
                gsm-Map-IDNNS   Gsm-map-IDNNS,
                ansi-41-IDNNS   Ansi-41-IDNNS
            }
        },
        later                SEQUENCE {
            futurecoding      BIT STRING (SIZE (15))
        }
    }
}

LAI ::= SEQUENCE {
    plmn-Identity          PLMN-Identity,
    lac                    BIT STRING (SIZE (16))
}

MCC ::= SEQUENCE (SIZE (3)) OF
    Digit

MNC ::= SEQUENCE (SIZE (2..3)) OF
    Digit

NAS-Message ::= OCTET STRING (SIZE (1..4095))

NAS-Synchronisation-Indicator ::= BIT STRING(SIZE(4))

```

```

NAS-SystemInformationGSM-MAP ::= OCTET STRING (SIZE (1..8))

P-TMSI-GSM-MAP ::= BIT STRING (SIZE (32))

PagingRecordTypeID ::= ENUMERATED {
    imsi-GSM-MAP,
    tmsi-GSM-MAP-P-TMSI,
    imsi-DS-41,
    tmsi-DS-41 }

PLMN-Identity ::= SEQUENCE {
    mcc,
    MCC,
    mnc,
    MNC
}

PLMN-Type ::= CHOICE {
    gsm-MAP
        plmn-Identity
    },
    ansi-41
        p-REV,
        min-P-REV,
        sid,
        nid
    },
    gsm-MAP-and-ANSI-41
        plmn-Identity
        p-REV,
        min-P-REV,
        sid,
        nid
    },
    spare
}

RAB-Identity ::= CHOICE {
    gsm-MAP-RAB-Identity
    ansi-41-RAB-Identity
}

RAI ::= SEQUENCE {
    lai,
    LAI,
    rac
    RoutingAreaCode
}

RoutingAreaCode ::= BIT STRING (SIZE (8))

RoutingParameter ::= BIT STRING (SIZE (10))

TMSI-GSM-MAP ::= BIT STRING (SIZE (32))

-- *****
-- 
--     UTRAN MOBILITY INFORMATION ELEMENTS (10.3.2)
-- 
-- *****

AccessClassBarred ::= ENUMERATED {
    barred,
    notBarred }

AccessClassBarredList ::= SEQUENCE (SIZE (maxAC)) OF
    AccessClassBarred

AllowedIndicator ::= ENUMERATED {
    allowed,
    notAllowed }

CellAccessRestriction ::= SEQUENCE {
    cellBarred,
    CellBarred,
    cellReservedForOperatorUse,
    ReservedIndicator,
    cellReservationExtension,
    ReservedIndicator,
    -- NOTE: IE accessClassBarredList should not be included if the IE CellAccessRestriction
    -- is included in the IE SysInfoType4
    accessClassBarredList
        AccessClassBarredList
        OPTIONAL
}

CellBarred ::= CHOICE {
    barred
        SEQUENCE {
            intraFreqCellReselectionInd
                AllowedIndicator,

```

```

        t-Barred
    },
    notBarred
}
}

CellIdentity ::= BIT STRING (SIZE (28))

CellIdentity-PerRL-List ::= SEQUENCE (SIZE (1..maxRL)) OF CellIdentity

CellSelectReselectInfoSIB-3-4 ::= SEQUENCE {
    mappingInfo
    cellSelectQualityMeasure
        cpich-Ec-N0
            -- Default value for q-HYST-2-S is q-HYST-1-S
            q-HYST-2-S
                Q-Hyst-S
            -- Default value for q-HYST-2-S is q-HYST-1-S
        },
        cpich-RSCP
    },
    modeSpecificInfo
        fdd
            s-Intrasearch
            s-Intersearch
            s-SearchHCS
            rat-List
            q-QualMin
            q-RxlevMin
        },
        tdd
            s-Intrasearch
            s-Intersearch
            s-SearchHCS
            rat-List
            q-RxlevMin
    },
    q-Hyst-1-S
    t-Reselection-S
    hcs-ServingCellInformation
    maxAllowedUL-TX-Power
}

MapParameter ::= INTEGER (0..99)

Mapping ::= SEQUENCE {
    rat
    mappingFunctionParameterList
}

Mapping-LCR-r4 ::= SEQUENCE {
    mappingFunctionParameterList
}

MappingFunctionParameter ::= SEQUENCE {
    functionType
    mapParameter1
    mapParameter2
        -- The presence of upperLimit is conditional on the number of repetition
        upperLimit
}

MappingFunctionParameterList ::= SEQUENCE (SIZE (1..maxMeasIntervals)) OF
    MappingFunctionParameter

MappingFunctionType ::= ENUMERATED {
    linear,
    functionType2,
    functionType3,
    functionType4 }

-- In MappingInfo list, mapping for FDD and 3.84Mcps TDD is defined.
-- For 1.28Mcps TDD, Mapping-LCR-r4 is used instead.
MappingInfo ::= SEQUENCE (SIZE (1..maxRAT)) OF
    Mapping

-- Actual value Q-Hyst-S = IE value * 2
Q-Hyst-S ::= INTEGER (0..20)

RAT ::= ENUMERATED {

```

```

        ultra-FDD,
        ultra-TDD,
        gsm,
        cdma2000 }

RAT-FDD-Info ::= SEQUENCE {
    rat-Identifier,
    S-SearchRAT
    S-HCS-RAT
    S-Limit-SearchRAT
} OPTIONAL,

RAT-FDD-InfoList ::= SEQUENCE (SIZE (1..maxOtherRAT)) OF
    RAT-FDD-Info

RAT-Identifier ::= ENUMERATED {
    gsm, cdma2000 }

RAT-TDD-Info ::= SEQUENCE {
    rat-Identifier,
    S-SearchRAT
    S-HCS-RAT
    S-Limit-SearchRAT
} OPTIONAL,

RAT-TDD-InfoList ::= SEQUENCE (SIZE (1..maxOtherRAT)) OF
    RAT-TDD-Info

ReservedIndicator ::= ENUMERATED {
    reserved,
    notReserved }

-- Actual value S-SearchedQual = IE value * 2
S-SearchQual ::= INTEGER (-16..10)

-- Actual value S-SearchRXLEV = (IE value * 2) + 1
S-SearchRXLEV ::= INTEGER (-53..45)

T-Barred ::= ENUMERATED {
    s10, s20, s40, s80,
    s160, s320, s640, s1280 }

T-Reselection-S ::= INTEGER (0..31)

-- For UpperLimit, the used range depends on the RAT used.
UpperLimit ::= INTEGER (1..91)

URA-Identity ::= BIT STRING (SIZE (16))

URA-IdentityList ::= SEQUENCE (SIZE (1..maxURA)) OF
    URA-Identity

-- ****
-- USER EQUIPMENT INFORMATION ELEMENTS (10.3.3)
-- ****

AccessStratumReleaseIndicator ::= ENUMERATED {
    rel-4, spare15, spare14, spare13,
    spare12, spare11, spare10, spare9, spare8,
    spare7, spare6, spare5, spare4, spare3,
    spare2, spare1 }

-- TABULAR : for ActivationTime, value 'now' always appear as default, and is encoded
-- by absence of the field
ActivationTime ::= INTEGER (0..255)

BackoffControlParams ::= SEQUENCE {
    n-AP-RetransMax,
    N-AccessFails,
    nf-BO-NoAICH,
    ns-BO-Busy,
    nf-BO-AllBusy,
    nf-BO-Mismatch,
    t-CPCH
}

C-RNTI ::= BIT STRING (SIZE (16))

```

```

CapabilityUpdateRequirement ::= SEQUENCE {
    ue-RadioCapabilityFDDUpdateRequirement-FDD    BOOLEAN,
    -- ue-RadioCapabilityTDDUpdateRequirement-TDD is for 3.84Mcps TDD update requirement
    ue-RadioCapabilityTDDUpdateRequirement-TDD    BOOLEAN,
    systemSpecificCapUpdateReqList      SystemSpecificCapUpdateReqList      OPTIONAL
}

CapabilityUpdateRequirement-r4-ext ::= SEQUENCE {
    ue-RadioCapabilityUpdateRequirement-TDD128    BOOLEAN
}

CapabilityUpdateRequirement-r4 ::= SEQUENCE {
    ue-RadioCapabilityFDDUpdateRequirement-FDD    BOOLEAN,
    ue-RadioCapabilityTDDUpdateRequirement-TDD384  BOOLEAN,
    ue-RadioCapabilityTDDUpdateRequirement-TDD128  BOOLEAN,
    systemSpecificCapUpdateReqList      SystemSpecificCapUpdateReqList      OPTIONAL
}

CellUpdateCause ::= ENUMERATED {
    cellReselection,
    periodicalCellUpdate,
    uplinkDataTransmission,
    utran-pagingResponse,
    re-enteredServiceArea,
    radiolinkFailure,
    rlc-unrecoverableError,
    spare1
}

ChipRateCapability ::= ENUMERATED {
    mcps3-84, mcps1-28
}

CipheringAlgorithm ::= ENUMERATED {
    uea0, uea1
}

CipheringModeCommand ::= CHOICE {
    startRestart
    dummy
    NULL
}

CipheringModeInfo ::= SEQUENCE {
    -- TABULAR: The ciphering algorithm is included in the CipheringModeCommand.
    cipheringModeCommand      CipheringModeCommand,
    activationTimeForDPCH     ActivationTime           OPTIONAL,
    rb-DL-CiphActivationTimeInfo RB-ActivationTimeInfoList   OPTIONAL
}

CN-DRX-CycleLengthCoefficient ::= INTEGER (6..9)

CN-PagedUE-Identity ::= CHOICE {
    imsi-GSM-MAP
    tmsi-GSM-MAP
    p-TMSI-GSM-MAP
    imsi-DS-41
    tmsi-DS-41
    spare3
    spare2
    spare1
}

CompressedModeMeasCapability ::= SEQUENCE {
    fdd-Measurements          BOOLEAN,
    -- TABULAR: The IEs tdd-Measurements, gsm-Measurements and multiCarrierMeasurements
    -- are made optional since they are conditional based on another information element.
    -- Their absence corresponds to the case where the condition is not true.
    tdd-Measurements          BOOLEAN           OPTIONAL,
    gsm-Measurements          GSM-Measurements   OPTIONAL,
    multiCarrierMeasurements  BOOLEAN           OPTIONAL
}

CompressedModeMeasCapability-LCR-r4 ::= SEQUENCE {
    tdd128-Measurements       BOOLEAN           OPTIONAL
}

CompressedModeMeasCapabFDDList ::= SEQUENCE (SIZE (1..maxFreqBandsFDD)) OF
    CompressedModeMeasCapabFDD

CompressedModeMeasCapabFDD ::= SEQUENCE {
    radioFrequencyBandFDD    RadioFrequencyBandFDD   OPTIONAL,
}

```

```

dl-MeasurementsFDD                         BOOLEAN,
ul-MeasurementsFDD                         BOOLEAN
}

CompressedModeMeasCapabTDDList ::= SEQUENCE (SIZE (1..maxFreqBandsTDD)) OF
                                    CompressedModeMeasCapabTDD

CompressedModeMeasCapabTDD ::= SEQUENCE {
    radioFrequencyBandTDD                  RadioFrequencyBandTDD,
    dl-MeasurementsTDD                   BOOLEAN,
    ul-MeasurementsTDD                   BOOLEAN
}

CompressedModeMeasCapabGSMList ::= SEQUENCE (SIZE (1..maxFreqBandsGSM)) OF
                                    CompressedModeMeasCapabGSM

CompressedModeMeasCapabGSM ::= SEQUENCE {
    radioFrequencyBandGSM                RadioFrequencyBandGSM,
    dl-MeasurementsGSM                 BOOLEAN,
    ul-MeasurementsGSM                 BOOLEAN
}

CompressedModeMeasCapabMC ::= SEQUENCE {
    dl-MeasurementsMC                  BOOLEAN,
    ul-MeasurementsMC                  BOOLEAN
}

CPCH-Parameters ::= SEQUENCE {
    initialPriorityDelayList           InitialPriorityDelayList          OPTIONAL,
    backoffControlParams              BackoffControlParams,
    -- TABULAR: TPC step size nested inside PowerControlAlgorithm
    powerControlAlgorithm             PowerControlAlgorithm,
    dl-DPCCH-BER                      DL-DPCCH-BER
}

DL-CapabilityWithSimultaneousHS-DSCHConfig ::= ENUMERATED{kbps32, kbps64, kbps128, kbps384}

DL-DPCCH-BER ::= INTEGER (0..63)

DL-PhysChCapabilityFDD ::= SEQUENCE {
    maxNoDPCH-PDSCH-Codes            INTEGER (1..8),
    maxNoPhysChBitsReceived          MaxNoPhysChBitsReceived,
    supportForSF-512                 BOOLEAN,
    supportOfPDSCH                  BOOLEAN,
    simultaneousSCCPCH-DPCH-Reception SimultaneousSCCPCH-DPCH-Reception
}

DL-PhysChCapabilityFDD-v380ext ::= SEQUENCE {
    supportOfDedicatedPilotsForChEstimation SupportOfDedicatedPilotsForChEstimation      OPTIONAL
}

SupportOfDedicatedPilotsForChEstimation ::= ENUMERATED { true }

DL-PhysChCapabilityTDD ::= SEQUENCE {
    maxTS-PerFrame                  MaxTS-PerFrame,
    maxPhysChPerFrame               MaxPhysChPerFrame,
    minimumSF                        MinimumSF-DL,
    supportOfPDSCH                  BOOLEAN,
    maxPhysChPerTS                  MaxPhysChPerTS
}

DL-PhysChCapabilityTDD-LCR-r4 ::= SEQUENCE {
    maxTS-PerSubFrame               MaxTS-PerSubFrame-r4,
    maxPhysChPerFrame               MaxPhysChPerSubFrame-r4,
    minimumSF                        MinimumSF-DL,
    supportOfPDSCH                  BOOLEAN,
    maxPhysChPerTS                  MaxPhysChPerTS,
    supportOf8PSK                    BOOLEAN
}

DL-TransChCapability ::= SEQUENCE {
    maxNoBitsReceived               MaxNoBits,
    maxConvCodeBitsReceived          MaxNoBits,
    turboDecodingSupport            TurboSupport,
    maxSimultaneousTransChs         MaxSimultaneousTransChsDL,
    maxSimultaneousCCTrCH-Count     MaxSimultaneousCCTrCH-Count,
    maxReceivedTransportBlocks       MaxTransportBlocksDL,
    maxNumberOfTFC-DL                MaxNumberOfTFC-DL,
    maxNumberOfTF                   MaxNumberOfTF
}

```

```

}

DRAC-SysInfo ::= SEQUENCE {
    transmissionProbability,
    maximumBitRate
}

DRAC-SysInfoList ::= SEQUENCE (SIZE (1..maxDRACclasses)) OF
    DRAC-SysInfo

DSCH-RNTI ::= BIT STRING (SIZE (16))

ESN-DS-41 ::= BIT STRING (SIZE (32))

EstablishmentCause ::= ENUMERATED {
    originatingConversationalCall,
    originatingStreamingCall,
    originatingInteractiveCall,
    originatingBackgroundCall,
    originatingSubscribedTrafficCall,
    terminatingConversationalCall,
    terminatingStreamingCall,
    terminatingInteractiveCall,
    terminatingBackgroundCall,
    emergencyCall,
    interRAT-CellReselection,
    interRAT-CellChangeOrder,
    registration,
    detach,
    originatingHighPrioritySignalling,
    originatingLowPrioritySignalling,
    callRe-establishment,
    terminatingHighPrioritySignalling,
    terminatingLowPrioritySignalling,
    terminatingCauseUnknown,
    spare12,
    spare11,
    spare10,
    spare9,
    spare8,
    spare7,
    spare6,
    spare5,
    spare4,
    spare3,
    spare2,
    spare1
}

FailureCauseWithProtErr ::= CHOICE {
    configurationUnsupported      NULL,
    physicalChannelFailure       NULL,
    incompatibleSimultaneousReconfiguration   NULL,
    compressedModeRuntimeError   TGPsi,
    protocolError                ProtocolErrorInformation,
    cellUpdateOccurred           NULL,
    invalidConfiguration          NULL,
    configurationIncomplete      NULL,
    unsupportedMeasurement        NULL,
    spare7                      NULL,
    spare6                      NULL,
    spare5                      NULL,
    spare4                      NULL,
    spare3                      NULL,
    spare2                      NULL,
    spare1                      NULL
}

FailureCauseWithProtErrTrId ::= SEQUENCE {
    rrc-TransactionIdentifier,
    failureCause
}

GSM-Measurements ::= SEQUENCE {
    gsm900 BOOLEAN,
    dcs1800 BOOLEAN,
    gsm1900 BOOLEAN
}

```

```

H-RNTI ::= BIT STRING (SIZE (16))

HSDSCH-capability-class ::= INTEGER (0..63)

UESpecificBehaviourInformation2 ::= CHOICE {
    uESpecificBehaviourInformation2fixednotavailable      NULL,
    uESpecificBehaviourInformation2fixed                 UESpecificBehaviourInformation2fixed,
    uESpecificBehaviourInformation2variable            UESpecificBehaviourInformation2variable,
    spare                                         NULL
}

UESpecificBehaviourInformation2fixed ::= = BIT STRING (SIZE (16))
UESpecificBehaviourInformation2variable ::= = BIT STRING (SIZE (1..256))

IMSI-and-ESN-DS-41 ::= SEQUENCE {
    imsi-DS-41           IMSI-DS-41,
    esn-DS-41            ESN-DS-41
}

IMSI-DS-41 ::= OCTET STRING (SIZE (5..7))

InitialPriorityDelayList ::= SEQUENCE (SIZE (1..maxASC)) OF
                            NS-IP

END

```

## 11.5 RRC information between network nodes

```
Internode-definitions DEFINITIONS AUTOMATIC TAGS ::=
```

```
BEGIN
```

```
IMPORTS
```

```

HandoverToUTRANCommand,
MeasurementReport,
PhysicalChannelReconfiguration,
RadioBearerReconfiguration,
RadioBearerRelease,
RadioBearerSetup,
RRC-FailureInfo-r3-IEs,
TransportChannelReconfiguration
FROM PDU-definitions

```

```

-- Core Network IEs :
CN-DomainIdentity,
CN-DomainInformationList,
CN-DomainInformationListFull,
CN-DRX-CycleLengthCoefficient,
NAS-SystemInformationGSM-MAP,
-- UTRAN Mobility IEs :
CellIdentity,
URA-Identity,
-- User Equipment IEs :
AccessStratumReleaseIndicator,
C-RNTI,
ChipRateCapability,
DL-PhysChCapabilityFDD-v380ext,
DL-PhysChCapabilityTDD,
DL-PhysChCapabilityTDD-LCR-r4,
GSM-Measurements,
FailureCauseWithProtErr,
MaxHcContextSpace,
MaxNoPhysChBitsReceived,
MaxROHC-ContextSessions-r4,
NetworkAssistedGPS-Supported,
RadioFrequencyBandTDDList,
RLC-Capability,
RRC-MessageSequenceNumber,
SecurityCapability,
SimultaneousSCCPCH-DPCH-Reception,
STARTList,
STARTSingle,
START-Value,
SupportOfDedicatedPilotsForChEstimation,
TransportChannelCapability,

```

```

TxRxFrequencySeparation,
U-RNTI,
UE-MultiModeRAT-Capability,
UE-PowerClass-v370,
UE-RadioAccessCapabBandFDDList,
UE-RadioAccessCapability,
UE-RadioAccessCapability-v370ext,
UE-RadioAccessCapability-v380ext,
UE-RadioAccessCapability-v3a0ext,
UE-RadioAccessCapability-v4xyext,
UL-PhysChCapabilityFDD,
UL-PhysChCapabilityTDD,
UL-PhysChCapabilityTDD-LCR-r4,
-- Radio Bearer IEs :
PredefinedConfigStatusList,
PredefinedConfigValueTag,
RAB-InformationSetupList,
RAB-InformationSetupList-r4,
RAB-Identity,
RB-Identity,
RB-Identity,
SRB-InformationSetupList,
-- Transport Channel IEs :
CPCH-SetID,
DL-CommonTransChInfo,
DL-CommonTransChInfo-r4,
DL-AddReconfTransChInfoList,
DL-AddReconfTransChInfoList-r4,
DRAC-StaticInformationList,
UL-CommonTransChInfo,
UL-CommonTransChInfo-r4,
UL-AddReconfTransChInfoList,
-- Measurement IEs :
MeasurementIdentity,
MeasurementReportingMode,
MeasurementType,
MeasurementType-r4,
AdditionalMeasurementID-List,
PositionEstimate,
UE-Positioning-IPDL-Parameters-TDD-r4-ext,
-- Other IEs :
InterRAT-UE-RadioAccessCapabilityList
FROM InformationElements

maxCNdomains,
maxNoOfMeas,

maxRB,
maxRBallRABs,
maxRFC3095-CID,
maxSRBsetup
FROM Constant-definitions
;

-- Part 1: Class definitions similar to what has been defined in 11.1 for RRC messages
-- Information that is transferred in the same direction and across the same path is grouped

-- ****
-- 
-- RRC information, to target RNC
-- 
-- ****
-- RRC Information to target RNC sent either from source RNC or from another RAT

ToTargetRNC-Container ::= CHOICE {
    interRATHandoverInfo           InterRATHandoverInfoWithInterRATCapabilities-r3,
    srncRelocation                 SRNC-RelocationInfo-r3,
    rfc3095-ContextInfo            RFC3095-ContextInfo-r5,
    extension                       NULL
}

-- ****
-- 
-- RRC information, target RNC to source RNC
-- 
-- ****

Target-RNC-ToSourceRNC-Container ::= CHOICE {

```

```

radioBearerSetup           RadioBearerSetup,
radioBearerReconfiguration RadioBearerReconfiguration,
radioBearerRelease         RadioBearerRelease,
transportChannelReconfiguration TransportChannelReconfiguration,
physicalChannelReconfiguration PhysicalChannelReconfiguration,
rrc-FailureInfo          RRC-FailureInfo-r3-IEs,
dL-DCCHmessage           OCTET STRING,
extension                 NULL
}

-- Part 2: Container definitions, similar to the PDU definitions in 11.2 for RRC messages
-- In alphabetical order

-- ****
-- Handover to UTRAN information
-- ****

InterRATHandoverInfoWithInterRATCapabilities-r3 ::= CHOICE {
    r3           SEQUENCE {
        -- IE InterRATHandoverInfoWithInterRATCapabilities-r3-IEs also
        -- includes non critical extensions
        interRATHandoverInfo-r3      InterRATHandoverInfoWithInterRATCapabilities-r3-IEs,
        v390NonCriticalExtensions   SEQUENCE {
            interRATHandoverInfoWithInterRATCapabilities-v390ext
        InterRATHandoverInfoWithInterRATCapabilities-v390ext-IEs,
            -- Reserved for future non critical extension
            nonCriticalExtensions     SEQUENCE {} OPTIONAL
        }
        OPTIONAL
    },
    criticalExtensions       SEQUENCE {}
}

InterRATHandoverInfoWithInterRATCapabilities-r3-IEs ::= SEQUENCE {
    -- The order of the IEs may not reflect the tabular format
    -- but has been chosen to simplify the handling of the information in the BSC
    -- Other IEs
    ue-RATSpecificCapability   InterRAT-UE-RadioAccessCapabilityList OPTIONAL,
    -- interRATHandoverInfo, Octet string is used to obtain 8 bit length field prior to
    -- actual information. This makes it possible for BSS to transparently handle information
    -- received via GSM air interface even when it includes non critical extensions.
    -- The octet string shall include the InterRATHandoverInfo information
    -- The BSS can re-use the 04.18 length field received from the MS
    interRATHandoverInfo       OCTET STRING (SIZE (0..255))
}

InterRATHandoverInfoWithInterRATCapabilities-v390ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    failureCauseWithProtErr   FailureCauseWithProtErr
                                OPTIONAL
}

-- ****
-- RFC3095 context, source RNC to target RNC
-- ****

RFC3095-ContextInfo-r5 ::= CHOICE {
    r5           SEQUENCE {
        rFC3095-ContextInfoList-r5      RFC3095-ContextInfoList-r5,
        -- Reserved for future non critical extension
        nonCriticalExtensions         SEQUENCE {} OPTIONAL
    },
    criticalExtensions       SEQUENCE {}
}

RFC3095-ContextInfoList-r5 ::= SEQUENCE (SIZE (1..maxRBallRABs)) OF
                            RFC3095-ContextInfo

-- ****
-- SRNC Relocation information
-- ****

SRNC-RelocationInfo-r3 ::= CHOICE {

```

```

r3
    SEQUENCE {
        sRNC-RelocationInfo-r3           SRNC-RelocationInfo-r3-IEs,
        v380NonCriticalExtensions       SEQUENCE {
            sRNC-RelocationInfo-v380ext SRNC-RelocationInfo-v380ext-IEs,
            -- Reserved for future non critical extension
            v390NonCriticalExtensions   SEQUENCE {
                sRNC-RelocationInfo-v390ext      SRNC-RelocationInfo-v390ext-IEs,
                v3a0NonCriticalExtensions     SEQUENCE {
                    sRNC-RelocationInfo-v3a0ext      SRNC-RelocationInfo-v3a0ext-IEs,
                    v3b0NonCriticalExtensions   SEQUENCE {
                        sRNC-RelocationInfo-v3b0ext      SRNC-RelocationInfo-v3b0ext-IEs,
                        v3c0NonCriticalExtensions   SEQUENCE {
                            sRNC-RelocationInfo-v3c0ext      SRNC-RelocationInfo-v3c0ext-IEs,
                            v3d0NonCriticalExtensions SEQUENCE {
                                sRNC-RelocationInfo-v3d0ext      SRNC-RelocationInfo-v3d0ext-IEs,
                                v4xyNonCriticalExtensions SEQUENCE {
                                    sRNC-RelocationInfo-v4xyext      SRNC-RelocationInfo-v4xyext-
                                    IEs,
                                    -- Reserved for future non critical extension
                                    nonCriticalExtensions      SEQUENCE {} OPTIONAL
                                } OPTIONAL
                            } OPTIONAL
                        } OPTIONAL
                    } OPTIONAL
                } OPTIONAL
            } OPTIONAL
        } OPTIONAL
    },
    later-than-r3
    CHOICE {
        r4
            SEQUENCE {
                sRNC-RelocationInfo-r4           SRNC-RelocationInfo-r4-IEs,
                nonCriticalExtensions         SEQUENCE {} OPTIONAL
            },
            criticalExtensions            SEQUENCE {}
        }
    }
}

SRNC-RelocationInfo-r3-IEs ::= SEQUENCE {
    -- Non-RRC IEs
    stateOfRRC                  StateOfRRC,
    stateOfRRC-Procedure          StateOfRRC-Procedure,
    -- Ciphering related information IEs
    -- If the extension v380 is included use the extension for the ciphering status per CN domain
    cipheringStatus               CipheringStatus,
    calculationTimeForCiphering   CalculationTimeForCiphering OPTIONAL,
    -- The order of occurrence in the IE cipheringInfoPerRB-List is the
    -- same as the RBs in the IE "Signalling RB information list" and in the
    -- IE "RAB information list". The signalling RBs are supposed to be listed
    -- first. Only UM and AM RBs that are ciphered are listed here
    cipheringInfoPerRB-List       CipheringInfoPerRB-List OPTIONAL,
    count-C-List                 COUNT-C-List OPTIONAL,
    integrityProtectionStatus    IntegrityProtectionStatus,
    srb-SpecificIntegrityProtInfo SRB-SpecificIntegrityProtInfoList,
    implementationSpecificParams ImplementationSpecificParams OPTIONAL,
    -- User equipment IEs
    u-RNTI                      U-RNTI,
    c-RNTI                      C-RNTI OPTIONAL,
    ue-RadioAccessCapability     UE-RadioAccessCapability,
    ue-Positioning-LastKnownPos  UE-Positioning-LastKnownPos OPTIONAL,
    -- Other IEs
    ue-RATSpecificCapability    InterRAT-UE-RadioAccessCapabilityList OPTIONAL,
    -- UTRAN mobility IEs
    ura-Identity                 URA-Identity OPTIONAL,
    -- Core network IEs
    cn-CommonGSM-MAP-NAS-SysInfo NAS-SystemInformationGSM-MAP,
    cn-DomainInformationList     CN-DomainInformationList OPTIONAL,
    -- Measurement IEs
    ongoingMeasRepList           OngoingMeasRepList OPTIONAL,
    -- Radio bearer IEs
    predefinedConfigStatusList   PredefinedConfigStatusList,
    srb-InformationList          SRB-InformationSetupList,
    rab-InformationList          RAB-InformationSetupList OPTIONAL,
    -- Transport channel IEs
    ul-CommonTransChInfo         UL-CommonTransChInfo OPTIONAL,
    ul-TransChInfoList           UL-AddReconfTransChInfoList OPTIONAL,
    modeSpecificInfo             CHOICE {
        fdd
            SEQUENCE {
                cpch-SetID                 CPCH-SetID OPTIONAL,
                transChDRAC-Info           DRAC-StaticInformationList OPTIONAL
            }
        }
    }
}

```

```

        },
        tdd           NULL
    },
    dl-CommonTransChInfo      DL-CommonTransChInfo          OPTIONAL,
    dl-TransChInfoList        DL-AddReconfTransChInfoList  OPTIONAL,
-- Measurement report
    measurementReport         MeasurementReport           OPTIONAL ,
    nonCriticalExtensions    SEQUENCE {
        -- In case of TDD only up-IpdL-Parameters-TDD is present, otherwise
        -- this IE is absent
        up-IpdL-Parameters-TDD      UE-Positioning-IPDL-Parameters-TDD-r4-ext  OPTIONAL,
-- Extension mechanism for non- release4 information
        nonCriticalExtensions     SEQUENCE {}
    }
}
}

SRNC-RelocationInfo-v380ext-IEs ::= SEQUENCE {
    -- Ciphering related information IEs
    cn-DomainIdentity          CN-DomainIdentity,
    cipheringStatusList        CipheringStatusList
}

SRNC-RelocationInfo-v390ext-IEs ::= SEQUENCE {
    cn-DomainInformationList-v390ext   CN-DomainInformationList-v390ext      OPTIONAL,
    ue-RadioAccessCapability-v370ext   UE-RadioAccessCapability-v370ext      OPTIONAL,
    ue-RadioAccessCapability-v380ext   UE-RadioAccessCapability-v380ext      OPTIONAL,
    dl-PhysChCapabilityFDD-v380ext    DL-PhysChCapabilityFDD-v380ext,
    failureCauseWithProtErr        FailureCauseWithProtErr      OPTIONAL
}

SRNC-RelocationInfo-v3a0ext-IEs ::= SEQUENCE {
    -- cn-domain identity for IE startValueForCiphering-v3a0ext is specified
    -- in subsequent extension (SRNC-RelocationInfo-v3b0ext-IEs)
    startValueForCIphering-v3a0ext    START-Value,
    cipheringInfoForSRB1-v3a0ext     CipheringInfoForSRB1-v3a0ext,
    ue-RadioAccessCapability-v3a0ext  UE-RadioAccessCapability-v3a0ext      OPTIONAL
}

SRNC-RelocationInfo-v3b0ext-IEs ::= SEQUENCE {
    -- cn-domain identity for IE startValueForCiphering-v3a0ext included in previous extension
    cn-DomainIdentity              CN-DomainIdentity,
    -- the remaining start values are contained in IE startValueForCiphering-v3b0ext
    startValueForCiphering-v3b0ext   STARTList2      OPTIONAL
}

SRNC-RelocationInfo-v3c0ext-IEs ::= SEQUENCE {
    -- IE rb-IdentityForHOMessage includes the identity of the RB used by the source SRNC
    -- to send the message contained in the IE "TargetRNC-ToSourceRNC-Container".
    -- Only included if type is "UE involved"
    rb-IdentityForHOMessage        RB-Identity      OPTIONAL
}

SRNC-RelocationInfo-v3d0ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ueSpecificBehaviourInformation2    UEspecificBehaviourInformation2      OPTIONAL
}

STARTList2 ::=           SEQUENCE (SIZE (2..maxCNdomains)) OF
                        STARTSingle

SRNC-RelocationInfo-v4xyext-IEs ::= SEQUENCE {
    ue-RadioAccessCapability-v4xyext  UE-RadioAccessCapability-v4xyext
}

CipheringInfoForSRB1-v3a0ext ::= SEQUENCE {
    dl-UM-SN                      BIT STRING (SIZE (7))
}

CipheringStatusList ::=           SEQUENCE (SIZE (1..maxCNdomains)) OF
                                    CipheringStatusCNdomain

CipheringStatusCNdomain ::=           SEQUENCE {
    cn-DomainIdentity              CN-DomainIdentity,
    cipheringStatus                CipheringStatus
}

SRNC-RelocationInfo-r4-IEs ::=           SEQUENCE {
    -- Non-RRC IEs
    -- IE rb-IdentityForHOMessage includes the identity of the RB used by the source SRNC
}

```

```

-- to send the message contained in the IE "TargetRNC-ToSourceRNC-Container".
-- Only included if type is "UE involved"
rb-IdentityForHOMessage          RB-Identity                               OPTIONAL,
stateOfRRC                        StateOfRRC,
stateOfRRC-Procedure              StateOfRRC-Procedure,
-- Ciphering related information IEs
cipheringStatusList              CipheringStatusList-r4,
latestConfiguredCN-Domain        CN-DomainIdentity,
calculationTimeForCiphering     CalculationTimeForCiphering      OPTIONAL,
count-C-List                      COUNT-C-List                  OPTIONAL,
cipheringInfoPerRB-List          CipheringInfoPerRB-List-r4    OPTIONAL,
-- Integrity protection related information IEs
integrityProtectionStatus        IntegrityProtectionStatus,
srB-SpecificIntegrityProtInfo   SRB-SpecificIntegrityProtInfoList, OPTIONAL,
implementationSpecificParams    ImplementationSpecificParams    OPTIONAL,
-- User equipment IEs
u-RNTI                           U-RNTI,
c-RNTI                           C-RNTI                               OPTIONAL,
ue-RadioAccessCapability         UE-RadioAccessCapability-r4,
ue-RadioAccessCapability-ext    UE-RadioAccessCapabBandFDDList  OPTIONAL,
ue-Positioning-LastKnownPos     UE-Positioning-LastKnownPos    OPTIONAL,
| | ueSpecificBehaviourInformation2      UESpecificBehaviourInformation2      OPTIONAL,
-- Other IEs
ue-RATSpecificCapability        InterRAT-UE-RadioAccessCapabilityList OPTIONAL,
-- UTRAN mobility IEs
ura-Identity                     URA-Identity                OPTIONAL,
-- Core network IEs
cn-CommonGSM-MAP-NAS-SysInfo   NAS-SystemInformationGSM-MAP,
cn-DomainInformationList         CN-DomainInformationListFull  OPTIONAL,
-- Measurement IEs
ongoingMeasRepList              OngoingMeasRepList-r4        OPTIONAL,
-- Radio bearer IEs
predefinedConfigStatusList       PredefinedConfigStatusList,
srB-InformationList             SRB-InformationSetupList,
rab-InformationList              RAB-InformationSetupList-r4  OPTIONAL,
-- Transport channel IEs
ul-CommonTransChInfo            UL-CommonTransChInfo-r4      OPTIONAL,
ul-TransChInfoList              UL-AddReconfTransChInfoList  OPTIONAL,
modeSpecificInfo
  fdd                            CHOICE {
    cpch-SetID                   CPCH-SetID                 OPTIONAL,
    transChDRAC-Info             DRAC-StaticInformationList OPTIONAL
  },
  tdd                            NULL
}
dl-CommonTransChInfo            DL-CommonTransChInfo-r4      OPTIONAL,
dl-TransChInfoList              DL-AddReconfTransChInfoList  OPTIONAL,
-- Measurement report
measurementReport               MeasurementReport           OPTIONAL,
failureCause                    FailureCauseWithProtErr    OPTIONAL
}

-- IE definitions

CalculationTimeForCiphering ::= SEQUENCE {
  cell-Id                         CellIdentity,
  sfn                                INTEGER (0..4095)
}

CipheringInfoPerRB ::= SEQUENCE {
  dl-HFN                           BIT STRING (SIZE (20..25)),
  ul-HFN                           BIT STRING (SIZE (20..25))
}

CipheringInfoPerRB-r4 ::= SEQUENCE {
  rb-Identity                      RB-Identity,
  dl-HFN                           BIT STRING (SIZE (20..25)),
  dl-UM-SN                          BIT STRING (SIZE (7))      OPTIONAL,
  ul-HFN                           BIT STRING (SIZE (20..25))
}

-- TABULAR: CipheringInfoPerRB-List, multiplicity value numberOfRadioBearers
-- has been replaced with maxRB.
CipheringInfoPerRB-List ::= SEQUENCE (SIZE (1..maxRB)) OF
  CipheringInfoPerRB

CipheringInfoPerRB-List-r4 ::= SEQUENCE (SIZE (1..maxRB)) OF
  CipheringInfoPerRB-r4

```

```

CipheringStatus ::= ENUMERATED {
    started, notStarted }

CipheringStatusList-r4 ::= SEQUENCE (SIZE (1..maxCNdomains)) OF
    CipheringStatusCNdomain-r4

CipheringStatusCNdomain-r4 ::= SEQUENCE {
    cn-DomainIdentity,
    cipheringStatus,
    start-Value
}

CN-DomainInformation-v390ext ::= SEQUENCE {
    cn-DRX-CycleLengthCoeff
}

CN-DomainInformationList-v390ext ::= SEQUENCE (SIZE (1..maxCNdomains)) OF
    CN-DomainInformation-v390ext

CompressedModeMeasCapability-r4 ::= SEQUENCE {
    fdd-Measurements
        BOOLEAN,
    -- TABULAR: The IEs tdd-Measurements, gsm-Measurements and multiCarrierMeasurements
    -- are made optional since they are conditional based on another information element.
    -- Their absence corresponds to the case where the condition is not true.
    tdd384-Measurements
        BOOLEAN
            OPTIONAL,
    tdd128-Measurements
        BOOLEAN
            OPTIONAL,
    gsm-Measurements
        GSM-Measurements
            OPTIONAL,
    multiCarrierMeasurements
        BOOLEAN
            OPTIONAL
}

COUNT-C-List ::= SEQUENCE (SIZE (1..maxCNdomains)) OF
    COUNT-CSingle

COUNT-CSingle ::= SEQUENCE {
    cn-DomainIdentity,
    count-C
}

DL-PhysChCapabilityFDD-r4 ::= SEQUENCE {
    maxNoDPCH-PDSCH-Codes
        INTEGER (1..8),
    maxNoPhysChBitsReceived
        MaxNoPhysChBitsReceived,
    supportForSF-512
        BOOLEAN,
    supportOfPDSCH
        BOOLEAN,
    simultaneousSCCPCH-DPCH-Reception
        SimultaneousSCCPCH-DPCH-Reception,
    supportOfDedicatedPilotsForChEstimation
        SupportOfDedicatedPilotsForChEstimation
            OPTIONAL
}

-- The structure of DL-RFC3095-Context is FFS
DL-RFC3095-Context ::= SEQUENCE {
    rfc3095-Context-Identity
        INTEGER (0..16383),
    dl-mode
        ENUMERATED {u, o, r}
}

ImplementationSpecificParams ::= BIT STRING (SIZE (1..512))

IntegrityProtectionStatus ::= ENUMERATED {
    started, notStarted }

MeasurementCapability-r4 ::= SEQUENCE {
    downlinkCompressedMode,
    uplinkCompressedMode
}

MeasurementCommandWithType ::= CHOICE {
    setup
        MeasurementType,
    modify
        NULL,
    release
        NULL
}

MeasurementCommandWithType-r4 ::= CHOICE {
    setup
        MeasurementType-r4,
    modify
        NULL,
    release
        NULL
}

OngoingMeasRep ::= SEQUENCE {
    measurementIdentity
}

```

```

-- TABULAR: The CHOICE Measurement in the tabular description is included
-- in MeasurementCommandWithType
measurementCommandWithType      MeasurementCommandWithType,
measurementReportingMode      MeasurementReportingMode          OPTIONAL,
additionalMeasurementID-List  AdditionalMeasurementID-List    OPTIONAL
}

OngoingMeasRep-r4 ::=           SEQUENCE {
  measurementIdentity      MeasurementIdentity,
-- TABULAR: The CHOICE Measurement in the tabular description is included
-- in MeasurementCommandWithType-r4.
  measurementCommandWithType MeasurementCommandWithType-r4,
  measurementReportingMode  MeasurementReportingMode          OPTIONAL,
  additionalMeasurementID-List AdditionalMeasurementID-List    OPTIONAL
}

OngoingMeasRepList ::=          SEQUENCE (SIZE (1..maxNoOfMeas)) OF
                                OngoingMeasRep

OngoingMeasRepList-r4 ::=        SEQUENCE (SIZE (1..maxNoOfMeas)) OF
                                OngoingMeasRep-r4

PDCP-Capability-r4 ::=          SEQUENCE {
  losslessSRNS-RelocationSupport BOOLEAN,
  supportForRfc2507                CHOICE {
    notSupported                  NULL,
    supported                      MaxHcContextSpace
  },
  supportForRfc3095                CHOICE {
    notSupported                  NULL,
    supported                      SEQUENCE {
      maxROHC-ContextSessions     MaxROHC-ContextSessions-r4 DEFAULT s16,
      reverseCompressionDepth     INTEGER (0..65535)      DEFAULT 0
    }
  }
}

PhysicalChannelCapability-r4 ::= SEQUENCE {
  fddPhysChCapability            SEQUENCE {
    downlinkPhysChCapability    DL-PhysChCapabilityFDD-r4,
    uplinkPhysChCapability      UL-PhysChCapabilityFDD
                                OPTIONAL,
  },
  tdd384-PhysChCapability       SEQUENCE {
    downlinkPhysChCapability    DL-PhysChCapabilityTDD,
    uplinkPhysChCapability      UL-PhysChCapabilityTDD
                                OPTIONAL,
  },
  tdd128-PhysChCapability       SEQUENCE {
    downlinkPhysChCapability    DL-PhysChCapabilityTDD-LCR-r4,
    uplinkPhysChCapability      UL-PhysChCapabilityTDD-LCR-r4
                                OPTIONAL
  }
}

RF-Capability-r4 ::=           SEQUENCE {
  fddRF-Capability              SEQUENCE {
    ue-PowerClass                UE-PowerClass-v370,
    txRxFrequencySeparation     TxRxFrequencySeparation
                                OPTIONAL,
  },
  tdd384-RF-Capability          SEQUENCE {
    ue-PowerClass                UE-PowerClass-v370,
    radioFrequencyBandTDDList    RadioFrequencyBandTDDList,
    chipRateCapability           ChipRateCapability
                                OPTIONAL,
  },
  tdd128-RF-Capability          SEQUENCE {
    ue-PowerClass                UE-PowerClass-v370,
    radioFrequencyBandTDDList    RadioFrequencyBandTDDList,
    chipRateCapability           ChipRateCapability
                                OPTIONAL
  }
}

RFC3095-ContextInfo ::=         SEQUENCE {
  rb-Identity                  RB-Identity,
  rfc3095-Context-List         RFC3095-Context-List
}

RFC3095-Context-List ::=        SEQUENCE (SIZE (1..maxRFC3095-CID)) OF SEQUENCE {
  dl-RFC3095-Context           OPTIONAL,
  ul-RFC3095-Context           OPTIONAL
}

```

```

SRB-SpecificIntegrityProtInfo ::= SEQUENCE {
    ul-RRC-HFN
    dl-RRC-HFN
    ul-RRC-SequenceNumber
    dl-RRC-SequenceNumber
}
SRB-SpecificIntegrityProtInfoList ::= SEQUENCE (SIZE (4..maxSRBsetup)) OF
    SRB-SpecificIntegrityProtInfo

StateOfRRC ::= ENUMERATED {
    cell-DCH, cell-FACH,
    cell-PCH, ura-PCH }

StateOfRRC-Procedure ::= ENUMERATED {
    awaitNoRRC-Message,
    awaitRB-ReleaseComplete,
    awaitRB-SetupComplete,
    awaitRB-ReconfigurationComplete,
    awaitTransportCH-ReconfigurationComplete,
    awaitPhysicalCH-ReconfigurationComplete,
    awaitActiveSetUpdateComplete,
    awaitHandoverComplete,
    sendCellUpdateConfirm,
    sendUraUpdateConfirm,
    -- dummy is not used in this version of specification
    -- It should not be sent
    dummy,
    otherStates
}

UE-Positioning-Capability-r4 ::= SEQUENCE {
    standaloneLocMethodsSupported      BOOLEAN,
    ue-BasedOTDOA-Supported           BOOLEAN,
    networkAssistedGPS-Supported      NetworkAssistedGPS-Supported,
    supportForUE-GPS-TimingOfCellFrames BOOLEAN,
    supportForIPDL                    BOOLEAN,
    rx-tx-TimeDifferenceType2Capable  BOOLEAN,
    validity-CellPCH-UraPCH           ENUMERATED { true (0) }      OPTIONAL
}
UE-Positioning-LastKnownPos ::= SEQUENCE {
    sfn
    cell-id
    positionEstimate
}
UE-RadioAccessCapability-r4 ::= SEQUENCE {
    accessStratumReleaseIndicator,
    pdcp-Capability
    rlc-Capability
    transportChannelCapability
    rf-Capability
    physicalChannelCapability
    ue-MultiModeRAT-Capability
    securityCapability
    ue-positioning-Capability
    measurementCapability
}
-- The structure of UL-RFC3095-Context is FFS
UL-RFC3095-Context ::= SEQUENCE {
    rfc3095-Context-Identity      INTEGER (0..16383),
    ul-mode                         ENUMERATED {u, o, r}
}

END

```

#### 14.12.4.2 SRNS RELOCATION INFO

This RRC message is sent between network nodes when preparing for an SRNS relocation.

With the presence or absence of the IE "RB identity for Hard Handover message" the source RNC indicates to the target SRNC whether the source RNC expects to receive the choice "DL DCCH message" in the IE "RRC information, target RNC to source RNC" in case the SRNS relocation is of type "UE involved". Furthermore the target RNC uses this information for the calculation of the MAC-I.

Direction: source RNC→target RNC

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
<b>Non RRC IEs</b>				
RB identity for Handover message	OP		RB identity 10.3.4.16	Gives the id of the radio bearer on which the source RNC will transmit the RRC message in the case the relocation is of type "UE involved".
>State of RRC	MP		RRC state indicator, 10.3.3.35a	
>State of RRC procedure	MP		Enumerated (await no RRC message, await RB Release Complete, await RB Setup Complete, await RB Reconfiguration Complete, await Transport CH Reconfiguration Complete, await Physical CH Reconfiguration Complete, await Active Set Update Complete, await Handover Complete, send Cell Update Confirm, send URA Update Confirm, , others)	
<b>Ciphering related information</b>				
>Ciphering status for each CN domain	MP	<1 to maxCNDomains>		
>>CN domain identity	MP		CN domain identity 10.3.1.1	
>>Ciphering status	MP		Enumerated(	)

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
			Not started, Started)	
>>START	MP		START 10.3.3.38	START value to be used in this CN domain.
>Latest configured CN domain	MP		CN domain identity 10.3.1.1	Value contained in the variable of the same name. In case this variable is empty, the source RNC can set any CN domain identity. In that case, the Ciphering status and the Integrity protection status should be Not started and the target RNC should not initialise the variable Latest configured CN domain.
>Calculation time for ciphering related information	CV-Ciphering			Time when the ciphering information of the message were calculated, relative to a cell of the target RNC
>>Cell Identity	MP		Cell Identity 10.3.2.2	Identity of one of the cells under the target RNC and included in the active set of the current call
>>SFN	MP		Integer(0..4095)	
>COUNT-C list	OP	1 to <maxCNdomains>		COUNT-C values for radio bearers using transparent mode RLC
>>CN domain identity	MP		CN domain identity 10.3.1.1	
>>COUNT-C	MP		Bit string(32)	
>Ciphering info per radio bearer	OP	1 to <maxRB>		For signalling radio bearers this IE is mandatory.
>>RB identity	MP		RB identity 10.3.4.16	
>>Downlink HFN	MP		Bit string(20..25)	This IE is either RLC AM HFN (20 bits) or RLC UM HFN (25 bits)
>>Downlink SN	CV-SRB1		Bit String(7)	VT(US) of RLC UM
>>Uplink HFN	MP		Bit string(20..25)	This IE is either RLC AM HFN (20 bits) or RLC UM HFN (25 bits)
<b>Integrity protection related information</b>				
>Integrity protection status	MP		Enumerated(Not started, Started)	
>Signalling radio bearer specific integrity protection information	CV-IP	4 to <maxSRBs etup>		
>>Uplink RRC HFN	MP		Bit string (28)	For each SRB, this IE corresponds to the last value used.
>>Downlink RRC HFN	MP		Bit string (28)	For each SRB, this IE corresponds to the last value used. In particular, for SRB2, this IE should not take into account the RRC message that will trigger the relocation.
>>Uplink RRC Message sequence number	MP		Integer (0..15)	For each SRB, this IE corresponds to the last value used.
>>Downlink RRC Message sequence number	MP		Integer (0..15)	For each SRB, this IE corresponds to the last value used. In particular, for SRB2,

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
				this IE should not take into account the RRC message that will trigger the relocation.
>Implementation specific parameters	OP		Bit string (1..512)	
<b>RRC IEs</b>				
<b>UE Information elements</b>				
>U-RNTI	MP		U-RNTI 10.3.3.47	
>C-RNTI	OP		C-RNTI 10.3.3.8	
>UE radio access Capability	MP		UE radio access capability 10.3.3.42	
>UE radio access capability extension	OP		UE radio access capability extension 10.3.3.42a	
>Last known UE position	OP			
>>SFN	MP		Integer (0..4095)	Time when position was estimated
>>Cell ID	MP		Cell identity; 10.3.2.2	Indicates the cell, the SFN is valid for.
>>CHOICE Position estimate	MP			
>>>Ellipsoid Point			Ellipsoid Point; 10.3.8.4a	
>>>Ellipsoid point with uncertainty circle			Ellipsoid point with uncertainty circle 10.3.8.4d	
>>>Ellipsoid point with uncertainty ellipse			Ellipsoid point with uncertainty ellipse 10.3.8.4e	
>>>Ellipsoid point with altitude			Ellipsoid point with altitude 10.3.8.4b	
>>>Ellipsoid point with altitude and uncertainty ellipsoid			Ellipsoid point with altitude and uncertainty ellipsoid 10.3.8.4c	
<a href="#"><u>&gt;UE Specific Behaviour Information 2</u></a>	<a href="#"><u>OP</u></a>		<a href="#"><u>UE Specific Behaviour Information 2</u></a> <a href="#"><u>10.3.3.53</u></a>	<a href="#"><u>This IE should be included if received via the "HANDOVER TO UTRAN COMPLETE" or the "RRC CONNECTION SETUP COMPLETE" or the IE "SRNS RELOCATION INFO"</u></a>
<b>Other Information elements</b>				
>UE system specific capability	OP	1 to <maxSystemCapability>		
>>Inter-RAT UE radio access capability	MP		Inter-RAT UE radio access capability 10.3.8.7	

<b>Information Element/Group Name</b>	<b>Need</b>	<b>Multi</b>	<b>Type and reference</b>	<b>Semantics description</b>
<b>UTRAN Mobility Information elements</b>				
>URA Identifier	OP		URA identity 10.3.2.6	
<b>CN Information Elements</b>				
>CN common GSM-MAP NAS system information	MP		NAS system information (GSM-MAP) 10.3.1.9	
>CN domain related information	OP	1 to <MaxCndo mains>		CN related information to be provided for each CN domain
>>CN domain identity	MP			
>>CN domain specific GSM-MAP NAS system info	MP		NAS system information (GSM-MAP) 10.3.1.9	
>>CN domain specific DRX cycle length coefficient	MP		CN domain specific DRX cycle length coefficient, 10.3.3.6	
<b>Measurement Related Information elements</b>				
>For each ongoing measurement reporting	OP	1 to <MaxNoOf Meas>		
>>Measurement Identity	MP		Measuremen t identity 10.3.7.48	
>>Measurement Command	MP		Measuremen t command 10.3.7.46	
>>Measurement Type	CV-Setup		Measuremen t type 10.3.7.50	
>>Measurement Reporting Mode	OP		Measuremen t reporting mode 10.3.7.49	
>>Additional Measurements list	OP		Additional measurements list 10.3.7.1	
>>CHOICE Measurement	OP			
>>>Intra-frequency				
>>>>Intra-frequency cell info	OP		Intra-frequency cell info list 10.3.7.33	
>>>>Intra-frequency measurement quantity	OP		Intra-frequency measurement quantity 10.3.7.38	
>>>>Intra-frequency reporting quantity	OP		Intra-frequency reporting quantity 10.3.7.41	
>>>>Reporting cell status	OP		Reporting cell status 10.3.7.61	
>>>>Measurement validity	OP		Measuremen t validity 10.3.7.51	

<b>Information Element/Group Name</b>	<b>Need</b>	<b>Multi</b>	<b>Type and reference</b>	<b>Semantics description</b>
>>>CHOICE report criteria	OP			
>>>>Intra-frequency measurement reporting criteria			Intra-frequency measurement reporting criteria 10.3.7.39	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting			NULL	
>>>Inter-frequency				
>>>>Inter-frequency cell info	OP		Inter-frequency cell info list 10.3.7.13	
>>>>Inter-frequency measurement quantity	OP		Inter-frequency measurement quantity 10.3.7.18	
>>>>Inter-frequency reporting quantity	OP		Inter-frequency reporting quantity 10.3.7.21	
>>>>Reporting cell status	OP		Reporting cell status 10.3.7.61	
>>>>Measurement validity	OP		Measurement validity 10.3.7.51	
>>>CHOICE report criteria	OP			
>>>>Inter-frequency measurement reporting criteria			Inter-frequency measurement reporting criteria 10.3.7.19	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting			NULL	
>>>Inter-RAT				
>>>>Inter-RAT cell info	OP		Inter-RAT cell info list 10.3.7.23	
>>>>Inter-RAT measurement quantity	OP		Inter-RAT measurement quantity 10.3.7.29	
>>>>Inter-RAT reporting quantity	OP		Inter-RAT reporting quantity 10.3.7.32	
>>>>Reporting cell status	OP		Reporting cell status 10.3.7.61	
>>>>Measurement validity	OP		Measurement validity 10.3.7.51	
>>>CHOICE report criteria	OP			
>>>>Inter-RAT measurement reporting criteria			Inter-RAT measurement	

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
			t reporting criteria 10.3.7.30	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting			NULL	
>>>Traffic Volume				
>>>Traffic volume measurement Object	OP		Traffic volume measurement object 10.3.7.70	
>>>Traffic volume measurement quantity	OP		Traffic volume measurement quantity 10.3.7.71	
>>>Traffic volume reporting quantity	OP		Traffic volume reporting quantity 10.3.7.74	
>>>CHOICE report criteria	OP			
>>>>Traffic volume measurement reporting criteria			Traffic volume measurement reporting criteria 10.3.7.72	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting			NULL	
>>>Quality				
>>>Quality measurement Object	OP		Quality measurement object	
>>>CHOICE report criteria	OP			
>>>>Quality measurement reporting criteria			Quality measurement reporting criteria 10.3.7.58	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting			NULL	
>>>UE internal				
>>>UE internal measurement quantity	OP		UE internal measurement quantity 10.3.7.79	
>>>UE internal reporting quantity	OP		UE internal reporting quantity 10.3.7.82	
>>>CHOICE report criteria	OP			
>>>>UE internal measurement reporting criteria			UE internal measurement reporting criteria 10.3.7.80	

<b>Information Element/Group Name</b>	<b>Need</b>	<b>Multi</b>	<b>Type and reference</b>	<b>Semantics description</b>
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting			NULL	
>>>>UE positioning				
>>>>LCS reporting quantity	OP		LCS reporting quantity 10.3.7.111	
>>>>CHOICE report criteria	OP			
>>>>LCS reporting criteria			LCS reporting criteria 10.3.7.110	
>>>>Periodical reporting			Periodical reporting criteria 10.3.7.53	
>>>>No reporting				
<b>Radio Bearer Information Elements</b>				
>Predefined configuration status information	OP		Predefined configuration status information 10.3.4.5a	
>Signalling RB information list	MP	1 to <maxSRBs etup>		For each signalling radio bearer
>>Signalling RB information	MP		Signalling RB information to setup 10.3.4.24	
>RAB information list	OP	1 to <maxRABs etup>		Information for each RAB
>>RAB information	MP		RAB information to setup 10.3.4.10	
<b>Transport Channel Information Elements</b>				
<b>Uplink transport channels</b>				
>UL Transport channel information common for all transport channels	OP		UL Transport channel information common for all transport channels 10.3.5.24	
>UL transport channel information list	OP	1 to <MaxTrCH>		
>>UL transport channel information	MP		Added or reconfigured UL TrCH information 10.3.5.2	
>CHOICE mode	OP			
>>FDD				
>>>CPCH set ID	OP		CPCH set ID 10.3.5.5	
>>>Transport channel information for DRAC list	OP	1 to <MaxTrCH>		

Information Element/Group Name	Need	Multi	Type and reference	Semantics description
		>		
>>>DRAC static information	MP		DRAC static information 10.3.5.7	
>>TDD				(no data)
<b>Downlink transport channels</b>				
>DL Transport channel information common for all transport channels	OP		DL Transport channel information common for all transport channels 10.3.5.6	
>DL transport channel information list	OP	1 to <MaxTrCH>		
>>DL transport channel information	MP		Added or reconfigured DL TrCH information 10.3.5.1	
>Measurement report	OP		MEASUREMENT REPORT 10.2.17	
<b>Other Information elements</b>				
Failure cause	OP		Failure cause 10.3.3.13	Diagnostics information related to an earlier SRNC Relocation request (see NOTE 2 in 14.12.0a)
Protocol error information	CV-ProtErr		Protocol error information 10.3.8.12	

Multi Bound	Explanation
MaxNoOfMeas	Maximum number of active measurements, upper limit 16

Condition	Explanation
Setup	The IE is mandatory present when the IE Measurement command has the value "Setup", otherwise the IE is not needed.
Ciphering	The IE is mandatory present when the IE Ciphering Status has the value "started" and the ciphering counters need not be reinitialised, otherwise the IE is not needed.
IP	The IE is mandatory present when the IE Integrity protection status has the value "started" and the integrity protection counters need not be reinitialised, otherwise the IE is not needed.
ProtErr	This IE is mandatory present if the IE "Protocol error indicator" is included and has the value "TRUE". Otherwise it is not needed.
SRB1	The IE is mandatory present for RB1. Otherwise it is not needed.

## CHANGE REQUEST

⌘ 25.331 CR 1788 ⌘ rev 1 ⌘ Current version: 3.12.0 ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

**Proposed change affects:** UICC apps ⌘ ME  Radio Access Network  Core Network ⌘

<b>Title:</b>	⌘ Compact IMEI-SV transfer across Uu and within RRC containers	
<b>Source:</b>	⌘ Ericsson	
<b>Work item code:</b>	⌘ TEI	<b>Date:</b> ⌘ 13/11/2002
<b>Category:</b>	⌘ <b>B</b> Use <u>one</u> of the following categories: <b>F</b> (correction) <b>A</b> (corresponds to a correction in an earlier release) <b>B</b> (addition of feature), <b>C</b> (functional modification of feature) <b>D</b> (editorial modification)	<b>Release:</b> ⌘ R99 Use <u>one</u> of the following releases: 2 (GSM Phase 2) R96 (Release 1996) R97 (Release 1997) R98 (Release 1998) R99 (Release 1999) Rel-4 (Release 4) Rel-5 (Release 5) Rel-6 (Release 6)
<b>Reason for change:</b> ⌘ The changes included in this CR are proposed for the following reasons:		<ul style="list-style-type: none"> <li>RP has tasked R2 to agree on a solution for the handling of early UEs, which is currently not sufficiently covered in R99. The proposal is to introduce an IE indicating the version of a UE implementation. This indication may be used by the network to avoid invoking functionality towards UEs for which interoperability problems are experienced/ foreseen.</li> </ul>

<b>Summary of change:</b>	This CR introduces the following changes: <ul style="list-style-type: none"> <li>A new IE “UE specific behaviour info” is defined. It is added to the following messages:                     <ul style="list-style-type: none"> <li>RRC CONNECTION REQUEST message (MP)</li> <li>INTER RAT HANDOVER INFO message (MP) and the INTER RAT HANDOVER INFO WITH INTER RAT CAPABILITIES (implicitly, since it includes INTER RAT HANDOVER INFO message)</li> <li>UE CAPABILITY INFORMATION message (OP)</li> <li>SRNS RELOCATION INFO message (MP)</li> </ul> </li> <li>The “UE specific behaviour info” IE includes the decimal to binary conversion of the first 6 bits of the TAC concatenated with the SVN fields of the IMEI-SV</li> </ul>
<b>Impact analysis:</b>	<b>Impacted functionality:</b> The CR affects the handling of early UE implementations. It may be used by the network to avoid using functionality for which interoperability problems are experienced/ foreseen with a specific UE implementation

**Correction type:** The CR has isolated impact since it only affects functions for which interoperability problems are experienced/ foreseen

<p><b>Interoperability:</b></p> <ul style="list-style-type: none"> <li>• In case the network implements the CR but the UE does not, the network can not make use of the additional information. As a result the network either will experience interoperability problem or it has to refrain for using functionality that does not work towards all early UEs</li> <li>• In case the network has not implemented the CR, it will just ignore the additional information provided by the UE</li> </ul>									
<b>Consequences if not approved:</b>	⌘ In case there are interoperability problems with early UE implementations, networks have no other choice but to either experience these problems or to refrain for using functionality with interoperability problems towards all early UEs								
<b>Clauses affected:</b>	⌘ 8.1.16.3, 8.6.3.12, 10.2.39, 10.3.3.42, 10.3.3.45a (new), 11.2, 11.3, 11.5, 14.12.2								
<b>Other specs affected:</b>	<table border="1"> <tr> <td>Y</td><td>N</td></tr> <tr> <td>⌘ X</td><td>Other core specifications</td></tr> <tr> <td> </td><td>X Test specifications</td></tr> <tr> <td> </td><td>X O&amp;M Specifications</td></tr> </table>	Y	N	⌘ X	Other core specifications		X Test specifications		X O&M Specifications
Y	N								
⌘ X	Other core specifications								
	X Test specifications								
	X O&M Specifications								
<b>Other comments:</b>	<p>⌘ This is a complete proposal that does not require changes on other interfaces</p> <p>The differences between the draft and the original version of this CR are as follows:</p> <ul style="list-style-type: none"> <li>• The full 8 digits TAC is now transferred</li> <li>• The cover page was updated to clarify the impact on the INTER RAT HO WITH INTER RAT CAPABILITIES message, the impact on measurements and the impact on other specifications</li> <li>• The statement on the decimal to binary translation was updated to clarify that the concatenated decimals are converted</li> <li>• The UE specific behaviour information is made optional in the SRNS relocation info since the RNC may not receive it (e.g. UE's not supporting this CR)</li> <li>• The tabular format of the SRNS RELOCATION INFO is removed since the UE specific behaviour info is implicitly covered by the extension of the UE radio access capability</li> <li>• Additional clarification is included indicating that upon parameter change the UE specific behaviour info need not be included</li> <li>• The UE version info is renamed to UE specific behaviour info to align with RAN3</li> </ul>								

### How to create CRs using this form:

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>. Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

### 8.1.16.3 INTER RAT HANDOVER INFO message contents to set

The UE shall:

- 1> include the IE "Predefined configuration status information" and the IE "UE security information";
- 1> include the IE "UE capability container", containing the IE "UE radio access capability" and the IE "UE radio access capability extension", in accordance with the following:
  - 2> if the UE supports multiple UTRA FDD Frequency Bands; or
  - 2> if the UE supports a single UTRA FDD Frequency Band different from 2100 MHz:
    - 3> include the IE "UE radio access capability", excluding IEs "RF capability FDD" and "Measurement capability";
    - 3> include the IE "UE radio access capability extension", including the IEs "RF capability FDD extension" and the "Measurement capability extension" associated with each supported UTRA FDD frequency band indicated in the IE "Frequency band".

2> else:

- 3> include the IE "UE radio access capability", including the IEs "RF capability FDD" and "Measurement capability" associated with the 2100 MHz UTRA FDD frequency band;
- 3> include the IE "UE radio access capability extension", including the IEs "RF capability FDD extension" and the "Measurement capability extension" associated with each supported UTRA FDD frequency band indicated in the IE "Frequency band".

**2> include its UE specific behaviour information in the IE "UE specific behaviour info" in the variable UE\_CAPABILITY\_REQUESTED.**

- 1> initiate the transfer of the INTER RAT HANDOVER INFO message via the other radio access technology, using radio access technology-specific procedures;
- 1> store the IE "Predefined configuration status information", the IE "UE security information", the IE "UE radio access capability" and the IE "UE radio access capability extension", if included in the INTER RAT HANDOVER MESSAGE, in variable INTER\_RAT\_HANDOVER\_INFO\_TRANSFERRED;
- 1> and the procedure ends.

### 8.6.3.12 Capability Update Requirement

If the IE "Capability Update Requirement" is included, the UE shall:

- 1> if the IE "UE radio access FDD capability update requirement" has the value TRUE:
    - 2> if the UE supports FDD mode:
      - 3> store its UTRA FDD capabilities and its UTRA capabilities common to FDD and TDD in the IE "UE radio access capability" and the IE "UE radio access capability extension" in variable **UE\_CAPABILITY\_REQUESTED** as specified below:
        - 4> if the UE supports multiple UTRA FDD Frequency Bands; or
        - 4> if the UE supports a single UTRA FDD Frequency Band different from 2100 MHz:
          - 5> store the IE "UE radio access capability", excluding IEs "RF capability FDD" and "Measurement capability";
          - 5> store the IE "UE radio access capability extension", including the IEs "RF capability FDD extension" and the "Measurement capability extension" associated with each supported UTRA FDD frequency band indicated in the IE "Frequency band".
        - 4> else:
          - 5> store the IE "UE radio access capability", including the IEs "RF capability FDD" and "Measurement capability" associated with the 2100 MHz UTRA FDD frequency band.
- 
- 3> include its UE specific behaviour information in the IE "UE specific behaviour info" in the variable **UE\_CAPABILITY\_REQUESTED**.
- 1> if the IE "UE radio access TDD capability update requirement" has the value TRUE:
    - 2> if the UE supports TDD mode:
      - 3> store its UTRA TDD capabilities and its UTRA capabilities common to FDD and TDD in the IE "UE radio access capability" in the variable **UE\_CAPABILITY\_REQUESTED**.
        - 3> include its UE specific behaviour information in the IE "UE specific behaviour info" in the variable **UE\_CAPABILITY\_REQUESTED**.
- 
- 1> if the IE "System specific capability update requirement list" is present:
    - 2> for each of the RAT requested in the IE "UE system specific capability":
      - 3> if the UE supports the listed RAT:
        - 4> include its inter-RAT radio access capabilities for the listed RAT in the IE "UE system specific capability" from the variable **UE\_CAPABILITY\_REQUESTED**.

If the IE "Capability update requirement" is not present, the UE shall:

- 1> assume the default values as specified in subclause 10.3.3.2 and act in accordance with the above.

### 10.2.39 RRC CONNECTION REQUEST

RRC Connection Request is the first message transmitted by the UE when setting up an RRC Connection to the network.

RLC-SAP: TM

Logical channel: CCCH

Direction: UE → UTRAN

Information Element/Group name	Need	Multi	Type and reference	Semantics description
Message Type	MP		Message Type	
<b>UE information elements</b>				
Initial UE identity	MP		Initial UE identity 10.3.3.15	
Establishment cause	MP		Establishment cause 10.3.3.11	
Protocol error indicator	MD		Protocol error indicator 10.3.3.27	Default value is FALSE
<b>Measurement information elements</b>				
Measured results on RACH	OP		Measured results on RACH 10.3.7.45	
<u>UE specific behaviour info</u>	MP		<u>UE specific behaviour info</u> 10.3.3.45a	

If the encoded message does not fill a transport block, the RRC layer shall insert padding according to subclause 12.1.

### 10.3.3.42 UE radio access capability

Information Element/Group name	Need	Multi	Type and reference	Semantics description
Access stratum release indicator	MP		Enumerated( R99)	Indicates the release of the UE according to [35]. The IE also indicates the release of the RRC transfer syntax supported by the UE.
<u>UE specific behaviour info</u>	<u>CH- <i>rrcConncti onSetupCo mplete</i></u>		<u>UE specific behaviour info</u> <u>10.3.3.45a</u>	
PDCP capability	MP		PDCP capability 10.3.3.24	
RLC capability	MP		RLC capability 10.3.3.34	
Transport channel capability	MP		Transport channel capability 10.3.3.40	
RF capability FDD	OP		RF capability FDD 10.3.3.33	
RF Capability TDD	OP		RF capability TDD 10.3.3.33b	
Physical channel capability	MP		Physical channel capability 10.3.3.25	
UE multi-mode/multi-RAT capability	MP		UE multi-mode/multi-RAT capability 10.3.3.41	
Security capability	MP		Security capability 10.3.3.37	
UE positioning capability	MP		UE positioning capability 10.3.3.45	
Measurement capability	CH- <i>fdd_req_su p</i>		Measuremen t capability 10.3.3.21	

Condition	Explanation
<i>fdd_req_sup</i>	The IE is mandatory present if the IE "Multi-mode capability" has the value "FDD" or "FDD/TDD" and a FDD capability update has been requested in a previous message. Otherwise this field is not needed in the message.
<u><i>rrcConnctionSetupComplete</i></u>	The IE is not needed in the RRC CONNECTION SETUP COMPLETE message. The IE is optional in the UE CAPABILITY INFORMATION and the SRNS RELOCATION INFO message. Otherwise the IE is mandatory present.

**10.3.3.45a UE specific behaviour info**

<u>Information Element/Group name</u>	<u>Need</u>	<u>Multi</u>	<u>Type and reference</u>	<u>Semantics description</u>
IMEI-SV	MP		Bitstring (32)	A compact version of the IMEI-SV [see 23.003] comprising of the decimal to binary conversion of the concatenation of the TAC and the SVN digits. The bits of the result are numbered from b0 to b31, with bit b0 being the least significant.

## 11.2 PDU definitions

```
--*****
-- TABULAR: The message type and integrity check info are not
-- visible in this module as they are defined in the class module.
-- Also, all FDD/TDD specific choices have the FDD option first
-- and TDD second, just for consistency.
--*****
PDU-definitions DEFINITIONS AUTOMATIC TAGS ::=

BEGIN

--*****
-- IE parameter types from other modules
--*****
IMPORTS

-- Core Network IEs :
CN-DomainIdentity,
CN-InformationInfo,
CN-InformationInfoFull,
NAS-Message,
PagingRecordTypeID,
-- UTRAN Mobility IEs :
URA-Identity,
-- User Equipment IEs :
ActivationTime,
C-RNTI,
CapabilityUpdateRequirement,
CellUpdateCause,
CipheringAlgorithm,
CipheringModeInfo,
DSCH-RNTI,
EstablishmentCause,
FailureCauseWithProtErr,
FailureCauseWithProtErrTrId,
InitialUE-Identity,
IntegrityProtActivationInfo,
IntegrityProtectionModeInfo,
N-308,
PagingCause,
PagingRecordList,
ProtocolErrorIndicator,
ProtocolErrorIndicatorWithMoreInfo,
Rb-timer-indicator,
RedirectionInfo,
RejectionCause,
ReleaseCause,
RRC-StateIndicator,
RRC-TransactionIdentifier,
SecurityCapability,
START-Value,
STARTList,
U-RNTI,
U-RNTI-Short,
UE-RadioAccessCapability,
UE-RadioAccessCapability-v370ext,
UE-RadioAccessCapability-v380ext,
UE-RadioAccessCapability-v3a0ext,
DL-PhysChCapabilityFDD-v380ext,
UE-ConnTimersAndConstants,
UE-ConnTimersAndConstants-v3a0ext,
UE-SecurityInformation,
URA-UpdateCause,
UE-SpecificBehaviourInfo,
UTRAN-DRX-CycleLengthCoefficient,
WaitTime,
-- Radio Bearer IEs :
DefaultConfigIdentity,
DefaultConfigMode,
```

```
DL-CounterSynchronisationInfo,
PredefinedConfigIdentity,
PredefinedConfigStatusList,
RAB-Info,
RAB-Info-Post,
RAB-InformationList,
RAB-InformationReconfigList,
RAB-InformationSetupList,
RB-ActivationTimeInfoList,
RB-COUNT-C-InformationList,
RB-COUNT-C-MSB-InformationList,
RB-IdentityList,
RB-InformationAffectedList,
RB-InformationReconfigList,
RB-InformationReleaseList,
SRB-InformationSetupList,
SRB-InformationSetupList2,
UL-CounterSynchronisationInfo,
-- Transport Channel IEs:
CPCH-SetID,
DL-AddReconfTransChInfo2List,
DL-AddReconfTransChInfoList,
DL-CommonTransChInfo,
DL-DeletedTransChInfoList,
DRAC-StaticInformationList,
TFC-Subset,
TFCS-Identity,
UL-AddReconfTransChInfoList,
UL-CommonTransChInfo,
UL-DeletedTransChInfoList,
-- Physical Channel IEs :
Alpha,
CCTrCH-PowerControlInfo,
ConstantValue,
ConstantValueTdd,
CPCH-SetInfo,
DL-CommonInformation,
DL-CommonInformationPost,
DL-InformationPerRL,
DL-InformationPerRL-List,
DL-InformationPerRL-ListPostFDD,
DL-InformationPerRL-PostTDD,
DL-PDSCH-Information,
DPCH-CompressedModeStatusInfo,
FrequencyInfo,
FrequencyInfoFDD,
FrequencyInfoTDD,
MaxAllowedUL-TX-Power,
PDSCH-CapacityAllocationInfo,
PDSCH-Identity,
PrimaryCCPCH-TX-Power,
PUSCH-CapacityAllocationInfo,
PUSCH-Identity,
RL-AdditionInformationList,
RL-RemovalInformationList,
SpecialBurstScheduling,
SSDT-Information,
TFC-ControlDuration,
TimeslotList,
TX-DiversityMode,
UL-ChannelRequirement,
UL-ChannelRequirementWithCPCH-SetID,
UL-DPCH-Info,
UL-DPCH-InfoPostFDD,
UL-DPCH-InfoPostTDD,
UL-TimingAdvance,
UL-TimingAdvanceControl,
-- Measurement IEs :
AdditionalMeasurementID-List,
Frequency-Band,
EventResults,
InterRAT-TargetCellDescription,
MeasuredResults,
MeasuredResults-v390ext,
MeasuredResultsList,
MeasuredResultsOnRACH,
MeasurementCommand,
MeasurementIdentity,
```

```

MeasurementReportingMode,
PrimaryCCPCH-RSCP,
SFN-Offset-Validity,
TimeslotListWithISCP,
TrafficVolumeMeasuredResultsList,
UE-Positioning-GPS-AssistanceData,
UE-Positioning-Measurement-v390ext,
UE-Positioning-OTDOA-AssistanceData,
UE-Positioning-OTDOA-AssistanceData-UEB,
-- Other IEs :
BCCH-ModificationInfo,
CDMA2000-MessageList,
GSM-MessageList,
InterRAT-ChangeFailureCause,
InterRAT-HO-FailureCause,
InterRAT-UE-RadioAccessCapabilityList,
InterRAT-UE-SecurityCapList,
IntraDomainNasNodeSelector,
ProtocolErrorMoreInformation,
Rplmn-Information,
SegCount,
SegmentIndex,
SPN-Prime,
SIB-Data-fixed,
SIB-Data-variable,
SIB-Type
FROM InformationElements

maxSIBperMsg
FROM Constant-definitions;

<Cut until the next modified section>

-- ****
-- 
-- INTER RAT HANDOVER INFO
-- 
-- ****

InterRATHandoverInfo ::= SEQUENCE {
    -- This structure is defined for historical reasons, backward compatibility with 04.18
    predefinedConfigStatusList      CHOICE {
        absent                  NULL,
        present                 PredefinedConfigStatusList
    },
    uE-SecurityInformation         CHOICE {
        absent                  NULL,
        present                 UE-SecurityInformation
    },
    ue-CapabilityContainer         CHOICE {
        absent                  NULL,
        -- present is an octet aligned string containing IE UE-RadioAccessCapabilityInfo
        present                 OCTET STRING (SIZE (0..63))
    },
    -- Non critical extensions
    v390NonCriticalExtensions     CHOICE {
        absent                  NULL,
        present                 SEQUENCE {
            interRATHandoverInfo-v390ext   InterRATHandoverInfo-v390ext-IEs,
            -- Reserved for future non critical extension
            v3a0NonCriticalExtensions   SEQUENCE {
                interRATHandoverInfo-v3a0ext   InterRATHandoverInfo-v3a0ext-IEs,
            },
            v3d0NonCriticalExtensions   SEQUENCE {
                interRATHandoverInfo-v3d0ext   InterRATHandoverInfo-v3d0ext-IEs,
                -- Reserved for future non critical extension
                nonCriticalExtensions       SEQUENCE {} OPTIONAL
            }
        }
    }
}

InterRATHandoverInfo-v390ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v380ext   UE-RadioAccessCapability-v380ext           OPTIONAL,
    dl-PhysChCapabilityFDD-v380ext    DL-PhysChCapabilityFDD-v380ext
}

InterRATHandoverInfo-v3a0ext-IEs ::= SEQUENCE {

```

```

-- User equipment IEs
    ue-RadioAccessCapability-v3a0ext      UE-RadioAccessCapability-v3a0ext      OPTIONAL
}

InterRATHandoverInfo-v3b0ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v3d0ext      UE-SpecificBehaviourInfo
}

<Cut until the next modified section>

-- ****
-- 
-- RRC CONNECTION REQUEST
-- 
-- ****

RRCConnectionRequest ::= SEQUENCE {
    -- TABULAR: Integrity protection shall not be performed on this message.
    -- User equipment IEs
    initialUE-Identity          InitialUE-Identity,
    establishmentCause           EstablishmentCause,
    -- protocolErrorIndicator is MD, but for compactness reasons no default value
    -- has been assigned to it.
    protocolErrorIndicator       ProtocolErrorIndicator,
    -- Measurement IEs
    measuredResultsOnRACH        MeasuredResultsOnRACH      OPTIONAL,
    v3d0NonCriticalExtensions   SEQUENCE {
        RRCConnectionRequest-v3d0ext      RRCConnectionRequest-v3d0ext-IEs,
        -- Reserved for future non critical extension
        Extension mechanism for non release99 information
        nonCriticalExtensions            SEQUENCE {}      OPTIONAL
    }                                OPTIONAL
}

RRCConnectionRequest-v3d0ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v3d0ext      UE-SpecificBehaviourInfo
}
-- ****
-- 
-- RRC CONNECTION SETUP
-- 
-- ****

RRCConnectionSetup ::= CHOICE {
    r3
        SEQUENCE {
            rrcConnectionSetup-r3
            nonCriticalExtensions      SEQUENCE {} OPTIONAL
        },
    later-than-r3
        SEQUENCE {
            rrc-TransactionIdentifier   RRC-TransactionIdentifier,
            criticalExtensions         SEQUENCE {}
        }
}

RRCConnectionSetup-r3-IEs ::= SEQUENCE {
    -- TABULAR: Integrity protection shall not be performed on this message.
    -- User equipment IEs
    initialUE-Identity          InitialUE-Identity,
    rrc-TransactionIdentifier   RRC-TransactionIdentifier,
    activationTime               ActivationTime      OPTIONAL,
    new-U-RNTI                  U-RNTI,
    new-c-RNTI                  C-RNTI      OPTIONAL,
    rrc-StateIndicator          RRC-StateIndicator,
    utran-DRX-CycleLengthCoeff  UTRAN-DRX-CycleLengthCoefficient,
    -- TABULAR: If capabilityUpdateRequirement is not present, the default value
    -- defined in 10.3.3.2 shall be used.
    capabilityUpdateRequirement  CapabilityUpdateRequirement      OPTIONAL,
    -- Radio bearer IEs
    srb-InformationSetupList     SRB-InformationSetupList2,
    -- Transport channel IEs
    ul-CommonTransChInfo        UL-CommonTransChInfo      OPTIONAL,
    -- NOTE: ul-AddReconfTransChInfoList should be optional in later versions
    -- of this message
    ul-AddReconfTransChInfoList  UL-AddReconfTransChInfoList,
    dl-CommonTransChInfo        DL-CommonTransChInfo      OPTIONAL,
    -- NOTE: dl-AddReconfTransChInfoList should be optional in later versions
}

```

```

-- of this message
dl-AddReconfTransChInfoList      DL-AddReconfTransChInfoList,
-- Physical channel IEs
frequencyInfo                   FrequencyInfo           OPTIONAL,
maxAllowedUL-TX-Power          MaxAllowedUL-TX-Power    OPTIONAL,
ul-ChannelRequirement          UL-ChannelRequirement    OPTIONAL,
dl-CommonInformation           DL-CommonInformation    OPTIONAL,
dl-InformationPerRL-List       DL-InformationPerRL-List  OPTIONAL
}

-- ****
-- RRC CONNECTION SETUP COMPLETE
-- ****

RRCConnectionSetupComplete ::= SEQUENCE {
  -- TABULAR: Integrity protection shall not be performed on this message.
  -- User equipment IEs
  rrc-TransactionIdentifier      RRC-TransactionIdentifier,
  startList                      STARTList,
  ue-RadioAccessCapability       UE-RadioAccessCapability   OPTIONAL,
  -- Other IEs
  ue-RATSpecificCapability      InterRAT-UE-RadioAccessCapabilityList  OPTIONAL,
  -- Non critical extensions
  v370NonCriticalExtensions     SEQUENCE {
    rrcConnectionSetupComplete-v370ext  RRCConnectionSetupComplete-v370ext,
    v380NonCriticalExtensions         SEQUENCE {
      rrcConnectionSetupComplete-v380ext  RRCConnectionSetupComplete-v380ext-IEs,
      -- Reserved for future non critical extension
      v3a0NonCriticalExtensions        SEQUENCE {
        rrcConnectionSetupComplete-v3a0ext  RRCConnectionSetupComplete-v3a0ext-IEs,
        nonCriticalExtensions           SEQUENCE {}           OPTIONAL
      }                                OPTIONAL
    }                                OPTIONAL
  }                                OPTIONAL
}

RRCConnectionSetupComplete-v370ext ::= SEQUENCE {
  -- User equipment IEs
  ue-RadioAccessCapability-v370ext  UE-RadioAccessCapability-v370ext   OPTIONAL
}

RRCConnectionSetupComplete-v380ext-IEs ::= SEQUENCE {
  -- User equipment IEs
  ue-RadioAccessCapability-v380ext  UE-RadioAccessCapability-v380ext   OPTIONAL,
  dl-PhysChCapabilityFDD-v380ext   DL-PhysChCapabilityFDD-v380ext
}

RRCConnectionSetupComplete-v3a0ext-IEs ::= SEQUENCE {
  -- User equipment IEs
  ue-RadioAccessCapability-v3a0ext  UE-RadioAccessCapability-v3a0ext   OPTIONAL
}

<Cut until the next modified section>

-- ****
-- UE CAPABILITY INFORMATION
-- ****

UECapabilityInformation ::= SEQUENCE {
  -- User equipment IEs
  rrc-TransactionIdentifier      RRC-TransactionIdentifier   OPTIONAL,
  ue-RadioAccessCapability       UE-RadioAccessCapability    OPTIONAL,
  -- Other IEs
  ue-RATSpecificCapability      InterRAT-UE-RadioAccessCapabilityList
  OPTIONAL,
  -- Non critical extensions
  v370NonCriticalExtensions     SEQUENCE {
    ueCapabilityInformation-v370ext  UECapabilityInformation-v370ext,
    v380NonCriticalExtensions      SEQUENCE {
      ueCapabilityInformation-v380ext  UECapabilityInformation-v380ext-IEs,
      -- Reserved for future non critical extension
      v3a0NonCriticalExtensions    SEQUENCE {
        ueCapabilityInformation-v3a0ext  UECapabilityInformation-v3a0ext-IEs,
        v3d0NonCriticalExtensions   SEQUENCE {

```

```
ueCapabilityInformation-v3d0ext UECapabilityInformation-v3d0ext-IEs,
-- Reserved for future non critical extension
nonCriticalExtensions           SEQUENCE { }          OPTIONAL
}                                OPTIONAL
}                                OPTIONAL
}                                OPTIONAL
}

UECapabilityInformation-v370ext ::= SEQUENCE {
-- User equipment IEs
    ue-RadioAccessCapability-v370ext      UE-RadioAccessCapability-v370ext      OPTIONAL
}

UECapabilityInformation-v380ext-IEs ::= SEQUENCE {
-- User equipment IEs
    ue-RadioAccessCapability-v380ext      UE-RadioAccessCapability-v380ext      OPTIONAL,
    dl-PhysChCapabilityFDD-v380ext       DL-PhysChCapabilityFDD-v380ext
}

UECapabilityInformation-v3a0ext-IEs ::= SEQUENCE {
-- User equipment IEs
    ue-RadioAccessCapability-v3a0ext      UE-RadioAccessCapability-v3a0ext      OPTIONAL
}

UECapabilityInformation-v3d0ext ::= SEQUENCE {
-- User equipment IEs
    ue-RadioAccessCapability-v3d0ext      UE-SpecificBehaviourInfo          OPTIONAL
}
```

## 11.3 Information element definitions

```
InformationElements DEFINITIONS AUTOMATIC TAGS ::=

<Cut until the next modified section>

-- ****
-- USER EQUIPMENT INFORMATION ELEMENTS (10.3.3)
-- ****

<Cut until the next modified section>

| UE-SpecificBehaviourInfo ::= SEQUENCE {
|   imei-sv-compact           BIT STRING (SIZE (32))
| }
```

## 11.5 RRC information between network nodes

```

Internode-definitions DEFINITIONS AUTOMATIC TAGS ::=
BEGIN
IMPORTS

    HandoverToUTRANCommand,
    MeasurementReport,
    PhysicalChannelReconfiguration,
    RadioBearerReconfiguration,
    RadioBearerRelease,
    RadioBearerSetup,
    RRC-FailureInfo,
    TransportChannelReconfiguration
FROM PDU-definitions

-- Core Network IEs :
    CN-DomainIdentity,
    CN-DomainInformationList,
    CN-DRX-CycleLengthCoefficient,
    NAS-SystemInformationGSM-MAP,
-- UTRAN Mobility IE s :
    CellIdentity,
    URA-Identity,
-- User Equipment IE s :
    C-RNTI,
    DL-PhysChCapabilityFDD-v380ext,
    FailureCauseWithProtErr,
    RRC-MessageSequenceNumber,
    STARTList,
    STARTSingle,
    START-Value,
    U-RNTI,
    UE-RadioAccessCapability,
    UE-RadioAccessCapability-v370ext,
    UE-RadioAccessCapability-v380ext,
    UE-RadioAccessCapability-v3a0ext,
    UE-SpecificBehaviourInfo,
-- Radio Bearer IE s :
    PredefinedConfigStatusList,
    PredefinedConfigValueTag,
    RAB-InformationSetupList,
    RB-Identity,
    SRB-InformationSetupList,
-- Transport Channel IE s :
    CPCH-SetID,
    DL-CommonTransChInfo,
    DL-AddReconfTransChInfoList,
    DRAC-StaticInformationList,
    UL-CommonTransChInfo,
    UL-AddReconfTransChInfoList,
-- Measurement IE s :
    MeasurementIdentity,
    MeasurementReportingMode,
    MeasurementType,
    AdditionalMeasurementID-List,
    PositionEstimate,
-- Other IE s :
    InterRAT-UE-RadioAccessCapabilityList
FROM InformationElements

    maxCNdomains,
    maxNoOfMeas,
    maxRB,
    maxSRBsetup
FROM Constant-definitions;

<Cut until the next modified section>

-- Part2: Container definitions, similar to the PDU definitions in 11.2 for RRC messages
-- In alphabetical order

```

```

-- ****
-- Handover to UTRAN information
-- ****

InterRATHandoverInfoWithInterRATCapabilities ::= CHOICE {
    r3           SEQUENCE {
        -- IE InterRATHandoverInfoWithInterRATCapabilities-r3-IEs also
        -- includes non critical extensions
        interRATHandoverInfo-r3       InterRATHandoverInfoWithInterRATCapabilities-r3-IEs,
        v390NonCriticalExtensions     SEQUENCE {
            interRATHandoverInfoWithInterRATCapabilities-v390ext
            InterRATHandoverInfoWithInterRATCapabilities-v390ext-IEs,
            -- Reserved for future non critical extension
            nonCriticalExtensions      SEQUENCE {} OPTIONAL
        }                           OPTIONAL
    },
    criticalExtensions          SEQUENCE {}
}

InterRATHandoverInfoWithInterRATCapabilities-r3-IEs ::= SEQUENCE {
    -- The order of the IEs may not reflect the tabular format
    -- but has been chosen to simplify the handling of the information in the BSC
    -- Other IEs
    ue-RATSpecificCapability     InterRAT-UE-RadioAccessCapabilityList OPTIONAL,
    -- interRATHandoverInfo, Octet string is used to obtain 8 bit length field prior to
    -- actual information. This makes it possible for BSS to transparently handle information
    -- received via GSM air interface even when it includes non critical extensions.
    -- The octet string shall include the InterRATHandoverInfo information
    -- The BSS can re-use the 04.18 length field received from the MS
    interRATHandoverInfo         OCTET STRING (SIZE (0..255))
}

InterRATHandoverInfoWithInterRATCapabilities-v390ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    failureCauseWithProtErr      FailureCauseWithProtErr
                                OPTIONAL
}

-- ****
-- SRNC Relocation information
-- ****

SRNC-RelocationInfo ::= CHOICE {
    r3           SEQUENCE {
        SRNC-RelocationInfo-r3       SRNC-RelocationInfo-r3-IEs,
        v380NonCriticalExtensions   SEQUENCE {
            SRNC-RelocationInfo-v380ext SRNC-RelocationInfo-v380ext-IEs,
            -- Reserved for future non critical extension
            v390NonCriticalExtensions   SEQUENCE {
                SRNC-RelocationInfo-v390ext SRNC-RelocationInfo-v390ext-IEs,
                v3a0NonCriticalExtensions SEQUENCE {
                    SRNC-RelocationInfo-v3a0ext SRNC-RelocationInfo-v3a0ext-IEs,
                    v3b0NonCriticalExtensions SEQUENCE {
                        SRNC-RelocationInfo-v3b0ext SRNC-RelocationInfo-v3b0ext-IEs,
                        v3c0NonCriticalExtensions SEQUENCE {
                            SRNC-RelocationInfo-v3c0ext SRNC-RelocationInfo-v3c0ext-IEs,
                            v3d0NonCriticalExtensions SEQUENCE {
                                SRNC-RelocationInfo-v3d0ext SRNC-RelocationInfo-v3d0ext-IEs,
                                -- Reserved for future non critical extension
                                nonCriticalExtensions      SEQUENCE {} OPTIONAL
                            }                           OPTIONAL
                        }                           OPTIONAL
                    }                           OPTIONAL
                }                           OPTIONAL
            }                           OPTIONAL
        }                           OPTIONAL
    }                           OPTIONAL
    criticalExtensions          SEQUENCE {}
}

SRNC-RelocationInfo-r3-IEs ::= SEQUENCE {
    -- Non-RRC IEs
    stateOfRRM                 StateOfRRM,
    stateOfRRM-Procedure        StateOfRRM-Procedure,
    -- Ciphering related information IEs
}

```

```

-- If the extension v380 is included use the extension for the ciphering status per CN domain
cipheringStatus          CipheringStatus,
calculationTimeForCiphering CalculationTimeForCiphering      OPTIONAL,
-- The order of occurrence in the IE cipheringInfoPerRB-List is the
-- same as the RBs in the IE "Signalling RB information list" and in the
-- IE "RAB information list". The signalling RBs are supposed to be listed
-- first. Only UM and AM RBs that are ciphered are listed here
cipheringInfoPerRB-List   CipheringInfoPerRB-List      OPTIONAL,
count-C-List              COUNT-C-List                OPTIONAL,
integrityProtectionStatus IntegrityProtectionStatus,
srb-SpecificIntegrityProtInfo SRB-SpecificIntegrityProtInfoList,
implementationSpecificParams ImplementationSpecificParams OPTIONAL,
-- User equipment IEs
u-RNTI                   U-RNTI,
c-RNTI                   C-RNTI                OPTIONAL,
ue-RadioAccessCapability UE-RadioAccessCapability,
ue-Positioning-LastKnownPos UE-Positioning-LastKnownPos OPTIONAL,
-- Other IEs
ue-RATSpecificCapability InterRAT-UE-RadioAccessCapabilityList OPTIONAL,
-- UTRAN mobility IEs
ura-Identity             URA-Identity           OPTIONAL,
-- Core network IEs
cn-CommonGSM-MAP-NAS-SysInfo NAS-SystemInformationGSM-MAP,
cn-DomainInformationList   CN-DomainInformationList    OPTIONAL,
-- Measurement IEs
ongoingMeasRepList       OngoingMeasRepList        OPTIONAL,
-- Radio bearer IEs
predefinedConfigStatusList PredefinedConfigStatusList,
srb-InformationList       SRB-InformationSetupList,
rab-InformationList       RAB-InformationSetupList    OPTIONAL,
-- Transport channel IEs
ul-CommonTransChInfo     UL-CommonTransChInfo      OPTIONAL,
ul-TransChInfoList        UL-AddReconfTransChInfoList OPTIONAL,
modeSpecificInfo          CHOICE {
                           SEQUENCE {
                               cpch-SetID      CPCH-SetID      OPTIONAL,
                               transChDRAC-Info DRAC-StaticInformationList OPTIONAL
                           },
                           tdd
                           NULL
},
dl-CommonTransChInfo     DL-CommonTransChInfo      OPTIONAL,
dl-TransChInfoList        DL-AddReconfTransChInfoList OPTIONAL,
-- Measurement report
measurementReport         MeasurementReport        OPTIONAL
}

SRNC-RelocationInfo-v380ext-IEs ::= SEQUENCE {
-- Ciphering related information IEs
cn-DomainIdentity          CN-DomainIdentity,
cipheringStatusList         CipheringStatusList
}

SRNC-RelocationInfo-v390ext-IEs ::= SEQUENCE {
cn-DomainInformationList-v390ext CN-DomainInformationList-v390ext      OPTIONAL,
ue-RadioAccessCapability-v370ext  UE-RadioAccessCapability-v370ext      OPTIONAL,
ue-RadioAccessCapability-v380ext  UE-RadioAccessCapability-v380ext      OPTIONAL,
dl-PhysChCapabilityFDD-v380ext  DL-PhysChCapabilityFDD-v380ext      OPTIONAL,
failureCauseWithProtErr      FailureCauseWithProtErr    OPTIONAL
}

SRNC-RelocationInfo-v3a0ext-IEs ::= SEQUENCE {
cipheringInfoForSRB1-v3a0ext   CipheringInfoPerRB-List-v3a0ext,
ue-RadioAccessCapability-v3a0ext UE-RadioAccessCapability-v3a0ext      OPTIONAL,
-- cn-domain identity for IE startValueForCiphering-v3a0ext is specified
-- in subsequent extension (SRNC-RelocationInfo-v3b0ext-IEs)
startValueForCiphering-v3a0ext START-Value
}

SRNC-RelocationInfo-v3b0ext-IEs ::= SEQUENCE {
-- cn-domain identity for IE startValueForCiphering-v3a0ext included in previous extension
cn-DomainIdentity            CN-DomainIdentity,
-- the remaining start values are contained in IE startValueForCiphering-v3b0ext
startValueForCiphering-v3b0ext STARTList2      OPTIONAL
}

SRNC-RelocationInfo-v3c0ext-IEs ::= SEQUENCE {
-- IE rb-IdentityForHOMessage includes the identity of the RB used by the source SRNC
-- to send the message contained in the IE "TargetRNC-ToSourceRNC-Container".
}

```

```
-- Only included if type is "UE involved"
rb-IdentityForHOMessage          RB-Identity      OPTIONAL
}
```

```
| SRNC-RelocationInfo-v3d0ext-IEs ::= SEQUENCE {
|   ue-RadioAccessCapability-v3d0ext    UE-SpecificBehaviourInfo    OPTIONAL
| }
```

### 14.12.2 RRC information, target RNC to source RNC

There are 2 possible cases for RNC relocation:

1. The UE is already under control of target RNC; and
2. The SRNC Relocation with Hard Handover (UE still under control of SRNC), but UE is moving to a location controlled by the target RNC (based on measurement information).

In case 1 the relocation is transparent to the UE and there is no "reverse" direction container. The SRNC just assigns the 'serving' function to the target RNC, which then becomes the Serving RNC.

In case 2 the relocation is initiated by SRNC, which also provides the RRC Initialisation Information to the target RNC. Base on this information, the target RNC prepares the Hard Handover Message ("Physical channel reconfiguration" (subclause 8.2.6), "radio bearer establishment" (subclause 8.2.1), "Radio bearer reconfiguration" (subclause 8.2.2), "Radio bearer release" (subclause 8.2.3) or "Transport channel reconfiguration" (subclause 8.2.4)).

In case 2 two possibilities are defined in order to transmit the relocation message from the target RNC to the source RNC which can be chosen by the source RNC by including or not including the IE "RB Id for handover message" in the IE "SRNS Relocation Info".

In case the IE "RB Id for handover message" has been received by the target RNC in the IE "SRNS Relocation Info", the target RNC should choose the IE "DL DCCH message" and include the DL DCCH message that should be transmitted transparently to the UE by the source RNC. In that case, the target RNC is integrity protecting the message if applicable.

If the target RNC did not receive the IE "RB Id for handover message" in the IE "SRNS Relocation Info" the target RNC should use another choice. In that case, the source RNC should integrity protect the message before transmitting it to the UE if applicable.

If the source RNC received the IE "UE specific behaviour info" from the UE, it should include this IE in the SRNS RELOCATION INFO message.

The source RNC ~~then~~ transmits the Handover Message to the UE, which then performs the handover.

In the successful case, the UE transmits an XXX COMPLETE message, using the new configuration, to the target RNC.

In case of failure, the UE transmits an XXX FAILURE, using the old configuration, to the source RNC and the RRC context remains unchanged (has to be confirmed and checked with the SRNS relocation procedure).

Information Element/Group name	Need	Multi	Type and reference	Semantics description
CHOICE RRC message	MP			At least one spare choice, Criticality: Reject, is needed
>RADIO BEARER SETUP			RADIO BEARER SETUP 10.2.31	
>RADIO BEARER RECONFIGURATION			RADIO BEARER RECONFIGURATION 10.2.25	
>RADIO BEARER RELEASE			RADIO BEARER RELEASE 10.2.28	
>TRANSPORT CHANNEL RECONFIGURATION			TRANSPORT CHANNEL RECONFIGURATION 10.2.51	
>PHYSICAL CHANNEL RECONFIGURATION			PHYSICAL CHANNEL RECONFIGURATION	

Information Element/Group name	Need	Multi	Type and reference	Semantics description
			10.2.20	
>RRC FAILURE INFO			RRC FAILURE INFO 10.2.41 a	
>DL DCCH message			OCTET STRING	

## CHANGE REQUEST

⌘ 25.331 CR 1789 ⌘ rev 1 ⌘ Current version: 4.7.0 ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

**Proposed change affects:** UICC apps ⌘ ME  Radio Access Network  Core Network ⌘

<b>Title:</b>	⌘ Compact IMEI-SV transfer across Uu and within RRC containers	
<b>Source:</b>	⌘ Ericsson	
<b>Work item code:</b>	⌘ TEI	<b>Date:</b> ⌘ 13/11/2002
<b>Category:</b>	⌘ <b>B</b> <i>Use one of the following categories:</i> <b>F</b> (correction) <b>A</b> (corresponds to a correction in an earlier release) <b>B</b> (addition of feature), <b>C</b> (functional modification of feature) <b>D</b> (editorial modification)	<b>Release:</b> ⌘ REL-4 <i>Use one of the following releases:</i> 2 (GSM Phase 2) R96 (Release 1996) R97 (Release 1997) R98 (Release 1998) R99 (Release 1999) Rel-4 (Release 4) Rel-5 (Release 5) Rel-6 (Release 6)
<i>Detailed explanations of the above categories can be found in 3GPP TR 21.900.</i>		

<b>Reason for change:</b>	⌘ The changes included in this CR are proposed for the following reasons:
	<ul style="list-style-type: none"> <li>RP has tasked R2 to agree on a solution for the handling of early UEs, which is currently not sufficiently covered in R99. The proposal is to introduce an IE indicating the version of a UE implementation. This indication may be used by the network to avoid invoking functionality towards UEs for which interoperability problems are experienced/ foreseen.</li> </ul>

<b>Summary of change:</b>	⌘ This CR introduces the following changes:
	<ul style="list-style-type: none"> <li>A new IE “UE specific behaviour info” is defined. It is added to the following messages:           <ul style="list-style-type: none"> <li>RRC CONNECTION REQUEST message (MP)</li> <li>INTER RAT HANDOVER INFO message (MP) and the INTER RAT HANDOVER INFO WITH INTER RAT CAPABILITIES (implicitly, since it includes INTER RAT HANDOVER INFO message)</li> <li>UE CAPABILITY INFORMATION message (OP)</li> <li>SRNS RELOCATION INFO message (MP)</li> </ul> </li> <li>The “UE specific behaviour info” IE includes the decimal to binary conversion of the first 6 bits of the TAC concatenated with the SVN fields of the IMEI-SV</li> </ul>

<b>Consequences if not approved:</b>	⌘ In case there are interoperability problems with early UE implementations, networks have no other choice but to either experience these problems or to refrain from using functionality with interoperability problems towards all early UEs
--------------------------------------	--

<b>Clauses affected:</b>	⌘ 8.1.16.3, 8.6.3.12, 10.2.39, 10.3.3.42, 10.3.3.45a (new), 11.2, 11.3, 11.5, 14.12.2
--------------------------	---

<b>Other specs affected:</b>	<table border="1" style="display: inline-table; vertical-align: middle;"> <tr><td>Y</td><td>N</td></tr> <tr><td>X</td><td>Other core specifications</td></tr> <tr><td>X</td><td>Test specifications</td></tr> <tr><td>X</td><td>O&amp;M Specifications</td></tr> </table> <span style="margin-left: 20px;">⌘</span> <span style="background-color: yellow; width: 200px; height: 20px; display: inline-block;"></span>	Y	N	X	Other core specifications	X	Test specifications	X	O&M Specifications
Y	N								
X	Other core specifications								
X	Test specifications								
X	O&M Specifications								
<b>Other comments:</b>	⌘ This is a complete proposal that does not require changes on other interfaces								

**How to create CRs using this form:**

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>. Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

### 8.1.16.3 INTER RAT HANDOVER INFO message contents to set

The UE shall:

- 1> include the IE "Predefined configuration status information" and the IE "UE security information";
- 1> include the IE "UE capability container", containing the IE "UE radio access capability" and the IE "UE radio access capability extension", in accordance with the following:
  - 2> if the UE supports multiple UTRA FDD Frequency Bands; or
  - 2> if the UE supports a single UTRA FDD Frequency Band different from 2100 MHz:
    - 3> include the IE "UE radio access capability", excluding IEs "RF capability FDD" and "Measurement capability";
    - 3> include the IE "UE radio access capability extension", including the IEs "RF capability FDD extension" and the "Measurement capability extension" associated with each supported UTRA FDD frequency band indicated in the IE "Frequency band".
  - 2> else:
    - 3> include the IE "UE radio access capability", including the IEs "RF capability FDD" and "Measurement capability" associated with the 2100 MHz UTRA FDD frequency band;
    - 3> include the IE "UE radio access capability extension", including the IEs "RF capability FDD extension" and the "Measurement capability extension" associated with each supported UTRA FDD frequency band indicated in the IE "Frequency band".
- 2> include its UE specific behaviour information in the IE "UE specific behaviour info" in the variable UE\_CAPABILITY\_REQUESTED.
  - 1> initiate the transfer of the INTER RAT HANDOVER INFO message via the other radio access technology, using radio access technology-specific procedures;
  - 1> store the IE "Predefined configuration status information", the IE "UE security information", the IE "UE radio access capability" and the IE "UE radio access capability extension", if included in the INTER RAT HANDOVER MESSAGE, in variable INTER\_RAT\_HANDOVER\_INFO\_TRANSFERRED;
  - 1> and the procedure ends.

### 8.6.3.12 Capability Update Requirement

If the IE "Capability Update Requirement" is included the UE shall:

- 1> if the IE "UE radio access FDD capability update requirement" has the value TRUE:
  - 2> if the UE supports FDD mode:
    - 3> store its UTRA FDD capabilities and its UTRA capabilities common to FDD and TDD in the IE "UE radio access capability" and the IE "UE radio access capability extension" in variable UE\_CAPABILITY\_REQUESTED as specified below:
      - 4> if the UE supports multiple UTRA FDD Frequency Bands; or
      - 4> if the UE supports a single UTRA FDD Frequency Band different from 2100 MHz:
        - 5> store the IE "UE radio access capability", excluding IEs "RF capability FDD" and "Measurement capability";
        - 5> store the IE "UE radio access capability extension", including the IEs "RF capability FDD extension" and the "Measurement capability extension" associated with each supported UTRA FDD frequency band indicated in the IE "Frequency band".
      - 4> else:
        - 5> store the IE "UE radio access capability", including the IEs "RF capability FDD" and "Measurement capability" associated with the 2100 MHz UTRA FDD frequency band.
    - 3> include its UE specific behaviour information in the IE "UE specific behaviour info" in the variable UE\_CAPABILITY\_REQUESTED.
  - 1> if the IE "UE radio access 3.84 Mcps TDD capability update requirement" has the value TRUE:
    - 2> if the UE supports 3.84 Mcps TDD mode:
      - 3> store its UTRAN-specific 3.84 Mcps TDD capabilities and its UTRAN-specific capabilities common to FDD and TDD in the variable UE\_CAPABILITY\_REQUESTED.
      - 3> include its UE specific behaviour information in the IE "UE specific behaviour info" in the variable UE\_CAPABILITY\_REQUESTED.
    - 1> if the IE "UE radio access 1.28 Mcps TDD capability update requirement" has the value TRUE:
      - 2> if the UE supports 1.28 Mcps TDD mode:
        - 3> store its UTRAN-specific 1.28 Mcps TDD capabilities and its UTRAN-specific capabilities common to FDD and TDD in the variable UE\_CAPABILITY\_REQUESTED.
        - 3> include its UE specific behaviour information in the IE "UE specific behaviour info" in the variable UE\_CAPABILITY\_REQUESTED.
      - 1> if the IE "System specific capability update requirement list" is present:
        - 2> for each of the RAT requested in the IE "UE system specific capability"
          - 3> if the UE supports the listed RAT:
            - 4> include its inter-RAT radio access capabilities for the listed RAT in the IE "UE system specific capability" from the variable UE\_CAPABILITY\_REQUESTED.

If the IE " Capability update requirement " is not present, the UE shall:

- 1> assume the default values as specified in subclause 10.3.3.2 and act in accordance with the above.

### 10.2.39 RRC CONNECTION REQUEST

RRC Connection Request is the first message transmitted by the UE when setting up an RRC Connection to the network.

RLC-SAP: TM

Logical channel: CCCH

Direction: UE → UTRAN

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
Message Type	MP		Message Type		
<b>UE information elements</b>					
Initial UE identity	MP		Initial UE identity 10.3.3.15		
Establishment cause	MP		Establishment cause 10.3.3.11		
Protocol error indicator	MD		Protocol error indicator 10.3.3.27	Default value is FALSE	
<b>Measurement information elements</b>					
Measured results on RACH	OP		Measured results on RACH 10.3.7.45		
Access stratum release indicator	MP		Enumerated( REL-4)	Absence of the IE implies R99. The IE also indicates the release of the RRC transfer syntax supported by the UE 15 spare values are needed	REL-4
<u>UE specific behaviour info</u>	MP		<u>UE specific behaviour info</u> 10.3.3.45a		

If the encoded message does not fill a transport block, the RRC layer shall insert padding according to subclause 12.1.

## 10.3.3.42 UE radio access capability

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
Access stratum release indicator	MP		Enumerated( R99)	Indicates the release of the UE according to [35]. The IE also indicates the release of the RRC transfer syntax supported by the UE..	
	CV- <i>not_rrc_connectionSetupComplete</i>		Enumerated( REL-4)	15 spare values are needed.	REL-4
<u>UE specific behaviour info</u>	<u>CH- <i>rrcConnectionSetupComplete</i></u>		<u>UE specific behaviour info</u> 10.3.3.45a		
PDCP capability	MP		PDCP capability 10.3.3.24		
RLC capability	MP		RLC capability 10.3.3.34		
Transport channel capability	MP		Transport channel capability 10.3.3.40		
RF capability FDD	OP		RF capability FDD 10.3.3.33		
RF capability TDD	OP		RF capability TDD 10.3.3.33b	One "TDD RF capability" entity shall be included for every Chip rate capability supported.	
		1 to 2			REL-4
Physical channel capability	MP		Physical channel capability 10.3.3.25		
UE multi-mode/multi-RAT capability	MP		UE multi-mode/multi-RAT capability 10.3.3.41		
Security capability	MP		Security capability 10.3.3.37		
UE positioning capability	MP		UE positioning capability 10.3.3.45		
Measurement capability	CH- <i>fdd_req_su</i> p		Measuremen t capability 10.3.3.21		

Condition	Explanation
<i>fdd_req_sup</i>	The IE is mandatory present if the IE "Multi-mode capability" has the value "FDD" or "FDD/TDD" and a FDD capability update has been requested in a previous message. Otherwise this field is not needed in the message.
<i>not_rrc_connectionSetupComplete</i>	The IE is not needed in the RRC CONNECTION SETUP COMPLETE message. Otherwise the IE is mandatory present.
<i>rrcConnectionSetupComplete</i>	The IE is not needed in the RRC CONNECTION SETUP COMPLETE message. The IE is optional in the UE CAPABILITY INFORMATION and the SRNS RELOCATION INFO message. Otherwise the IE is mandatory present.

### 10.3.3.45a UE specific behaviour info

<u>Information Element/Group name</u>	<u>Need</u>	<u>Multi</u>	<u>Type and reference</u>	<u>Semantics description</u>
IMEI-SV	MP		Bitstring (32)	A compact version of the IMEI-SV [see 23.003] comprising of the decimal to binary conversion of the concatenation of the TAC and the SVN digits. The bits of the result are numbered from b0 to b31, with bit b0 being the least significant.

## 11.2 PDU definitions

```
--*****
-- TABULAR: The message type and integrity check info are not
-- visible in this module as they are defined in the class module.
-- Also, all FDD/TDD specific choices have the FDD option first
-- and TDD second, just for consistency.
--*****
PDU-definitions DEFINITIONS AUTOMATIC TAGS ::=

BEGIN

--*****
-- IE parameter types from other modules
--*****
IMPORTS

-- Core Network IEs :
CN-DomainIdentity,
CN-InformationInfo,
CN-InformationInfoFull,
NAS-Message,
PagingRecordTypeID,
-- UTRAN Mobility IEs :
CellIdentity,
CellIdentity-PerRL-List,
URA-Identity,
-- User Equipment IEs :
ActivationTime,
C-RNTI,
CapabilityUpdateRequirement,
CapabilityUpdateRequirement-r4,
CapabilityUpdateRequirement-r4-ext,
CellUpdateCause,
CipheringAlgorithm,
CipheringModeInfo,
DSCH-RNTI,
EstablishmentCause,
FailureCauseWithProtErr,
FailureCauseWithProtErrTrId,
InitialUE-Identity,
IntegrityProtActivationInfo,
IntegrityProtectionModeInfo,
N-308,
PagingCause,
PagingRecordList,
ProtocolErrorIndicator,
ProtocolErrorIndicatorWithMoreInfo,
Rb-timer-indicator,
RedirectionInfo,
RejectionCause,
ReleaseCause,
RRC-StateIndicator,
RRC-TransactionIdentifier,
SecurityCapability,
START-Value,
STARTList,
U-RNTI,
U-RNTI-Short,
UE-RadioAccessCapability,
UE-RadioAccessCapability-r4-ext,
UE-RadioAccessCapability-v370ext,
UE-RadioAccessCapability-v380ext,
UE-RadioAccessCapability-v3a0ext,
UE-RadioAccessCapability-v4xyext,
DL-PhysChCapabilityFDD-v380ext,
UE-ConnTimersAndConstants,
UE-ConnTimersAndConstants-v3a0ext,
UE-SecurityInformation,
UE-SpecificBehaviourInfo,
```

```

URA-UpdateCause,
UTRAN-DRX-CycleLengthCoefficient,
WaitTime,
-- Radio Bearer IEs :
DefaultConfigIdentity,
DefaultConfigIdentity-r4,
DefaultConfigMode,
DL-CounterSynchronisationInfo,
PredefinedConfigIdentity,
PredefinedConfigStatusList,
RAB-Info,
RAB-Info-Post,
RAB-InformationList,
RAB-InformationReconfigList,
RAB-InformationSetupList,
RAB-InformationSetupList-r4,
RB-ActivationTimeInfoList,
RB-COUNT-C-InformationList,
RB-COUNT-C-MSB-InformationList,
RB-IdentityList,
RB-InformationAffectedList,
RB-InformationReconfigList,
RB-InformationReconfigList-r4,
RB-InformationReleaseList,
SRB-InformationSetupList,
SRB-InformationSetupList2,
UL-CounterSynchronisationInfo,
-- Transport Channel IEs:
CPCH-SetID,
DL-AddReconfTransChInfo2List,
DL-AddReconfTransChInfoList,
DL-AddReconfTransChInfoList-r4,
DL-CommonTransChInfo,
DL-CommonTransChInfo-r4,
DL-DeletedTransChInfoList,
DRAC-StaticInformationList,
TFC-Subset,
TFCS-Identity,
UL-AddReconfTransChInfoList,
UL-CommonTransChInfo,
UL-CommonTransChInfo-r4,
UL-DeletedTransChInfoList,
-- Physical Channel IEs :
Alpha,
CCTrCH-PowerControlInfo,
CCTrCH-PowerControlInfo-r4,
ConstantValue,
ConstantValueTdd,
CPCH-SetInfo,
DL-CommonInformation,
DL-CommonInformation-r4,
DL-CommonInformationPost,
DL-InformationPerRL,
DL-InformationPerRL-List,
DL-InformationPerRL-List-r4,
DL-InformationPerRL-ListPostFDD,
DL-InformationPerRL-PostTDD,
DL-InformationPerRL-PostTDD-LCR-r4,
DL-PDSCH-Information,
DPCH-CompressedModeStatusInfo,
FrequencyInfo,
FrequencyInfoFDD,
FrequencyInfoTDD,
MaxAllowedUL-TX-Power,
OpenLoopPowerControl-IPDL-TDD-r4,
PDSCH-CapacityAllocationInfo,
PDSCH-CapacityAllocationInfo-r4,
PDSCH-Identity,
PrimaryCCPCH-TX-Power,
PUSCH-CapacityAllocationInfo,
PUSCH-CapacityAllocationInfo-r4,
PUSCH-Identity,
RL-AdditionInformationList,
RL-RemovalInformationList,
SpecialBurstScheduling,
SSDT-Information,
TFC-ControlDuration,
SSDT-UL-r4,

```

```

TimeslotList,
TimeslotList-r4,
TX-DiversityMode,
UL-ChannelRequirement,
UL-ChannelRequirement-r4,
UL-ChannelRequirementWithCPCH-SetID,
UL-ChannelRequirementWithCPCH-SetID-r4,
UL-DPCH-Info,
UL-DPCH-Info-r4,
UL-DPCH-InfoPostFDD,
UL-DPCH-InfoPostTDD,
UL-DPCH-InfoPostTDD-LCR-r4,
UL-SynchronisationParameters-r4,
UL-TimingAdvance,
UL-TimingAdvanceControl,
UL-TimingAdvanceControl-r4,
-- Measurement IEs :
AdditionalMeasurementID-List,
Frequency-Band,
EventResults,
InterFreqEventResults-LCR-r4-ext,
InterRAT-TargetCellDescription,
MeasuredResults,
MeasuredResults-v390ext,
MeasuredResultsList,
MeasuredResultsList-LCR-r4-ext,
MeasuredResultsOnRACH,
MeasurementCommand,
MeasurementCommand-r4,
MeasurementIdentity,
MeasurementReportingMode,
PrimaryCCPCH-RSCP,
SFN-Offset-Validity,
TimeslotListWithISCP,
TrafficVolumeMeasuredResultsList,
UE-Positioning-GPS-AssistanceData,
UE-Positioning-Measurement-v390ext,
UE-Positioning-OTDOA-AssistanceData,
UE-Positioning-OTDOA-AssistanceData-r4ext,
UE-Positioning-OTDOA-AssistanceData-UEB,
UE-Positioning-IPDL-Parameters-TDD-r4-ext,
-- Other IEs :
BCCH-ModificationInfo,
CDMA2000-MessageList,
GSM-MessageList,
InterRAT-ChangeFailureCause,
InterRAT-HO-FailureCause,
InterRAT-UE-RadioAccessCapabilityList,
InterRAT-UE-SecurityCapList,
IntraDomainNasNodeSelector,
ProtocolErrorMoreInformation,
Rplmn-Information,
Rplmn-Information-r4,
SegCount,
SegmentIndex,
SPN-Prime,
SIB-Data-fixed,
SIB-Data-variable,
SIB-Type
FROM InformationElements

maxSIBperMsg
FROM Constant-definitions;

<Cut until the next modified section>

-- ****
-- INTER RAT HANDOVER INFO
-- ****

InterRATHandoverInfo ::= SEQUENCE {
    -- This structure is defined for historical reasons, backward compatibility with 04.18
    predefinedConfigStatusList      CHOICE {
        absent                  NULL,
        present                 PredefinedConfigStatusList
    },
    uE-SecurityInformation         CHOICE {

```

```

        absent           NULL,
        present          UE-SecurityInformation
    },
    ue-CapabilityContainer      CHOICE {
        absent           NULL,
        -- present is an octet aligned string containing IE UE-RadioAccessCapabilityInfo
        present          OCTET STRING (SIZE (0..63))
    },
    -- Non critical extensions
    v390NonCriticalExtensions  CHOICE {
        absent           NULL,
        present          SEQUENCE {
            interRATHandoverInfo-v390ext   InterRATHandoverInfo-v390ext-IEs,
            v3a0NonCriticalExtensions     SEQUENCE {
                interRATHandoverInfo-v3a0ext   InterRATHandoverInfo-v3a0ext,
                v3d0NonCriticalExtensions     SEQUENCE {
                    interRATHandoverInfo-v3d0ext   InterRATHandoverInfo-v3d0ext-IEs,
                    v4xyNonCriticalExtensions   SEQUENCE {
                        interRATHandoverInfo-v4xyext   InterRATHandoverInfo-v4xyext-IEs,
                        -- Reserved for future non critical extension
                        nonCriticalExtensions       SEQUENCE {} OPTIONAL
                    }
                }
            }
        }
    }
}

InterRATHandoverInfo-v390ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v380ext     UE-RadioAccessCapability-v380ext      OPTIONAL,
    dl-PhysChCapabilityFDD-v380ext      DL-PhysChCapabilityFDD-v380ext
}

InterRATHandoverInfo-v3a0ext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v3a0ext     UE-RadioAccessCapability-v3a0ext      OPTIONAL
}

InterRATHandoverInfo-v3b0ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v3d0ext     UE-SpecificBehaviourInfo
}

InterRATHandoverInfo-v4xyext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v4xyext     UE-RadioAccessCapability-v4xyext
}

<Cut until the next modified section>

-- ****
-- RRC CONNECTION REQUEST
-- ****

RRCCConnectionRequest ::= SEQUENCE {
    -- TABULAR: Integrity protection shall not be performed on this message.
    -- User equipment IEs
    initialUE-Identity           InitialUE-Identity,
    establishmentCause            EstablishmentCause,
    -- protocolErrorIndictator is MD, but for compactness reasons no default value
    -- has been assigned to it.
    protocolErrorIndicator        ProtocolErrorIndicator,
    -- Measurement IEs
    measuredResultsOnRACH         MeasuredResultsOnRACH      OPTIONAL,
    v3d0NonCriticalExtensions     SEQUENCE {
        RRCCConnectionRequest-v3d0ext   RRCCConnectionRequest-v3d0ext-IEs,
        v4xyNonCriticalExtensions     SEQUENCE {
            rrcConnectionRequest-v4xyext   RRCCConnectionRequest-v4xyext-IEs,
            -- Reserved for future non critical extension
            nonCriticalExtensions       SEQUENCE {}      OPTIONAL
        }
    }
}
}

RRCCConnectionRequest-v3d0ext-IEs ::= SEQUENCE {

```

```

-- User equipment IEs
ue-RadioAccessCapability-v3d0ext      UE-SpecificBehaviourInfo
}

RRCConnectionRequest-v4xyext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v4xyext      UE-RadioAccessCapability-v4xyext
}

<Cut until the next modified section>

-- ****
-- UE CAPABILITY INFORMATION
-- ****

UECapabilityInformation ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier      OPTIONAL,
    ue-RadioAccessCapability       UE-RadioAccessCapability      OPTIONAL,
    -- Other IEs
    ue-RATSpecificCapability      InterRAT-UE-RadioAccessCapabilityList
    OPTIONAL,
    v370NonCriticalExtensions     SEQUENCE {
        ueCapabilityInformation-v370ext  UECapabilityInformation-v370ext,
        v380NonCriticalExtensions      SEQUENCE {
            ueCapabilityInformation-v380ext  UECapabilityInformation-v380ext-IEs,
            v3a0NonCriticalExtensions    SEQUENCE {
                ueCapabilityInformation-v3a0ext  UECapabilityInformation-v3a0ext,
                Reserved for future non critical extension
            }
            v3d0NonCriticalExtensions      SEQUENCE {
                ueCapabilityInformation-v3d0ext  UECapabilityInformation-v3d0ext-IEs,
                -- Reserved for future non critical extension
            }
            v4xyNonCriticalExtensions     SEQUENCE {
                ueCapabilityInformation-v4xyext  UECapabilityInformation-v4xyext,
                -- Reserved for future non critical extension
            }
            nonCriticalExtensions        SEQUENCE {}      OPTIONAL
        }
        OPTIONAL
    }
    OPTIONAL
}
OPTIONAL

UECapabilityInformation-v370ext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v370ext      UE-RadioAccessCapability-v370ext      OPTIONAL
}

UECapabilityInformation-v380ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v380ext      UE-RadioAccessCapability-v380ext
    OPTIONAL,
    dl-PhysChCapabilityFDD-v380ext      DL-PhysChCapabilityFDD-v380ext
}

UECapabilityInformation-v3a0ext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v3a0ext      UE-RadioAccessCapability-v3a0ext      OPTIONAL
}

UECapabilityInformation-v3d0ext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v3d0ext      UE-SpecificBehaviourInfo      OPTIONAL
}

UECapabilityInformation-v4xyext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-r4-ext      UE-RadioAccessCapability-r4-ext      OPTIONAL,
    ue-RadioAccessCapability-v4xyext      UE-RadioAccessCapability-v4xyext
}

```

## 11.3 Information element definitions

InformationElements DEFINITIONS AUTOMATIC TAGS ::=

```
<Cut until the next modified section>
-- ****
-- USER EQUIPMENT INFORMATION ELEMENTS (10.3.3)
-- ****

<Cut until the next modified section>
| UE-SpecificBehaviourInfo ::= SEQUENCE {
|   imei-sv-compact           BIT STRING (SIZE (32))
| }
```

## 11.5 RRC information between network nodes

Internode-definitions DEFINITIONS AUTOMATIC TAGS ::=

BEGIN

IMPORTS

```

HandoverToUTRANCommand,
MeasurementReport,
PhysicalChannelReconfiguration,
RadioBearerReconfiguration,
RadioBearerRelease,
RadioBearerSetup,
RRC-FailureInfo-r3-IEs,
TransportChannelReconfiguration
FROM PDU-definitions

-- Core Network IE-s :
CN-DomainIdentity,
CN-DomainInformationList,
CN-DomainInformationListFull,
CN-DRX-CycleLengthCoefficient,
NAS-SystemInformationGSM-MAP,
-- UTRAN Mobility IE-s :
CellIdentity,
URA-Identity,
-- User Equipment IE-s :
AccessStratumReleaseIndicator,
C-RNTI,
ChipRateCapability,
DL-PhysChCapabilityFDD-v380ext,
DL-PhysChCapabilityTDD,
DL-PhysChCapabilityTDD-LCR-r4,
GSM-Measurements,
FailureCauseWithProtErr,
MaxHcContextSpace,
MaxNoPhysChBitsReceived,
MaxROHC-ContextSessions-r4,
NetworkAssistedGPS-Supported,
RadioFrequencyBandTDDList,
RLC-Capability,
RRC-MessageSequenceNumber,
SecurityCapability,
SimultaneousSCCPCH-DPCH-Reception,
STARTList,
STARTSingle,
START-Value,
SupportOfDedicatedPilotsForChEstimation,
TransportChannelCapability,
TxRxFrequencySeparation,
U-RNTI,
UE-MultiModeRAT-Capability,
UE-PowerClass-v370,
UE-RadioAccessCapabBandFDDList,
UE-RadioAccessCapability,
UE-RadioAccessCapability-v370ext,
UE-RadioAccessCapability-v380ext,
UE-RadioAccessCapability-v3a0ext,
UE-RadioAccessCapability-v4xyext,
UL-PhysChCapabilityFDD,
UL-PhysChCapabilityTDD,
UL-PhysChCapabilityTDD-LCR-r4,
UE-SpecificBehaviourInfo,
-- Radio Bearer IE-s :
PredefinedConfigStatusList,
PredefinedConfigValueTag,
RAB-InformationSetupList,
RAB-InformationSetupList-r4,
RAB-Identity,
RB-Identity,
SRB-InformationSetupList,
-- Transport Channel IE-s :
CPCH-SetID,
DL-CommonTransChInfo,
DL-CommonTransChInfo-r4,
```

```

DL-AddReconfTransChInfoList,
DL-AddReconfTransChInfoList-r4,
DRAC-StaticInformationList,
UL-CommonTransChInfo,
UL-CommonTransChInfo-r4,
UL-AddReconfTransChInfoList,
-- Measurement IEs :
MeasurementIdentity,
MeasurementReportingMode,
MeasurementType,
MeasurementType-r4,
AdditionalMeasurementID-List,
PositionEstimate,
UE-Positioning-IPDL-Parameters-TDD-r4-ext,
-- Other IEs :
InterRAT-UE-RadioAccessCapabilityList

FROM InformationElements

maxCNdomains,
maxNoOfMeas,

maxRB,
maxSRBsetup
FROM Constant-definitions
;

<Cut until the next modified section>

-- Part2: Container definitions, similar to the PDU definitions in 11.2 for RRC messages
-- In alphabetical order

-- ****
-- Handover to UTRAN information
-- ****

InterRATHandoverInfoWithInterRATCapabilities-r3 ::= CHOICE {
r3
    SEQUENCE {
        -- IE InterRATHandoverInfoWithInterRATCapabilities-r3-IEs also
        -- includes non critical extensions
        interRATHandoverInfo-r3           InterRATHandoverInfoWithInterRATCapabilities-r3-IEs,
        v390NonCriticalExtensions       SEQUENCE {
            interRATHandoverInfoWithInterRATCapabilities-v390ext
        InterRATHandoverInfoWithInterRATCapabilities-v390ext-IEs,
            -- Reserved for future non critical extension
            nonCriticalExtensions     SEQUENCE {} OPTIONAL
        }
        OPTIONAL
    },
    criticalExtensions          SEQUENCE {}
}

InterRATHandoverInfoWithInterRATCapabilities-r3-IEs ::=      SEQUENCE {
    -- The order of the IEs may not reflect the tabular format
    -- but has been chosen to simplify the handling of the information in the BSC
    -- Other IEs
    ue-RATSpecificCapability      InterRAT-UE-RadioAccessCapabilityList OPTIONAL,
    -- interRATHandoverInfo, Octet string is used to obtain 8 bit length field prior to
    -- actual information. This makes it possible for BSS to transparently handle information
    -- received via GSM air interface even when it includes non critical extensions.
    -- The octet string shall include the InterRATHandoverInfo information
    -- The BSS can re-use the 04.18 length field received from the MS
    interRATHandoverInfo          OCTET STRING (SIZE (0..255))
}

InterRATHandoverInfoWithInterRATCapabilities-v390ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    failureCauseWithProtErr      FailureCauseWithProtErr
    OPTIONAL
}

-- ****
-- SRNC Relocation information
-- ****

```

```

SRNC-RelocationInfo-r3 ::= CHOICE {
  r3
    SEQUENCE {
      SRNC-RelocationInfo-r3           SRNC-RelocationInfo-r3-IEs,
      v380NonCriticalExtensions       SEQUENCE {
        sRNC-RelocationInfo-v380ext   SRNC-RelocationInfo-v380ext-IEs,
        -- Reserved for future non critical extension
        v390NonCriticalExtensions     SEQUENCE {
          sRNC-RelocationInfo-v390ext   SRNC-RelocationInfo-v390ext-IEs,
          v3a0NonCriticalExtensions     SEQUENCE {
            sRNC-RelocationInfo-v3a0ext   SRNC-RelocationInfo-v3a0ext-IEs,
            v3b0NonCriticalExtensions     SEQUENCE {
              sRNC-RelocationInfo-v3b0ext   SRNC-RelocationInfo-v3b0ext-IEs,
              v3c0NonCriticalExtensions     SEQUENCE {
                sRNC-RelocationInfo-v3c0ext   SRNC-RelocationInfo-v3c0ext-IEs,
                v3d0NonCriticalExtensions     SEQUENCE {
                  sRNC-RelocationInfo-v3d0ext   SRNC-RelocationInfo-v3d0ext-
                IEs,
                v4xyNonCriticalExtensions     SEQUENCE {
                  SRNC-RelocationInfo-v4xyext
                }
                -- Reserved for future non critical extension
                nonCriticalExtensions       SEQUENCE {} OPTIONAL
              }
            }
          }
        }
      }
    }
  },
  later-than-r3
    CHOICE {
      r4
        SEQUENCE {
          SRNC-RelocationInfo-r4           SRNC-RelocationInfo-r4-IEs,
          nonCriticalExtensions         SEQUENCE {} OPTIONAL
        },
        criticalExtensions             SEQUENCE {}
    }
}

SRNC-RelocationInfo-r3-IEs ::= SEQUENCE {
  -- Non-RRC IEs
  stateOfRRC                   StateOfRRC,
  stateOfRRC-Procedure          StateOfRRC-Procedure,
  -- Ciphering related information IEs
  -- If the extension v380 is included use the extension for the ciphering status per CN domain
  cipheringStatus               CipheringStatus,
  calculationTimeForCiphering   CalculationTimeForCiphering OPTIONAL,
  -- The order of occurrence in the IE cipheringInfoPerRB-List is the
  -- same as the RBs in the IE "Signalling RB information list" and in the
  -- IE "RAB information list". The signalling RBs are supposed to be listed
  -- first. Only UM and AM RBs that are ciphered are listed here
  cipheringInfoPerRB-List       CipheringInfoPerRB-List OPTIONAL,
  count-C-List                  COUNT-C-List OPTIONAL,
  integrityProtectionStatus     IntegrityProtectionStatus,
  srb-SpecificIntegrityProtInfo SRB-SpecificIntegrityProtInfoList,
  implementationSpecificParams  ImplementationSpecificParams OPTIONAL,
  -- User equipment IEs
  u-RNTI                       U-RNTI,
  c-RNTI                         C-RNTI OPTIONAL,
  ue-RadioAccessCapability       UE-RadioAccessCapability,
  ue-Positioning-LastKnownPos   UE-Positioning-LastKnownPos OPTIONAL,
  -- Other IEs
  ue-RATSpecificCapability      InterRAT-UE-RadioAccessCapabilityList OPTIONAL,
  -- UTRAN mobility IEs
  ura-Identity                   URA-Identity OPTIONAL,
  -- Core network IEs
  cn-CommonGSM-MAP-NAS-SysInfo  NAS-SystemInformationGSM-MAP,
  cn-DomainInformationList       CN-DomainInformationList OPTIONAL,
  -- Measurement IEs
  ongoingMeasRepList            OngoingMeasRepList OPTIONAL,
  -- Radio bearer IEs
  predefinedConfigStatusList    PredefinedConfigStatusList,
  srb-InformationList           SRB-InformationSetupList,
  rab-InformationList           RAB-InformationSetupList OPTIONAL,
  -- Transport channel IEs
  ul-CommonTransChInfo          UL-CommonTransChInfo OPTIONAL,
  ul-TransChInfoList             UL-AddReconfTransChInfoList OPTIONAL,
}

```

```

modeSpecificInfo          CHOICE {
    fdd                  SEQUENCE {
        cpch-SetID      CPCH-SetID           OPTIONAL,
        transChDRAC-Info DRAC-StaticInformationList OPTIONAL
    },
    tdd                  NULL
},
dl-CommonTransChInfo     DL-CommonTransChInfo   OPTIONAL,
dl-TransChInfoList       DL-AddReconfTransChInfoList OPTIONAL,
-- Measurement report
measurementReport        MeasurementReport      OPTIONAL ,
nonCriticalExtensions    SEQUENCE {
    -- In case of TDD only up-Ipd1-Parameters-TDD is present, otherwise
    -- this IE is absent
    up-Ipd1-Parameters-TDD      UE-Positioning-IPDL-Parameters-TDD-r4-ext  OPTIONAL,
    -- Extension mechanism for non- release4 information
    nonCriticalExtensions     SEQUENCE {}
}
}                           OPTIONAL

SRNC-RelocationInfo-v380ext-IEs ::= SEQUENCE {
    -- Ciphering related information IEs
    cn-DomainIdentity          CN-DomainIdentity,
    cipheringStatusList         CipheringStatusList
}

SRNC-RelocationInfo-v390ext-IEs ::= SEQUENCE {
    cn-DomainInformationList-v390ext  CN-DomainInformationList-v390ext   OPTIONAL,
    ue-RadioAccessCapability-v370ext  UE-RadioAccessCapability-v370ext   OPTIONAL,
    ue-RadioAccessCapability-v380ext  UE-RadioAccessCapability-v380ext   OPTIONAL,
    dl-PhysChCapabilityFDD-v380ext  DL-PhysChCapabilityFDD-v380ext,
    failureCauseWithProtErr       FailureCauseWithProtErr
}

SRNC-RelocationInfo-v3a0ext-IEs ::= SEQUENCE {
    -- cn-domain identity for IE startValueForCiphering-v3a0ext is specified
    -- in subsequent extension (SRNC-RelocationInfo-v3b0ext-IEs)
    startValueForCiphering-v3a0ext  START-Value,
    cipheringInfoForSRB1-v3a0ext   CipheringInfoForSRB1-v3a0ext,
    ue-RadioAccessCapability-v3a0ext UE-RadioAccessCapability-v3a0ext   OPTIONAL
}

SRNC-RelocationInfo-v3b0ext-IEs ::= SEQUENCE {
    -- cn-domain identity for IE startValueForCiphering-v3a0ext included in previous extension
    cn-DomainIdentity          CN-DomainIdentity,
    -- the remaining start values are contained in IE startValueForCiphering-v3b0ext
    startValueForCiphering-v3b0ext  STARTList2
}

SRNC-RelocationInfo-v3c0ext-IEs ::= SEQUENCE {
    -- IE rb-IdentityForHOMessage includes the identity of the RB used by the source SRNC
    -- to send the message contained in the IE "TargetRNC-ToSourceRNC-Container".
    -- Only included if type is "UE involved"
    rb-IdentityForHOMessage     RB-Identity      OPTIONAL
}

SRNC-RelocationInfo-v3d0ext-IEs ::= SEQUENCE {
    ue-RadioAccessCapability-v3d0ext  UE-SpecificBehaviourInfo   OPTIONAL
}

STARTList2 ::= SEQUENCE (SIZE (2..maxCNdomains)) OF
                    STARTSingle

SRNC-RelocationInfo-v4xyext-IEs ::= SEQUENCE {
    ue-RadioAccessCapability-v4xyext  UE-RadioAccessCapability-v4xyext
}

CipheringInfoForSRB1-v3a0ext ::= SEQUENCE {
    dl-UM-SN                  BIT STRING (SIZE (7))
}

CipheringStatusList ::= SEQUENCE (SIZE (1..maxCNdomains)) OF
                    CipheringStatusCNdomain

CipheringStatusCNdomain ::= SEQUENCE {
    cn-DomainIdentity          CN-DomainIdentity,
    cipheringStatus            CipheringStatus
}

```

```

}

SRNC-RelocationInfo-r4-IEs ::= SEQUENCE {
  -- Non-RRC IEs
  -- IE rb-IdentityForHOMessage includes the identity of the RB used by the source SRNC
  -- to send the message contained in the IE "TargetRNC-ToSourceRNC-Container".
  -- Only included if type is "UE involved"
  rb-IdentityForHOMessage      RB-Identity                                OPTIONAL,
  stateOfRRC                  StateOfRRC,
  stateOfRRC-Procedure        StateOfRRC-Procedure,
  -- Ciphering related information IEs
  cipheringStatusList          CipheringStatusList-r4,
  latestConfiguredCN-Domain   CN-DomainIdentity,
  calculationTimeForCiphering CalculationTimeForCiphering           OPTIONAL,
  count-C-List                COUNT-C-List                           OPTIONAL,
  cipheringInfoPerRB-List     CipheringInfoPerRB-List-r4            OPTIONAL,
  -- Integrity protection related information IEs
  integrityProtectionStatus   IntegrityProtectionStatus,
  srb-SpecificIntegrityProtInfo SRB-SpecificIntegrityProtInfoList,
  implementationSpecificParams ImplementationSpecificParams        OPTIONAL,
  -- User equipment IEs
  ue-RNTI                     U-RNTI,
  c-RNTI                      C-RNTI                                OPTIONAL,
  ue-RadioAccessCapability    UE-RadioAccessCapability-r4,
  ue-RadioAccessCapability-ext UE-RadioAccessCapabBandFDDList       OPTIONAL,
  ue-Positioning-LastKnownPos UE-Positioning-LastKnownPos         OPTIONAL,
  -- Other IEs
  ue-RATSpecificCapability   InterRAT-UE-RadioAccessCapabilityList OPTIONAL,
  -- UTRAN mobility IEs
  ura-Identity                URA-Identity                           OPTIONAL,
  -- Core network IEs
  cn-CommonGSM-MAP-NAS-SysInfo NAS-SystemInformationGSM-MAP,
  cn-DomainInformationList    CN-DomainInformationListFull        OPTIONAL,
  -- Measurement IEs
  ongoingMeasRepList          OngoingMeasRepList-r4             OPTIONAL,
  -- Radio bearer IEs
  predefinedConfigStatusList  PredefinedConfigStatusList,
  srb-InformationList         SRB-InformationSetupList,
  rab-InformationList         RAB-InformationSetupList-r4        OPTIONAL,
  -- Transport channel IEs
  ul-CommonTransChInfo        UL-CommonTransChInfo-r4           OPTIONAL,
  ul-TransChInfoList          UL-AddReconfTransChInfoList        OPTIONAL,
  modeSpecificInfo
    fdd
      cpch-SetID              CPCH-SetID                            OPTIONAL,
      transChDRAC-Info        DRAC-StaticInformationList        OPTIONAL
    },
    tdd
  NULL
}
dl-CommonTransChInfo          DL-CommonTransChInfo-r4           OPTIONAL,
dl-TransChInfoList            DL-AddReconfTransChInfoList-r4  OPTIONAL,
-- Measurement report
measurementReport             MeasurementReport                   OPTIONAL,
failureCause                 FailureCauseWithProtErr        OPTIONAL
}

```

<Cut until the next modified section>

<pre> UE-RadioAccessCapability-r4 ::= SEQUENCE {   accessStratumReleaseIndicator AccessStratumReleaseIndicator,   ue-SpecificBehaviourInfo     UE-SpecificBehaviourInfo        OPTIONAL,   pdcp-Capability              PDCP-Capability-r4,   rlc-Capability               RLC-Capability,   transportChannelCapability   TransportChannelCapability,   rf-Capability                RF-Capability-r4,   physicalChannelCapability   PhysicalChannelCapability-r4,   ue-MultiModeRAT-Capability  UE-MultiModeRAT-Capability,   securityCapability           SecurityCapability,   ue-positioning-Capability   UE-Positioning-Capability-r4,   measurementCapability        MeasurementCapability-r4        OPTIONAL } </pre>
--

### 14.12.2 RRC information, target RNC to source RNC

There are 2 possible cases for RNC relocation:

1. The UE is already under control of target RNC; and
2. The SRNC Relocation with Hard Handover (UE still under control of SRNC), but UE is moving to a location controlled by the target RNC (based on measurement information).

In case 1 the relocation is transparent to the UE and there is no "reverse" direction container. The SRNC just assigns the 'serving' function to the target RNC, which then becomes the Serving RNC.

In case 2 the relocation is initiated by SRNC, which also provides the RRC Initialisation Information to the target RNC. Base on this information, the target RNC prepares the Hard Handover Message ("Physical channel reconfiguration" (subclause 8.2.6), "radio bearer establishment" (subclause 8.2.1), "Radio bearer reconfiguration" (subclause 8.2.2), "Radio bearer release" (subclause 8.2.3) or "Transport channel reconfiguration" (subclause 8.2.4)).

In case 2 two possibilities are defined in order to transmit the relocation message from the target RNC to the source RNC which can be chosen by the source RNC by including or not including the IE "RB Id for handover message" in the IE "SRNS Relocation Info".

In case the IE "RB Id for handover message" has been received by the target RNC in the IE "SRNS Relocation Info", the target RNC should choose the IE "DL DCCH message" and include the DL DCCH message that should be transmitted transparently to the UE by the source RNC. In that case, the target RNC is integrity protecting the message if applicable.

If the target RNC did not receive the IE "RB Id for handover message" in the IE "SRNS Relocation Info" the target RNC should use another choice. In that case, the source RNC should integrity protect the message before transmitting it to the UE if applicable.

If the source RNC received the IE "UE specific behaviour info" from the UE, it should include this IE in the SRNS RELOCATION INFO message.

The source RNC ~~then~~ transmits the Handover Message to the UE, which then performs the handover.

In the successful case, the UE transmits an XXX COMPLETE message, using the new configuration, to the target RNC.

In case of failure, the UE transmits an XXX FAILURE, using the old configuration, to the source RNC and the RRC context remains unchanged (has to be confirmed and checked with the SRNS relocation procedure).

Information Element/Group name	Need	Multi	Type and reference	Semantics description
CHOICE RRC message	MP			At least one spare choice, Criticality: Reject, is needed
>RADIO BEARER SETUP			RADIO BEARER SETUP 10.2.31	
>RADIO BEARER RECONFIGURATION			RADIO BEARER RECONFIGURATION 10.2.25	
>RADIO BEARER RELEASE			RADIO BEARER RELEASE 10.2.28	
>TRANSPORT CHANNEL RECONFIGURATION			TRANSPORT CHANNEL RECONFIGURATION 10.2.51	
>PHYSICAL CHANNEL RECONFIGURATION			PHYSICAL CHANNEL RECONFIGURATION	

Information Element/Group name	Need	Multi	Type and reference	Semantics description
			10.2.20	
>RRC FAILURE INFO			RRC FAILURE INFO 10.2.41 a	
>DL DCCH message			OCTET STRING	

## CHANGE REQUEST

⌘ 25.331 CR 1790 ⌘ rev 1 ⌘ Current version: 5.2.0 ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

**Proposed change affects:** UICC apps ⌘ ME  Radio Access Network  Core Network ⌘

<b>Title:</b>	⌘ Compact IMEI-SV transfer across Uu and within RRC containers	
<b>Source:</b>	⌘ Ericsson	
<b>Work item code:</b>	⌘ TEI	<b>Date:</b> ⌘ 13/11/2002
<b>Category:</b>	⌘ <b>B</b> <i>Use one of the following categories:</i> <b>F</b> (correction) <b>A</b> (corresponds to a correction in an earlier release) <b>B</b> (addition of feature), <b>C</b> (functional modification of feature) <b>D</b> (editorial modification)	<b>Release:</b> ⌘ REL-5 <i>Use one of the following releases:</i> 2 (GSM Phase 2) R96 (Release 1996) R97 (Release 1997) R98 (Release 1998) R99 (Release 1999) Rel-4 (Release 4) Rel-5 (Release 5) Rel-6 (Release 6)
<i>Detailed explanations of the above categories can be found in 3GPP TR 21.900.</i>		

<b>Reason for change:</b>	⌘ The changes included in this CR are proposed for the following reasons:
<ul style="list-style-type: none"> <li>RP has tasked R2 to agree on a solution for the handling of early UEs, which is currently not sufficiently covered in R99. The proposal is to introduce an IE indicating the version of a UE implementation. This indication may be used by the network to avoid invoking functionality towards UEs for which interoperability problems are experienced/ foreseen.</li> </ul>	

<b>Summary of change:</b>	⌘ This CR introduces the following changes:
<ul style="list-style-type: none"> <li>A new IE “UE specific behaviour info” is defined. It is added to the following messages:           <ul style="list-style-type: none"> <li>RRC CONNECTION REQUEST message (MP)</li> <li>INTER RAT HANDOVER INFO message (MP) and the INTER RAT HANDOVER INFO WITH INTER RAT CAPABILITIES (implicitly, since it includes INTER RAT HANDOVER INFO message)</li> <li>UE CAPABILITY INFORMATION message (OP)</li> <li>SRNS RELOCATION INFO message (MP)</li> </ul> </li> <li>The “UE specific behaviour info” IE includes the decimal to binary conversion of the first 6 bits of the TAC concatenated with the SVN fields of the IMEI-SV</li> </ul>	
<b>Consequences if not approved:</b>	⌘ In case there are interoperability problems with early UE implementations, networks have no other choice but to either experience these problems or to refrain from using functionality with interoperability problems towards all early UEs

**Clauses affected:** ⌘ 8.1.16.3, 8.6.3.12, 10.2.39, 10.3.3.42, 10.3.3.45a (new), 11.2, 11.3, 11.5, 14.12.2

<b>Other specs affected:</b>	<table border="1" style="display: inline-table; vertical-align: middle;"> <tr><td>Y</td><td>N</td></tr> <tr><td>X</td><td>Other core specifications</td></tr> <tr><td>X</td><td>Test specifications</td></tr> <tr><td>X</td><td>O&amp;M Specifications</td></tr> </table> <span style="display: inline-block; vertical-align: middle;">⌘ Other core specifications ⌘</span> <span style="display: inline-block; background-color: #ffffcc; width: 150px; height: 20px; vertical-align: middle;"></span>	Y	N	X	Other core specifications	X	Test specifications	X	O&M Specifications
Y	N								
X	Other core specifications								
X	Test specifications								
X	O&M Specifications								
<b>Other comments:</b>	⌘ This is a complete proposal that does not require changes on other interfaces								

**How to create CRs using this form:**

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>. Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

### 8.1.16.3 INTER RAT HANDOVER INFO message contents to set

The UE shall:

- 1> include the IE "Predefined configuration status information" and the IE "UE security information";
- 1> include the IE "UE capability container", containing the IE "UE radio access capability" and the IE "UE radio access capability extension", in accordance with the following:
  - 2> if the UE supports multiple UTRA FDD Frequency Bands; or
  - 2> if the UE supports a single UTRA FDD Frequency Band different from 2100 MHz:
    - 3> include the IE "UE radio access capability", excluding IEs "RF capability FDD" and "Measurement capability";
    - 3> include the IE "UE radio access capability extension", including the IEs "RF capability FDD extension" and the "Measurement capability extension" associated with each supported UTRA FDD frequency band indicated in the IE "Frequency band".
  - 2> else:
    - 3> include the IE "UE radio access capability", including the IEs "RF capability FDD" and "Measurement capability" associated with the 2100 MHz UTRA FDD frequency band;
    - 3> include the IE "UE radio access capability extension", including the IEs "RF capability FDD extension" and the "Measurement capability extension" associated with each supported UTRA FDD frequency band indicated in the IE "Frequency band".
- 2> include its UE specific behaviour information in the IE "UE specific behaviour info" in the variable UE\_CAPABILITY\_REQUESTED.
  - 1> initiate the transfer of the INTER RAT HANDOVER INFO message via the other radio access technology, using radio access technology-specific procedures;
  - 1> store the IE "Predefined configuration status information", the IE "UE security information", the IE "UE radio access capability" and the IE "UE radio access capability extension", if included in the INTER RAT HANDOVER MESSAGE, in variable INTER\_RAT\_HANDOVER\_INFO\_TRANSFERRED;
  - 1> and the procedure ends.

### 8.6.3.12 Capability Update Requirement

If the IE "Capability Update Requirement" is included the UE shall:

- 1> if the IE "UE radio access FDD capability update requirement" has the value TRUE:
  - 2> if the UE supports FDD mode:
    - 3> store its UTRA FDD capabilities and its UTRA capabilities common to FDD and TDD in the IE "UE radio access capability" and the IE "UE radio access capability extension" in variable UE\_CAPABILITY\_REQUESTED as specified below:
      - 4> if the UE supports multiple UTRA FDD Frequency Bands; or
      - 4> if the UE supports a single UTRA FDD Frequency Band different from 2100 MHz:
        - 5> store the IE "UE radio access capability", excluding IEs "RF capability FDD" and "Measurement capability";
        - 5> store the IE "UE radio access capability extension", including the IEs "RF capability FDD extension" and the "Measurement capability extension" associated with each supported UTRA FDD frequency band indicated in the IE "Frequency band".
      - 4> else:
        - 5> store the IE "UE radio access capability", including the IEs "RF capability FDD" and "Measurement capability" associated with the 2100 MHz UTRA FDD frequency band.
    - 3> include its UE specific behaviour information in the IE "UE specific behaviour info" in the variable UE\_CAPABILITY\_REQUESTED.
  - 1> if the IE "UE radio access 3.84 Mcps TDD capability update requirement" has the value TRUE:
    - 2> if the UE supports 3.84 Mcps TDD mode:
      - 3> store its UTRAN-specific 3.84 Mcps TDD capabilities and its UTRAN-specific capabilities common to FDD and TDD in the variable UE\_CAPABILITY\_REQUESTED.
      - 3> include its UE specific behaviour information in the IE "UE specific behaviour info" in the variable UE\_CAPABILITY\_REQUESTED.
    - 1> if the IE "UE radio access 1.28 Mcps TDD capability update requirement" has the value TRUE:
      - 2> if the UE supports 1.28 Mcps TDD mode:
        - 3> store its UTRAN-specific 1.28 Mcps TDD capabilities and its UTRAN-specific capabilities common to FDD and TDD in the variable UE\_CAPABILITY\_REQUESTED.
        - 3> include its UE specific behaviour information in the IE "UE specific behaviour info" in the variable UE\_CAPABILITY\_REQUESTED.
      - 1> if the IE "System specific capability update requirement list" is present:
        - 2> for each of the RAT requested in the IE "UE system specific capability"
          - 3> if the UE supports the listed RAT:
            - 4> include its inter-RAT radio access capabilities for the listed RAT in the IE "UE system specific capability" from the variable UE\_CAPABILITY\_REQUESTED.

If the IE " Capability update requirement " is not present, the UE shall:

- 1> assume the default values as specified in subclause 10.3.3.2 and act in accordance with the above.

### 10.2.39 RRC CONNECTION REQUEST

RRC Connection Request is the first message transmitted by the UE when setting up an RRC Connection to the network.

RLC-SAP: TM

Logical channel: CCCH

Direction: UE → UTRAN

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
Message Type	MP		Message Type		
<b>UE information elements</b>					
Initial UE identity	MP		Initial UE identity 10.3.3.15		
Establishment cause	MP		Establishment cause 10.3.3.11		
Protocol error indicator	MD		Protocol error indicator 10.3.3.27	Default value is FALSE	
<b>Measurement information elements</b>					
Measured results on RACH	OP		Measured results on RACH 10.3.7.45		
Access stratum release indicator	MP		Enumerated( REL-4)	Absence of the IE implies R99. The IE also indicates the release of the RRC transfer syntax supported by the UE 15 spare values are needed	REL-4
<u>UE specific behaviour info</u>	MP		<u>UE specific behaviour info</u> 10.3.3.45a		

If the encoded message does not fill a transport block, the RRC layer shall insert padding according to subclause 12.1.

## 10.3.3.42 UE radio access capability

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
Access stratum release indicator	MP		Enumerated( R99)	Indicates the release of the UE according to [35]. The IE also indicates the release of the RRC transfer syntax supported by the UE..	
	CV- <i>not_rrc_connectionSetupComplete</i>		Enumerated( REL-4)	15 spare values are needed.	REL-4
<u>UE specific behaviour info</u>	<u>CH- <i>rrcConnectionSetupComplete</i></u>		<u>UE specific behaviour info</u> 10.3.3.45a		
DL capability with simultaneous HS-DSCH configuration	OP		Enumerated( 32kbps, 64kbps, 128kbps, 384kbps)		REL-5
PDCP capability	MP		PDCP capability 10.3.3.24		
RLC capability	MP		RLC capability 10.3.3.34		
Transport channel capability	MP		Transport channel capability 10.3.3.40		
RF capability FDD	OP		RF capability FDD 10.3.3.33		
RF capability TDD	OP		RF capability TDD 10.3.3.33b	One "TDD RF capability" entity shall be included for every Chip rate capability supported.	
		1 to 2			REL-4
Physical channel capability	MP		Physical channel capability 10.3.3.25		
UE multi-mode/multi-RAT capability	MP		UE multi-mode/multi-RAT capability 10.3.3.41		
Security capability	MP		Security capability 10.3.3.37		
UE positioning capability	MP		UE positioning capability 10.3.3.45		
Measurement capability	CH- <i>fdd_req_sup</i>		Measuremen t capability 10.3.3.21		

Condition	Explanation
<i>fdd_req_sup</i>	The IE is mandatory present if the IE "Multi-mode capability" has the value "FDD" or "FDD/TDD" and a FDD capability update has been requested in a previous message. Otherwise this field is not needed in the message.
<i>not_rrc_connectionSetupComplete</i>	The IE is not needed in the RRC CONNECTION SETUP COMPLETE message. Otherwise the IE is mandatory present.
<i>rrcConnectionSetupComplete</i>	The IE is not needed in the RRC CONNECTION SETUP COMPLETE message. The IE is optional in the UE CAPABILITY INFORMATION and the SRNS RELOCATION INFO message. Otherwise the IE is mandatory present.

### 10.3.3.45a UE specific behaviour info

<u>Information Element/Group name</u>	<u>Need</u>	<u>Multi</u>	<u>Type and reference</u>	<u>Semantics description</u>
IMEI-SV	MP		Bitstring (32)	A compact version of the IMEI-SV [see 23.003] comprising of the decimal to binary conversion of the concatenation of the TAC and the SVN digits. The bits of the result are numbered from b0 to b31, with bit b0 being the least significant.

## 11.2 PDU definitions

```
--*****
-- TABULAR: The message type and integrity check info are not
-- visible in this module as they are defined in the class module.
-- Also, all FDD/TDD specific choices have the FDD option first
-- and TDD second, just for consistency.
--*****
PDU-definitions DEFINITIONS AUTOMATIC TAGS ::=

BEGIN

--*****
-- IE parameter types from other modules
--*****
IMPORTS

-- Core Network IEs :
CN-DomainIdentity,
CN-InformationInfo,
CN-InformationInfoFull,
NAS-Message,
PagingRecordTypeID,
-- UTRAN Mobility IEs :
CellIdentity,
CellIdentity-PerRL-List,
URA-Identity,
-- User Equipment IEs :
ActivationTime,
C-RNTI,
CapabilityUpdateRequirement,
CapabilityUpdateRequirement-r4,
CapabilityUpdateRequirement-r4-ext,
CellUpdateCause,
CipheringAlgorithm,
CipheringModeInfo,
DSCH-RNTI,
EstablishmentCause,
FailureCauseWithProtErr,
FailureCauseWithProtErrTrId,
H-RNTI,
InitialUE-Identity,
IntegrityProtActivationInfo,
IntegrityProtectionModeInfo,
N-308,
PagingCause,
PagingRecordList,
ProtocolErrorIndicator,
ProtocolErrorIndicatorWithMoreInfo,
Rb-timer-indicator,
RedirectionInfo,
RejectionCause,
ReleaseCause,
RRC-StateIndicator,
RRC-TransactionIdentifier,
SecurityCapability,
START-Value,
STARTList,
U-RNTI,
U-RNTI-Short,
UE-RadioAccessCapability,
UE-RadioAccessCapability-r4-ext,
UE-RadioAccessCapability-r5-ext,
UE-RadioAccessCapability-v370ext,
UE-RadioAccessCapability-v380ext,
UE-RadioAccessCapability-v3a0ext,
UE-RadioAccessCapability-v4xyext,
DL-PhysChCapabilityFDD-v380ext,
UE-ConnTimersAndConstants,
UE-ConnTimersAndConstants-v3a0ext,
```

```

UE-ConnTimersAndConstants-r5,
UE-SecurityInformation,
URA-UpdateCause,
UE-SpecificBehaviourInfo,
UTRAN-DRX-CycleLengthCoefficient,
WaitTime,
-- Radio Bearer IEs :
DefaultConfigIdentity,
DefaultConfigIdentity-r4,
DefaultConfigMode,
DL-CounterSynchronisationInfo,
DL-CounterSynchronisationInfo-r5,
PredefinedConfigIdentity,
PredefinedConfigStatusList,
RAB-Info,
RAB-Info-Post,
RAB-InformationList,
RAB-InformationReconfigList,
RAB-InformationSetupList,
RAB-InformationSetupList-r4,
RB-ActivationTimeInfoList,
RB-COUNT-C-InformationList,
RB-COUNT-C-MSB-InformationList,
RB-IdentityList,
RB-InformationAffectedList,
RB-InformationAffectedList-r5,
RB-InformationReconfigList,
RB-InformationReconfigList-r4,
RB-InformationReconfigList-r5,
RB-InformationReleaseList,
RB-PDCPContextRelocationList,
SRB-InformationSetupList,
SRB-InformationSetupList2,
UL-CounterSynchronisationInfo,
-- Transport Channel IEs:
CPCH-SetID,
DL-AddReconfTransChInfo2List,
DL-AddReconfTransChInfoList,
DL-AddReconfTransChInfoList-r4,
DL-AddReconfTransChInfoList-r5,
DL-CommonTransChInfo,
DL-CommonTransChInfo-r4,
DL-DeletedTransChInfoList,
DL-DeletedTransChInfoList-r5,
DRAC-StaticInformationList,
TFC-Subset,
TFCS-Identity,
UL-AddReconfTransChInfoList,
UL-CommonTransChInfo,
UL-CommonTransChInfo-r4,
UL-DeletedTransChInfoList,
-- Physical Channel IEs :
Alpha,
CCTrCH-PowerControlInfo,
CCTrCH-PowerControlInfo-r4,
ConstantValue,
ConstantValueTdd,
CPCH-SetInfo,
DL-CommonInformation,
DL-CommonInformation-r4,
DL-CommonInformationPost,
DL-HSPDSCH-Information,
DL-InformationPerRL,
DL-InformationPerRL-List,
DL-InformationPerRL-List-r4,
DL-InformationPerRL-List-r5,
DL-InformationPerRL-ListPostFDD,
DL-InformationPerRL-PostTDD,
DL-InformationPerRL-PostTDD-LCR-r4,
DL-PDSCH-Information,
DPCH-CompressedModeStatusInfo,
FrequencyInfo,
FrequencyInfoFDD,
FrequencyInfoTDD,
MaxAllowedUL-TX-Power,
OpenLoopPowerControl-IPDL-TDD-r4,
PDSCH-CapacityAllocationInfo,
PDSCH-CapacityAllocationInfo-r4,

```

```

PDSCH-Identity,
PrimaryCCPCH-TX-Power,
PUSCH-CapacityAllocationInfo,
PUSCH-CapacityAllocationInfo-r4,
PUSCH-Identity,
RL-AdditionInformationList,
RL-RemovalInformationList,
SpecialBurstScheduling,
SSDT-Information,
TFC-ControlDuration,
SSDT-UL-r4,
TimeslotList,
TimeslotList-r4,
TX-DiversityMode,
UL-ChannelRequirement,
UL-ChannelRequirement-r4,
UL-ChannelRequirement-r5,
UL-ChannelRequirementWithCPCH-SetID,
UL-ChannelRequirementWithCPCH-SetID-r4,
UL-ChannelRequirementWithCPCH-SetID-r5,
UL-DPCH-Info,
UL-DPCH-Info-r4,
UL-DPCH-InfoPostFDD,
UL-DPCH-InfoPostTDD,
UL-DPCH-InfoPostTDD-LCR-r4,
UL-SynchronisationParameters-r4,
UL-TimingAdvance,
UL-TimingAdvanceControl,
UL-TimingAdvanceControl-r4,
-- Measurement IEs :
AdditionalMeasurementID-List,
Frequency-Band,
EventResults,
InterFreqEventResults-LCR-r4-ext,
InterRAT-TargetCellDescription,
MeasuredResults,
MeasuredResults-v390ext,
MeasuredResultsList,
MeasuredResultsList-LCR-r4-ext,
MeasuredResultsOnRACH,
MeasurementCommand,
MeasurementCommand-r4,
MeasurementIdentity,
MeasurementReportingMode,
PrimaryCCPCH-RSCP,
SFN-Offset-Validity,
TimeslotListWithISCP,
TrafficVolumeMeasuredResultsList,
UE-Positioning-GPS-AssistanceData,
UE-Positioning-Measurement-v390ext,
UE-Positioning-OTDOA-AssistanceData,
UE-Positioning-OTDOA-AssistanceData-r4ext,
UE-Positioning-OTDOA-AssistanceData-UEB,
UE-Positioning-IPDL-Parameters-TDD-r4-ext,
-- Other IEs :
BCCH-ModificationInfo,
CDMA2000-MessageList,
GSM-MessageList,
InterRAT-ChangeFailureCause,
InterRAT-HO-FailureCause,
InterRAT-UE-RadioAccessCapabilityList,
InterRAT-UE-SecurityCapList,
IntraDomainNasNodeSelector,
ProtocolErrorMoreInformation,
Rplmn-Information,
Rplmn-Information-r4,
SegCount,
SegmentIndex,
SFN-Prime,
SIB-Data-fixed,
SIB-Data-variable,
SIB-Type
FROM InformationElements

    maxSIBperMsg
FROM Constant-definitions;

<Cut until the next modified section>

```

```

-- ****
-- INTER RAT HANDOVER INFO
-- ****

InterRATHandoverInfo ::= SEQUENCE {
    -- This structure is defined for historical reasons, backward compatibility with 04.18
    predefinedConfigStatusList      CHOICE {
        absent                  NULL,
        present                 PredefinedConfigStatusList
    },
    uE-SecurityInformation         CHOICE {
        absent                  NULL,
        present                UE-SecurityInformation
    },
    ue-CapabilityContainer         CHOICE {
        absent                  NULL,
        -- present is an octet aligned string containing IE UE-RadioAccessCapabilityInfo
        present                OCTET STRING (SIZE (0..63))
    },
    -- Non critical extensions
    v390NonCriticalExtensions     CHOICE {
        absent                  NULL,
        present                SEQUENCE {
            interRATHandoverInfo-v390ext   InterRATHandoverInfo-v390ext-IEs,
            v3a0NonCriticalExtensions   SEQUENCE {
                interRATHandoverInfo-v3a0ext   InterRATHandoverInfo-v3a0ext,
                v3d0NonCriticalExtensions   SEQUENCE {
                    interRATHandoverInfo-v3d0ext   InterRATHandoverInfo-v3d0ext-IEs,
                    v4xyNonCriticalExtensions   SEQUENCE {
                        interRATHandoverInfo-v4xyext   InterRATHandoverInfo-v4xyext-IEs,
                        -- Reserved for future non critical extension
                        nonCriticalExtensions       SEQUENCE {} OPTIONAL
                    } OPTIONAL
                } OPTIONAL
            } OPTIONAL
        } OPTIONAL
    }
}

InterRATHandoverInfo-v390ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v380ext     UE-RadioAccessCapability-v380ext           OPTIONAL,
    dl-PhysChCapabilityFDD-v380ext      DL-PhysChCapabilityFDD-v380ext
}

InterRATHandoverInfo-v3a0ext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v3a0ext     UE-RadioAccessCapability-v3a0ext           OPTIONAL
}

InterRATHandoverInfo-v3b0ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v3d0ext     UE-SpecificBehaviourInfo
}

InterRATHandoverInfo-v4xyext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v4xyext    UE-RadioAccessCapability-v4xyext
}

<Cut until the next modified section>

-- ****
-- RRC CONNECTION REQUEST
-- ****

RRConnectionRequest ::= SEQUENCE {
    -- TABULAR: Integrity protection shall not be performed on this message.
    -- User equipment IEs
    initialUE-Identity              InitialUE-Identity,
    establishmentCause               EstablishmentCause,
    -- protocolErrorIndictator is MD, but for compactness reasons no default value
    -- has been assigned to it.
}

```

```

    protocolErrorIndicator          ProtocolErrorIndicator,
-- Measurement IEs
    measuredResultsOnRACH         MeasuredResultsOnRACH           OPTIONAL,
    v3d0NonCriticalExtensions     SEQUENCE {
        RRCConnectionRequest-v3d0ext   RRCConnectionRequest-v3d0ext-IEs,
    }
    v4xyNonCriticalExtensions     SEQUENCE {
        rrcConnectionRequest-v4xyext   RRCConnectionRequest-v4xyext-IEs,
    }
    -- Reserved for future non critical extension
    nonCriticalExtensions        SEQUENCE {}      OPTIONAL
}
} OPTIONAL
}

RRCConnectionRequest-v4xyext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v4xyext   UE-RadioAccessCapability-v4xyext
}

<Cut until the next modified section>

-- ****
-- UE CAPABILITY INFORMATION
-- ****

UECapabilityInformation ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier       RRC-TransactionIdentifier           OPTIONAL,
    ue-RadioAccessCapability        UE-RadioAccessCapability           OPTIONAL,
    -- Other IEs
    ue-RATSpecificCapability       InterRAT-UE-RadioAccessCapabilityList
OPTIONAL,
    v370NonCriticalExtensions      SEQUENCE {
        ueCapabilityInformation-v370ext UECapabilityInformation-v370ext,
    }
    v380NonCriticalExtensions      SEQUENCE {
        ueCapabilityInformation-v380ext UECapabilityInformation-v380ext-IEs,
        v3a0NonCriticalExtensions    SEQUENCE {
            ueCapabilityInformation-v3a0ext   UECapabilityInformation-v3a0ext,
        }
        -- Reserved for future non critical extension
    }
    v3d0NonCriticalExtensions      SEQUENCE {
        ueCapabilityInformation-v3d0ext UECapabilityInformation-v3d0ext-IEs,
    }
    -- Reserved for future non critical extension
    v4xyNonCriticalExtensions     SEQUENCE {
        ueCapabilityInformation-v4xyext   UECapabilityInformation-v4xyext,
    }
    v5xyNonCriticalExtensions     SEQUENCE {
        ueCapabilityInformation-v5xyext   UECapabilityInformation-v5xyext,
    }
    nonCriticalExtensions         SEQUENCE {}      OPTIONAL
}
} OPTIONAL
}
} OPTIONAL
}
} OPTIONAL
}

UECapabilityInformation-v370ext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v370ext   UE-RadioAccessCapability-v370ext           OPTIONAL
}

UECapabilityInformation-v380ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v380ext   UE-RadioAccessCapability-v380ext
OPTIONAL,
    dl-PhysChCapabilityFDD-v380ext   DL-PhysChCapabilityFDD-v380ext
}

UECapabilityInformation-v3a0ext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v3a0ext   UE-RadioAccessCapability-v3a0ext           OPTIONAL
}

UECapabilityInformation-v3d0ext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v3d0ext   UE-SpecificBehaviourInfo           OPTIONAL
}

```

```
UECapabilityInformation-v4xyext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-r4-ext      UE-RadioAccessCapability-r4-ext      OPTIONAL,
    ue-RadioAccessCapability-v4xyext      UE-RadioAccessCapability-v4xyext
}

UECapabilityInformation-v5xyext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-r5-ext      UE-RadioAccessCapability-r5-ext      OPTIONAL
}
```

## 11.3 Information element definitions

```
InformationElements DEFINITIONS AUTOMATIC TAGS ::=

<Cut until the next modified section>

-- ****
-- USER EQUIPMENT INFORMATION ELEMENTS (10.3.3)
-- ****

<Cut until the next modified section>

| UE-SpecificBehaviourInfo ::= SEQUENCE {
|   imei-sv-compact           BIT STRING (SIZE (32))
| }
```

## 11.5 RRC information between network nodes

Internode-definitions DEFINITIONS AUTOMATIC TAGS ::=

BEGIN

IMPORTS

```

HandoverToUTRANCommand,
MeasurementReport,
PhysicalChannelReconfiguration,
RadioBearerReconfiguration,
RadioBearerRelease,
RadioBearerSetup,
RRC-FailureInfo-r3-IEs,
TransportChannelReconfiguration
FROM PDU-definitions

-- Core Network IE-s :
CN-DomainIdentity,
CN-DomainInformationList,
CN-DomainInformationListFull,
CN-DRX-CycleLengthCoefficient,
NAS-SystemInformationGSM-MAP,
-- UTRAN Mobility IE-s :
CellIdentity,
URA-Identity,
-- User Equipment IE-s :
AccessStratumReleaseIndicator,
C-RNTI,
ChipRateCapability,
DL-PhysChCapabilityFDD-v380ext,
DL-PhysChCapabilityTDD,
DL-PhysChCapabilityTDD-LCR-r4,
GSM-Measurements,
FailureCauseWithProtErr,
MaxHcContextSpace,
MaxNoPhysChBitsReceived,
MaxROHC-ContextSessions-r4,
NetworkAssistedGPS-Supported,
RadioFrequencyBandTDDList,
RLC-Capability,
RRC-MessageSequenceNumber,
SecurityCapability,
SimultaneousSCCPCH-DPCH-Reception,
STARTList,
STARTSingle,
START-Value,
SupportOfDedicatedPilotsForChEstimation,
TransportChannelCapability,
TxRxFrequencySeparation,
U-RNTI,
UE-MultiModeRAT-Capability,
UE-PowerClass-v370,
UE-RadioAccessCapabBandFDDList,
UE-RadioAccessCapability,
UE-RadioAccessCapability-v370ext,
UE-RadioAccessCapability-v380ext,
UE-RadioAccessCapability-v3a0ext,
UE-RadioAccessCapability-v4xyext,
UE-SpecificBehaviourInfo,
UL-PhysChCapabilityFDD,
UL-PhysChCapabilityTDD,
UL-PhysChCapabilityTDD-LCR-r4,
-- Radio Bearer IE-s :
PredefinedConfigStatusList,
PredefinedConfigValueTag,
RAB-InformationSetupList,
RAB-InformationSetupList-r4,
RAB-Identity,
RB-Identity,
RB-Identity,
SRB-InformationSetupList,
-- Transport Channel IE-s :
CPCH-SetID,
DL-CommonTransChInfo,

```

```

DL-CommonTransChInfo-r4,
DL-AddReconfTransChInfoList,
DL-AddReconfTransChInfoList-r4,
DRAC-StaticInformationList,
UL-CommonTransChInfo,
UL-CommonTransChInfo-r4,
UL-AddReconfTransChInfoList,
-- Measurement IEs :
MeasurementIdentity,
MeasurementReportingMode,
MeasurementType,
MeasurementType-r4,
AdditionalMeasurementID-List,
PositionEstimate,
UE-Positioning-IPDL-Parameters-TDD-r4-ext,
-- Other IEs :
InterRAT-UE-RadioAccessCapabilityList
FROM InformationElements

maxCNdomains,
maxNoOfMeas,

maxRB,
maxRBallRABs,
maxRFC3095-CID,
maxSRBsetup
FROM Constant-definitions
;

<Cut until the next modified section>

-- Part2: Container definitions, similar to the PDU definitions in 11.2 for RRC messages
-- In alphabetical order

-- ****
-- Handover to UTRAN information
-- ****

InterRATHandoverInfoWithInterRATCapabilities-r3 ::= CHOICE {
    r3           SEQUENCE {
        -- IE InterRATHandoverInfoWithInterRATCapabilities-r3-IEs also
        -- includes non critical extensions
        interRATHandoverInfo-r3      InterRATHandoverInfoWithInterRATCapabilities-r3-IEs,
        v390NonCriticalExtensions   SEQUENCE {
            interRATHandoverInfoWithInterRATCapabilities-v390ext
        InterRATHandoverInfoWithInterRATCapabilities-v390ext-IEs,
            -- Reserved for future non critical extension
            nonCriticalExtensions     SEQUENCE {} OPTIONAL
        }                           OPTIONAL
    },
    criticalExtensions       SEQUENCE {}
}

InterRATHandoverInfoWithInterRATCapabilities-r3-IEs ::= SEQUENCE {
    -- The order of the IEs may not reflect the tabular format
    -- but has been chosen to simplify the handling of the information in the BSC
    -- Other IEs
    ue-RATSpecificCapability     InterRAT-UE-RadioAccessCapabilityList   OPTIONAL,
    -- interRATHandoverInfo, Octet string is used to obtain 8 bit length field prior to
    -- actual information. This makes it possible for BSS to transparently handle information
    -- received via GSM air interface even when it includes non critical extensions.
    -- The octet string shall include the InterRATHandoverInfo information
    -- The BSS can re-use the 04.18 length field received from the MS
    interRATHandoverInfo         OCTET STRING (SIZE (0..255))
}

InterRATHandoverInfoWithInterRATCapabilities-v390ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    failureCauseWithProtErr      FailureCauseWithProtErr                OPTIONAL
}
-- ****
-- RFC3095 context, source RNC to target RNC

```

```

-- ****
RFC3095-ContextInfo-r5 ::= CHOICE {
  r5           SEQUENCE {
    RFC3095-ContextInfoList-r5      RFC3095-ContextInfoList-r5,
    -- Reserved for future non critical extension
    nonCriticalExtensions          SEQUENCE {} OPTIONAL
  },
  criticalExtensions             SEQUENCE {}
}

RFC3095-ContextInfoList-r5 ::= SEQUENCE (SIZE (1..maxRBallRABs)) OF
                                RFC3095-ContextInfo

-- ****
-- SRNC Relocation information
-- ****

SRNC-RelocationInfo-r3 ::= CHOICE {
  r3           SEQUENCE {
    sRNC-RelocationInfo-r3          SRNC-RelocationInfo-r3-IEs,
    v380NonCriticalExtensions      SEQUENCE {
      sRNC-RelocationInfo-v380ext   SRNC-RelocationInfo-v380ext-IEs,
      -- Reserved for future non critical extension
      v390NonCriticalExtensions    SEQUENCE {
        sRNC-RelocationInfo-v390ext   SRNC-RelocationInfo-v390ext-IEs,
        v3a0NonCriticalExtensions    SEQUENCE {
          sRNC-RelocationInfo-v3a0ext   SRNC-RelocationInfo-v3a0ext-IEs,
          v3b0NonCriticalExtensions    SEQUENCE {
            sRNC-RelocationInfo-v3b0ext   SRNC-RelocationInfo-v3b0ext-IEs,
            v3c0NonCriticalExtensions    SEQUENCE {
              sRNC-RelocationInfo-v3c0ext   SRNC-RelocationInfo-v3c0ext-IEs,
              v3d0NonCriticalExtensions    SEQUENCE {
                sRNC-RelocationInfo-v3d0ext   SRNC-RelocationInfo-v3d0ext-
                IEs,
                v4xyNonCriticalExtensions    SEQUENCE {
                  sRNC-RelocationInfo-v4xyext   SRNC-RelocationInfo-
                  v4xyext-IEs,
                  -- Reserved for future non critical extension
                  nonCriticalExtensions        SEQUENCE {} OPTIONAL
                }
                OPTIONAL
              }
              OPTIONAL
            }
            OPTIONAL
          }
          OPTIONAL
        }
        OPTIONAL
      }
      OPTIONAL
    }
    later-than-r3             CHOICE {
      r4           SEQUENCE {
        sRNC-RelocationInfo-r4          SRNC-RelocationInfo-r4-IEs,
        nonCriticalExtensions          SEQUENCE {} OPTIONAL
      },
      criticalExtensions            SEQUENCE {}
    }
}

SRNC-RelocationInfo-r3-IEs ::= SEQUENCE {
  -- Non-RRC IEs
  stateOfRRC                  StateOfRRC,
  stateOfRRC-Procedure          StateOfRRC-Procedure,
  -- Ciphering related information IE
  -- If the extension v380 is included use the extension for the ciphering status per CN domain
  cipheringStatus               CipheringStatus,
  calculationTimeForCiphering   CalculationTimeForCiphering   OPTIONAL,
  -- The order of occurrence in the IE cipheringInfoPerRB-List is the
  -- same as the RBs in the IE "Signalling RB information list" and in the
  -- IE "RAB information list". The signalling RBs are supposed to be listed
  -- first. Only UM and AM RBs that are ciphered are listed here
  cipheringInfoPerRB-List       CipheringInfoPerRB-List      OPTIONAL,
  count-C-List                 COUNT-C-List                 OPTIONAL,
  integrityProtectionStatus     IntegrityProtectionStatus,
  srb-SpecificIntegrityProtInfo SRB-SpecificIntegrityProtInfoList,
  implementationSpecificParams ImplementationSpecificParams   OPTIONAL,
}

```

```

-- User equipment IEs
    u-RNTI
    c-RNTI
    ue-RadioAccessCapability
    ue-Positioning-LastKnownPos
-- Other IEs
    ue-RATSpecificCapability
-- UTRAN mobility IEs
    ura-Identity
-- Core network IEs
    cn-CommonGSM-MAP-NAS-SysInfo
    cn-DomainInformationList
-- Measurement IEs
    ongoingMeasRepList
-- Radio bearer IEs
    predefinedConfigStatusList
    srb-InformationList
    rab-InformationList
-- Transport channel IEs
    ul-CommonTransChInfo
    ul-TransChInfoList
    modeSpecificInfo
        fdd
            cpch-SetID
            transChDRAC-Info
        },
        tdd
            NULL
    },
    dl-CommonTransChInfo
    dl-TransChInfoList
-- Measurement report
    measurementReport
    nonCriticalExtensions
        -- In case of TDD only up-Ipd1-Parameters-TDD is present, otherwise
        -- this IE is absent
        up-Ipd1-Parameters-TDD
        -- Extension mechanism for non- release4 information
        nonCriticalExtensions
            SEQUENCE {}
}                                     OPTIONAL,
}                                     OPTIONAL

SRNC-RelocationInfo-v380ext-IEs ::= SEQUENCE {
    -- Ciphering related information IEs
    cn-DomainIdentity
    cipheringStatusList
}

SRNC-RelocationInfo-v390ext-IEs ::= SEQUENCE {
    cn-DomainInformationList-v390ext
    ue-RadioAccessCapability-v370ext
    ue-RadioAccessCapability-v380ext
    dl-PhysChCapabilityFDD-v380ext
    failureCauseWithProtErr
}

SRNC-RelocationInfo-v3a0ext-IEs ::= SEQUENCE {
    -- cn-domain identity for IE startValueForCiphering-v3a0ext is specified
    -- in subsequent extension (SRNC-RelocationInfo-v3b0ext-IEs)
    startValueForCiphering-v3a0ext
    cipheringInfoForSRB1-v3a0ext
    ue-RadioAccessCapability-v3a0ext
}

SRNC-RelocationInfo-v3b0ext-IEs ::= SEQUENCE {
    -- cn-domain identity for IE startValueForCiphering-v3a0ext included in previous extension
    cn-DomainIdentity
    -- the remaining start values are contained in IE startValueForCiphering-v3b0ext
    startValueForCiphering-v3b0ext
}

SRNC-RelocationInfo-v3c0ext-IEs ::= SEQUENCE {
    -- IE rb-IdentityForHOMessage includes the identity of the RB used by the source SRNC
    -- to send the message contained in the IE "TargetRNC-ToSourceRNC-Container".
    -- Only included if type is "UE involved"
    rb-IdentityForHOMessage
}

SRNC-RelocationInfo-v3d0ext-IEs ::= SEQUENCE {
}

```

<code> ue-RadioAccessCapability-v3d0ext  STARTList2 ::= SEQUENCE (SIZE (2..maxCNdomains)) OF  STARTSingle  SRNC-RelocationInfo-v4xyext-IEs ::= SEQUENCE {      ue-RadioAccessCapability-v4xyext    UE-RadioAccessCapability-v4xyext  }  CipheringInfoForSRB1-v3a0ext ::= SEQUENCE {      dl-UM-SN          BIT STRING (SIZE (7))  }  CipheringStatusList ::= SEQUENCE (SIZE (1..maxCNdomains)) OF      CipheringStatusCNdomain  CipheringStatusCNdomain ::= SEQUENCE {      cn-DomainIdentity,      cipheringStatus  }  SRNC-RelocationInfo-r4-IEs ::= SEQUENCE {      -- Non-RRC IEs      -- IE rb-IdentityForHOMessage includes the identity of the RB used by the source SRNC      -- to send the message contained in the IE "TargetRNC-ToSourceRNC-Container".      -- Only included if type is "UE involved"      rb-IdentityForHOMessage      RB-Identity           OPTIONAL,      stateOfRRRC                 StateOfRRRC,      stateOfRRC-Procedure        StateOfRRC-Procedure,      -- Ciphering related information IEs      cipheringStatusList         CipheringStatusList-r4,      latestConfiguredCN-Domain   CN-DomainIdentity,      calculationTimeForCiphering CalculationTimeForCiphering   OPTIONAL,      count-C-List                COUNT-C-List          OPTIONAL,      cipheringInfoPerRB-List     CipheringInfoPerRB-List-r4   OPTIONAL,      -- Integrity protection related information IEs      integrityProtectionStatus  IntegrityProtectionStatus,      srb-SpecificIntegrityProtInfo SRB-SpecificIntegrityProtInfoList,   OPTIONAL,      implementationSpecificParams ImplementationSpecificParams   OPTIONAL,      -- User equipment IEs      u-RNTI                     U-RNTI,      c-RNTI                     C-RNTI           OPTIONAL,      ue-RadioAccessCapability    UE-RadioAccessCapability-r4,      ue-RadioAccessCapability-ext UE-RadioAccessCapabBandFDDList   OPTIONAL,      ue-Positioning-LastKnownPos UE-Positioning-LastKnownPos   OPTIONAL,      -- Other IEs      ue-RATSpecificCapability   InterRAT-UE-RadioAccessCapabilityList   OPTIONAL,      -- UTRAN mobility IEs      ura-Identity               URA-Identity           OPTIONAL,      -- Core network IEs      cn-CommonGSM-MAP-NAS-SysInfo NAS-SystemInformationGSM-MAP,      cn-DomainInformationList   CN-DomainInformationListFull   OPTIONAL,      -- Measurement IEs      ongoingMeasRepList         OngoingMeasRepList-r4           OPTIONAL,      -- Radio bearer IEs      predefinedConfigStatusList PredefinedConfigStatusList,      srb-InformationList        SRB-InformationSetupList,      rab-InformationList        RAB-InformationSetupList-r4   OPTIONAL,      -- Transport channel IEs      ul-CommonTransChInfo       UL-CommonTransChInfo-r4           OPTIONAL,      ul-TransChInfoList         UL-AddReconfTransChInfoList   OPTIONAL,      modeSpecificInfo {          fdd {              cpch-SetID          CPCH-SetID           OPTIONAL,              transChDRAC-Info   DRAC-StaticInformationList   OPTIONAL          },          tdd {              NULL          }      }      dl-CommonTransChInfo       DL-CommonTransChInfo-r4           OPTIONAL,      dl-TransChInfoList         DL-AddReconfTransChInfoList-r4   OPTIONAL,      -- Measurement report      measurementReport          MeasurementReport           OPTIONAL,      failureCause               FailureCauseWithProtErr   OPTIONAL } </code>	<code> UE-SpecificBehaviourInfo  OPTIONAL </code>
---	---

&lt;Cut until the next modified section&gt;

```
UE-RadioAccessCapability-r4 ::= SEQUENCE {
    accessStratumReleaseIndicator,
    ue-SpecificBehaviourInfo OPTIONAL,
    pdcp-Capability,
    rlc-Capability,
    transportChannelCapability,
    rf-Capability,
    physicalChannelCapability,
    ue-MultiModeRAT-Capability,
    securityCapability,
    ue-positioning-Capability,
    measurementCapability
}
```

### 14.12.2 RRC information, target RNC to source RNC

There are 2 possible cases for RNC relocation:

1. The UE is already under control of target RNC; and
2. The SRNC Relocation with Hard Handover (UE still under control of SRNC), but UE is moving to a location controlled by the target RNC (based on measurement information).

In case 1 the relocation is transparent to the UE and there is no "reverse" direction container. The SRNC just assigns the 'serving' function to the target RNC, which then becomes the Serving RNC.

In case 2 the relocation is initiated by SRNC, which also provides the RRC Initialisation Information to the target RNC. Base on this information, the target RNC prepares the Hard Handover Message ("Physical channel reconfiguration" (subclause 8.2.6), "radio bearer establishment" (subclause 8.2.1), "Radio bearer reconfiguration" (subclause 8.2.2), "Radio bearer release" (subclause 8.2.3) or "Transport channel reconfiguration" (subclause 8.2.4)).

In case 2 two possibilities are defined in order to transmit the relocation message from the target RNC to the source RNC which can be chosen by the source RNC by including or not including the IE "RB Id for handover message" in the IE "SRNS Relocation Info".

In case the IE "RB Id for handover message" has been received by the target RNC in the IE "SRNS Relocation Info", the target RNC should choose the IE "DL DCCH message" and include the DL DCCH message that should be transmitted transparently to the UE by the source RNC. In that case, the target RNC is integrity protecting the message if applicable.

If the target RNC did not receive the IE "RB Id for handover message" in the IE "SRNS Relocation Info" the target RNC should use another choice. In that case, the source RNC should integrity protect the message before transmitting it to the UE if applicable.

If the source RNC received the IE "UE specific behaviour info" from the UE, it should include this IE in the SRNS RELOCATION INFO message.

The source RNC ~~then~~ transmits the Handover Message to the UE, which then performs the handover.

In the successful case, the UE transmits an XXX COMPLETE message, using the new configuration, to the target RNC.

In case of failure, the UE transmits an XXX FAILURE, using the old configuration, to the source RNC and the RRC context remains unchanged (has to be confirmed and checked with the SRNS relocation procedure).

Information Element/Group name	Need	Multi	Type and reference	Semantics description
CHOICE RRC message	MP			At least one spare choice, Criticality: Reject, is needed
>RADIO BEARER SETUP			RADIO BEARER SETUP 10.2.31	
>RADIO BEARER RECONFIGURATION			RADIO BEARER RECONFIGURATION 10.2.25	
>RADIO BEARER RELEASE			RADIO BEARER RELEASE 10.2.28	
>TRANSPORT CHANNEL RECONFIGURATION			TRANSPORT CHANNEL RECONFIGURATION 10.2.51	
>PHYSICAL CHANNEL RECONFIGURATION			PHYSICAL CHANNEL RECONFIGURATION	

Information Element/Group name	Need	Multi	Type and reference	Semantics description
			10.2.20	
>RRC FAILURE INFO			RRC FAILURE INFO 10.2.41 a	
>DL DCCH message			OCTET STRING	