

TSG-RAN Meeting #19
Birmingham, UK, 11 - 14 March 2003

RP-030111

Title: CRs (Rel-4 and Rel-5 Category A) on TS 25.331

Source: TSG-RAN WG2

Agenda item: 8.2.4

Spec	CR	Rev	Phase	Subject	Cat	Version-Current	Version-New	Doc-2nd-Level	Workitem
25.331	1859	-	Rel-4	Correction of PNBSCH for 1.28Mcps TDD	F	4.8.0	4.9.0	R2-030496	LCRTDD-L23
25.331	1860	-	Rel-5	Correction of PNBSCH for 1.28Mcps TDD	A	5.3.0	5.4.0	R2-030497	LCRTDD-L23
25.331	1861	-	Rel-4	Correction of SFN-SFN observed time difference for 1.28Mcps TDD	F	4.8.0	4.9.0	R2-030498	LCRTDD-L23
25.331	1862	-	Rel-5	Correction of SFN-SFN observed time difference for 1.28Mcps TDD	A	5.3.0	5.4.0	R2-030499	LCRTDD-L23
25.331	1863	1	Rel-4	ASN.1 corrections concerning missing UE capability extensions	F	4.8.0	4.9.0	R2-030625	TEI4
25.331	1864	3	Rel-5	ASN.1 corrections concerning missing UE capability extensions	F	5.3.0	5.4.0	R2-030637	TEI4
25.331	1865	-	Rel-4	Extensions for 1.28 Mcps specific elements in system information	F	4.8.0	4.9.0	R2-030502	LCRTDD-L23
25.331	1866	-	Rel-5	Extensions for 1.28 Mcps specific elements in system information	A	5.3.0	5.4.0	R2-030503	LCRTDD-L23
25.331	1867	-	Rel-4	Corrections to power control parameter signalling for 1.28 Mcps TDD	F	4.8.0	4.9.0	R2-030504	LCRTDD-L23
25.331	1868	-	Rel-5	Corrections to power control parameter signalling for 1.28 Mcps TDD	A	5.3.0	5.4.0	R2-030505	LCRTDD-L23
25.331	1898	-	Rel-4	Removal of MRRU parameter in PDCP info	F	4.8.0	4.9.0	R2-030596	TEI4
25.331	1899	-	Rel-5	Removal of MRRU parameter in PDCP info	A	5.3.0	5.4.0	R2-030597	TEI4

CHANGE REQUEST

⌘ **25.331 CR 1859** ⌘ rev - ⌘ Current version: **4.8.0** ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

Proposed change affects: UICC apps ME Radio Access Network Core Network

Title:	⌘ Correction of PNBSCH for 1.28Mcps TDD		
Source:	⌘ TSG-RAN WG2		
Work item code:	⌘ LCRTDD-L23	Date:	⌘ January 2002
Category:	⌘ F	Release:	⌘ Rel-4
	Use <u>one</u> of the following categories:		Use <u>one</u> of the following releases:
	F (correction)	2 (GSM Phase 2)	
	A (corresponds to a correction in an earlier release)	R96 (Release 1996)	
	B (addition of feature),	R97 (Release 1997)	
	C (functional modification of feature)	R98 (Release 1998)	
	D (editorial modification)	R99 (Release 1999)	
	Detailed explanations of the above categories can be found in 3GPP TR 21.900 .		Rel-4 (Release 4)
			Rel-5 (Release 5)
			Rel-6 (Release 6)

Reason for change:	⌘ PNBSCH shall be used in 3.84Mcps TDD only.		
Summary of change:	⌘ Remove IE "PNBSCH allocation" to 3.84Mcps TDD option.		
	Isolated Impact analysis: This CR has isolated impact with the previous version of the specification (same release) because it only removes an optional IE not used in 1.28Mcps TDD.		
Consequences if not approved:	⌘ For 1.28Mcps TDD, UE will receive message including "PNBSCH allocation" IE that it is unexpected.		

Clauses affected:	⌘ 10.3.6.52										
Other specs affected:	<table border="1" style="display: inline-table; border-collapse: collapse;"> <tr> <td style="width: 20px; text-align: center;">Y</td> <td style="width: 20px; text-align: center;">N</td> </tr> <tr> <td style="text-align: center;">⌘</td> <td style="text-align: center;">X</td> </tr> <tr> <td style="text-align: center;">⌘</td> <td style="text-align: center;">X</td> </tr> <tr> <td style="text-align: center;">⌘</td> <td style="text-align: center;">X</td> </tr> </table>	Y	N	⌘	X	⌘	X	⌘	X	Other core specifications	⌘ N
Y	N										
⌘	X										
⌘	X										
⌘	X										
		Test specifications									
		O&M Specifications									
Other comments:	⌘										

How to create CRs using this form:

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>. Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name

with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.

- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

10.3.6.52 PRACH info (for RACH)

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
CHOICE <i>mode</i>	MP				
>FDD					
>>Available Signature	MP		Bit string(16)	Each bit indicates availability for a signature, where the signatures are numbered "signature 0" up to "signature 15". The value 1 of a bit indicates that the corresponding signature is available and the value 0 that it is not available.	
>>>Available SF	MP		Integer (32,64,128,256)	In chips per symbol Defines the minimum allowed SF (i.e. the maximum rate)	
>>>Preamble scrambling code number	MP		Integer (0 .. 15)	Identification of scrambling code see [28]	
>>>Puncturing Limit	MP		Real(0.40..1.00 by step of 0.04)		
>>>Available Sub Channel Number	MP		Bit string(12)	Each bit indicates availability for a subchannel, where the subchannels are numbered "subchannel 0" to "subchannel 11". The value 1 of a bit indicates that the corresponding subchannel is available and the value 0 indicates that it is not available.	
>TDD					
>>CHOICE <i>TDD option</i>	MP				REL-4
>>>3.84 Mcps TDD					REL-4
>>>>Timeslot number	MP		Timeslot number 10.3.6.84		
>>>>PRACH Channelisation Code List	MP		PRACH Channelisation Code List 10.3.6.51		
>>>>PRACH Midamble	MP		Enumerated (Direct, Direct/Inverted)	Direct or direct and inverted midamble are used for PRACH	
>>>>PNBSCH allocation	OP		PNBSCH allocation 10.3.8.10a	Identifies frames used for cell synchronisation purposes	REL-4
>>>1.28 Mcps TDD					REL-4

>>>>SYNC_UL info	MP		SYNC_UL info 10.3.6.78a		REL-4
>>>>PRACH Definition	MP	1..<maxPRACH_FPA CH>			REL-4
>>>>Timeslot number	MP		Timeslot number 10.3.6.84		REL-4
>>>>PRACH Channelisation Code	MP		PRACH Channelisation Code 1.28 Mcps TDD 10.3.6.51a		REL-4
>>>>Midamble Shift and burst type	MP		Midamble shift and burst type 10.3.6.41		REL-4
>>>>FPACH info	MP		FPACH info 10.3.6.35a		REL-4
>>PNBSCH-allocation	OP		PNBSCH-allocation-10.3.8.10a	Identifies frames-used for cell-synchronisation-purposes	REL-4

[ASN.1]

```

SysInfoType5 ::=
    sib6indicator                SEQUENCE {
        BOOLEAN,
        -- Physical channel IEs
        pich-PowerOffset        PICH-PowerOffset,
        modeSpecificInfo        CHOICE {
            fdd                  SEQUENCE {
                aich-PowerOffset AICH-PowerOffset
            },
            tdd                  SEQUENCE {
                -- If PDSCH/PUSCH is configured for 1.28Mcps TDD, the following IEs should be absent
                -- and the info included in the tdd128specificInfo instead.
                pusch-SysInfoList-SFN PUSCH-SysInfoList-SFN OPTIONAL,
                pdsch-SysInfoList-SFN PDSCH-SysInfoList-SFN OPTIONAL,
                openLoopPowerControl-TDD OpenLoopPowerControl-TDD
            }
        },
        primaryCCPCH-Info        PrimaryCCPCH-Info OPTIONAL,
        prach-SystemInformationList PRACH-SystemInformationList,
        sccpch-SystemInformationList SCCPCH-SystemInformationList,
        -- cbs-DRX-Level1Information is conditional on any of the CTCH indicator IEs in
        -- sccpch-SystemInformationList
        cbs-DRX-Level1Information CBS-DRX-Level1Information OPTIONAL,
        -- Extension mechanism for non- release99 information
        v4xyNonCriticalExtensions SEQUENCE {
            sysInfoType5-v4xyext SysInfoType5-v4xyext-IEs,
            -- Extension mechanism for non- rel-4 information
            nonCriticalExtensions SEQUENCE {} OPTIONAL
        }
    } OPTIONAL

SysInfoType5-v4xyext-IEs ::= SEQUENCE {
    --The following IE PNBSCH-Allocation-r4 shall be used 3.84Mcps TDD only.
    pNBSCH-Allocation-r4        PNBSCH-Allocation-r4 OPTIONAL,
    -- In case of TDD, the following IE is included instead of the
    -- IE up-IPDL-Parameter in up-OTDOA-AssistanceData.
    openLoopPowerControl-IPDL-TDD OpenLoopPowerControl-IPDL-TDD-r4 OPTIONAL,
    -- If SysInfoType5 is sent to describe a 1.28Mcps TDD cell, the IE PRACH-RACH-Info included in
    -- PRACH-SystemInformationList shall be ignored, the IE PRACH-Partitioning and the
    -- IE rach-TransportFormatSet shall be absent and the corresponding IE in the following
    -- PRACH-SystemInformationList-LCR-r4 shall be used
    prach-SystemInformationList-LCR-r4 PRACH-SystemInformationList-LCR-r4 OPTIONAL,
    tdd128specificInfo          SEQUENCE {
        pusch-SysInfoList-SFN    PUSCH-SysInfoList-SFN-LCR-r4 OPTIONAL,
        pdsch-SysInfoList-SFN    PDSCH-SysInfoList-SFN-LCR-r4 OPTIONAL,
    }
}

```

```
pCCPCH-LCR-Extensions          PrimaryCCPCH-Info-LCR-r4-ext    OPTIONAL,  
sCCPCH-LCR-ExtensionsList     SCCPCH-SystemInformationList-LCR-r4-ext  
                                OPTIONAL  
}
```

CHANGE REQUEST

⌘ **25.331 CR 1860** ⌘ rev **-** ⌘ Current version: **5.3.0** ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

Proposed change affects: UICC apps ME Radio Access Network Core Network

Title:	⌘ Correction of PNBSCH for 1.28Mcps TDD		
Source:	⌘ TSG-RAN WG2		
Work item code:	⌘ LCR-TDD L2/L3	Date:	⌘ January 2002
Category:	⌘ A	Release:	⌘ Rel-5
	Use <u>one</u> of the following categories:		Use <u>one</u> of the following releases:
	F (correction)	2 (GSM Phase 2)	
	A (corresponds to a correction in an earlier release)	R96 (Release 1996)	
	B (addition of feature),	R97 (Release 1997)	
	C (functional modification of feature)	R98 (Release 1998)	
	D (editorial modification)	R99 (Release 1999)	
	Detailed explanations of the above categories can be found in 3GPP TR 21.900 .		Rel-4 (Release 4)
			Rel-5 (Release 5)
			Rel-6 (Release 6)

Reason for change:	⌘ PNBSCH shall be used in 3.84Mcps TDD only.		
Summary of change:	⌘ Remove IE "PNBSCH allocation" to 3.84Mcps TDD option.		
	Isolated Impact analysis: This CR has isolated impact with the previous version of the specification (same release) because it only removes an optional IE not used in 1.28Mcps TDD.		
Consequences if not approved:	⌘ For 1.28Mcps TDD, UE will receive message including "PNBSCH allocation" IE that it is unexpected.		

Clauses affected:	⌘ 10.3.6.52										
Other specs affected:	<table border="1" style="display: inline-table; border-collapse: collapse;"> <tr> <td style="width: 20px; text-align: center;">Y</td> <td style="width: 20px; text-align: center;">N</td> </tr> <tr> <td style="text-align: center;">⌘</td> <td style="text-align: center;">X</td> </tr> <tr> <td style="text-align: center;">⌘</td> <td style="text-align: center;">X</td> </tr> <tr> <td style="text-align: center;">⌘</td> <td style="text-align: center;">X</td> </tr> </table>	Y	N	⌘	X	⌘	X	⌘	X	Other core specifications	⌘ N
Y	N										
⌘	X										
⌘	X										
⌘	X										
		Test specifications									
		O&M Specifications									
Other comments:	⌘										

How to create CRs using this form:

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>. Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name

with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.

- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

10.3.6.52 PRACH info (for RACH)

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
CHOICE <i>mode</i>	MP				
>FDD					
>>Available Signature	MP		Bit string(16)	Each bit indicates availability for a signature, where the signatures are numbered "signature 0" up to "signature 15". The value 1 of a bit indicates that the corresponding signature is available and the value 0 that it is not available.	
>>>Available SF	MP		Integer (32,64,128,256)	In chips per symbol Defines the minimum allowed SF (i.e. the maximum rate)	
>>>Preamble scrambling code number	MP		Integer (0 .. 15)	Identification of scrambling code see [28]	
>>>Puncturing Limit	MP		Real(0.40..1.00 by step of 0.04)		
>>>Available Sub Channel Number	MP		Bit string(12)	Each bit indicates availability for a subchannel, where the subchannels are numbered "subchannel 0" to "subchannel 11". The value 1 of a bit indicates that the corresponding subchannel is available and the value 0 indicates that it is not available.	
>TDD					
>>CHOICE <i>TDD option</i>	MP				REL-4
>>>3.84 Mcps TDD					REL-4
>>>>Timeslot number	MP		Timeslot number 10.3.6.84		
>>>>PRACH Channelisation Code List	MP		PRACH Channelisation Code List 10.3.6.51		
>>>>PRACH Midamble	MP		Enumerated (Direct, Direct/Inverted)	Direct or direct and inverted midamble are used for PRACH	
>>>>PNBSCH allocation	OP		PNBSCH allocation 10.3.8.10a	Identifies frames used for cell synchronisation purposes	REL-4
>>>1.28 Mcps TDD					REL-4

>>>>SYNC_UL info	MP		SYNC_UL info 10.3.6.78a		REL-4
>>>>PRACH Definition	MP	1..<maxPRACH_FPA CH>			REL-4
>>>>Timeslot number	MP		Timeslot number 10.3.6.84		REL-4
>>>>PRACH Channelisation Code	MP		PRACH Channelisation Code 1.28 Mcps TDD 10.3.6.51a		REL-4
>>>>Midamble Shift and burst type	MP		Midamble shift and burst type 10.3.6.41		REL-4
>>>>FPACH info	MP		FPACH info 10.3.6.35a		REL-4
>>PNBSCH-allocation	OP		PNBSCH-allocation-10.3.8.10a	Identifies frames-used for cell-synchronisation-purposes	REL-4

[ASN.1]

```

SysInfoType5 ::=
    sib6indicator                SEQUENCE {
        BOOLEAN,
        -- Physical channel IEs
        pich-PowerOffset        PICH-PowerOffset,
        modeSpecificInfo        CHOICE {
            fdd                  SEQUENCE {
                aich-PowerOffset AICH-PowerOffset
            },
            tdd                  SEQUENCE {
                -- If PDSCH/PUSCH is configured for 1.28Mcps TDD, the following IEs should be absent
                -- and the info included in the tdd128specificInfo instead.
                pusch-SysInfoList-SFN PUSCH-SysInfoList-SFN OPTIONAL,
                pdsch-SysInfoList-SFN PDSCH-SysInfoList-SFN OPTIONAL,
                openLoopPowerControl-TDD OpenLoopPowerControl-TDD
            }
        },
        primaryCCPCH-Info        PrimaryCCPCH-Info OPTIONAL,
        prach-SystemInformationList PRACH-SystemInformationList,
        sccpch-SystemInformationList SCCPCH-SystemInformationList,
        -- cbs-DRX-Level1Information is conditional on any of the CTCH indicator IEs in
        -- sccpch-SystemInformationList
        cbs-DRX-Level1Information CBS-DRX-Level1Information OPTIONAL,
        -- Extension mechanism for non- release99 information
        v4xyNonCriticalExtensions SEQUENCE {
            sysInfoType5-v4xyext SysInfoType5-v4xyext-IEs,
            -- Extension mechanism for non- rel-4 information
            nonCriticalExtensions SEQUENCE {} OPTIONAL
        }
    } OPTIONAL

SysInfoType5-v4xyext-IEs ::= SEQUENCE {
    --The following IE PNBSCH-Allocation-r4 shall be used 3.84Mcps TDD only.
    pNBSCH-Allocation-r4        PNBSCH-Allocation-r4 OPTIONAL,
    -- In case of TDD, the following IE is included instead of the
    -- IE up-IPDL-Parameter in up-OTDOA-AssistanceData.
    openLoopPowerControl-IPDL-TDD OpenLoopPowerControl-IPDL-TDD-r4 OPTIONAL,
    -- If SysInfoType5 is sent to describe a 1.28Mcps TDD cell, the IE PRACH-RACH-Info included in
    -- PRACH-SystemInformationList shall be ignored, the IE PRACH-Partitioning and the
    -- IE rach-TransportFormatSet shall be absent and the corresponding IE in the following
    -- PRACH-SystemInformationList-LCR-r4 shall be used
    prach-SystemInformationList-LCR-r4 PRACH-SystemInformationList-LCR-r4 OPTIONAL,
    tdd128specificInfo          SEQUENCE {
        pusch-SysInfoList-SFN        PUSCH-SysInfoList-SFN-LCR-r4 OPTIONAL,
        pdsch-SysInfoList-SFN        PDSCH-SysInfoList-SFN-LCR-r4 OPTIONAL,
    }
}

```

```
pCCPCH-LCR-Extensions      PrimaryCCPCH-Info-LCR-r4-ext    OPTIONAL,  
sCCPCH-LCR-ExtensionsList  SCCPCH-SystemInformationList-LCR-r4-ext  
                                OPTIONAL  
}
```

CHANGE REQUEST

⌘ **25.331 CR 1861** ⌘ rev ⌘ Current version: **4.8.0** ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

Proposed change affects: UICC apps ME Radio Access Network Core Network

Title:	⌘ Correction of SFN-SFN observed time difference for 1.28Mcps TDD		
Source:	⌘ TSG-RAN WG2		
Work item code:	⌘ LCRTDD-L23	Date:	⌘ January 2002
Category:	⌘ F	Release:	⌘ Rel-4
	Use <u>one</u> of the following categories:		Use <u>one</u> of the following releases:
	F (correction)	2 (GSM Phase 2)	
	A (corresponds to a correction in an earlier release)	R96 (Release 1996)	
	B (addition of feature),	R97 (Release 1997)	
	C (functional modification of feature)	R98 (Release 1998)	
	D (editorial modification)	R99 (Release 1999)	
	Detailed explanations of the above categories can be found in 3GPP TR 21.900 .		Rel-4 (Release 4)
			Rel-5 (Release 5)
			Rel-6 (Release 6)

Reason for change:	⌘ According to definition of SFN-SFN observed time difference, section 5.1.10 in 25.225. The range of SFN-SFN observed time difference for 1.28Mcps TDD is not correct.		
Summary of change:	⌘ Correct the range of SFN-SFN observed time difference for 1.28Mcps TDD.		
	Isolated Impact analysis: This CR has isolated impact with the previous version of the specification (same release) because it only corrects the range of SFN-SFN observed time difference for 1.28Mcps TDD.		
Consequences if not approved:	⌘ The range of SFN-SFN observed time difference is unambiguous for 1.28Mcps TDD.		

Clauses affected:	⌘ 10.3.7.63						
Other specs affected:	<table border="1" style="display: inline-table; border-collapse: collapse;"> <tr> <td style="width: 20px; text-align: center;">Y</td> <td style="width: 20px; text-align: center;">N</td> </tr> <tr> <td style="text-align: center;"><input type="checkbox"/></td> <td style="text-align: center;"><input checked="" type="checkbox"/></td> </tr> </table>	Y	N	<input type="checkbox"/>	<input checked="" type="checkbox"/>	Other core specifications	⌘ N
Y	N						
<input type="checkbox"/>	<input checked="" type="checkbox"/>						
	<input checked="" type="checkbox"/>	Test specifications					
	<input checked="" type="checkbox"/>	O&M Specifications					
Other comments:	⌘						

How to create CRs using this form:

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>. Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.

- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

10.3.7.63 SFN-SFN observed time difference

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
CHOICE <i>type</i>	MP				
>Type 1			Integer(0..9830399)	According to T1_SFN-SFN_TIME in [19] and [20]. For FDD and 3.84Mcps TDD: 6946816 spare values are needed.	
			Integer(0..3276799)	For 1.28Mcps TDD: 13500416 spare values are needed.	Rel-4
>Type 2			Integer(0..40961)	According to T2_SFN-SFN_TIME in [19] and [20]. 24574 spare values are needed.	

[ASN.1]

```

SFN-SFN-ObsTimeDifference ::= CHOICE {
    type1          SFN-SFN-ObsTimeDifference1,
    type2          SFN-SFN-ObsTimeDifference2
}

```

```

--SPARE: SFN-SFN-ObsTimeDifference1, Max = 9830399 For 1.28Mcps TDD,Max value of
-- SFN-SFN-ObsTimeDifference1 is 3276799.

```

```

-- Values above Max are spare

```

```

SFN-SFN-ObsTimeDifference1 ::= INTEGER (0..16777215)

```

```

-- SPARE: SFN-SFN-ObsTimeDifference2, Max = 40961

```

```

-- Values above Max are spare

```

```

SFN-SFN-ObsTimeDifference2 ::= INTEGER (0..65535)

```

...

CHANGE REQUEST

⌘ **25.331 CR 1862** ⌘ rev ⌘ Current version: **5.3.0** ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

Proposed change affects: UICC apps ME Radio Access Network Core Network

Title:	⌘ Correction of SFN-SFN observed time difference for 1.28Mcps TDD		
Source:	⌘ TSG-RAN WG2		
Work item code:	⌘ LCRTDD-L23	Date:	⌘ January 2002
Category:	⌘ A	Release:	⌘ Rel-5
	Use <u>one</u> of the following categories:		Use <u>one</u> of the following releases:
	F (correction)	2 (GSM Phase 2)	
	A (corresponds to a correction in an earlier release)	R96 (Release 1996)	
	B (addition of feature),	R97 (Release 1997)	
	C (functional modification of feature)	R98 (Release 1998)	
	D (editorial modification)	R99 (Release 1999)	
	Detailed explanations of the above categories can be found in 3GPP TR 21.900 .		Rel-4 (Release 4)
			Rel-5 (Release 5)
			Rel-6 (Release 6)

Reason for change:	⌘ According to definition of SFN-SFN observed time difference, section 5.1.10 in 25.225. The range of SFN-SFN observed time difference for 1.28Mcps TDD is not correct.		
Summary of change:	⌘ Correct the range of SFN-SFN observed time difference for 1.28Mcps TDD.		
	Isolated Impact analysis: This CR has isolated impact with the previous version of the specification (same release) because it only corrects the range of SFN-SFN observed time difference for 1.28Mcps TDD.		
Consequences if not approved:	⌘ The range of SFN-SFN observed time difference is unambiguous for 1.28Mcps TDD.		

Clauses affected:	⌘ 10.3.7.63										
Other specs affected:	<table border="1" style="display: inline-table; border-collapse: collapse;"> <tr> <td style="width: 20px; text-align: center;">Y</td> <td style="width: 20px; text-align: center;">N</td> </tr> <tr> <td style="text-align: center;"><input type="checkbox"/></td> <td style="text-align: center;"><input checked="" type="checkbox"/></td> </tr> <tr> <td style="text-align: center;"><input type="checkbox"/></td> <td style="text-align: center;"><input checked="" type="checkbox"/></td> </tr> <tr> <td style="text-align: center;"><input type="checkbox"/></td> <td style="text-align: center;"><input checked="" type="checkbox"/></td> </tr> </table>	Y	N	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	Other core specifications	⌘ N
Y	N										
<input type="checkbox"/>	<input checked="" type="checkbox"/>										
<input type="checkbox"/>	<input checked="" type="checkbox"/>										
<input type="checkbox"/>	<input checked="" type="checkbox"/>										
		Test specifications									
		O&M Specifications									
Other comments:	⌘										

How to create CRs using this form:

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>. Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.

- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

10.3.7.63 SFN-SFN observed time difference

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
CHOICE <i>type</i>	MP				
>Type 1			Integer(0..9830399)	According to T1_SFN-SFN_TIME in [19] and [20]. For FDD and 3.84Mcps TDD: 6946816 spare values are needed.	
			Integer(0..3276799)	For 1.28Mcps TDD: 13500416 spare values are needed.	Rel-4
>Type 2			Integer(0..40961)	According to T2_SFN-SFN_TIME in [19] and [20]. 24574 spare values are needed.	

[ASN.1]

```

SFN-SFN-ObsTimeDifference ::= CHOICE {
    type1          SFN-SFN-ObsTimeDifference1,
    type2          SFN-SFN-ObsTimeDifference2
}

```

```

--SPARE: SFN-SFN-ObsTimeDifference1, Max = 9830399 For 1.28Mcps TDD,Max value of
-- SFN-SFN-ObsTimeDifference1 is 3276799.

```

```

-- Values above Max are spare

```

```

SFN-SFN-ObsTimeDifference1 ::= INTEGER (0..16777215)

```

```

-- SPARE: SFN-SFN-ObsTimeDifference2, Max = 40961

```

```

-- Values above Max are spare

```

```

SFN-SFN-ObsTimeDifference2 ::= INTEGER (0..65535)

```

...

CHANGE REQUEST

⌘ **25.331 CR 1863** ⌘ rev **1** ⌘ Current version: **4.8.0** ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

Proposed change affects: UICC apps ME Radio Access Network Core Network

Title:	⌘ ASN.1 corrections concerning missing UE capability extensions	
Source:	⌘ TSG-RAN WG2	
Work item code:	⌘ TEI-4	Date: ⌘ 21/02/2003
Category:	⌘ F	Release: ⌘ REL-4
	Use <u>one</u> of the following categories:	Use <u>one</u> of the following releases:
	F (correction)	2 (GSM Phase 2)
	A (corresponds to a correction in an earlier release)	R96 (Release 1996)
	B (addition of feature),	R97 (Release 1997)
	C (functional modification of feature)	R98 (Release 1998)
	D (editorial modification)	R99 (Release 1999)
	Detailed explanations of the above categories can be found in 3GPP TR 21.900 .	Rel-4 (Release 4)
		Rel-5 (Release 5)
		Rel-6 (Release 6)

Reason for change:	⌘ The original version of this CR includes the following changes: <ul style="list-style-type: none"> The release 4 extensions to UE radio access capabilities except for access stratum release indicator are missing in the INTER RAT HANDOVER INFO and the SRNS RELOCATION INFO messages
Summary of change:	⌘ The original version of this CR includes the following changes: <p><u>Addition of missing extensions</u></p> <ul style="list-style-type: none"> The release 4 extensions to UE radio access capabilities except for access stratum release indicator have been added to the INTER RAT HANDOVER INFO and the SRNS RELOCATION INFO messages to align with the tabular format. This change is performed by merging these extension that were included in UE-RadioAccessCapability-r4-ext with the access stratum release indicator into IE UE-RadioAccessCapability-v4xyext. Furthermore, some changes were performed concerning the optionality of the information in order to reduce the overhead: <ul style="list-style-type: none"> The optionality is removed for the extension formerly included in IE UE-RadioAccessCapability-r4-ext because the PDCP capability might as well be included always; the number of bits to signal "not supported" is equal to omitting the IE To optimise the signalling, an optionality bit has been introduced for extensions that are TDD specific The access stratum release indicator is made optional so the same ASN.1 type can be used in all messages (rather than specifying all constraints in ASN.1 by defining a specific type without this IE for the RRC CONNECTION SETUP COMPLETE message)

Note The name UE-RadioAccessCapability-v4xyext is used for the merged IE in accordance with the conventions defined in 25.921. However, there are some other r4 extensions are not in accordance with these conventions

The CR introduced a side effect on the RRC connection request message, that has been removed in revision 1 of this CR

Consequences if not approved:

⌘ The inconsistency between the tabular and the ASN.1 remains

Impact analysis:

- The target RNC may have insufficient information to successfully complete handover to UTRAN or SRNS relocation. The missing information concerns REL-4 specific capabilities concerning PDCP and TDD.
- This CR concerns a clarification of a function where the specification is incorrect/ inconsistent. This CR involves a change of the REL-4 ASN.1
- If only UTRAN or the UE implements the CR, this may result in a transfer syntax error as a result of which the handover/ SRNS relocation is likely to fail

Clauses affected: ⌘ 11.2, 11.3, 11.5

Other specs affected:

Y	N		⌘
	X	Other core specifications	
	X	Test specifications	
	X	O&M Specifications	

Other comments: ⌘

How to create CRs using this form:

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>. Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

11.2 PDU definitions

<Skipped until the next modified section>

```

-- *****
--
-- INTER RAT HANDOVER INFO
--
-- *****

InterRATHandoverInfo ::= SEQUENCE {
  -- This structure is defined for historical reasons, backward compatibility with 04.18
  predefinedConfigStatusList CHOICE {
    absent NULL,
    present PredefinedConfigStatusList
  },
  ue-SecurityInformation CHOICE {
    absent NULL,
    present UE-SecurityInformation
  },
  ue-CapabilityContainer CHOICE {
    absent NULL,
    -- present is an octet aligned string containing IE UE-RadioAccessCapabilityInfo
    present OCTET STRING (SIZE (0..63))
  },
  -- Non critical extensions
  v390NonCriticalExtensions CHOICE {
    absent NULL,
    present SEQUENCE {
      interRATHandoverInfo-v390ext InterRATHandoverInfo-v390ext-IEs,
      v3a0NonCriticalExtensions SEQUENCE {
        interRATHandoverInfo-v3a0ext InterRATHandoverInfo-v3a0ext,
        laterNonCriticalExtensions SEQUENCE {
          interRATHandoverInfo-v3d0ext InterRATHandoverInfo-v3d0ext-IEs,
          -- Container for additional R99 extensions
          interRATHandoverInfo-r3-add-ext BIT STRING OPTIONAL,
          v4xyNonCriticalExtensions SEQUENCE {
            interRATHandoverInfo-v4xyext InterRATHandoverInfo-v4xyext-IEs,
            -- Reserved for future non critical extension
            nonCriticalExtensions SEQUENCE {} OPTIONAL
          } OPTIONAL
        } OPTIONAL
      } OPTIONAL
    } OPTIONAL
  }
}

InterRATHandoverInfo-v390ext-IEs ::= SEQUENCE {
  -- User equipment IEs
  ue-RadioAccessCapability-v380ext UE-RadioAccessCapability-v380ext OPTIONAL,
  dl-PhysChCapabilityFDD-v380ext DL-PhysChCapabilityFDD-v380ext
}

InterRATHandoverInfo-v3a0ext ::= SEQUENCE {
  -- User equipment IEs
  ue-RadioAccessCapability-v3a0ext UE-RadioAccessCapability-v3a0ext OPTIONAL
}

InterRATHandoverInfo-v3d0ext-IEs ::= SEQUENCE {
  -- User equipment IEs
  ueSpecificBehaviourInformationlinterRAT UESpecificBehaviourInformationlinterRAT
  OPTIONAL
}

InterRATHandoverInfo-v4xyext-IEs ::= SEQUENCE {
  -- User equipment IEs
  ue-RadioAccessCapability-v4xyext UE-RadioAccessCapability-v4xyext
}

```

<Skipped until the next modified section>

```

-- *****
--
-- RRC CONNECTION REQUEST
--

```

```

-- *****

RRCConnectionRequest ::= SEQUENCE {
  -- TABULAR: Integrity protection shall not be performed on this message.
  -- User equipment IEs
  initialUE-Identity          InitialUE-Identity,
  establishmentCause          EstablishmentCause,
  -- protocolErrorIndictator is MD, but for compactness reasons no default value
  -- has been assigned to it.
  protocolErrorIndicator      ProtocolErrorIndicator,
  -- Measurement IEs
  measuredResultsOnRACH       MeasuredResultsOnRACH          OPTIONAL,
  -- Non critical Extensions
  v3d0NonCriticalExtensions   SEQUENCE {
    rrcConnectionRequest-v3d0ext  RRCConnectionRequest-v3d0ext-IEs,
    -- Reserved for future non critical extension
    v4xyNonCriticalExtensions     SEQUENCE {
      rrcConnectionRequest-v4xyext  RRCConnectionRequest-v4xyext-IEs,
      -- Reserved for future non critical extension
      nonCriticalExtensions         SEQUENCE {}          OPTIONAL
    } OPTIONAL
  } OPTIONAL
}

RRCConnectionRequest-v3d0ext-IEs ::= SEQUENCE {
  -- User equipment IEs
  ueSpecificBehaviourInformationIdle  UESpecificBehaviourInformationIdle  OPTIONAL
}

RRCConnectionRequest-v4xyext-IEs ::= SEQUENCE {
  -- User equipment IEs
  ue-RadioAccessCapability-v4xyext UE-RadioAccessCapability-v4xyext
  accessStratumReleaseIndicator      AccessStratumReleaseIndicator
}

-- *****
--
-- RRC CONNECTION SETUP COMPLETE
--
-- *****

RRCConnectionSetupComplete ::= SEQUENCE {
  -- TABULAR: Integrity protection shall not be performed on this message.
  -- User equipment IEs
  rrc-TransactionIdentifier      RRC-TransactionIdentifier,
  startList                      STARTList,
  ue-RadioAccessCapability       UE-RadioAccessCapability          OPTIONAL,
  -- Other IEs
  ue-RATSpecificCapability       InterRAT-UE-RadioAccessCapabilityList  OPTIONAL,
  -- Non critical extensions
  v370NonCriticalExtensions      SEQUENCE {
    rrcConnectionSetupComplete-v370ext  RRCConnectionSetupComplete-v370ext,
    v380NonCriticalExtensions          SEQUENCE {
      rrcConnectionSetupComplete-v380ext  RRCConnectionSetupComplete-v380ext-IEs,
      -- Reserved for future non critical extension
      v3a0NonCriticalExtensions          SEQUENCE {
        rrcConnectionSetupComplete-v3a0ext  RRCConnectionSetupComplete-v3a0ext,
        laterNonCriticalExtensions         SEQUENCE {
          -- Container for additional R99 extensions
          rrcConnectionSetupComplete-r3-add-ext  BIT STRING          OPTIONAL,
          v4xyNonCriticalExtensions          SEQUENCE {
            rrcConnectionSetupComplete-v4xyext  RRCConnectionSetupComplete-v4xyext-
IEs,
            nonCriticalExtensions          SEQUENCE {}          OPTIONAL
          } OPTIONAL
        } OPTIONAL
      } OPTIONAL
    } OPTIONAL
  } OPTIONAL
}

RRCConnectionSetupComplete-v370ext ::= SEQUENCE {
  -- User equipment IEs
  ue-RadioAccessCapability-v370ext  UE-RadioAccessCapability-v370ext  OPTIONAL
}

RRCConnectionSetupComplete-v380ext-IEs ::= SEQUENCE {
  -- User equipment IEs

```

```

        ue-RadioAccessCapability-v380ext      UE-RadioAccessCapability-v380ext      OPTIONAL,
        dl-PhysChCapabilityFDD-v380ext        DL-PhysChCapabilityFDD-v380ext
    }

RRCConnectionSetupComplete-v3a0ext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v3a0ext      UE-RadioAccessCapability-v3a0ext      OPTIONAL
}

RRCConnectionSetupComplete-v4xyext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-r4-v4xyext    UE-RadioAccessCapability-r4-v4xyext    OPTIONAL
}

<Skipped until the next modified section>

-- *****
--
-- UE CAPABILITY INFORMATION
--
-- *****

UECapabilityInformation ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier      RRC-TransactionIdentifier      OPTIONAL,
    ue-RadioAccessCapability        UE-RadioAccessCapability        OPTIONAL,
    -- Other IEs
    ue-RATSpecificCapability        InterRAT-UE-RadioAccessCapabilityList
    OPTIONAL,
    v370NonCriticalExtensions      SEQUENCE {
        ueCapabilityInformation-v370ext    UECapabilityInformation-v370ext,
        v380NonCriticalExtensions        SEQUENCE {
            ueCapabilityInformation-v380ext    UECapabilityInformation-v380ext-IEs,
            v3a0NonCriticalExtensions        SEQUENCE {
                ueCapabilityInformation-v3a0ext    UECapabilityInformation-v3a0ext,
                laterNonCriticalExtensions        SEQUENCE {
                    -- Container for additional R99 extensions
                    ueCapabilityInformation-r3-add-ext    BIT STRING      OPTIONAL,
                    -- Reserved for future non critical extension
                    v4xyNonCriticalExtensions        SEQUENCE {
                        ueCapabilityInformation-v4xyext    UECapabilityInformation-v4xyext,
                        nonCriticalExtensions        SEQUENCE {}      OPTIONAL
                    }
                }
            }
        }
    }
}

UECapabilityInformation-v370ext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v370ext      UE-RadioAccessCapability-v370ext      OPTIONAL
}

UECapabilityInformation-v380ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v380ext      UE-RadioAccessCapability-v380ext
    OPTIONAL,
    dl-PhysChCapabilityFDD-v380ext        DL-PhysChCapabilityFDD-v380ext
}

UECapabilityInformation-v3a0ext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v3a0ext      UE-RadioAccessCapability-v3a0ext      OPTIONAL
}

UECapabilityInformation-v4xyext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-r4-ext    UE-RadioAccessCapability-r4-ext    OPTIONAL,
    ue-RadioAccessCapability-v4xyext      UE-RadioAccessCapability-v4xyext
}

```

11.3 Information element definitions

<Skipped until the next modified section>

```
-- *****
--
-- USER EQUIPMENT INFORMATION ELEMENTS (10.3.3)
--
-- *****
```

<Skipped until the next modified section>

```
UE-RadioAccessCapabBandFDD ::= SEQUENCE{
    radioFrequencyBandFDD          RadioFrequencyBandFDD,
    fddRF-Capability                SEQUENCE {
        ue-PowerClass              UE-PowerClass-v370,
        txRxFrequencySeparation    TxRxFrequencySeparation
    }
    measurementCapability           MeasurementCapability-v370
}

UE-RadioAccessCapability-r4-v4xyext ::= SEQUENCE {
    pdcp-Capability-r4-ext         PDCP-Capability-r4-ext,
    tdd-CapabilityExt              SEQUENCE {
        rf-Capability              RF-Capability-r4-ext,
        physicalChannelCapability-LCR PhysicalChannelCapability-LCR-r4,
        measurementCapability-r4-ext MeasurementCapability-r4-ext
        OPTIONAL,
        -- IE " AccessStratumReleaseIndicator" is not needed in RRC CONNECTION SETUP COMPLETE
        accessStratumReleaseIndicator AccessStratumReleaseIndicator OPTIONAL
    }
}

UE-RadioAccessCapability-v4xyext ::= SEQUENCE {
    R99-UEs shall include IE "ue-TestLevelIndicator"
    accessStratumReleaseIndicator AccessStratumReleaseIndicator
}

... just for information

PDCP-Capability-r4-ext ::= SEQUENCE {
    supportForRfc3095           CHOICE {
        notSupported            NULL,
        supported               SEQUENCE {
            maxROHC-ContextSessions MaxROHC-ContextSessions-r4 DEFAULT s16,
            reverseCompressionDepth  INTEGER (0..65535)           DEFAULT 0
        }
    }
}

RF-Capability-r4-ext ::= SEQUENCE {
    tddRF-Capability           SEQUENCE {
        ue-PowerClass          UE-PowerClass,
        radioFrequencyBandTDDList RadioFrequencyBandTDDList,
        chipRateCapability      ChipRateCapability
    }
    OPTIONAL
}

-- PhysicalChannelCapability-LCR-r4 describes the 1.28Mcps TDD physical channel capability
PhysicalChannelCapability-LCR-r4 ::= SEQUENCE {
    tdd128-PhysChCapability     SEQUENCE {
        downlinkPhysChCapability DL-PhysChCapabilityTDD-LCR-r4,
        uplinkPhysChCapability   UL-PhysChCapabilityTDD-LCR-r4
    }
    OPTIONAL
}

MeasurementCapability-r4-ext ::= SEQUENCE {
    downlinkCompressedMode-LCR  CompressedModeMeasCapability-LCR-r4,
    uplinkCompressedMode-LCR    CompressedModeMeasCapability-LCR-r4
}

AccessStratumReleaseIndicator ::= ENUMERATED {
    rel-4, spare15, spare14, spare13,
    spare12, spare11, spare10, spare9, spare8,
    spare7, spare6, spare5, spare4, spare3,
    spare2, spare1 }

```

11.5 RRC information between network nodes

<Skipped until the next modified section>

```
-- *****
--
-- SRNC Relocation information
--
-- *****

SRNC-RelocationInfo-r3 ::= CHOICE {
  r3
    SRNC-RelocationInfo-r3 SEQUENCE {
      SRNC-RelocationInfo-r3-IEs,
      v380NonCriticalExtensions SEQUENCE {
        SRNC-RelocationInfo-v380ext SRNC-RelocationInfo-v380ext-IEs,
        -- Reserved for future non critical extension
        v390NonCriticalExtensions SEQUENCE {
          SRNC-RelocationInfo-v390ext SRNC-RelocationInfo-v390ext-IEs,
          v3a0NonCriticalExtensions SEQUENCE {
            SRNC-RelocationInfo-v3a0ext SRNC-RelocationInfo-v3a0ext-IEs,
            v3b0NonCriticalExtensions SEQUENCE {
              SRNC-RelocationInfo-v3b0ext SRNC-RelocationInfo-v3b0ext-IEs,
              v3c0NonCriticalExtensions SEQUENCE {
                SRNC-RelocationInfo-v3c0ext SRNC-RelocationInfo-v3c0ext-IEs,
                laterNonCriticalExtensions SEQUENCE {
                  SRNC-RelocationInfo-v3d0ext SRNC-RelocationInfo-v3d0ext-IEs,
                  -- Container for additional R99 extensions
                  SRNC-RelocationInfo-r3-add-ext BIT STRING OPTIONAL,
                  v4xyNonCriticalExtensions SEQUENCE {
                    SRNC-RelocationInfo-v4xyext SRNC-RelocationInfo-
v4xyext-IEs,
                    -- Reserved for future non critical extension
                    nonCriticalExtensions SEQUENCE {} OPTIONAL
                  }
                } OPTIONAL
              } OPTIONAL
            } OPTIONAL
          } OPTIONAL
        } OPTIONAL
      },
      later-than-r3 CHOICE {
        r4 SEQUENCE {
          SRNC-RelocationInfo-r4 SRNC-RelocationInfo-r4-IEs,
          nonCriticalExtensions SEQUENCE {} OPTIONAL
        },
        criticalExtensions SEQUENCE {}
      }
    }
}

SRNC-RelocationInfo-r3-IEs ::= SEQUENCE {
  -- Non-RRC IEs
  stateOfRRC StateOfRRC,
  stateOfRRC-Procedure StateOfRRC-Procedure,
  -- Ciphering related information IEs
  -- If the extension v380 is included use the extension for the ciphering status per CN domain
  cipheringStatus CipheringStatus,
  calculationTimeForCiphering CalculationTimeForCiphering OPTIONAL,
  -- The order of occurrence in the IE cipheringInfoPerRB-List is the
  -- same as the RBs in the IE "Signalling RB information list" and in the
  -- IE "RAB information list". The signalling RBs are supposed to be listed
  -- first. Only UM and AM RBs that are ciphered are listed here
  cipheringInfoPerRB-List CipheringInfoPerRB-List OPTIONAL,
  count-C-List COUNT-C-List OPTIONAL,
  integrityProtectionStatus IntegrityProtectionStatus,
  -- The order of occurrence in the IE srb-SpecificIntegrityProtInfo is the
  -- same as the SRBs in the IE "Signalling RB information list"
  srb-SpecificIntegrityProtInfo SRB-SpecificIntegrityProtInfoList,
  implementationSpecificParams ImplementationSpecificParams OPTIONAL,
  -- User equipment IEs
  u-RNTI U-RNTI,
  c-RNTI C-RNTI OPTIONAL,
  ue-RadioAccessCapability UE-RadioAccessCapability,
  ue-Positioning-LastKnownPos UE-Positioning-LastKnownPos OPTIONAL,
  -- Other IEs
  ue-RATSpecificCapability InterRAT-UE-RadioAccessCapabilityList OPTIONAL,
}
```



```

-- UTRAN mobility IEs
ura-Identity          URA-Identity          OPTIONAL,
-- Core network IEs
cn-CommonGSM-MAP-NAS-SysInfo  NAS-SystemInformationGSM-MAP,
cn-DomainInformationList      CN-DomainInformationList      OPTIONAL,
-- Measurement IEs
ongoingMeasRepList          OngoingMeasRepList          OPTIONAL,
-- Radio bearer IEs
predefinedConfigStatusList    PredefinedConfigStatusList,
srb-InformationList          SRB-InformationSetupList,
rab-InformationList          RAB-InformationSetupList    OPTIONAL,
-- Transport channel IEs
ul-CommonTransChInfo        UL-CommonTransChInfo        OPTIONAL,
ul-TransChInfoList          UL-AddReconfTransChInfoList  OPTIONAL,
modeSpecificInfo            CHOICE {
    fdd                      SEQUENCE {
        cpch-SetID          CPCH-SetID          OPTIONAL,
        transChDRAC-Info    DRAC-StaticInformationList  OPTIONAL
    },
    tdd                      NULL
},
dl-CommonTransChInfo        DL-CommonTransChInfo        OPTIONAL,
dl-TransChInfoList          DL-AddReconfTransChInfoList  OPTIONAL,
-- Measurement report
measurementReport            MeasurementReport            OPTIONAL
}

SRNC-RelocationInfo-v380ext-IEs ::= SEQUENCE {
-- Ciphering related information IEs
cn-DomainIdentity          CN-DomainIdentity,
cipheringStatusList        CipheringStatusList
}

SRNC-RelocationInfo-v390ext-IEs ::= SEQUENCE {
cn-DomainInformationList-v390ext  CN-DomainInformationList-v390ext  OPTIONAL,
ue-RadioAccessCapability-v370ext  UE-RadioAccessCapability-v370ext  OPTIONAL,
ue-RadioAccessCapability-v380ext  UE-RadioAccessCapability-v380ext  OPTIONAL,
dl-PhysChCapabilityFDD-v380ext    DL-PhysChCapabilityFDD-v380ext,
failureCauseWithProtErr          FailureCauseWithProtErr          OPTIONAL
}

SRNC-RelocationInfo-v3a0ext-IEs ::= SEQUENCE {
-- cn-domain identity for IE startValueForCiphering-v3a0ext is specified
-- in subsequent extension (SRNC-RelocationInfo-v3b0ext-IEs)
startValueForCIphering-v3a0ext    START-Value,
cipheringInfoForSRB1-v3a0ext      CipheringInfoForSRB1-v3a0ext,
ue-RadioAccessCapability-v3a0ext  UE-RadioAccessCapability-v3a0ext  OPTIONAL
}

SRNC-RelocationInfo-v3b0ext-IEs ::= SEQUENCE {
-- cn-domain identity for IE startValueForCiphering-v3a0ext included in previous extension
cn-DomainIdentity          CN-DomainIdentity,
-- the remaining start values are contained in IE startValueForCiphering-v3b0ext
startValueForCiphering-v3b0ext    STARTList2          OPTIONAL
}

SRNC-RelocationInfo-v3c0ext-IEs ::= SEQUENCE {
-- IE rb-IdentityForHOMessage includes the identity of the RB used by the source SRNC
-- to send the message contained in the IE "TargetRNC-ToSourceRNC-Container".
-- Only included if type is "UE involved"
rb-IdentityForHOMessage          RB-Identity          OPTIONAL
}

SRNC-RelocationInfo-v3d0ext-IEs ::= SEQUENCE {
-- User equipment IEs
ueSpecificBehaviourInformationlidle  UESpecificBehaviourInformationlidle  OPTIONAL,
ueSpecificBehaviourInformationlinterRAT  UESpecificBehaviourInformationlinterRAT
OPTIONAL
}

STARTList2 ::=
SEQUENCE (SIZE (2..maxCNdomains)) OF
STARTSingle

SRNC-RelocationInfo-v4xyext-IEs ::= SEQUENCE {
ue-RadioAccessCapability-v4xyext  UE-RadioAccessCapability-v4xyext
}

```

```

CipheringInfoForSRB1-v3a0ext ::= SEQUENCE {
    dl-UM-SN                BIT STRING (SIZE (7))
}

CipheringStatusList ::=          SEQUENCE (SIZE (1..maxCNdomains)) OF
                                CipheringStatusCNdomain

CipheringStatusCNdomain ::=      SEQUENCE {
    cn-DomainIdentity        CN-DomainIdentity,
    cipheringStatus          CipheringStatus
}

SRNC-RelocationInfo-r4-IEs ::=  SEQUENCE {
    -- Non-RRC IEs
    -- IE rb-IdentityForHOMessage includes the identity of the RB used by the source SRNC
    -- to send the message contained in the IE "TargetRNC-ToSourceRNC-Container".
    -- Only included if type is "UE involved"
    rb-IdentityForHOMessage    RB-Identity                OPTIONAL,
    stateOfRRC                StateOfRRC,
    stateOfRRC-Procedure       StateOfRRC-Procedure,
    -- Ciphering related information IEs
    cipheringStatusList        CipheringStatusList-r4,
    latestConfiguredCN-Domain  CN-DomainIdentity,
    calculationTimeForCiphering CalculationTimeForCiphering    OPTIONAL,
    count-C-List               COUNT-C-List                OPTIONAL,
    cipheringInfoPerRB-List     CipheringInfoPerRB-List-r4    OPTIONAL,
    -- Integrity protection related information IEs
    integrityProtectionStatus    IntegrityProtectionStatus,
    srb-SpecificIntegrityProtInfo SRB-SpecificIntegrityProtInfoList,
    implementationSpecificParams ImplementationSpecificParams    OPTIONAL,
    -- User equipment IEs
    u-RNTI                     U-RNTI,
    c-RNTI                     C-RNTI                OPTIONAL,
    ue-RadioAccessCapability    UE-RadioAccessCapability-r4,
    ue-RadioAccessCapability-ext UE-RadioAccessCapabBandFDDList    OPTIONAL,
    ue-Positioning-LastKnownPos UE-Positioning-LastKnownPos        OPTIONAL,
    ueSpecificBehaviourInformationIdle UESpecificBehaviourInformationIdle    OPTIONAL,
    ueSpecificBehaviourInformationInterRAT UESpecificBehaviourInformationInterRAT
    OPTIONAL,
    -- Other IEs
    ue-RATSpecificCapability     InterRAT-UE-RadioAccessCapabilityList    OPTIONAL,
    -- UTRAN mobility IEs
    ura-Identity                URA-Identity                OPTIONAL,
    -- Core network IEs
    cn-CommonGSM-MAP-NAS-SysInfo NAS-SystemInformationGSM-MAP,
    cn-DomainInformationList     CN-DomainInformationListFull    OPTIONAL,
    -- Measurement IEs
    ongoingMeasRepList           OngoingMeasRepList-r4        OPTIONAL,
    -- Radio bearer IEs
    predefinedConfigStatusList    PredefinedConfigStatusList,
    srb-InformationList           SRB-InformationSetupList,
    rab-InformationList           RAB-InformationSetupList-r4    OPTIONAL,
    -- Transport channel IEs
    ul-CommonTransChInfo         UL-CommonTransChInfo-r4        OPTIONAL,
    ul-TransChInfoList           UL-AddReconfTransChInfoList    OPTIONAL,
    modeSpecificInfo              CHOICE {
        fdd                      SEQUENCE {
            cpch-SetID            CPCH-SetID                OPTIONAL,
            transChDRAC-Info      DRAC-StaticInformationList    OPTIONAL
        },
        tdd                      NULL
    }
    dl-CommonTransChInfo         DL-CommonTransChInfo-r4        OPTIONAL,
    dl-TransChInfoList           DL-AddReconfTransChInfoList-r4    OPTIONAL,
    -- Measurement report
    measurementReport            MeasurementReport            OPTIONAL,
    failureCause                 FailureCauseWithProtErr        OPTIONAL
}

-- IE definitions

CalculationTimeForCiphering ::= SEQUENCE {
    cell-Id                    CellIdentity,
    sfn                        INTEGER (0..4095)
}

CipheringInfoPerRB ::=          SEQUENCE {
    dl-HFN                    BIT STRING (SIZE (20..25)),

```

```

    ul-HFN                                BIT STRING (SIZE (20..25))
}

CipheringInfoPerRB-r4 ::=                SEQUENCE {
    rb-Identity                            RB-Identity,
    dl-HFN                                BIT STRING (SIZE (20..25)),
    dl-UM-SN                              BIT STRING (SIZE (7))                OPTIONAL,
    ul-HFN                                BIT STRING (SIZE (20..25))
}

-- TABULAR: CipheringInfoPerRB-List, multiplicity value numberOfRadioBearers
-- has been replaced with maxRB.
CipheringInfoPerRB-List ::=              SEQUENCE (SIZE (1..maxRB)) OF
                                          CipheringInfoPerRB

CipheringInfoPerRB-List-r4 ::=            SEQUENCE (SIZE (1..maxRB)) OF
                                          CipheringInfoPerRB-r4

CipheringStatus ::=                      ENUMERATED {
                                          started, notStarted }

CipheringStatusList-r4 ::=                SEQUENCE (SIZE (1..maxCNdomains)) OF
                                          CipheringStatusCNdomain-r4

CipheringStatusCNdomain-r4 ::=            SEQUENCE {
    cn-DomainIdentity                      CN-DomainIdentity,
    cipheringStatus                        CipheringStatus,
    start-Value                            START-Value
}

CN-DomainInformation-v390ext ::=           SEQUENCE {
    cn-DRX-CycleLengthCoeff               CN-DRX-CycleLengthCoefficient
}

CN-DomainInformationList-v390ext ::=       SEQUENCE (SIZE (1..maxCNdomains)) OF
                                          CN-DomainInformation-v390ext

CompressedModeMeasCapability-r4 ::=       SEQUENCE {
    fdd-Measurements                       BOOLEAN,
    -- TABULAR: The IEs tdd-Measurements, gsm-Measurements and multiCarrierMeasurements
    -- are made optional since they are conditional based on another information element.
    -- Their absence corresponds to the case where the condition is not true.
    tdd384-Measurements                    BOOLEAN                OPTIONAL,
    tdd128-Measurements                    BOOLEAN                OPTIONAL,
    gsm-Measurements                       GSM-Measurements        OPTIONAL,
    multiCarrierMeasurements                BOOLEAN                OPTIONAL
}

COUNT-C-List ::=                        SEQUENCE (SIZE (1..maxCNdomains)) OF
                                          COUNT-CSingle

COUNT-CSingle ::=                       SEQUENCE {
    cn-DomainIdentity                      CN-DomainIdentity,
    count-C                                BIT STRING (SIZE (32))
}

DL-PhysChCapabilityFDD-r4 ::=             SEQUENCE {
    maxNoDPCH-PDSCH-Codes                  INTEGER (1..8),
    maxNoPhysChBitsReceived                MaxNoPhysChBitsReceived,
    supportForSF-512                       BOOLEAN,
    supportOfPDSCH                          BOOLEAN,
    simultaneousSCCPCH-DPCH-Reception       SimultaneousSCCPCH-DPCH-Reception,
    supportOfDedicatedPilotsForChEstimation SupportOfDedicatedPilotsForChEstimation    OPTIONAL
}

```

CHANGE REQUEST

25.331 CR 1864 # rev 3 # Current version: 5.3.0

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the # symbols.

Proposed change affects: UICC apps ME Radio Access Network Core Network

Title:	# ASN.1 corrections concerning missing UE capability extensions		
Source:	# Ericsson		
Work item code:	# TEI-4	Date:	# 27/02/2002
Category:	# F	Release:	# REL-5
	Use <u>one</u> of the following categories:		Use <u>one</u> of the following releases:
	F (correction)		2 (GSM Phase 2)
	A (corresponds to a correction in an earlier release)		R96 (Release 1996)
	B (addition of feature),		R97 (Release 1997)
	C (functional modification of feature)		R98 (Release 1998)
	D (editorial modification)		R99 (Release 1999)
	Detailed explanations of the above categories can be found in 3GPP TR 21.900 .		Rel-4 (Release 4)
			Rel-5 (Release 5)
			Rel-6 (Release 6)

Reason for change:	# The original version of this CR includes the following changes: <ul style="list-style-type: none"> • Included in section "Summary of change" (see below)
Summary of change:	# The original version of this CR includes the following changes: <p><u>Addition of missing extensions</u></p> <ul style="list-style-type: none"> • The release 4 extensions to UE radio access capabilities except for access stratum release indicator have been added to the INTER RAT HANDOVER INFO and the SRNS RELOCATION INFO messages to align with the tabular format. This change is performed by merging these extension that were included in UE-RadioAccessCapability-r4-ext with the access stratum release indicator into IE UE-RadioAccessCapability-v4xyext. Furthermore, some changes were performed concerning the optionality of the information in order to reduce the overhead: <ul style="list-style-type: none"> ○ The optionality is removed for the extension formerly included in IE UE-RadioAccessCapability-r4-ext because the PDCP capability might as well be included always ○ An optionality bit has been introduced for extensions that are TDD specific ○ The access stratum release indicator is made optional so the same type can be used in all messages (rather than specifying all constraints in ASN.1 by defining a specific type without this IE for the RRC CONNECTION SETUP COMPLETE message) • The release 5 extensions to UE radio access capabilities are added to the INTER RAT HANDOVER INFO, the RRC CONNECTION SETUP COMPLETE and the SRNS RELOCATION INFO messages (were missing)

Note The name UE-RadioAccessCapability-v4xyext is used for the merged IE in accordance with the conventions defined in 25.921. However, there are some other r4 extensions are not in accordance with these conventions

The CR introduced a side effect on the RRC connection request message, that has been removed in revision 2 of this CR

In revision 3 of this CR, the optionality of two IEs within UE-RadioAccessCapability-v4xyext is changed to align with the release 4 version of the specification (highlighted in yellow)

Consequences if not approved:

⌘ The inconsistency between the tabular and the ASN.1 (due to an error in the ASN.1) remains

Clauses affected:

⌘ 11.2, 11.3, 11.5

Other specs affected:

Y	N		⌘
<input checked="" type="checkbox"/>	<input type="checkbox"/>	Other core specifications	
<input checked="" type="checkbox"/>	<input type="checkbox"/>	Test specifications	
<input checked="" type="checkbox"/>	<input type="checkbox"/>	O&M Specifications	

Other comments:

⌘ This is not an exact shadow CR since it includes additional corrections for the release 5 part (see above), **hence the category is set to F.**

In revision 1 of this CR the rel-5 extensions of UE radio access capability is also added to the rel-4 version of the SRNS RELOCATION INFO message. Furthermore, the rel-5 extension of UE radio access capability is added to the import lists. With these additional changes the CR should cover the changes originally proposed in R2-030230.

How to create CRs using this form:

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>. Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

11.2 PDU definitions

```

--*****
--
-- TABULAR: The message type and integrity check info are not
-- visible in this module as they are defined in the class module.
-- Also, all FDD/TDD specific choices have the FDD option first
-- and TDD second, just for consistency.
--
--*****

PDU-definitions DEFINITIONS AUTOMATIC TAGS ::=

BEGIN

--*****
--
-- IE parameter types from other modules
--
--*****

IMPORTS

-- Core Network IEs :
  CN-DomainIdentity,
  CN-InformationInfo,
  CN-InformationInfoFull,
  NAS-Message,
  PagingRecordTypeID,
-- UTRAN Mobility IEs :
  CellIdentity,
  CellIdentity-PerRL-List,
  URA-Identity,
-- User Equipment IEs :
  ActivationTime,
  C-RNTI,
  CapabilityUpdateRequirement,
  CapabilityUpdateRequirement-r4,
  CapabilityUpdateRequirement-r4-ext,
  CellUpdateCause,
  CipheringAlgorithm,
  CipheringModeInfo,
  DSCH-RNTI,
  EstablishmentCause,
  FailureCauseWithProtErr,
  FailureCauseWithProtErrTrId,
  H-RNTI,
  UESpecificBehaviourInformationIdle,
  UESpecificBehaviourInformationInterRAT,
  InitialUE-Identity,
  IntegrityProtActivationInfo,
  IntegrityProtectionModeInfo,
  N-308,
  PagingCause,
  PagingRecordList,
  ProtocolErrorIndicator,
  ProtocolErrorIndicatorWithMoreInfo,
  Rb-timer-indicator,
  RedirectionInfo,
  RejectionCause,
  ReleaseCause,
  RRC-StateIndicator,
  RRC-TransactionIdentifier,
  SecurityCapability,
  START-Value,
  STARTList,
  U-RNTI,
  U-RNTI-Short,
  UE-RadioAccessCapability,
  UE-RadioAccessCapability-r4-ext,
  UE-RadioAccessCapability-r5-ext,
  UE-RadioAccessCapability-v370ext,
  UE-RadioAccessCapability-v380ext,
  UE-RadioAccessCapability-v3a0ext,
  UE-RadioAccessCapability-v4xyext,
  UE-RadioAccessCapability-v5xyext,

```

```

DL-PhysChCapabilityFDD-v380ext,
UE-ConnTimersAndConstants,
UE-ConnTimersAndConstants-v3a0ext,
UE-ConnTimersAndConstants-r5,
UE-SecurityInformation,
URA-UpdateCause,
UTRAN-DRX-CycleLengthCoefficient,
WaitTime,
-- Radio Bearer IEs :
DefaultConfigIdentity,
DefaultConfigIdentity-r4,
DefaultConfigMode,
DL-CounterSynchronisationInfo,
DL-CounterSynchronisationInfo-r5,
PredefinedConfigIdentity,
PredefinedConfigStatusList,
RAB-Info,
RAB-Info-Post,
RAB-InformationList,
RAB-InformationReconfigList,
RAB-InformationSetupList,
RAB-InformationSetupList-r4,
RB-ActivationTimeInfoList,
RB-COUNT-C-InformationList,
RB-COUNT-C-MSB-InformationList,
RB-IdentityList,
RB-InformationAffectedList,
RB-InformationAffectedList-r5,
RB-InformationReconfigList,
RB-InformationReconfigList-r4,
RB-InformationReconfigList-r5,
RB-InformationReleaseList,
RB-PDCPContextRelocationList,
SRB-InformationSetupList,
SRB-InformationSetupList2,
UL-CounterSynchronisationInfo,
-- Transport Channel IEs:
CPCH-SetID,
DL-AddReconfTransChInfo2List,
DL-AddReconfTransChInfoList,
DL-AddReconfTransChInfoList-r4,
DL-AddReconfTransChInfoList-r5,
DL-CommonTransChInfo,
DL-CommonTransChInfo-r4,
DL-DeletedTransChInfoList,
DL-DeletedTransChInfoList-r5,
DRAC-StaticInformationList,
TFC-Subset,
TFCS-Identity,
UL-AddReconfTransChInfoList,
UL-CommonTransChInfo,
UL-CommonTransChInfo-r4,
UL-DeletedTransChInfoList,
-- Physical Channel IEs :
Alpha,
CCTrCH-PowerControlInfo,
CCTrCH-PowerControlInfo-r4,
ConstantValue,
ConstantValueTdd,
CPCH-SetInfo,
DL-CommonInformation,
DL-CommonInformation-r4,
DL-CommonInformationPost,
DL-HSPDSCH-Information,
DL-InformationPerRL,
DL-InformationPerRL-List,
DL-InformationPerRL-List-r4,
DL-InformationPerRL-List-r5,
DL-InformationPerRL-ListPostFDD,
DL-InformationPerRL-PostTDD,
DL-InformationPerRL-PostTDD-LCR-r4,
DL-PDSCH-Information,
DPC-Mode,
DPCH-CompressedModeStatusInfo,
FrequencyInfo,
FrequencyInfoFDD,
FrequencyInfoTDD,
MaxAllowedUL-TX-Power,

```

```

OpenLoopPowerControl-IPDL-TDD-r4,
PDSCH-CapacityAllocationInfo,
PDSCH-CapacityAllocationInfo-r4,
PDSCH-Identity,
PrimaryCPICH-Info,
PrimaryCCPCH-TX-Power,
PUSCH-CapacityAllocationInfo,
PUSCH-CapacityAllocationInfo-r4,
PUSCH-Identity,
RL-AdditionInformationList,
RL-RemovalInformationList,
SpecialBurstScheduling,
SSDT-Information,
TFC-ControlDuration,
SSDT-UL-r4,
TimeslotList,
TimeslotList-r4,
TX-DiversityMode,
UL-ChannelRequirement,
UL-ChannelRequirement-r4,
UL-ChannelRequirement-r5,
UL-ChannelRequirementWithCPCH-SetID,
UL-ChannelRequirementWithCPCH-SetID-r4,
UL-ChannelRequirementWithCPCH-SetID-r5,
UL-DPCH-Info,
UL-DPCH-Info-r4,
UL-DPCH-InfoPostFDD,
UL-DPCH-InfoPostTDD,
UL-DPCH-InfoPostTDD-LCR-r4,
UL-SynchronisationParameters-r4,
UL-TimingAdvance,
UL-TimingAdvanceControl,
UL-TimingAdvanceControl-r4,
-- Measurement IEs :
AdditionalMeasurementID-List,
DeltaRSCP,
Frequency-Band,
EventResults,
Inter-FreqEventCriteriaList-v5xyext,
Intra-FreqEventCriteriaList-v5xyext,
IntraFreqReportingCriteria-lb-r5ext,
InterFreqEventResults-LCR-r4-ext,
InterRAT-TargetCellDescription,
MeasuredResults,
MeasuredResults-v390ext,
MeasuredResults-v5xyext,
MeasuredResultsList,
MeasuredResultsList-LCR-r4-ext,
MeasuredResultsOnRACH,
MeasurementCommand,
MeasurementCommand-r4,
MeasurementIdentity,
MeasurementReportingMode,
PrimaryCCPCH-RSCP,
SFN-Offset-Validity,
TimeslotListWithISCP,
TrafficVolumeMeasuredResultsList,
UE-Positioning-GPS-AssistanceData,
UE-Positioning-Measurement-v390ext,
UE-Positioning-OTDOA-AssistanceData,
UE-Positioning-OTDOA-AssistanceData-r4ext,
UE-Positioning-OTDOA-AssistanceData-UEB,
UE-Positioning-IPDL-Parameters-TDD-r4-ext,
-- Other IEs :
BCCH-ModificationInfo,
CDMA2000-MessageList,
GSM-MessageList,
InterRAT-ChangeFailureCause,
InterRAT-HO-FailureCause,
InterRAT-UE-RadioAccessCapabilityList,
InterRAT-UE-SecurityCapList,
IntraDomainNasNodeSelector,
ProtocolErrorMoreInformation,
Rplmn-Information,
Rplmn-Information-r4,
SegCount,
SegmentIndex,
SFN-Prime,
SIB-Data-fixed,

```



```

    SIB-Data-variable,
    SIB-Type
FROM InformationElements

```

```

    maxSIBperMsg
FROM Constant-definitions;

```

<Skipped until the next modified section>

```

-- *****
--
-- INTER RAT HANDOVER INFO
--
-- *****

InterRATHandoverInfo ::= SEQUENCE {
    -- This structure is defined for historical reasons, backward compatibility with 04.18
    predefinedConfigStatusList CHOICE {
        absent NULL,
        present PredefinedConfigStatusList
    },
    ue-SecurityInformation CHOICE {
        absent NULL,
        present UE-SecurityInformation
    },
    ue-CapabilityContainer CHOICE {
        absent NULL,
        -- present is an octet aligned string containing IE UE-RadioAccessCapabilityInfo
        present OCTET STRING (SIZE (0..63))
    },
    -- Non critical extensions
    v390NonCriticalExtensions CHOICE {
        absent NULL,
        present SEQUENCE {
            interRATHandoverInfo-v390ext InterRATHandoverInfo-v390ext-IEs,
            v3a0NonCriticalExtensions SEQUENCE {
                interRATHandoverInfo-v3a0ext InterRATHandoverInfo-v3a0ext,
                laterNonCriticalExtensions SEQUENCE {
                    interRATHandoverInfo-v3d0ext InterRATHandoverInfo-v3d0ext-IEs,
                    -- Container for additional R99 extensions
                    interRATHandoverInfo-r3-add-ext BIT STRING OPTIONAL,
                    v4xyNonCriticalExtensions SEQUENCE {
                        interRATHandoverInfo-v4xyext InterRATHandoverInfo-v4xyext-IEs,
                        v5xyNonCriticalExtensions SEQUENCE {
                            interRATHandoverInfo-v5xyext InterRATHandoverInfo-v5xyext-IEs,
                            -- Reserved for future non critical extension
                            nonCriticalExtensions SEQUENCE {} OPTIONAL
                        } OPTIONAL
                    } OPTIONAL
                } OPTIONAL
            } OPTIONAL
        } OPTIONAL
    }
}

InterRATHandoverInfo-v390ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v380ext UE-RadioAccessCapability-v380ext OPTIONAL,
    dl-PhysChCapabilityFDD-v380ext DL-PhysChCapabilityFDD-v380ext
}

InterRATHandoverInfo-v3a0ext ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v3a0ext UE-RadioAccessCapability-v3a0ext OPTIONAL
}

InterRATHandoverInfo-v3d0ext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ueSpecificBehaviourInformationInterRAT UESpecificBehaviourInformationInterRAT
    OPTIONAL
}

InterRATHandoverInfo-v4xyext-IEs ::= SEQUENCE {
    -- User equipment IEs
    ue-RadioAccessCapability-v4xyext UE-RadioAccessCapability-v4xyext
}

```

```

InterRATHandoverInfo-v5xyext-IEs ::= SEQUENCE {
  -- User equipment IEs
  ue-RadioAccessCapability-v5xyext  UE-RadioAccessCapability-v5xyext
}

```

<Skipped until the next modified section>

```

-- *****
--
-- RRC CONNECTION REQUEST
--
-- *****

```

```

RRCConnectionRequest ::= SEQUENCE {
  -- TABULAR: Integrity protection shall not be performed on this message.
  -- User equipment IEs
  initialUE-Identity          InitialUE-Identity,
  establishmentCause          EstablishmentCause,
  -- protocolErrorIndicator is MD, but for compactness reasons no default value
  -- has been assigned to it.
  protocolErrorIndicator      ProtocolErrorIndicator,
  -- Measurement IEs
  measuredResultsOnRACH       MeasuredResultsOnRACH          OPTIONAL,
  -- Non critical Extensions
  v3d0NonCriticalExtensions   SEQUENCE {
    rrcConnectionRequest-v3d0ext  RRCConnectionRequest-v3d0ext-IEs,
    -- Reserved for future non critical extension
    v4xyNonCriticalExtensions     SEQUENCE {
      rrcConnectionRequest-v4xyext  RRCConnectionRequest-v4xyext-IEs,
      -- Reserved for future non critical extension
      nonCriticalExtensions         SEQUENCE {}          OPTIONAL
    } OPTIONAL
  } OPTIONAL
}

```

```

RRCConnectionRequest-v3d0ext-IEs ::= SEQUENCE {
  -- User equipment IEs
  uESpecificBehaviourInformationIdle  UESpecificBehaviourInformationIdle  OPTIONAL
}

```

```

RRCConnectionRequest-v4xyext-IEs ::= SEQUENCE {
  -- User equipment IEs
  ue-RadioAccessCapability-v4xyext UE-RadioAccessCapability-v4xyext
  accessStratumReleaseIndicator      AccessStratumReleaseIndicator
}

```

```

-- *****
--
-- RRC CONNECTION SETUP COMPLETE
--
-- *****

```

```

RRCConnectionSetupComplete ::= SEQUENCE {
  -- TABULAR: Integrity protection shall not be performed on this message.
  -- User equipment IEs
  rrc-TransactionIdentifier    RRC-TransactionIdentifier,
  startList                    STARTList,
  ue-RadioAccessCapability     UE-RadioAccessCapability          OPTIONAL,
  -- Other IEs
  ue-RATSpecificCapability     InterRAT-UE-RadioAccessCapabilityList  OPTIONAL,
  -- Non critical extensions
  v370NonCriticalExtensions    SEQUENCE {
    rrcConnectionSetupComplete-v370ext  RRCConnectionSetupComplete-v370ext,
    v380NonCriticalExtensions          SEQUENCE {
      rrcConnectionSetupComplete-v380ext  RRCConnectionSetupComplete-v380ext-IEs,
      -- Reserved for future non critical extension
      v3a0NonCriticalExtensions          SEQUENCE {
        rrcConnectionSetupComplete-v3a0ext  RRCConnectionSetupComplete-v3a0ext,
        laterNonCriticalExtensions         SEQUENCE {
          -- Container for additional R99 extensions
          rrcConnectionSetupComplete-r3-add-ext  BIT STRING          OPTIONAL,
          v4xyNonCriticalExtensions          SEQUENCE {
            rrcConnectionSetupComplete-v4xyext  RRCConnectionSetupComplete-v4xyext-IEs,
            v5xyNonCriticalExtensions          SEQUENCE {
            rrcConnectionSetupComplete-v5xyext      RRCConnectionSetupComplete-
v5xyext-IEs,
            nonCriticalExtensions          SEQUENCE {}          OPTIONAL
          }
        }
      }
    }
  }
}

```

```

    } OPTIONAL
  } OPTIONAL
} OPTIONAL

RRCConnectionSetupComplete-v370ext ::= SEQUENCE {
  -- User equipment IEs
  ue-RadioAccessCapability-v370ext  UE-RadioAccessCapability-v370ext  OPTIONAL
}

RRCConnectionSetupComplete-v380ext-IEs ::= SEQUENCE {
  -- User equipment IEs
  ue-RadioAccessCapability-v380ext  UE-RadioAccessCapability-v380ext  OPTIONAL,
  dl-PhysChCapabilityFDD-v380ext    DL-PhysChCapabilityFDD-v380ext
}

RRCConnectionSetupComplete-v3a0ext ::= SEQUENCE {
  -- User equipment IEs
  ue-RadioAccessCapability-v3a0ext  UE-RadioAccessCapability-v3a0ext  OPTIONAL
}

RRCConnectionSetupComplete-v4xyext-IEs ::= SEQUENCE {
  -- User equipment IEs
  ue-RadioAccessCapability-r4-v4xyext  UE-RadioAccessCapability-r4-v4xyext OPTIONAL
}

```

```

RRCConnectionSetupComplete-v5xyext-IEs ::= SEQUENCE {
  -- User equipment IEs
  ue-RadioAccessCapability-v5xyext  UE-RadioAccessCapability-v5xyext
}

```

<Skipped until the next modified section>

```

-- *****
--
-- UE CAPABILITY INFORMATION
--
-- *****

```

```

UECapabilityInformation ::= SEQUENCE {
  -- User equipment IEs
  rrc-TransactionIdentifier  RRC-TransactionIdentifier  OPTIONAL,
  ue-RadioAccessCapability  UE-RadioAccessCapability  OPTIONAL,
  -- Other IEs
  ue-RATSpecificCapability  InterRAT-UE-RadioAccessCapabilityList
OPTIONAL,
  v370NonCriticalExtensions  SEQUENCE {
    ueCapabilityInformation-v370ext  UECapabilityInformation-v370ext,
    v380NonCriticalExtensions  SEQUENCE {
      ueCapabilityInformation-v380ext  UECapabilityInformation-v380ext-IEs,
      v3a0NonCriticalExtensions  SEQUENCE {
        ueCapabilityInformation-v3a0ext  UECapabilityInformation-v3a0ext,
        laterNonCriticalExtensions  SEQUENCE {
          -- Container for additional R99 extensions
          ueCapabilityInformation-r3-add-ext  BIT STRING  OPTIONAL,
          -- Reserved for future non critical extension
          v4xyNonCriticalExtensions  SEQUENCE {
            ueCapabilityInformation-v4xyext  UECapabilityInformation-v4xyext,
            v5xyNonCriticalExtensions  SEQUENCE {
              ueCapabilityInformation-v5xyext  UECapabilityInformation-v5xyext,
              nonCriticalExtensions  SEQUENCE {}  OPTIONAL
            } OPTIONAL
          } OPTIONAL
        } OPTIONAL
      } OPTIONAL
    } OPTIONAL
  } OPTIONAL
} OPTIONAL

```

```

UECapabilityInformation-v370ext ::= SEQUENCE {
  -- User equipment IEs
  ue-RadioAccessCapability-v370ext  UE-RadioAccessCapability-v370ext  OPTIONAL
}

```

```

UECapabilityInformation-v380ext-IEs ::= SEQUENCE {
  -- User equipment IEs

```

```

        ue-RadioAccessCapability-v380ext      UE-RadioAccessCapability-v380ext
OPTIONAL,
        dl-PhysChCapabilityFDD-v380ext      DL-PhysChCapabilityFDD-v380ext
    }
UECapabilityInformation-v3a0ext ::= SEQUENCE {
    -- User equipment IEs
        ue-RadioAccessCapability-v3a0ext      UE-RadioAccessCapability-v3a0ext      OPTIONAL
    }
UECapabilityInformation-v4xyext ::= SEQUENCE {
    -- User equipment IEs
ue-RadioAccessCapability-r4-ext      UE-RadioAccessCapability-r4-ext      OPTIONAL,
        ue-RadioAccessCapability-v4xyext      UE-RadioAccessCapability-v4xyext
    }
UECapabilityInformation-v5xyext ::= SEQUENCE {
    -- User equipment IEs
        ue-RadioAccessCapability-r5-ext      UE-RadioAccessCapability-r5-ext      OPTIONAL
    }

```

11.3 Information element definitions

<Skipped until the next modified section>

```

-- *****
--
--     USER EQUIPMENT INFORMATION ELEMENTS (10.3.3)
--
-- *****

UE-PowerClass-v370 ::=          ENUMERATED {class1, class2, class3, class4,
                                     spare4, spare3, spare2, spare1 }

UE-RadioAccessCapability ::=    SEQUENCE {
  pdcp-Capability              PDCP-Capability,
  rlc-Capability               RLC-Capability,
  transportChannelCapability    TransportChannelCapability,
  rf-Capability                RF-Capability,
  physicalChannelCapability     PhysicalChannelCapability,
  ue-MultiModeRAT-Capability    UE-MultiModeRAT-Capability,
  securityCapability           SecurityCapability,
  ue-positioning-Capability     UE-Positioning-Capability,
  measurementCapability        MeasurementCapability          OPTIONAL
}

UE-RadioAccessCapabilityInfo ::= SEQUENCE {
  ue-RadioAccessCapability      UE-RadioAccessCapability,
  ue-RadioAccessCapability-v370ext UE-RadioAccessCapability-v370ext
}

UE-RadioAccessCapability-v370ext ::= SEQUENCE {
  ue-RadioAccessCapabBandFDDList UE-RadioAccessCapabBandFDDList
}

UE-RadioAccessCapability-v380ext ::= SEQUENCE {
  ue-PositioningCapabilityExt-v380 UE-PositioningCapabilityExt-v380
}

UE-RadioAccessCapability-v3a0ext ::= SEQUENCE {
  ue-PositioningCapabilityExt-v3a0 UE-PositioningCapabilityExt-v3a0
}

UE-PositioningCapabilityExt-v380 ::= SEQUENCE {
  rx-tx-TimeDifferenceType2Capable BOOLEAN
}

UE-PositioningCapabilityExt-v3a0 ::= SEQUENCE {
  validity-CellPCH-UraPCH          ENUMERATED { true }
}

UE-RadioAccessCapabBandFDDList ::= SEQUENCE (SIZE (1..maxFreqBandsFDD)) OF
                                     UE-RadioAccessCapabBandFDD

UE-RadioAccessCapabBandFDD ::= SEQUENCE{
  radioFrequencyBandFDD          RadioFrequencyBandFDD,
  fddRF-Capability               SEQUENCE {
    ue-PowerClass                UE-PowerClass-v370,
    txRxFrequencySeparation      TxRxFrequencySeparation
  }
  measurementCapability          MeasurementCapability-v370          OPTIONAL,
}

UE-RadioAccessCapability-r4-v4xyext ::= SEQUENCE {
  pdcp-Capability-r4-ext         PDCP-Capability-r4-ext,
  tdd-CapabilityExt              SEQUENCE {
    rf-Capability                RF-Capability-r4-ext,
    physicalChannelCapability-LCR PhysicalChannelCapability-LCR-r4,
    measurementCapability-r4-ext  MeasurementCapability-r4-ext OPTIONAL
  }
  -- IE " AccessStratumReleaseIndicator" is not needed in RRC CONNECTION SETUP COMPLETE
  accessStratumReleaseIndicator AccessStratumReleaseIndicator OPTIONAL
}

UE-RadioAccessCapability-v4xyext ::= SEQUENCE {
-- R99 UEs shall include IE "ue-TestLevelIndicator"
accessStratumReleaseIndicator AccessStratumReleaseIndicator

```

†

```

UE-RadioAccessCapability-r5-v5xyext ::= SEQUENCE {
  dl-CapabilityWithSimultaneousHS-DSCHConfig DL-CapabilityWithSimultaneousHS-DSCHConfig
  OPTIONAL,
  pdcp-Capability-r5-ext                      PDCP-Capability-r5-ext,
  rlc-Capability-r5-ext                       RLC-Capability-r5-ext,
  physicalChannelCapability                   PhysicalChannelCapability-hspdsch-r5
}

UL-PhysChCapabilityFDD ::= SEQUENCE {
  maxNoDPDCH-BitsTransmitted                MaxNoDPDCH-BitsTransmitted,
  supportOfPCPCH                             BOOLEAN
}

UL-PhysChCapabilityTDD ::= SEQUENCE {
  maxTS-PerFrame                             MaxTS-PerFrame,
  maxPhysChPerTimeslot                       MaxPhysChPerTimeslot,
  minimumSF                                  MinimumSF-UL,
  supportOfPUSCH                             BOOLEAN
}

UL-PhysChCapabilityTDD-LCR-r4 ::= SEQUENCE {
  maxTS-PerSubFrame                          MaxTS-PerSubFrame-r4,
  maxPhysChPerTimeslot                       MaxPhysChPerTimeslot,
  minimumSF                                  MinimumSF-UL,
  supportOfPUSCH                             BOOLEAN,
  supportOf8PSK                              BOOLEAN
}

```

11.5 RRC information between network nodes

```
Internode-definitions DEFINITIONS AUTOMATIC TAGS ::=
```

```
BEGIN
```

```
IMPORTS
```

```
    HandoverToUTRANCommand,
    MeasurementReport,
    PhysicalChannelReconfiguration,
    RadioBearerReconfiguration,
    RadioBearerRelease,
    RadioBearerSetup,
    RRC-FailureInfo-r3-IEs,
    TransportChannelReconfiguration
FROM PDU-definitions
```

```
-- Core Network IEs :
    CN-DomainIdentity,
    CN-DomainInformationList,
    CN-DomainInformationListFull,
    CN-DRX-CycleLengthCoefficient,
    NAS-SystemInformationGSM-MAP,
-- UTRAN Mobility IEs :
    CellIdentity,
    URA-Identity,
-- User Equipment IEs :
    AccessStratumReleaseIndicator,
    C-RNTI,
    ChipRateCapability,
    DL-PhysChCapabilityFDD-v380ext,
    DL-PhysChCapabilityTDD,
    DL-PhysChCapabilityTDD-LCR-r4,
    GSM-Measurements,
    FailureCauseWithProtErr,
    MaxHcContextSpace,
    MaxNoPhysChBitsReceived,
    MaxROHC-ContextSessions-r4,
    NetworkAssistedGPS-Supported,
    RadioFrequencyBandTDDList,
    RLC-Capability,
    RRC-MessageSequenceNumber,
    SecurityCapability,
    SimultaneousSCCPCH-DPCH-Reception,
    STARTList,
    STARTSingle,
    START-Value,
    SupportOfDedicatedPilotsForChEstimation,
    TransportChannelCapability,
    TxRxFrequencySeparation,
    U-RNTI,
    UE-MultiModeRAT-Capability,
    UE-PowerClass-v370,
    UE-RadioAccessCapabBandFDDList,
    UE-RadioAccessCapability,
    UE-RadioAccessCapability-v370ext,
    UE-RadioAccessCapability-v380ext,
    UE-RadioAccessCapability-v3a0ext,
    UE-RadioAccessCapability-v4xyext,
    UE-RadioAccessCapability-v5xyext,
    UL-PhysChCapabilityFDD,
    UL-PhysChCapabilityTDD,
    UL-PhysChCapabilityTDD-LCR-r4,
-- Radio Bearer IEs :
    PredefinedConfigStatusList,
    PredefinedConfigValueTag,
    RAB-InformationSetupList,
    RAB-InformationSetupList-r4,
    RAB-Identity,
    RB-Identity,
    RB-Identity,
    SRB-InformationSetupList,
-- Transport Channel IEs :
    CPCH-SetID,
    DL-CommonTransChInfo,
```

```

DL-CommonTransChInfo-r4,
DL-AddReconfTransChInfoList,
DL-AddReconfTransChInfoList-r4,
DRAC-StaticInformationList,
UL-CommonTransChInfo,
UL-CommonTransChInfo-r4,
UL-AddReconfTransChInfoList,
-- Measurement IEs :
MeasurementIdentity,
MeasurementReportingMode,
MeasurementType,
MeasurementType-r4,
AdditionalMeasurementID-List,
PositionEstimate,
-- Other IEs :
InterRAT-UE-RadioAccessCapabilityList,
UESpecificBehaviourInformationIdle,
UESpecificBehaviourInformationInterRAT

```

FROM InformationElements

```

maxCNdomains,
maxNoOfMeas,

maxRB,
maxRBallRABs,
maxRFC3095-CID,
maxSRBsetup

```

FROM Constant-definitions

;

<Skipped until the next modified section>

```

-- *****
--
-- SRNC Relocation information
--
-- *****

```

```

SRNC-RelocationInfo-r3 ::= CHOICE {
  r3 SEQUENCE {
    sRNC-RelocationInfo-r3 SRNC-RelocationInfo-r3-IEs,
    v380NonCriticalExtensions SEQUENCE {
      sRNC-RelocationInfo-v380ext SRNC-RelocationInfo-v380ext-IEs,
      -- Reserved for future non critical extension
      v390NonCriticalExtensions SEQUENCE {
        sRNC-RelocationInfo-v390ext SRNC-RelocationInfo-v390ext-IEs,
        v3a0NonCriticalExtensions SEQUENCE {
          sRNC-RelocationInfo-v3a0ext SRNC-RelocationInfo-v3a0ext-IEs,
          v3b0NonCriticalExtensions SEQUENCE {
            sRNC-RelocationInfo-v3b0ext SRNC-RelocationInfo-v3b0ext-IEs,
            v3c0NonCriticalExtensions SEQUENCE {
              sRNC-RelocationInfo-v3c0ext SRNC-RelocationInfo-v3c0ext-IEs,
              laterNonCriticalExtensions SEQUENCE {
                sRNC-RelocationInfo-v3d0ext SRNC-RelocationInfo-v3d0ext-
IEs,
                -- Container for additional R99 extensions
                sRNC-RelocationInfo-r3-add-ext BIT STRING OPTIONAL,
                v4xyNonCriticalExtensions SEQUENCE {
                  sRNC-RelocationInfo-v4xyext SRNC-RelocationInfo-
v4xyext-IEs,
                  v5xyNonCriticalExtensions SEQUENCE {
                    sRNC-RelocationInfo-v5xyext SRNC-RelocationInfo-
v5xyext-IEs,
                    -- Reserved for future non critical extension
                    nonCriticalExtensions SEQUENCE {} OPTIONAL
                  } OPTIONAL
                } OPTIONAL
              } OPTIONAL
            } OPTIONAL
          } OPTIONAL
        } OPTIONAL
      } OPTIONAL
    } OPTIONAL
  },
  later-than-r3 CHOICE {
    r4 SEQUENCE {
      sRNC-RelocationInfo-r4 SRNC-RelocationInfo-r4-IEs,

```



```

    v5xyNonCriticalExtensions SEQUENCE {
      SRNC-RelocationInfo-v5xyext SRNC-RelocationInfo-v5xyext-IEs,
      nonCriticalExtensions SEQUENCE {} OPTIONAL
    } OPTIONAL
  },
  criticalExtensions SEQUENCE {}
}

SRNC-RelocationInfo-r3-IEs ::= SEQUENCE {
  -- Non-RRC IEs
  stateOfRRC StateOfRRC,
  stateOfRRC-Procedure StateOfRRC-Procedure,
  -- Ciphering related information IEs
  -- If the extension v380 is included use the extension for the ciphering status per CN domain
  cipheringStatus CipheringStatus,
  calculationTimeForCiphering CalculationTimeForCiphering OPTIONAL,
  -- The order of occurrence in the IE cipheringInfoPerRB-List is the
  -- same as the RBs in the IE "Signalling RB information list" and in the
  -- IE "RAB information list". The signalling RBs are supposed to be listed
  -- first. Only UM and AM RBs that are ciphered are listed here
  cipheringInfoPerRB-List CipheringInfoPerRB-List OPTIONAL,
  count-C-List COUNT-C-List OPTIONAL,
  integrityProtectionStatus IntegrityProtectionStatus,
  -- The order of occurrence in the IE srb-SpecificIntegrityProtInfo is the
  -- same as the SRBs in the IE "Signalling RB information list"
  srb-SpecificIntegrityProtInfo SRB-SpecificIntegrityProtInfoList,
  implementationSpecificParams ImplementationSpecificParams OPTIONAL,
  -- User equipment IEs
  u-RNTI U-RNTI,
  c-RNTI C-RNTI OPTIONAL,
  ue-RadioAccessCapability UE-RadioAccessCapability,
  ue-Positioning-LastKnownPos UE-Positioning-LastKnownPos OPTIONAL,
  -- Other IEs
  ue-RATSpecificCapability InterRAT-UE-RadioAccessCapabilityList OPTIONAL,
  -- UTRAN mobility IEs
  ura-Identity URA-Identity OPTIONAL,
  -- Core network IEs
  cn-CommonGSM-MAP-NAS-SysInfo NAS-SystemInformationGSM-MAP,
  cn-DomainInformationList CN-DomainInformationList OPTIONAL,
  -- Measurement IEs
  ongoingMeasRepList OngoingMeasRepList OPTIONAL,
  -- Radio bearer IEs
  predefinedConfigStatusList PredefinedConfigStatusList,
  srb-InformationList SRB-InformationSetupList,
  rab-InformationList RAB-InformationSetupList OPTIONAL,
  -- Transport channel IEs
  ul-CommonTransChInfo UL-CommonTransChInfo OPTIONAL,
  ul-TransChInfoList UL-AddReconfTransChInfoList OPTIONAL,
  modeSpecificInfo CHOICE {
    fdd SEQUENCE {
      cpch-SetID CPCH-SetID OPTIONAL,
      transChDRAC-Info DRAC-StaticInformationList OPTIONAL
    },
    tdd NULL
  },
  dl-CommonTransChInfo DL-CommonTransChInfo OPTIONAL,
  dl-TransChInfoList DL-AddReconfTransChInfoList OPTIONAL,
  -- Measurement report
  measurementReport MeasurementReport OPTIONAL
}

SRNC-RelocationInfo-v380ext-IEs ::= SEQUENCE {
  -- Ciphering related information IEs
  cn-DomainIdentity CN-DomainIdentity,
  cipheringStatusList CipheringStatusList
}

SRNC-RelocationInfo-v390ext-IEs ::= SEQUENCE {
  cn-DomainInformationList-v390ext CN-DomainInformationList-v390ext OPTIONAL,
  ue-RadioAccessCapability-v370ext UE-RadioAccessCapability-v370ext OPTIONAL,
  ue-RadioAccessCapability-v380ext UE-RadioAccessCapability-v380ext OPTIONAL,
  dl-PhysChCapabilityFDD-v380ext DL-PhysChCapabilityFDD-v380ext,
  failureCauseWithProtErr FailureCauseWithProtErr OPTIONAL
}

SRNC-RelocationInfo-v3a0ext-IEs ::= SEQUENCE {
  -- cn-domain identity for IE startValueForCiphering-v3a0ext is specified

```

```

-- in subsequent extension (SRNC-RelocationInfo-v3b0ext-IEs)
startValueForCipherng-v3a0ext      START-Value,
cipherngInfoForSRB1-v3a0ext      CipherngInfoForSRB1-v3a0ext,
ue-RadioAccessCapability-v3a0ext  UE-RadioAccessCapability-v3a0ext      OPTIONAL
}

SRNC-RelocationInfo-v3b0ext-IEs ::= SEQUENCE {
-- cn-domain identity for IE startValueForCipherng-v3a0ext included in previous extension
cn-DomainIdentity      CN-DomainIdentity,
-- the IE startValueForCipherng-v3b0ext contains the start values for each CN Domain. The
-- value of start indicated by the IE startValueForCipherng-v3a0ext should be set to the
-- same value as the start-Value for the corresponding cn-DomainIdentity in the IE
-- startValueForCipherng-v3b0ext
startValueForCipherng-v3b0ext      STARTList2      OPTIONAL
}

SRNC-RelocationInfo-v3c0ext-IEs ::= SEQUENCE {
-- IE rb-IdentityForHOMessage includes the identity of the RB used by the source SRNC
-- to send the message contained in the IE "TargetRNC-ToSourceRNC-Container".
-- Only included if type is "UE involved"
rb-IdentityForHOMessage      RB-Identity      OPTIONAL
}

SRNC-RelocationInfo-v3d0ext-IEs ::= SEQUENCE {
-- User equipment IEs
ueSpecificBehaviourInformationIdle      UESpecificBehaviourInformationIdle      OPTIONAL,
ueSpecificBehaviourInformationInterRAT  UESpecificBehaviourInformationInterRAT
OPTIONAL
}

STARTList2 ::=
SEQUENCE (SIZE (2..maxCNdomains)) OF
STARTSingle

SRNC-RelocationInfo-v4xyext-IEs ::= SEQUENCE {
ue-RadioAccessCapability-v4xyext      UE-RadioAccessCapability-v4xyext
}

SRNC-RelocationInfo-v5xyext-IEs ::= SEQUENCE {
ue-RadioAccessCapability-v5xyext      UE-RadioAccessCapability-v5xyext
}

CipherngInfoForSRB1-v3a0ext ::= SEQUENCE {
dl-UM-SN      BIT STRING (SIZE (7))
}

CipherngStatusList ::=
SEQUENCE (SIZE (1..maxCNdomains)) OF
CipherngStatusCNdomain

CipherngStatusCNdomain ::=
SEQUENCE {
cn-DomainIdentity      CN-DomainIdentity,
cipherngStatus      CipherngStatus
}

SRNC-RelocationInfo-r4-IEs ::=
SEQUENCE {
-- Non-RRC IEs
-- IE rb-IdentityForHOMessage includes the identity of the RB used by the source SRNC
-- to send the message contained in the IE "TargetRNC-ToSourceRNC-Container".
-- Only included if type is "UE involved"
rb-IdentityForHOMessage      RB-Identity      OPTIONAL,
stateOfRRC      StateOfRRC,
stateOfRRC-Procedure      StateOfRRC-Procedure,
-- Cipherng related information IEs
cipherngStatusList      CipherngStatusList-r4,
latestConfiguredCN-Domain      CN-DomainIdentity,
calculationTimeForCipherng      CalculationTimeForCipherng      OPTIONAL,
count-C-List      COUNT-C-List      OPTIONAL,
cipherngInfoPerRB-List      CipherngInfoPerRB-List-r4      OPTIONAL,
-- Integrity protection related information IEs
integrityProtectionStatus      IntegrityProtectionStatus,
srb-SpecificIntegrityProtInfo      SRB-SpecificIntegrityProtInfoList,
implementationSpecificParams      ImplementationSpecificParams      OPTIONAL,
-- User equipment IEs
u-RNTI      U-RNTI,
c-RNTI      C-RNTI      OPTIONAL,
ue-RadioAccessCapability      UE-RadioAccessCapability-r4,
ue-RadioAccessCapability-ext      UE-RadioAccessCapabBandFDDList      OPTIONAL,
ue-Positioning-LastKnownPos      UE-Positioning-LastKnownPos      OPTIONAL,
ueSpecificBehaviourInformationIdle      UESpecificBehaviourInformationIdle      OPTIONAL,
}

```

```

        uESpecificBehaviourInformationInterRAT      UESpecificBehaviourInformationInterRAT
OPTIONAL,
-- Other IEs
  ue-RATSpecificCapability      InterRAT-UE-RadioAccessCapabilityList  OPTIONAL,
-- UTRAN mobility IEs
  ura-Identity                  URA-Identity                  OPTIONAL,
-- Core network IEs
  cn-CommonGSM-MAP-NAS-SysInfo NAS-SystemInformationGSM-MAP,
  cn-DomainInformationList     CN-DomainInformationListFull  OPTIONAL,
-- Measurement IEs
  ongoingMeasRepList           OngoingMeasRepList-r4        OPTIONAL,
-- Radio bearer IEs
  predefinedConfigStatusList   PredefinedConfigStatusList,
  srb-InformationList          SRB-InformationSetupList,
  rab-InformationList          RAB-InformationSetupList-r4   OPTIONAL,
-- Transport channel IEs
  ul-CommonTransChInfo        UL-CommonTransChInfo-r4      OPTIONAL,
  ul-TransChInfoList          UL-AddReconfTransChInfoList  OPTIONAL,
  modeSpecificInfo            CHOICE {
    fdd                        SEQUENCE {
      cpch-SetID              CPCH-SetID                    OPTIONAL,
      transChDRAC-Info        DRAC-StaticInformationList  OPTIONAL
    },
    tdd                        NULL
  }
  dl-CommonTransChInfo        DL-CommonTransChInfo-r4      OPTIONAL,
  dl-TransChInfoList          DL-AddReconfTransChInfoList-r4  OPTIONAL,
-- Measurement report
  measurementReport            MeasurementReport              OPTIONAL,
  failureCause                 FailureCauseWithProtErr        OPTIONAL
}

-- IE definitions

CalculationTimeForCiphering ::= SEQUENCE {
  cell-Id      CellIdentity,
  sfn          INTEGER (0..4095)
}

CipheringInfoPerRB ::= SEQUENCE {
  dl-HFN      BIT STRING (SIZE (20..25)),
  ul-HFN      BIT STRING (SIZE (20..25))
}

CipheringInfoPerRB-r4 ::= SEQUENCE {
  rb-Identity  RB-Identity,
  dl-HFN      BIT STRING (SIZE (20..25)),
  dl-UM-SN    BIT STRING (SIZE (7))          OPTIONAL,
  ul-HFN      BIT STRING (SIZE (20..25))
}

-- TABULAR: CipheringInfoPerRB-List, multiplicity value numberOfRadioBearers
-- has been replaced with maxRB.
CipheringInfoPerRB-List ::= SEQUENCE (SIZE (1..maxRB)) OF
  CipheringInfoPerRB

CipheringInfoPerRB-List-r4 ::= SEQUENCE (SIZE (1..maxRB)) OF
  CipheringInfoPerRB-r4

CipheringStatus ::= ENUMERATED {
  started, notStarted }

CipheringStatusList-r4 ::= SEQUENCE (SIZE (1..maxCNdomains)) OF
  CipheringStatusCNdomain-r4

CipheringStatusCNdomain-r4 ::= SEQUENCE {
  cn-DomainIdentity  CN-DomainIdentity,
  cipheringStatus    CipheringStatus,
  start-Value        START-Value
}

CN-DomainInformation-v390ext ::= SEQUENCE {
  cn-DRX-CycleLengthCoeff  CN-DRX-CycleLengthCoefficient
}

CN-DomainInformationList-v390ext ::= SEQUENCE (SIZE (1..maxCNdomains)) OF
  CN-DomainInformation-v390ext

```

```

CompressedModeMeasCapability-r4 ::= SEQUENCE {
    fdd-Measurements          BOOLEAN,
    -- TABULAR: The IEs tdd-Measurements, gsm-Measurements and multiCarrierMeasurements
    -- are made optional since they are conditional based on another information element.
    -- Their absence corresponds to the case where the condition is not true.
    tdd384-Measurements      BOOLEAN          OPTIONAL,
    tdd128-Measurements      BOOLEAN          OPTIONAL,
    gsm-Measurements         GSM-Measurements OPTIONAL,
    multiCarrierMeasurements BOOLEAN          OPTIONAL
}

COUNT-C-List ::= SEQUENCE (SIZE (1..maxCNdomains)) OF
COUNT-C-List

COUNT-C-List ::= SEQUENCE {
    cn-DomainIdentity      CN-DomainIdentity,
    count-C                BIT STRING (SIZE (32))
}

DL-PhysChCapabilityFDD-r4 ::= SEQUENCE {
    maxNoDPCH-PDSCH-Codes      INTEGER (1..8),
    maxNoPhysChBitsReceived    MaxNoPhysChBitsReceived,
    supportForSF-512           BOOLEAN,
    supportOfPDSCH             BOOLEAN,
    simultaneousSCCPCH-DPCH-Reception SimultaneousSCCPCH-DPCH-Reception,
    supportOfDedicatedPilotsForChEstimation SupportOfDedicatedPilotsForChEstimation OPTIONAL
}

```

CHANGE REQUEST

⌘ **25.331 CR 1865** ⌘ rev **-** ⌘ Current version: **4.8.0** ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

Proposed change affects: UICC apps ME Radio Access Network Core Network

Title:	⌘ Extensions for 1.28 Mcps specific elements in system information		
Source:	⌘ TSG-RAN WG2		
Work item code:	⌘ LCRTDD-L23	Date:	⌘ 03/02/2003
Category:	⌘ F	Release:	⌘ Rel-4
	Use <u>one</u> of the following categories:		Use <u>one</u> of the following releases:
	F (correction)	2	(GSM Phase 2)
	A (corresponds to a correction in an earlier release)	R96	(Release 1996)
	B (addition of feature),	R97	(Release 1997)
	C (functional modification of feature)	R98	(Release 1998)
	D (editorial modification)	R99	(Release 1999)
	Detailed explanations of the above categories can be found in 3GPP TR 21.900 .	Rel-4	(Release 4)
		Rel-5	(Release 5)
		Rel-6	(Release 6)

Reason for change: ⌘ A number of elements were included in system information for 1.28 Mcps by utilising non-critical extensions. These elements were included as mandatory elements.

As soon as further extensions are needed for e.g. FDD there is a need to include these 1.28 Mcps elements even if they are not needed.

Especially, in case of SIB11 and SIB12 this will lead to a significant overhead for FDD if no 1.28 Mcps TDD neighbours exist.

For clarity the structure that would be required to be included is shown below:

```

MeasurementControlSysInfo-LCR-r4-ext ::= SEQUENCE {
  -- CHOICE use-of-HCS shall have the same value as the use-of-HCS
  -- in MeasurementControlSysInfo
  use-of-HCS CHOICE {
    hcs-not-used SEQUENCE {
      -- CHOICE cellSelectQualityMeasure shall have the same value as
      the
      -- cellSelectQualityMeasure in MeasurementControlSysInfo
      cellSelectQualityMeasure CHOICE {
        cpich-RSCP SEQUENCE {
          intraFreqMeasurementSysInfo
          IntraFreqMeasurementSysInfo-RSCP-LCR-r4 OPTIONAL,
          interFreqMeasurementSysInfo
          InterFreqMeasurementSysInfo-RSCP-LCR-r4 OPTIONAL
        },
        cpich-Ec-N0 SEQUENCE {
          intraFreqMeasurementSysInfo
          IntraFreqMeasurementSysInfo-ECN0-LCR-r4 OPTIONAL,
          interFreqMeasurementSysInfo
          InterFreqMeasurementSysInfo-ECN0-LCR-r4 OPTIONAL
        }
      }
    },
    hcs-used SEQUENCE {
      -- CHOICE cellSelectQualityMeasure shall have the same value as
      the
  
```

```

-- cellSelectQualityMeasure in MeasurementControlSysInfo
cellSelectQualityMeasure CHOICE {
  cpich-RSCP SEQUENCE {
    intraFreqMeasurementSysInfo
    IntraFreqMeasurementSysInfo-HCS-RSCP-LCR-r4 OPTIONAL,
    interFreqMeasurementSysInfo
    InterFreqMeasurementSysInfo-HCS-RSCP-LCR-r4 OPTIONAL
  },
  cpich-Ec-N0 SEQUENCE {
    intraFreqMeasurementSysInfo
    IntraFreqMeasurementSysInfo-HCS-ECN0-LCR-r4 OPTIONAL,
    interFreqMeasurementSysInfo
    InterFreqMeasurementSysInfo-HCS-ECN0-LCR-r4 OPTIONAL
  }
}
}
}
}

```

Summary of change: ⌘ 1.28 Mcps related additions to system information are made optional.

Consequences if not approved: ⌘ This change affects currently 1.28 Mcps TDD only (system information) Without this change significant overhead needs to be send in FDD systems in case additions are required for FDD. Currently, these changes do not affect FDD.

Clauses affected: ⌘ 11.3

	Y	N		
Other specs affected:		X	Other core specifications	⌘
		X	Test specifications	
		X	O&M Specifications	

Other comments: ⌘

How to create CRs using this form:

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>. Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

11.3 Information element definitions

```

InformationElements DEFINITIONS AUTOMATIC TAGS ::=
-- *****
--
-- CORE NETWORK INFORMATION ELEMENTS (10.3.1)
--
-- *****

BEGIN

...

SysInfoType5 ::=
    SEQUENCE {
        sib6indicator                BOOLEAN,
        -- Physical channel IEs
        pich-PowerOffset             PICH-PowerOffset,
        modeSpecificInfo             CHOICE {
            fdd                      SEQUENCE {
                aich-PowerOffset     AICH-PowerOffset
            },
            tdd                      SEQUENCE {
                -- If PDSCH/PUSCH is configured for 1.28Mcps TDD, the following IEs should be absent
                -- and the info included in the tddl28SpecificInfo instead.
                pusch-SysInfoList-SFN PUSCH-SysInfoList-SFN        OPTIONAL,
                pdsch-SysInfoList-SFN PDSCH-SysInfoList-SFN        OPTIONAL,
                openLoopPowerControl-TDD OpenLoopPowerControl-TDD
            }
        },
        primaryCCPCH-Info            PrimaryCCPCH-Info            OPTIONAL,
        prach-SystemInformationList  PRACH-SystemInformationList,
        sccpch-SystemInformationList SCCPCH-SystemInformationList,
        -- cbs-DRX-Level1Information is conditional on any of the CTCH indicator IEs in
        -- sccpch-SystemInformationList
        cbs-DRX-Level1Information    CBS-DRX-Level1Information    OPTIONAL,
        -- Extension mechanism for non- release99 information
        v4xyNonCriticalExtensions    SEQUENCE {
            sysInfoType5-v4xyext     SysInfoType5-v4xyext-Ies    OPTIONAL,
            -- Extension mechanism for non- rel-4 information
            nonCriticalExtensions     SEQUENCE {}                  OPTIONAL
        }
    }

SysInfoType5-v4xyext-Ies ::= SEQUENCE {
    pNBSCH-Allocation-r4            PNBSCH-Allocation-r4        OPTIONAL,
    -- In case of TDD, the following IE is included instead of the
    -- IE up-IPDL-Parameter in up-OTDOA-AssistanceData.
    openLoopPowerControl-IPDL-TDD   OpenLoopPowerControl-IPDL-TDD-r4    OPTIONAL,
    -- If SysInfoType5 is sent to describe a 1.28Mcps TDD cell, the IE PRACH-RACH-Info included in
    -- PRACH-SystemInformationList shall be ignored, the IE PRACH-Partitioning and the
    -- IE rach-TransportFormatSet shall be absent and the corresponding IE in the following
    -- PRACH-SystemInformationList-LCR-r4 shall be used
    prach-SystemInformationList-LCR-r4 PRACH-SystemInformationList-LCR-r4    OPTIONAL,
    tddl28SpecificInfo              SEQUENCE {
        pusch-SysInfoList-SFN        PUSCH-SysInfoList-SFN-LCR-r4    OPTIONAL,
        pdsch-SysInfoList-SFN        PDSCH-SysInfoList-SFN-LCR-r4    OPTIONAL,
        pCCPCH-LCR-Extensions        PrimaryCCPCH-Info-LCR-r4-ext    OPTIONAL,
        sccpch-LCR-ExtensionsList     SCCPCH-SystemInformationList-LCR-r4-ext
    }
    }

SysInfoType6 ::=
    SEQUENCE {
        -- Physical channel IEs
        pich-PowerOffset             PICH-PowerOffset,
        modeSpecificInfo             CHOICE {
            fdd                      SEQUENCE {
                aich-PowerOffset     AICH-PowerOffset,
                -- dummy is not used in this version of specification, it should
                -- not be sent and if received it should be ignored.
                dummy                CSICH-PowerOffset             OPTIONAL
            },
            tdd                      SEQUENCE {
                -- If PDSCH/PUSCH is configured for 1.28Mcps TDD, pusch-SysInfoList-SFN,
                -- pdsch-SysInfoList-SFN and openLoopPowerControl-TDD should be absent
                -- and the info included in the tddl28SpecificInfo instead.

```

```

        pusch-SysInfoList-SFN          PUSCH-SysInfoList-SFN          OPTIONAL,
        pdsch-SysInfoList-SFN          PDSCH-SysInfoList-SFN          OPTIONAL,
        openLoopPowerControl-TDD        OpenLoopPowerControl-TDD
    },
    primaryCCPCH-Info                  PrimaryCCPCH-Info                OPTIONAL,
    prach-SystemInformationList         PRACH-SystemInformationList     OPTIONAL,
    sCCPCH-SystemInformationList        SCCPCH-SystemInformationList    OPTIONAL,
    cbs-DRX-Level1Information           CBS-DRX-Level1Information       OPTIONAL,
    -- Conditional on any of the CTCH indicator IEs in
    -- sCCPCH-SystemInformationList
-- Extension mechanism for non- release99 information
v4xyNonCriticalExtensions             SEQUENCE {
    sysInfoType6-v4xyext               SysInfoType6-v4xyext-Ies       OPTIONAL,
    -- Extension mechanism for non- rel-4 information
    nonCriticalExtensions               SEQUENCE {}                     OPTIONAL
}
}

SysInfoType6-v4xyext-IEs ::= SEQUENCE {
-- openLoopPowerControl-IPDL-TDD is present only if IPDLs are applied for TDD
openLoopPowerControl-IPDL-TDD         OpenLoopPowerControl-IPDL-TDD-r4 OPTIONAL,
-- If SysInfoType6 is sent to describe a 1.28Mcps TDD cell, the IE PRACH-RACH-Info included
-- in PRACH-SystemInformationList shall be ignored, the IE PRACH-Partitioning and the
-- IE rach-TransportFormatSet shall be absent and the corresponding IEs in the following
-- PRACH-SystemInformationList-LCR-r4 shall be used
prach-SystemInformationList-LCR-r4    PRACH-SystemInformationList-LCR-r4 OPTIONAL,
tddl28SpecificInfo                    SEQUENCE {
    pusch-SysInfoList-SFN              PUSCH-SysInfoList-SFN-LCR-r4  OPTIONAL,
    pdsch-SysInfoList-SFN              PDSCH-SysInfoList-SFN-LCR-r4  OPTIONAL,
    pCCPCH-LCR-Extensions               PrimaryCCPCH-Info-LCR-r4-ext    OPTIONAL,
    sCCPCH-LCR-ExtensionsList           SCCPCH-SystemInformationList-LCR-r4-ext OPTIONAL
}
}

SysInfoType7 ::= SEQUENCE {
-- Physical channel IEs
modeSpecificInfo                       CHOICE {
    fdd                                 SEQUENCE {
        ul-Interference                 UL-Interference
    },
    tdd                                 NULL
},
prach-Information-SIB5-List             DynamicPersistenceLevelList,
prach-Information-SIB6-List             DynamicPersistenceLevelList     OPTIONAL,
expirationTimeFactor                   ExpirationTimeFactor            OPTIONAL,
-- Extension mechanism for non- release99 information
nonCriticalExtensions                   SEQUENCE {}                     OPTIONAL
}

SysInfoType8 ::= SEQUENCE {
-- User equipment IEs
cpch-Parameters                         CPCH-Parameters,
-- Physical channel IEs
cpch-SetInfoList                       CPCH-SetInfoList,
csich-PowerOffset                       CSICH-PowerOffset,
-- Extension mechanism for non- release99 information
nonCriticalExtensions                   SEQUENCE {}                     OPTIONAL
}

SysInfoType9 ::= SEQUENCE {
-- Physical channel IEs
cpch-PersistenceLevelsList             CPCH-PersistenceLevelsList,
-- Extension mechanism for non- release99 information
nonCriticalExtensions                   SEQUENCE {}                     OPTIONAL
}

SysInfoType10 ::= SEQUENCE {
-- User equipment IEs
drac-SysInfoList                       DRAC-SysInfoList,
-- Extension mechanism for non- release99 information
nonCriticalExtensions                   SEQUENCE {}                     OPTIONAL
}

SysInfoType11 ::= SEQUENCE {
sibl2indicator                          BOOLEAN,
-- Measurement IEs
fach-MeasurementOccasionInfo           FACH-MeasurementOccasionInfo    OPTIONAL,

```



```

        measurementControlSysInfo      MeasurementControlSysInfo,
-- Extension mechanism for non- release99 information
        v4xyNonCriticalExtensions      SEQUENCE {
        sysInfoType11-v4xyext          SysInfoType11-v4xyext-Ies OPTIONAL,
        nonCriticalExtensions          SEQUENCE {} OPTIONAL
    }
}

SysInfoType11-v4xyext-IEs ::= SEQUENCE {
    fach-MeasurementOccasionInfo-LCR-Ext FACH-MeasurementOccasionInfo-LCR-r4-ext OPTIONAL,
    measurementControlSysInfo-LCR      MeasurementControlSysInfo-LCR-r4-ext
}

SysInfoType12 ::= SEQUENCE {
-- Measurement IEs
    fach-MeasurementOccasionInfo      FACH-MeasurementOccasionInfo OPTIONAL,
    measurementControlSysInfo      MeasurementControlSysInfo,
-- Extension mechanism for non- release99 information
    v4xyNonCriticalExtensions      SEQUENCE {
    sysInfoType12-v4xyext          SysInfoType12-v4xyext-Ies OPTIONAL,
    nonCriticalExtensions          SEQUENCE {} OPTIONAL
    }
}

SysInfoType12-v4xyext-IEs ::= SEQUENCE {
    fach-MeasurementOccasionInfo-LCR-Ext FACH-MeasurementOccasionInfo-LCR-r4-ext OPTIONAL,
    measurementControlSysInfo-LCR      MeasurementControlSysInfo-LCR-r4-ext
}

SysInfoType13 ::= SEQUENCE {
-- Core network IEs
    cn-DomainSysInfoList            CN-DomainSysInfoList,
-- User equipment IEs
    ue-IdleTimersAndConstants        UE-IdleTimersAndConstants OPTIONAL,
    capabilityUpdateRequirement      CapabilityUpdateRequirement OPTIONAL,
-- Extension mechanism for non- release99 information
    v3a0NonCriticalExtensions        SEQUENCE {
    sysInfoType13-v3a0ext          SysInfoType13-v3a0ext-IEs,
    v4xyNonCriticalExtensions        SEQUENCE {
    sysInfoType13-v4xyext          SysInfoType13-v4xyext-IEs,
    -- Extension mechanism for non- release99 information
    nonCriticalExtensions          SEQUENCE {} OPTIONAL
    }
    }
}

SysInfoType13-v3a0ext-IEs ::= SEQUENCE {
    ue-IdleTimersAndConstants-v3a0ext UE-IdleTimersAndConstants-v3a0ext
}

SysInfoType13-v4xyext-IEs ::= SEQUENCE {
    capabilityUpdateRequirement-r4Ext CapabilityUpdateRequirement-r4-ext OPTIONAL
}

SysInfoType13-1 ::= SEQUENCE {
-- ANSI-41 IEs
    ansi-41-RAND-Information          ANSI-41-RAND-Information,
-- Extension mechanism for non- release99 information
    nonCriticalExtensions            SEQUENCE {} OPTIONAL
}

SysInfoType13-2 ::= SEQUENCE {
-- ANSI-41 IEs
    ansi-41-UserZoneID-Information    ANSI-41-UserZoneID-Information,
-- Extension mechanism for non- release99 information
    nonCriticalExtensions            SEQUENCE {} OPTIONAL
}

SysInfoType13-3 ::= SEQUENCE {
-- ANSI-41 IEs
    ansi-41-PrivateNeighbourListInfo  ANSI-41-PrivateNeighbourListInfo,
-- Extension mechanism for non- release99 information
    nonCriticalExtensions            SEQUENCE {} OPTIONAL
}

SysInfoType13-4 ::= SEQUENCE {
-- ANSI-41 IEs
    ansi-41-GlobalServiceRedirectInfo

```

```

        ANSI-41-GlobalServiceRedirectInfo,
-- Extension mechanism for non- release99 information
    nonCriticalExtensions          SEQUENCE {}          OPTIONAL
}

SysInfoType14 ::=
-- Physical channel IEs
    individualTS-InterferenceList  IndividualTS-InterferenceList,
    expirationTimeFactor           ExpirationTimeFactor          OPTIONAL,
-- Extension mechanism for non- release99 information
    nonCriticalExtensions          SEQUENCE {}          OPTIONAL
}

SysInfoType15 ::=
-- Measurement IEs

    ue-positioning-GPS-CipherParameters  UE-Positioning-CipherParameters  OPTIONAL,
    ue-positioning-GPS-ReferenceLocation  ReferenceLocation,
    ue-positioning-GPS-ReferenceTime      UE-Positioning-GPS-ReferenceTime,

    ue-positioning-GPS-Real-timeIntegrity  BadSatList          OPTIONAL,
-- Extension mechanism for non- release99 information
    v4xyNonCriticalExtensions          SEQUENCE {}
        sysInfoType15-v4xyext          SysInfoType15-v4xyext-IEs,
-- Extension mechanism for non- release4 information
        nonCriticalExtensions          SEQUENCE {}          OPTIONAL
    }
}

SysInfoType15-v4xyext-IEs ::= SEQUENCE {
    up-IPDL-Parameters-TDD            UE-Positioning-IPDL-Parameters-TDD-r4-ext  OPTIONAL
}

SysInfoType15-1 ::=
-- DGPS corrections
    ue-positioning-GPS-DGPS-Corrections          UE-Positioning-GPS-DGPS-Corrections,

-- Extension mechanism for non- release99 information
    nonCriticalExtensions          SEQUENCE {}          OPTIONAL
}

SysInfoType15-2 ::=
-- Ephemeris and clock corrections
    transmissionTOW                INTEGER (0..604799),
    satID                           SatID,
    ephemerisParameter              EphemerisParameter,

-- Extension mechanism for non- release99 information
    nonCriticalExtensions          SEQUENCE {}          OPTIONAL
}

SysInfoType15-3 ::=
-- Almanac and other data
    transmissionTOW                INTEGER (0.. 604799),
    ue-positioning-GPS-Almanac      UE-Positioning-GPS-Almanac
OPTIONAL,
    ue-positioning-GPS-IonosphericModel  UE-Positioning-GPS-IonosphericModel
OPTIONAL,
    ue-positioning-GPS-UTC-Model      UE-Positioning-GPS-UTC-Model
OPTIONAL,
    satMask                          BIT STRING (SIZE (1..32))  OPTIONAL,
    lsbTOW                            BIT STRING (SIZE (8))    OPTIONAL,
-- Extension mechanism for non- release99 information
    nonCriticalExtensions          SEQUENCE {}          OPTIONAL
}

SysInfoType15-4 ::=
-- Measurement IEs
    ue-positioning-OTDOA-CipherParameters  UE-Positioning-CipherParameters  OPTIONAL,
    ue-positioning-OTDOA-AssistanceData     UE-Positioning-OTDOA-AssistanceData,
    v3a0NonCriticalExtensions              SEQUENCE {
        sysInfoType15-4-v3a0ext          SysInfoType15-4-v3a0ext,
-- Extension mechanism for non- release99 information
        v4xyNonCriticalExtensions        SEQUENCE {
            sysInfoType15-4-v4xyext      SysInfoType15-4-v4xyext,
            nonCriticalExtensions        SEQUENCE {}          OPTIONAL
        }
    }
}

```

```

}

SysInfoType15-4-v3a0ext ::= SEQUENCE {
    sfn-Offset-Validity          SFN-Offset-Validity          OPTIONAL
}

SysInfoType15-4-v4xyext ::= SEQUENCE {
    ue-Positioning-OTDOA-AssistanceData-r4ext  UE-Positioning-OTDOA-AssistanceData-r4ext  OPTIONAL
}

SysInfoType15-5 ::=
    SEQUENCE {
        -- Measurement IEs
        ue-positioning-OTDOA-AssistanceData-UEB  UE-Positioning-OTDOA-AssistanceData-UEB,
        v3a0NonCriticalExtensions                SEQUENCE {
            sysInfoType15-5-v3a0ext              SysInfoType15-5-v3a0ext,
            -- Extension mechanism for non- release99 information
            nonCriticalExtensions                SEQUENCE {}          OPTIONAL
        }          OPTIONAL
    }

SysInfoType15-5-v3a0ext ::= SEQUENCE {
    sfn-Offset-Validity          SFN-Offset-Validity          OPTIONAL
}

SysInfoType16 ::=
    SEQUENCE {
        -- Radio bearer IEs
        preDefinedRadioConfiguration  PreDefRadioConfiguration,
        -- Extension mechanism for non- release99 information
        nonCriticalExtensions          SEQUENCE {}          OPTIONAL
    }

SysInfoType17 ::=
    SEQUENCE {
        -- Physical channel IEs
        -- If PDSCH/PUSCH is configured for 1.28Mcps TDD, pusch-SysInfoList and
        -- pdsch-SysInfoList should be absent and the info included in the
        -- tdd128SpecificInfo instead.
        pusch-SysInfoList              PUSCH-SysInfoList          OPTIONAL,
        pdsch-SysInfoList              PDSCH-SysInfoList          OPTIONAL,
        -- Extension mechanism for non- release99 information
        v4xyNonCriticalExtensions      SEQUENCE {
            sysInfoType17-v4xyext      SysInfoType17-v4xyext-IEs,
            nonCriticalExtensions      SEQUENCE {}          OPTIONAL
        }          OPTIONAL
    }

SysInfoType17-v4xyext-IEs ::= SEQUENCE {
    tdd128SpecificInfo                SEQUENCE {
        pusch-SysInfoList              PUSCH-SysInfoList-LCR-r4          OPTIONAL,
        pdsch-SysInfoList              PDSCH-SysInfoList-LCR-r4          OPTIONAL
    }          OPTIONAL
}

SysInfoType18 ::=
    SEQUENCE {
        idleModePLMNIdentities         PLMNIdentitiesOfNeighbourCells  OPTIONAL,
        connectedModePLMNIdentities    PLMNIdentitiesOfNeighbourCells  OPTIONAL,
        -- Extension mechanism for non- release99 information
        nonCriticalExtensions          SEQUENCE {}          OPTIONAL
    }

SysInfoTypeSB1 ::=
    SEQUENCE {
        -- Other IEs
        sib-ReferenceList               SIB-ReferenceList,
        -- Extension mechanism for non- release99 information
        nonCriticalExtensions          SEQUENCE {}          OPTIONAL
    }

SysInfoTypeSB2 ::=
    SEQUENCE {
        -- Other IEs
        sib-ReferenceList               SIB-ReferenceList,
        -- Extension mechanism for non- release99 information
        nonCriticalExtensions          SEQUENCE {}          OPTIONAL
    }

TDD-UMTS-Frequency-List ::=
    SEQUENCE (SIZE (1..maxNumTDDFreqs)) OF
        FrequencyInfoTDD
...

```

END

CHANGE REQUEST

⌘ **25.331 CR 1866** ⌘ rev **-** ⌘ Current version: **5.3.0** ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

Proposed change affects: UICC apps ME Radio Access Network Core Network

Title:	⌘ Extensions for 1.28 Mcps specific elements in system information		
Source:	⌘ TSG-RAN WG2		
Work item code:	⌘ LCRTDD-L23	Date:	⌘ 03/02/2003
Category:	⌘ A	Release:	⌘ Rel-5
	Use <u>one</u> of the following categories:		Use <u>one</u> of the following releases:
	F (correction)		2 (GSM Phase 2)
	A (corresponds to a correction in an earlier release)	R96 (Release 1996)	
	B (addition of feature),	R97 (Release 1997)	
	C (functional modification of feature)	R98 (Release 1998)	
	D (editorial modification)	R99 (Release 1999)	
	Detailed explanations of the above categories can be found in 3GPP TR 21.900 .	Rel-4 (Release 4)	
		Rel-5 (Release 5)	
		Rel-6 (Release 6)	

Reason for change: ⌘ A number of elements were included in system information for 1.28 Mcps by utilising non-critical extensions. These elements were included as mandatory elements.

As soon as further extensions are needed for e.g. FDD there is a need to include these 1.28 Mcps elements even if they are not needed.

Especially, in case of SIB11 and SIB12 this will lead to a significant overhead for FDD if no 1.28 Mcps TDD neighbours exist.

For clarity the structure that would be required to be included is shown below:

```

MeasurementControlSysInfo-LCR-r4-ext ::= SEQUENCE {
    -- CHOICE use-of-HCS shall have the same value as the use-of-HCS
    -- in MeasurementControlSysInfo
    use-of-HCS CHOICE {
        hcs-not-used SEQUENCE {
            -- CHOICE cellSelectQualityMeasure shall have the same value as
            the
            -- cellSelectQualityMeasure in MeasurementControlSysInfo
            cellSelectQualityMeasure CHOICE {
                cpich-RSCP SEQUENCE {
                    intraFreqMeasurementSysInfo
                    IntraFreqMeasurementSysInfo-RSCP-LCR-r4 OPTIONAL,
                    interFreqMeasurementSysInfo
                    InterFreqMeasurementSysInfo-RSCP-LCR-r4 OPTIONAL
                },
                cpich-Ec-N0 SEQUENCE {
                    intraFreqMeasurementSysInfo
                    IntraFreqMeasurementSysInfo-ECN0-LCR-r4 OPTIONAL,
                    interFreqMeasurementSysInfo
                    InterFreqMeasurementSysInfo-ECN0-LCR-r4 OPTIONAL
                }
            }
        },
        hcs-used SEQUENCE {
            -- CHOICE cellSelectQualityMeasure shall have the same value as
            the
    
```

```

-- cellSelectQualityMeasure in MeasurementControlSysInfo
cellSelectQualityMeasure CHOICE {
  cpich-RSCP SEQUENCE {
    intraFreqMeasurementSysInfo
    IntraFreqMeasurementSysInfo-HCS-RSCP-LCR-r4 OPTIONAL,
    interFreqMeasurementSysInfo
    InterFreqMeasurementSysInfo-HCS-RSCP-LCR-r4 OPTIONAL
  },
  cpich-Ec-N0 SEQUENCE {
    intraFreqMeasurementSysInfo
    IntraFreqMeasurementSysInfo-HCS-ECN0-LCR-r4 OPTIONAL,
    interFreqMeasurementSysInfo
    InterFreqMeasurementSysInfo-HCS-ECN0-LCR-r4 OPTIONAL
  }
}
}
}
}

```

Summary of change: ⌘ 1.28 Mcps related additions to system information are made optional.

Consequences if not approved: ⌘ This change affects 1.28 Mcps TDD only (system information) Without this change significant overhead needs to be send in FDD systems in case additions are required for FDD. Currently, these changes do not affect FDD.

Clauses affected: ⌘ 11.3

	Y	N	
Other specs affected:		X	Other core specifications ⌘
		X	Test specifications
		X	O&M Specifications

Other comments: ⌘

How to create CRs using this form:

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>. Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

11.3 Information element definitions

...

```

SysInfoType5 ::=
    sib6indicator                SEQUENCE {
        BOOLEAN,
    -- Physical channel IEs
    pich-PowerOffset            PICH-PowerOffset,
    modeSpecificInfo            CHOICE {
        fdd                      SEQUENCE {
            aich-PowerOffset      AICH-PowerOffset
        },
        tdd                      SEQUENCE {
    -- If PDSCH/PUSCH is configured for 1.28Mcps TDD, the following IEs should be absent
    -- and the info included in the tddl28SpecificInfo instead.
        pusch-SysInfoList-SFN    PUSCH-SysInfoList-SFN        OPTIONAL,
        pdsch-SysInfoList-SFN    PDSCH-SysInfoList-SFN        OPTIONAL,
        openLoopPowerControl-TDD OpenLoopPowerControl-TDD
    }
    },
    primaryCCPCH-Info           PrimaryCCPCH-Info                OPTIONAL,
    prach-SystemInformationList PRACH-SystemInformationList,
    sCCPCH-SystemInformationList SCCPCH-SystemInformationList,
    -- cbs-DRX-Level1Information is conditional on any of the CTCH indicator IEs in
    -- sCCPCH-SystemInformationList
    cbs-DRX-Level1Information   CBS-DRX-Level1Information        OPTIONAL,
    -- Extension mechanism for non- release99 information
    v4xyNonCriticalExtensions    SEQUENCE {
        sysInfoType5-v4xyext     SysInfoType5-v4xyext-Ies OPTIONAL,
    -- Extension mechanism for non- rel-4 information
        nonCriticalExtensions     SEQUENCE {}                    OPTIONAL
    }
}

SysInfoType5-v4xyext-IEs ::= SEQUENCE {
    pNBSCH-Allocation-r4        PNBSCH-Allocation-r4            OPTIONAL,
    -- In case of TDD, the following IE is included instead of the
    -- IE up-IPDL-Parameter in up-OTDOA-AssistanceData.
    openLoopPowerControl-IPDL-TDD OpenLoopPowerControl-IPDL-TDD-r4 OPTIONAL,
    -- If SysInfoType5 is sent to describe a 1.28Mcps TDD cell, the IE PRACH-RACH-Info included in
    -- PRACH-SystemInformationList shall be ignored, the IE PRACH-Partitioning and the
    -- IE rach-TransportFormatSet shall be absent and the corresponding IE in the following
    -- PRACH-SystemInformationList-LCR-r4 shall be used
    prach-SystemInformationList-LCR-r4 PRACH-SystemInformationList-LCR-r4 OPTIONAL,
    tddl28SpecificInfo          SEQUENCE {
        pusch-SysInfoList-SFN    PUSCH-SysInfoList-SFN-LCR-r4    OPTIONAL,
        pdsch-SysInfoList-SFN    PDSCH-SysInfoList-SFN-LCR-r4    OPTIONAL,
        pCCPCH-LCR-Extensions    PrimaryCCPCH-Info-LCR-r4-ext  OPTIONAL,
        sCCPCH-LCR-ExtensionsList SCCPCH-SystemInformationList-LCR-r4-ext
    }
}

SysInfoType6 ::=
    Physical channel IEs
    pich-PowerOffset            PICH-PowerOffset,
    modeSpecificInfo            CHOICE {
        fdd                      SEQUENCE {
            aich-PowerOffset      AICH-PowerOffset,
            -- dummy is not used in this version of specification, it should
            -- not be sent and if received it should be ignored.
            dummy                  CSICH-PowerOffset                OPTIONAL
        },
        tdd                      SEQUENCE {
    -- If PDSCH/PUSCH is configured for 1.28Mcps TDD, pusch-SysInfoList-SFN,
    -- pdsch-SysInfoList-SFN and openLoopPowerControl-TDD should be absent
    -- and the info included in the tddl28SpecificInfo instead.
        pusch-SysInfoList-SFN    PUSCH-SysInfoList-SFN        OPTIONAL,
        pdsch-SysInfoList-SFN    PDSCH-SysInfoList-SFN        OPTIONAL,
        openLoopPowerControl-TDD OpenLoopPowerControl-TDD
    }
    },
    primaryCCPCH-Info           PrimaryCCPCH-Info                OPTIONAL,
    prach-SystemInformationList PRACH-SystemInformationList        OPTIONAL,
    sCCPCH-SystemInformationList SCCPCH-SystemInformationList        OPTIONAL,
    cbs-DRX-Level1Information   CBS-DRX-Level1Information        OPTIONAL,
    -- Conditional on any of the CTCH indicator IEs in

```

```

-- sCCPCH-SystemInformationList
-- Extension mechanism for non- release99 information
v4xyNonCriticalExtensions SEQUENCE {
  sysInfoType6-v4xyext SysInfoType6-v4xyext-IEs OPTIONAL,
  -- Extension mechanism for non- rel-4 information
  nonCriticalExtensions SEQUENCE {} OPTIONAL
}
}

SysInfoType6-v4xyext-IEs ::= SEQUENCE {
  -- openLoopPowerControl-IPDL-TDD is present only if IPDLs are applied for TDD
  openLoopPowerControl-IPDL-TDD OpenLoopPowerControl-IPDL-TDD-r4 OPTIONAL,
  -- If SysInfoType6 is sent to describe a 1.28Mcps TDD cell, the IE PRACH-RACH-Info included
  -- in PRACH-SystemInformationList shall be ignored, the IE PRACH-Partitioning and the
  -- IE rach-TransportFormatSet shall be absent and the corresponding IEs in the following
  -- PRACH-SystemInformationList-LCR-r4 shall be used
  prach-SystemInformationList-LCR-r4 PRACH-SystemInformationList-LCR-r4 OPTIONAL,
  tdd128SpecificInfo SEQUENCE {
    pusSch-SysInfoList-SFN PUSCH-SysInfoList-SFN-LCR-r4 OPTIONAL,
    pdsch-SysInfoList-SFN PDSCH-SysInfoList-SFN-LCR-r4 OPTIONAL,
    pCCPCH-LCR-Extensions PrimaryCCPCH-Info-LCR-r4-ext OPTIONAL,
    sCCPCH-LCR-ExtensionsList SCCPCH-SystemInformationList-LCR-r4-ext OPTIONAL
  }
}

SysInfoType7 ::= SEQUENCE {
  -- Physical channel IEs
  modeSpecificInfo CHOICE {
    fdd SEQUENCE {
      ul-Interference UL-Interference
    },
    tdd NULL
  },
  prach-Information-SIB5-List DynamicPersistenceLevelList,
  prach-Information-SIB6-List DynamicPersistenceLevelList OPTIONAL,
  expirationTimeFactor ExpirationTimeFactor OPTIONAL,
  -- Extension mechanism for non- release99 information
  nonCriticalExtensions SEQUENCE {} OPTIONAL
}

SysInfoType8 ::= SEQUENCE {
  -- User equipment IEs
  cpch-Parameters CPCH-Parameters,
  -- Physical channel IEs
  cpch-SetInfoList CPCH-SetInfoList,
  csich-PowerOffset CSICH-PowerOffset,
  -- Extension mechanism for non- release99 information
  nonCriticalExtensions SEQUENCE {} OPTIONAL
}

SysInfoType9 ::= SEQUENCE {
  -- Physical channel IEs
  cpch-PersistenceLevelsList CPCH-PersistenceLevelsList,
  -- Extension mechanism for non- release99 information
  nonCriticalExtensions SEQUENCE {} OPTIONAL
}

SysInfoType10 ::= SEQUENCE {
  -- User equipment IEs
  drac-SysInfoList DRAC-SysInfoList,
  -- Extension mechanism for non- release99 information
  nonCriticalExtensions SEQUENCE {} OPTIONAL
}

SysInfoType11 ::= SEQUENCE {
  sib12indicator BOOLEAN,
  -- Measurement IEs
  fach-MeasurementOccasionInfo FACH-MeasurementOccasionInfo OPTIONAL,
  measurementControlSysInfo MeasurementControlSysInfo,
  -- Extension mechanism for non- release99 information
  v4xyNonCriticalExtensions SEQUENCE {
    sysInfoType11-v4xyext SysInfoType11-v4xyext-IEs OPTIONAL,
    v5xyNonCriticalExtension SEQUENCE {
      sysInfoType11-v5xyext SysInfoType11-v5xyext-IEs,
      nonCriticalExtensions SEQUENCE {} OPTIONAL
    }
  }
}
}

```



```

SysInfoType11-v4xyext-IEs ::= SEQUENCE {
  fach-MeasurementOccasionInfo-LCR-Ext  FACH-MeasurementOccasionInfo-LCR-r4-ext OPTIONAL,
  measurementControlSysInfo-LCR         MeasurementControlSysInfo-LCR-r4-ext
}

```

```

SysInfoType11-v5xyext-IEs ::= SEQUENCE {
  --The order of the list corresponds to the order of cell in newIntraFrequencyCellInfoList
  newIntraFrequencyCellInfoList-v5xyext SEQUENCE (SIZE (1..maxCellMeas)) OF
                                          CellSelectReselectInfo-v5xyExt OPTIONAL,
  --The order of the list corresponds to the order of cell in newInterFrequencyCellInfoList
  newInterFrequencyCellInfoList-v5xyext SEQUENCE (SIZE (1..maxCellMeas)) OF
                                          CellSelectReselectInfo-v5xyExt OPTIONAL,
  --The order of the list corresponds to the order of cell in newInterRATCellInfoList
  newInterRATCellInfoList-v5xyext      SEQUENCE (SIZE (1..maxCellMeas)) OF
                                          CellSelectReselectInfo-v5xyExt OPTIONAL,
  intraFreqEventCriteriaList-v5xyext   Intra-FreqEventCriteriaList-v5xyext OPTIONAL,
  intraFreqReportingCriteria-lb-r5ext   IntraFreqReportingCriteria-lb-r5ext OPTIONAL
}

```

```

SysInfoType12 ::= SEQUENCE {
  -- Measurement IEs
  fach-MeasurementOccasionInfo  FACH-MeasurementOccasionInfo OPTIONAL,
  measurementControlSysInfo     MeasurementControlSysInfo,
  -- Extension mechanism for non- release99 information
  v4xyNonCriticalExtensions     SEQUENCE {
    sysInfoType12-v4xyext       SysInfoType12-v4xyext-IEs OPTIONAL,
    v5xyNonCriticalExtension    SEQUENCE {
      sysInfoType12-v5xyext     SysInfoType12-v5xyext-IEs,
      nonCriticalExtensions     SEQUENCE {} OPTIONAL
    } OPTIONAL
  } OPTIONAL
}

```

```

SysInfoType12-v4xyext-IEs ::= SEQUENCE {
  fach-MeasurementOccasionInfo-LCR-Ext  FACH-MeasurementOccasionInfo-LCR-r4-ext OPTIONAL,
  measurementControlSysInfo-LCR         MeasurementControlSysInfo-LCR-r4-ext
}

```

```

SysInfoType12-v5xyext-IEs ::= SEQUENCE {
  --The order of the list corresponds to the order of cell in newIntraFrequencyCellInfoList
  newIntraFrequencyCellInfoList-v5xyext SEQUENCE (SIZE (1..maxCellMeas)) OF
                                          CellSelectReselectInfo-v5xyExt OPTIONAL,
  --The order of the list corresponds to the order of cell in newInterFrequencyCellInfoList
  newInterFrequencyCellInfoList-v5xyext SEQUENCE (SIZE (1..maxCellMeas)) OF
                                          CellSelectReselectInfo-v5xyExt OPTIONAL,
  --The order of the list corresponds to the order of cell in newInterRATCellInfoList
  newInterRATCellInfoList-v5xyext      SEQUENCE (SIZE (1..maxCellMeas)) OF
                                          CellSelectReselectInfo-v5xyExt OPTIONAL,
  intraFreqEventCriteriaList-v5xyext   Intra-FreqEventCriteriaList-v5xyext OPTIONAL,
  intraFreqReportingCriteria-lb-r5ext   IntraFreqReportingCriteria-lb-r5ext OPTIONAL
}

```

CHANGE REQUEST

⌘ **25.331 CR 1867** ⌘ rev - ⌘ Current version: **4.7.0** ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

Proposed change affects: UICC apps ME Radio Access Network Core Network

Title:	⌘ Corrections to power control parameter signalling for 1.28 Mcps TDD		
Source:	⌘ TSG-RAN WG2		
Work item code:	⌘ LCRTDD-L23	Date:	⌘ 11 February 2003
Category:	⌘ F	Release:	⌘ REL-4
	Use <i>one</i> of the following categories: F (correction) A (corresponds to a correction in an earlier release) B (addition of feature), C (functional modification of feature) D (editorial modification) Detailed explanations of the above categories can be found in 3GPP TR 21.900 .		Use <i>one</i> of the following releases: 2 (GSM Phase 2) R96 (Release 1996) R97 (Release 1997) R98 (Release 1998) R99 (Release 1999) Rel-4 (Release 4) Rel-5 (Release 5) Rel-6 (Release 6)

Reason for change:	⌘ Certain Information Elements and the comments associated with them do not properly reflect the way in which closed loop power control is now implemented in 1.28 Mcps TDD.
Summary of change:	⌘ (i) In IE 10.3.6.37 the description associated with the parameter ‘additional codes’ is incorrect and is replaced. ⌘ (ii) In IE 10.3.6.45 ‘PDSCH Power Control info’ a note is added to indicate that the loop ‘UL CCTrCH TPC List’ is not required for 1.28 Mcps TDD. ⌘ (iii) IE 10.3.6.65 ‘PUSCH power control info’ contains a redundant list ‘DL CCTrCH TPC List’ which is removed. ⌘ (iv) In IE 10.3.6.21 a note is added to indicate that the loop ‘UL CCTrCH TPC List’ is not required for 1.28 Mcps TDD.
Consequences if not approved:	⌘ UE behaviour will not be specified for 1.28 Mcps TDD leading to loss of radio connections. The specification will be inconsistent with WG1 specifications.

Clauses affected:	⌘ 10.3.6.21, 10.3.6.37, 10.3.6.45, 10.3.6.65., 11.3						
Other specs	<table border="1" style="display: inline-table; vertical-align: middle;"> <tr> <td style="text-align: center;">Y</td> <td style="text-align: center;">N</td> </tr> <tr> <td style="text-align: center;"> </td> <td style="text-align: center;">X</td> </tr> </table> Other core specifications	Y	N		X	⌘	
Y	N						
	X						

affected:	<input checked="" type="checkbox"/>	Test specifications	
	<input checked="" type="checkbox"/>	O&M Specifications	
Other comments:	⌘		

How to create CRs using this form:

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>. Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

10.3.6.21 Downlink DPCH info for each RL

Information Element/Group name	Need	Multi	Type and reference	Semantics description
CHOICE <i>mode</i>	MP			
>FDD				
>>Primary CPICH usage for channel estimation	MP		Primary CPICH usage for channel estimation 10.3.6.62	
>>DPCH frame offset	MP		Integer(0..38 144 by step of 256)	Offset (in number of chips) between the beginning of the P-CCPCH frame and the beginning of the DPCH frame This is called $\tau_{DPCH,n}$ in [26]
>>Secondary CPICH info	OP		Secondary CPICH info 10.3.6.73	
>>DL channelisation code	MP	1 to <maxDPC H-DLchan>		For the purpose of physical channel mapping [27] the DPCHs are numbered, starting from DPCH number 1, according to the order that they are contained in this IE.
>>>Secondary scrambling code	MD		Secondary scrambling code 10.3.6.74	Default is the same scrambling code as for the Primary CPICH
>>>Spreading factor	MP		Integer(4, 8, 16, 32, 64, 128, 256, 512)	Defined in CHOICE SF512-AndCodenum with "code number" in ASN.1
>>>Code number	MP		Integer(0..Sp reading factor - 1)	
>>>Scrambling code change	CH-SF/2		Enumerated (code change, no code change)	Indicates whether the alternative scrambling code is used for compressed mode method 'SF/2'.
>>TPC combination index	MP		TPC combination index 10.3.6.85	
>>SSDT Cell Identity	OP		SSDT Cell Identity 10.3.6.76	
>>Closed loop timing adjustment mode	CH- <i>TxDiversity Mode</i>		Integer(1, 2)	It is present if Tx Diversity is used in the radio link.
>TDD				
>>DL CCTrCh List	OP	1..<maxCC TrCH>		DL physical channels to establish or reconfigure list.
>>>TFCS ID	MD		Integer(1..8)	Identity of this CCTrCh. Default value is 1
>>>Time info	MP		Time Info 10.3.6.83	
>>>Common timeslot info	MD		Common	Default is the current Common

Information Element/Group name	Need	Multi	Type and reference	Semantics description
			Timeslot Info 10.3.6.10	timeslot info
>>>Downlink DPCH timeslots and codes	MD		Downlink Timeslots and Codes 10.3.6.32	Default is to use the old timeslots and codes.
>>>UL CCTrCH TPC List	MD	0..<maxCC TrCH>		UL CCTrCH identities for TPC commands associated with this DL CCTrCH. Default is previous list or all defined UL CCTrCHs This list is not required for 1.28 Mcps TDD and is to be ignored by the UE.
>>>>UL TPC TFCS Identity	MP		Transport Format Combination Set Identity 10.3.5.21	
>>DL CCTrCH List to Remove	OP	1..<maxCC TrCH>		DL physical channels to remove list.
>>>TFCS ID	MP		Integer(1..8)	

Condition	Explanation
<i>SF/2</i>	The information element is mandatory present if the UE has a compressed mode pattern sequence configured in variable TGPS_IDENTITY or included in the message including IE "Downlink DPCH info for each RL", which is using compressed mode method "SF/2". Otherwise the IE is not needed.
<i>TxDiversity Mode</i>	This IE is mandatory present if any TX Diversity Mode is used on the radio link, i.e. if STTD, "closed loop mode 1" or "closed loop mode 2" is used on the radio link. Otherwise the IE is not needed.

10.3.6.37 Individual timeslot info

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
Timeslot number	MP		Timeslot number 10.3.6.84	Timeslot within a frame	
TFCI existence	MP		Boolean	TRUE indicates that the TFCI exists. It shall be coded in the first physical channel of this timeslot.	
Midamble Shift and burst type	MP		Midamble shift and burst type 10.3.6.41		
CHOICE <i>TDD option</i>	MP				REL-4
>3.84 Mcps TDD				(no data)	REL-4
>1.28 Mcps TDD					REL-4

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
>>Modulation	MP		Enumerated(QPSK, 8PSK)		REL-4
>>SS-TPC Symbols	MP		Enumerated(0, 1, 16/SF)	Denotes amount of SS and TPC bits send in this timeslot	REL-4
>>Additional TPC-SS Symbols	OP		Integer(1..15)	Specifies the number of additional codes in this timeslot that carry TPC and SS symbols as specified in [33]	REL-4

10.3.6.45 PDSCH Power Control info

NOTE: Only for TDD.

Information Element/Group name	Need	Multi	Type and reference	Semantics description
TPC Step Size	OP		Integer (1, 2, 3)	In dB
UL CCTrCH TPC List	OP	1..<maxCC TrCH>		UL CCTrCH identities for TPC commands associated with this DL CCTrCH . This list is not used by 1.28 Mcps TDD.
>UL TPC TFCS Identity	MP		Transport Format Combination Set Identity 10.3.5.21	

10.3.6.65 PUSCH power control info

NOTE: Only for TDD.

Interference level measured for a frequency at the UTRAN access point used by UE to set PUSCH output power.

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
CHOICE <i>TDD option</i>	MP				REL-4
>3.84 Mcps TDD					REL-4
>>UL target SIR	MP		Real (-11 .. 20 by step of 0.5)	in dB	
>1.28 Mcps TDD					REL-4
>>PRX _{PUSCHdes}	MP		Integer(-120...-58 by step of 1)	in dBm	REL-4
>>TPC Step Size	OP		Integer (1, 2, 3)	In dB	REL-4
>>DL CCTrCH TPC List	OP	0..<maxCC TrCH>		DL CCTrCH identities for TPC	REL-4

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
				commands associated with this UL CCTrCH	
>>>DL-TPC-TFCS-Identity	MP		Transport Format Combination Set-Identity 10.3.5.21		REL-4


```

sulCodeIndex6(1),
sulCodeIndex5(2),
sulCodeIndex4(3),
sulCodeIndex3(4),
sulCodeIndex2(5),
sulCodeIndex1(6),
sulCodeIndex0(7)
} (SIZE(8)) OPTIONAL,
subchannelSize CHOICE {
size1 NULL,
size2 SEQUENCE {
-- subch0 means bitstring '01' in the tabular, subch1 means bitsring '10'.
subchannels ENUMERATED { subch0, subch1 } OPTIONAL
},
size4 SEQUENCE {
subchannels BIT STRING {
subCh3(0),
subCh2(1),
subCh1(2),
subCh0(3)
} (SIZE(4)) OPTIONAL
},
size8 SEQUENCE {
subchannels BIT STRING {
subCh7(0),
subCh6(1),
subCh5(2),
subCh4(3),
subCh3(4),
subCh2(5),
subCh1(6),
subCh0(7)
} (SIZE(8)) OPTIONAL
}
}
}
}
}

AICH-Info ::= SEQUENCE {
channelisationCode256 ChannelisationCode256,
sttd-Indicator BOOLEAN,
aich-TransmissionTiming AICH-TransmissionTiming
}

AICH-PowerOffset ::= INTEGER (-22..5)

AICH-TransmissionTiming ::= ENUMERATED {
e0, e1 }

AllocationPeriodInfo ::= SEQUENCE {
allocationActivationTime INTEGER (0..255),
allocationDuration INTEGER (1..256)
}

-- Actual value Alpha = IE value * 0.125
Alpha ::= INTEGER (0..8)

AP-AICH-ChannelisationCode ::= INTEGER (0..255)

AP-PreambleScramblingCode ::= INTEGER (0..79)

AP-Signature ::= INTEGER (0..15)

AP-Signature-VCAM ::= SEQUENCE {
ap-Signature AP-Signature,
availableAP-SubchannelList AvailableAP-SubchannelList OPTIONAL
}

AP-Subchannel ::= INTEGER (0..11)

ASCS-Setting-FDD ::= SEQUENCE {

```

```

-- TABULAR: accessServiceClass-FDD is MD in tabular description
-- Default value is previous ASC
-- If this is the first ASC, the default value is all available signature and sub-channels
accessServiceClass-FDD          AccessServiceClass-FDD  OPTIONAL
}

ASCSetting-TDD ::=                SEQUENCE {
-- TABULAR: accessServiceClass-TDD is MD in tabular description
-- Default value is previous ASC
-- If this is the first ASC, the default value is all available channelisation codes and
-- all available sub-channels with subchannelSize=size1.
accessServiceClass-TDD          AccessServiceClass-TDD  OPTIONAL
}

ASCSetting-TDD-LCR-r4 ::=         SEQUENCE {
-- TABULAR: accessServiceClass-TDD-LCR is MD in tabular description
-- Default value is previous ASC
-- If this is the first ASC, the default value is all available SYNC_UL codes and
-- all available sub-channels with subchannelSize=size1.
accessServiceClass-TDD-LCR      AccessServiceClass-TDD-LCR-r4  OPTIONAL
}

AvailableAP-Signature-VCAMList ::= SEQUENCE (SIZE (1..maxPCPCH-APsig)) OF
AP-Signature-VCAM

AvailableAP-SignatureList ::=     SEQUENCE (SIZE (1..maxPCPCH-APsig)) OF
AP-Signature

AvailableAP-SubchannelList ::=    SEQUENCE (SIZE (1..maxPCPCH-APsubCh)) OF
AP-Subchannel

AvailableMinimumSF-ListVCAM ::=  SEQUENCE (SIZE (1..maxPCPCH-SF)) OF
AvailableMinimumSF-VCAM

AvailableMinimumSF-VCAM ::=      SEQUENCE {
minimumSpreadingFactor          MinimumSpreadingFactor,
nf-Max                          NF-Max,
maxAvailablePCPCH-Number        MaxAvailablePCPCH-Number,
availableAP-Signature-VCAMList  AvailableAP-Signature-VCAMList
}

AvailableSignatures ::=          BIT STRING {
signature15(0),
signature14(1),
signature13(2),
signature12(3),
signature11(4),
signature10(5),
signature9(6),
signature8(7),
signature7(8),
signature6(9),
signature5(10),
signature4(11),
signature3(12),
signature2(13),
signature1(14),
signature0(15)
} (SIZE(16))

AvailableSubChannelNumbers ::=   BIT STRING {
subCh11(0),
subCh10(1),
subCh9(2),
subCh8(3),
subCh7(4),
subCh6(5),
subCh5(6),
subCh4(7),
subCh3(8),
subCh2(9),

```

```

        subCh1(10),
        subCh0(11)
    } (SIZE(12))

BurstType ::= ENUMERATED {
    short1, long2 }

CCTrCH-PowerControlInfo ::= SEQUENCE {
    tfcs-Identity          OPTIONAL,
    ul-DPCH-PowerControlInfo
}

CCTrCH-PowerControlInfo-r4 ::= SEQUENCE {
    tfcs-Identity          OPTIONAL,
    ul-DPCH-PowerControlInfo-r4
}

CD-AccessSlotSubchannel ::= INTEGER (0..11)

CD-AccessSlotSubchannelList ::= SEQUENCE (SIZE (1..maxPCPCH-CDsubCh)) OF
    CD-AccessSlotSubchannel

CD-CA-ICH-ChannelisationCode ::= INTEGER (0..255)

CD-PreambleScramblingCode ::= INTEGER (0..79)

CD-SignatureCode ::= INTEGER (0..15)

CD-SignatureCodeList ::= SEQUENCE (SIZE (1..maxPCPCH-CDsig)) OF
    CD-SignatureCode

CellAndChannelIdentity ::= SEQUENCE {
    burstType             BurstType,
    midambleShift         MidambleShiftLong,
    timeslot              TimeslotNumber,
    cellParametersID      CellParametersID
}

CellParametersID ::= INTEGER (0..127)

Cfntargetsfnsframeoffset ::= INTEGER(0..255)

ChannelAssignmentActive ::= CHOICE {
    notActive             NULL,
    isActive              AvailableMinimumSF-ListVCAM
}

ChannelisationCode256 ::= INTEGER (0..255)

ChannelReqParamsForUCSM ::= SEQUENCE {
    availableAP-SignatureList,
    availableAP-SubchannelList
} OPTIONAL

ClosedLoopTimingAdjMode ::= ENUMERATED {
    slot1, slot2 }

CodeNumberDSCH ::= INTEGER (0..255)

CodeRange ::= SEQUENCE {
    pdsch-CodeMapList    PDSCH-CodeMapList
}

CodeWordSet ::= ENUMERATED {
    longCWS,
    mediumCWS,
    shortCWS,
    ssdtOff }

CommonTimeslotInfo ::= SEQUENCE {
    -- TABULAR: secondInterleavingMode is MD, but since it can be encoded in a single

```

```

-- bit it is not defined as OPTIONAL.
secondInterleavingMode      SecondInterleavingMode,
tfci-Coding                  TFCI-Coding                      OPTIONAL,
puncturingLimit              PuncturingLimit,
repetitionPeriodAndLength    RepetitionPeriodAndLength        OPTIONAL
}

CommonTimeslotInfoSCCPCH ::=          SEQUENCE {
-- TABULAR: secondInterleavingMode is MD, but since it can be encoded in a single
-- bit it is not defined as OPTIONAL.
secondInterleavingMode      SecondInterleavingMode,
tfci-Coding                  TFCI-Coding                      OPTIONAL,
puncturingLimit              PuncturingLimit,
repetitionPeriodLengthAndOffset  RepetitionPeriodLengthAndOffset    OPTIONAL
}

ConstantValue ::=                  INTEGER (-35..-10)

ConstantValueTdd ::=               INTEGER (-35..10)

CPCH-PersistenceLevels ::=         SEQUENCE {
  cpch-SetID                  CPCH-SetID,
  dynamicPersistenceLevelTF-List  DynamicPersistenceLevelTF-List
}

CPCH-PersistenceLevelsList ::=     SEQUENCE (SIZE (1..maxCPCHsets)) OF
  CPCH-PersistenceLevels

CPCH-SetInfo ::=                   SEQUENCE {
  cpch-SetID                  CPCH-SetID,
  transportFormatSet          TransportFormatSet,
  tfcs                         TFCS,
  ap-PreambleScramblingCode    AP-PreambleScramblingCode,
  ap-AICH-ChannelisationCode    AP-AICH-ChannelisationCode,
  cd-PreambleScramblingCode     CD-PreambleScramblingCode,
  cd-CA-ICH-ChannelisationCode  CD-CA-ICH-ChannelisationCode,
  cd-AccessSlotSubchannelList   CD-AccessSlotSubchannelList        OPTIONAL,
  cd-SignatureCodeList          CD-SignatureCodeList                OPTIONAL,
  deltaPp-m                     DeltaPp-m,
  ul-DPCCH-SlotFormat           UL-DPCCH-SlotFormat,
  n-StartMessage                N-StartMessage,
  n-EOT                          N-EOT,
-- TABULAR: VCAM info has been nested inside ChannelAssignmentActive,
-- which in turn is mandatory since it's only a binary choice.
channelAssignmentActive         ChannelAssignmentActive,
cpch-StatusIndicationMode       CPCH-StatusIndicationMode,
pcpch-ChannelInfoList           PCPCH-ChannelInfoList
}

CPCH-SetInfoList ::=               SEQUENCE (SIZE (1..maxCPCHsets)) OF
  CPCH-SetInfo

CPCH-StatusIndicationMode ::=      ENUMERATED {
  pa-mode,
  pamsf-mode }

CSICH-PowerOffset ::=              INTEGER (-10..5)

-- DefaultDPCH-OffsetValueFDD and DefaultDPCH-OffsetValueTDD corresponds to
-- IE "Default DPCH Offset Value" depending on the mode.
-- Actual value DefaultDPCH-OffsetValueFDD = IE value * 512
DefaultDPCH-OffsetValueFDD ::=     INTEGER (0..599)

DefaultDPCH-OffsetValueTDD ::=     INTEGER (0..7)

DeltaPp-m ::=                       INTEGER (-10..10)

-- Actual value DeltaSIR = IE value * 0.1
DeltaSIR ::=                        INTEGER (0..30)

DL-CCTrCh ::=                       SEQUENCE {

```

```

    tfcs-ID                TFCS-IdentityPlain                DEFAULT 1,
    timeInfo               TimeInfo,
    commonTimeslotInfo     CommonTimeslotInfo                OPTIONAL,
    dl-CCTrCH-TimeslotsCodes DownlinkTimeslotsCodes            OPTIONAL,
    ul-CCTrChTPCList       UL-CCTrChTPCList                    OPTIONAL
}

DL-CCTrCh-r4 ::=          SEQUENCE {
    tfcs-ID                TFCS-IdentityPlain                DEFAULT 1,
    timeInfo               TimeInfo,
    commonTimeslotInfo     CommonTimeslotInfo                OPTIONAL,
    tddOption              CHOICE {
        tdd384              SEQUENCE {
            dl-CCTrCH-TimeslotsCodes DownlinkTimeslotsCodes OPTIONAL
        },
        tdd128              SEQUENCE {
            dl-CCTrCH-TimeslotsCodes DownlinkTimeslotsCodes-LCR-r4 OPTIONAL
        }
    },
    ul-CCTrChTPCList       UL-CCTrChTPCList                    OPTIONAL
}

DL-CCTrChList ::=        SEQUENCE (SIZE (1..maxCCTrCH)) OF
    DL-CCTrCh

DL-CCTrChList-r4 ::=     SEQUENCE (SIZE (1..maxCCTrCH)) OF
    DL-CCTrCh-r4

DL-CCTrChListToRemove ::= SEQUENCE (SIZE (1..maxCCTrCH)) OF
    TFCS-IdentityPlain

DL-CCTrChTPCList ::=    SEQUENCE (SIZE (0..maxCCTrCH)) OF
    TFCS-Identity

DL-ChannelisationCode ::= SEQUENCE {
    secondaryScramblingCode SecondaryScramblingCode            OPTIONAL,
    sf-AndCodeNumber        SF512-AndCodeNumber,
    scramblingCodeChange     ScramblingCodeChange            OPTIONAL
}

DL-ChannelisationCodeList ::= SEQUENCE (SIZE (1..maxDPCH-DLchan)) OF
    DL-ChannelisationCode

DL-CommonInformation ::= SEQUENCE {
    dl-DPCH-InfoCommon      DL-DPCH-InfoCommon                OPTIONAL,
    modeSpecificInfo        CHOICE {
        fdd                  SEQUENCE {
            defaultDPCH-OffsetValue DefaultDPCH-OffsetValueFDD OPTIONAL,
            dpch-CompressedModeInfo DPCH-CompressedModeInfo        OPTIONAL,
            tx-DiversityMode      TX-DiversityMode                OPTIONAL,
            ssdt-Information       SSDT-Information                OPTIONAL
        },
        tdd                  SEQUENCE {
            defaultDPCH-OffsetValue DefaultDPCH-OffsetValueTDD OPTIONAL
        }
    }
}

DL-CommonInformation-r4 ::= SEQUENCE {
    dl-DPCH-InfoCommon      DL-DPCH-InfoCommon                OPTIONAL,
    modeSpecificInfo        CHOICE {
        fdd                  SEQUENCE {
            defaultDPCH-OffsetValue DefaultDPCH-OffsetValueFDD OPTIONAL,
            dpch-CompressedModeInfo DPCH-CompressedModeInfo        OPTIONAL,
            tx-DiversityMode      TX-DiversityMode                OPTIONAL,
            ssdt-Information-r4    SSDT-Information-r4            OPTIONAL
        },
        tdd                  SEQUENCE {
            tddOption           CHOICE {
                tdd384          NULL,
                tdd128          SEQUENCE {

```

```

        tstd-Indicator                BOOLEAN
    }
},
defaultDPCH-OffsetValue              DefaultDPCH-OffsetValueTDD  OPTIONAL
}
}
}

DL-CommonInformationPost ::=          SEQUENCE {
    dl-DPCH-InfoCommon                DL-DPCH-InfoCommonPost
}

DL-CommonInformationPredef ::=        SEQUENCE {
    dl-DPCH-InfoCommon                DL-DPCH-InfoCommonPredef  OPTIONAL
}

DL-CompressedModeMethod ::=           ENUMERATED {
    puncturing, sf-2,
    higherLayerScheduling }

DL-DPCH-InfoCommon ::=               SEQUENCE {
    cfnHandling                        CHOICE {
        maintain                        NULL,
        initialise                       SEQUENCE {
            cfntargetsfnframeoffset    Cfntargetsfnframeoffset  OPTIONAL
        }
    },
    modeSpecificInfo                  CHOICE {
        fdd                             SEQUENCE {
            dl-DPCH-PowerControlInfo    DL-DPCH-PowerControlInfo  OPTIONAL,
            powerOffsetPilot-pdpdch     PowerOffsetPilot-pdpdch,
            dl-rate-matching-restriction Dl-rate-matching-restriction  OPTIONAL,
            -- TABULAR: The number of pilot bits is nested inside the spreading factor.
            spreadingFactorAndPilot     SF512-AndPilot,
            positionFixedOrFlexible     PositionFixedOrFlexible,
            tfci-Existence              BOOLEAN
        },
        tdd                             SEQUENCE {
            dl-DPCH-PowerControlInfo    DL-DPCH-PowerControlInfo  OPTIONAL
        }
    }
}

DL-DPCH-InfoCommonPost ::=           SEQUENCE {
    dl-DPCH-PowerControlInfo          DL-DPCH-PowerControlInfo  OPTIONAL
}

DL-DPCH-InfoCommonPredef ::=         SEQUENCE {
    modeSpecificInfo                  CHOICE {
        fdd                             SEQUENCE {
            -- TABULAR: The number of pilot bits is nested inside the spreading factor.
            spreadingFactorAndPilot     SF512-AndPilot,
            positionFixedOrFlexible     PositionFixedOrFlexible,
            tfci-Existence              BOOLEAN
        },
        tdd                             SEQUENCE {
            commonTimeslotInfo          CommonTimeslotInfo
        }
    }
}

DL-DPCH-InfoPerRL ::=               CHOICE {
    fdd                                SEQUENCE {
        pCPICH-UsageForChannelEst      PCPICH-UsageForChannelEst,
        dpch-FrameOffset               DPCH-FrameOffset,
        secondaryCPICH-Info            SecondaryCPICH-Info  OPTIONAL,
        dl-ChannelisationCodeList     DL-ChannelisationCodeList,
        tpc-CombinationIndex           TPC-CombinationIndex,
        ssdt-CellIdentity              SSDT-CellIdentity  OPTIONAL,
        closedLoopTimingAdjMode        ClosedLoopTimingAdjMode  OPTIONAL
    },
}

```

<pre> tdd dl-CCTrChListToEstablish dl-CCTrChListToRemove } </pre>	<pre> SEQUENCE { DL-CCTrChList DL-CCTrChListToRemove } </pre>	<pre> OPTIONAL, OPTIONAL </pre>
<pre> DL-DPCH-InfoPerRL-r4 ::= fdd pCPICH-UsageForChannelEst dpch-FrameOffset secondaryCPICH-Info dl-ChannelisationCodeList tpc-CombinationIndex ssdt-CellIdentity closedLoopTimingAdjMode }, tdd dl-CCTrChListToEstablish dl-CCTrChListToRemove } </pre>	<pre> CHOICE { SEQUENCE { PCPICH-UsageForChannelEst, DPCH-FrameOffset, SecondaryCPICH-Info }, SEQUENCE { DL-CCTrChList-r4 DL-CCTrChListToRemove } } </pre>	<pre> OPTIONAL, OPTIONAL, OPTIONAL, OPTIONAL </pre>
<pre> DL-DPCH-InfoPerRL-PostFDD ::= pCPICH-UsageForChannelEst dl-ChannelisationCode tpc-CombinationIndex } </pre>	<pre> SEQUENCE { PCPICH-UsageForChannelEst, DL-ChannelisationCode, TPC-CombinationIndex } </pre>	
<pre> DL-DPCH-InfoPerRL-PostTDD ::= dl-DPCH-TimeslotsCodes } </pre>	<pre> SEQUENCE { DownlinkTimeslotsCodes } </pre>	
<pre> DL-DPCH-InfoPerRL-PostTDD-LCR-r4 ::= dl-CCTrCH-TimeslotsCodes } </pre>	<pre> SEQUENCE { DownlinkTimeslotsCodes-LCR-r4 } </pre>	
<pre> DL-DPCH-PowerControlInfo ::= modeSpecificInfo fdd dpc-Mode }, tdd tpc-StepSizeTDD } </pre>	<pre> SEQUENCE { CHOICE { SEQUENCE { DPC-Mode }, SEQUENCE { TPC-StepSizeTDD } } } </pre>	<pre> OPTIONAL </pre>
<pre> DL-FrameType ::= </pre>	<pre> ENUMERATED { dl-FrameTypeA, dl-FrameTypeB } </pre>	
<pre> DL-InformationPerRL ::= modeSpecificInfo fdd primaryCPICH-Info pdsch-SHO-DCH-Info pdsch-CodeMapping }, tdd PrimaryCCPCH-Info }, dl-DPCH-InfoPerRL sccpch-InfoForFACH } </pre>	<pre> SEQUENCE { CHOICE { SEQUENCE { PrimaryCPICH-Info, PDSCH-SHO-DCH-Info, PDSCH-CodeMapping }, PrimaryCCPCH-Info }, DL-DPCH-InfoPerRL SCCPCH-InfoForFACH } </pre>	<pre> OPTIONAL, OPTIONAL </pre>
<pre> DL-InformationPerRL-r4 ::= modeSpecificInfo fdd primaryCPICH-Info pdsch-SHO-DCH-Info pdsch-CodeMapping }, tdd PrimaryCCPCH-Info-r4 } </pre>	<pre> SEQUENCE { CHOICE { SEQUENCE { PrimaryCPICH-Info, PDSCH-SHO-DCH-Info, PDSCH-CodeMapping }, PrimaryCCPCH-Info-r4 } } </pre>	<pre> OPTIONAL, OPTIONAL </pre>

```

    },
    dl-DPCH-InfoPerRL          DL-DPCH-InfoPerRL-r4          OPTIONAL,
    sccpch-InfoForFACH        SCCPCH-InfoForFACH-r4        OPTIONAL,
    cell-id                    CellIdentity                OPTIONAL
}

DL-InformationPerRL-List ::= SEQUENCE (SIZE (1..maxRL)) OF
                             DL-InformationPerRL

DL-InformationPerRL-List-r4 ::= SEQUENCE (SIZE (1..maxRL)) OF
                               DL-InformationPerRL-r4

DL-InformationPerRL-ListPostFDD ::= SEQUENCE (SIZE (1..maxRL)) OF
                                     DL-InformationPerRL-PostFDD

DL-InformationPerRL-PostFDD ::= SEQUENCE {
    primaryCPICH-Info          PrimaryCPICH-Info,
    dl-DPCH-InfoPerRL         DL-DPCH-InfoPerRL-PostFDD
}

DL-InformationPerRL-PostTDD ::= SEQUENCE {
    primaryCCPCH-Info          PrimaryCCPCH-InfoPost,
    dl-DPCH-InfoPerRL         DL-DPCH-InfoPerRL-PostTDD
}

DL-InformationPerRL-PostTDD-LCR-r4 ::= SEQUENCE {
    primaryCCPCH-Info          PrimaryCCPCH-InfoPostTDD-LCR-r4,
    dl-DPCH-InfoPerRL         DL-DPCH-InfoPerRL-PostTDD-LCR-r4
}

DL-PDSCH-Information ::= SEQUENCE {
    pdsch-SHO-DCH-Info        PDSCH-SHO-DCH-Info          OPTIONAL,
    pdsch-CodeMapping         PDSCH-CodeMapping            OPTIONAL
}

Dl-rate-matching-restriction ::= SEQUENCE {
    restrictedTrCH-InfoList    RestrictedTrCH-InfoList      OPTIONAL
}

DL-TS-ChannelisationCode ::= ENUMERATED {
    cc16-1, cc16-2, cc16-3, cc16-4,
    cc16-5, cc16-6, cc16-7, cc16-8,
    cc16-9, cc16-10, cc16-11, cc16-12,
    cc16-13, cc16-14, cc16-15, cc16-16 }

DL-TS-ChannelisationCodesShort ::= SEQUENCE {
    codesRepresentation        CHOICE {
        consecutive            SEQUENCE {
            firstChannelisationCode    DL-TS-ChannelisationCode,
            lastChannelisationCode     DL-TS-ChannelisationCode
        },
        bitmap                 BIT STRING {
            chCode16-SF16(0),
            chCode15-SF16(1),
            chCode14-SF16(2),
            chCode13-SF16(3),
            chCode12-SF16(4),
            chCode11-SF16(5),
            chCode10-SF16(6),
            chCode9-SF16(7),
            chCode8-SF16(8),
            chCode7-SF16(9),
            chCode6-SF16(10),
            chCode5-SF16(11),
            chCode4-SF16(12),
            chCode3-SF16(13),
            chCode2-SF16(14),
            chCode1-SF16(15)
        } (SIZE (16))
    }
}

```



```

DownlinkAdditionalTimeslots ::= SEQUENCE {
    parameters CHOICE {
        sameAsLast SEQUENCE {
            timeslotNumber TimeslotNumber
        },
        newParameters SEQUENCE {
            individualTimeslotInfo IndividualTimeslotInfo,
            dl-TS-ChannelisationCodesShort DL-TS-ChannelisationCodesShort
        }
    }
}

DownlinkAdditionalTimeslots-LCR-r4 ::= SEQUENCE {
    parameters CHOICE {
        sameAsLast SEQUENCE {
            timeslotNumber TimeslotNumber-LCR-r4
        },
        newParameters SEQUENCE {
            individualTimeslotInfo IndividualTimeslotInfo-LCR-r4,
            dl-TS-ChannelisationCodesShort DL-TS-ChannelisationCodesShort
        }
    }
}

DownlinkTimeslotsCodes ::= SEQUENCE {
    firstIndividualTimeslotInfo IndividualTimeslotInfo,
    dl-TS-ChannelisationCodesShort DL-TS-ChannelisationCodesShort,
    moreTimeslots CHOICE {
        noMore NULL,
        additionalTimeslots CHOICE {
            consecutive INTEGER (1..maxTS-1),
            timeslotList SEQUENCE (SIZE (1..maxTS-1)) OF
                DownlinkAdditionalTimeslots
        }
    }
}

DownlinkTimeslotsCodes-LCR-r4 ::= SEQUENCE {
    firstIndividualTimeslotInfo IndividualTimeslotInfo-LCR-r4,
    dl-TS-ChannelisationCodesShort DL-TS-ChannelisationCodesShort,
    moreTimeslots CHOICE {
        noMore NULL,
        additionalTimeslots CHOICE {
            consecutive INTEGER (1..maxTS-LCR-1),
            timeslotList SEQUENCE (SIZE (1..maxTS-LCR-1)) OF
                DownlinkAdditionalTimeslots-LCR-r4
        }
    }
}

DPC-Mode ::= ENUMERATED {
    singleTPC,
    tpcTripletInSoft }

-- Actual value DPCCH-PowerOffset = IE value * 2
DPCCH-PowerOffset ::= INTEGER (-82..-3)

-- Actual value DPCCH-PowerOffset = 2 + (IE value * 4)
DPCCH-PowerOffset2 ::= INTEGER (-28..-13)

DPCH-CompressedModeInfo ::= SEQUENCE {
    tgp-SequenceList TGP-SequenceList
}

DPCH-CompressedModeStatusInfo ::= SEQUENCE {
    tgps-Reconfiguration-CFN TGPS-Reconfiguration-CFN,
    tgp-SequenceShortList SEQUENCE (SIZE (1..maxTGPS)) OF
        TGP-SequenceShort
}

```

```

-- Actual value DPCH-FrameOffset = IE value * 256
DPCH-FrameOffset ::= INTEGER (0..149)

DSCH-Mapping ::= SEQUENCE {
    maxTFCI-Field2Value
    spreadingFactor
    codeNumber
    multiCodeInfo
}

DSCH-MappingList ::= SEQUENCE (SIZE (1..maxPDSCH-TFCIgroups)) OF
    DSCH-Mapping

DSCH-RadioLinkIdentifier ::= INTEGER (0..511)

DurationTimeInfo ::= INTEGER (1..4096)

DynamicPersistenceLevel ::= INTEGER (1..8)

DynamicPersistenceLevelList ::= SEQUENCE (SIZE (1..maxPRACH)) OF
    DynamicPersistenceLevel

DynamicPersistenceLevelTF-List ::= SEQUENCE (SIZE (1..maxTF-CPCH)) OF
    DynamicPersistenceLevel

FACH-PCH-Information ::= SEQUENCE {
    transportFormatSet
    transportChannelIdentity
    ctch-Indicator
}

FACH-PCH-InformationList ::= SEQUENCE (SIZE (1..maxFACHPCH)) OF
    FACH-PCH-Information

FPACH-Info-r4 ::= SEQUENCE {
    timeslot
    channelisationCode
    midambleShiftAndBurstType
    wi
}

FrequencyInfo ::= SEQUENCE {
    modeSpecificInfo
    CHOICE {
        fdd
        tdd
    }
}

FrequencyInfoFDD ::= SEQUENCE {
    uarfcn-UL
    uarfcn-DL
}

FrequencyInfoTDD ::= SEQUENCE {
    uarfcn-Nt
}

IndividualTimeslotInfo ::= SEQUENCE {
    timeslotNumber
    tfci-Existence
    midambleShiftAndBurstType
}

IndividualTimeslotInfo-LCR-r4 ::= SEQUENCE {
    timeslotNumber
    tfci-Existence
    midambleShiftAndBurstType
    modulation
    ss-TPC-Symbols
    additionalSS-TPC-Symbols
}

```

```

}

IndividualTimeslotInfo-LCR-r4-ext ::= SEQUENCE {
-- timeslotNumber and tfci-Existence is taken from IndividualTimeslotInfo.
-- midambleShiftAndBurstType in IndividualTimeslotInfo shall be ignored.
    midambleShiftAndBurstType      MidambleShiftAndBurstType-LCR-r4,
    modulation                      ENUMERATED { mod-QPSK, mod-8PSK },
    ss-TPC-Symbols                  ENUMERATED { zero, one, sixteenOverSF }
}

IndividualTS-Interference ::= SEQUENCE {
    timeslot                        TimeslotNumber,
    ul-TimeslotInterference        TDD-UL-Interference
}

IndividualTS-InterferenceList ::= SEQUENCE (SIZE (1..maxTS)) OF
    IndividualTS-Interference

ITP ::= ENUMERATED {
    mode0, mode1 }

NidentifyAbort ::= INTEGER (1..128)

MaxAllowedUL-TX-Power ::= INTEGER (-50..33)

MaxAvailablePCPCH-Number ::= INTEGER (1..64)

MaxPowerIncrease-r4 ::= INTEGER (0..3)

MaxTFCI-Field2Value ::= INTEGER (1..1023)

MidambleConfigurationBurstTypeand3 ::= ENUMERATED {ms4, ms8, ms16}

MidambleConfigurationBurstType2 ::= ENUMERATED {ms3, ms6}

MidambleShiftAndBurstType ::= SEQUENCE {
    burstType                       CHOICE {
        type1                       SEQUENCE {
            midambleConfigurationBurstTypeand3 MidambleConfigurationBurstTypeand3,
            midambleAllocationMode             CHOICE {
                defaultMidamble             NULL,
                commonMidamble             NULL,
                ueSpecificMidamble         SEQUENCE {
                    midambleShift             MidambleShiftLong
                }
            }
        },
        type2                       SEQUENCE {
            midambleConfigurationBurstType2   MidambleConfigurationBurstType2,
            midambleAllocationMode             CHOICE {
                defaultMidamble             NULL,
                commonMidamble             NULL,
                ueSpecificMidamble         SEQUENCE {
                    midambleShift             MidambleShiftShort
                }
            }
        },
        type3                       SEQUENCE {
            midambleConfigurationBurstTypeand3 MidambleConfigurationBurstTypeand3,
            midambleAllocationMode             CHOICE {
                defaultMidamble             NULL,
                ueSpecificMidamble         SEQUENCE {
                    midambleShift             MidambleShiftLong
                }
            }
        }
    }
}

MidambleShiftAndBurstType-LCR-r4 ::= SEQUENCE {
    midambleAllocationMode           CHOICE {

```

```

        defaultMidamble                NULL,
        commonMidamble                 NULL,
        ueSpecificMidamble             SEQUENCE {
            midambleShift               INTEGER (0..15)
        }
    },
    -- Actual value midambleConfiguration = IE value * 2
    midambleConfiguration              INTEGER (1..8)
}

MidambleShiftLong ::=                 INTEGER (0..15)

MidambleShiftShort ::=                INTEGER (0..5)

MinimumSpreadingFactor ::=            ENUMERATED {
    sf4, sf8, sf16, sf32,
    sf64, sf128, sf256 }

MultiCodeInfo ::=                    INTEGER (1..16)

N-EOT ::=                             INTEGER (0..7)

N-GAP ::=                              ENUMERATED {
    f2, f4, f8 }

N-PCH ::=                              INTEGER (1..8)

N-StartMessage ::=                   INTEGER (1..8)

NB01 ::=                               INTEGER (0..50)

NF-Max ::=                             INTEGER (1..64)

NumberOfDPDCH ::=                     INTEGER (1..maxDPDCH-UL)

NumberOfFBI-Bits ::=                  INTEGER (1..2)

OpenLoopPowerControl-TDD ::=          SEQUENCE {
    primaryCCPCH-TX-Power              PrimaryCCPCH-TX-Power,
    -- alpha, prach-ConstantValue, dpch-ConstantValue and pusch-ConstantValue
    -- shall be ignored in 1.28Mcps TDD mode.
    alpha                              Alpha                                OPTIONAL,
    prach-ConstantValue                 ConstantValueTdd,
    dpch-ConstantValue                  ConstantValueTdd,
    pusch-ConstantValue                 ConstantValueTdd                    OPTIONAL
}

OpenLoopPowerControl-IPDL-TDD-r4 ::=  SEQUENCE {
    ipdl-alpha                          Alpha,
    maxPowerIncrease                    MaxPowerIncrease-r4
}

PagingIndicatorLength ::=              ENUMERATED {
    pi4, pi8, pi16 }

PC-Preamble ::=                       INTEGER (0..7)

PCP-Length ::=                         ENUMERATED {
    as0, as8 }

PCPCH-ChannelInfo ::=                 SEQUENCE {
    pcpch-UL-ScramblingCode             INTEGER (0..79),
    pcpch-DL-ChannelisationCode         INTEGER (0..511),
    pcpch-DL-ScramblingCode             SecondaryScramblingCode           OPTIONAL,
    pcp-Length                           PCP-Length,
    ucsm-Info                            UCSM-Info                          OPTIONAL
}

PCPCH-ChannelInfoList ::=              SEQUENCE (SIZE (1..maxPCPCHs)) OF

```

```

PCPCH-ChannelInfo
PCPICH-UsageForChannelEst ::= ENUMERATED {
    maybeUsed,
    shallNotBeUsed }

PDSCH-CapacityAllocationInfo ::= SEQUENCE {
    -- pdsch-PowerControlInfo is conditional on new-configuration branch below, if this
    -- selected the IE is OPTIONAL otherwise it should not be sent
    pdsch-PowerControlInfo PDSCH-PowerControlInfo OPTIONAL,
    pdsch-AllocationPeriodInfo AllocationPeriodInfo,
    configuration CHOICE {
        old-Configuration SEQUENCE {
            tfcs-ID TFCS-IdentityPlain DEFAULT 1,
            pdsch-Identity PDSCH-Identity
        },
        new-Configuration SEQUENCE {
            pdsch-Info PDSCH-Info,
            pdsch-Identity PDSCH-Identity OPTIONAL
        }
    }
}

PDSCH-CapacityAllocationInfo-r4 ::= SEQUENCE {
    pdsch-AllocationPeriodInfo AllocationPeriodInfo,
    configuration CHOICE {
        old-Configuration SEQUENCE {
            tfcs-ID TFCS-IdentityPlain DEFAULT 1,
            pdsch-Identity PDSCH-Identity
        },
        new-Configuration SEQUENCE {
            pdsch-Info PDSCH-Info-r4,
            pdsch-Identity PDSCH-Identity OPTIONAL,
            pdsch-PowerControlInfo PDSCH-PowerControlInfo OPTIONAL
        }
    }
}

PDSCH-CodeInfo ::= SEQUENCE {
    spreadingFactor SF-PDSCH,
    codeNumber CodeNumberDSCH,
    multiCodeInfo MultiCodeInfo
}

PDSCH-CodeInfoList ::= SEQUENCE (SIZE (1..maxTFCI-2-Combs)) OF
    PDSCH-CodeInfo

PDSCH-CodeMap ::= SEQUENCE {
    spreadingFactor SF-PDSCH,
    multiCodeInfo MultiCodeInfo,
    codeNumberStart CodeNumberDSCH,
    codeNumberStop CodeNumberDSCH
}

PDSCH-CodeMapList ::= SEQUENCE (SIZE (1..maxPDSCH-TFCIgroups)) OF
    PDSCH-CodeMap

PDSCH-CodeMapping ::= SEQUENCE {
    dl-ScramblingCode SecondaryScramblingCode OPTIONAL,
    signallingMethod CHOICE {
        codeRange CodeRange,
        tfci-Range DSCH-MappingList,
        explicit-config PDSCH-CodeInfoList,
        replace ReplacedPDSCH-CodeInfoList
    }
}

PDSCH-Identity ::= INTEGER (1..hiPDSCHidentities)

PDSCH-Info ::= SEQUENCE {

```

<pre> tfcs-ID commonTimeslotInfo pdsch-TimeslotsCodes } </pre>	<pre> TFCS-IdentityPlain CommonTimeslotInfo DownlinkTimeslotsCodes </pre>	<pre> DEFAULT 1, OPTIONAL, OPTIONAL </pre>
<pre> PDSCH-Info-r4 ::= tfcs-ID commonTimeslotInfo tddOption tdd384 pdsch-TimeslotsCodes }, tddl28 pdsch-TimeslotsCodes } } </pre>	<pre> SEQUENCE { TFCS-IdentityPlain CommonTimeslotInfo CHOICE { SEQUENCE { DownlinkTimeslotsCodes } SEQUENCE { DownlinkTimeslotsCodes-LCR-r4 } } } </pre>	<pre> DEFAULT 1, OPTIONAL, OPTIONAL OPTIONAL </pre>
<pre> PDSCH-Info-LCR-r4 ::= tfcs-ID commonTimeslotInfo pdsch-TimeslotsCodes } </pre>	<pre> SEQUENCE { TFCS-IdentityPlain CommonTimeslotInfo DownlinkTimeslotsCodes-LCR-r4 } </pre>	<pre> DEFAULT 1, OPTIONAL, OPTIONAL </pre>
<pre> PDSCH-PowerControlInfo ::= tpc-StepSizeTDD ul-CCTrChTPCList } </pre>	<pre> SEQUENCE { TPC-StepSizeTDD UL-CCTrChTPCList } </pre>	<pre> OPTIONAL, OPTIONAL </pre>
<pre> PDSCH-SHO-DCH-Info ::= dsch-RadioLinkIdentifier rl-IdentifierList } </pre>	<pre> SEQUENCE { DSCH-RadioLinkIdentifier, RL-IdentifierList } </pre>	<pre> OPTIONAL </pre>
<pre> PDSCH-SysInfo ::= pdsch-Identity pdsch-Info dsch-TFS dsch-TFCS } </pre>	<pre> SEQUENCE { PDSCH-Identity, PDSCH-Info, TransportFormatSet TFCS } </pre>	<pre> OPTIONAL, OPTIONAL </pre>
<pre> PDSCH-SysInfo-LCR-r4 ::= pdsch-Identity pdsch-Info dsch-TFS dsch-TFCS } </pre>	<pre> SEQUENCE { PDSCH-Identity, PDSCH-Info-LCR-r4, TransportFormatSet TFCS } </pre>	<pre> OPTIONAL, OPTIONAL </pre>
<pre> PDSCH-SysInfoList ::= </pre>	<pre> SEQUENCE (SIZE (1..maxPDSCH)) OF PDSCH-SysInfo </pre>	
<pre> PDSCH-SysInfoList-LCR-r4 ::= </pre>	<pre> SEQUENCE (SIZE (1..maxPDSCH)) OF PDSCH-SysInfo-LCR-r4 </pre>	
<pre> PDSCH-SysInfoList-SFN ::= pdsch-SysInfo sfn-TimeInfo } </pre>	<pre> SEQUENCE (SIZE (1..maxPDSCH)) OF SEQUENCE { PDSCH-SysInfo, SFN-TimeInfo } </pre>	<pre> OPTIONAL </pre>
<pre> PDSCH-SysInfoList-SFN-LCR-r4 ::= pdsch-SysInfo sfn-TimeInfo } </pre>	<pre> SEQUENCE (SIZE (1..maxPDSCH)) OF SEQUENCE { PDSCH-SysInfo-LCR-r4, SFN-TimeInfo } </pre>	<pre> OPTIONAL </pre>
<pre> PersistenceScalingFactor ::= </pre>	<pre> ENUMERATED { psf0-9, psf0-8, psf0-7, psf0-6, psf0-5, psf0-4, psf0-3, psf0-2 } </pre>	
<pre> PersistenceScalingFactorList ::= </pre>	<pre> SEQUENCE (SIZE (1..maxASCpersist)) OF </pre>	

```

PersistenceScalingFactor

PI-CountPerFrame ::=          ENUMERATED {
                                e18, e36, e72, e144 }

PichChannelisationCodeList-LCR-r4 ::=          SEQUENCE (SIZE (1..2)) OF
                                                DL-TS-ChannelisationCode

PICH-Info ::=                  CHOICE {
    fdd                          SEQUENCE {
        channelisationCode256      ChannelisationCode256,
        pi-CountPerFrame          PI-CountPerFrame,
        sttd-Indicator            BOOLEAN
    },
    tdd                          SEQUENCE {
        channelisationCode          TDD-PICH-CCode                OPTIONAL,
        timeslot                   TimeslotNumber                OPTIONAL,
        midambleShiftAndBurstType  MidambleShiftAndBurstType,
        repetitionPeriodLengthOffset RepPerLengthOffset-PICH    OPTIONAL,
        pagingIndicatorLength      PagingIndicatorLength        DEFAULT pi4,
        n-GAP                      N-GAP                        DEFAULT f4,
        n-PCH                      N-PCH                         DEFAULT 2
    }
}

PICH-Info-LCR-r4 ::=          SEQUENCE {
    timeslot                      TimeslotNumber-LCR-r4          OPTIONAL,
    pichChannelisationCodeList-LCR-r4 PichChannelisationCodeList-LCR-r4,
    midambleShiftAndBurstType     MidambleShiftAndBurstType-LCR-r4,
    repetitionPeriodLengthOffset  RepPerLengthOffset-PICH      OPTIONAL,
    pagingIndicatorLength         PagingIndicatorLength          DEFAULT pi4,
    n-GAP                         N-GAP                          DEFAULT f4,
    n-PCH                         N-PCH                           DEFAULT 2
}

PICH-PowerOffset ::=          INTEGER (-10..5)

PilotBits128 ::=              ENUMERATED {
                                pb4, pb8 }

PilotBits256 ::=              ENUMERATED {
                                pb2, pb4, pb8 }

PositionFixedOrFlexible ::=   ENUMERATED {
                                fixed,
                                flexible }

PowerControlAlgorithm ::=     CHOICE {
    algorithm1                    TPC-StepSizeFDD,
    algorithm2                    NULL
}

PowerOffsetPilot-pdpdch ::=   INTEGER (0..24)

PowerRampStep ::=              INTEGER (1..8)

PRACH-ChanCodes-LCR-r4 ::=    SEQUENCE (SIZE (1..4)) OF
                                TDD-PRACH-CCode-LCR-r4

PRACH-Definition-LCR-r4 ::=   SEQUENCE {
    timeslot                      TimeslotNumber-PRACH-LCR-r4,
    prach-ChanCodes-LCR           PRACH-ChanCodes-LCR-r4,
    midambleShiftAndBurstType     MidambleShiftAndBurstType-LCR-r4,
    fpach-Info                    FPACH-Info-r4
}

PRACH-Midamble ::=            ENUMERATED {
                                direct,
                                direct-Inverted }

PRACH-Partitioning ::=        CHOICE {

```

```

    fdd                SEQUENCE (SIZE (1..maxASC)) OF
                        ASCSetting-FDD,
    tdd                SEQUENCE (SIZE (1..maxASC)) OF
                        ASCSetting-TDD
}

PRACH-Partitioning-LCR-r4 ::= SEQUENCE (SIZE (1..maxASC)) OF
                              ASCSetting-TDD-LCR-r4

PRACH-PowerOffset ::= SEQUENCE {
    powerRampStep      PowerRampStep,
    preambleRetransMax PreambleRetransMax
}

PRACH-RACH-Info ::= SEQUENCE {
    modeSpecificInfo CHOICE {
        fdd SEQUENCE {
            availableSignatures AvailableSignatures,
            availableSF          SF-PRACH,
            preambleScramblingCodeWordNumber PreambleScramblingCodeWordNumber,
            puncturingLimit      PuncturingLimit,
            availableSubChannelNumbers AvailableSubChannelNumbers
        },
        tdd SEQUENCE {
            timeslot      TimeslotNumber,
            channelisationCodeList TDD-PRACH-CCodeList,
            prach-Midamble PRACH-Midamble
        }
    }
}

PRACH-RACH-Info-LCR-r4 ::= SEQUENCE {
    sync-UL-Info SYNC-UL-Info-r4,
    prach-DefinitionList SEQUENCE (SIZE (1..maxPRACH-FPACH)) OF
                          PRACH-Definition-LCR-r4
}

PRACH-SystemInformation ::= SEQUENCE {
    prach-RACH-Info PRACH-RACH-Info,
    transportChannelIdentity TransportChannelIdentity,
    rach-TransportFormatSet TransportFormatSet OPTIONAL,
    rach-TFCS TFCS OPTIONAL,
    prach-Partitioning PRACH-Partitioning OPTIONAL,
    persistenceScalingFactorList PersistenceScalingFactorList OPTIONAL,
    ac-To-ASC-MappingTable AC-To-ASC-MappingTable OPTIONAL,
    modeSpecificInfo CHOICE {
        fdd SEQUENCE {
            primaryCPICH-TX-Power PrimaryCPICH-TX-Power OPTIONAL,
            constantValue ConstantValue OPTIONAL,
            prach-PowerOffset PRACH-PowerOffset OPTIONAL,
            rach-TransmissionParameters RACH-TransmissionParameters OPTIONAL,
            aich-Info AICH-Info OPTIONAL
        },
        tdd NULL
    }
}

PRACH-SystemInformation-LCR-r4 ::= SEQUENCE {
    prach-RACH-Info-LCR PRACH-RACH-Info-LCR-r4,
    rach-TransportFormatSet-LCR TransportFormatSet-LCR OPTIONAL,
    prach-Partitioning-LCR PRACH-Partitioning-LCR-r4 OPTIONAL
}

PRACH-SystemInformationList ::= SEQUENCE (SIZE (1..maxPRACH)) OF
                              PRACH-SystemInformation

PRACH-SystemInformationList-LCR-r4 ::= SEQUENCE (SIZE (1..maxPRACH)) OF
                                       PRACH-SystemInformation-LCR-r4

PreambleRetransMax ::= INTEGER (1..64)

```



```

PreambleScramblingCodeWordNumber ::=    INTEGER (0..15)

PreDefPhyChConfiguration ::=            SEQUENCE {
    ul-DPCH-InfoPredef                    UL-DPCH-InfoPredef,
    dl-CommonInformationPredef            DL-CommonInformationPredef    OPTIONAL
}

PrimaryCCPCH-Info ::=                   CHOICE {
    fdd                                     SEQUENCE {
        tx-DiversityIndicator              BOOLEAN
    },
    tdd                                     SEQUENCE {
        -- syncCase should be ignored for 1.28Mcps TDD mode
        syncCase                           CHOICE {
            syncCase1                       SEQUENCE {
                timeslot                     TimeslotNumber
            },
            syncCase2                       SEQUENCE {
                timeslotSync2                TimeslotSync2
            }
        }
        cellParametersID                    CellParametersID            OPTIONAL,
        sctd-Indicator                       BOOLEAN                    OPTIONAL,
    }
}

PrimaryCCPCH-Info-r4 ::=                 CHOICE {
    fdd                                     SEQUENCE {
        tx-DiversityIndicator              BOOLEAN
    },
    tdd                                     SEQUENCE {
        tddOption                           CHOICE {
            tdd384                           SEQUENCE {
                syncCase                       CHOICE {
                    syncCase1                 SEQUENCE {
                        timeslot                TimeslotNumber
                    },
                    syncCase2                 SEQUENCE {
                        timeslotSync2          TimeslotSync2
                    }
                }
            },
            tdd128                           SEQUENCE {
                tstd-Indicator                 BOOLEAN
            }
        }
        cellParametersID                    CellParametersID            OPTIONAL,
        blockSTTD-Indicator                 BOOLEAN
    }
}

PrimaryCCPCH-Info-LCR-r4 ::=             SEQUENCE {
    tstd-Indicator                          BOOLEAN,
    cellParametersID                        CellParametersID            OPTIONAL,
    blockSTTD-Indicator                     BOOLEAN
}

-- For 1.28Mcps TDD, the following IE includes elements for the PCCPCH Info additional to those
-- in PrimaryCCPCH-Info
PrimaryCCPCH-Info-LCR-r4-ext ::=         SEQUENCE {
    tstd-Indicator                          BOOLEAN
}

PrimaryCCPCH-InfoPost ::=                SEQUENCE {
    syncCase                                 CHOICE {
        syncCase1                           SEQUENCE {
            timeslot                          TimeslotNumber
        },
        syncCase2                           SEQUENCE {
            timeslotSync2                     TimeslotSync2
        }
    }
}

```

```

    },
    cellParametersID          CellParametersID,
    sctd-Indicator            BOOLEAN
}

PrimaryCCPCH-InfoPostTDD-LCR-r4 ::= SEQUENCE {
    tstd-Indicator            BOOLEAN,
    cellParametersID          CellParametersID,
    blockSTTD-Indicator        BOOLEAN
}

PrimaryCCPCH-TX-Power ::=          INTEGER (6..43)

PrimaryCPICH-Info ::=              SEQUENCE {
    primaryScramblingCode      PrimaryScramblingCode
}

PrimaryCPICH-TX-Power ::=          INTEGER (-10..50)

PrimaryScramblingCode ::=          INTEGER (0..511)

PuncturingLimit ::=                ENUMERATED {
    p10-40, p10-44, p10-48, p10-52, p10-56,
    p10-60, p10-64, p10-68, p10-72, p10-76,
    p10-80, p10-84, p10-88, p10-92, p10-96, p11 }

PUSCH-CapacityAllocationInfo ::= SEQUENCE {
    pusch-Allocation          CHOICE {
        pusch-AllocationPending    NULL,
        pusch-AllocationAssignment SEQUENCE {
            pusch-AllocationPeriodInfo AllocationPeriodInfo,
            pusch-PowerControlInfo     UL-TargetSIR                OPTIONAL,
            configuration              CHOICE {
                old-Configuration      SEQUENCE {
                    tfcs-ID            TFCS-IdentityPlain          DEFAULT 1,
                    pusch-Identity     PUSCH-Identity
                },
                new-Configuration     SEQUENCE {
                    pusch-Info         PUSCH-Info,
                    pusch-Identity     PUSCH-Identity                OPTIONAL
                }
            }
        }
    }
}

PUSCH-CapacityAllocationInfo-r4 ::= SEQUENCE {
    pusch-Allocation          CHOICE {
        pusch-AllocationPending    NULL,
        pusch-AllocationAssignment SEQUENCE {
            pusch-AllocationPeriodInfo AllocationPeriodInfo,
            pusch-PowerControlInfo     PUSCH-PowerControlInfo-r4    OPTIONAL,
            configuration              CHOICE {
                old-Configuration      SEQUENCE {
                    tfcs-ID            TFCS-IdentityPlain          DEFAULT 1,
                    pusch-Identity     PUSCH-Identity
                },
                new-Configuration     SEQUENCE {
                    pusch-Info-r4      PUSCH-Info-r4,
                    pusch-Identity     PUSCH-Identity                OPTIONAL
                }
            }
        }
    }
}

PUSCH-Identity ::=                INTEGER (1..hiPUSCHidentities)

PUSCH-Info ::=                     SEQUENCE {
    tfcs-ID                      TFCS-IdentityPlain          DEFAULT 1,
    commonTimeslotInfo            CommonTimeslotInfo              OPTIONAL,
}

```

```

    pusch-TimeslotsCodes          UplinkTimeslotsCodes          OPTIONAL
}

PUSCH-Info-r4 ::=                SEQUENCE {
    tfcs-ID                       TFCS-IdentityPlain          DEFAULT 1,
    commonTimeslotInfo            CommonTimeslotInfo        OPTIONAL,
    tddOption                     CHOICE {
        tdd384                   SEQUENCE {
            pusch-TimeslotsCodes  UplinkTimeslotsCodes    OPTIONAL
        },
        tddl28                   SEQUENCE {
            pusch-TimeslotsCodes  UplinkTimeslotsCodes-LCR-r4 OPTIONAL
        }
    }
}

PUSCH-Info-LCR-r4 ::=           SEQUENCE {
    tfcs-ID                       TFCS-IdentityPlain          DEFAULT 1,
    commonTimeslotInfo            CommonTimeslotInfo        OPTIONAL,
    pusch-TimeslotsCodes          UplinkTimeslotsCodes-LCR-r4 OPTIONAL
}

PUSCH-PowerControlInfo-r4 ::=  SEQUENCE {
    -- The IE ul-TargetSIR corresponds to PRX-PUSCHdes for 1.28Mcps TDD
    -- Actual value PRX-PUSCHdes = (value of IE "ul-TargetSIR" - 120)
    ul-TargetSIR                 UL-TargetSIR,
    tddOption                     CHOICE {
        tdd384                   NULL,
        tddl28                   SEQUENCE {
            tpc-StepSize          TPC-StepSizeTDD          OPTIONAL,
            dl-CCTrChTPCList DL-CCTrChTPCList OPTIONAL
        }
    }
}

PUSCH-SysInfo ::=              SEQUENCE {
    pusch-Identity                PUSCH-Identity,
    pusch-Info                    PUSCH-Info,
    usch-TFS                      TransportFormatSet      OPTIONAL,
    usch-TFCS                    TFCS                      OPTIONAL
}

PUSCH-SysInfo-LCR-r4 ::=       SEQUENCE {
    pusch-Identity                PUSCH-Identity,
    pusch-Info                    PUSCH-Info-LCR-r4,
    usch-TFS                      TransportFormatSet      OPTIONAL,
    usch-TFCS                    TFCS                      OPTIONAL
}

PUSCH-SysInfoList ::=         SEQUENCE (SIZE (1..maxPUSCH)) OF
    PUSCH-SysInfo

PUSCH-SysInfoList-LCR-r4 ::=   SEQUENCE (SIZE (1..maxPUSCH)) OF
    PUSCH-SysInfo-LCR-r4

PUSCH-SysInfoList-SFN ::=     SEQUENCE (SIZE (1..maxPUSCH)) OF
    SEQUENCE {
        pusch-SysInfo            PUSCH-SysInfo,
        sfn-TimeInfo             SFN-TimeInfo          OPTIONAL
    }
}

PUSCH-SysInfoList-SFN-LCR-r4 ::= SEQUENCE (SIZE (1..maxPUSCH)) OF
    SEQUENCE {
        pusch-SysInfo            PUSCH-SysInfo-LCR-r4,
        sfn-TimeInfo             SFN-TimeInfo          OPTIONAL
    }
}

RACH-TransmissionParameters ::= SEQUENCE {
    mmax                          INTEGER (1..32),
    nb01Min                       NB01,
}

```

```

    nb01Max                NB01
}

ReducedScramblingCodeNumber ::=    INTEGER (0..8191)

RepetitionPeriodAndLength ::=    CHOICE {
    repetitionPeriod1        NULL,
    -- repetitionPeriod2 could just as well be NULL also.
    repetitionPeriod2        INTEGER (1..1),
    repetitionPeriod4        INTEGER (1..3),
    repetitionPeriod8        INTEGER (1..7),
    repetitionPeriod16       INTEGER (1..15),
    repetitionPeriod32       INTEGER (1..31),
    repetitionPeriod64       INTEGER (1..63)
}

RepetitionPeriodLengthAndOffset ::= CHOICE {
    repetitionPeriod1        NULL,
    repetitionPeriod2        SEQUENCE {
        length                NULL,
        offset                INTEGER (0..1)
    },
    repetitionPeriod4        SEQUENCE {
        length                INTEGER (1..3),
        offset                INTEGER (0..3)
    },
    repetitionPeriod8        SEQUENCE {
        length                INTEGER (1..7),
        offset                INTEGER (0..7)
    },
    repetitionPeriod16       SEQUENCE {
        length                INTEGER (1..15),
        offset                INTEGER (0..15)
    },
    repetitionPeriod32       SEQUENCE {
        length                INTEGER (1..31),
        offset                INTEGER (0..31)
    },
    repetitionPeriod64       SEQUENCE {
        length                INTEGER (1..63),
        offset                INTEGER (0..63)
    }
}

ReplacedPDSCH-CodeInfo ::=    SEQUENCE {
    tfci-Field2              MaxTFCI-Field2Value,
    spreadingFactor          SF-PDSCH,
    codeNumber               CodeNumberDSCH,
    multiCodeInfo            MultiCodeInfo
}

ReplacedPDSCH-CodeInfoList ::= SEQUENCE (SIZE (1..maxTFCI-2-Combs)) OF
    ReplacedPDSCH-CodeInfo

RepPerLengthOffset-PICH ::=    CHOICE {
    rpp4-2                  INTEGER (0..3),
    rpp8-2                  INTEGER (0..7),
    rpp8-4                  INTEGER (0..7),
    rpp16-2                 INTEGER (0..15),
    rpp16-4                 INTEGER (0..15),
    rpp32-2                 INTEGER (0..31),
    rpp32-4                 INTEGER (0..31),
    rpp64-2                 INTEGER (0..63),
    rpp64-4                 INTEGER (0..63)
}

RestrictedTrCH ::=            SEQUENCE {
    dl-restrictedTrCh-Type   DL-TrCH-Type,
    restrictedDL-TrCH-Identity TransportChannelIdentity,
    allowedTFIList           AllowedTFI-List
}

```

```

RestrictedTrCH-InfoList ::= SEQUENCE (SIZE(1..maxTrCH)) OF
                             RestrictedTrCH

RL-AdditionInformation ::= SEQUENCE {
    primaryCPICH-Info      PrimaryCPICH-Info,
    dl-DPCH-InfoPerRL     DL-DPCH-InfoPerRL,
    tfci-CombiningIndicator BOOLEAN,
    sccpch-InfoForFACH    SCCPCH-InfoForFACH
}
                                                                    OPTIONAL

RL-AdditionInformationList ::= SEQUENCE (SIZE (1..maxRL-1)) OF
                                RL-AdditionInformation

RL-IdentifierList ::= SEQUENCE (SIZE (1..maxRL)) OF
                       PrimaryCPICH-Info

RL-RemovalInformationList ::= SEQUENCE (SIZE (1..maxRL)) OF
                                PrimaryCPICH-Info

RPP ::= ENUMERATED {
    mode0, mode1 }

S-Field ::= ENUMERATED {
    elbit, e2bits }

SCCPCH-ChannelisationCode ::= ENUMERATED {
    cc16-1, cc16-2, cc16-3, cc16-4,
    cc16-5, cc16-6, cc16-7, cc16-8,
    cc16-9, cc16-10, cc16-11, cc16-12,
    cc16-13, cc16-14, cc16-15, cc16-16 }

SCCPCH-ChannelisationCodeList ::= SEQUENCE (SIZE (1..16)) OF
                                    SCCPCH-ChannelisationCode

SCCPCH-InfoForFACH ::= SEQUENCE {
    secondaryCCPCH-Info      SecondaryCCPCH-Info,
    tfcs                     TFCS,
    modeSpecificInfo        CHOICE {
        fdd                  SEQUENCE {
            fach-PCH-InformationList FACH-PCH-InformationList,
            sib-ReferenceListFACH    SIB-ReferenceListFACH
        },
        tdd                  SEQUENCE {
            fach-PCH-InformationList FACH-PCH-InformationList
        }
    }
}

SCCPCH-InfoForFACH-r4 ::= SEQUENCE {
    secondaryCCPCH-Info      SecondaryCCPCH-Info-r4,
    tfcs                     TFCS,
    fach-PCH-InformationList FACH-PCH-InformationList,
    modeSpecificInfo        CHOICE {
        fdd                  SEQUENCE {
            sib-ReferenceListFACH    SIB-ReferenceListFACH
        },
        tdd                  NULL
    }
}

SCCPCH-SystemInformation ::= SEQUENCE {
    secondaryCCPCH-Info      SecondaryCCPCH-Info,
    tfcs                     TFCS
                                                                    OPTIONAL,
    fach-PCH-InformationList FACH-PCH-InformationList
                                                                    OPTIONAL,
    pich-Info                PICH-Info
                                                                    OPTIONAL
}

SCCPCH-SystemInformation-LCR-r4-ext ::= SEQUENCE {
    secondaryCCPCH-LCR-Extensions SecondaryCCPCH-Info-LCR-r4-ext,
    -- pich-Info in the SCCPCH-SystemInformation IE shall be absent,
}

```

```

-- and instead the following used.
pich-Info          PICH-Info-LCR-r4          OPTIONAL
}

SCCPCH-SystemInformationList ::= SEQUENCE (SIZE (1..maxSCCPCH)) OF
    SCCPCH-SystemInformation

-- SCCPCH-SystemInformationList-LCR-r4-ext includes elements additional to those in
-- SCCPCH-SystemInformationList for the 1.28Mcps TDD. The order of the IEs
-- indicates which SCCPCH-SystemInformation-LCR-r4-ext IE extends which
-- SCCPCH-SystemInformation IE.
SCCPCH-SystemInformationList-LCR-r4-ext ::= SEQUENCE (SIZE (1..maxSCCPCH)) OF
    SCCPCH-SystemInformation-LCR-r4-ext

ScramblingCodeChange ::= ENUMERATED {
    codeChange, noCodeChange }

ScramblingCodeType ::= ENUMERATED {
    shortSC,
    longSC }

SecondaryCCPCH-Info ::= SEQUENCE {
    modeSpecificInfo CHOICE {
        fdd SEQUENCE {
            -- dummy1 is not used in this version of the specification and should be ignored.
            dummy1 PCPICH-UsageForChannelEst,
            -- dummy2 is not used in this version of the specification. It should not
            -- be sent and if received it should be ignored.
            dummy2 SecondaryCPICH-Info OPTIONAL,
            secondaryScramblingCode SecondaryScramblingCode OPTIONAL,
            sttd-Indicator BOOLEAN,
            sf-AndCodeNumber SF256-AndCodeNumber,
            pilotSymbolExistence BOOLEAN,
            tfci-Existence BOOLEAN,
            positionFixedOrFlexible PositionFixedOrFlexible,
            timingOffset TimingOffset DEFAULT 0
        },
        tdd SEQUENCE {
            -- TABULAR: the offset is included in CommonTimeslotInfoSCCPCH
            commonTimeslotInfo CommonTimeslotInfoSCCPCH,
            individualTimeslotInfo IndividualTimeslotInfo,
            channelisationCode SCCPCH-ChannelisationCodeList
        }
    }
}

SecondaryCCPCH-Info-r4 ::= SEQUENCE {
    modeSpecificInfo CHOICE {
        fdd SEQUENCE {
            secondaryScramblingCode SecondaryScramblingCode OPTIONAL,
            sttd-Indicator BOOLEAN,
            sf-AndCodeNumber SF256-AndCodeNumber,
            pilotSymbolExistence BOOLEAN,
            tfci-Existence BOOLEAN,
            positionFixedOrFlexible PositionFixedOrFlexible,
            timingOffset TimingOffset DEFAULT 0
        },
        tdd SEQUENCE {
            -- TABULAR: the offset is included in CommonTimeslotInfoSCCPCH
            commonTimeslotInfo CommonTimeslotInfoSCCPCH,
            tddOption CHOICE {
                tdd384 SEQUENCE {
                    individualTimeslotInfo IndividualTimeslotInfo
                },
                tdd128 SEQUENCE {
                    individualTimeslotInfo IndividualTimeslotInfo-LCR-r4
                }
            }
        },
        channelisationCode SCCPCH-ChannelisationCodeList
    }
}

```

```

}

SecondaryCCPCH-Info-LCR-r4-ext ::= SEQUENCE {
    individualTimeslotLCR-Ext      IndividualTimeslotInfo-LCR-r4-ext
}

SecondaryCPICH-Info ::= SEQUENCE {
    secondaryDL-ScramblingCode      SecondaryScramblingCode          OPTIONAL,
    channelisationCode              ChannelisationCode256
}

SecondaryScramblingCode ::= INTEGER (1..15)

SecondInterleavingMode ::= ENUMERATED {
    frameRelated, timeslotRelated }

-- SF256-AndCodeNumber encodes both "Spreading factor" and "Code Number"
SF256-AndCodeNumber ::= CHOICE {
    sf4          INTEGER (0..3),
    sf8          INTEGER (0..7),
    sf16         INTEGER (0..15),
    sf32         INTEGER (0..31),
    sf64         INTEGER (0..63),
    sf128        INTEGER (0..127),
    sf256        INTEGER (0..255)
}

-- SF512-AndCodeNumber encodes both "Spreading factor" and "Code Number"
SF512-AndCodeNumber ::= CHOICE {
    sf4          INTEGER (0..3),
    sf8          INTEGER (0..7),
    sf16         INTEGER (0..15),
    sf32         INTEGER (0..31),
    sf64         INTEGER (0..63),
    sf128        INTEGER (0..127),
    sf256        INTEGER (0..255),
    sf512        INTEGER (0..511)
}

-- SF512-AndPilot encodes both "Spreading factor" and "Number of bits for Pilot bits"
SF512-AndPilot ::= CHOICE {
    sfd4         NULL,
    sfd8         NULL,
    sfd16        NULL,
    sfd32        NULL,
    sfd64        NULL,
    sfd128       PilotBits128,
    sfd256       PilotBits256,
    sfd512       NULL
}

SF-PDSCH ::= ENUMERATED {
    sfp4, sfp8, sfp16, sfp32,
    sfp64, sfp128, sfp256 }

SF-PRACH ::= ENUMERATED {
    sfpr32, sfpr64, sfpr128, sfpr256 }

SFN-TimeInfo ::= SEQUENCE {
    activationTimeSFN      INTEGER (0..4095),
    physChDuration         DurationTimeInfo
}

SpecialBurstScheduling ::= INTEGER (0..7)

SpreadingFactor ::= ENUMERATED {
    sf4, sf8, sf16, sf32,
    sf64, sf128, sf256 }

SRB-delay ::= INTEGER (0..7)

SSDT-CellIdentity ::= ENUMERATED {

```

```

        ssdt-id-a, ssdt-id-b, ssdt-id-c,
        ssdt-id-d, ssdt-id-e, ssdt-id-f,
        ssdt-id-g, ssdt-id-h }

SSDT-Information ::=          SEQUENCE {
    s-Field                    S-Field,
    codeWordSet                CodeWordSet
}

SSDT-Information-r4 ::=      SEQUENCE {
    s-Field                    S-Field,
    codeWordSet                CodeWordSet,
    ssdt-UL                    SSDT-UL-r4
}
                                                                    OPTIONAL

-- SSDT-UL-r4 is used to extend the
-- SSDT-Information IE from Release 4 onwards.
SSDT-UL-r4 ::=              ENUMERATED {
    ul, ul-AndDL }

SynchronisationParameters-r4 ::= SEQUENCE {
    sync-UL-CodesBitmap        BIT STRING {
        code7(0),
        code6(1),
        code5(2),
        code4(3),
        code3(4),
        code2(5),
        code1(6),
        code0(7)
    } (SIZE (8)),
    fpach-Info                 FPACH-Info-r4,
    -- Actual value prxUpPCHdes = IE value - 120
    prxUpPCHdes                INTEGER (0..62),
    sync-UL-Procedure          SYNC-UL-Procedure-r4
}
                                                                    OPTIONAL

SYNC-UL-Procedure-r4 ::=    SEQUENCE {
    max-SYNC-UL-Transmissions  ENUMERATED { tr1, tr2, tr4, tr8 },
    powerRampStep              INTEGER (0..3)
}

SYNC-UL-Info-r4 ::=        SEQUENCE {
    sync-UL-CodesBitmap        BIT STRING {
        code7(0),
        code6(1),
        code5(2),
        code4(3),
        code3(4),
        code2(5),
        code1(6),
        code0(7)
    } ( SIZE (8)),
    -- Actual value prxUpPCHdes = IE value - 120
    prxUpPCHdes                INTEGER (0..62),
    powerRampStep              INTEGER (0..3),
    max-SYNC-UL-Transmissions  ENUMERATED { tr1, tr2, tr4, tr8 } ,
    mmax                       INTEGER(1..32)
}

TDD-FPACH-CCode16-r4 ::=   ENUMERATED {
    cc16-1, cc16-2, cc16-3, cc16-4,
    cc16-5, cc16-6, cc16-7, cc16-8,
    cc16-9, cc16-10, cc16-11, cc16-12,
    cc16-13, cc16-14, cc16-15, cc16-16 }

TDD-UL-Interference ::=    INTEGER (-110..-52)

TDD-PICH-CCode ::=         ENUMERATED {
    cc16-1, cc16-2, cc16-3, cc16-4,
    cc16-5, cc16-6, cc16-7, cc16-8,

```



```

        cc16-9, cc16-10, cc16-11, cc16-12,
        cc16-13, cc16-14, cc16-15, cc16-16 }

TDD-PRACH-CCode8 ::=          ENUMERATED {
                                cc8-1, cc8-2, cc8-3, cc8-4,
                                cc8-5, cc8-6, cc8-7, cc8-8 }

TDD-PRACH-CCode16 ::=        ENUMERATED {
                                cc16-1, cc16-2, cc16-3, cc16-4,
                                cc16-5, cc16-6, cc16-7, cc16-8,
                                cc16-9, cc16-10, cc16-11, cc16-12,
                                cc16-13, cc16-14, cc16-15, cc16-16 }

TDD-PRACH-CCode-LCR-r4 ::=   ENUMERATED {
                                cc4-1, cc4-2, cc4-3, cc4-4,
                                cc8-1, cc8-2, cc8-3, cc8-4,
                                cc8-5, cc8-6, cc8-7, cc8-8,
                                cc16-1, cc16-2, cc16-3, cc16-4,
                                cc16-5, cc16-6, cc16-7, cc16-8,
                                cc16-9, cc16-10, cc16-11, cc16-12,
                                cc16-13, cc16-14, cc16-15, cc16-16 }

TDD-PRACH-CCodeList ::=     CHOICE {
                                sf8
                                SEQUENCE (SIZE (1..8)) OF
                                    TDD-PRACH-CCode8,
                                sf16
                                SEQUENCE (SIZE (1..8)) OF
                                    TDD-PRACH-CCode16
                                }

TFC-ControlDuration ::=      ENUMERATED {
                                tfc-cd1, tfc-cd2, tfc-cd4, tfc-cd8,
                                tfc-cd16, tfc-cd24, tfc-cd32,
                                tfc-cd48, tfc-cd64, tfc-cd128,
                                tfc-cd192, tfc-cd256, tfc-cd512 }

TFCI-Coding ::=             ENUMERATED {
                                tfci-bits-4, tfci-bits-8,
                                tfci-bits-16, tfci-bits-32 }

TGCFN ::=                   INTEGER (0..255)

-- In TGD, value 270 represents "undefined" in the tabular description.
TGD ::=                     INTEGER (15..270)

TGL ::=                     INTEGER (1..14)

TGMP ::=                    ENUMERATED {
                                tdd-Measurement, fdd-Measurement,
                                gsm-CarrierRSSIMeasurement,
                                gsm-initialBSICIdentification, gsmBSICReconfirmation,
                                multi-carrier }

TGP-Sequence ::=           SEQUENCE {
                                tgpsi
                                tgps-Status
                                activate
                                tgcfn
                                },
                                deactivate
                                },
                                tgps-ConfigurationParams
                                TGPS-ConfigurationParams
                                OPTIONAL
                                }

TGPS-Reconfiguration-CFN ::= INTEGER (0..255)

TGP-SequenceList ::=       SEQUENCE (SIZE (1..maxTGPS)) OF
                                TGP-Sequence

TGP-SequenceShort ::=      SEQUENCE {
                                tgpsi
                                tgps-Status
                                CHOICE {

```

```

        activate                SEQUENCE {
            tgcfn                TGCFN
        },
        deactivate              NULL
    }
}

TGPL ::=                        INTEGER (1..144)

-- TABULAR: In TGPRC, value 0 represents "infinity" in the tabular description.
TGPRC ::=                       INTEGER (0..511)

TGPS-ConfigurationParams ::=    SEQUENCE {
    tgmp                        TGMP,
    tgprc                       TGPRC,
    tgsn                        TGSN,
    tgl1                         TGL,
    tgl2                         TGL,
    tgd                          TGD,
    tgpl1                       TGPL,
    tgpl2                       TGPL,
    rpp                          RPP,
    itp                          ITP,
    -- TABULAR: Compressed mode method is nested inside UL-DL-Mode
    ul-DL-Mode                  UL-DL-Mode,
    dl-FrameType                DL-FrameType,
    deltaSIR1                   DeltaSIR,
    deltaSIRAfter1              DeltaSIR,
    deltaSIR2                   DeltaSIR,
    deltaSIRAfter2              DeltaSIR,
    nidentifyAbort              NidentifyAbort,
    treconfirmAbort              TreconfirmAbort
}

TGPSI ::=                       INTEGER (1..maxTGPS)

TGSN ::=                       INTEGER (0..14)

TimeInfo ::=                    SEQUENCE {
    activationTime              ActivationTime,
    durationTimeInfo            DurationTimeInfo
}

TimeslotList ::=               SEQUENCE (SIZE (1..maxTS)) OF
    TimeslotNumber

TimeslotList-r4 ::=            CHOICE {
    tdd384                      SEQUENCE (SIZE (1..maxTS)) OF
        TimeslotNumber,
    tdd128                      SEQUENCE (SIZE (1..maxTS-LCR)) OF
        TimeslotNumber-LCR-r4
}

-- If TimeslotNumber is included for a 1.28Mcps TDD description, it shall take values from 0..6
TimeslotNumber ::=            INTEGER (0..14)

TimeslotNumber-LCR-r4 ::=      INTEGER (0..6)

TimeslotNumber-PRACH-LCR-r4 ::=  INTEGER (1..6)

TimeslotSync2 ::=              INTEGER (0..6)

-- Actual value TimingOffset = IE value * 256
TimingOffset ::=              INTEGER (0..149)

TPC-CombinationIndex ::=      INTEGER (0..5)

-- Actual value TPC-StepSizeFDD = IE value + 1
TPC-StepSizeFDD ::=           INTEGER (0..1)

TPC-StepSizeTDD ::=           INTEGER (1..3)

```

```

-- Actual value TreconfirmAbort = IE value * 0.5 seconds
TreconfirmAbort ::= INTEGER (1..20)

TX-DiversityMode ::=
    ENUMERATED {
        noDiversity,
        sttd,
        closedLoopModel1,
        closedLoopMode2 }

UARFCN ::=
    INTEGER (0..16383)

UCSM-Info ::=
    SEQUENCE {
        minimumSpreadingFactor MinimumSpreadingFactor,
        nf-Max NF-Max,
        channelReqParamsForUCSM ChannelReqParamsForUCSM
    }

UL-CCTrCH ::=
    SEQUENCE {
        tfcs-ID TFCS-IdentityPlain DEFAULT 1,
        ul-TargetSIR UL-TargetSIR,
        timeInfo TimeInfo,
        commonTimeslotInfo CommonTimeslotInfo OPTIONAL,
        ul-CCTrCH-TimeslotsCodes UplinkTimeslotsCodes OPTIONAL
    }

UL-CCTrCH-r4 ::=
    SEQUENCE {
        tfcs-ID TFCS-IdentityPlain DEFAULT 1,
        ul-TargetSIR UL-TargetSIR,
        timeInfo TimeInfo,
        commonTimeslotInfo CommonTimeslotInfo OPTIONAL,
        tddOption CHOICE {
            tdd384 SEQUENCE {
                ul-CCTrCH-TimeslotsCodes UplinkTimeslotsCodes OPTIONAL
            },
            tdd128 SEQUENCE {
                ul-CCTrCH-TimeslotsCodes UplinkTimeslotsCodes-LCR-r4 OPTIONAL
            }
        }
    }

UL-CCTrCHList ::=
    SEQUENCE (SIZE (1..maxCCTrCH)) OF
        UL-CCTrCH

UL-CCTrCHList-r4 ::=
    SEQUENCE (SIZE (1..maxCCTrCH)) OF
        UL-CCTrCH-r4

UL-CCTrCHListToRemove ::=
    SEQUENCE (SIZE (1..maxCCTrCH)) OF
        TFCS-IdentityPlain

UL-CCTrChTPCList ::=
    SEQUENCE (SIZE (0..maxCCTrCH)) OF
        TFCS-Identity

UL-ChannelRequirement ::=
    CHOICE {
        ul-DPCH-Info UL-DPCH-Info,
        cpch-SetInfo CPCH-SetInfo
    }

UL-ChannelRequirement-r4 ::=
    CHOICE {
        ul-DPCH-Info UL-DPCH-Info-r4,
        cpch-SetInfo CPCH-SetInfo
    }

UL-ChannelRequirementWithCPCH-SetID ::= CHOICE {
        ul-DPCH-Info UL-DPCH-Info,
        cpch-SetInfo CPCH-SetInfo,
        cpch-SetID CPCH-SetID
    }

UL-ChannelRequirementWithCPCH-SetID-r4 ::= CHOICE {
        ul-DPCH-Info UL-DPCH-Info-r4,

```

```

    cpch-SetInfo          CPCH-SetInfo,
    cpch-SetID           CPCH-SetID
}

UL-CompressedModeMethod ::=          ENUMERATED {
    sf-2,
    higherLayerScheduling }

UL-DL-Mode ::=                      CHOICE {
    ul          UL-CompressedModeMethod,
    dl          DL-CompressedModeMethod,
    ul-and-dl   SEQUENCE {
        ul      UL-CompressedModeMethod,
        dl      DL-CompressedModeMethod
    }
}

UL-DPCCH-SlotFormat ::=             ENUMERATED {
    slf0, slf1, slf2 }

UL-DPCH-Info ::=                   SEQUENCE {
    ul-DPCH-PowerControlInfo        UL-DPCH-PowerControlInfo        OPTIONAL,
    modeSpecificInfo                CHOICE {
        fdd                          SEQUENCE {
            scramblingCodeType        ScramblingCodeType,
            scramblingCode             UL-ScramblingCode,
            numberOfDPDCH              NumberOfDPDCH                DEFAULT 1,
            spreadingFactor            SpreadingFactor,
            tfci-Existence             BOOLEAN,
            -- numberOfFBI-Bits is conditional based on history
            numberOfFBI-Bits           NumberOfFBI-Bits            OPTIONAL,
            puncturingLimit            PuncturingLimit
        },
        tdd                          SEQUENCE {
            ul-TimingAdvance           UL-TimingAdvanceControl    OPTIONAL,
            ul-CCTrCHList              UL-CCTrCHList            OPTIONAL,
            ul-CCTrCHListToRemove      UL-CCTrCHListToRemove    OPTIONAL
        }
    }
}

UL-DPCH-Info-r4 ::=                SEQUENCE {
    ul-DPCH-PowerControlInfo-r4      UL-DPCH-PowerControlInfo-r4    OPTIONAL,
    modeSpecificInfo-r4              CHOICE {
        fdd                          SEQUENCE {
            scramblingCodeType        ScramblingCodeType,
            scramblingCode             UL-ScramblingCode,
            numberOfDPDCH              NumberOfDPDCH                DEFAULT 1,
            spreadingFactor            SpreadingFactor,
            tfci-Existence             BOOLEAN,
            -- numberOfFBI-Bits is conditional based on history
            numberOfFBI-Bits           NumberOfFBI-Bits            OPTIONAL,
            puncturingLimit            PuncturingLimit
        },
        tdd                          SEQUENCE {
            ul-TimingAdvance           UL-TimingAdvanceControl-r4  OPTIONAL,
            ul-CCTrCHList              UL-CCTrCHList-r4          OPTIONAL,
            ul-CCTrCHListToRemove      UL-CCTrCHListToRemove    OPTIONAL
        }
    }
}

UL-DPCH-InfoPostFDD ::=            SEQUENCE {
    ul-DPCH-PowerControlInfoPostFDD UL-DPCH-PowerControlInfoPostFDD,
    scramblingCodeType               ScramblingCodeType,
    reducedScramblingCodeNumber       ReducedScramblingCodeNumber,
    spreadingFactor                   SpreadingFactor
}

UL-DPCH-InfoPostTDD ::=            SEQUENCE {
    ul-DPCH-PowerControlInfoPostTDD UL-DPCH-PowerControlInfoPostTDD,

```

```

    ul-TimingAdvance                UL-TimingAdvanceControl                OPTIONAL,
    ul-CCTrCH-TimeslotsCodes        UplinkTimeslotsCodes
}

UL-DPCH-InfoPostTDD-LCR-r4 ::=    SEQUENCE {
    ul-DPCH-PowerControlInfo        UL-DPCH-PowerControlInfoPostTDD-LCR-r4,
    ul-TimingAdvance                UL-TimingAdvanceControl-LCR-r4        OPTIONAL,
    ul-CCTrCH-TimeslotsCodes        UplinkTimeslotsCodes-LCR-r4
}

UL-DPCH-InfoPredef ::=            SEQUENCE {
    ul-DPCH-PowerControlInfo        UL-DPCH-PowerControlInfoPredef,
    modeSpecificInfo                CHOICE {
        fdd                          SEQUENCE {
            tfci-Existence            BOOLEAN,
            puncturingLimit          PuncturingLimit
        },
        tdd                          SEQUENCE {
            commonTimeslotInfo        CommonTimeslotInfo
        }
    }
}

UL-DPCH-PowerControlInfo ::=      CHOICE {
    fdd                              SEQUENCE {
        dpcch-PowerOffset            DPCCH-PowerOffset,
        pc-Preamble                  PC-Preamble,
        srb-delay                    SRB-delay,
        -- TABULAR: TPC step size nested inside PowerControlAlgorithm
        powerControlAlgorithm        PowerControlAlgorithm
    },
    tdd                              SEQUENCE {
        ul-TargetSIR                 UL-TargetSIR                OPTIONAL,
        ul-OL-PC-Signalling           CHOICE {
            broadcast-UL-OL-PC-info   NULL,
            individuallySignalled     SEQUENCE {
                individualTS-InterferenceList IndividualTS-InterferenceList,
                dpch-ConstantValue     ConstantValueTdd,
                primaryCCPCH-TX-Power  PrimaryCCPCH-TX-Power
            }
        }
    }
}

UL-DPCH-PowerControlInfo-r4 ::=    CHOICE {
    fdd                              SEQUENCE {
        dpcch-PowerOffset            DPCCH-PowerOffset,
        pc-Preamble                  PC-Preamble,
        srb-delay                    SRB-delay,
        -- TABULAR: TPC step size nested inside PowerControlAlgorithm
        powerControlAlgorithm        PowerControlAlgorithm
    },
    tdd                              SEQUENCE {
        -- The IE ul-TargetSIR corresponds to PRX-PDPCHdes for 1.28Mcps TDD
        -- Actual value PRX-PDPCHdes = (value of IE "ul-TargetSIR" - 120)
        ul-TargetSIR                 UL-TargetSIR                OPTIONAL,
        ul-OL-PC-Signalling           CHOICE {
            broadcast-UL-OL-PC-info   NULL,
            individuallySignalled     SEQUENCE {
                tddOption              CHOICE {
                    tdd384              SEQUENCE {
                        individualTS-InterferenceList IndividualTS-InterferenceList,
                        dpch-ConstantValue ConstantValue
                    },
                    tdd128              SEQUENCE {
                        tpc-StepSize     TPC-StepSizeTDD
                    }
                }
            },
            primaryCCPCH-TX-Power     PrimaryCCPCH-TX-Power
        }
    }
}

```

```

    }
}

UL-DPCH-PowerControlInfoPostFDD ::= SEQUENCE {
    -- DPCCH-PowerOffset2 has a smaller range to save bits
    dpccch-PowerOffset          DPCCH-PowerOffset2,
    pc-Preamble                  PC-Preamble,
    srb-delay                     SRB-delay
}

UL-DPCH-PowerControlInfoPostTDD ::= SEQUENCE {
    ul-TargetSIR                 UL-TargetSIR,
    ul-TimeslotInterference      TDD-UL-Interference
}

UL-DPCH-PowerControlInfoPostTDD-LCR-r4 ::= SEQUENCE {
    ul-TargetSIR                 UL-TargetSIR
}

UL-DPCH-PowerControlInfoPredef ::= CHOICE {
    fdd                          SEQUENCE {
        -- TABULAR: TPC step size nested inside PowerControlAlgorithm
        powerControlAlgorithm     PowerControlAlgorithm
    },
    tdd                          SEQUENCE {
        -- dpch-ConstantValue shall be ignored if in 1.28Mcps TDD mode.
        dpch-ConstantValue        ConstantValueTdd
    }
}

UL-Interference ::= INTEGER (-110..-70)

UL-ScramblingCode ::= INTEGER (0..16777215)

UL-SynchronisationParameters-r4 ::= SEQUENCE {
    stepSize                     INTEGER (1..8),
    frequency                     INTEGER (1..8)
}

-- Actual value UL-TargetSIR = (IE value * 0.5) - 11
UL-TargetSIR ::= INTEGER (0..62)

UL-TimingAdvance ::= INTEGER (0..63)

UL-TimingAdvanceControl ::= CHOICE {
    disabled                     NULL,
    enabled                       SEQUENCE {
        ul-TimingAdvance          UL-TimingAdvance          OPTIONAL,
        activationTime             ActivationTime             OPTIONAL
    }
}

UL-TimingAdvanceControl-r4 ::= CHOICE {
    disabled                     NULL,
    enabled                       SEQUENCE {
        tddOption                 CHOICE {
            tdd384                 SEQUENCE {
                ul-TimingAdvance    UL-TimingAdvance          OPTIONAL,
                activationTime       ActivationTime             OPTIONAL
            },
            tdd128                 SEQUENCE {
                ul-SynchronisationParameters    UL-SynchronisationParameters-r4 OPTIONAL,
                synchronisationParameters    SynchronisationParameters-r4  OPTIONAL
            }
        }
    }
}

UL-TimingAdvanceControl-LCR-r4 ::= CHOICE {
    disabled                     NULL,

```

```

    enabled                SEQUENCE {
        ul-SynchronisationParameters  UL-SynchronisationParameters-r4 OPTIONAL,
        synchronisationParameters     SynchronisationParameters-r4   OPTIONAL
    }
}

UL-TS-ChannelisationCode ::=          ENUMERATED {
    cc1-1, cc2-1, cc2-2,
    cc4-1, cc4-2, cc4-3, cc4-4,
    cc8-1, cc8-2, cc8-3, cc8-4,
    cc8-5, cc8-6, cc8-7, cc8-8,
    cc16-1, cc16-2, cc16-3, cc16-4,
    cc16-5, cc16-6, cc16-7, cc16-8,
    cc16-9, cc16-10, cc16-11, cc16-12,
    cc16-13, cc16-14, cc16-15, cc16-16 }

UL-TS-ChannelisationCodeList ::=     SEQUENCE (SIZE (1..2)) OF
    UL-TS-ChannelisationCode

UplinkAdditionalTimeslots ::=        SEQUENCE {
    parameters                CHOICE {
        sameAsLast            SEQUENCE {
            timeslotNumber    TimeslotNumber
        },
        newParameters         SEQUENCE {
            individualTimeslotInfo  IndividualTimeslotInfo,
            ul-TS-ChannelisationCodeList  UL-TS-ChannelisationCodeList
        }
    }
}

UplinkAdditionalTimeslots-LCR-r4 ::= SEQUENCE {
    parameters                CHOICE {
        sameAsLast            SEQUENCE {
            timeslotNumber    TimeslotNumber
        },
        newParameters         SEQUENCE {
            individualTimeslotInfo  IndividualTimeslotInfo-LCR-r4,
            ul-TS-ChannelisationCodeList  UL-TS-ChannelisationCodeList
        }
    }
}

UplinkTimeslotsCodes ::=            SEQUENCE {
    dynamicSFusage            BOOLEAN,
    firstIndividualTimeslotInfo  IndividualTimeslotInfo,
    ul-TS-ChannelisationCodeList  UL-TS-ChannelisationCodeList,
    moreTimeslots             CHOICE {
        noMore                NULL,
        additionalTimeslots   CHOICE {
            consecutive        SEQUENCE {
                numAdditionalTimeslots  INTEGER (1..maxTS-1)
            },
            timeslotList      SEQUENCE (SIZE (1..maxTS-1)) OF
                UplinkAdditionalTimeslots
        }
    }
}

UplinkTimeslotsCodes-LCR-r4 ::=     SEQUENCE {
    dynamicSFusage            BOOLEAN,
    firstIndividualTimeslotInfo  IndividualTimeslotInfo-LCR-r4,
    ul-TS-ChannelisationCodeList  UL-TS-ChannelisationCodeList,
    moreTimeslots             CHOICE {
        noMore                NULL,
        additionalTimeslots   CHOICE {
            consecutive        SEQUENCE {
                numAdditionalTimeslots  INTEGER (1..maxTS-LCR-1)
            },
            timeslotList      SEQUENCE (SIZE (1..maxTS-LCR-1)) OF
                UplinkAdditionalTimeslots-LCR-r4
        }
    }
}

```

```
    }  
  }
```

```
Wi-LCR ::=
```

```
INTEGER(1..4)
```


CHANGE REQUEST

⌘ **25.331 CR 1868** ⌘ rev - ⌘ Current version: **5.3.0** ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

Proposed change affects: UICC apps ME Radio Access Network Core Network

Title:	⌘ Corrections to power control parameter signalling for 1.28 Mcps TDD		
Source:	⌘ TSG-RAN WG2		
Work item code:	⌘ LCRTDD-L23	Date:	⌘ 11 February 2003
Category:	⌘ A	Release:	⌘ Rel-5
	Use <i>one</i> of the following categories:		Use <i>one</i> of the following releases:
	<i>F</i> (correction)	R96	(Release 1996)
	<i>A</i> (corresponds to a correction in an earlier release)	R97	(Release 1997)
	<i>B</i> (addition of feature),	R98	(Release 1998)
	<i>C</i> (functional modification of feature)	R99	(Release 1999)
	<i>D</i> (editorial modification)	Rel-4	(Release 4)
	Detailed explanations of the above categories can be found in 3GPP TR 21.900 .	Rel-5	(Release 5)
		Rel-6	(Release 6)

Reason for change:	⌘ Certain Information Elements and the comments associated with them do not properly reflect the way in which closed loop power control is now implemented in 1.28 Mcps TDD.
Summary of change:	⌘ (i) In IE 10.3.6.37 the description associated with the parameter ‘additional codes’ is incorrect and is replaced. (ii) In IE 10.3.6.45 ‘PDSCH Power Control info’ a note is added to indicate that the loop ‘UL CCTrCH TPC List’ is not required for 1.28 Mcps TDD. (iii) IE 10.3.6.65 ‘PUSCH power control info’ contains a redundant list ‘DL CCTrCH TPC List’ which is removed. (iv) In IE 10.3.6.21 a note is added to indicate that the loop ‘UL CCTrCH TPC List’ is not required for 1.28 Mcps TDD.
Consequences if not approved:	⌘ Power control will not be specified for 1.28 Mcps leading to loss of radio connections. The specification will be inconsistent with WG1 specifications.

Clauses affected:	⌘ 10.3.6.21, 10.3.6.37, 10.3.6.45, 10.3.6.65., 11.3							
Other specs	⌘	<table border="1" style="display: inline-table; vertical-align: middle;"> <tr> <td style="text-align: center;">Y</td> <td style="text-align: center;">N</td> </tr> <tr> <td style="text-align: center;"> </td> <td style="text-align: center;">X</td> </tr> </table>	Y	N		X	Other core specifications	⌘
Y	N							
	X							

affected:

<input checked="" type="checkbox"/>	Test specifications
<input checked="" type="checkbox"/>	O&M Specifications

Other comments: ☞

How to create CRs using this form:

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>. Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ☞ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

10.3.6.21 Downlink DPCH info for each RL

Information Element/Group name	Need	Multi	Type and reference	Semantics description
CHOICE <i>mode</i>	MP			
>FDD				
>>Primary CPICH usage for channel estimation	MP		Primary CPICH usage for channel estimation 10.3.6.62	
>>DPCH frame offset	MP		Integer(0..38 144 by step of 256)	Offset (in number of chips) between the beginning of the P-CCPCH frame and the beginning of the DPCH frame This is called $\tau_{DPCH,n}$ in [26]
>>Secondary CPICH info	OP		Secondary CPICH info 10.3.6.73	
>>DL channelisation code	MP	1 to <maxDPC H-DLchan>		For the purpose of physical channel mapping [27] the DPCHs are numbered, starting from DPCH number 1, according to the order that they are contained in this IE.
>>>Secondary scrambling code	MD		Secondary scrambling code 10.3.6.74	Default is the same scrambling code as for the Primary CPICH
>>>Spreading factor	MP		Integer(4, 8, 16, 32, 64, 128, 256, 512)	Defined in CHOICE SF512-AndCodenum with "code number" in ASN.1
>>>Code number	MP		Integer(0..Sp reading factor - 1)	
>>>Scrambling code change	CH-SF/2		Enumerated (code change, no code change)	Indicates whether the alternative scrambling code is used for compressed mode method 'SF/2'.
>>TPC combination index	MP		TPC combination index 10.3.6.85	
>>SSDT Cell Identity	OP		SSDT Cell Identity 10.3.6.76	
>>Closed loop timing adjustment mode	CH- <i>TxDiversity Mode</i>		Integer(1, 2)	It is present if Tx Diversity is used in the radio link.
>TDD				
>>DL CCTrCh List	OP	1..<maxCC TrCH>		DL physical channels to establish or reconfigure list.
>>>TFCS ID	MD		Integer(1..8)	Identity of this CCTrCh. Default value is 1
>>>Time info	MP		Time Info 10.3.6.83	
>>>Common timeslot info	MD		Common	Default is the current Common

Information Element/Group name	Need	Multi	Type and reference	Semantics description
			Timeslot Info 10.3.6.10	timeslot info
>>>Downlink DPCH timeslots and codes	MD		Downlink Timeslots and Codes 10.3.6.32	Default is to use the old timeslots and codes.
>>>UL CCTrCH TPC List	MD	0..<maxCC TrCH>		UL CCTrCH identities for TPC commands associated with this DL CCTrCH. Default is previous list or all defined UL CCTrCHs This list is not required for 1.28 Mcps TDD and is to be ignored by the UE.
>>>>UL TPC TFCS Identity	MP		Transport Format Combination Set Identity 10.3.5.21	
>>DL CCTrCH List to Remove	OP	1..<maxCC TrCH>		DL physical channels to remove list.
>>>TFCS ID	MP		Integer(1..8)	

Condition	Explanation
<i>SF/2</i>	The information element is mandatory present if the UE has a compressed mode pattern sequence configured in variable TGPS_IDENTITY or included in the message including IE "Downlink DPCH info for each RL", which is using compressed mode method "SF/2". Otherwise the IE is not needed.
<i>TxDiversity Mode</i>	This IE is mandatory present if any TX Diversity Mode is used on the radio link, i.e. if STTD, "closed loop mode 1" or "closed loop mode 2" is used on the radio link. Otherwise the IE is not needed.

10.3.6.37 Individual timeslot info

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
Timeslot number	MP		Timeslot number 10.3.6.84	Timeslot within a frame	
TFCI existence	MP		Boolean	TRUE indicates that the TFCI exists. It shall be coded in the first physical channel of this timeslot.	
Midamble Shift and burst type	MP		Midamble shift and burst type 10.3.6.41		
CHOICE <i>TDD option</i>	MP				REL-4
>3.84 Mcps TDD				(no data)	REL-4
>1.28 Mcps TDD					REL-4

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
>>Modulation	MP		Enumerated(QPSK, 8PSK)		REL-4
>>SS-TPC Symbols	MP		Enumerated(0, 1, 16/SF)	Denotes amount of SS and TPC bits send in this timeslot	REL-4
>>Additional TPC-SS Symbols	OP		Integer(1..15)	Specifies the number of additional codes in this timeslot that carry TPC and SS symbols as specified in [33]	REL-4

10.3.6.45 PDSCH Power Control info

NOTE: Only for TDD.

Information Element/Group name	Need	Multi	Type and reference	Semantics description
TPC Step Size	OP		Integer (1, 2, 3)	In dB
UL CCTrCH TPC List	OP	1..<maxCC TrCH>		UL CCTrCH identities for TPC commands associated with this DL CCTrCH . This list is not used by 1.28 Mcps TDD.
>UL TPC TFCS Identity	MP		Transport Format Combination Set Identity 10.3.5.21	

10.3.6.65 PUSCH power control info

NOTE: Only for TDD.

Interference level measured for a frequency at the UTRAN access point used by UE to set PUSCH output power.

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
CHOICE <i>TDD option</i>	MP				REL-4
>3.84 Mcps TDD					REL-4
>>UL target SIR	MP		Real (-11 .. 20 by step of 0.5)	in dB	
>1.28 Mcps TDD					REL-4
>>PRX _{PUSCHdes}	MP		Integer(-120...-58 by step of 1)	in dBm	REL-4
>>TPC Step Size	OP		Integer (1, 2, 3)	In dB	REL-4
>>DL CCTrCH TPC List	OP	0..<maxCC TrCH>		DL CCTrCH identities for TPC	REL-4

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
				commands associated with this UL CCTrCH	
>>>DL-TPC-TFCS-Identity	MP		Transport Format Combination Set-Identity 10.3.5.21		REL-4

11.3 Information element definitions

```

-- *****
--
--     PHYSICAL CHANNEL INFORMATION ELEMENTS (10.3.6)
--
-- *****

ACK-NACK-repetitionFactor ::=      INTEGER(1..4)

AC-To-ASC-Mapping ::=              INTEGER (0..7)

AC-To-ASC-MappingTable ::=         SEQUENCE (SIZE (maxASCmap)) OF
                                   AC-To-ASC-Mapping

AccessServiceClass-FDD ::=         SEQUENCE {
    availableSignatureStartIndex    INTEGER (0..15),
    availableSignatureEndIndex      INTEGER (0..15),

    assignedSubChannelNumber        BIT STRING {
                                    b3(0),
                                    b2(1),
                                    b1(2),
                                    b0(3)
                                    } (SIZE(4))
}

AccessServiceClass-TDD ::=         SEQUENCE {
    channelisationCodeIndices       BIT STRING {
                                    chCodeIndex7(0),
                                    chCodeIndex6(1),
                                    chCodeIndex5(2),
                                    chCodeIndex4(3),
                                    chCodeIndex3(4),
                                    chCodeIndex2(5),
                                    chCodeIndex1(6),
                                    chCodeIndex0(7)
                                    } (SIZE(8))                OPTIONAL,

    subchannelSize                  CHOICE {
        size1                        NULL,
        size2                        SEQUENCE {
            -- subch0 means bitstring '01' in the tabular, subch1 means bitsring '10'
            subchannels                ENUMERATED { subch0, subch1 } OPTIONAL
        },
        size4                        SEQUENCE {
            subchannels                BIT STRING {
                                    subCh3(0),
                                    subCh2(1),
                                    subCh1(2),
                                    subCh0(3)
                                    } (SIZE(4))                OPTIONAL
            },
        size8                        SEQUENCE {
            subchannels                BIT STRING {
                                    subCh7(0),
                                    subCh6(1),
                                    subCh5(2),
                                    subCh4(3),
                                    subCh3(4),
                                    subCh2(5),
                                    subCh1(6),
                                    subCh0(7)
                                    } (SIZE(8))                OPTIONAL
            }
        }
}

AccessServiceClass-TDD-LCR-r4 ::= SEQUENCE {

```

```

availableSYNC-UlCodesIndics      BIT STRING {
                                   sulCodeIndex7(0),
                                   sulCodeIndex6(1),
                                   sulCodeIndex5(2),
                                   sulCodeIndex4(3),
                                   sulCodeIndex3(4),
                                   sulCodeIndex2(5),
                                   sulCodeIndex1(6),
                                   sulCodeIndex0(7)
                                   } (SIZE(8))                                OPTIONAL,

subchannelSize                   CHOICE {
  size1                           NULL,
  size2                           SEQUENCE {
    -- subch0 means bitstring '01' in the tabular, subch1 means bitsring '10'.
    subchannels                    ENUMERATED { subch0, subch1 } OPTIONAL
  },
  size4                           SEQUENCE {
    subchannels                    BIT STRING {
                                   subCh3(0),
                                   subCh2(1),
                                   subCh1(2),
                                   subCh0(3)
                                   } (SIZE(4))                                OPTIONAL
    },
  size8                           SEQUENCE {
    subchannels                    BIT STRING {
                                   subCh7(0),
                                   subCh6(1),
                                   subCh5(2),
                                   subCh4(3),
                                   subCh3(4),
                                   subCh2(5),
                                   subCh1(6),
                                   subCh0(7)
                                   } (SIZE(8))                                OPTIONAL
    }
  }
}

AICH-Info ::=
  channelisationCode256          SEQUENCE {
    ChannelisationCode256,
    sttd-Indicator               BOOLEAN,
    aich-TransmissionTiming      AICH-TransmissionTiming
  }

AICH-PowerOffset ::=            INTEGER (-22..5)

AICH-TransmissionTiming ::=    ENUMERATED {
    e0, e1 }

AllocationPeriodInfo ::=       SEQUENCE {
  allocationActivationTime       INTEGER (0..255),
  allocationDuration             INTEGER (1..256)
}

-- Actual value Alpha = IE value * 0.125
Alpha ::=                       INTEGER (0..8)

AP-AICH-ChannelisationCode ::= INTEGER (0..255)

AP-PreambleScramblingCode ::=  INTEGER (0..79)

AP-Signature ::=               INTEGER (0..15)

AP-Signature-VCAM ::=          SEQUENCE {
  ap-Signature                   AP-Signature,
  availableAP-SubchannelList     AvailableAP-SubchannelList OPTIONAL
}

AP-Subchannel ::=              INTEGER (0..11)

```



```

ASCSetting-FDD ::=                               SEQUENCE {
  -- TABULAR: accessServiceClass-FDD is MD in tabular description
  -- Default value is previous ASC
  -- If this is the first ASC, the default value is all available signature and sub-channels
  accessServiceClass-FDD                        AccessServiceClass-FDD  OPTIONAL
}

ASCSetting-TDD ::=                               SEQUENCE {
  -- TABULAR: accessServiceClass-TDD is MD in tabular description
  -- Default value is previous ASC
  -- If this is the first ASC, the default value is all available channelisation codes and
  -- all available sub-channels with subchannelSize=size1.
  accessServiceClass-TDD                        AccessServiceClass-TDD  OPTIONAL
}

ASCSetting-TDD-LCR-r4 ::=                       SEQUENCE {
  -- TABULAR: accessServiceClass-TDD-LCR is MD in tabular description
  -- Default value is previous ASC
  -- If this is the first ASC, the default value is all available SYNC_UL codes and
  -- all available sub-channels with subchannelSize=size1.
  accessServiceClass-TDD-LCR                    AccessServiceClass-TDD-LCR-r4  OPTIONAL
}

AvailableAP-Signature-VCAMList ::= SEQUENCE (SIZE (1..maxPCPCH-APsig)) OF
  AP-Signature-VCAM

AvailableAP-SignatureList ::= SEQUENCE (SIZE (1..maxPCPCH-APsig)) OF
  AP-Signature

AvailableAP-SubchannelList ::= SEQUENCE (SIZE (1..maxPCPCH-APsubCh)) OF
  AP-Subchannel

AvailableMinimumSF-ListVCAM ::= SEQUENCE (SIZE (1..maxPCPCH-SF)) OF
  AvailableMinimumSF-VCAM

AvailableMinimumSF-VCAM ::= SEQUENCE {
  minimumSpreadingFactor      MinimumSpreadingFactor,
  nf-Max                       NF-Max,
  maxAvailablePCPCH-Number     MaxAvailablePCPCH-Number,
  availableAP-Signature-VCAMList AvailableAP-Signature-VCAMList
}

AvailableSignatures ::= BIT STRING {
  signature15(0),
  signature14(1),
  signature13(2),
  signature12(3),
  signature11(4),
  signature10(5),
  signature9(6),
  signature8(7),
  signature7(8),
  signature6(9),
  signature5(10),
  signature4(11),
  signature3(12),
  signature2(13),
  signature1(14),
  signature0(15)
} (SIZE(16))

AvailableSubChannelNumbers ::= BIT STRING {
  subCh11(0),
  subCh10(1),
  subCh9(2),
  subCh8(3),
  subCh7(4),
  subCh6(5),
  subCh5(6),
  subCh4(7),

```

```

        subCh3(8),
        subCh2(9),
        subCh1(10),
        subCh0(11)
    } (SIZE(12))

BurstType ::= ENUMERATED {
    short1, long2 }

-- Actual value Bler-Target = IE value * 0.05
Bler-Target ::= INTEGER (-63..0)

CCTrCH-PowerControlInfo ::= SEQUENCE {
    tfcs-Identity          TFCS-Identity          OPTIONAL,
    ul-DPCH-PowerControlInfo  UL-DPCH-PowerControlInfo
}

CCTrCH-PowerControlInfo-r4 ::= SEQUENCE {
    tfcs-Identity          TFCS-Identity          OPTIONAL,
    ul-DPCH-PowerControlInfo-r4  UL-DPCH-PowerControlInfo-r4
}

CD-AccessSlotSubchannel ::= INTEGER (0..11)

CD-AccessSlotSubchannelList ::= SEQUENCE (SIZE (1..maxPCPCH-CDsubCh)) OF
    CD-AccessSlotSubchannel

CD-CA-ICH-ChannelisationCode ::= INTEGER (0..255)

CD-PreambleScramblingCode ::= INTEGER (0..79)

CD-SignatureCode ::= INTEGER (0..15)

CD-SignatureCodeList ::= SEQUENCE (SIZE (1..maxPCPCH-CDsig)) OF
    CD-SignatureCode

CellAndChannelIdentity ::= SEQUENCE {
    burstType          BurstType,
    midambleShift      MidambleShiftLong,
    timeslot           TimeslotNumber,
    cellParametersID   CellParametersID
}

CellParametersID ::= INTEGER (0..127)

Cfntargetsfnframeoffset ::= INTEGER(0..255)

ChannelAssignmentActive ::= CHOICE {
    notActive          NULL,
    isActive           AvailableMinimumSF-ListVCAM
}

ChannelisationCode256 ::= INTEGER (0..255)

ChannelReqParamsForUCSM ::= SEQUENCE {
    availableAP-SignatureList  AvailableAP-SignatureList,
    availableAP-SubchannelList AvailableAP-SubchannelList
} OPTIONAL

ClosedLoopTimingAdjMode ::= ENUMERATED {
    slot1, slot2 }

CodeNumberDSCH ::= INTEGER (0..255)

CodeRange ::= SEQUENCE {
    pdsch-CodeMapList  PDSCH-CodeMapList
}

CodeWordSet ::= ENUMERATED {
    longCWS,
    mediumCWS,

```

```

        shortCWS,
        ssdtOff }

CommonTimeslotInfo ::=          SEQUENCE {
-- TABULAR: secondInterleavingMode is MD, but since it can be encoded in a single
-- bit it is not defined as OPTIONAL.
secondInterleavingMode          SecondInterleavingMode,
tfcI-Coding                     TFCI-Coding                               OPTIONAL,
puncturingLimit                 PuncturingLimit,
repetitionPeriodAndLength       RepetitionPeriodAndLength           OPTIONAL
}

CommonTimeslotInfoSCCPCH ::=    SEQUENCE {
-- TABULAR: secondInterleavingMode is MD, but since it can be encoded in a single
-- bit it is not defined as OPTIONAL.
secondInterleavingMode          SecondInterleavingMode,
tfcI-Coding                     TFCI-Coding                               OPTIONAL,
puncturingLimit                 PuncturingLimit,
repetitionPeriodLengthAndOffset RepetitionPeriodLengthAndOffset   OPTIONAL
}

ConstantValue ::=              INTEGER (-35..-10)

ConstantValueTdd ::=           INTEGER (-35..10)

CPCH-PersistenceLevels ::=     SEQUENCE {
cpch-SetID                      CPCH-SetID,
dynamicPersistenceLevelTF-List   DynamicPersistenceLevelTF-List
}

CPCH-PersistenceLevelsList ::= SEQUENCE (SIZE (1..maxCPCHsets)) OF
CPCH-PersistenceLevels

CPCH-SetInfo ::=               SEQUENCE {
cpch-SetID                      CPCH-SetID,
transportFormatSet              TransportFormatSet,
tfcs                            TFCS,
ap-PreambleScramblingCode       AP-PreambleScramblingCode,
ap-AICH-ChannelisationCode       AP-AICH-ChannelisationCode,
cd-PreambleScramblingCode        CD-PreambleScramblingCode,
cd-CA-ICH-ChannelisationCode     CD-CA-ICH-ChannelisationCode,
cd-AccessSlotSubchannelList      CD-AccessSlotSubchannelList   OPTIONAL,
cd-SignatureCodeList            CD-SignatureCodeList         OPTIONAL,
deltaPp-m                       DeltaPp-m,
ul-DPCCH-SlotFormat             UL-DPCCH-SlotFormat,
n-StartMessage                  N-StartMessage,
n-EOT                           N-EOT,
-- TABULAR: VCAM info has been nested inside ChannelAssignmentActive,
-- which in turn is mandatory since it's only a binary choice.
channelAssignmentActive          ChannelAssignmentActive,
cpch-StatusIndicationMode        CPCH-StatusIndicationMode,
pcpch-ChannelInfoList           PCPCH-ChannelInfoList
}

CPCH-SetInfoList ::=           SEQUENCE (SIZE (1..maxCPCHsets)) OF
CPCH-SetInfo

CPCH-StatusIndicationMode ::=  ENUMERATED {
pa-mode,
pamsf-mode }

CQI-RepetitionFactor ::=       INTEGER(1..4)

CSICH-PowerOffset ::=          INTEGER (-10..5)

-- DefaultDPCH-OffsetValueFDD and DefaultDPCH-OffsetValueTDD corresponds to
-- IE "Default DPCH Offset Value" depending on the mode.
-- Actual value DefaultDPCH-OffsetValueFDD = IE value * 512
DefaultDPCH-OffsetValueFDD ::= INTEGER (0..599)

DefaultDPCH-OffsetValueTDD ::= INTEGER (0..7)

```

```

DeltaPp-m ::=                               INTEGER (-10..10)

DeltaCQI ::=                                 INTEGER (0..8)

DeltaNACK ::=                                INTEGER (0..8)

DeltaACK ::=                                 INTEGER (0..8)

-- Actual value DeltaSIR = IE value * 0.1
DeltaSIR ::=                                 INTEGER (0..30)

DL-CCTrCh ::=                                SEQUENCE {
    tfcs-ID                                  TFCS-IdentityPlain           DEFAULT 1,
    timeInfo                                  TimeInfo,
    commonTimeslotInfo                       CommonTimeslotInfo           OPTIONAL,
    dl-CCTrCH-TimeslotsCodes                 DownlinkTimeslotsCodes      OPTIONAL,
    ul-CCTrChTPCList                         UL-CCTrChTPCList            OPTIONAL
}

DL-CCTrCh-r4 ::=                             SEQUENCE {
    tfcs-ID                                  TFCS-IdentityPlain           DEFAULT 1,
    timeInfo                                  TimeInfo,
    commonTimeslotInfo                       CommonTimeslotInfo           OPTIONAL,
    tddOption                                 CHOICE {
        tdd384                               SEQUENCE {
            dl-CCTrCH-TimeslotsCodes         DownlinkTimeslotsCodes      OPTIONAL
        },
        tdd128                               SEQUENCE {
            dl-CCTrCH-TimeslotsCodes         DownlinkTimeslotsCodes-LCR-r4  OPTIONAL
        }
    },
    ul-CCTrChTPCList                         UL-CCTrChTPCList            OPTIONAL
}

DL-CCTrChList ::=                            SEQUENCE (SIZE (1..maxCCTrCH)) OF
    DL-CCTrCh

DL-CCTrChList-r4 ::=                         SEQUENCE (SIZE (1..maxCCTrCH)) OF
    DL-CCTrCh-r4

DL-CCTrChListToRemove ::=                   SEQUENCE (SIZE (1..maxCCTrCH)) OF
    TFCS-IdentityPlain

DL-CCTrChTPCList ::=                        SEQUENCE (SIZE (0..maxCCTrCH)) OF
    TFCS-Identity

DL-ChannelisationCode ::=                   SEQUENCE {
    secondaryScramblingCode                 SecondaryScramblingCode      OPTIONAL,
    sf-AndCodeNumber                       SF512-AndCodeNumber,
    scramblingCodeChange                    ScramblingCodeChange        OPTIONAL
}

DL-ChannelisationCodeList ::=                SEQUENCE (SIZE (1..maxDPCH-DLchan)) OF
    DL-ChannelisationCode

DL-CommonInformation ::=                    SEQUENCE {
    dl-DPCH-InfoCommon                     DL-DPCH-InfoCommon          OPTIONAL,
    modeSpecificInfo                       CHOICE {
        fdd                                  SEQUENCE {
            defaultDPCH-OffsetValue         DefaultDPCH-OffsetValueFDD   OPTIONAL,
            dpch-CompressedModeInfo         DPCH-CompressedModeInfo     OPTIONAL,
            tx-DiversityMode                TX-DiversityMode            OPTIONAL,
            ssdt-Information                 SSDT-Information            OPTIONAL
        },
        tdd                                  SEQUENCE {
            defaultDPCH-OffsetValue         DefaultDPCH-OffsetValueTDD   OPTIONAL
        }
    }
}

```

```

DL-CommonInformation-r4 ::=          SEQUENCE {
  dl-DPCH-InfoCommon                DL-DPCH-InfoCommon          OPTIONAL,
  modeSpecificInfo                   CHOICE {
    fdd                               SEQUENCE {
      defaultDPCH-OffsetValue        DefaultDPCH-OffsetValueFDD  OPTIONAL,
      dpch-CompressedModeInfo        DPCH-CompressedModeInfo    OPTIONAL,
      tx-DiversityMode                TX-DiversityMode           OPTIONAL,
      ssdt-Information-r4             SSDT-Information-r4        OPTIONAL
    },
    tdd                               SEQUENCE {
      tddOption                       CHOICE {
        tdd384                        NULL,
        tdd128                        SEQUENCE {
          tstd-Indicator              BOOLEAN
        }
      },
      defaultDPCH-OffsetValue        DefaultDPCH-OffsetValueTDD  OPTIONAL
    }
  }
}

DL-CommonInformationPost ::=        SEQUENCE {
  dl-DPCH-InfoCommonPost            DL-DPCH-InfoCommonPost
}

DL-CommonInformationPredef ::=      SEQUENCE {
  dl-DPCH-InfoCommonPredef          DL-DPCH-InfoCommonPredef  OPTIONAL
}

DL-CompressedModeMethod ::=         ENUMERATED {
  puncturing, sf-2,
  higherLayerScheduling }

DL-DPCH-InfoCommon ::=             SEQUENCE {
  cfnHandling                        CHOICE {
    maintain                          NULL,
    initialise                         SEQUENCE {
      cfntargetsfnsframeoffset        Cfntargetsfnsframeoffset    OPTIONAL
    }
  },
  modeSpecificInfo                   CHOICE {
    fdd                               SEQUENCE {
      dl-DPCH-PowerControlInfo        DL-DPCH-PowerControlInfo    OPTIONAL,
      powerOffsetPilot-pdpdch         PowerOffsetPilot-pdpdch,
      dl-rate-matching-restriction    Dl-rate-matching-restriction  OPTIONAL,
      -- TABULAR: The number of pilot bits is nested inside the spreading factor.
      spreadingFactorAndPilot         SF512-AndPilot,
      positionFixedOrFlexible         PositionFixedOrFlexible,
      tfci-Existence                  BOOLEAN
    },
    tdd                               SEQUENCE {
      dl-DPCH-PowerControlInfo        DL-DPCH-PowerControlInfo    OPTIONAL
    }
  }
}

DL-DPCH-InfoCommon-r4 ::=          SEQUENCE {
  cfnHandling                        CHOICE {
    maintain                          NULL,
    initialise                         SEQUENCE {
      cfntargetsfnsframeoffset        Cfntargetsfnsframeoffset    OPTIONAL
    }
  },
  modeSpecificInfo                   CHOICE {
    fdd                               SEQUENCE {
      dl-DPCH-PowerControlInfo        DL-DPCH-PowerControlInfo    OPTIONAL,
      powerOffsetPilot-pdpdch         PowerOffsetPilot-pdpdch,
      dl-rate-matching-restriction    Dl-rate-matching-restriction  OPTIONAL,
      -- TABULAR: The number of pilot bits is nested inside the spreading factor.
      spreadingFactorAndPilot         SF512-AndPilot,
      positionFixedOrFlexible         PositionFixedOrFlexible,
    }
  }
}

```

```

        tfci-Existence                BOOLEAN
    },
    tdd                                SEQUENCE {
        dl-DPCH-PowerControlInfo      DL-DPCH-PowerControlInfo      OPTIONAL
    }
},
-- The IE mac-d-HFN-initial-value should be absent in the RRCConnectionSetup-r4-IEs or
-- RRCConnectionSetup-r5-IEs or HandoverToUTRANCommand-r4-IEs or HandoverToUTRANCommand-r5-IEs and
-- if the IE is included, the general error handling for conditional IEs applies.
    mac-d-HFN-initial-value           MAC-d-HFN-initial-value           OPTIONAL
}

DL-DPCH-InfoCommonPost ::=           SEQUENCE {
    dl-DPCH-PowerControlInfo          DL-DPCH-PowerControlInfo          OPTIONAL
}

DL-DPCH-InfoCommonPredef ::=        SEQUENCE {
    modeSpecificInfo                  CHOICE {
        fdd                            SEQUENCE {
            -- TABULAR: The number of pilot bits is nested inside the spreading factor.
            spreadingFactorAndPilot     SF512-AndPilot,
            positionFixedOrFlexible     PositionFixedOrFlexible,
            tfci-Existence              BOOLEAN
        },
        tdd                            SEQUENCE {
            commonTimeslotInfo          CommonTimeslotInfo
        }
    }
}

DL-DPCH-InfoPerRL ::=               CHOICE {
    fdd                                SEQUENCE {
        pCPICH-UsageForChannelEst      PCPICH-UsageForChannelEst,
        dpch-FrameOffset               DPCH-FrameOffset,
        secondaryCPICH-Info            SecondaryCPICH-Info            OPTIONAL,
        dl-ChannelisationCodeList      DL-ChannelisationCodeList,
        tpc-CombinationIndex           TPC-CombinationIndex,
        ssdt-CellIdentity              SSDT-CellIdentity           OPTIONAL,
        closedLoopTimingAdjMode        ClosedLoopTimingAdjMode      OPTIONAL
    },
    tdd                                SEQUENCE {
        dl-CCTrChListToEstablish        DL-CCTrChList                OPTIONAL,
        dl-CCTrChListToRemove          DL-CCTrChListToRemove        OPTIONAL
    }
}

DL-DPCH-InfoPerRL-r4 ::=            CHOICE {
    fdd                                SEQUENCE {
        pCPICH-UsageForChannelEst      PCPICH-UsageForChannelEst,
        dpch-FrameOffset               DPCH-FrameOffset,
        secondaryCPICH-Info            SecondaryCPICH-Info            OPTIONAL,
        dl-ChannelisationCodeList      DL-ChannelisationCodeList,
        tpc-CombinationIndex           TPC-CombinationIndex,
        ssdt-CellIdentity              SSDT-CellIdentity           OPTIONAL,
        closedLoopTimingAdjMode        ClosedLoopTimingAdjMode      OPTIONAL
    },
    tdd                                SEQUENCE {
        dl-CCTrChListToEstablish        DL-CCTrChList-r4            OPTIONAL,
        dl-CCTrChListToRemove          DL-CCTrChListToRemove        OPTIONAL
    }
}

DL-DPCH-InfoPerRL-PostFDD ::=       SEQUENCE {
    pCPICH-UsageForChannelEst          PCPICH-UsageForChannelEst,
    dl-ChannelisationCode              DL-ChannelisationCode,
    tpc-CombinationIndex               TPC-CombinationIndex
}

DL-DPCH-InfoPerRL-PostTDD ::=       SEQUENCE {

```

```

    dl-DPCH-TimeslotsCodes          DownlinkTimeslotsCodes
}
DL-DPCH-InfoPerRL-PostTDD-LCR-r4 ::= SEQUENCE {
    dl-CCTrCH-TimeslotsCodes      DownlinkTimeslotsCodes-LCR-r4
}
DL-DPCH-PowerControlInfo ::= SEQUENCE {
    modeSpecificInfo              CHOICE {
        fdd                        SEQUENCE {
            dpc-Mode                DPC-Mode
        },
        tdd                        SEQUENCE {
            tpc-StepSizeTDD         TPC-StepSizeTDD           OPTIONAL
        }
    }
}
DL-FrameType ::= ENUMERATED {
    dl-FrameTypeA, dl-FrameTypeB }
DL-HSPDSCH-Information ::= SEQUENCE {
    hs-scch-Info                  HS-SCCH-Info,
    measurement-feedback-Info     Measurement-Feedback-Info   OPTIONAL
}
DL-InformationPerRL ::= SEQUENCE {
    modeSpecificInfo              CHOICE {
        fdd                        SEQUENCE {
            primaryCPICH-Info       PrimaryCPICH-Info,
            pdsch-SHO-DCH-Info     PDSCH-SHO-DCH-Info         OPTIONAL,
            pdsch-CodeMapping       PDSCH-CodeMapping         OPTIONAL
        },
        tdd                        PrimaryCCPCH-Info
    },
    dl-DPCH-InfoPerRL             DL-DPCH-InfoPerRL           OPTIONAL,
    sccpch-InfoForFACH            SCCPCH-InfoForFACH         OPTIONAL
}
DL-InformationPerRL-r4 ::= SEQUENCE {
    modeSpecificInfo              CHOICE {
        fdd                        SEQUENCE {
            primaryCPICH-Info       PrimaryCPICH-Info,
            pdsch-SHO-DCH-Info     PDSCH-SHO-DCH-Info         OPTIONAL,
            pdsch-CodeMapping       PDSCH-CodeMapping         OPTIONAL
        },
        tdd                        PrimaryCCPCH-Info-r4
    },
    dl-DPCH-InfoPerRL            DL-DPCH-InfoPerRL-r4       OPTIONAL,
    sccpch-InfoForFACH           SCCPCH-InfoForFACH-r4     OPTIONAL,
    cell-id                       CellIdentity              OPTIONAL
}
DL-InformationPerRL-r5 ::= SEQUENCE {
    modeSpecificInfo              CHOICE {
        fdd                        SEQUENCE {
            primaryCPICH-Info       PrimaryCPICH-Info,
            pdsch-SHO-DCH-Info     PDSCH-SHO-DCH-Info         OPTIONAL,
            pdsch-CodeMapping       PDSCH-CodeMapping         OPTIONAL,
            servingHSDSCH-RL-indicator BOOLEAN
        },
        tdd                        PrimaryCCPCH-Info-r4
    },
    dl-DPCH-InfoPerRL            DL-DPCH-InfoPerRL-r4       OPTIONAL,
    sccpch-InfoForFACH           SCCPCH-InfoForFACH-r4     OPTIONAL,
    cell-id                       CellIdentity              OPTIONAL
}
DL-InformationPerRL-List ::= SEQUENCE (SIZE (1..maxRL)) OF
    DL-InformationPerRL

```



```

        newParameters                SEQUENCE {
            individualTimeslotInfo    IndividualTimeslotInfo,
            dl-TS-ChannelisationCodesShort DL-TS-ChannelisationCodesShort
        }
    }
}

DownlinkAdditionalTimeslots-LCR-r4 ::= SEQUENCE {
    parameters CHOICE {
        sameAsLast SEQUENCE {
            timeslotNumber TimeslotNumber-LCR-r4
        },
        newParameters SEQUENCE {
            individualTimeslotInfo IndividualTimeslotInfo-LCR-r4,
            dl-TS-ChannelisationCodesShort DL-TS-ChannelisationCodesShort
        }
    }
}

DownlinkTimeslotsCodes ::= SEQUENCE {
    firstIndividualTimeslotInfo IndividualTimeslotInfo,
    dl-TS-ChannelisationCodesShort DL-TS-ChannelisationCodesShort,
    moreTimeslots CHOICE {
        noMore NULL,
        additionalTimeslots CHOICE {
            consecutive INTEGER (1..maxTS-1),
            timeslotList SEQUENCE (SIZE (1..maxTS-1)) OF
                DownlinkAdditionalTimeslots
        }
    }
}

DownlinkTimeslotsCodes-LCR-r4 ::= SEQUENCE {
    firstIndividualTimeslotInfo IndividualTimeslotInfo-LCR-r4,
    dl-TS-ChannelisationCodesShort DL-TS-ChannelisationCodesShort,
    moreTimeslots CHOICE {
        noMore NULL,
        additionalTimeslots CHOICE {
            consecutive INTEGER (1..maxTS-LCR-1),
            timeslotList SEQUENCE (SIZE (1..maxTS-LCR-1)) OF
                DownlinkAdditionalTimeslots-LCR-r4
        }
    }
}

DPC-Mode ::= ENUMERATED {
    singleTPC,
    tpcTripletInSoft }

-- Actual value DPCCH-PowerOffset = IE value * 2
DPCCH-PowerOffset ::= INTEGER (-82..-3)

-- Actual value DPCCH-PowerOffset = 2 + (IE value * 4)
DPCCH-PowerOffset2 ::= INTEGER (-28..-13)

DPCH-CompressedModeInfo ::= SEQUENCE {
    tgp-SequenceList TGP-SequenceList
}

DPCH-CompressedModeStatusInfo ::= SEQUENCE {
    tgps-Reconfiguration-CFN TGPS-Reconfiguration-CFN,
    tgp-SequenceShortList SEQUENCE (SIZE (1..maxTGPS)) OF
        TGP-SequenceShort
}

-- Actual value DPCH-FrameOffset = IE value * 256
DPCH-FrameOffset ::= INTEGER (0..149)

DSCH-Mapping ::= SEQUENCE {
    maxTFCI-Field2Value MaxTFCI-Field2Value,

```

```

        spreadingFactor                SF-PDSCH,
        codeNumber                     CodeNumberDSCH,
        multiCodeInfo                  MultiCodeInfo
    }
DSCH-MappingList ::=                 SEQUENCE (SIZE (1..maxPDSCH-TFCIgroups)) OF
                                     DSCH-Mapping
DSCH-RadioLinkIdentifier ::=         INTEGER (0..511)
DurationTimeInfo ::=                 INTEGER (1..4096)
DynamicPersistenceLevel ::=          INTEGER (1..8)
DynamicPersistenceLevelList ::=      SEQUENCE (SIZE (1..maxPRACH)) OF
                                     DynamicPersistenceLevel
DynamicPersistenceLevelTF-List ::=   SEQUENCE (SIZE (1..maxTF-CPCH)) OF
                                     DynamicPersistenceLevel
FACH-PCH-Information ::=             SEQUENCE {
    transportFormatSet                TransportFormatSet,
    transportChannelIdentity          TransportChannelIdentity,
    ctch-Indicator                    BOOLEAN
}
FACH-PCH-InformationList ::=         SEQUENCE (SIZE (1..maxFACHPCH)) OF
                                     FACH-PCH-Information
Feedback-cycle ::=                   ENUMERATED {
    fc0, fc2, fc4, fc8, fc10, fc20, fc40, fc80, fc160}
FPACH-Info-r4 ::=                   SEQUENCE {
    timeslot                          TimeslotNumber-LCR-r4,
    channelisationCode                TDD-FPACH-CCode16-r4,
    midambleShiftAndBurstType         MidambleShiftAndBurstType-LCR-r4,
    wi                                 Wi-LCR
}
FrequencyInfo ::=                   SEQUENCE {
    modeSpecificInfo                  CHOICE {
        fdd                          FrequencyInfoFDD,
        tdd                          FrequencyInfoTDD    }
}
FrequencyInfoFDD ::=                SEQUENCE {
    uarfcn-UL                         UARFCN                OPTIONAL,
    uarfcn-DL                         UARFCN
}
FrequencyInfoTDD ::=                SEQUENCE {
    uarfcn-Nt                         UARFCN
}
HS-ChannelisationCode ::=           ENUMERATED {
    cc16-1, cc16-2, cc16-3, cc16-4,
    cc16-5, cc16-6, cc16-7, cc16-8,
    cc16-9, cc16-10, cc16-11, cc16-12,
    cc16-13, cc16-14, cc16-15, cc16-16 }
HS-ChannelisationCode-LCR ::=       ENUMERATED {
    cc16-1, cc16-2, cc16-3, cc16-4,
    cc16-5, cc16-6, cc16-7, cc16-8,
    cc16-9, cc16-10, cc16-11, cc16-12,
    cc16-13, cc16-14, cc16-15, cc16-16 }
HS-SCCH-Info ::=                   SEQUENCE {
    modeSpecificInfo                  CHOICE {
        fdd                          SEQUENCE (SIZE (1..maxHSSCCHs)) OF
                                     HS-SCCH-Codes,
        tdd                          CHOICE {

```

```

        tdd384                SEQUENCE (SIZE (1..maxHSSCCHs)) OF
                               HS-SCCH-TDD384,
        tdd128                SEQUENCE (SIZE (1..maxHSSCCHs)) OF
                               HS-SCCH-TDD128
    }
}

HS-SCCH-Codes ::=            INTEGER (0..127)

HS-SCCH-TDD128 ::=          SEQUENCE (SIZE (1..maxHSSCCHs)) OF
                               HS-SCCH-TDD128List

HS-SCCH-TDD128List ::=      SEQUENCE {
    timeslotNumber           TimeslotNumber-LCR-r4,
    firstChannelisationCode  HS-ChannelisationCode-LCR,
    secondChannelisationCode HS-ChannelisationCode-LCR,
    midambleAllocationMode   CHOICE {
        defaultMidamble      NULL,
        commonMidamble       NULL
    },
    -- Actual value midambleConfiguration = IE value * 2
    midambleConfiguration    INTEGER (1..8),
    bler-target               Bler-Target,
    hs-sich-configuration    HS-SICH-Configuration-TDD128
}

HS-SICH-Configuration-TDD128 ::= SEQUENCE {
    timeslotNumber           TimeslotNumber-LCR-r4,
    channelisationCode      HS-ChannelisationCode-LCR,
    midambleAllocationMode   CHOICE {
        defaultMidamble      NULL,
        ueSpecificMidamble   SEQUENCE {
            midambleShift    MidambleShiftLong
        }
    },
    -- Actual value midambleConfiguration = IE value * 2
    midambleConfiguration    INTEGER (1..8),
    nack-ack-power-offset    INTEGER (-7..8),
    power-level-HSSICH       INTEGER (-120..-58),
    tpc-step-size            ENUMERATED { s1, s2, s3 , spare1}
}

HS-SCCH-TDD384 ::=          SEQUENCE (SIZE (1..maxHSSCCHs)) OF
                               HS-SCCH-TDD384List

HS-SCCH-TDD384List ::=      SEQUENCE {
    timeslotNumber           TimeslotNumber,
    channelisationCode      HS-ChannelisationCode,
    midambleAllocationMode   CHOICE {
        defaultMidamble      NULL,
        commonMidamble       NULL
    },
    midambleconfiguration    MidambleConfiguration,
    bler-target               Bler-Target,
    hs-sich-configuration    HS-SICH-Configuration-TDD384
}

HS-SICH-Configuration-TDD384 ::= SEQUENCE {
    timeslotNumber           TimeslotNumber,
    channelisationCode      HS-ChannelisationCode,
    midambleAllocationMode   CHOICE {
        defaultMidamble      NULL,
        ueSpecificMidamble   SEQUENCE {
            midambleShift    MidambleShiftLong
        }
    },
    midambleconfiguration    MidambleConfiguration,
    nack-ack-power-offset    INTEGER (-7..8),
    -- Actual value ul-target-SIR = IE value * 0.5
    ul-target-SIR            INTEGER (-22..40)
}

```

```

}

IndividualTimeslotInfo ::=          SEQUENCE {
    timeslotNumber                 TimeslotNumber,
    tfci-Existence                 BOOLEAN,
    midambleShiftAndBurstType      MidambleShiftAndBurstType
}

IndividualTimeslotInfo-LCR-r4 ::=   SEQUENCE {
    timeslotNumber                 TimeslotNumber-LCR-r4,
    tfci-Existence                 BOOLEAN,
    midambleShiftAndBurstType      MidambleShiftAndBurstType-LCR-r4,
    modulation                     ENUMERATED { mod-QPSK, mod-8PSK },
    ss-TPC-Symbols                 ENUMERATED { zero, one, sixteenOverSF },
    additionalSS-TPC-Symbols       INTEGER(1..15)      OPTIONAL
}

IndividualTimeslotInfo-LCR-r4-ext ::= SEQUENCE {
-- timeslotNumber and tfci-Existence is taken from IndividualTimeslotInfo.
-- midambleShiftAndBurstType in IndividualTimeslotInfo shall be ignored.
    midambleShiftAndBurstType      MidambleShiftAndBurstType-LCR-r4,
    modulation                     ENUMERATED { mod-QPSK, mod-8PSK },
    ss-TPC-Symbols                 ENUMERATED { zero, one, sixteenOverSF }
}

IndividualTS-Interference ::=      SEQUENCE {
    timeslot                       TimeslotNumber,
    ul-TimeslotInterference        TDD-UL-Interference
}

IndividualTS-InterferenceList ::=  SEQUENCE (SIZE (1..maxTS)) OF
    IndividualTS-Interference

ITP ::=                            ENUMERATED {
    mode0, mode1 }

NidentifyAbort ::=                 INTEGER (1..128)

MaxAllowedUL-TX-Power ::=          INTEGER (-50..33)

MaxAvailablePCPCH-Number ::=       INTEGER (1..64)

MaxPowerIncrease-r4 ::=            INTEGER (0..3)

MaxTFCI-Field2Value ::=            INTEGER (1..1023)

Measurement-Feedback-Info ::=      SEQUENCE {
    modeSpecificInfo               CHOICE {
        fdd                        SEQUENCE {
            pohsdsch                Po-hsdsch,
            feedback-cycle           Feedback-cycle,
            cqi-RepetitionFactor     CQI-RepetitionFactor,
            deltaCQI                 DeltaCQI
        },
        tdd                        NULL
    }
}

MidambleConfiguration ::=          ENUMERATED {ms4, ms8, ms16}

MidambleConfigurationBurstTypeand3 ::= ENUMERATED {ms4, ms8, ms16}

MidambleConfigurationBurstType2 ::= ENUMERATED {ms3, ms6}

MidambleShiftAndBurstType ::=      SEQUENCE {
    burstType                      CHOICE {
        type1                      SEQUENCE {
            midambleConfigurationBurstTypeand3 MidambleConfigurationBurstTypeand3,
            midambleAllocationMode        CHOICE {

```

```

        defaultMidamble          NULL,
        commonMidamble          NULL,
        ueSpecificMidamble      SEQUENCE {
            midambleShift
        }
    },
    type2                        SEQUENCE {
        midambleConfigurationBurstType2 MidambleConfigurationBurstType2,
        midambleAllocationMode        CHOICE {
            defaultMidamble          NULL,
            commonMidamble          NULL,
            ueSpecificMidamble      SEQUENCE {
                midambleShift
            }
        }
    },
    type3                        SEQUENCE {
        midambleConfigurationBurstTypeand3 MidambleConfigurationBurstTypeand3,
        midambleAllocationMode        CHOICE {
            defaultMidamble          NULL,
            ueSpecificMidamble      SEQUENCE {
                midambleShift
            }
        }
    }
}

MidambleShiftAndBurstType-LCR-r4 ::= SEQUENCE {
    midambleAllocationMode        CHOICE {
        defaultMidamble          NULL,
        commonMidamble          NULL,
        ueSpecificMidamble      SEQUENCE {
            midambleShift
        }
    },
    -- Actual value midambleConfiguration = IE value * 2
    midambleConfiguration        INTEGER (1..8)
}

MidambleShiftLong ::=          INTEGER (0..15)

MidambleShiftShort ::=        INTEGER (0..5)

MinimumSpreadingFactor ::=    ENUMERATED {
    sf4, sf8, sf16, sf32,
    sf64, sf128, sf256 }

MultiCodeInfo ::=            INTEGER (1..16)

N-EOT ::=                    INTEGER (0..7)

N-GAP ::=                    ENUMERATED {
    f2, f4, f8 }

N-PCH ::=                    INTEGER (1..8)

N-StartMessage ::=          INTEGER (1..8)

NB01 ::=                    INTEGER (0..50)

NF-Max ::=                   INTEGER (1..64)

NumberOfDPDCH ::=           INTEGER (1..maxDPDCH-UL)

NumberOfFBI-Bits ::=         INTEGER (1..2)

OpenLoopPowerControl-TDD ::= SEQUENCE {

```

```

    primaryCCPCH-TX-Power          PrimaryCCPCH-TX-Power,
    -- alpha, prach-ConstantValue, dpch-ConstantValue and pusch-ConstantValue
    -- shall be ignored in 1.28Mcps TDD mode.
    alpha                          Alpha                      OPTIONAL,
    prach-ConstantValue            ConstantValueTdd,
    dpch-ConstantValue             ConstantValueTdd,
    pusch-ConstantValue            ConstantValueTdd          OPTIONAL
}

OpenLoopPowerControl-IPDL-TDD-r4 ::= SEQUENCE {
    ipdl-alpha                     Alpha,
    maxPowerIncrease               MaxPowerIncrease-r4
}

PagingIndicatorLength ::=          ENUMERATED {
    pi4, pi8, pi16 }

PC-Preamble ::=                   INTEGER (0..7)

PCP-Length ::=                     ENUMERATED {
    as0, as8 }

PCPCH-ChannelInfo ::=             SEQUENCE {
    pcpch-UL-ScramblingCode        INTEGER (0..79),
    pcpch-DL-ChannelisationCode    INTEGER (0..511),
    pcpch-DL-ScramblingCode        SecondaryScramblingCode    OPTIONAL,
    pcp-Length                      PCP-Length,
    ucsM-Info                       UCSM-Info                      OPTIONAL
}

PCPCH-ChannelInfoList ::=         SEQUENCE (SIZE (1..maxPCPCHs)) OF
    PCPCH-ChannelInfo

PCPICH-UsageForChannelEst ::=     ENUMERATED {
    mayBeUsed,
    shallNotBeUsed }

PDSCH-CapacityAllocationInfo ::= SEQUENCE {
    -- pdsch-PowerControlInfo is conditional on new-configuration branch below, if this
    -- selected the IE is OPTIONAL otherwise it should not be sent
    pdsch-PowerControlInfo         PDSCH-PowerControlInfo    OPTIONAL,
    pdsch-AllocationPeriodInfo     AllocationPeriodInfo,
    configuration                   CHOICE {
        old-Configuration           SEQUENCE {
            tfcs-ID                 TFCS-IdentityPlain        DEFAULT 1,
            pdsch-Identity          PDSCH-Identity
        },
        new-Configuration           SEQUENCE {
            pdsch-Info              PDSCH-Info,
            pdsch-Identity          PDSCH-Identity    OPTIONAL
        }
    }
}

PDSCH-CapacityAllocationInfo-r4 ::= SEQUENCE {
    pdsch-AllocationPeriodInfo     AllocationPeriodInfo,
    configuration                   CHOICE {
        old-Configuration           SEQUENCE {
            tfcs-ID                 TFCS-IdentityPlain        DEFAULT 1,
            pdsch-Identity          PDSCH-Identity
        },
        new-Configuration           SEQUENCE {
            pdsch-Info              PDSCH-Info-r4,
            pdsch-Identity          PDSCH-Identity    OPTIONAL,
            pdsch-PowerControlInfo  PDSCH-PowerControlInfo    OPTIONAL
        }
    }
}

PDSCH-CodeInfo ::=               SEQUENCE {
    spreadingFactor                SF-PDSCH,

```

```

    codeNumber                CodeNumberDSCH,
    multiCodeInfo             MultiCodeInfo
}

PDSCH-CodeInfoList ::=      SEQUENCE (SIZE (1..maxTFCI-2-Combs)) OF
                              PDSCH-CodeInfo

PDSCH-CodeMap ::=          SEQUENCE {
    spreadingFactor           SF-PDSCH,
    multiCodeInfo             MultiCodeInfo,
    codeNumberStart           CodeNumberDSCH,
    codeNumberStop            CodeNumberDSCH
}

PDSCH-CodeMapList ::=      SEQUENCE (SIZE (1..maxPDSCH-TFCIgroups)) OF
                              PDSCH-CodeMap

PDSCH-CodeMapping ::=      SEQUENCE {
    dl-ScramblingCode         SecondaryScramblingCode           OPTIONAL,
    signallingMethod          CHOICE {
        codeRange              CodeRange,
        tfci-Range             DSCH-MappingList,
        explicit-config        PDSCH-CodeInfoList,
        replace                 ReplacedPDSCH-CodeInfoList
    }
}

PDSCH-Identity ::=         INTEGER (1..hiPDSCHidentities)

PDSCH-Info ::=             SEQUENCE {
    tfcs-ID                   TFCS-IdentityPlain                DEFAULT 1,
    commonTimeslotInfo        CommonTimeslotInfo                 OPTIONAL,
    pdsch-TimeslotsCodes      DownlinkTimeslotsCodes             OPTIONAL
}

PDSCH-Info-r4 ::=         SEQUENCE {
    tfcs-ID                   TFCS-IdentityPlain                DEFAULT 1,
    commonTimeslotInfo        CommonTimeslotInfo                 OPTIONAL,
    tddOption                 CHOICE {
        tdd384                 SEQUENCE {
            pdsch-TimeslotsCodes DownlinkTimeslotsCodes         OPTIONAL
        },
        tdd128                 SEQUENCE {
            pdsch-TimeslotsCodes DownlinkTimeslotsCodes-LCR-r4  OPTIONAL
        }
    }
}

PDSCH-Info-LCR-r4 ::=     SEQUENCE {
    tfcs-ID                   TFCS-IdentityPlain                DEFAULT 1,
    commonTimeslotInfo        CommonTimeslotInfo                 OPTIONAL,
    pdsch-TimeslotsCodes      DownlinkTimeslotsCodes-LCR-r4    OPTIONAL
}

PDSCH-PowerControlInfo ::= SEQUENCE {
    tpc-StepSizeTDD           TPC-StepSizeTDD                 OPTIONAL,
    ul-CCTrChTPCList         UL-CCTrChTPCList                 OPTIONAL
}

PDSCH-SHO-DCH-Info ::=    SEQUENCE {
    dsch-RadioLinkIdentifier  DSCH-RadioLinkIdentifier,
    rl-IdentifierList         RL-IdentifierList                 OPTIONAL
}

PDSCH-SysInfo ::=         SEQUENCE {
    pdsch-Identity            PDSCH-Identity,
    pdsch-Info                PDSCH-Info,
    dsch-TFS                  TransportFormatSet                OPTIONAL,
    dsch-TFCS                 TFCS                             OPTIONAL
}

```

```

PDSCH-SysInfo-LCR-r4 ::= SEQUENCE {
    pdsch-Identity          PDSCH-Identity,
    pdsch-Info              PDSCH-Info-LCR-r4,
    dsch-TFS                TransportFormatSet,
    dsch-TFCS               TFCS,
}
OPTIONAL,
OPTIONAL

PDSCH-SysInfoList ::= SEQUENCE (SIZE (1..maxPDSCH)) OF
    PDSCH-SysInfo

PDSCH-SysInfoList-LCR-r4 ::= SEQUENCE (SIZE (1..maxPDSCH)) OF
    PDSCH-SysInfo-LCR-r4

PDSCH-SysInfoList-SFN ::= SEQUENCE (SIZE (1..maxPDSCH)) OF
    SEQUENCE {
        pdsch-SysInfo      PDSCH-SysInfo,
        sfm-TimeInfo       SFN-TimeInfo,
    }
OPTIONAL

PDSCH-SysInfoList-SFN-LCR-r4 ::= SEQUENCE (SIZE (1..maxPDSCH)) OF
    SEQUENCE {
        pdsch-SysInfo      PDSCH-SysInfo-LCR-r4,
        sfm-TimeInfo       SFN-TimeInfo,
    }
OPTIONAL

PersistenceScalingFactor ::= ENUMERATED {
    psf0-9, psf0-8, psf0-7, psf0-6,
    psf0-5, psf0-4, psf0-3, psf0-2 }

PersistenceScalingFactorList ::= SEQUENCE (SIZE (1..maxASCPersist)) OF
    PersistenceScalingFactor

PI-CountPerFrame ::= ENUMERATED {
    e18, e36, e72, e144 }

PichChannelisationCodeList-LCR-r4 ::= SEQUENCE (SIZE (1..2)) OF
    DL-TS-ChannelisationCode

PICH-Info ::= CHOICE {
    fdd SEQUENCE {
        channelisationCode256 ChannelisationCode256,
        pi-CountPerFrame      PI-CountPerFrame,
        sttd-Indicator         BOOLEAN,
    },
    tdd SEQUENCE {
        channelisationCode      TDD-PICH-CCode,
        timeslot                 TimeslotNumber,
        midambleShiftAndBurstType MidambleShiftAndBurstType,
        repetitionPeriodLengthOffset RepPerLengthOffset-PICH,
        pagingIndicatorLength     PagingIndicatorLength,
        n-GAP                     N-GAP,
        n-PCH                     N-PCH,
    }
}
OPTIONAL,
OPTIONAL,
OPTIONAL,
DEFAULT pi4,
DEFAULT f4,
DEFAULT 2

PICH-Info-LCR-r4 ::= SEQUENCE {
    timeslot           TimeslotNumber-LCR-r4,
    pichChannelisationCodeList-LCR-r4 PichChannelisationCodeList-LCR-r4,
    midambleShiftAndBurstType MidambleShiftAndBurstType-LCR-r4,
    repetitionPeriodLengthOffset RepPerLengthOffset-PICH,
    pagingIndicatorLength PagingIndicatorLength,
    n-GAP                 N-GAP,
    n-PCH                 N-PCH,
}
OPTIONAL,
OPTIONAL,
OPTIONAL,
DEFAULT pi4,
DEFAULT f4,
DEFAULT 2

PICH-PowerOffset ::= INTEGER (-10..5)

PilotBits128 ::= ENUMERATED {
    pb4, pb8 }

```



```

PRACH-RACH-Info-LCR-r4 ::= SEQUENCE {
    sync-UL-Info
    prach-DefinitionList
}

PRACH-SystemInformation ::= SEQUENCE {
    prach-RACH-Info PRACH-RACH-Info,
    transportChannelIdentity TransportChannelIdentity,
    rach-TransportFormatSet TransportFormatSet OPTIONAL,
    rach-TFCS TFCS OPTIONAL,
    prach-Partitioning PRACH-Partitioning OPTIONAL,
    persistenceScalingFactorList PersistenceScalingFactorList OPTIONAL,
    ac-To-ASC-MappingTable AC-To-ASC-MappingTable OPTIONAL,
    modeSpecificInfo CHOICE {
        fdd SEQUENCE {
            primaryCPICH-TX-Power PrimaryCPICH-TX-Power OPTIONAL,
            constantValue ConstantValue OPTIONAL,
            prach-PowerOffset PRACH-PowerOffset OPTIONAL,
            rach-TransmissionParameters RACH-TransmissionParameters OPTIONAL,
            aich-Info AICH-Info OPTIONAL
        },
        tdd NULL
    }
}

PRACH-SystemInformation-LCR-r4 ::= SEQUENCE {
    prach-RACH-Info-LCR PRACH-RACH-Info-LCR-r4,
    rach-TransportFormatSet-LCR TransportFormatSet-LCR OPTIONAL,
    prach-Partitioning-LCR PRACH-Partitioning-LCR-r4 OPTIONAL
}

PRACH-SystemInformationList ::= SEQUENCE (SIZE (1..maxPRACH)) OF
    PRACH-SystemInformation

PRACH-SystemInformationList-LCR-r4 ::= SEQUENCE (SIZE (1..maxPRACH)) OF
    PRACH-SystemInformation-LCR-r4

PreambleRetransMax ::= INTEGER (1..64)

PreambleScramblingCodeWordNumber ::= INTEGER (0..15)

PreDefPhyChConfiguration ::= SEQUENCE {
    ul-DPCH-InfoPredef UL-DPCH-InfoPredef,
    dl-CommonInformationPredef DL-CommonInformationPredef OPTIONAL
}

PrimaryCCPCH-Info ::= CHOICE {
    fdd SEQUENCE {
        tx-DiversityIndicator BOOLEAN
    },
    tdd SEQUENCE {
        -- syncCase should be ignored for 1.28Mcps TDD mode
        syncCase CHOICE {
            syncCase1 SEQUENCE {
                timeslot TimeslotNumber
            },
            syncCase2 SEQUENCE {
                timeslotSync2 TimeslotSync2
            }
        }
    }
    cellParametersID CellParametersID OPTIONAL,
    sctd-Indicator BOOLEAN OPTIONAL
}

PrimaryCCPCH-Info-r4 ::= CHOICE {
    fdd SEQUENCE {
        tx-DiversityIndicator BOOLEAN
    },
    tdd SEQUENCE {

```

```

        tddOption CHOICE {
            tdd384 SEQUENCE {
                syncCase CHOICE {
                    syncCase1 SEQUENCE {
                        timeslot TimeslotNumber
                    },
                    syncCase2 SEQUENCE {
                        timeslotSync2 TimeslotSync2
                    }
                }
            } OPTIONAL
        },
        tdd128 SEQUENCE {
            tstd-Indicator BOOLEAN
        }
    },
    cellParametersID CellParametersID OPTIONAL,
    blockSTTD-Indicator BOOLEAN
}

PrimaryCCPCH-Info-LCR-r4 ::= SEQUENCE {
    tstd-Indicator BOOLEAN,
    cellParametersID CellParametersID OPTIONAL,
    blockSTTD-Indicator BOOLEAN
}

-- For 1.28Mcps TDD, the following IE includes elements for the PCCPCH Info additional to those
-- in PrimaryCCPCH-Info
PrimaryCCPCH-Info-LCR-r4-ext ::= SEQUENCE {
    tstd-Indicator BOOLEAN
}

PrimaryCCPCH-InfoPost ::= SEQUENCE {
    syncCase CHOICE {
        syncCase1 SEQUENCE {
            timeslot TimeslotNumber
        },
        syncCase2 SEQUENCE {
            timeslotSync2 TimeslotSync2
        }
    },
    cellParametersID CellParametersID,
    sctd-Indicator BOOLEAN
}

PrimaryCCPCH-InfoPostTDD-LCR-r4 ::= SEQUENCE {
    tstd-Indicator BOOLEAN,
    cellParametersID CellParametersID,
    blockSTTD-Indicator BOOLEAN
}

PrimaryCCPCH-TX-Power ::= INTEGER (6..43)

PrimaryCPICH-Info ::= SEQUENCE {
    primaryScramblingCode PrimaryScramblingCode
}

PrimaryCPICH-TX-Power ::= INTEGER (-10..50)

PrimaryScramblingCode ::= INTEGER (0..511)

PuncturingLimit ::= ENUMERATED {
    p10-40, p10-44, p10-48, p10-52, p10-56,
    p10-60, p10-64, p10-68, p10-72, p10-76,
    p10-80, p10-84, p10-88, p10-92, p10-96, p11 }

PUSCH-CapacityAllocationInfo ::= SEQUENCE {
    pusch-Allocation CHOICE {
        pusch-AllocationPending NULL,
        pusch-AllocationAssignment SEQUENCE {
            pusch-AllocationPeriodInfo AllocationPeriodInfo,

```

pusch-PowerControlInfo	UL-TargetSIR	OPTIONAL,
configuration	CHOICE {	
old-Configuration	SEQUENCE {	
tfcs-ID	TFCS-IdentityPlain	DEFAULT 1,
pusch-Identity	PUSCH-Identity	
},		
new-Configuration	SEQUENCE {	
pusch-Info	PUSCH-Info,	
pusch-Identity	PUSCH-Identity	OPTIONAL
}		
}		
}		
}		
}		
}		
PUSCH-CapacityAllocationInfo-r4 ::=	SEQUENCE {	
pusch-Allocation	CHOICE {	
pusch-AllocationPending	NULL,	
pusch-AllocationAssignment	SEQUENCE {	
pusch-AllocationPeriodInfo	AllocationPeriodInfo,	
pusch-PowerControlInfo	PUSCH-PowerControlInfo-r4	OPTIONAL,
configuration	CHOICE {	
old-Configuration	SEQUENCE {	
tfcs-ID	TFCS-IdentityPlain	DEFAULT 1,
pusch-Identity	PUSCH-Identity	
},		
new-Configuration	SEQUENCE {	
pusch-Info	PUSCH-Info-r4,	
pusch-Identity	PUSCH-Identity	OPTIONAL
}		
}		
}		
}		
}		
PUSCH-Identity ::=	INTEGER (1..hiPUSCHidentities)	
PUSCH-Info ::=	SEQUENCE {	
tfcs-ID	TFCS-IdentityPlain	DEFAULT 1,
commonTimeslotInfo	CommonTimeslotInfo	OPTIONAL,
pusch-TimeslotsCodes	UplinkTimeslotsCodes	OPTIONAL
}		
PUSCH-Info-r4 ::=	SEQUENCE {	
tfcs-ID	TFCS-IdentityPlain	DEFAULT 1,
commonTimeslotInfo	CommonTimeslotInfo	OPTIONAL,
tddOption	CHOICE {	
tdd384	SEQUENCE {	
pusch-TimeslotsCodes	UplinkTimeslotsCodes	OPTIONAL
},		
tdd128	SEQUENCE {	
pusch-TimeslotsCodes	UplinkTimeslotsCodes-LCR-r4	OPTIONAL
}		
}		
}		
PUSCH-Info-LCR-r4 ::=	SEQUENCE {	
tfcs-ID	TFCS-IdentityPlain	DEFAULT 1,
commonTimeslotInfo	CommonTimeslotInfo	OPTIONAL,
pusch-TimeslotsCodes	UplinkTimeslotsCodes-LCR-r4	OPTIONAL
}		
PUSCH-PowerControlInfo-r4 ::=	SEQUENCE {	
-- The IE ul-TargetSIR corresponds to PRX-PUSCHdes for 1.28Mcps TDD		
-- Actual value PRX-PUSCHdes = (value of IE "ul-TargetSIR" - 120)		
ul-TargetSIR	UL-TargetSIR,	
tddOption	CHOICE {	
tdd384	NULL,	
tdd128	SEQUENCE {	
tpc-StepSize	TPC-StepSizeTDD	OPTIONAL, 7
}		
}		

```

| ----- dl-CCTrChTPCList ----- DL-CCTrChTPCList ----- OPTIONAL
    }
}

PUSCH-SysInfo ::= SEQUENCE {
    pusch-Identity          PUSCH-Identity,
    pusch-Info              PUSCH-Info,
    usch-TFS                TransportFormatSet
    usch-TFCS                TFCS
}
OPTIONAL,
OPTIONAL

PUSCH-SysInfo-LCR-r4 ::= SEQUENCE {
    pusch-Identity          PUSCH-Identity,
    pusch-Info              PUSCH-Info-LCR-r4,
    usch-TFS                TransportFormatSet
    usch-TFCS                TFCS
}
OPTIONAL,
OPTIONAL

PUSCH-SysInfoList ::= SEQUENCE (SIZE (1..maxPUSCH)) OF
    PUSCH-SysInfo

PUSCH-SysInfoList-LCR-r4 ::= SEQUENCE (SIZE (1..maxPUSCH)) OF
    PUSCH-SysInfo-LCR-r4

PUSCH-SysInfoList-SFN ::= SEQUENCE (SIZE (1..maxPUSCH)) OF
    SEQUENCE {
        pusch-SysInfo      PUSCH-SysInfo,
        sfn-TimeInfo        SFN-TimeInfo
    }
OPTIONAL

PUSCH-SysInfoList-SFN-LCR-r4 ::= SEQUENCE (SIZE (1..maxPUSCH)) OF
    SEQUENCE {
        pusch-SysInfo      PUSCH-SysInfo-LCR-r4,
        sfn-TimeInfo        SFN-TimeInfo
    }
OPTIONAL

RACH-TransmissionParameters ::= SEQUENCE {
    mmax                    INTEGER (1..32),
    nb01Min                 NB01,
    nb01Max                 NB01
}

ReducedScramblingCodeNumber ::= INTEGER (0..8191)

RepetitionPeriodAndLength ::= CHOICE {
    repetitionPeriod1      NULL,
    -- repetitionPeriod2 could just as well be NULL also.
    repetitionPeriod2      INTEGER (1..1),
    repetitionPeriod4      INTEGER (1..3),
    repetitionPeriod8      INTEGER (1..7),
    repetitionPeriod16     INTEGER (1..15),
    repetitionPeriod32     INTEGER (1..31),
    repetitionPeriod64     INTEGER (1..63)
}

RepetitionPeriodLengthAndOffset ::= CHOICE {
    repetitionPeriod1      NULL,
    repetitionPeriod2      SEQUENCE {
        length              NULL,
        offset              INTEGER (0..1)
    },
    repetitionPeriod4      SEQUENCE {
        length              INTEGER (1..3),
        offset              INTEGER (0..3)
    },
    repetitionPeriod8      SEQUENCE {
        length              INTEGER (1..7),
        offset              INTEGER (0..7)
    },
    repetitionPeriod16     SEQUENCE {
}

```

```

        length                INTEGER (1..15),
        offset                INTEGER (0..15)
    },
    repetitionPeriod32        SEQUENCE {
        length                INTEGER (1..31),
        offset                INTEGER (0..31)
    },
    repetitionPeriod64        SEQUENCE {
        length                INTEGER (1..63),
        offset                INTEGER (0..63)
    }
}

ReplacedPDSCH-CodeInfo ::= SEQUENCE {
    tfci-Field2              MaxTFCI-Field2Value,
    spreadingFactor          SF-PDSCH,
    codeNumber               CodeNumberDSCH,
    multiCodeInfo           MultiCodeInfo
}

ReplacedPDSCH-CodeInfoList ::= SEQUENCE (SIZE (1..maxTFCI-2-Combs)) OF
    ReplacedPDSCH-CodeInfo

RepPerLengthOffset-PICH ::= CHOICE {
    rpp4-2                   INTEGER (0..3),
    rpp8-2                   INTEGER (0..7),
    rpp8-4                   INTEGER (0..7),
    rpp16-2                  INTEGER (0..15),
    rpp16-4                  INTEGER (0..15),
    rpp32-2                  INTEGER (0..31),
    rpp32-4                  INTEGER (0..31),
    rpp64-2                  INTEGER (0..63),
    rpp64-4                  INTEGER (0..63)
}

RestrictedTrCH ::= SEQUENCE {
    dl-restrictedTrCh-Type   DL-TrCH-Type,
    restrictedDL-TrCH-Identity TransportChannelIdentity,
    allowedTFIList          AllowedTFI-List
}

RestrictedTrCH-InfoList ::= SEQUENCE (SIZE(1..maxTrCH)) OF
    RestrictedTrCH

RL-AdditionInformation ::= SEQUENCE {
    primaryCPICH-Info        PrimaryCPICH-Info,
    dl-DPCH-InfoPerRL        DL-DPCH-InfoPerRL,
    tfci-CombiningIndicator  BOOLEAN,
    sccpch-InfoForFACH        SCCPCH-InfoForFACH
} OPTIONAL

RL-AdditionInformationList ::= SEQUENCE (SIZE (1..maxRL-1)) OF
    RL-AdditionInformation

RL-IdentifierList ::= SEQUENCE (SIZE (1..maxRL)) OF
    PrimaryCPICH-Info

RL-RemovalInformationList ::= SEQUENCE (SIZE (1..maxRL)) OF
    PrimaryCPICH-Info

RPP ::= ENUMERATED {
    mode0, mode1 }

S-Field ::= ENUMERATED {
    elbit, e2bits }

SCCPCH-ChannelisationCode ::= ENUMERATED {
    cc16-1, cc16-2, cc16-3, cc16-4,
    cc16-5, cc16-6, cc16-7, cc16-8,
    cc16-9, cc16-10, cc16-11, cc16-12,
    cc16-13, cc16-14, cc16-15, cc16-16 }

```

```

SCCPCH-ChannelisationCodeList ::= SEQUENCE (SIZE (1..16)) OF
    SCCPCH-ChannelisationCode

SCCPCH-InfoForFACH ::= SEQUENCE {
    secondaryCCPCH-Info      SecondaryCCPCH-Info,
    tfcs                    TFCS,
    modeSpecificInfo        CHOICE {
        fdd                 SEQUENCE {
            fach-PCH-InformationList      FACH-PCH-InformationList,
            sib-ReferenceListFACH         SIB-ReferenceListFACH
        },
        tdd                 SEQUENCE {
            fach-PCH-InformationList      FACH-PCH-InformationList
        }
    }
}

SCCPCH-InfoForFACH-r4 ::= SEQUENCE {
    secondaryCCPCH-Info      SecondaryCCPCH-Info-r4,
    tfcs                    TFCS,
    fach-PCH-InformationList FACH-PCH-InformationList,
    modeSpecificInfo        CHOICE {
        fdd                 SEQUENCE {
            sib-ReferenceListFACH         SIB-ReferenceListFACH
        },
        tdd                 NULL
    }
}

SCCPCH-SystemInformation ::= SEQUENCE {
    secondaryCCPCH-Info      SecondaryCCPCH-Info,
    tfcs                    TFCS,
    fach-PCH-InformationList FACH-PCH-InformationList,
    pich-Info               PICH-Info
}
OPTIONAL,
OPTIONAL,
OPTIONAL

SCCPCH-SystemInformation-LCR-r4-ext ::= SEQUENCE {
    secondaryCCPCH-LCR-Extensions SecondaryCCPCH-Info-LCR-r4-ext,
    -- pich-Info in the SCCPCH-SystemInformation IE shall be absent,
    -- and instead the following used.
    pich-Info               PICH-Info-LCR-r4
}
OPTIONAL

SCCPCH-SystemInformationList ::= SEQUENCE (SIZE (1..maxSCCPCH)) OF
    SCCPCH-SystemInformation

-- SCCPCH-SystemInformationList-LCR-r4-ext includes elements additional to those in
-- SCCPCH-SystemInformationList for the 1.28Mcps TDD. The order of the IEs
-- indicates which SCCPCH-SystemInformation-LCR-r4-ext IE extends which
-- SCCPCH-SystemInformation IE.
SCCPCH-SystemInformationList-LCR-r4-ext ::= SEQUENCE (SIZE (1..maxSCCPCH)) OF
    SCCPCH-SystemInformation-LCR-r4-ext

ScramblingCodeChange ::= ENUMERATED {
    codeChange, noCodeChange }

ScramblingCodeType ::= ENUMERATED {
    shortSC,
    longSC }

SecondaryCCPCH-Info ::= SEQUENCE {
    modeSpecificInfo        CHOICE {
        fdd                 SEQUENCE {
            -- dummy1 is not used in this version of the specification and should be ignored.
            dummy1          PCPICH-UsageForChannelEst,
            -- dummy2 is not used in this version of the specification. It should not
            -- be sent and if received it should be ignored.
            dummy2          SecondaryCPICH-Info,
            secondaryScramblingCode SecondaryScramblingCode,
            sttd-Indicator  BOOLEAN,
        }
    }
}
OPTIONAL,
OPTIONAL,

```

```

        sf-AndCodeNumber          SF256-AndCodeNumber,
        pilotSymbolExistence      BOOLEAN,
        tfci-Existence            BOOLEAN,
        positionFixedOrFlexible    PositionFixedOrFlexible,
        timingOffset              TimingOffset                                DEFAULT 0
    },
    tdd                            SEQUENCE {
        -- TABULAR: the offset is included in CommonTimeslotInfoSCCPCH
        commonTimeslotInfo        CommonTimeslotInfoSCCPCH,
        individualTimeslotInfo    IndividualTimeslotInfo,
        channelisationCode        SCCPCH-ChannelisationCodeList
    }
}

SecondaryCCPCH-Info-r4 ::= SEQUENCE {
    modeSpecificInfo             CHOICE {
        fdd                      SEQUENCE {
            secondaryScramblingCode SecondaryScramblingCode    OPTIONAL,
            sttd-Indicator          BOOLEAN,
            sf-AndCodeNumber        SF256-AndCodeNumber,
            pilotSymbolExistence    BOOLEAN,
            tfci-Existence          BOOLEAN,
            positionFixedOrFlexible PositionFixedOrFlexible,
            timingOffset            TimingOffset                DEFAULT 0
        },
        tdd                      SEQUENCE {
            -- TABULAR: the offset is included in CommonTimeslotInfoSCCPCH
            commonTimeslotInfo      CommonTimeslotInfoSCCPCH,
            tddOption              CHOICE {
                tdd384             SEQUENCE {
                    individualTimeslotInfo IndividualTimeslotInfo
                },
                tdd128             SEQUENCE {
                    individualTimeslotInfo IndividualTimeslotInfo-LCR-r4
                }
            },
            channelisationCode      SCCPCH-ChannelisationCodeList
        }
    }
}

SecondaryCCPCH-Info-LCR-r4-ext ::= SEQUENCE {
    individualTimeslotLCR-Ext     IndividualTimeslotInfo-LCR-r4-ext
}

SecondaryCPICH-Info ::= SEQUENCE {
    secondaryDL-ScramblingCode    SecondaryScramblingCode    OPTIONAL,
    channelisationCode            ChannelisationCode256
}

SecondaryScramblingCode ::= INTEGER (1..15)

SecondInterleavingMode ::= ENUMERATED {
    frameRelated, timeslotRelated }

-- SF256-AndCodeNumber encodes both "Spreading factor" and "Code Number"
SF256-AndCodeNumber ::= CHOICE {
    sf4          INTEGER (0..3),
    sf8          INTEGER (0..7),
    sf16         INTEGER (0..15),
    sf32         INTEGER (0..31),
    sf64         INTEGER (0..63),
    sf128        INTEGER (0..127),
    sf256        INTEGER (0..255)
}

-- SF512-AndCodeNumber encodes both "Spreading factor" and "Code Number"
SF512-AndCodeNumber ::= CHOICE {
    sf4          INTEGER (0..3),
    sf8          INTEGER (0..7),

```



```

    sf16                INTEGER (0..15),
    sf32                INTEGER (0..31),
    sf64                INTEGER (0..63),
    sf128               INTEGER (0..127),
    sf256               INTEGER (0..255),
    sf512               INTEGER (0..511)
}

-- SF512-AndPilot encodes both "Spreading factor" and "Number of bits for Pilot bits"
SF512-AndPilot ::= CHOICE {
    sfd4                NULL,
    sfd8                NULL,
    sfd16               NULL,
    sfd32               NULL,
    sfd64                NULL,
    sfd128              PilotBits128,
    sfd256              PilotBits256,
    sfd512              NULL
}

SF-PDSCH ::= ENUMERATED {
    sfp4, sfp8, sfp16, sfp32,
    sfp64, sfp128, sfp256 }

SF-PRACH ::= ENUMERATED {
    sfpr32, sfpr64, sfpr128, sfpr256 }

SFN-TimeInfo ::= SEQUENCE {
    activationTimeSFN   INTEGER (0..4095),
    physChDuration      DurationTimeInfo
}

SpecialBurstScheduling ::= INTEGER (0..7)

SpreadingFactor ::= ENUMERATED {
    sf4, sf8, sf16, sf32,
    sf64, sf128, sf256 }

SRB-delay ::= INTEGER (0..7)

SSDT-CellIdentity ::= ENUMERATED {
    ssdt-id-a, ssdt-id-b, ssdt-id-c,
    ssdt-id-d, ssdt-id-e, ssdt-id-f,
    ssdt-id-g, ssdt-id-h }

SSDT-Information ::= SEQUENCE {
    s-Field             S-Field,
    codeWordSet         CodeWordSet
}

SSDT-Information-r4 ::= SEQUENCE {
    s-Field             S-Field,
    codeWordSet         CodeWordSet,
    ssdt-UL             SSDT-UL-r4
}

-- SSDT-UL-r4 is used to extend the
-- SSDT-Information IE from Release 4 onwards.
SSDT-UL-r4 ::= ENUMERATED {
    ul, ul-AndDL }

SynchronisationParameters-r4 ::= SEQUENCE {
    sync-UL-CodesBitmap BIT STRING {
        code7(0),
        code6(1),
        code5(2),
        code4(3),
        code3(4),
        code2(5),
        code1(6),
        code0(7)
    } (SIZE (8)),

```

```

    fpach-Info                                FPACH-Info-r4,
    -- Actual value prxUpPCHdes = IE value - 120
    prxUpPCHdes                                INTEGER (0..62),
    sync-UL-Procedure                          SYNC-UL-Procedure-r4                                OPTIONAL
}

SYNC-UL-Procedure-r4 ::=                     SEQUENCE {
    max-SYNC-UL-Transmissions                 ENUMERATED { tr1, tr2, tr4, tr8 },
    powerRampStep                             INTEGER (0..3)
}

SYNC-UL-Info-r4 ::=                          SEQUENCE {
    sync-UL-Codes-Bitmap                     BIT STRING {
                                                code7(0),
                                                code6(1),
                                                code5(2),
                                                code4(3),
                                                code3(4),
                                                code2(5),
                                                code1(6),
                                                code0(7)
                                                } ( SIZE (8)),
    -- Actual value prxUpPCHdes = IE value - 120
    prxUpPCHdes                               INTEGER (0..62),
    powerRampStep                             INTEGER (0..3),
    max-SYNC-UL-Transmissions                 ENUMERATED { tr1, tr2, tr4, tr8 } ,
    mmax                                       INTEGER(1..32)
}

TDD-FPACH-CCode16-r4 ::=                     ENUMERATED {
    cc16-1, cc16-2, cc16-3, cc16-4,
    cc16-5, cc16-6, cc16-7, cc16-8,
    cc16-9, cc16-10, cc16-11, cc16-12,
    cc16-13, cc16-14, cc16-15, cc16-16 }

TDD-UL-Interference ::=                     INTEGER (-110..-52)

TDD-PICH-CCode ::=                           ENUMERATED {
    cc16-1, cc16-2, cc16-3, cc16-4,
    cc16-5, cc16-6, cc16-7, cc16-8,
    cc16-9, cc16-10, cc16-11, cc16-12,
    cc16-13, cc16-14, cc16-15, cc16-16 }

TDD-PRACH-CCode8 ::=                         ENUMERATED {
    cc8-1, cc8-2, cc8-3, cc8-4,
    cc8-5, cc8-6, cc8-7, cc8-8 }

TDD-PRACH-CCode16 ::=                       ENUMERATED {
    cc16-1, cc16-2, cc16-3, cc16-4,
    cc16-5, cc16-6, cc16-7, cc16-8,
    cc16-9, cc16-10, cc16-11, cc16-12,
    cc16-13, cc16-14, cc16-15, cc16-16 }

TDD-PRACH-CCode-LCR-r4 ::=                  ENUMERATED {
    cc4-1, cc4-2, cc4-3, cc4-4,
    cc8-1, cc8-2, cc8-3, cc8-4,
    cc8-5, cc8-6, cc8-7, cc8-8,
    cc16-1, cc16-2, cc16-3, cc16-4,
    cc16-5, cc16-6, cc16-7, cc16-8,
    cc16-9, cc16-10, cc16-11, cc16-12,
    cc16-13, cc16-14, cc16-15, cc16-16 }

TDD-PRACH-CCodeList ::=                     CHOICE {
    sf8                                       SEQUENCE (SIZE (1..8)) OF
                                                TDD-PRACH-CCode8,
    sf16                                       SEQUENCE (SIZE (1..8)) OF
                                                TDD-PRACH-CCode16
}

TFC-ControlDuration ::=                      ENUMERATED {
    tfc-cd1, tfc-cd2, tfc-cd4, tfc-cd8,

```

```

        tfc-cd16, tfc-cd24, tfc-cd32,
        tfc-cd48, tfc-cd64, tfc-cd128,
        tfc-cd192, tfc-cd256, tfc-cd512 }

TFCI-Coding ::=          ENUMERATED {
                           tfcI-bits-4, tfcI-bits-8,
                           tfcI-bits-16, tfcI-bits-32 }

TGCFN ::=              INTEGER (0..255)

-- In TGD, value 270 represents "undefined" in the tabular description.
TGD ::=               INTEGER (15..270)

TGL ::=               INTEGER (1..14)

TGMP ::=              ENUMERATED {
                           tdd-Measurement, fdd-Measurement,
                           gsm-CarrierRSSIMeasurement,
                           gsm-initialBSICIdentification, gsmBSICReconfirmation,
                           multi-carrier }

TGP-Sequence ::=      SEQUENCE {
    tgpsi                TGPSI,
    tgps-Status          CHOICE {
        activate         SEQUENCE {
            tgcfn
        },
        deactivate       NULL
    },
    tgps-ConfigurationParams  TGPS-ConfigurationParams  OPTIONAL
}

TGPS-Reconfiguration-CFN ::=  INTEGER (0..255)

TGP-SequenceList ::=      SEQUENCE (SIZE (1..maxTGPS)) OF
    TGP-Sequence

TGP-SequenceShort ::=      SEQUENCE {
    tgpsi                TGPSI,
    tgps-Status          CHOICE {
        activate         SEQUENCE {
            tgcfn
        },
        deactivate       NULL
    }
}

TGPL ::=              INTEGER (1..144)

-- TABULAR: In TGPRC, value 0 represents "infinity" in the tabular description.
TGPRC ::=             INTEGER (0..511)

TGPS-ConfigurationParams ::= SEQUENCE {
    tgmp                 TGMP,
    tgprc                TGPRC,
    tgsn                 TGSN,
    tgl1                 TGL,
    tgl2                 TGL  OPTIONAL,
    tgd                  TGD,
    tgpl1                TGPL,
    tgpl2                TGPL  OPTIONAL,
    rpp                  RPP,
    itp                  ITP,
    -- TABULAR: Compressed mode method is nested inside UL-DL-Mode
    ul-DL-Mode           UL-DL-Mode,
    dl-FrameType         DL-FrameType,
    deltaSIR1            DeltaSIR,
    deltaSIRAfter1      DeltaSIR,
    deltaSIR2            DeltaSIR  OPTIONAL,
    deltaSIRAfter2      DeltaSIR  OPTIONAL,
    nIdentifyAbort       NIdentifyAbort  OPTIONAL,
}

```

```

    treconfirmAbort                TreconfirmAbort                OPTIONAL
}
TGPSI ::=                          INTEGER (1..maxTGPS)
TGSN ::=                          INTEGER (0..14)
TimeInfo ::=                       SEQUENCE {
    activationTime                 ActivationTime                OPTIONAL,
    durationTimeInfo              DurationTimeInfo              OPTIONAL
}
TimeslotList ::=                   SEQUENCE (SIZE (1..maxTS)) OF
    TimeslotNumber
TimeslotList-r4 ::=                CHOICE {
    tdd384                         SEQUENCE (SIZE (1..maxTS)) OF
        TimeslotNumber,
    tdd128                         SEQUENCE (SIZE (1..maxTS-LCR)) OF
        TimeslotNumber-LCR-r4
}
-- If TimeslotNumber is included for a 1.28Mcps TDD description, it shall take values from 0..6
TimeslotNumber ::=                 INTEGER (0..14)
TimeslotNumber-LCR-r4 ::=          INTEGER (0..6)
TimeslotNumber-PRACH-LCR-r4 ::=    INTEGER (1..6)
TimeslotSync2 ::=                  INTEGER (0..6)
-- Actual value TimingOffset = IE value * 256
TimingOffset ::=                   INTEGER (0..149)
TPC-CombinationIndex ::=           INTEGER (0..5)
-- Actual value TPC-StepSizeFDD = IE value + 1
TPC-StepSizeFDD ::=                INTEGER (0..1)
TPC-StepSizeTDD ::=                INTEGER (1..3)
-- Actual value TreconfirmAbort = IE value * 0.5 seconds
TreconfirmAbort ::=                INTEGER (1..20)
TX-DiversityMode ::=               ENUMERATED {
    noDiversity,
    sttd,
    closedLoopMode1,
    closedLoopMode2 }
UARFCN ::=                          INTEGER (0..16383)
UCSM-Info ::=                       SEQUENCE {
    minimumSpreadingFactor         MinimumSpreadingFactor,
    nf-Max                         NF-Max,
    channelReqParamsForUCSM        ChannelReqParamsForUCSM
}
UL-CCTrCH ::=                       SEQUENCE {
    tfcs-ID                        TFCS-IdentityPlain           DEFAULT 1,
    ul-TargetSIR                   UL-TargetSIR,
    timeInfo                        TimeInfo,
    commonTimeslotInfo             CommonTimeslotInfo           OPTIONAL,
    ul-CCTrCH-TimeslotsCodes       UplinkTimeslotsCodes        OPTIONAL
}
UL-CCTrCH-r4 ::=                    SEQUENCE {
    tfcs-ID                        TFCS-IdentityPlain           DEFAULT 1,
    ul-TargetSIR                   UL-TargetSIR,
    timeInfo                        TimeInfo,
    commonTimeslotInfo             CommonTimeslotInfo           OPTIONAL,

```

```

    tddOption
      tdd384
        ul-CCTrCH-TimeslotsCodes
      },
      tdd128
        ul-CCTrCH-TimeslotsCodes
    }
  }
}

UL-CCTrCHList ::= SEQUENCE (SIZE (1..maxCCTrCH)) OF
                  UL-CCTrCH

UL-CCTrCHList-r4 ::= SEQUENCE (SIZE (1..maxCCTrCH)) OF
                    UL-CCTrCH-r4

UL-CCTrCHListToRemove ::= SEQUENCE (SIZE (1..maxCCTrCH)) OF
                          TFCS-IdentityPlain

UL-CCTrChTPCList ::= SEQUENCE (SIZE (0..maxCCTrCH)) OF
                    TFCS-Identity

UL-ChannelRequirement ::= CHOICE {
  ul-DPCH-Info
  cpch-SetInfo
}

UL-ChannelRequirement-r4 ::= CHOICE {
  ul-DPCH-Info
  cpch-SetInfo
}

UL-ChannelRequirement-r5 ::= CHOICE {
  ul-DPCH-Info
  cpch-SetInfo
}

UL-ChannelRequirementWithCPCH-SetID ::= CHOICE {
  ul-DPCH-Info
  cpch-SetInfo
  cpch-SetID
}

UL-ChannelRequirementWithCPCH-SetID-r4 ::= CHOICE {
  ul-DPCH-Info
  cpch-SetInfo
  cpch-SetID
}

UL-ChannelRequirementWithCPCH-SetID-r5 ::= CHOICE {
  ul-DPCH-Info
  cpch-SetInfo
  cpch-SetID
}

UL-CompressedModeMethod ::= ENUMERATED {
  sf-2,
  higherLayerScheduling }

UL-DL-Mode ::= CHOICE {
  ul
  dl
  ul-and-dl
    ul
    dl
  }}

UL-DPCCH-SlotFormat ::= ENUMERATED {
  slf0, slf1, slf2 }

UL-DPCH-Info ::= SEQUENCE {

```

```

ul-DPCH-PowerControlInfo          UL-DPCH-PowerControlInfo          OPTIONAL,
modeSpecificInfo                   CHOICE {
  fdd                               SEQUENCE {
    scramblingCodeType              ScramblingCodeType,
    scramblingCode                   UL-ScramblingCode,
    numberOfDPDCH                    NumberOfDPDCH                DEFAULT 1,
    spreadingFactor                  SpreadingFactor,
    tfci-Existence                   BOOLEAN,
    -- numberOfFBI-Bits is conditional based on history
    numberOfFBI-Bits                 NumberOfFBI-Bits            OPTIONAL,
    puncturingLimit                  PuncturingLimit
  },
  tdd                               SEQUENCE {
    ul-TimingAdvance                 UL-TimingAdvanceControl    OPTIONAL,
    ul-CCTrCHList                    UL-CCTrCHList              OPTIONAL,
    ul-CCTrCHListToRemove            UL-CCTrCHListToRemove      OPTIONAL
  }
}
}

UL-DPCH-Info-r4 ::=                SEQUENCE {
  ul-DPCH-PowerControlInfo          UL-DPCH-PowerControlInfo-r4  OPTIONAL,
  modeSpecificInfo                   CHOICE {
    fdd                               SEQUENCE {
      scramblingCodeType              ScramblingCodeType,
      scramblingCode                   UL-ScramblingCode,
      numberOfDPDCH                    NumberOfDPDCH                DEFAULT 1,
      spreadingFactor                  SpreadingFactor,
      tfci-Existence                   BOOLEAN,
      -- numberOfFBI-Bits is conditional based on history
      numberOfFBI-Bits                 NumberOfFBI-Bits            OPTIONAL,
      puncturingLimit                  PuncturingLimit
    },
    tdd                               SEQUENCE {
      ul-TimingAdvance                 UL-TimingAdvanceControl-r4  OPTIONAL,
      ul-CCTrCHList                    UL-CCTrCHList-r4           OPTIONAL,
      ul-CCTrCHListToRemove            UL-CCTrCHListToRemove      OPTIONAL
    }
  }
}

UL-DPCH-Info-r5 ::=                SEQUENCE {
  ul-DPCH-PowerControlInfo          UL-DPCH-PowerControlInfo-r5  OPTIONAL,
  modeSpecificInfo                   CHOICE {
    fdd                               SEQUENCE {
      scramblingCodeType              ScramblingCodeType,
      scramblingCode                   UL-ScramblingCode,
      numberOfDPDCH                    NumberOfDPDCH                DEFAULT 1,
      spreadingFactor                  SpreadingFactor,
      tfci-Existence                   BOOLEAN,
      -- numberOfFBI-Bits is conditional based on history
      numberOfFBI-Bits                 NumberOfFBI-Bits            OPTIONAL,
      puncturingLimit                  PuncturingLimit
    },
    tdd                               SEQUENCE {
      ul-TimingAdvance                 UL-TimingAdvanceControl-r4  OPTIONAL,
      ul-CCTrCHList                    UL-CCTrCHList-r4           OPTIONAL,
      ul-CCTrCHListToRemove            UL-CCTrCHListToRemove      OPTIONAL
    }
  }
}

UL-DPCH-InfoPostFDD ::=            SEQUENCE {
  ul-DPCH-PowerControlInfo          UL-DPCH-PowerControlInfoPostFDD,
  scramblingCodeType                  ScramblingCodeType,
  reducedScramblingCodeNumber         ReducedScramblingCodeNumber,
  spreadingFactor                      SpreadingFactor
}

UL-DPCH-InfoPostTDD ::=            SEQUENCE {

```

```

    ul-DPCH-PowerControlInfo          UL-DPCH-PowerControlInfoPostTDD,
    ul-TimingAdvance                  UL-TimingAdvanceControl          OPTIONAL,
    ul-CCTrCH-TimeslotsCodes          UplinkTimeslotsCodes
}

UL-DPCH-InfoPostTDD-LCR-r4 ::=      SEQUENCE {
    ul-DPCH-PowerControlInfo          UL-DPCH-PowerControlInfoPostTDD-LCR-r4,
    ul-TimingAdvance                  UL-TimingAdvanceControl-LCR-r4      OPTIONAL,
    ul-CCTrCH-TimeslotsCodes          UplinkTimeslotsCodes-LCR-r4
}

UL-DPCH-InfoPredef ::=              SEQUENCE {
    ul-DPCH-PowerControlInfo          UL-DPCH-PowerControlInfoPredef,
    modeSpecificInfo                  CHOICE {
        fdd                            SEQUENCE {
            tfci-Existence              BOOLEAN,
            puncturingLimit             PuncturingLimit
        },
        tdd                            SEQUENCE {
            commonTimeslotInfo          CommonTimeslotInfo
        }
    }
}

UL-DPCH-PowerControlInfo ::=        CHOICE {
    fdd                                SEQUENCE {
        dpcch-PowerOffset              DPCCH-PowerOffset,
        pc-Preamble                    PC-Preamble,
        SRB-delay                      SRB-delay,
        -- TABULAR: TPC step size nested inside PowerControlAlgorithm
        powerControlAlgorithm          PowerControlAlgorithm
    },
    tdd                                SEQUENCE {
        ul-TargetSIR                   UL-TargetSIR                        OPTIONAL,
        ul-OL-PC-Signalling             CHOICE {
            broadcast-UL-OL-PC-info     NULL,
            individuallySignalled       SEQUENCE {
                individualTS-InterferenceList IndividualTS-InterferenceList,
                dpch-ConstantValue      ConstantValueTdd,
                primaryCCPCH-TX-Power   PrimaryCCPCH-TX-Power
            }
        }
    }
}

UL-DPCH-PowerControlInfo-r4 ::=      CHOICE {
    fdd                                SEQUENCE {
        dpcch-PowerOffset              DPCCH-PowerOffset,
        pc-Preamble                    PC-Preamble,
        SRB-delay                      SRB-delay,
        -- TABULAR: TPC step size nested inside PowerControlAlgorithm
        powerControlAlgorithm          PowerControlAlgorithm
    },
    tdd                                SEQUENCE {
        -- The IE ul-TargetSIR corresponds to PRX-PDPCHdes for 1.28Mcps TDD
        -- Actual value PRX-PDPCHdes = (value of IE "ul-TargetSIR" - 120)
        ul-TargetSIR                   UL-TargetSIR                        OPTIONAL,
        ul-OL-PC-Signalling             CHOICE {
            broadcast-UL-OL-PC-info     NULL,
            individuallySignalled       SEQUENCE {
                tddOption               CHOICE {
                    tdd384              SEQUENCE {
                        individualTS-InterferenceList IndividualTS-InterferenceList,
                        dpch-ConstantValue ConstantValue
                    },
                    tdd128              SEQUENCE {
                        tpc-StepSize     TPC-StepSizeTDD
                    }
                }
            },
            primaryCCPCH-TX-Power       PrimaryCCPCH-TX-Power
        }
    }
}

```

```

    }
  }
}

UL-DPCH-PowerControlInfo-r5 ::= CHOICE {
  fdd SEQUENCE {
    dpcch-PowerOffset DPCCH-PowerOffset,
    pc-Preamble PC-Preamble,
    -- TABULAR: TPC step size nested inside PowerControlAlgorithm
    powerControlAlgorithm PowerControlAlgorithm,
    deltaACK DeltaACK OPTIONAL,
    deltaNACK DeltaNACK OPTIONAL,
    ack-NACK-repetition-factor ACK-NACK-repetitionFactor OPTIONAL
  },
  tdd SEQUENCE {
    -- The IE ul-TargetSIR corresponds to PRX-PDPCHdes for 1.28Mcps TDD
    -- Actual value PRX-PDPCHdes = (value of IE "ul-TargetSIR" - 120)
    ul-TargetSIR UL-TargetSIR OPTIONAL,
    ul-OL-PC-Signalling CHOICE {
      broadcast-UL-OL-PC-info NULL,
      individuallySignalled SEQUENCE {
        tddOption CHOICE {
          tdd384 SEQUENCE {
            individualTS-InterferenceList IndividualTS-InterferenceList,
            dpch-ConstantValue ConstantValue
          },
          tdd128 SEQUENCE {
            tpc-StepSize TPC-StepSizeTDD
          }
        }
      },
      primaryCCPCH-TX-Power PrimaryCCPCH-TX-Power
    }
  }
}

UL-DPCH-PowerControlInfoPostFDD ::= SEQUENCE {
  -- DPCCH-PowerOffset2 has a smaller range to save bits
  dpcch-PowerOffset2 DPCCH-PowerOffset2,
  pc-Preamble PC-Preamble,
  sRB-delay SRB-delay
}

UL-DPCH-PowerControlInfoPostTDD ::= SEQUENCE {
  ul-TargetSIR UL-TargetSIR,
  ul-TimeslotInterference TDD-UL-Interference
}

UL-DPCH-PowerControlInfoPostTDD-LCR-r4 ::= SEQUENCE {
  ul-TargetSIR UL-TargetSIR
}

UL-DPCH-PowerControlInfoPredef ::= CHOICE {
  fdd SEQUENCE {
    -- TABULAR: TPC step size nested inside PowerControlAlgorithm
    powerControlAlgorithm PowerControlAlgorithm
  },
  tdd SEQUENCE {
    -- dpch-ConstantValue shall be ignored if in 1.28Mcps TDD mode.
    dpch-ConstantValue ConstantValueTdd
  }
}

UL-Interference ::= INTEGER (-110..-70)

UL-ScramblingCode ::= INTEGER (0..16777215)

UL-SynchronisationParameters-r4 ::= SEQUENCE {
  stepSize INTEGER (1..8),
  frequency INTEGER (1..8)
}

```



```

}

-- Actual value UL-TargetSIR = (IE value * 0.5) - 11
UL-TargetSIR ::=
    INTEGER (0..62)

UL-TimingAdvance ::=
    INTEGER (0..63)

UL-TimingAdvanceControl ::=
    CHOICE {
        disabled
            NULL,
        enabled
            SEQUENCE {
                ul-TimingAdvance
                    UL-TimingAdvance
                    OPTIONAL,
                activationTime
                    ActivationTime
                    OPTIONAL
            }
    }

UL-TimingAdvanceControl-r4 ::=
    CHOICE {
        disabled
            NULL,
        enabled
            SEQUENCE {
                tddOption
                    CHOICE {
                        tdd384
                            SEQUENCE {
                                ul-TimingAdvance
                                    UL-TimingAdvance
                                    OPTIONAL,
                                activationTime
                                    ActivationTime
                                    OPTIONAL
                            },
                        tdd128
                            SEQUENCE {
                                ul-SynchronisationParameters
                                    UL-SynchronisationParameters-r4
                                    OPTIONAL,
                                synchronisationParameters
                                    SynchronisationParameters-r4
                                    OPTIONAL
                            }
                    }
            }
    }

UL-TimingAdvanceControl-LCR-r4 ::= CHOICE {
    disabled
        NULL,
    enabled
        SEQUENCE {
            ul-SynchronisationParameters
                UL-SynchronisationParameters-r4
                OPTIONAL,
            synchronisationParameters
                SynchronisationParameters-r4
                OPTIONAL
        }
}

UL-TS-ChannelisationCode ::=
    ENUMERATED {
        cc1-1, cc2-1, cc2-2,
        cc4-1, cc4-2, cc4-3, cc4-4,
        cc8-1, cc8-2, cc8-3, cc8-4,
        cc8-5, cc8-6, cc8-7, cc8-8,
        cc16-1, cc16-2, cc16-3, cc16-4,
        cc16-5, cc16-6, cc16-7, cc16-8,
        cc16-9, cc16-10, cc16-11, cc16-12,
        cc16-13, cc16-14, cc16-15, cc16-16 }

UL-TS-ChannelisationCodeList ::=
    SEQUENCE (SIZE (1..2)) OF
        UL-TS-ChannelisationCode

UplinkAdditionalTimeslots ::=
    SEQUENCE {
        parameters
            CHOICE {
                sameAsLast
                    SEQUENCE {
                        timeslotNumber
                            TimeslotNumber
                    },
                newParameters
                    SEQUENCE {
                        individualTimeslotInfo
                            IndividualTimeslotInfo,
                        ul-TS-ChannelisationCodeList
                            UL-TS-ChannelisationCodeList
                    }
            }
    }

UplinkAdditionalTimeslots-LCR-r4 ::=
    SEQUENCE {
        parameters
            CHOICE {
                sameAsLast
                    SEQUENCE {
                        timeslotNumber
                            TimeslotNumber
                    },
                newParameters
                    SEQUENCE {
                        individualTimeslotInfo
                            IndividualTimeslotInfo-LCR-r4,
                    }
            }
    }

```

```

        ul-TS-ChannelisationCodeList          UL-TS-ChannelisationCodeList
    }
}

UplinkTimeslotsCodes ::=          SEQUENCE {
    dynamicSFusage                  BOOLEAN,
    firstIndividualTimeslotInfo     IndividualTimeslotInfo,
    ul-TS-ChannelisationCodeList    UL-TS-ChannelisationCodeList,
    moreTimeslots                   CHOICE {
        noMore                      NULL,
        additionalTimeslots         CHOICE {
            consecutive              SEQUENCE {
                numAdditionalTimeslots  INTEGER (1..maxTS-1)
            },
            timeslotList              SEQUENCE (SIZE (1..maxTS-1)) OF
                UplinkAdditionalTimeslots
        }
    }
}

UplinkTimeslotsCodes-LCR-r4 ::=    SEQUENCE {
    dynamicSFusage                  BOOLEAN,
    firstIndividualTimeslotInfo     IndividualTimeslotInfo-LCR-r4,
    ul-TS-ChannelisationCodeList    UL-TS-ChannelisationCodeList,
    moreTimeslots                   CHOICE {
        noMore                      NULL,
        additionalTimeslots         CHOICE {
            consecutive              SEQUENCE {
                numAdditionalTimeslots  INTEGER (1..maxTS-LCR-1)
            },
            timeslotList              SEQUENCE (SIZE (1..maxTS-LCR-1)) OF
                UplinkAdditionalTimeslots-LCR-r4
        }
    }
}

Wi-LCR ::=                          INTEGER(1..4)

```

CHANGE REQUEST

⌘ **25.331 CR 1898** ⌘ rev **-** ⌘ Current version: **4.8.0** ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

Proposed change affects: UICC apps ME Radio Access Network Core Network

Title:	⌘ Removal of MRRU parameter in PDCP info		
Source:	⌘ TSG-RAN WG2		
Work item code:	⌘ TEI4	Date:	⌘ February 2003
Category:	⌘ F	Release:	⌘ Rel-4
	Use <u>one</u> of the following categories:		Use <u>one</u> of the following releases:
	F (correction)	2 (GSM Phase 2)	
	A (corresponds to a correction in an earlier release)	R96 (Release 1996)	
	B (addition of feature),	R97 (Release 1997)	
	C (functional modification of feature)	R98 (Release 1998)	
	D (editorial modification)	R99 (Release 1999)	
	Detailed explanations of the above categories can be found in 3GPP TR 21.900 .		Rel-4 (Release 4)
			Rel-5 (Release 5)
			Rel-6 (Release 6)

Reason for change:	⌘ During meeting #34, it was agreed that ROHC segmentation should not be used. Thus, the segmentation related parameter MRRU (Maximum Reconstructed Reception Unit) should be removed from the IE "PDCP info". The IE "Reverse-Decompression_Depth" should be in the loop of "Downlink", since this parameter is used for UE decompressor.
Summary of change:	⌘ MRRU is removed from the IE "PDCP info". The IE "Reverse-Decompression_Depth" is put into the loop of "Downlink".
Consequences if not approved:	⌘ Useless parameter is signalled through air interface. UE decompressor will operate unpredictably.

Clauses affected:	⌘ 10.3.4.2, 11.3						
Other specs Affected:	<table border="1" style="display: inline-table; border-collapse: collapse;"> <tr> <td style="padding: 2px;">Y</td> <td style="padding: 2px;">N</td> </tr> <tr> <td style="padding: 2px;"><input type="checkbox"/></td> <td style="padding: 2px;"><input checked="" type="checkbox"/></td> </tr> </table>	Y	N	<input type="checkbox"/>	<input checked="" type="checkbox"/>	Other core specifications	⌘
Y	N						
<input type="checkbox"/>	<input checked="" type="checkbox"/>						
	<input checked="" type="checkbox"/>	Test specifications					
	<input checked="" type="checkbox"/>	O&M Specifications					
Other comments:	⌘						

How to create CRs using this form:

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>. Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

10.3.3.24 PDCP capability

Indicates which algorithms and which value range of their parameters are supported by the UE.

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
Support for lossless SRNS relocation	MP		Boolean	TRUE means supported	
Support for RFC2507	MP		Boolean	TRUE means supported	
>Max HC context space			Integer(512, 1024, 2048, 4096, 8192)		
Support for RFC 3095	MP		Boolean	TRUE means supported	REL-4
>Maximum number of ROHC context sessions	MD		Integer(2, 4, 8, 12, 16, 24, 32, 48, 64, 128, 256, 512, 1024, 16384)	Default value is 16.	REL-4
>Reverse decompression depth	MD		Integer (0..65535)	Default value is 0 (reverse decompression is not supported).	REL-4

10.3.4.2 PDCP info

The purpose of the PDCP info IE is to indicate which algorithms shall be established and to configure the parameters of each of the algorithms.

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
Support for lossless SRNS relocation	CV- <i>LosslessCriteria</i>		Boolean	TRUE means support	
Max PDCP SN window size	CV- <i>Lossless</i>		Enumerated(sn255, sn65535)	Maximum PDCP sequence number window size. The handling of sequence number when the Max PDCP SN window size is 255 is specified in [23].	
PDCP PDU header	MD		Enumerated (present, absent)	Whether a PDCP PDU header is 7existent or not. Default value is "present"	
Header compression information	OP	1 to <maxPDCPAlgoType >			
>CHOICE <i>algorithm type</i>	MP				
>>RFC 2507				Header compression according to IETF standard RFC 2507	
>>>F_MAX_PERIOD	MD		Integer (1..65535)	Largest number of compressed non-TCP headers that may be sent	

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
				without sending a full header. Default value is 256.	
>>>F_MAX_TIME	MD		Integer (1..255)	Compressed headers may not be sent more than F_MAX_TIME seconds after sending last full header. Default value is 5.	
>>>MAX_HEADER	MD		Integer (60..65535)	The largest header size in octets that may be compressed. Default value is 168.	
>>>TCP_SPACE	MD		Integer (3..255)	Maximum CID value for TCP connections. Default value is 15.	
>>>NON_TCP_SPACE	MD		Integer (3..65535)	Maximum CID value for non-TCP connections. Default value is 15.	
>>>EXPECT_REORDERING	MD		Enumerated (reordering not expected, reordering expected)	Whether the algorithm shall reorder PDCP SDUs or not. Default value is "reordering not expected".	
>>RFC 3095				Header compression according to IETF standard RFC 3095	REL-4
>>>Uplink	OP			Indicates the necessary information elements for Uplink.	REL-4
>>>>CID inclusion info	MP		Enumerated (PDCP header, RFC3095 packet format)	Configures which method shall be used to carry RFC3095 CID values.	REL-4
>>>>Max_CID	MD		Integer (1..16383)	Highest context ID number to be used by the UE compressor. Default value is 15.	REL-4
>>>>Profiles	MP	1 to <maxROHC-Profiles>		Profiles supported by the UTRAN decompressor.	REL-4
>>>>>Profile instance	MP		Integer(1 .. 3)	Supported profile types. At least four spare values.	REL-4
>>>>>MRRU	MD		Integer (0..65535)	Maximum reconstructed reception unit.	REL-4

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
				Default value is 0 (no segmentation).	
>>>>Packet_Sizes_Allowed	OP	1 to <maxROHC- PacketSize s>		List of packet sizes that are allowed to be produced by the UE compressor.	REL-4
>>>>Packet size	MP		Integer (2 .. 1500)	Packet size as defined in RFC 3095.	REL-4
>>>Downlink	OP			Indicates the necessary information elements for Downlink.	REL-4
>>>>CID inclusion info	MP		Enumerated (PDCP header, RFC3095 packet format)	Configures which method shall be used to carry RFC3095 CID values.	REL-4
>>>>Max_CID	MD		Integer (1.. 16383)	Highest context ID number to be used by the UE decompressor. Default value is 15.	REL-4
>>>>Reverse-Decompression_Depth	MD		Integer (0..65535)	Determines whether reverse decompression should be used or not and the maximum number of packets that can be reverse decompressed by the UE decompressor. Default value is 0 (reverse decompression shall not be used).	REL-4

Condition	Explanation
<i>LosslessCriteria</i>	This IE is mandatory present if the IE "RLC mode" is "Acknowledged", the IE "In-sequence delivery" is "True" and the IE "SDU Discard Mode" is "No discard" and not needed otherwise.
<i>Lossless</i>	This IE is mandatory present if the IE "Support for lossless SRNS relocation" is TRUE, otherwise it is not needed.

11.3 Information element definitions

```

-- *****
--
--     USER EQUIPMENT INFORMATION ELEMENTS (10.3.3)
--
-- *****
-----//-----

PDCP-Capability ::=
    losslessSRNS-RelocationSupport    SEQUENCE {
    supportForRfc2507                   CHOICE {
        notSupported                    NULL,
        supported                        MaxHcContextSpace
    }
}

PDCP-Capability-r4-ext ::=
    supportForRfc3095                   CHOICE {
        notSupported                    NULL,
        supported                        SEQUENCE {
            maxROHC-ContextSessions     MaxROHC-ContextSessions-r4  DEFAULT s16,
            reverseCompressionDepth     INTEGER (0..65535)           DEFAULT 0
        }
    }
}

PhysicalChannelCapability ::=
    fddPhysChCapability                 SEQUENCE {
        downlinkPhysChCapability        DL-PhysChCapabilityFDD,
        uplinkPhysChCapability          UL-PhysChCapabilityFDD
    }
    -- tddPhysChCapability describes the 3.84Mcps TDD physical channel capability
    tddPhysChCapability                 SEQUENCE {
        downlinkPhysChCapability        DL-PhysChCapabilityTDD,
        uplinkPhysChCapability          UL-PhysChCapabilityTDD
    }
    OPTIONAL
}
-----//-----

RLC-Capability ::=
    totalRLC-AM-BufferSize              SEQUENCE {
    maximumRLC-WindowSize               TotalRLC-AM-BufferSize,
    maximumAM-EntityNumber              MaximumRLC-WindowSize,
                                        MaximumAM-EntityNumberRLC-Cap
}

RRC-MessageSequenceNumber ::=
    INTEGER (0..15)

RRC-MessageSequenceNumberList ::=
    SEQUENCE (SIZE (4..5)) OF
        RRC-MessageSequenceNumber

RRC-StateIndicator ::=
    ENUMERATED {
        cell-DCH, cell-FACH, cell-PCH, ura-PCH }
-----//-----

-- *****
--
--     RADIO BEARER INFORMATION ELEMENTS (10.3.4)
--
-- *****
-----//-----

DL-CounterSynchronisationInfo ::=
    rB-WithPDCP-InfoList               SEQUENCE {
                                        RB-WithPDCP-InfoList  OPTIONAL
}

```



```

}
DL-LogicalChannelMapping ::= SEQUENCE {
    -- TABULAR: DL-TransportChannelType contains TransportChannelIdentity as well.
    dl-TransportChannelType DL-TransportChannelType,
    logicalChannelIdentity LogicalChannelIdentity OPTIONAL
}
DL-LogicalChannelMappingList ::= SEQUENCE (SIZE (1..maxLoCHperRLC)) OF
    DL-LogicalChannelMapping
DL-RFC3095-r4 ::= SEQUENCE {
    cid-InclusionInfo CID-InclusionInfo-r4,
    max-CID INTEGER (1..16383) DEFAULT 15,
    reverseDecompressionDepth INTEGER (0..65535) DEFAULT 0
}
DL-RLC-Mode ::= CHOICE {
    dl-AM-RLC-Mode DL-AM-RLC-Mode,
    dl-UM-RLC-Mode NULL,
    dl-TM-RLC-Mode DL-TM-RLC-Mode
}
DL-RLC-StatusInfo ::= SEQUENCE {
    timerStatusProhibit TimerStatusProhibit OPTIONAL,
    timerEPC TimerEPC OPTIONAL,
    missingPDU-Indicator BOOLEAN,
    timerStatusPeriodic TimerStatusPeriodic OPTIONAL
}
DL-TM-RLC-Mode ::= SEQUENCE {
    segmentationIndication BOOLEAN
}
-----//-----
RFC2507-Info ::= SEQUENCE {
    f-MAX-PERIOD INTEGER (1..65535) DEFAULT 256,
    f-MAX-TIME INTEGER (1..255) DEFAULT 5,
    max-HEADER INTEGER (60..65535) DEFAULT 168,
    tcp-SPACE INTEGER (3..255) DEFAULT 15,
    non-TCP-SPACE INTEGER (3..65535) DEFAULT 15,
    -- TABULAR: expectReordering has only two possible values, so using Optional or Default
    -- would be wasteful
    expectReordering ExpectReordering
}
RFC3095-Info-r4 ::= SEQUENCE {
    ul-RFC3095 UL-RFC3095-r4 OPTIONAL,
    dl-RFC3095 DL-RFC3095-r4 OPTIONAL
}
RLC-Info ::= SEQUENCE {
    ul-RLC-Mode UL-RLC-Mode OPTIONAL,
    dl-RLC-Mode DL-RLC-Mode OPTIONAL
}
RLC-InfoChoice ::= CHOICE {
    rlc-Info RLC-Info,
    same-as-RB RB-Identity
}
-----//-----
UL-LogicalChannelMappingList ::= SEQUENCE {
    -- rlc-LogicalChannelMappingIndicator shall be set to TRUE in this version
    -- of the specification
    rlc-LogicalChannelMappingIndicator BOOLEAN,
    ul-LogicalChannelMapping SEQUENCE (SIZE (maxLoCHperRLC)) OF
        UL-LogicalChannelMapping
}
UL-LogicalChannelMappings ::= CHOICE {
    oneLogicalChannel UL-LogicalChannelMapping,
    twoLogicalChannels UL-LogicalChannelMappingList
}

```

```

UL-RFC3095-r4 ::=
  cid-InclusionInfo          SEQUENCE {
  max-CID                   CID-InclusionInfo-r4,
  rohcProfileList           INTEGER (1..16383)           DEFAULT 15,
  mrru                  ROHC-ProfileList-r4,
  rohcPacketSizeList       INTEGER (0..65535)       DEFAULT 0,
                           ROHC-PacketSizeList-r4
  }

UL-RLC-Mode ::=
  ul-AM-RLC-Mode           CHOICE {
  ul-UM-RLC-Mode           UL-AM-RLC-Mode,
  ul-TM-RLC-Mode           UL-UM-RLC-Mode,
  spare                    UL-TM-RLC-Mode,
                           NULL
  }

UL-TM-RLC-Mode ::=
  transmissionRLC-Discard  SEQUENCE {
  segmentationIndication  TransmissionRLC-Discard   OPTIONAL,
                           BOOLEAN
  }

```

-----//-----

CHANGE REQUEST

⌘ **25.331 CR 1899** ⌘ rev **-** ⌘ Current version: **5.3.0** ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

Proposed change affects: UICC apps ME Radio Access Network Core Network

Title:	⌘ Removal of MRRU parameter in PDCP info		
Source:	⌘ TSG-RAN WG2		
Work item code:	⌘ TEI4	Date:	⌘ February 2003
Category:	⌘ A	Release:	⌘ Rel-5
	Use <u>one</u> of the following categories:		Use <u>one</u> of the following releases:
	F (correction)	2	(GSM Phase 2)
	A (corresponds to a correction in an earlier release)	R96	(Release 1996)
	B (addition of feature),	R97	(Release 1997)
	C (functional modification of feature)	R98	(Release 1998)
	D (editorial modification)	R99	(Release 1999)
	Detailed explanations of the above categories can be found in 3GPP TR 21.900 .	Rel-4	(Release 4)
		Rel-5	(Release 5)
		Rel-6	(Release 6)

Reason for change:	⌘ During meeting #34, it was agreed that ROHC segmentation should not be used. Thus, the segmentation related parameter MRRU (Maximum Reconstructed Reception Unit) should be removed from the IE "PDCP info". The IE "Reverse-Decompression_Depth" should be in the loop of "Downlink", since this parameter is used for UE decompressor.
Summary of change:	⌘ MRRU is removed from the IE "PDCP info". The IE "Reverse-Decompression_Depth" is put into the loop of "Downlink".
Consequences if not approved:	⌘ Useless parameter is signalled through air interface. UE decompressor will operate unpredictably.

Clauses affected:	⌘ 10.3.4.2, 11.3						
Other specs Affected:	<table border="1" style="display: inline-table; border-collapse: collapse;"> <tr> <td style="width: 20px; text-align: center;">Y</td> <td style="width: 20px; text-align: center;">N</td> </tr> <tr> <td style="text-align: center;"><input type="checkbox"/></td> <td style="text-align: center;"><input checked="" type="checkbox"/></td> </tr> </table>	Y	N	<input type="checkbox"/>	<input checked="" type="checkbox"/>	Other core specifications	⌘
Y	N						
<input type="checkbox"/>	<input checked="" type="checkbox"/>						
	<input checked="" type="checkbox"/>	Test specifications					
	<input checked="" type="checkbox"/>	O&M Specifications					
Other comments:	⌘						

How to create CRs using this form:

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>. Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ☞ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

10.3.3.24 PDCP capability

Indicates which algorithms and which value range of their parameters are supported by the UE.

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
Support for lossless SRNS relocation	MP		Boolean	TRUE means supported	
Support for RFC2507	MP		Boolean	TRUE means supported	
>Max HC context space			Integer(512, 1024, 2048, 4096, 8192)		
Support for RFC 3095	MP		Boolean	TRUE means supported	REL-4
>Maximum number of ROHC context sessions	MD		Integer(2, 4, 8, 12, 16, 24, 32, 48, 64, 128, 256, 512, 1024, 16384)	Default value is 16.	REL-4
>Reverse decompression depth	MD		Integer (0..65535)	Default value is 0 (reverse decompression is not supported).	REL-4
>Support for RFC 3095 context relocation	MP		Boolean	TRUE means supported	REL-5

10.3.4.2 PDCP info

The purpose of the PDCP info IE is to indicate which algorithms shall be established and to configure the parameters of each of the algorithms.

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
Support for lossless SRNS relocation	CV- <i>LosslessCriteria</i>		Boolean	TRUE means support	
Max PDCP SN window size	CV- <i>Lossless</i>		Enumerated(sn255, sn65535)	Maximum PDCP sequence number window size. The handling of sequence number when the Max PDCP SN window size is 255 is specified in [23].	
PDCP PDU header	MD		Enumerated (present, absent)	Whether a PDCP PDU header is 7existent or not. Default value is "present"	
Header compression information	OP	1 to <maxPDCPAlgoType >			
>CHOICE <i>algorithm type</i>	MP				
>>RFC 2507				Header compression according to IETF standard RFC 2507	
>>>F_MAX_PERIOD	MD		Integer (1..65535)	Largest number of compressed non-	

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
				TCP headers that may be sent without sending a full header. Default value is 256.	
>>>F_MAX_TIME	MD		Integer (1..255)	Compressed headers may not be sent more than F_MAX_TIME seconds after sending last full header. Default value is 5.	
>>>MAX_HEADER	MD		Integer (60..65535)	The largest header size in octets that may be compressed. Default value is 168.	
>>>TCP_SPACE	MD		Integer (3..255)	Maximum CID value for TCP connections. Default value is 15.	
>>>NON_TCP_SPACE	MD		Integer (3..65535)	Maximum CID value for non-TCP connections. Default value is 15.	
>>>EXPECT_REORDERING	MD		Enumerated (reordering not expected, reordering expected)	Whether the algorithm shall reorder PDCP SDUs or not. Default value is "reordering not expected".	
>>RFC 3095				Header compression according to IETF standard RFC 3095	REL-4
>>>Uplink	OP			Indicates the necessary information elements for Uplink.	REL-4
>>>>CID inclusion info	MP		Enumerated (PDCP header, RFC3095 packet format)	Configures which method shall be used to carry RFC3095 CID values.	REL-4
>>>>Max_CID	MD		Integer (1..16383)	Highest context ID number to be used by the UE compressor. Default value is 15.	REL-4
>>>>Profiles	MP	1 to <maxROH C-Profiles>		Profiles supported by the UTRAN decompressor.	REL-4
>>>>>Profile instance	MP		Integer(1 .. 3)	Supported profile types. At least four spare values.	REL-4
>>>>>MRRU	MD		Integer (0..	Maximum	REL-4

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
			65535)	reconstructed reception unit. Default value is 0 (no segmentation).	
>>>>Packet_Sizes_Allowed	OP	1 to <maxROHC-PacketSizes>		List of packet sizes that are allowed to be produced by the UE compressor.	REL-4
>>>>>Packet size	MP		Integer (2 .. 1500)	Packet size as defined in RFC 3095.	REL-4
>>>>Downlink	OP			Indicates the necessary information elements for Downlink.	REL-4
>>>>>CID inclusion info	MP		Enumerated (PDCP header, RFC3095 packet format)	Configures which method shall be used to carry RFC3095 CID values.	REL-4
>>>>>Max_CID	MD		Integer (1.. 16383)	Highest context ID number to be used by the UE decompressor. Default value is 15.	REL-4
>>>>>Reverse-Decompression_Depth	MD		Integer (0..65535)	Determines whether reverse decompression should be used or not and the maximum number of packets that can be reverse decompressed by the UE decompressor. Default value is 0 (reverse decompression shall not be used).	REL-4

Condition	Explanation
<i>LosslessCriteria</i>	This IE is mandatory present if the IE "RLC mode" is "Acknowledged", the IE "In-sequence delivery" is "True" and the IE "SDU Discard Mode" is "No discard" and not needed otherwise.
<i>Lossless</i>	This IE is mandatory present if the IE "Support for lossless SRNS relocation" Is TRUE, otherwise it is not needed.

11.3 Information element definitions

```

-- *****
--
--     USER EQUIPMENT INFORMATION ELEMENTS (10.3.3)
--
-- *****
-----//-----

PDCP-Capability ::=
    losslessSRNS-RelocationSupport    SEQUENCE {
    supportForRfc2507                   CHOICE {
        notSupported                     NULL,
        supported                         MaxHcContextSpace
    }
}

PDCP-Capability-r4-ext ::=
    supportForRfc3095                   CHOICE {
        notSupported                     NULL,
        supported                         SEQUENCE {
            maxROHC-ContextSessions      MaxROHC-ContextSessions-r4  DEFAULT s16,
            reverseCompressionDepth      INTEGER (0..65535)           DEFAULT 0
        }
    }
}

PDCP-Capability-r5-ext ::=
    supportForRfc3095ContextRelocation  BOOLEAN
}

PhysicalChannelCapability ::=
    fddPhysChCapability                 SEQUENCE {
        downlinkPhysChCapability         DL-PhysChCapabilityFDD,
        uplinkPhysChCapability           UL-PhysChCapabilityFDD
    }
    -- tddPhysChCapability describes the 3.84Mcps TDD physical channel capability
    tddPhysChCapability                 SEQUENCE {
        downlinkPhysChCapability         DL-PhysChCapabilityTDD,
        uplinkPhysChCapability           UL-PhysChCapabilityTDD
    }
    OPTIONAL
}
-----//-----

RLC-Capability ::=
    totalRLC-AM-BufferSize              TotalRLC-AM-BufferSize,
    maximumRLC-WindowSize               MaximumRLC-WindowSize,
    maximumAM-EntityNumber              MaximumAM-EntityNumberRLC-Cap
}

RRC-MessageSequenceNumber ::=
    INTEGER (0..15)

RRC-MessageSequenceNumberList ::=
    SEQUENCE (SIZE (4..5)) OF
        RRC-MessageSequenceNumber

RRC-StateIndicator ::=
    ENUMERATED {
        cell-DCH, cell-FACH, cell-PCH, ura-PCH }
-----//-----

-- *****
--
--     RADIO BEARER INFORMATION ELEMENTS (10.3.4)
--
-- *****

```



```

-----//-----
DL-CounterSynchronisationInfo ::= SEQUENCE {
    rB-WithPDCP-InfoList          RB-WithPDCP-InfoList    OPTIONAL
}

DL-LogicalChannelMapping ::= SEQUENCE {
    -- TABULAR: DL-TransportChannelType contains TransportChannelIdentity as well.
    dl-TransportChannelType        DL-TransportChannelType,
    logicalChannelIdentity          LogicalChannelIdentity    OPTIONAL
}

DL-LogicalChannelMappingList ::= SEQUENCE (SIZE (1..maxLoCHperRLC)) OF
    DL-LogicalChannelMapping

DL-RFC3095-r4 ::= SEQUENCE {
    cid-InclusionInfo              CID-InclusionInfo-r4,
    max-CID                       INTEGER (1..16383)           DEFAULT 15,
    reverseDecompressionDepth      INTEGER (0..65535)         DEFAULT 0
}

DL-RLC-Mode ::= CHOICE {
    dl-AM-RLC-Mode                DL-AM-RLC-Mode,
    dl-UM-RLC-Mode                NULL,
    dl-TM-RLC-Mode                DL-TM-RLC-Mode
}

DL-RLC-StatusInfo ::= SEQUENCE {
    timerStatusProhibit           TimerStatusProhibit    OPTIONAL,
    timerEPC                      TimerEPC                OPTIONAL,
    missingPDU-Indicator          BOOLEAN,
    timerStatusPeriodic          TimerStatusPeriodic    OPTIONAL
}

DL-TM-RLC-Mode ::= SEQUENCE {
    segmentationIndication        BOOLEAN
}

-----//-----

RFC2507-Info ::= SEQUENCE {
    f-MAX-PERIOD                  INTEGER (1..65535)         DEFAULT 256,
    f-MAX-TIME                    INTEGER (1..255)             DEFAULT 5,
    max-HEADER                    INTEGER (60..65535)          DEFAULT 168,
    tcp-SPACE                     INTEGER (3..255)             DEFAULT 15,
    non-TCP-SPACE                 INTEGER (3..65535)           DEFAULT 15,
    -- TABULAR: expectReordering has only two possible values, so using Optional or Default
    -- would be wasteful
    expectReordering              ExpectReordering
}

RFC3095-Info-r4 ::= SEQUENCE {
    ul-RFC3095                    UL-RFC3095-r4              OPTIONAL,
    dl-RFC3095                    DL-RFC3095-r4              OPTIONAL
}

RLC-Info ::= SEQUENCE {
    ul-RLC-Mode                  UL-RLC-Mode              OPTIONAL,
    dl-RLC-Mode                  DL-RLC-Mode              OPTIONAL
}

RLC-InfoChoice ::= CHOICE {
    rlc-Info                      RLC-Info,
    same-as-RB                    RB-Identity
}

-----//-----

UL-LogicalChannelMappingList ::= SEQUENCE {
    -- rlc-LogicalChannelMappingIndicator shall be set to TRUE in this version
    -- of the specification
    rlc-LogicalChannelMappingIndicator    BOOLEAN,
    ul-LogicalChannelMapping              SEQUENCE (SIZE (maxLoCHperRLC)) OF
        UL-LogicalChannelMapping
}

```

```

UL-LogicalChannelMappings ::= CHOICE {
    oneLogicalChannel
    twoLogicalChannels
}

UL-RFC3095-r4 ::= SEQUENCE {
    cid-InclusionInfo
    max-CID INTEGER (1..16383) DEFAULT 15,
    rohcProfileList
    mrpu INTEGER (0..65535) DEFAULT 0,
    rohcPacketSizeList ROHC-PacketSizeList-r4
}

UL-RLC-Mode ::= CHOICE {
    ul-AM-RLC-Mode
    ul-UM-RLC-Mode
    ul-TM-RLC-Mode
    spare
    NULL
}

UL-TM-RLC-Mode ::= SEQUENCE {
    transmissionRLC-Discard
    segmentationIndication
    TransmissionRLC-Discard OPTIONAL,
    BOOLEAN
}

```

-----//-----