

**Agenda Item:** 4  
**Source:** Alcatel  
**Title:** CR 25.214-110r1: power setting in compressed and recovery frames for downlink compressed mode  
**Document for:** Decision

---

## Introduction

During the joint 3GPP R1-R3 ad-hoc meeting that took place April 11<sup>th</sup>, it was agreed that downlink inner-loop power control would be fully specified, including the downlink inner-loop power control in compressed mode. This is now reflected in TS 25.214 [1].

However, in compressed mode, the change of the downlink transmit power during the compressed and recovery frames (due to the increased bit rate) is currently not yet specified.

Therefore, in this contribution, we propose to complete the current description of downlink power control in compressed mode, see attached CR.

The proposed solution is simple and does not require any additional signalling. It consists in having a transmit power change in compressed and recovery frames equal to the target SIR variation in these frames. In downlink, the target SIR variation during compressed and recovery frames is currently specified in TS 25.331 [2]. This SIR variation is the sum of two terms:

- The first term ( $\Delta\text{SIR}_{\text{compression}}$ ) enables to compensate for the bit rate increase during compressed frames and is equal to 0 dB in recovery frames,
- The second term ( $\Delta\text{SIR}_{\text{coding}}$ ) enables to compensate for the performance degradation due to the power control interruption during the transmission gap or excessive puncturing (in case of compressed mode by puncturing). This term is determined in the UE thanks to signaling from the UTRAN to the UE, see TS 25.331 [2] (parameters DeltaSIR1, DeltaSIR2, DeltaSIRafter1 and DeltaSIRafter2).

In the Node B, the first term can be computed the same way as in the UE, but for the second term, the parameters DeltaSIR1, DeltaSIR2, DeltaSIRafter1 and DeltaSIRafter2 are not known for the downlink power control, but only for the uplink [3, 4]. However, these parameters mainly depend on the environment and UE speed and therefore will have the same order of magnitude for both links. Therefore, we propose to use the uplink values of these parameters (known in the Node B) in order to derive the downlink transmit power changes during the compressed and recovery frames.

Thus, the proposed solution simply consists in increasing the DPDCH and DPCCH powers in the same proportion as the downlink target SIR (the power offsets PO1, PO2 and PO3 being unchanged).

## References

- [1] 3GPP TS 25.214 version 3.3.0, “Physical layer procedures”, June 2000
- [2] 3GPP TS 25.331 version 3.4.0, “RRC protocol specifications”, June 2000
- [3] 3GPP TS 25.433 version 3.2.0, “UTRAN Iub Interface NBAP Signalling”, June 2000
- [4] 3GPP R3-00-1975, “CR 25.433-195r1: compressed mode”, Nokia, June 2000

<h2 style="margin: 0;">CHANGE REQUEST</h2>		Please see embedded help file at the bottom of this page for instructions on how to fill in this form correctly.
<b>25.214</b>	<b>CR</b>	<b>110r1</b>
GSM (AA.BB) or 3G (AA.BBB) specification number ↑		↑ CR number as allocated by MCC support team
For submission to: <b>TSG-RAN #9</b> <small>List expected approval meeting # here ↑</small>	for approval <input checked="" type="checkbox"/> for information <input type="checkbox"/>	Current Version: <b>3.3.0</b>  strategic <input type="checkbox"/> non-strategic <input type="checkbox"/> <small>(for SMG use only)</small>

Form: CR cover sheet, version 2 for 3GPP and SMG The latest version of this form is available from: ftp://ftp.3gpp.org/Information/CR-Form-v2.doc

**Proposed change affects:** (U)SIM  ME  UTRAN / Radio  Core Network   
(at least one should be marked with an X)

**Source:** Alcatel **Date:** 2000-08-14

**Subject:** Downlink inner-loop power control in compressed mode

**Work item:** Inner-loop power control

<b>Category:</b>	F Correction <input type="checkbox"/> A Corresponds to a correction in an earlier release <input type="checkbox"/> B Addition of feature <input type="checkbox"/> C Functional modification of feature <input checked="" type="checkbox"/> D Editorial modification <input type="checkbox"/>	<b>Release:</b>	Phase 2 <input type="checkbox"/> Release 96 <input type="checkbox"/> Release 97 <input type="checkbox"/> Release 98 <input type="checkbox"/> Release 99 <input checked="" type="checkbox"/> Release 00 <input type="checkbox"/>
------------------	--	-----------------	--

(only one category Shall be marked With an X)

**Reason for change:** In downlink compressed mode, the change of transmit power during the compressed frames was not specified so far.

**Clauses affected:** 5.2.1.3

<b>Other specs affected:</b>	Other 3G core specifications <input type="checkbox"/> Other GSM core specifications <input type="checkbox"/> MS test specifications <input type="checkbox"/> BSS test specifications <input type="checkbox"/> O&M specifications <input type="checkbox"/>	→ List of CRs: → List of CRs: → List of CRs: → List of CRs: → List of CRs:	
------------------------------	---	--	--

**Other comments:**



<----- double-click here for help and instructions on how to create a CR

### 5.2.1.3 Power control in compressed mode

The aim of downlink power control in uplink or/and downlink compressed mode is to recover as fast as possible a signal-to-interference ratio (SIR) close to the target SIR after each transmission gap.

The UE behaviour is the same in compressed mode as in normal mode, described in subclause 5.2.1.2.

In compressed mode, compressed frames may occur in either the uplink or the downlink or both. In compressed frames, the transmission of downlink DPDCH(s) and DPCCH shall be stopped during transmission gaps.

The power of the DPCCH in the first slot after the transmission gap should be set to the same value as in the slot just before the transmission gap.

~~During RPL slots after each transmission gap, ordinary transmit power control algorithm is applied with a step size  $\Delta_{RP\_TPC}$  instead of  $\Delta_{TPC}$ , where:~~

~~—  $\Delta_{RP\_TPC}$  is called the recovery power control step size and is expressed in dB.  $\Delta_{RP\_TPC}$  is equal to the minimum value of 3 dB and  $2\Delta_{TPC}$ .~~

~~— RPL is called recovery period length and is equal to the minimum value out of the transmission gap length and 7 slots.~~

~~After the recovery period, ordinary transmit power control resumes with step size  $\Delta_{TPC}$ .~~

~~Due to transmission gaps in compressed frames, there may be missing TPC commands in the uplink. If no uplink TPC command is transmitted, the corresponding TPC cmd derived by the Node B shall be set to zero.~~

~~In every slot during compressed mode, the DPCH transmit power shall be adjusted by  $(TPC\_cmd \times \Delta_{STEP} + \Delta P)$  dB where  $\Delta_{STEP}$  is the power control step size and  $\Delta P$  is the power change that is applied when the downlink target SIR is modified.~~

~~The power control step size  $\Delta_{STEP} = \Delta_{RP\_TPC}$  during RPL slots after each transmission gap and  $\Delta_{STEP} = \Delta_{TPC}$  otherwise, where:~~

~~— RPL is the recovery period length and is expressed as a number of slots. RPL is equal to the minimum value out of the transmission gap length and 7 slots. If a transmission gap is scheduled to start before RPL slots have elapsed, then the recovery period shall end at the start of the gap, and the value of RPL shall be reduced accordingly.~~

~~—  $\Delta_{RP\_TPC}$  is called the recovery power control step size and is expressed in dB.  $\Delta_{RP\_TPC}$  is equal to the minimum value of 3 dB and  $2\Delta_{TPC}$ .~~

~~The power offset  $\Delta P = \delta P_{curr} - \delta P_{prev}$ , where  $\delta P_{curr}$  and  $\delta P_{prev}$  are respectively the value of  $\delta P$  in the current slot and the most recently transmitted slot and  $\delta P$  is computed as follows:~~

$$\delta P = \max(\Delta SIR1\_compression, \dots, \Delta SIRn\_compression) + \Delta SIR\_coding$$

~~where n is the number of different TTI lengths amongst TTIs of all TrChs of the CCTrCh, where  $\Delta SIR\_coding$  fulfills:~~

~~—  $\Delta SIR\_coding = \Delta SIR1$  if the start of the first transmission gap in the transmission gap pattern is within the current frame.~~

~~—  $\Delta SIR\_coding = \Delta SIRafter1$  if the current frame just follows a frame containing the start of the first transmission gap in the transmission gap pattern.~~

~~—  $\Delta SIR\_coding = \Delta SIR2$  if the start of the second transmission gap in the transmission gap pattern is within the current frame.~~

~~—  $\Delta SIR\_coding = \Delta SIRafter2$  if the current frame just follows a frame containing the start of the second transmission gap in the transmission gap pattern.~~

~~and  $\Delta SIRi\_compression$  is defined by :~~

~~—  $\Delta SIRi\_compression = 3$  dB for frames compressed by reducing the spreading factor by 2.~~

- $\Delta\text{SIR}_i \text{ compression} = 10 \log (15 \cdot F_i / (15 \cdot F_i - \text{TGL}_i))$  if there is a transmission gap created by puncturing method within the current TTI of length  $F_i$  frames, where  $\text{TGL}_i$  is the gap length in number of slots (either from one gap or a sum of gaps) in the current TTI of length  $F_i$  frames.
- $\Delta\text{SIR}_i \text{ compression} = 0 \text{ dB}$  in all other cases.