

Presentation of Specification to TSG

Presentation to: TSG SA Meeting #10

Document for presentation: TS 26.202, Version 1.0.0

Presented for: Information

Agenda Item: 7.4.1

Title of document:

AMR Wideband Speech Codec; Interface to Iu and Uu

3G TS 26.202 V 1.0.0 (2000-12)

Technical Specification



3rd Generation Partnership Project; Wideband speech codec; AMR wideband speech codec; Interface to lu and Uu (Release 4)

The present document has been developed within the 3rd Generation Partnership Project (3GPP™) and may be further elaborated for the purposes of 3GPP.

The present document has not been subject to any approval process by the 3GPP Organisational Partners and shall not be implemented.

This Specification is provided for future development work within 3GPP only. The Organisational Partners accept no liability for any use of this Specification.

Specifications and reports for implementation of the 3GPP™ system should be obtained via the 3GPP Organisational Partners' Publications Offices.

Keywords

Adaptive Multi-Rate, Wideband speech coder

3GPP

Postal address

3GPP support office address

650 Route des Lucioles - Sophia Antipolis
Valbonne - FRANCE
Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Internet

<http://www.3gpp.org>

Copyright Notification

No part may be reproduced except as authorized by written permission.
The copyright and the foregoing restriction extend to reproduction in all media.

© 2000, 3GPP Organizational Partners (ARIB, CWTS, ETSI, T1, TTA, TTC).
All rights reserved.

Contents

Foreword.....	5
1 Scope	6
2 References	6
3 Definitions and abbreviations.....	6
3.1 Definitions	6
3.2 Abbreviations	6
4 General	7
5 RAB aspects	8
6 Iu Interface User Plane (RAN).....	9
6.1 Frame structure on the Iu UP transport protocol	9
6.1.1 Initialisation	9
6.1.2 Time Alignment Procedure.....	9
6.2 Mapping of the bits.....	9
6.3 Frame handlers	10
6.3.1 Handling of frames from TC to Iu interface (downlink).....	11
6.3.1.1 Frame Quality Indicator	11
6.3.1.2 Frame Type	11
6.3.1.3 Codec Mode Indication	11
6.3.1.4 Codec Mode Request	11
6.3.1.5 Optional internal 8 bits CRC.....	11
6.3.1.6 Mapping of Speech or Comfort Noise parameter bits.....	11
6.3.2 Handling of frames from Iu interface to TC (uplink).....	12
6.3.2.1 Frame Quality Indicator	12
6.3.2.2 Frame Type	12
6.3.2.3 Codec Mode Indication	12
6.3.2.4 Codec Mode Request	12
6.3.2.5 Optional internal 8 bits CRC.....	12
6.3.2.6 Speech and Comfort noise parameter bits	12
7 Uu Interface User Plane (UE).....	12
8 Other aspects	12
Annex A (informative): Change history	13

Foreword

This Technical Specification (TS) has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

1 Scope

The present document specifies the mapping of the AMR wideband generic frame format (TS 26.201) to the Iu Interface (TS 25.415) and the Uu Interface.

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies.

[1] 3G TS 25.415: "Iu Interface CN-UTRAN User plane Protocols".

[2] 3G TS 26.201: "AMR Wideband Speech Codec, Frame structure".

[3] 3G TS 23.107: "QoS Concept and Architecture".

[Editor's note: To add references to the 3G TS 28.062 (TFO).]

3 Definitions and abbreviations

3.1 Definitions

For the purposes of the present document the following terms and definitions apply:

AMR Wideband Generic Frame Interface: this interface transports the AMR WB IF1 generic frame as defined in TS 26.201.

3.2 Abbreviations

For the purposes of the present document, the following abbreviations apply:

AAL2	ATM Adaptation Layer 2
ACS	Active Codec Set
AMR	Adaptive Multi-Rate
AS	Access Stratum
ATM	Asynchronous Transfer Mode
BFH	Bad Frame Handling
CMR/CMC	Codec Mode Request or Codec Mode Command
CMI	Codec Mode Indication
CN	Core Network
CDMA	Code Division Multiple Access
DRC	Downlink Rate Command
FDD	Frequency Duplex Division
FQC	Frame Quality Classification (IU Interface)
FQI	Frame Quality Indication (AMR IF1)
GSM	Global System for Mobile communications
ITU-T	International Telecommunication Union – Telecommunication standardisation sector (former CCITT)
PLMN	Public Land Mobile Network

RAN	Radio Access Network
RAB	Radio Access Bearer
RF	Radio Frequency
RFC	Rab sub Flow Combination
RFCI	RFC Indicator
RFCS	RFC Set
RX	Receive
SCR	Source Controlled Rate
SID	Silence Insertion Descriptor
SMpSDU	Support Mode for Predefined SDU sizes
SPD	SPeech Decoder
SPE	SPeech Encoder
TC	Transcoder
TDD	Time Duplex Division
TFO	Tandem Free Operation
TrFO	Transcoder Free Operation
TX	Transmit
UE	User Equipment (terminal)
URC	Uplink Rate Command

4 General

The mapping of the Speech Codec parameters to the Iu interface specifies the frame structure of the speech data exchanged between the RNC and the TC in case of normal operation and Tandem Free Operation, respectively between RNC 1 and RNC 2 in case of Transcoder Free Operation. This mapping is independent from the radio interface in the sense that it has the same structure for both FDD and TDD modes of the UTRAN.

The mapping between the Speech Codec and the MAC layer within the UE is not an open interface and need not to be detailed.

5 RAB aspects

During the RAB Assignment procedure initiated by the CN to establish the RAB for AMR WB, the RAB parameters are defined. The AMR RAB is established with one or more RAB co-ordinated sub flows with predefined sizes and QoS parameters. In this way, each Transport Format Combination between sub flows corresponds to one AMR WB frame type. On the Iu interface, these RAB parameters define the corresponding parameters regarding the transport of AMR WB frames.

Some of the QoS parameters in the RAB assignment procedure are determined from the Bearer Capability Information Element used at call set up. These QoS parameters as defined in [3], can be set as follows:

Table 5-1: Example of mapping of BC IE into QoS parameters for UMTS AMR

RAB service attribute	RAB service attribute value		Comments
Traffic Class	Conversational		
RAB Asymmetry Indicator	Symmetric, bidirectional		Symmetric RABs are used for uplink and downlink
Maximum bit rate	23.85 / 23.05 / 19.85 / 18.25 / 15.85 / 14.25 / 12.65 / 8.85 / 6.6 kbit/s		This value depends on the highest mode rate in the RFCS
Guaranteed bit rate	23.85 / 23.05 / 19.85 / 18.25 / 15.85 / 14.25 / 12.65 / 8.85 / 6.6 kbit/s		One of the values is chosen, depending on the lowest rate controllable SDU format (note 2)
Delivery Order	Yes		(note 1)
Maximum SDU size	477 / 461 / 397 / 317 / 285 / 253 / 177 / 132 bits		Maximum size of payload field in IU UP, according to the highest mode rate in the RFCS
Traffic Handling Priority	Not applicable		Parameter not applicable for the conversational traffic class. (note 1)
Source statistics descriptor	Speech		(note 1)
SDU Parameters	RAB subflow 1 (Class A bits)	RAB subflow 2 (Class B bits)	The number of SDU, their number of RAB subflow is subject to operator tuning (note 3)
SDU error ratio	$7 * 10^{-3}$	-	(note 3)
Residual bit error ratio	10^{-6}	10^{-3}	(note 3 – applicable for every subflow)
Delivery of erroneous SDUs	yes	-	Class A bits are delivered with error indication; Class B bits are delivered without any error indication.
SDU format information 1-9			(note 4)
Subflow SDU size 1-9	(note 5)	(note 5)	
SDU format information 10			(note 4)
Subflow SDU size 10	0	0	(note 6)
NOTE 1: These parameters apply to all UMTS speech codec types.			
NOTE 2: The guaranteed bit rate depends on the periodicity and the lowest rate controllable SDU size.			
NOTE 3: These parameters are subject to operator tuning.			
NOTE 4: SDU format information has to be specified for each AMR core frame type (i.e. with speech bits and comfort noise bits) included in the RFCS as defined in [2].			
NOTE 5: The subflow SDU size corresponding to an AMR core frame type indicates the number of bits in the class A, class B fields.			
NOTE 6: SDU size = 0 is needed for Initial Time Alignment.			

The conversational traffic class shall be used for the speech service, which is identified by the ITC parameter of the bearer capability information element in the SETUP message. This shall apply for all UMTS speech codec types. The parameters traffic class, transfer delay, traffic handling priority and source statistics descriptor shall be the same for all speech codec types applicable for UMTS.

6 Iu Interface User Plane (RAN)

The data structure exchanged on the Iu interface are symmetrical, i.e. the structure of the uplink data frames is identical to that of the downlink data frames. This facilitates Tandem Free Operation and Transcoder Free Operation.

6.1 Frame structure on the Iu UP transport protocol

6.1.1 Initialisation

At the initialisation of the SMpSDU mode of operation, several parameters are set by the CN. The initialisation procedure is described in TS 25.415 [1].

- RFCS:

In the case of AMR WB, the RFCS corresponds to the Active Codec Set (ACS) authorised in the communication. *Annex A of [1] gives an illustration of the usage of RFCI for AMR WB speech RAB. RFCS used in downlink may differ from that in uplink.* [Editor's note: 25.415 may need to be updated to cover AMR WB]

- Delivery of erroneous SDUs:

This parameter shall be set to YES. Erroneous speech frames may be used to assist the error concealment procedures.

[Editor's note: This might need to be specified in another specifications] PDU type.

The PDU type 0 shall be used for the transport of AMR data.

[Editor's note: This might need to be specified in another specifications].

6.1.2 Time Alignment Procedure

TC should adjust timing of speech data transmission according to time alignment frame sent by RNC.

TC should get into Initial Time Alignment state immediately after Iu initialisation. At Initial Time Alignment state, TC shall send Iu userplane PDU type 0 frame with SDU size = 0 to RNC until speech data transmission starts.

Time alignment procedure shall be dismissed in case of TFO.

6.2 Mapping of the bits

The mapping of the bits between the generic AMR WB frames and the PDU is the same for both uplink and downlink frames.

The following table gives the correspondence of the bit fields between the generic AMR WB frames at the TC interface and the PDU exchanged with the Iu transport layer.

Table 6-1: Mapping of generic AMR WB frames onto lu PDUs

PDU field	Corresponding AMR generic frame field	Comment
PDU Type	N/A	Type 0
Frame Number	N/A	
FQC	Frame Quality Indicator	
RFCI	AMR WB Frame Type	
Payload CRC	N/A	
Header CRC	N/A	
Payload Fields (N Sub Flows)	Class A or SID payload Class B	
SDU #1	Most important speech bits come first	Mandatory
SDU #2	Next bits follow	Optional
...	...	Optional
SDU #N	Least important speech bits	Optional

The number of RAB sub flows, their corresponding sizes, and their attributes such as "Delivery of erroneous SDUs" shall be defined at the RAB establishment and signalled in the RANAP RAB establishment request, as proposed in clause 5. The number of RAB sub flows are corresponding to the desired bit protection classes. The total number of bits in all sub flows for one RFC shall correspond to the total number given in TS 26.201 for the corresponding Codec Mode respectively Frame Type.

Guidance for setting the number of bits in each RAB Sub Flow according to their relative subjective importance is given in TS 26.201.

The following two tables are examples of mapping of RAB sub flows.

Table 6-2 gives three examples of sub flow mapping.

The RFCI definition is given in order of increasing SDU sizes.

- Example 1 describes Codec Type UMTS_AMR_WB, with all nine codec modes foreseen in the Active Codec Set (ACS) and provision for Source Controlled Rate operation (SCR). In this example, Blind Transport Format Detection is supported and the sub flow mapping follows the 26.201 class division guidance.

Table 6-2: Example for AMR with SCR and three sub flows, according to subjective class division indication of TS 26.101

UMTS_AMR RFCI Example 1	RAB sub-flows		Total size of bits/RAB sub- flows combination (Mandatory)	Source rate
	RAB sub- Flow 1 (Optional)	RAB sub- Flow 2 (Optional)		
2	54	78	132	AMR 6.6 kbps
3	64	113	177	AMR 8.85 kbps
4	72	181	253	AMR 12.65 kbps
5	72	213	285	AMR 14.25 kbps
6	72	245	317	AMR 15.85 kbps
7	72	293	365	AMR 18.25 kbps
8	72	325	397	AMR 19.85 kbps
9	72	389	461	AMR 23.05 kbps
10	72	405	477	AMR 23.85 kbps
1	35	0	35	AMR SID
0	0	0	0	NO DATA

6.3 Frame handlers

lu PDU Frame handling functions are described in TS 25.415. This sections describes the mandatory frame handling functions at the AMR WB Generic frame interface. [Editor's note: 25.415 may need to be updated to cover AMR WB]

6.3.1 Handling of frames from TC to Iu interface (downlink)

The frames from the TC in AMR WB generic frame format are mapped onto the Iu PDU as follows.

6.3.1.1 Frame Quality Indicator

The Frame Quality Indicator from the TC, respectively from the distant TFO partner, is directly mapped to the Frame Quality Classification of the Iu frame according to Table 6-3.

Table 6-3: FQI AMR to FQC Iu PDU mapping

FQI AMR	FQC PDU	FQC value
GOOD	GOOD	0
BAD	BAD	1

6.3.1.2 Frame Type

The received Frame Type Index is mapped onto the RFCI thanks to the assigned RFCS table: the correspondence between Codec Mode, Frame Type Index and RFCI is defined at RAB assignment.

6.3.1.3 Codec Mode Indication

The Codec Mode Indication is not used because it is redundant to the Frame Type.

6.3.1.4 Codec Mode Request

Codec Mode Request (CMR) in downlink direction is forwarded to the rate control procedure if it changes.

6.3.1.5 Optional internal 8 bits CRC

The internal AMR WB CRC is not used on the Iu interface.

6.3.1.6 Mapping of Speech or Comfort Noise parameter bits

Let define the N payload fields of the N Sub flows for RFCI j as follow :

$U_i(k)$ shall be the bits in Sub Flow i, for $k=1$ to M_i

M_i shall be the size of Sub Flow i, for $i = 1$ to N

$S(k)$ shall be the bits of the speech or comfort noise parameters of the corresponding Frame Type j in decreasing subjective importance.

Then the following mapping in pseudo code applies:

$$\begin{aligned} U_1(k) &= S(k) && \text{with } k = 1, \dots M_1 \\ U_2(k) &= S(k + M_1) && \text{with } k = 1, \dots M_2 \\ U_3(k) &= S(k + M_2) && \text{with } k = 1, \dots M_3 \\ &\dots && \\ U_N(k) &= S(k + M_{N-1}) && \text{with } k = 1 \dots M_N \end{aligned}$$

6.3.2 Handling of frames from Iu interface to TC (uplink)

The uplink Iu frames are mapped onto generic AMR WB frames as follow.

6.3.2.1 Frame Quality Indicator

At reception of Iu PDU the Iu frame handler function set the Frame Quality Classification according to the received FQC, Header-CRC check, and Payload-CRC check (see 25.415). AMR WB Frame Type and Frame Quality Indicator are determined according to the following table:

Table 6-4: FQC Iu PDU type 0 to AMR WB FQI and AMR WB Frame Type mapping

FQC	Resulting FQI	Resulting Frame Type
GOOD	GOOD	from RFCI
BAD	BAD	NO_DATA
BAD Radio	BAD	from RFCI
Reserved	Reserved	Reserved

6.3.2.2 Frame Type

The received RFCI is mapped onto the Frame Type thanks to the RFCS table. I.e. the Type_Index is set according to the AMR WB mode.

6.3.2.3 Codec Mode Indication

The Codec Mode Indication is not used because it is redundant to the Frame Type.

6.3.2.4 Codec Mode Request

The received Downlink Rate Control command is mapped onto the Codec Mode Request. In case a new DRC is received it is mapped into the corresponding CMR AMR WB generic frame format. It is remembered by the TC until the next DRC is received. In each new frame that is sent to the AMR WB Codec, the stored CMR is resent, in order to control the Codec Mode for the downlink direction.

6.3.2.5 Optional internal 8 bits CRC

The internal AMR WB CRC is not used on the Iu interface.

6.3.2.6 Speech and Comfort noise parameter bits

The speech and Comfort noise parameter bits are mapped from the sub flows to the payload of the generic AMR WB frames with the reverse function of subclause 6.3.1.6.

7 Uu Interface User Plane (UE)

The interface between the UE AMR WB speech codec (see TS 26.201) and the Radio Access Network is an internal UE interface and is not detailed. The mapping is corresponding to the mapping described in clause 6 for the IU interface.

8 Other aspects

[ffs]

Annex A (informative):
Change history

Change history							
Date	TSG #	TSG Doc.	CR	Rev	Subject/Comment	Old	New