

**Technical Specification Group Services and System Aspects TSGS#27 (05)0084  
Meeting #27, Tokyo, Japan, 14-17 March 2005**

**Source: TSG-SA WG4**

**Title: 3GPP TS 26.411 version 1.0.0 "Enhanced aacPlus General Audio Codec;  
Fixed-point ANSI-C code" (Release 6)**

**Agenda Item: 7.4.3**

**Presentation of Specification to TSG SA Plenary**

---

**Presentation to: TSG SA Meeting #27**

**Document for presentation: TS 26.411 "Enhanced aacPlus General Audio Codec;  
Fixed-point ANSI-C code", Version 1.0.0 (Release 6)**

**Presented for: Approval**

---

**Abstract of document:**

The present document contains an electronic copy of the ANSI-C code for the Fixed-point Enhanced aacPlus codec. Alternatively, floating-point ANSI-C code is specified in 3GPP TS 26.410. The fixed-point codec/encoder/decoder specified in this document or the floating-point codec/encoder/decoder may be used depending on if the implementation platform is better suited for a floating-point or a fixed-point implementation. It has been verified that the fixed-point and floating-point codecs interoperate with each other without any artifacts.

Standard conformance is enforced by meeting the conformance criteria defined in TS 26.406.

The present document includes information applicable to network operators, service providers and manufacturers.

---

**Changes since last presentation:**

This specification is presented to TSG SA Plenary for the first time; it is considered stable (for approval).

---

**Outstanding Issues:**

None.

---

**Contentious Issues:**

None.

---

**Comment(s):**

None.

---

# 3GPP TS 26.411 V1.0.0 (2005-03)

---

*Technical Specification*

**3rd Generation Partnership Project;  
Technical Specification Group Services and System Aspects;  
General audio codec audio processing functions;  
Enhanced aacPlus general audio codec;  
Fixed-point ANSI-C code  
(Release 6)**



The present document has been developed within the 3<sup>rd</sup> Generation Partnership Project (3GPP™) and may be further elaborated for the purposes of 3GPP.

The present document has not been subject to any approval process by the 3GPP Organizational Partners and shall not be implemented. This Specification is provided for future development work within 3GPP only. The Organizational Partners accept no liability for any use of this Specification. Specifications and reports for implementation of the 3GPP™ system should be obtained via the 3GPP Organizational Partners' Publications Offices.

---

Keywords

---

UMTS, Enhanced aacPlus, CODEC, General  
Audio Coding

**3GPP**

Postal address

---

3GPP support office address

---

650 Route des Lucioles - Sophia Antipolis  
Valbonne - FRANCE  
Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Internet

---

<http://www.3gpp.org>

---

**Copyright Notification**

---

No part may be reproduced except as authorized by written permission.  
The copyright and the foregoing restriction extend to reproduction in all media.

© 2005, 3GPP Organizational Partners (ARIB, ATIS, CCSA, ETSI, TTA, TTC).  
All rights reserved.

---

# Contents

Foreword.....	4
1 Scope .....	5
2 References .....	5
3 Definitions and abbreviations.....	5
3.1 Definitions .....	5
3.2 Abbreviations .....	6
4 Fixed point ANSI-C code structure.....	6
4.1 Contents of the fixed point ANSI-C source code .....	6
4.2 Program execution.....	8
4.3 Memory requirements .....	9
4.3.1 Constants and tables.....	9
4.3.2 Static memory .....	14
4.3.3 Dynamic memory .....	16
4.3.4 Maximum stack size .....	16
5 File formats .....	21
5.1 Audio input file (encoder input/decoder output) .....	21
5.2 Bitstream file format (encoder output/decoder input) .....	21
5.3 Error pattern file (decoder input).....	21
<b>Annex A (Informative): Weighted MOPS.....</b>	<b>22</b>
<b>Annex B (informative): Change history .....</b>	<b>23</b>

---

## Foreword

This Technical Specification has been produced by the 3<sup>rd</sup> Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
  - 1 presented to TSG for information;
  - 2 presented to TSG for approval;
  - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

---

# 1 Scope

The present document contains an electronic copy of the ANSI-C code for the Fixed-point Enhanced aacPlus codec [1].

---

## 2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

- [1] 3GPP TS 26.401: "General audio codec audio processing functions; Enhanced aacPlus general audio codec; General description".
- [2] 3GPP TS 26.403: "General audio codec audio processing functions; Enhanced aacPlus general audio codec; Encoder specification; Advanced Audio Coding (AAC) part".
- [3] 3GPP TS 26.404: "General audio codec audio processing functions; Enhanced aacPlus general audio codec; Encoder specification; Spectral Band Replication (SBR) part".
- [4] 3GPP TS 26.405: "General audio codec audio processing functions; Enhanced aacPlus general audio codec; Encoder specification; Parametric stereo part".
- [5] ISO/IEC 14496-3 (2001): "Information technology - Coding of audio-visual objects - Part 3: Audio".
- [6] ISO/IEC 14496-3:2001/Amd.1:2003: "Bandwidth Extension".
- [7] ISO/IEC 14496-3:2001/Amd.1:2003/Cor 1:2004.
- [8] ISO/IEC 14496-3:2001/ Amd.2:2004: "Parametric coding for high quality audio".
- [9] 3GPP TS 26.402: "General audio codec audio processing functions; Enhanced aacPlus general audio codec; Additional decoder tools".
- [10] 3GPP TS 26.244: "Transparent end-to-end streaming service; 3GPP file format (3GP)".

---

## 3 Definitions and abbreviations

### 3.1 Definitions

For the purposes of the present document, the terms and definitions given in 3GPP TS 26.401 [1], 3GPP TS 26.403 [2], 3GPP TS 26.404 [3], 3GPP TS 26.405 [4] and 3GPP TS 26.402 [9] apply.

## 3.2 Abbreviations

For the purposes of the present document, the following abbreviations apply:

AAC	Advanced Audio Coding
aacPlus	Combination of MPEG-4 AAC and MPEG-4 Bandwidth extension (SBR)
ANSI	American National Standards Institute
Enhanced aacPlus	Combination of MPEG-4 AAC, MPEG-4 Bandwidth extension (SBR) and MPEG-4 Parametric Stereo
GSM	Global System for Mobile communications
I/O	Input/Output
MDCT	Modified Discrete Cosine Transform
QMF	Quadrature Mirror Filter
RAM	Random Access Memory
ROM	Read Only Memory
SBR	Spectral Band Replication

---

## 4 Fixed point ANSI-C code structure

This clause gives an overview of the structure of the fixed point ANSI-C code and provides an overview of the contents and organization of the C code attached to the present document.

The C code has been verified on the following systems:

- IBM PC/AT compatible computers with Windows XP, 2000 and Microsoft Visual C++ v.6.0 compiler.
- IBM PC/AT compatible computers with Linux OS and GCC v.3.3 compiler.

ANSI-C was selected as the programming language because portability was desirable.

### 4.1 Contents of the fixed point ANSI-C source code

The C code distribution is organized in two directories for encoder and decoder and further into several subdirectories, reflecting the major building blocks of the Enhanced aacPlus codec. The file descriptions on root level as well as the directory structure is given as follows.

**Table 1: Source code directory structure for the encoder (ETSI\_aacPlusenc)**

Directory	Description
README.txt	information on how to compile
Makefile	UNIX style encoder Makefile
enhAacPlusenc.dsw	Win32 MSVC 6.0 encoder workspace
enhAacPlusenc.dsp	Win32 MSVC 6.0 encoder makefile
src/	directory for the encoder frontend
etsiop_fastaacenc/	AAC encoder library
etsiop_resamplib/	resampler library
etsiop_sbrenclib/	SBR encoder library

**Table 2: Source code directory structure for the decoder (ETSI\_aacPlusdec)**

Directory	Description
README.txt	information on how to compile
Makefile	UNIX style encoder Makefile
enhAacPlusdec.dsw	Win32 MSVC 6.0 decoder workspace
src/	directory for the decoder frontend
etsiop_aacdec	AAC decoder library
etsiop_sbrdeclib/	SBR decoder library

**Table 3: Source code directory structure common for encoder and decoder**

Directory	Description
etsiop_bitbuf/	bitstream reading/writing library
etsiop_ffrlib/	general purpose functionalities
etsioplib/	ETSI operators implementation
3g_lib/	precompiled libraries for audio and bitstream file format handling

The distributed files with suffix "c" contain the source code and the files with suffix "h" are the header files. Within the respective libraries, the RAM data is contained in "xxx\_ram" files with suffix "c", the ROM data is contained in "xxx\_rom" files with suffix "c". Makefiles are provided for the platforms in which the C code has been verified (listed above).

A list of source code files is given below:

**Table 4: Encoder source code files**

Directory	Module
src/	main.c
	mp4file.c
etsiop_fastaacenc/	qc_main.c
	aacenc.c
	ms_stereo.c
	spreading.c
	interface.c
	bit_cnt.c
	adj_thr.c
	quantize.c
	psy_configuration.c
	sf_estim.c
	tns_param.c
	grp_data.c
	pre_echo_control.c
	stprepro.c
	tns.c
	dyn_bits.c
	psy_main.c
	channel_map.c
	block_switch.c
	band_nrg.c
	transform.c
	bitenc.c
	line_pe.c
stat_bits.c	
etsiop_sbrenc/	qmf_enc.c
	ton_corr.c
	fram_gen.c
	env_bit.c
	env_est.c
	mh_det.c
	hybrid.c
	bit_sbr.c
	ps_bitenc.c
	sbr_main.c
	tran_det.c
	sbr_misc.c
	code_env.c
	nf_est.c
freq_sca.c	
invf_est.c	
ps_enc.c	
etsiop_resamplib/	downsample_FIR.c

**Table 5: Decoder source code files**

Directory	Module
src/	main.c
	fileifc.c
	spline_resampler.c
etsiop_aacdec/	aacdecoder.c
	streaminfo.c
	channelinfo.c
	stereo.c
	longblock.c
	shortblock.c
	pulsedata.c
	block.c
	pns.c
	imdct.c
	tns.c
	bitstream.c
	channel.c
	conceal.c
datastream.c	
etsiop_sbrdeclib/	env_dec.c
	aacpluscheck.c
	sbr_bitb.c
	env_calc.c
	lpp_tran.c
	sbrdecoder.c
	sbr_dec.c
	sbr_crc.c
	hybrid.c
	ps_bitdec.c
	huff_dec.c
	env_extr.c
	freq_sca.c
	ps_dec.c
	qmf_dec.c

**Table 6: Common source code files**

Directory	Module
etsiop_bitbuf/	bitbuffer.c
etsiop_ffrlib/	fft_32x32.c
	transcendent.c
	transcendent_enc.c
	intrinsic.c
	vector.c

## 4.2 Program execution

The Enhanced AAC Plus codec is implemented in two programs:

- enhAacPlusEnc.exe.
- enhAacPlusDec.exe.

The programs should be called like:

- enhAacPlusEnc.exe <wav\_file> <bitstream\_file> <bitrate> <(m)ono/(s)tereo>.
- enhAacPlusDec.exe <bitstream\_file> <wav\_file> <mode> [error\_pattern\_file].

The audio files contain 16-bit linear encoded PCM samples with wav header, the bitstream files are of 3GPP type and the error pattern file is a ASCII file, see clause 5.

The encoder and decoder command line handling is also explained by running the applications without input arguments.

## 4.3 Memory requirements

The data types of variables and tables used in the fixed-point implementation are defined by the ETSI operator data types, the following types are used:

- Word8.
- Word16.
- Word32.
- Flag.

### 4.3.1 Constants and tables

This clause contains a listing of all constants and tables contributing to the ROM requirements of the encoder and decoder.

**Table 7: Encoder constants and tables**

Name	Data type	Size [16-bit word]	Allocated in Source File	Description
LongWindowSine	Word16	1 024	aac_rom.c	Window coefficients
ShortWindowSine	Word16	128	aac_rom.c	Window coefficients
LongWindowKBD	Word16	1 024	aac_rom.c	Window coefficients
fftTwiddleTable	Word16	513	aac_rom.c	FFT twiddle coefficients
formfac_sqrttable	Word32	192	aac_rom.c	Lookup table for efficient sqrt implementation
mTab_3_4	Word32	1 024	aac_rom.c	Quantizer table, used for efficient pow () implementation
mTab_4_3	Word32	1 024	aac_rom.c	Inverse quantizer table, used for efficient pow () implementation
pow2tominusNover16	Word16	17	aac_rom.c	Lookup table for efficient pow() implementation
specExpMantTableComb_enc	Word32	128	aac_rom.c	Lookup table for efficient inverse quantizer implementation
specExpTableComb_enc	Word8	32	aac_rom.c	Lookup table for efficient inverse quantizer implementation
quantBorders	Word16	16	aac_rom.c	Lookup table for efficient distortion calculation implementation
quantBorders	Word16	12	aac_rom.c	Lookup table for efficient distortion calculation implementation
p_8000_mono_long	TNS_CONFIG_T ABULATED	5	aac_rom.c	TNS tuning parameters
p_8000_stereo_long	TNS_CONFIG_T ABULATED	5	aac_rom.c	TNS tuning parameters
p_8000_mono_short	TNS_CONFIG_T ABULATED	5	aac_rom.c	TNS tuning parameters
p_8000_stereo_short	TNS_CONFIG_T ABULATED	5	aac_rom.c	TNS tuning parameters
p_16000_mono_long	TNS_CONFIG_T ABULATED	5	aac_rom.c	TNS tuning parameters
p_16000_stereo_long	TNS_CONFIG_T ABULATED	5	aac_rom.c	TNS tuning parameters
p_16000_mono_short	TNS_CONFIG_T ABULATED	5	aac_rom.c	TNS tuning parameters
p_16000_stereo_short	TNS_CONFIG_T ABULATED	5	aac_rom.c	TNS tuning parameters
p_24000_mono_long	TNS_CONFIG_T ABULATED	5	aac_rom.c	TNS tuning parameters

Name	Data type	Size [16-bit word]	Allocated in Source File	Description
p_24000_stereo_long	TNS_CONFIG_T ABULATED	5	aac_rom.c	TNS tuning parameters
p_24000_mono_short	TNS_CONFIG_T ABULATED	5	aac_rom.c	TNS tuning parameters
p_24000_stereo_short	TNS_CONFIG_T ABULATED	5	aac_rom.c	TNS tuning parameters
p_32000_mono_long	TNS_CONFIG_T ABULATED	5	aac_rom.c	TNS tuning parameters
p_32000_stereo_long	TNS_CONFIG_T ABULATED	5	aac_rom.c	TNS tuning parameters
p_32000_mono_short	TNS_CONFIG_T ABULATED	5	aac_rom.c	TNS tuning parameters
p_32000_stereo_short	TNS_CONFIG_T ABULATED	5	aac_rom.c	TNS tuning parameters
m_log2_table	Word32	64	aac_rom.c	Lookup table for efficient ld() implementation
tnsCoeff3	Word32	16	aac_rom.c	TNS filter coefficients
tnsCoeff3Borders	Word32	16	aac_rom.c	TNS filter borders
tnsCoeff4	Word32	32	aac_rom.c	TNS filter coefficients
tnsCoeff4Borders	Word32	32	aac_rom.c	TNS filter borders
tnsInfoTab	TNS_INFO_TAB	20	aac_rom.c	TNS bitrate to tuning mapping table
tnsMaxBandsTab	TNS_MAX_TAB_ENTRY	12	aac_rom.c	max. TNS bands per sampling rate table
huff_ltab1_2	Word16	81	aac_rom.c	Huffman codeword table AAC
huff_ltab3_4	Word16	81	aac_rom.c	Huffman codeword table AAC
huff_ltab5_6	Word16	81	aac_rom.c	Huffman codeword table AAC
huff_ltab7_8	Word16	64	aac_rom.c	Huffman codeword table AAC
huff_ltab9_10	Word16	169	aac_rom.c	Huffman codeword table AAC
huff_ltab11	Word16	289	aac_rom.c	Huffman codeword table AAC
huff_ltabscf	Word16	121	aac_rom.c	Huffman codeword table AAC
huff_ctab1	Word16	81	aac_rom.c	Huffman codeword table AAC
huff_ctab2	Word16	81	aac_rom.c	Huffman codeword table AAC
huff_ctab3	Word16	81	aac_rom.c	Huffman codeword table AAC
huff_ctab4	Word16	81	aac_rom.c	Huffman codeword table AAC
huff_ctab5	Word16	81	aac_rom.c	Huffman codeword table AAC
huff_ctab6	Word16	81	aac_rom.c	Huffman codeword table AAC
huff_ctab7	Word16	64	aac_rom.c	Huffman codeword table AAC
huff_ctab8	Word16	64	aac_rom.c	Huffman codeword table AAC
huff_ctab9	Word16	169	aac_rom.c	Huffman codeword table AAC
huff_ctab10	Word16	169	aac_rom.c	Huffman codeword table AAC
huff_ctab11	Word16	289	aac_rom.c	Huffman codeword table AAC
huff_ctabscf	Word32	242	aac_rom.c	Huffman codeword table AAC
sfb_16000_long_1024	Word8	22	aac_rom.c	Scalefactor band table
sfb_16000_short_128	Word8	8	aac_rom.c	Scalefactor band table
sfb_22050_long_1024	Word8	24	aac_rom.c	Scalefactor band table
sfb_22050_short_128	Word8	8	aac_rom.c	Scalefactor band table
sfb_24000_long_1024	Word8	24	aac_rom.c	Scalefactor band table
sfb_24000_short_128	Word8	8	aac_rom.c	Scalefactor band table
p4_13	Word32	26	sbr_rom.c	Hybrid filterbank coefficients
p8_13	Word32	26	sbr_rom.c	Hybrid filterbank coefficients
sbr_cos_twiddle_L32_enc	Word16	16	sbr_rom.c	QMF filterbank twiddle table
sbr_cos_twiddle_L64_enc	Word16	32	sbr_rom.c	QMF filterbank twiddle table
sbr_sin_twiddle_L32_enc	Word16	16	sbr_rom.c	QMF filterbank twiddle table
sbr_sin_twiddle_L64_enc	Word16	32	sbr_rom.c	QMF filterbank twiddle table
sbr_alt_sin_twiddle_L32_enc	Word16	17	sbr_rom.c	QMF filterbank twiddle table
sbr_alt_sin_twiddle_L64_enc	Word16	33	sbr_rom.c	QMF filterbank twiddle table
sbr_qmf_64_640_enc	Word16	330	sbr_rom.c	QMF window coefficients
aBookPslidTimeCode	Word32	58	sbr_rom.c	Huffman codeword table Parametric Stereo
aBookPslidFreqCode	Word32	58	sbr_rom.c	Huffman codeword table Parametric Stereo
aHybridResolution	Word16	3	sbr_rom.c	Number of hybrid bands in each QMF band
hiResBandBorders	Word8	11	sbr_rom.c	Borders of Parametric Stereo bins
groupBordersMix	Word8	15	sbr_rom.c	Borders of Parametric Stereo groups

Name	Data type	Size [16-bit word]	Allocated in Source File	Description
bins2groupMap	Word32	58	sbr_rom.c	Mapping of Parametric Stereo bins to Parametric Stereo groups
iidQuantLeft	Word32	14	sbr_rom.c	IID quant values for Parametric Stereo
iidQuantRight	Word32	14	sbr_rom.c	IID quant values for Parametric Stereo
iccQuant	Word32	16	sbr_rom.c	ICC quant values for Parametric Stereo
v_Huff_envelopeLevelC10T	Word32	242	sbr_rom.c	Huffman codeword table SBR
v_Huff_envelopeLevelC10F	Word32	242	sbr_rom.c	Huffman codeword table SBR
bookSbrEnvBalanceC10F	Word32	98	sbr_rom.c	Huffman codeword table SBR
bookSbrEnvBalanceC10T	Word32	98	sbr_rom.c	Huffman codeword table SBR
v_Huff_envelopeLevelC11T	Word32	126	sbr_rom.c	Huffman codeword table SBR
v_Huff_NoiseLevelC11T	Word32	126	sbr_rom.c	Huffman codeword table SBR
bookSbrEnvBalanceC11T	Word32	50	sbr_rom.c	Huffman codeword table SBR
bookSbrNoiseBalanceC11T	Word32	50	sbr_rom.c	Huffman codeword table SBR
v_Huff_envelopeLevelC11F	Word32	126	sbr_rom.c	Huffman codeword table SBR
bookSbrEnvBalanceC11F	Word32	50	sbr_rom.c	Huffman codeword table SBR
aBookPslidTimeLength	Word8	15	sbr_rom.c	Huffman codeword table Parametric Stereo
aBookPslidFreqLength	Word8	15	sbr_rom.c	Huffman codeword table Parametric Stereo
aBookPslccFreqLength	Word8	8	sbr_rom.c	Huffman codeword table Parametric Stereo
aBookPslccTimeLength	Word8	8	sbr_rom.c	Huffman codeword table Parametric Stereo
aBookPslccFreqCode	Word16	15	sbr_rom.c	Huffman codeword table Parametric Stereo
aBookPslccTimeCode;	Word16	15	sbr_rom.c	Huffman codeword table Parametric Stereo
v_Huff_envelopeLevelL10T	Word8	61	sbr_rom.c	Huffman codeword table SBR
v_Huff_envelopeLevelL10F	Word8	61	sbr_rom.c	Huffman codeword table SBR
bookSbrEnvBalanceL10F	Word8	25	sbr_rom.c	Huffman codeword table SBR
bookSbrEnvBalanceL10T	Word8	25	sbr_rom.c	Huffman codeword table SBR
v_Huff_envelopeLevelL11T	Word8	32	sbr_rom.c	Huffman codeword table SBR
bookSbrEnvBalanceL11T	Word8	13	sbr_rom.c	Huffman codeword table SBR
v_Huff_NoiseLevelL11T	Word8	32	sbr_rom.c	Huffman codeword table SBR
bookSbrNoiseBalanceL11T	Word8	13	sbr_rom.c	Huffman codeword table SBR
v_Huff_envelopeLevelL11F	Word8	32	sbr_rom.c	Huffman codeword table SBR
bookSbrEnvBalanceL11F	Word8	13	sbr_rom.c	Huffman codeword table SBR
logDualisTable	Word16	65	transcenden t.c	Lookup table for efficient log() implementation
pow2Table	Word32	512	transcenden t_enc.c	Lookup table for efficient pow() implementation
FIRenc_band24	Word16	49	downsample FIR.c	FIR filter coefficients for 2:1 resampling
FIRenc_band63	Word16	127	downsample FIR.c	FIR filter coefficients for 3:2 resampling
tuningTable	tuningTable	168	sbr_main.c	SBR tuning parameters
<b>Sum</b>		<b>21 288</b>		

Table 8: Decoder constants and tables

Name	Data type	Size [16-bit word]	Allocated in Source File	Description
tnsCoeff3	Word16	8	aac_rom.c	TNS filter coefficients
tnsCoeff4	Word16	16	aac_rom.c	TNS filter coefficients
trigData	Word16	513	aac_rom.c	Sine table, used for efficient sin(), cos()
OnlyLongWindowKBD	Word16	1 024	aac_rom.c	Window coefficients
OnlyShortWindowKBD	Word16	128	aac_rom.c	Window coefficients
OnlyLongWindowSine	Word16	1 024	aac_rom.c	Window coefficients
OnlyShortWindowSine	Word16	128	aac_rom.c	Window coefficients
sfb_48_1024	Word16	50	aac_rom.c	Scalefactor band table
sfb_48_128	Word16	15	aac_rom.c	Scalefactor band table
sfb_32_1024	Word16	51	aac_rom.c	Scalefactor band table
sfb_24_1024	Word16	49	aac_rom.c	Scalefactor band table
sfb_24_128	Word16	16	aac_rom.c	Scalefactor band table
sfb_16_1024	Word16	44	aac_rom.c	Scalefactor band table
sfb_16_128	Word16	16	aac_rom.c	Scalefactor band table

Name	Data type	Size [16-bit word]	Allocated in Source File	Description
sfb_8_1024	Word16	41	aac_rom.c	Scalefactor band table
sfb_8_128	Word16	16	aac_rom.c	Scalefactor band table
HuffmanCodeBook_1	Word16	204	aac_rom.c	Huffman codeword table AAC
HuffmanCodeBook_2	Word16	156	aac_rom.c	Huffman codeword table AAC
HuffmanCodeBook_3	Word16	156	aac_rom.c	Huffman codeword table AAC
HuffmanCodeBook_4	Word16	152	aac_rom.c	Huffman codeword table AAC
HuffmanCodeBook_5	Word16	164	aac_rom.c	Huffman codeword table AAC
HuffmanCodeBook_6	Word16	160	aac_rom.c	Huffman codeword table AAC
HuffmanCodeBook_7	Word16	124	aac_rom.c	Huffman codeword table AAC
HuffmanCodeBook_8	Word16	124	aac_rom.c	Huffman codeword table AAC
HuffmanCodeBook_9	Word16	336	aac_rom.c	Huffman codeword table AAC
HuffmanCodeBook_10	Word16	328	aac_rom.c	Huffman codeword table AAC
HuffmanCodeBook_11	Word16	544	aac_rom.c	Huffman codeword table AAC
HuffmanCodeBook_SCL	Word16	260	aac_rom.c	Huffman codeword table AAC
SamplingRateInfoTable	Word16	45	aac_rom.c	Sampling rate to scalefactor mapping table AAC
HuffmanCodeBooks	mixed	52	aac_rom.c	Huffman codeword table AAC
specExpTableComb	Word8	52	aac_rom.c	Lookup table for efficient exponent implementation
specExpTableMant	Word32	104	aac_rom.c	Lookup table for efficient exponent implementation, mantissa
InverseQuantTable	Word32	514	aac_rom.c	Lookup table for efficient inverse quantizer implementation
sgn_mask	Word8	3	aac_rom.c	Helper vector for efficient bit-wise operations in the TNS module
neg_mask	Word8	3	aac_rom.c	Helper vector for efficient bit-wise operations in the TNS module
tns_max_bands_tbl	Word8	18	aac_rom.c	max. TNS bands per sampling rate table
sbr_limGains_m	Word16	4	sbr_rom.c	SBR limiter gain values, mantissa
sbr_limGains_e	Word8	4	sbr_rom.c	SBR limiter gain values, exponent
sbr_limiterBandsPerOctaveDiv4	Word16	4	sbr_rom.c	Number of SBR limiter bands, divided by 4
sbr_smoothFilter	Word16	4	sbr_rom.c	Smoothing filter for gain values
sbr_invIntTable	Word16	49	sbr_rom.c	Table of 1/x function
sbr_randomPhase	Word16 or Word32	1 120	sbr_rom.c	Random numbers for SBR noise addition and PNS. Note: for mono only case the data type Word16 can be used.
sbr_qmf_64_640	Word16	340	sbr_rom.c	QMF window coefficients
sbr_ralt_sin_twiddle_L64	Word16	64	sbr_rom.c	FFT twiddle table
sbr_ralt_sin_twiddle_L32	Word16	32	sbr_rom.c	FFT twiddle table
sbr_cos_twiddle_L64	Word16	32	sbr_rom.c	FFT twiddle table, obsolete for mono only decoder
sbr_cos_twiddle_L32	Word16	16	sbr_rom.c	FFT twiddle table, obsolete for mono only decoder
sbr_sin_twiddle_L64	Word16	32	sbr_rom.c	FFT twiddle table, obsolete for mono only decoder
sbr_sin_twiddle_L32	Word16	16	sbr_rom.c	FFT twiddle table, obsolete for mono only decoder
sbr_alt_sin_twiddle_L64	Word16	33	sbr_rom.c	FFT twiddle table, obsolete for mono only decoder
sbr_cos_twiddle_ds_L32	Word16	32	sbr_rom.c	FFT twiddle table, obsolete for mono only decoder
sbr_sin_twiddle_ds_L32	Word16	32	sbr_rom.c	FFT twiddle table, obsolete for mono only decoder
sbr_t_cos_L32	Word16	32	sbr_rom.c	FFT twiddle table, obsolete for mono only decoder
sbr_t_sin_L32	Word16	32	sbr_rom.c	FFT twiddle table, obsolete for mono only decoder
pHybridResolution	Word8	3	sbr_rom.c	Parametric Stereo hybrid filterbank resolution
groupShift	Word8	6	sbr_rom.c	Parametric Stereo shift bits for uppermost frequency groups
aRevLinkDecaySer	Word16	3	sbr_rom.c	Parametric Stereo all-pass filter coefficients

Name	Data type	Size [16-bit word]	Allocated in Source File	Description
aFractDelayPhaseFactorReQmf	Word16	20	sbr_rom.c	Parametric Stereo phase rotation factor
aFractDelayPhaseFactorImQmf	Word16	20	sbr_rom.c	Parametric Stereo phase rotation factor
aFractDelayPhaseFactorReSubQmf	Word16	10	sbr_rom.c	Parametric Stereo phase rotation factor
aFractDelayPhaseFactorImSubQmf	Word16	10	sbr_rom.c	Parametric Stereo phase rotation factor
aFractDelayPhaseFactorSerReQmf0	Word16	20	sbr_rom.c	Parametric Stereo phase rotation factor
aFractDelayPhaseFactorSerReQmf1	Word16	20	sbr_rom.c	Parametric Stereo phase rotation factor
aFractDelayPhaseFactorSerReQmf2	Word16	20	sbr_rom.c	Parametric Stereo phase rotation factor
aFractDelayPhaseFactorSerImQmf0	Word16	20	sbr_rom.c	Parametric Stereo phase rotation factor
aFractDelayPhaseFactorSerImQmf1	Word16	20	sbr_rom.c	Parametric Stereo phase rotation factor
aFractDelayPhaseFactorSerImQmf2	Word16	20	sbr_rom.c	Parametric Stereo phase rotation factor
aFractDelayPhaseFactorSerReSubQmf0	Word16	10	sbr_rom.c	Parametric Stereo phase rotation factor
aFractDelayPhaseFactorSerReSubQmf1	Word16	10	sbr_rom.c	Parametric Stereo phase rotation factor
aFractDelayPhaseFactorSerReSubQmf2	Word16	10	sbr_rom.c	Parametric Stereo phase rotation factor
aFractDelayPhaseFactorSerImSubQmf0	Word16	10	sbr_rom.c	Parametric Stereo phase rotation factor
aFractDelayPhaseFactorSerImSubQmf1	Word16	10	sbr_rom.c	Parametric Stereo phase rotation factor
aFractDelayPhaseFactorSerImSubQmf2	Word16	10	sbr_rom.c	Parametric Stereo phase rotation factor
aaFractDelayPhaseFactorSerReQmf	Word16	3	sbr_rom.c	Parametric Stereo phase rotation factor
aaFractDelayPhaseFactorSerImQmf	Word16	3	sbr_rom.c	Parametric Stereo phase rotation factor
aaFractDelayPhaseFactorSerReSubQmf	Word16	3	sbr_rom.c	Parametric Stereo phase rotation factor
aaFractDelayPhaseFactorSerImSubQmf	Word16	3	sbr_rom.c	Parametric Stereo phase rotation factor
scaleFactors	Word16	15	sbr_rom.c	Parametric Stereo quantization table
scaleFactorsFine	Word16	31	sbr_rom.c	Parametric Stereo quantization table
alphas	Word16	8	sbr_rom.c	Parametric Stereo quantization table
p2_6	Word16	6	sbr_rom.c	Hybrid filterbank coefficients
p8_13	Word16	13	sbr_rom.c	Hybrid filterbank coefficients
sbr_whFactorsTable	Word32	108	sbr_rom.c	Tuning parameters for inverse filtering
sbr_whFactorsIndex	Word16	9	sbr_rom.c	Tuning parameter index for inverse filtering
sbr_start_freq_16	Word8	16	sbr_rom.c	SBR frequency scale index
sbr_start_freq_22	Word8	16	sbr_rom.c	SBR frequency scale index
sbr_start_freq_24	Word8	16	sbr_rom.c	SBR frequency scale index
sbr_start_freq_32	Word8	16	sbr_rom.c	SBR frequency scale index
sbr_start_freq_44	Word8	16	sbr_rom.c	SBR frequency scale index
sbr_start_freq_48	Word8	16	sbr_rom.c	SBR frequency scale index
sbr_frame_info1_16	Word16	18	sbr_rom.c	SBR frequency scale index
sbr_frame_info2_16	Word16	18	sbr_rom.c	SBR frequency scale index
sbr_frame_info4_16	Word16	18	sbr_rom.c	SBR frequency scale index
sbr_huffBook_EnvLevel10T	Word8	120	sbr_rom.c	Huffman codeword table SBR
sbr_huffBook_EnvLevel10F	Word8	120	sbr_rom.c	Huffman codeword table SBR
sbr_huffBook_EnvBalance10T	Word8	48	sbr_rom.c	Huffman codeword table SBR
sbr_huffBook_EnvBalance10F	Word8	48	sbr_rom.c	Huffman codeword table SBR
sbr_huffBook_EnvLevel11T	Word8	62	sbr_rom.c	Huffman codeword table SBR
sbr_huffBook_EnvLevel11F	Word8	62	sbr_rom.c	Huffman codeword table SBR
sbr_huffBook_EnvBalance11T	Word8	24	sbr_rom.c	Huffman codeword table SBR
sbr_huffBook_EnvBalance11F	Word8	24	sbr_rom.c	Huffman codeword table SBR
sbr_huffBook_NoiseLevel11T	Word8	62	sbr_rom.c	Huffman codeword table SBR
sbr_huffBook_NoiseBalance11T	Word8	24	sbr_rom.c	Huffman codeword table SBR
aRevLinkDelaySer	Word8	3	sbr_rom.c	Parametric Stereo all-pass delay line lengths
groupBorders	Word8	23	sbr_rom.c	Borders of Parametric Stereo groups
aGroupToBin	Word8	22	sbr_rom.c	Parametric Stereo group to bin table
aHybridToBin	Word8	10	sbr_rom.c	Parametric Stereo hybrid to bin table
aDelayToBin	Word8	20	sbr_rom.c	Parametric Stereo delay to bin table
aBookPslidTimeDecode	Word8	28	sbr_rom.c	Huffman codeword table Parametric Stereo
aBookPslidFreqDecode	Word8	28	sbr_rom.c	Huffman codeword table Parametric Stereo
aBookPslccTimeDecode	Word8	14	sbr_rom.c	Huffman codeword table Parametric Stereo
aBookPslccFreqDecode	Word8	14	sbr_rom.c	Huffman codeword table Parametric Stereo
aBookPslidFineTimeDecode	Word8	60	sbr_rom.c	Huffman codeword table Parametric Stereo

Name	Data type	Size [16-bit word]	Allocated in Source File	Description
aBookPslidFineFreqDecode	Word8	60	sbr_rom.c	Huffman codeword table Parametric Stereo
sbr_defaultHeader	mixed	22	sbr_rom.c	Default SBR header data
logDualisTable	Word16	65	transcendent.c	Lookup table for efficient log() implementation
invTable	Word16	256	transcendent.c	Lookup table for efficient 1/x implementation
<b>Sum</b>		<b>10 339</b>		

NOTE: All Parametric Stereo related coefficients which are marked as such in the table above are obsolete for mono only capable decoders.

### 4.3.2 Static memory

This clause contains a listing of all static buffers contributing to the RAM requirements of the encoder and decoder.

**Table 9: Encoder static memory**

Name	Data type	Size [16-bit word]	Allocated in Source File	Description
mdctDelayBuffer	Word16	3200	aac_ram.c	Time domain input signal delay , only half the size for mono only encoder
quantSpec	Word16	2048	aac_ram.c	Quantized spectrum, only half the size for mono only encoder
scf	Word16	120	aac_ram.c	Scalefactors, only half the size for mono only encoder
maxValueInSfb	Word16	120	aac_ram.c	Max. value per calefactor, only half the size for mono only encoder
sideInfoTabLong	Word16	52	aac_ram.c	Table lookup for side information, long blocks
sideInfoTabShort	Word16	16	aac_ram.c	Table lookup for side information, short blocks
aacEncoder	AAC_ENCODER	6 851	aacenc.c	AAC encoder instance, can be reduced to 3809 for mono only encoder
sbr_QmfStatesAnalysis	Word16	1 280	sbr_ram.c	QMF filterbank states buffer, only half the size for mono only encoder
sbr_QmfStatesSynthesis	Word32	640	sbr_ram.c	QMF filterbank states buffer, not needed for mono only encoder
sbr_envYBuffer	Word32	8 192	sbr_ram.c	QMF band energy buffer, only half the size for mono only encoder
sbr_quotaMatrix	Word32	1 024	sbr_ram.c	Tonality values. only half the size for mono only encoder
sbr_thresholds	Word32	256	sbr_ram.c	Detector parameters, only half the size for mono only encoder
sbr_toncorrBuff	Word32	2 160	sbr_ram.c	Detector value buffer, only half the size for mono only encoder
ps_lccDataBuffer	Word32	40	sbr_ram.c	ICC buffer, not needed for mono only encoder
ps_lidDataBuffer	Word32	40	sbr_ram.c	lid buffer, not needed for mono only encoder
ps_histQmfBuffer	Word16	1 608	sbr_ram.c	QMF history buffer, not needed for mono only encoder
sbr_freqBandTableLO	Word8	13	sbr_ram.c	SBR frequency band table, low resolution
sbr_freqBandTableHI	Word8	25	sbr_ram.c	SBR frequency band table, high resolution
sbr_v_k_master	Word8	25	sbr_ram.c	SBR frequency band table index
sbr_guideScfb	Word8	27	sbr_ram.c	Additional sine detection parameter, only half the size for mono only encoder
sbr_detectionVectors	Word8	108	sbr_ram.c	Additional sine detection parameter, only half the size for mono only encoder
sbr_prevEnvelopeCompensat	Word8	27	sbr_ram.c	Additional sine detection parameter,

Name	Data type	Size [16-bit word]	Allocated in Source File	Description
ion				only half the size for mono only encoder
sbr_guideVectorDetected	Word8	108	sbr_ram.c	Additional sine detection parameter, only half the size for mono only encoder
sbrEncoder	SBR_ENCODER	3 698	sbr_main.c	SBR encoder instance, can be reduced to 1722 for mono only encoder
outputBuffer	Word8	384	main.c	Bitstream output buffer
inputBuffer	Word16	8 234	main.c	Time domain input signal buffer, only half the size for mono only encoder
up2Sampler	RESAMPLER_FIR_2_1	144	main.c	1:2 FIR resampler instance (includes states) , only half the size for mono only encoder
down3Sampler	RESAMPLER_FIR_3_2	208	main.c	3:2 FIR resampler instance (includes states) , only half the size for mono only encoder
down2Sampler	RESAMPLER_FIR_2_1	144	main.c	2:1 FIR resampler instance (includes states) , only half the size for mono only encoder
<b>Sum</b>		<b>40 792</b>		

Table 10: Decoder static memory

Name	Data type	Size [16-bit word]	Allocated in Source File	Description
OverlapBuffer[nChan]	Word16	1 024	aac_ram.c	Delay buffer for overlap and add, only half the size for mono only decoder
AacDecoderInstance	AAC_DECODER_INSTANCE	12	aacdecoder.c	AAC decoder instance
sbrPayloadBuffer	short	128	aacdecoder.c	SBR payload buffer
StreamInfo	CStreamInfo	7	aac_ram.c	Bitstream information
AacDecoderStaticChannelInfo[nChan]	CaacDecoderStaticChannelInfo	16	aac_ram.c	Channel information, only half the size for mono only decoder
PnsStaticInterChannelData	Word16	2	aac_ram.c	PNS static data
ConcealmentInfoInstance	CConcealmentInfo	4 127	aac_ram.c	Concealment static data
sbr_CodecQmfStatesAnalysis	Word16	640	sbr_ram.c	QMF analysis filter bank states
sbr_GainSmooth_m	Word16	96	sbr_ram.c	Gain smoothing filter states, mantissa
sbr_GainSmooth_e	Word8	96	sbr_ram.c	Gain smoothing filter states, exponent
sbr_NoiseSmooth_m	Word16	96	sbr_ram.c	Noise level smoothing filter states, mantissa
sbr_QmfStatesSynthesis	Word16	2 560	sbr_ram.c	QMF synthesis filter bank states
sbr_OverlapBuffer	Word32	3 072	sbr_ram.c	SBR delay buffer, only half the size for mono only decoder
sbr_LpcFilterStatesReal	Word32	256	sbr_ram.c	LPC filter states
sbr_LpcFilterStatesImag	Word32	256	sbr_ram.c	LPC filter states, obsolete for mono only decoder
sbr_TransposerSettings	TRANSPOSER_SETTINGS	61	sbr_ram.c	Transposer configuration parameters
FreqBandData	FREQ_BAND_DATA	164	sbr_ram.c	SBR Frequency band information
PrevFrameData[nChan]	SBR_PREV_FRAME_DATA	120	sbr_ram.c	SBR previous frame data, only half the size for mono only decoder
sbrDecoderInstance	SBR_DECODER_INSTANCE	797	sbrdecoder.c	SBR decoder instance
timeData	Word16	4 096	main.c	Output buffer for time-domain signal, only half the size for mono only decoder
inBuffer	short	768	main.c	Input buffer for bitstream
splineResamplerInstance	SPLINE_RESAMPLER	19	spline_resampler.c	Spline resampler instance
<b>Sum</b>		<b>18 413</b>		

### 4.3.3 Dynamic memory

This clause contains a listing of all dynamic buffers contributing to the RAM requirements of the encoder and decoder. Dynamic memory can be re-used outside of the encoder or decoder application.

**Table 11: Encoder dynamic memory**

Name	Data type	Size [16-bit word]	Allocated in Source File	Description
ps_tempQmfBuffer	Word16	1 608	sbr_ram.c	NOTE: reused in AAC encoder, not needed for mono only encoder
sbr_envRBuffer	Word16	4 096	sbr_ram.c	NOTE: reused in AAC encoder
sbr_envIBuffer	Word16	4 096	sbr_ram.c	NOTE: reused in AAC encoder
sbr_transients	Word32	384	sbr_ram.c	NOTE: reused in AAC encoder
<b>Sum</b>		<b>10 184</b>		

**Table 12: Decoder dynamic memory**

Name	Data type	Size [16-bit word]	Allocated in Source File	Description
WorkBufferCore	Word32	4 096	aac_ram.c	NOTE: reused in SBR decoder
WorkBuffer1	Word32	4 096	sbr_ram.c	Work buffer, obsolete for mono only decoder
<b>Sum</b>		<b>8 192</b>		

### 4.3.4 Maximum stack size

This clause contains tables for the encoder and the decoder which describe the call stack that results in the maximum stack size usage.









Function	Local variables / Function call arguments	Stack used [16-bit words]
DSP_fft32x32s()	Word32 npoints Word32 *ptr_x	2 1 = 3
__fft32()	Word32 x[] Word16 m; Word32 re, ie, ro, io, rx, ix ; Word32 *x1m, *x2m, *x1mm, *x2mm;	2 1 12 4 = 19
__fft2x16()	Word32 x[] Word16 sch, sh, ch; Word32 a0, a1, a2, a3, a00, a10, a20, a30 ; Word32 tr, ti, vr, vi ; Word32 even [32], odd [32] ;	2 3 16 8 128 = 157
fixmul_32x16b()	Word32 a; Word16 b; Word16 hi1 lo1	2 1 2 = 5
	<b>Sum</b>	<b>919</b>

---

## 5 File formats

This clause describes the file formats used by the encoder and decoder programs.

### 5.1 Audio input file (encoder input/decoder output)

The audio input files read by the encoder and written by the decoder are 16-bit PCM wave files. For convenient handling of wave files a precompiled audio-file format library is used.

### 5.2 Bitstream file format (encoder output/decoder input)

The encoder program writes and the decoder program reads raw frames packetized in access units as described by 3GPP TS 26.244 [10]. For packetization the ISO media library is used. A precompiled library is used.

### 5.3 Error pattern file (decoder input)

The decoder program can optionally process an additional input file which describes an error pattern. The format of the error pattern file is 1 character per line. Each line corresponds to one frame, where a "0" indicates that the respective frame has been transmitted without errors, while a "1" indicates that the corresponding frame has been lost and error concealment shall be applied by the decoder.

## Annex A (Informative): Weighted MOPS

The complexity numbers for the Enhanced aacPlus audio codec can be found in the following table, the numbers have been derived using the "allcat.wav" item, which holds all the material from the selection test concatenated in one single item. For every test case the average and worst frame weighted MOPS figure has been derived. The worst case wMOPS figure over all test cases has been marked in **blue**.

**Table A.1: Weighted MOPS figures**

	Test Case	Mono Encoder	Stereo Encoder	Decoder	Decoder, mono only
<b>wMOPS [average / worst frame]</b>	14m	TBD	25.37 / 27.33	17.05 / 18.97	13.09 / 15.06
	18s	---	52.33 / 55.24	30.98 / 33.73	13.40 / 15.71
	24m	TBD	28.17 / 31.85	18.78 / 21.71	14.23 / 17.13
	24s	---	54.15 / 58.05	32.95 / 36.21	14.17 / 17.04
	32s	---	55.23 / 60.05	33.89 / 37.38	14.72 / 17.93
	48s	---	61.10 / 72.37	29.20 / 35.58	19.39 / 24.27
	14m, 16 kHz	TBD	TBD	11.37 / 12.64	8.72 / 10.04
	14m, 3% FER	---	---	16.95 / 18.97	12.95 / 15.06
	24s, 3% FER	---	---	32.80 / 36.21	14.01 / 17.04
	32s, 1%FER	---	---	33.78 / 37.38	14.58 / 17.93
	32s, 3%FER	---	---	33.31 / 37.38	14.32 / 17.93

---

## Annex B (informative): Change history

Change history							
Date	TSG SA#	TSG Doc.	CR	Rev	Subject/Comment	Old	New
2005-03	27	SP-050084			Presented to TSG SA#27 for approval		1.0.0