

**Agenda item:** Ad hoc 14  
**Source:** Philips  
**Title:** Text proposal and Change Request for rapid DCH initialisation  
**Document for:** Decision

---

## **Introduction**

The current description of the procedure for rapid initialisation of the DCH in TS25.214 leaves the inner loop power control step size during the power control preamble unspecified.

Simulation results in [1] (presented in Ad Hoc 9) have confirmed that a larger initial step size in the power control preamble is beneficial in reducing the required Eb/No and assisting the UE transmit power to converge to the required level as quickly as possible.

The attached Text Proposal and Change Request 25.214-CR005 specifies the initial power control step size for the power control preamble based on the optimal values from the simulation results in [1]. This reduces the large number of negotiable parameters in this procedure.

## **Reference:**

- [1] TSGR1#(99)g23 “*Further simulation results on power control on initialisation (DCH and CPCH)*”, Philips, October 1999

### 3G CHANGE REQUEST

*Please see embedded help file at the bottom of this page for instructions on how to fill in this form correctly.*

**25.214 CR 005**

Current Version: **3.0.0**

3G specification number ↑

↑ CR number as allocated by 3G support team

For submission to TSG **RAN#6**  
*list TSG meeting no. here ↑*

for approval  (only one box should  
for information  be marked with an X)

*Form: 3G CR cover sheet, version 1.0*

*The latest version of this form is available from: ftp://ftp.3gpp.org/Information/3GCRF-xx.rtf*

**Proposed change affects:**

*(at least one should be marked with an X)*

USIM

ME

UTRAN

Core Network

**Source:**

Philips

**Date:**

14-Oct-99

**Subject:**

Rapid DCH initialisation

**3G Work item:**

**Category:**

*(only one category shall be marked with an X)*

- F Correction
- A Corresponds to a correction in a 2G specification
- B Addition of feature
- C Functional modification of feature
- D Editorial modification

<b>X</b>

**Reason for change:**

Feature not fully defined at present.

**Clauses affected:**

7.1 Rapid Initialization of DCH for Packet Data Transfer

**Other specs affected:**

- Other 3G core specifications  → List of CRs:
- Other 2G core specifications  → List of CRs:
- MS test specifications  → List of CRs:
- BSS test specifications  → List of CRs:
- O&M specifications  → List of CRs:

**Other comments:**



help.doc

<----- double-click here for help and instructions on how to create a CR.

---

## 7. Procedures in Packet Data Transfer

### 7.1 Rapid Initialization of DCH for Packet Data Transfer

A rapid initialization procedure for establishing a DCH is defined to support bursting packet data transfer. The rapid initialization may be invoked for downlink packet data transfer on the DSCH or uplink packet data transfer on the DCH. The procedure may also be invoked to resume a recently discontinued DCH connection.

#### 7.1.1 Rapid Initialization of DCH for Packet Data Transfer using DSCH

The synchronization of the DSCH/DCH pair may be expedited so that data transmission using DSCH can commence in slightly over 10 ms following the FACH burst assigning the TFCI using DCH. Figure 3 shows the timing diagram of RACH/FACH to DCH/DCH+DSCH state transition. The parameter  $T_A$  specifies the RACH/FACH response time. The parameters  $T_B$ ,  $T_C$  and  $T_D$  are referenced relative to the FACH frame.  $T_B$  specifies the time period when the downlink DPCCH is started. The parameter  $T_C$  specifies the period at which the UE will start the uplink DPCCH. Finally,  $T_D$  specifies the period that the DCH will be stable and the first frame of data may arrive. The parameters  $T_B$ ,  $T_C$ , and  $T_D$  have the following relationship:

$$T_B < T_C \ll T_D$$

$$T_D = T_B + N_{slots} * 0.666$$

where  $N_{slots}$  is a positive integer.

In order to initialise fast uplink link power control loop, searcher and channel estimator at the Node B, the UE will adhere to the following:

- The transmission of uplink link DPCCH will start at  $N_{slots}$  slots (1 to 15 slots) prior to the scheduled downlink packet data transmission using DSCH.
- The DPCCH will be transmitted with an additional negative power offset  $P_{offset}$  from the computed open loop estimate.
- The initial power control step size for transmitting the DPCCH will be set at  $P_{step}$  (typically: 2dB). The initial power control step size for transmitting the DPCCH differs from that used after  $T_D$ : if inner loop power control algorithm 1 is to be used after  $T_D$ , then the initial step size for the DPCCH is  $\Delta_{TPC-init}$ , where  $\Delta_{TPC-init}$  is equal to the minimum value out of 3 dB and  $2\Delta_{TPC}$ , where  $\Delta_{TPC}$  is the power control step size used for the main part of the transmission (see section 5.1.2.2.1). If inner loop power control algorithm 2 is to be used after  $T_D$ , then inner loop power control algorithm 1 is used initially on the DPCCH, with a step size of 2dB.
- The UE will revert back to the normal power control (PC) step size and algorithm upon the receipt of the first down power control command during the uplink DPCCH transmission phase,
- The step size and algorithm always goes back to their nominal settings in at the beginning of DSCH transmission

The parameters  $T_B$ ,  $T_C$ ,  $T_D$ ,  $N_{slots}$  and  $P_{offset}$  and  $P_{step}$  may be negotiated with each individual UE or broadcast by the system so that the transition from RACH/FACH to DCH/DCH+DSCH sub-state is optimised.

## 7.1.2 Rapid Initialization of DCH for Uplink Packet Data Transfer

The synchronization of the DCH may also be expedited for the transfer of uplink packet data.. Figure 4 shows the same parameters  $T_B$ ,  $T_C$ , and  $T_D$  applied to an uplink packet data transfer. The UE, upon detecting data in its queue, transmits a RACH with measurement report. After the UTRAN assigns the DCH via the FACH message, the downlink DPCCH is started after a time period  $T_B$ . The UE then begins transmission of the uplink DPCCH for reasons as outlined in section 7.3.4 at time period  $T_C$ .  $T_C$  is measured relative to the FACH transmit timing. Finally, the UE begins transmitting the data on the DPDCH after the period  $T_D$ . [The initial power control procedure on the DPCCH is as described in section 7.2.1.](#) The procedure for starting the uplink DPCCH transmission will be similar to Section 7.3.4.1

## 7.1.3 Resumption of DCH for Downlink or Uplink Packet Data Transfer

The synchronization of the DCH technique may be used to resume a DCH/DCH+DSCH connection that has been dropped for a short period.. This is applicable for packet data transfer using DSCH or uplink DPDCH or bi-directional data transfer using DSCH/Uplink DPDCH. Figure 5 shows the case where the DCH has been discontinued based on an inactivity timer  $T_E$ . The UTRAN, upon detecting data in the queue, may resume the DCH operation provided the period  $T_E$  has not elapsed. Typically  $T_E$  is set to 1000ms.