

<h2 style="margin: 0;">CHANGE REQUEST</h2>		<i>Please see embedded help file at the bottom of this page for instructions on how to fill in this form correctly.</i>
<b>25.212</b>	<b>CR</b>	<b>026r1</b>
GSM (AA.BB) or 3G (AA.BBB) specification number ↑		↑ CR number as allocated by MCC support team
For submission to: <b>RAN #6</b> <small>list expected approval meeting # here ↑</small>	for approval for information	Current Version: <b>V3.0.0</b>
	<input checked="" type="checkbox"/>	strategic <input type="checkbox"/> non-strategic <input type="checkbox"/> <small>(for SMG use only)</small>

Form: CR cover sheet, version 2 for 3GPP and SMG      The latest version of this form is available from: <ftp://ftp.3gpp.org/Information/CR-Form-v2.doc>

**Proposed change affects:**      (U)SIM       ME       UTRAN / Radio       Core Network   
(at least one should be marked with an X)

**Source:**      Panasonic      **Date:**      1 Dec 1999

**Subject:**      Corrections to TS 25.212

**Work item:**      TS25.212

<b>Category:</b>	F Correction <input checked="" type="checkbox"/> A Corresponds to a correction in an earlier release <input type="checkbox"/> B Addition of feature <input type="checkbox"/> C Functional modification of feature <input type="checkbox"/> D Editorial modification <input type="checkbox"/>	<b>Release:</b>	Phase 2 <input type="checkbox"/> Release 96 <input type="checkbox"/> Release 97 <input type="checkbox"/> Release 98 <input type="checkbox"/> Release 99 <input checked="" type="checkbox"/> Release 00 <input type="checkbox"/>
------------------	--	-----------------	--

(only one category shall be marked with an X)

**Reason for change:**      Table 1 is updated. Turbo coding for FACH is not limited. It will gain in FER/BER in FACH, to reduce UE complexity and to get network flexibility.

**Clauses affected:**      \_\_\_\_\_

<b>Other specs affected:</b>	Other 3G core specifications <input type="checkbox"/> Other GSM core specifications <input type="checkbox"/> MS test specifications <input type="checkbox"/> BSS test specifications <input type="checkbox"/> O&M specifications <input type="checkbox"/>	→ List of CRs: → List of CRs: → List of CRs: → List of CRs: → List of CRs:	
------------------------------	---	--	--

**Other comments:**      We proposed to send liaison treating this topic. Tdoc No. is R1-99K20.

<----- double-click here for help and instructions on how to create a CR.

## 4.2.1 Channel coding

Code blocks are delivered to the channel coding block. They are denoted by  $O_{ir1}, O_{ir2}, O_{ir3}, \dots, O_{irK_i}$ , where  $i$  is the TrCH number,  $r$  is the code block number, and  $K_i$  is the number of bits in each code block. The number of code blocks on TrCH  $i$  is denoted by  $C_i$ . After encoding the bits are denoted by  $y_{ir1}, y_{ir2}, y_{ir3}, \dots, y_{irY_i}$ . The encoded blocks are serially multiplexed so that the block with lowest index  $r$  is output first from the channel coding block. The bits output are denoted by  $c_{i1}, c_{i2}, c_{i3}, \dots, c_{iE_i}$ , where  $i$  is the TrCH number and  $E_i = C_i Y_i$ . The output bits are defined by the following relations:

$$c_{ik} = y_{i1k} \quad k = 1, 2, \dots, Y_i$$

$$c_{ik} = y_{i,2,(k-Y_i)} \quad k = Y_i + 1, Y_i + 2, \dots, 2Y_i$$

$$c_{ik} = y_{i,3,(k-2Y_i)} \quad k = 2Y_i + 1, 2Y_i + 2, \dots, 3Y_i$$

...

$$c_{ik} = y_{i,C_i,(k-(C_i-1)Y_i)} \quad k = (C_i - 1)Y_i + 1, (C_i - 1)Y_i + 2, \dots, C_i Y_i$$

The relation between  $O_{irk}$  and  $y_{irk}$  and between  $K_i$  and  $Y_i$  is dependent on the channel coding scheme.

The following channel coding schemes can be applied to TrCHs:

- Convolutional coding
- Turbo coding
- No channel coding

The values of  $Y_i$  in connection with each coding scheme:

- Convolutional coding, 1/2 rate:  $Y_i = 2 * K_i + 16$ ; 1/3 rate:  $Y_i = 3 * K_i + 24$
- Turbo coding, 1/3 rate:  $Y_i = 3 * K_i + 12$
- No channel coding,  $Y_i = K_i$

**Table 1: Error Correction Coding Parameters**

Transport channel type	Coding scheme	Coding rate
BCH	Convolutional code	1/2
PCH		
FACH		
RACH		1/3, 1/2 or no coding
CPCH		
DCH	Turbo Code	1/3 or no coding
CPCH		
DCH		

<u>Transport channel type</u>	<u>Coding scheme</u>	<u>Coding rate</u>
<u>BCH</u>	<u>Convolutional code</u>	<u>1/2</u>
<u>PCH</u>		
<u>FACH</u>		
<u>RACH</u>		
<u>CPCH, DCH, DSCH, FACH</u>		<u>1/3, 1/2</u>
	<u>Turbo Code</u>	<u>1/3</u>
	<u>No coding</u>	