

**Source:** TSG CN WG 1  
**Title:** CRs to R99 (with mirror CRs) on Work Item GSM / UMTS interworking towards 24.008  
**Agenda item:** 7.14  
**Document for:** APPROVAL

---

**Introduction:**

This document contains 2 CRs on R99 (with mirror CRs) on Work Item "GSM / UMTS interworking", that was agreed by TSG CN WG1 in Rev2. But based on NP-010243 sent directly to CN#12 from GERAN, the 2 modified GERAN agreed CRs in Rev4 superceeding the CN WG1 CRs are forwarded to TSG CN Plenary meeting #12 for approval.

Spec	CR	Rev	Doc-2nd-Level	Phase	Subject	Cat	Version-Current	Workitem
24.008	402	4	For Rev2 it was N1-010837	R99	Classmark 1,2 and 3 corrections	F	3.7.0	GSM-UMTS interworking
24.008	403	4	For Rev2 it was N1-010838	Rel-4	Classmark 1,2 and 3 corrections	A	4.2.0	GSM-UMTS interworking

## CHANGE REQUEST

⌘ **24.008 CR 402** ⌘ rev **4** ⌘ Current version: **3.7.0** ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

**Proposed change affects:** ⌘ (U)SIM  ME/UE  Radio Access Network  Core Network

<b>Title:</b>	⌘ CLASSMARK1, 2 and 3 corrections.		
<b>Source:</b>	⌘ NEC		
<b>Work item code:</b>	⌘ TEI and GSM-UMTS interworking.	<b>Date:</b>	⌘ 2 <sup>nd</sup> May 2001.
<b>Category:</b>	⌘ F	<b>Release:</b>	⌘ R99
	Use <u>one</u> of the following categories: <b>F</b> (essential correction) <b>A</b> (corresponds to a correction in an earlier release) <b>B</b> (Addition of feature), <b>C</b> (Functional modification of feature) <b>D</b> (Editorial modification) Detailed explanations of the above categories can be found in 3GPP TR 21.900.		Use <u>one</u> of the following releases: <b>2</b> (GSM Phase 2) <b>R96</b> (Release 1996) <b>R97</b> (Release 1997) <b>R98</b> (Release 1998) <b>R99</b> (Release 1999) <b>REL-4</b> (Release 4) <b>REL-5</b> (Release 5)

<b>Reason for change:</b>	⌘ When access is performed via UMTS channels, information on GSM MS capability is <i>not</i> irrelevant as this is used by the RNC for decision on <b>handover from UMTS to GSM</b> .  The required specification of the coding of CLASSMARK doesn't allow the network to distinguish unambiguously single banded GSM mobiles. This may lead to dropped calls if the network can't understand the precise implementation in the mobile.  Also it is impossible for a UMTS mobile not supporting GSM to signal its capability without misleadingly indicate that it supports GSM as well.
<b>Summary of change:</b>	⌘ It is clarified how a single band GSM mobile and a UMTS only mobile need to code the classmarks 1, 2 and 3.
<b>Consequences if not approved:</b>	⌘ There will be a misunderstanding between network and mobile as to what coding schemes and handovers are supported. This can lead to the network attempting to hand the mobile some where or send information which the mobile is unable to decode.

<b>Clauses affected:</b>	⌘ 10.5.1.5, 10.5.1.6 & 10.5.1.7		
<b>Other specs affected:</b>	⌘ <input type="checkbox"/> Other core specifications	⌘ <input type="checkbox"/>	
	<input type="checkbox"/> Test specifications		
	<input type="checkbox"/> O&M Specifications		
<b>Other comments:</b>	⌘ This CR is a copy of that found within Tdoc N1-010620 (GP-010847). It has been created using the most recent reference version of 24.008, but the changes are the same as those identified in N1-010620 (GP-010847). A CR proposing almost		

identical changes for Release 4 appears in CR403.

10.5.1.5 Mobile Station Classmark 1

The purpose of the *Mobile Station Classmark 1* information element is to provide the network with information concerning aspects of high priority of the mobile station equipment. This affects the manner in which the network handles the operation of the mobile station. The Mobile Station Classmark information indicates general mobile station characteristics and it shall therefore, except for fields explicitly indicated, be independent of the frequency band of the channel it is sent on.

The *Mobile Station Classmark 1* information element is coded as shown in figure 10.5.5/3GPP TS 24.008 and table 10.5.5/3GPP TS 24.008.

The *Mobile Station Classmark 1* is a type 3 information element with 2 octets length.

8	7	6	5	4	3	2	1	
Mobile Station Classmark 1 IEI								octet 1
0	Revision	ES	A5/1	RF power				
spare	level	IND		capability				octet 2

**Figure 10.5.5/3GPP TS 24.008 *Mobile Station Classmark 1* information element**

A MS supporting GSM shall always encode all fields relevant for GSM radio access technology, even when accessing UMTS radio access technology. A UMTS MS which does not support GSM shall encode fields relevant only for GSM radio access technology using any value which has been defined for this version of the protocol and is not reserved.

**Table 10.5.5/3GPP TS 24.008: Mobile Station Classmark 1 information element**

Revision level (octet 2)			
<del>Required for MS supporting GSM and UMTS.</del>			
Bits			
<b>7</b>	<b>6</b>		
0	0	Reserved for GSM phase 1	
0	1	Used by GSM phase 2 mobile stations	
1	0	Used by mobile stations supporting R99 or later versions of the protocol	
1	1	Reserved for future use	
ES IND (octet 2, bit 5) "Controlled Early Classmark Sending" option implementation			
<del>Required for MS supporting GSM.</del>			
<u>An MS not supporting GSM shall set this bit to '0'.</u>			
<u>An MS supporting GSM shall indicate the associated GSM capability (see table):</u>			
0	"Controlled Early Classmark Sending" option is not implemented in the MS		
1	"Controlled Early Classmark Sending" option is implemented in the MS		
NOTE:	The value of the ES IND gives the implementation in the MS. It's value is <b>not</b> dependent on the broadcast SI 3 Rest Octet <Early Classmark Sending Control> value.		
A5/1 algorithm supported (octet 2, bit4)			
<del>Required for mobile station supporting GSM.</del>			
<u>An MS not supporting GSM shall set this bit to '1'.</u>			
<u>An MS supporting GSM shall indicate the associated GSM capability (see table):</u>			
0	encryption algorithm A5/1 available		
1	encryption algorithm A5/1 not available		
RF power capability (octet 2)			
<del>Required for mobile stations supporting GSM.</del>			
<u>When GSM 450, GSM 480, GSM 850, GSM 900 P, E [or R] band is used (for exceptions see GSM 04.18), the MS shall indicate the RF power capability of the band used (see table):</u>			
<u>When UMTS is used, a single band GSM 450, GSM 480, GSM 850, GSM 900 P, E [or R] MS shall indicate the RF power capability corresponding to the (GSM) band it supports (see table); in this case information on which single band is supported is found in classmark 3.</u>			
Bits			
<b>3</b>	<b>2</b>	<b>1</b>	
0	0	0	class 1
0	0	1	class 2
0	1	0	class 3
0	1	1	class 4
1	0	0	class 5
All other values are reserved.			
When the DCS 1800 or PCS 1900 band is used (for exceptions see <u>3GPP TS 04.18, sub-clause 3.4.18</u> ), the MS shall indicate the RF power capability of the band used (see table):			
<u>When UMTS is used, a single band DCS1800 or PCS 1900 MS shall indicate the RF power capability corresponding to the (GSM) band it supports (see table); in this case information on which single band is supported is found in classmark 3.</u>			
Bits			
<b>3</b>	<b>2</b>	<b>1</b>	
0	0	0	class 1
0	0	1	class 2
0	1	0	class 3
<u>All other values are reserved.</u>			
<del>All other values are reserved.</del>			
<u>When UMTS is used, an MS not supporting any GSM band or a multiband GSM MS shall code this field as follows (see table):</u>			
Bits			
<b>3</b>	<b>2</b>	<b>1</b>	
1	1	1	<del>Shall be sent.</del> RF Power capability is irrelevant in this information element
<u>All other values are reserved.</u>			

### 10.5.1.6 Mobile Station Classmark 2

The purpose of the *Mobile Station Classmark 2* information element is to provide the network with information concerning aspects of both high and low priority of the mobile station equipment. This affects the manner in which the network handles the operation of the mobile station. The Mobile Station Classmark information indicates general mobile station characteristics and it shall therefore, except for fields explicitly indicated, be independent of the frequency band of the channel it is sent on.

The *Mobile Station Classmark 2* information element is coded as shown in figure 10.5.6/3GPP TS 24.008, table 10.5.6a/3GPP TS 24.008 and table 10.5.6b/3GPP TS 24.008.

The *Mobile Station Classmark 2* is a type 4 information element with 5 octets length.

8	7	6	5	4	3	2	1	
Mobile station classmark 2 IEI								octet 1
Length of mobile station classmark 2 contents								octet 2
0 spare	Revision Level		ES IND	A5/1	RF power capability			octet 3
0 spare	PS capa.	SS Screen. Indicator		SM ca Pabi.	VBS	VGCS	FC	octet 4
CM3	0 spare	LCSVA CAP	UCS2	SoLSA	CMSP	A5/3	A5/2	octet 5

NOTE: Owing to backward compatibility problems, bit 8 of octet 4 should not be used unless it is also checked that the bits 8, 7 and 6 of octet 3 are not "0 0 0".

**Figure 10.5.6/3GPP TS 24.008 Mobile Station Classmark 2 information element**

**Table 10.5.6a/3GPP TS 24.008: Mobile Station Classmark 2 information element**

Revision level (octet 3)		
Required for MS supporting GSM and UMTS.		
Bits		
<b>7</b>	<b>6</b>	
0	0	Reserved for GSM phase 1
0	1	Used by GSM phase 2 mobile stations
1	0	Used by mobile stations supporting R99 or later versions of the protocol
1	1	Reserved for future use
ES IND (octet 3, bit 5) "Controlled Early Classmark Sending" option implementation		
Required for MS supporting GSM.		
An MS not supporting GSM shall set this bit to '0'.		
An MS supporting GSM shall indicate the associated GSM capability (see table):		
0	"Controlled Early Classmark Sending" option is not implemented in the MS	
1	"Controlled Early Classmark Sending" option is implemented in the MS	
NOTE: The value of the ES IND gives the implementation in the MS. It's value is <b>not</b> dependent on the broadcast SI 3 Rest Octet <Early Classmark Sending Control> value		

**Table 10.5.6a/3GPP TS 24.008: Mobile Station Classmark 2 information element**

<p>A5/1 algorithm supported (octet 3, bit 4)                  Required for MS supporting GSM.                  An MS not supporting GSM shall set this bit to '1'.                  An MS supporting GSM shall indicate the associated GSM capability (see table):</p>																									
0	encryption algorithm A5/1 available																								
1	encryption algorithm A5/1 not available																								
<p>RF Power Capability (Octet 3)                  Required for MS supporting GSM.                  When GSM 450, GSM 480, GSM 850, GSM 900 P, E [or R] band is used (for exceptions see GSM 04.18); the MS shall indicate the RF power capability of the band used (see table);                  When UMTS is used, a single band GSM 450, GSM 480, GSM 850, GSM 900 P, E [or R] MS shall indicate the RF power capability corresponding to the (GSM) band it supports (see table); in this case information on which single band is supported is found in classmark 3.</p>																									
<p>Bits</p> <table border="0"> <tr> <td><b>3</b></td> <td><b>2</b></td> <td><b>1</b></td> <td></td> </tr> <tr> <td>0</td> <td>0</td> <td>0</td> <td>Class 1</td> </tr> <tr> <td>0</td> <td>0</td> <td>1</td> <td>Class 2</td> </tr> <tr> <td>0</td> <td>1</td> <td>0</td> <td>Class 3</td> </tr> <tr> <td>0</td> <td>1</td> <td>1</td> <td>Class 4</td> </tr> <tr> <td>1</td> <td>0</td> <td>0</td> <td>Class 5</td> </tr> </table> <p>All other values are reserved.                  All other values are reserved.</p>		<b>3</b>	<b>2</b>	<b>1</b>		0	0	0	Class 1	0	0	1	Class 2	0	1	0	Class 3	0	1	1	Class 4	1	0	0	Class 5
<b>3</b>	<b>2</b>	<b>1</b>																							
0	0	0	Class 1																						
0	0	1	Class 2																						
0	1	0	Class 3																						
0	1	1	Class 4																						
1	0	0	Class 5																						
<p>When the DCS 1800 or PCS 1900 band is used (for exceptions see GSM 04.183); the MS shall indicate the RF power capability of the band used (see table);                  When UMTS is used, a single band DCS1800 or PCS 1900 MS shall indicate the RF power capability corresponding to the (GSM) band it supports (see table); in this case information on which single band is supported is found in classmark 3.</p>																									
<p>Bits</p> <table border="0"> <tr> <td><b>3</b></td> <td><b>2</b></td> <td><b>1</b></td> <td></td> </tr> <tr> <td>0</td> <td>0</td> <td>0</td> <td>Class 1</td> </tr> <tr> <td>0</td> <td>0</td> <td>1</td> <td>Class 2</td> </tr> <tr> <td>0</td> <td>1</td> <td>0</td> <td>Class 3</td> </tr> </table> <p>All other values are reserved.                  All other values are reserved.</p>		<b>3</b>	<b>2</b>	<b>1</b>		0	0	0	Class 1	0	0	1	Class 2	0	1	0	Class 3								
<b>3</b>	<b>2</b>	<b>1</b>																							
0	0	0	Class 1																						
0	0	1	Class 2																						
0	1	0	Class 3																						
<p>When UMTS is used, an MS not supporting any GSM band or a multiband GSM MS shall code this field as follows (see table):</p>																									
<p>Bits</p> <table border="0"> <tr> <td><b>3</b></td> <td><b>2</b></td> <td><b>1</b></td> <td></td> </tr> <tr> <td>1</td> <td>1</td> <td>1</td> <td>Shall be sent; RF Power capability is irrelevant in this information element</td> </tr> </table> <p>All other values are reserved.                  All other values are reserved.</p>		<b>3</b>	<b>2</b>	<b>1</b>		1	1	1	Shall be sent; RF Power capability is irrelevant in this information element																
<b>3</b>	<b>2</b>	<b>1</b>																							
1	1	1	Shall be sent; RF Power capability is irrelevant in this information element																						
<p>PS capability (pseudo-synchronization capability) (octet 4)                  Required for MS supporting GSM                  An MS not supporting GSM shall set this bit to '0'.                  An MS supporting GSM shall indicate the associated GSM capability (see table):</p>																									
<p>Bit 7</p> <table border="0"> <tr> <td>0</td> <td>PS capability not present</td> </tr> <tr> <td>1</td> <td>PS capability present</td> </tr> </table>		0	PS capability not present	1	PS capability present																				
0	PS capability not present																								
1	PS capability present																								
<p>SS Screening Indicator (octet 4)                  Required for MS supporting GSM and UMTS</p>																									
<p>Bits</p> <table border="0"> <tr> <td><b>6</b></td> <td><b>5</b></td> <td></td> </tr> <tr> <td>0</td> <td>0</td> <td>defined in 3GPP TS 24.080</td> </tr> <tr> <td>0</td> <td>1</td> <td>defined in 3GPP TS 24.080</td> </tr> <tr> <td>1</td> <td>0</td> <td>defined in 3GPP TS 24.080</td> </tr> <tr> <td>1</td> <td>1</td> <td>defined in 3GPP TS 24.080</td> </tr> </table>		<b>6</b>	<b>5</b>		0	0	defined in 3GPP TS 24.080	0	1	defined in 3GPP TS 24.080	1	0	defined in 3GPP TS 24.080	1	1	defined in 3GPP TS 24.080									
<b>6</b>	<b>5</b>																								
0	0	defined in 3GPP TS 24.080																							
0	1	defined in 3GPP TS 24.080																							
1	0	defined in 3GPP TS 24.080																							
1	1	defined in 3GPP TS 24.080																							

**Table 10.5.6a/3GPP TS 24.008: Mobile Station Classmark 2 information element**

SM capability (MT SMS pt to pt capability) (octet 4) Required for MS supporting GSM. Bit 4 0 Mobile station does not support mobile terminated point to point SMS 1 Mobile station supports mobile terminated point to point SMS
Table 10.5.6a/3GPP TS 24.008: Mobile Station Classmark 2 information element
VBS notification reception (octet 4) Required for MS supporting GSM. <u>An MS not supporting GSM shall set this bit to '0'.</u> <u>An MS supporting GSM shall indicate the associated GSM capability (see table):</u> Bit 3 0 no VBS capability or no notifications wanted 1 VBS capability and notifications wanted
VGCS notification reception (octet 4) Required for MS supporting GSM. <u>An MS not supporting GSM shall set this bit to '0'.</u> <u>An MS supporting GSM shall indicate the associated GSM capability (see table):</u> Bit 2 0 no VGCS capability or no notifications wanted 1 VGCS capability and notifications wanted
FC Frequency Capability (octet 4) Required for MS supporting GSM. When the GSM 400 or GSM 850 or DCS 1800 or PCS 1900 band or UMTS is used (for exceptions see GSM 04.18, for definitions of frequency band see GSM 05.05), this bit shall be sent with the value '0': Bit 1 0 Reserved for future use (for definition of frequency bands see GSM 05.05) Note: This bit conveys no information about support or non support of the E-GSM or R-GSM bands when transmitted on a GSM 400, GSM 850, DCS1800, PCS1900 band or UMTS is used channel.
When GSM 850 band is used (for exceptions see GSM 04.18): Bit 1 0 Reserved for future use (for definition of frequency bands see GSM 05.05) Note: This bit conveys no information about support or non support of the E-GSM or R-GSM band when transmitted on a GSM 850 channel.
When a GSM 900 band is used (for exceptions see GSM 04.18): Bit 1 0 The MS does not support the E-GSM or R-GSM band (For definition of frequency bands see GSM 05.05) 1 The MS does support the E-GSM or R-GSM (For definition of frequency bands see GSM 05.05) Note: For mobile station supporting the R-GSM band further information can be found in MS Classmark 3.
When the DCS 1800 band is used (for exceptions see GSM 04.18): Bit 1 0 Reserved for future use (for definition of frequency bands see GSM 05.05) Note: This bit conveys no information about support or non support of the E-GSM or R-GSM band when transmitted on a DCS 1800 channel.
When the PCS 1900 band is used (for exceptions see GSM 04.18): Bit 1 0 Reserved for future use (for definition of frequency bands see GSM 05.05) Note: This bit conveys no information about support or non support of the E-GSM or R-GSM band when transmitted on a PCS 1900 channel.



**Table 10.5.6a/3GPP TS 24.008: Mobile Station Classmark 2 information element**

CM3 (octet 5, bit 8)	
<del>Required for MS supporting GSM.</del>	
0	The MS does not support any options that are indicated in CM3
1	The MS supports options that are indicated in classmark 3 IE
LCS VA capability (LCS value added location request notification capability) (octet 5, bit 6)	
<del>Required for MS supporting GSM and UMTS</del>	
0	LCS value added location request notification capability not supported
1	LCS value added location request notification capability supported
UCS2 treatment (octet 5, bit 5)	
<del>Required for MS supporting UMTS.</del>	
This information field indicates the likely treatment by the mobile station of UCS2 encoded character strings. <u>For backward compatibility reasons, if this field is not included, the value 0 shall be assumed by the receiver.</u>	
0	The ME has a preference for the default alphabet (defined in GSM 03.38) over UCS2.
1	The ME has no preference between the use of the default alphabet and the use of UCS2.
SoLSA (octet 5, bit 4)	
<del>Required for MS supporting GSM.</del>	
<u>An MS not supporting GSM shall set this bit to '0'.</u>	
<u>An MS supporting GSM shall indicate the associated GSM capability (see table):</u>	
0	The ME does not support SoLSA.
1	The ME supports SoLSA.
CMSP: CM Service Prompt (octet 5, bit 3) \$(CCBS)\$	
<del>Required for MS supporting GSM and UMTS.</del>	
0	"Network initiated MO CM connection request" not supported.
1	"Network initiated MO CM connection request" supported for at least one CM protocol.
A5/3 algorithm supported (octet 5, bit 2)	
<del>Required for MS supporting GSM.</del>	
<u>An MS not supporting GSM shall set this bit to '0'.</u>	
<u>An MS supporting GSM shall indicate the associated GSM capability (see table):</u>	
0	encryption algorithm A5/3 not available
1	encryption algorithm A5/3 available
A5/2 algorithm supported (octet 5, bit 1)	
<del>Required for MS supporting GSM.</del>	
<u>An MS not supporting GSM shall set this bit to '0'.</u>	
<u>An MS supporting GSM shall indicate the associated GSM capability (see table):</u>	
0	encryption algorithm A5/2 not available
1	encryption algorithm A5/2 available

A MS supporting GSM shall always encode all fields relevant for GSM radio access technology, even when accessing UMTS radio access technology. A UMTS MS which does not support GSM shall encode fields relevant only for GSM radio access technology using any value which has been defined for this version of the protocol and is not reserved.

NOTE: Additional mobile station capability information might be obtained by invoking the classmark interrogation procedure when GSM is used~~the mobile station is accessing the GSM radio access technology.~~

### 10.5.1.7 Mobile Station Classmark 3

The purpose of the *Mobile Station Classmark 3* information element is to provide the network with information concerning aspects of the mobile station. The contents might affect the manner in which the network handles the operation of the mobile station. The Mobile Station Classmark information indicates general mobile station characteristics and it shall therefore, except for fields explicitly indicated, be independent of the frequency band of the channel it is sent on.

The *MS Classmark 3* is a type 4 information element with a maximum of 14 octets length.

The value part of a *MS Classmark 3* information element is coded as shown in figure 10.5.7/3GPP TS 24.008 and table 10.5.7/3GPP TS 24.008.

NOTE: The 14 octet limit is so that the CLASSMARK CHANGE message will fit in one layer 2 frame.

SEMANTIC RULE : a multiband mobile station shall provide information about all frequency bands it can support. A single band mobile station shall not indicate the band it supports in the *Multiband Supported*, *GSM 400 Bands Supported*, *GSM 850 Associated Radio Capability* or *PCS 1900 Associated Radio Capability* fields in the MS Classmark 3. Due to shared radio frequency channel numbers between DCS 1800 and PCS 1900, the mobile should indicate support for either DCS 1800 band OR PCS 1900 band.

SEMANTIC RULE : a mobile station shall include the MS Measurement Capability field if the *Multi Slot Class* field contains a value of 19 or greater (see GSM 05.02).

Typically, the number of spare bits at the end is the minimum to reach an octet boundary. The receiver may add any number of bits set to "0" at the end of the received string if needed for correct decoding.

```

<Classmark 3 Value part> ::=
|
|   < spare bit > [ These 2 lines added are to be removed at the incorporation of CR ]
|   {
|       < Multiband supported : { 000 } > bitmap indicating DCS 1800; EGSM/RGSM; PGSM.
|       < A5 bits >
|       |
|       < Multiband supported : { 101 | 110 } >
|       < A5 bits >
|       < Associated Radio Capability 2 : bit(4) >
|       < Associated Radio Capability 1 : bit(4) >
|       |
|       < Multiband supported : { 001 | 010 | 100 } >
|       < A5 bits >
|       < spare bit >(4)
|       < Associated Radio Capability 1 : bit(4) > }
|   { 0 | 1 < R Support > }
|   { 0 | 1 < Multi Slot Capability > }
|   < UCS2 treatment: bit >
|   < Extended Measurement Capability : bit >
|   { 0 | 1 < MS measurement capability > }
|   { 0 | 1 < MS Positioning Method Capability > }
|   { 0 | 1 < EDGE Multi Slot Capability > }
|   { 0 | 1 < EDGE Struct > }
|   { 0 | 1 < GSM 400 Bands Supported : { 01 | 10 | 11 } >
|       < GSM 400 Associated Radio Capability: bit(4) > }
|
|   { 0 | 1 <GSM 850 Associated Radio Capability : bit(4) > }
|   { 0 | 1 <PCS 1900 Associated Radio Capability : bit(4) > }
|   < UMTS FDD Radio Access Technology Capability : bit >
|   < UMTS TDD Radio Access Technology Capability : bit >
|   < CDMA 2000 Radio Access Technology Capability : bit >
|
|   { 0 | 1 < DTM GPRS Multi Slot Sub-Class : bit(2) >
|       < MAC Mode Support : bit >
|       _____ { 0 | 1 < EGPRS Support : bit-DTM EGPRS Multi Slot Sub-Class : bit(2) > } }
|   { 0 | 1 < Single Band Support > }
|   < spare bit >*_ ;

< A5 bits > ::=
    < A5/7 : bit > < A5/6 : bit > < A5/5 : bit > < A5/4 : bit > ;

<R Support>::=
    < R-GSM band Associated Radio Capability : bit(3) > ;

< Multi Slot Capability > ::=
    < Multi Slot Class : bit(5) > ;

< MS Measurement capability > ::=
    < SMS_VALUE : bit (4) >
    < SM_VALUE : bit (4) > ;

< MS Positioning Method Capability > ::=
    < MS Positioning Method : bit(5) > ;

< EDGE Multi Slot Capability > ::=
    < EDGE Multi Slot Class : bit(5) > ;

<EDGE Struct> ::=
    < Modulation Capability : bit >
    { 0 | 1 < EDGE RF Power Capability 1: bit(2) > }
    { 0 | 1 < EDGE RF Power Capability 2: bit(2) > };

< Single Band Support > ::=
    < GSMBand : bit(4) > ;

```

**Figure 10.5.7/3GPP TS 24.008 Mobile Station Classmark 3 information element**

**Table 10.5.7/3GPP TS 24.008: Mobile Station Classmark 3 information element**

Multiband Supported (3 bit field)		
Band 1 supported (third bit of the field)		
<u>Bit</u>	<u>3</u>	
0		P-GSM not supported
1		P-GSM supported
Band 2 supported (second bit of the field)		
<u>BIT</u>	<u>2</u>	
0		E-GSM or R-GSM not supported
1		E-GSM or R-GSM supported
Band 3 supported (first bit of the field)		
<u>Bit</u>	<u>1</u>	
0		DCS 1800 not supported
1		DCS 1800 supported
The indication of support of P-GSM band or E-GSM or R-GSM band is mutually exclusive.		
When the 'Band 2 supported' bit indicates support of E-GSM or R-GSM, the presence of the <R Support> field, see below, indicates if the E-GSM or R-GSM band is supported.		
In this version of the protocol, the sender indicates in this field either none, one or two of these 3 bands supported. If only one band is indicated, the receiver shall ignore the Associated Radio Capability 2.		
<u>For single band mobile station or a mobile station supporting none of the GSM 900 bands(P-GSM, E-GSM and R-GSM)P-GSM (and hence none of E-GSM and R-GSM) and DCS1800 bands, all bits are set to 0.</u>		
A5/4		
<u>Bit</u>	<u>1</u>	
0		Encryption algorithm A5/4 not available
1		Encryption algorithm A5/4 available
A5/5		
<u>Bit</u>	<u>1</u>	
0		Encryption algorithm A5/5 not available
1		Encryption algorithm A5/5 available
A5/6		
<u>Bit</u>	<u>1</u>	
0		Encryption algorithm A5/6 not available
1		Encryption algorithm A5/6 available
A5/7		
0		Encryption algorithm A5/7 not available
1		Encryption algorithm A5/7 available
Associated Radio capability 1 and 2 (4 bit fields)		
If either of P-GSM or E-GSM or R-GSM is supported, the radio capability 1 field indicates the radio capability for P-GSM, E-GSM or R-GSM, and the radio capability 2 field indicates the radio capability for DCS1800 if supported, and is spare otherwise.		
If none of P-GSM or E-GSM or R-GSM are supported, the radio capability 1 field indicates the radio capability for DCS1800, and the radio capability 2 field is spare.		
The radio capability contains the binary coding of the power class associated with the band indicated in multiband support bits (see GSM_05.05).		

(continued...)

**Table 10.5.1.7/3GPP TS 24.008 (continued): MS Classmark 3 information element**

**R Support**

In case where the R-GSM band is supported the R-GSM band associated radio capability field contains the binary coding of the power class associated (see GSM 05.05) (regardless of the number of GSM bands supported). A mobile station supporting the R-GSM band shall also when appropriate, (see 10.5.1.6) indicate its support in the 'FC' bit in the Mobile Station Classmark 2 information element.

Note: the coding of the power class for P-GSM, E-GSM, R-GSM and DCS 1800 in radio capability 1 and/or 2 is different to that used in the Mobile Station Classmark 1 and Mobile Station Classmark 2 information elements.

**Multi Slot Class (5 bit field)**

In case the MS supports the use of multiple timeslots then the Multi Slot Class field is coded as the binary representation of the multislots class defined in 3GPP TS GSM 05.02.

**UCS2 treatment (1 bit field)**

This information field indicates the likely treatment by the mobile station of UCS2 encoded character strings. If not included, the value 0 shall be assumed by the receiver.

Bit	1	
	0	the ME has a preference for the default alphabet (defined in GSM 03.38) over UCS2.
	1	the ME has no preference between the use of the default alphabet and the use of UCS2.

**Extended Measurement Capability (1 bit field)**

This bit indicates whether the mobile station supports 'Extended Measurements' or not

Bit	1	
	0	the MS does not support Extended Measurements
	1	the MS supports Extended Measurements

**SMS\_VALUE (Switch-Measure-Switch) (4 bit field)**

The SMS field indicates the time needed for the mobile station to switch from one radio channel to another, perform a neighbour cell power measurement, and the switch from that radio channel to another radio channel.

Bits		
4 3 2 1	0 0 0 0	1/4 timeslot (~144 microseconds)
	0 0 0 1	2/4 timeslot (~288 microseconds)
	0 0 1 0	3/4 timeslot (~433 microseconds)
	...	
	1 1 1 1	16/4 timeslot (~2307 microseconds)

**SM\_VALUE (Switch-Measure) (4 bit field)**

The SM field indicates the time needed for the mobile station to switch from one radio channel to another and perform a neighbour cell power measurement.

Bits		
4 3 2 1	0 0 0 0	1/4 timeslot (~144 microseconds)
	0 0 0 1	2/4 timeslot (~288 microseconds)
	0 0 1 0	3/4 timeslot (~433 microseconds)
	...	
	1 1 1 1	16/4 timeslot (~2307 microseconds)

**MS Positioning Method Capability (1 bit field)**

This bit indicates whether the MS supports Positioning Method or not for the provision of Location Services.

**MS Positioning Method (5 bit field)**

This field indicates the Positioning Method(s) supported by the mobile station.

**MS assisted E-OTD**

Bit	5	
	0	MS assisted E-OTD not supported
	1	MS assisted E-OTD supported

**Table 10.5.1.7/3GPP TS 24.008 (continued): MS Classmark 3 information element**

<u>MS based E-OTD</u>		
Bit	4	
0		MS based E-OTD not supported
1		MS based E-OTD supported
<u>MS assisted GPS</u>		
Bit	3	
0		MS assisted GPS not supported
1		MS assisted GPS supported
<u>MS based GPS</u>		
Bit	2	
0		MS based GPS not supported
1		MS based GPS supported
<u>MS conventional GPS</u>		
Bit	1	
0		conventional GPS not supported
1		conventional GPS supported
<b>EDGE Multi Slot class (5 bit field)</b>		
In case the EDGE MS supports the use of multiple timeslots and the number of supported time slots is different from number of time slots supported for GMSK then the EDGE Multi Slot class field is included and is coded as the binary representation of the multislot class defined in 3GPP TS GSM 05.02.		
<b>Modulation Capability</b>		
Modulation Capability field indicates the supported modulation scheme by MS in addition to GMSK		
Bit	1	
0		8-PSK supported for downlink reception only
1		8-PSK supported for uplink transmission and downlink reception
<b>EDGE RF Power Capability 1 (2 bit field)</b>		
If 8-PSK is supported for both uplink and downlink, the <b>EDGE RF Power Capability 1</b> field indicates the radio capability for GSM900.		
The radio capability contains the binary coding of the EDGE power class(see GSM05.05).		
<b>EDGE RF Power Capability 2 (2 bit field)</b>		
If 8-PSK is supported for both uplink and downlink, the <b>EDGE RF Power Capability 2</b> field indicates the radio capability for DCS1800 or PCS1900 if supported, and is not included otherwise.		
The radio capability contains the binary coding of the EDGE power class (see GSM 05.05).		

**Table 10.5.1.7/3GPP TS 24.008 (continued): MS Classmark 3 information element**

**GSM 400 Bands Supported (2 bit field)**

See the semantic rule for the sending of this field.

Bits

2 1

0 1	GSM 480 supported, GSM 450 not supported
1 0	GSM 450 supported, GSM 480 not supported
1 1	GSM 450 supported, GSM 480 supported

**GSM 400 Associated Radio Capability (4 bit field)**

If either GSM 450 or GSM 480 or both is supported, the GSM 400 Associated Radio Capability field indicates the radio capability for GSM 450 and/or GSM 480.

The radio capability contains the binary coding of the power class associated with the band indicated in GSM 400 Bands Supported bits (see GSM 05.05).

Note: the coding of the power class for GSM 450 and GSM 480 in GSM 400 Associated Radio Capability is different to that used in the Mobile Station Classmark 1 and Mobile Station Classmark 2 information elements.

**GSM 850 Associated Radio Capability (4 bit field)**

See the semantic rule for the sending of this field. This field indicates whether GSM 850 band is supported and its associated radio capability.

The radio capability contains the binary coding of the power class associated with the GSM 850 band (see GSM 05.05).

Note: the coding of the power class for GSM 850 in GSM 850 Associated Radio Capability is different to that used in the Mobile Station Classmark 1 and Mobile Station Classmark 2 information elements.

**PCS 1900 Associated Radio Capability (4 bit field)**

See the semantic rule for the sending of this field. This field indicates whether PCS 1900 band is supported and its associated radio capability.

The radio capability contains the binary coding of the power class associated with the PCS 1900 band (see GSM 05.05).

Note: the coding of the power class for PCS 1900 in PCS 1900 Associated Radio Capability is different to that used in the Mobile Station Classmark 1 and Mobile Station Classmark 2 information elements.

**Table 10.5.1.7/3GPP TS 24.008 (continued): MS Classmark 3 information element**

<b>UMTS FDD Radio Access Technology Capability (1 bit field)</b>	
Bit	1
0	UMTS FDD not supported
1	UMTS FDD supported
<b>UMTS TDD Radio Access Technology Capability (1 bit field)</b>	
Bit	1
0	UMTS TDD not supported
1	UMTS TDD supported
<b>CDMA 2000 Radio Access Technology Capability (1 bit field)</b>	
Bit	1
0	CDMA2000 not supported
1	CDMA2000 supported
<b>DTM GPRS Multi Slot Sub-Class (2 bit field)</b>	
This field indicates the GPRS DTM capabilities of the MS. The DTM GPRS Multi Slot Sub-Class is independent from the Multi Slot Capabilities field. It is coded as follows:	
Bit	2 1
0 0	Sub-Class 1 supported
0 1	Sub-Class 5 supported
1 0	Sub-Class 9 supported
1 1	Reserved for future extension. If received, the network shall interpret this as '00'
<b>DTM EGPRS Multi Slot Sub-Class (2 bit field)</b>	
This field indicates the EGPRS DTM capabilities of the MS. The DTM EGPRS Multi Slot Sub-Class is independent from the Multi Slot Capabilities field. This field shall be included only if the mobile station supports EGPRS DTM. This field is coded as the DTM GPRS Multi Slot Sub-Class field.	
<b>MAC Mode Support (1 bit field)</b>	
This field indicates whether the MS supports Dynamic and Fixed Allocation or only supports Exclusive Allocation. It is coded as follows:	
Bit	1
0	Dynamic and Fixed Allocation not supported
1	Dynamic and Fixed allocation supported
<b><u>Single Band Support</u></b>	
<u>This field shall be sent if the mobile station supports UMTS and one and only one GSM band with the exception of R-GSM; this field shall not be sent otherwise.</u>	
<b><u>GSMBand (4 bit field)</u></b>	
Bits	
4 3 2 1	
0 0 0 0	<u>E-GSM is supported</u>
0 0 0 1	<u>P-GSM is supported</u>
0 0 1 0	<u>DCS 1800 is supported</u>
0 0 1 1	<u>GSM 450 is supported</u>
0 1 0 0	<u>GSM 480 is supported</u>
0 1 0 1	<u>GSM 850 is supported</u>
0 1 1 0	<u>PCS 1900 is supported</u>
<u>All other values are reserved for future use.</u>	
<b>NOTE:</b> When this field is received, the associated RF Power capability is found in Classmark1 or 2.	



## 9.1.11 Classmark change

This message is sent on the main DCCH by the mobile station to the network to indicate a classmark change or as a response to a classmark enquiry. See Table 9.1.11.1/3GPP TS 04.18.

Message type: CLASSMARK CHANGE

Significance: dual

Direction: mobile station to network

**Table 9.1.11.1/3GPP TS 04.18: CLASSMARK CHANGE message content**

IEI	Information element	Type / Reference	Presence	Format	length
	RR management Protocol Discriminator	Protocol Discriminator 10.2	M	V	1/2
	Skip Indicator	Skip Indicator 10.3.1	M	V	1/2
	Classmark Change Message Type	Message Type 10.4	M	V	1
	Mobile Station Classmark	Mobile Station Classmark 2 10.5.1.6	M	LV	4
20	Additional Mobile Station Classmark Information	Mobile Station Classmark 3 10.5.1.7	C	TLV	3-14

### 9.1.11.1 Additional Mobile Station Classmark Information

This IE shall be included if and only if the CM3 bit in the *Mobile Station Classmark* IE is set to 1.

### 9.1.11.2 Mobile Station Classmark

This IE shall include for multiband MS the Classmark 2 corresponding to the frequency band in use.

CR-Form-v3

## CHANGE REQUEST

⌘ **24.008 CR 403** ⌘ rev **43** ⌘ Current version: **4.2.0** ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

**Proposed change affects:** ⌘ (U)SIM  ME/UE  Radio Access Network  Core Network

<b>Title:</b>	⌘ CLASSMARK1, 2 and 3 corrections.		
<b>Source:</b>	⌘ NEC		
<b>Work item code:</b>	⌘ TEI	<b>Date:</b>	⌘ 2 <sup>nd</sup> May 2001
<b>Category:</b>	⌘ <b>A</b>	<b>Release:</b>	⌘ REL-4
Use <u>one</u> of the following categories: <b>F</b> (essential correction) <b>A</b> (corresponds to a correction in an earlier release) <b>B</b> (Addition of feature), <b>C</b> (Functional modification of feature) <b>D</b> (Editorial modification) Detailed explanations of the above categories can be found in 3GPP TR 21.900.		Use <u>one</u> of the following releases: 2 (GSM Phase 2) R96 (Release 1996) R97 (Release 1997) R98 (Release 1998) R99 (Release 1999) REL-4 (Release 4) REL-5 (Release 5)	

<b>Reason for change:</b>	⌘ When access is performed via UMTS channels, information on GSM MS capability is <i>not</i> irrelevant as this is used by the RNC for decision on <b>handover from UMTS to GSM</b> .  The required specification of the coding of CLASSMARK doesn't allow the network to distinguish unambiguously single banded GSM mobiles. This may lead to dropped calls if the network can't understand the precise implementation in the mobile.  Also it is impossible for a UMTS mobile not supporting GSM to signal its capability without misleadingly indicate that it supports GSM as well.
<b>Summary of change:</b>	⌘ It is clarified how a single band GSM mobile and a UMTS only mobile need to code the classmarks 1, 2 and 3.
<b>Consequences if not approved:</b>	⌘ There will be a misunderstanding between network and mobile as to what coding schemes and handovers are supported. This can lead to the network attempting to hand the mobile some where or send information which the mobile is unable to decode.

<b>Clauses affected:</b>	⌘ 10.5.1.5, 10.5.1.6 & 10.5.1.7		
<b>Other specs affected:</b>	⌘ <input type="checkbox"/> Other core specifications	⌘	
	<input type="checkbox"/> Test specifications		
	<input type="checkbox"/> O&M Specifications		
<b>Other comments:</b>	⌘ An almost identical CR against Release 99 appears in CR402		

How to create CRs using this form:

Comprehensive information and tips about how to create CRs can be found at: [http://www.3gpp.org/3G\\_Specs/CRs.htm](http://www.3gpp.org/3G_Specs/CRs.htm). Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://www.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2000-09 contains the specifications resulting from the September 2000 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

### 10.5.1.5 Mobile Station Classmark 1

The purpose of the *Mobile Station Classmark 1* information element is to provide the network with information concerning aspects of high priority of the mobile station equipment. This affects the manner in which the network handles the operation of the mobile station. The Mobile Station Classmark information indicates general mobile station characteristics and it shall therefore, except for fields explicitly indicated, be independent of the frequency band of the channel it is sent on.

The *Mobile Station Classmark 1* information element is coded as shown in figure 10.5.5/3GPP TS 24.008 and table 10.5.5/3GPP TS 24.008.

The *Mobile Station Classmark 1* is a type 3 information element with 2 octets length.

8	7	6	5	4	3	2	1	
Mobile Station Classmark 1 IEI								octet 1
0	Revision	ES	A5/1	RF power				
spare	level	IND		capability				octet 2

**Figure 10.5.5/3GPP TS 24.008 *Mobile Station Classmark 1* information element**

~~A MS supporting GSM shall always encode all fields relevant for GSM radio access technology, even when accessing UMTS radio access technology. A UMTS MS which does not support GSM shall encode fields relevant only for GSM radio access technology using any value which has been defined for this version of the protocol and is not reserved.~~

**Table 10.5.5/3GPP TS 24.008: Mobile Station Classmark 1 information element**

Revision level (octet 2)			
Required for MS supporting GSM and UMTS.			
Bits			
<b>7</b>	<b>6</b>		
0	0	Reserved for GSM phase 1	
0	1	Used by GSM phase 2 mobile stations	
1	0	Used by mobile stations supporting R99 or later versions of the protocol	
1	1	Reserved for future use	
ES IND (octet 2, bit 5) "Controlled Early Classmark Sending" option implementation			
Required for MS supporting GSM.			
An MS not supporting GSM shall set this bit to '0'.			
An MS supporting GSM shall indicate the associated GSM capability (see table):			
0	"Controlled Early Classmark Sending" option is not implemented in the MS		
1	"Controlled Early Classmark Sending" option is implemented in the MS		
NOTE:	The value of the ES IND gives the implementation in the MS. It's value is <b>not</b> dependent on the broadcast SI 3 Rest Octet <Early Classmark Sending Control> value.		
A5/1 algorithm supported (octet 2, bit4)			
Required for mobile station supporting GSM.			
An MS not supporting GSM shall set this bit to '1'.			
An MS supporting GSM shall indicate the associated GSM capability (see table):			
0	Encryption algorithm A5/1 available		
1	Encryption algorithm A5/1 not available		
RF power capability (octet 2)			
Required for mobile stations supporting GSM.			
<u>When GSM 450, GSM 480, GSM 700, GSM 850, GSM 900 P, E [or R] band is used (for exceptions see 04.18), the MS shall indicate the RF power capability of the band used (see table):</u>			
<u>When UMTS is used, a single band GSM 450, GSM 480, GSM 700, GSM 850, GSM 900 P, E [or R] MS shall indicate the RF power capability corresponding to the (GSM) band it supports (see table). In this case information on which single band is supported is found in classmark 3.</u>			
Bits			
<b>3</b>	<b>2</b>	<b>1</b>	
0	0	0	class 1
0	0	1	class 2
0	1	0	class 3
0	1	1	class 4
1	0	0	class 5
All other values are reserved.			
When the DCS 1800 or PCS 1900 band is used (for exceptions see 3GPP TS 44.018, sub-clause 3.4.18), the MS shall indicate the RF power capability of the band used (see table):			
When UMTS is used, a single band DCS 1800 or PCS 1900 MS shall indicate the RF power capability corresponding to the (GSM) band it supports (see table). In this case, information on which single band is supported is found in classmark 3.			
Bits			
<b>3</b>	<b>2</b>	<b>1</b>	
0	0	0	class 1
0	0	1	class 2
0	1	0	class 3
All other values are reserved.			

When UMTS is used, an MS not supporting any GSM band or a multiband GSM MS shall code this field as follows (see table):

Bits

**3 2 1**

**1 1 1** RF power capability is irrelevant in this information element.  
All other values are reserved.

### 10.5.1.6 Mobile Station Classmark 2

The purpose of the *Mobile Station Classmark 2* information element is to provide the network with information concerning aspects of both high and low priority of the mobile station equipment. This affects the manner in which the network handles the operation of the mobile station. The Mobile Station Classmark information indicates general mobile station characteristics and it shall therefore, except for fields explicitly indicated, be independent of the frequency band of the channel it is sent on.

The *Mobile Station Classmark 2* information element is coded as shown in figure 10.5.6/3GPP TS 24.008, table 10.5.6a/3GPP TS 24.008 and table 10.5.6b/3GPP TS 24.008.

The *Mobile Station Classmark 2* is a type 4 information element with 5 octets length.

8	7	6	5	4	3	2	1	
Mobile station classmark 2 IEI								octet 1
Length of mobile station classmark 2 contents								octet 2
0 spare	Revision level		ES IND	A5/1	RF power Capability			octet 3
0 spare	PS capa.	SS Screen. Indicator		SM ca pabi.	VBS	VGCS	FC	octet 4
CM3	0 spare	LCSVA CAP	UCS2	SoLSA	CMSP	A5/3	A5/2	octet 5

NOTE: Owing to backward compatibility problems, bit 8 of octet 4 should not be used unless it is also checked that the bits 8, 7 and 6 of octet 3 are not "0 0 0".

**Figure 10.5.6/3GPP TS 24.008 Mobile Station Classmark 2 information element**

**Table 10.5.6a/3GPP TS 24.008: Mobile Station Classmark 2 information element**

Revision level (octet 3)	
Required for MS supporting GSM and UMTS.	
Bits	
<b>7 6</b>	
0 0	Reserved for GSM phase 1
0 1	Used by GSM phase 2 mobile stations
1 0	Used by mobile stations supporting R99 or later versions of the protocol
1 1	Reserved for future use
ES IND (octet 3, bit 5) "Controlled Early Classmark Sending" option implementation	
Required for MS supporting GSM.	
AN MS not supporting GSM shall set this bit to '0'.	
An MS supporting GSM shall indicate the associated GSM capability (see table):	
0	"Controlled Early Classmark Sending" option is not implemented in the MS
1	"Controlled Early Classmark Sending" option is implemented in the MS
NOTE:	The value of the ES IND gives the implementation in the MS. It's value is <b>not</b> dependent on the broadcast SI 3 Rest Octet <Early Classmark Sending Control> value

**Table 10.5.6a/3GPP TS 24.008: Mobile Station Classmark 2 information element**

<p>A5/1 algorithm supported (octet 3, bit 4)  <u>Required for MS supporting GSM.</u>  <u>An MS not supporting GSM shall set this bit to '1'.</u>  <u>An MS supporting GSM shall indicate the associated GSM capability (see table)</u></p>																									
0	encryption algorithm A5/1 available																								
1	encryption algorithm A5/1 not available																								
<p>RF Power Capability (Octet 3)  <u>Required for MS supporting GSM.</u>  <u>When GSM 450, GSM 480, GSM 700, GSM 850, GSM 900 P, E [or R] band is used (for exceptions see 3GPP TS 44.018), the MS shall indicate the RF power capability of the band used (see table).</u>  <u>When UMTS is used, a single band GSM 450, GSM 480, GSM 700, GSM 850, GSM 900 P, E [or R] MS shall indicate the RF power capability corresponding to the (GSM) band it supports (see table).</u> In this case, information on which single band is supported is found in classmark 3.:</p>																									
<p>Bits</p> <table border="1"> <thead> <tr> <th>3</th> <th>2</th> <th>1</th> <th></th> </tr> </thead> <tbody> <tr> <td>0</td> <td>0</td> <td>0</td> <td>class 1</td> </tr> <tr> <td>0</td> <td>0</td> <td>1</td> <td>class 2</td> </tr> <tr> <td>0</td> <td>1</td> <td>0</td> <td>class 3</td> </tr> <tr> <td>0</td> <td>1</td> <td>1</td> <td>class 4</td> </tr> <tr> <td>1</td> <td>0</td> <td>0</td> <td>class 5</td> </tr> </tbody> </table>		3	2	1		0	0	0	class 1	0	0	1	class 2	0	1	0	class 3	0	1	1	class 4	1	0	0	class 5
3	2	1																							
0	0	0	class 1																						
0	0	1	class 2																						
0	1	0	class 3																						
0	1	1	class 4																						
1	0	0	class 5																						
<p>All other values are reserved.</p> <p><u>When the DCS 1800 or PCS 1900 band is used (for exceptions see 344.018): The MS shall indicate the RF power capability of the band used (see table).</u>  <u>When UMTS is used, a single band DCS 1800 or PCS 1900 MS shall indicate the RF power capability corresponding to the (GSM) band it supports (see table).</u> In this case, information on which single band is supported is found in classmark 3.</p>																									
<p>Bits</p> <table border="1"> <thead> <tr> <th>3</th> <th>2</th> <th>1</th> <th></th> </tr> </thead> <tbody> <tr> <td>0</td> <td>0</td> <td>0</td> <td>class 1</td> </tr> <tr> <td>0</td> <td>0</td> <td>1</td> <td>class 2</td> </tr> <tr> <td>0</td> <td>1</td> <td>0</td> <td>class 3</td> </tr> </tbody> </table>		3	2	1		0	0	0	class 1	0	0	1	class 2	0	1	0	class 3								
3	2	1																							
0	0	0	class 1																						
0	0	1	class 2																						
0	1	0	class 3																						
<p>All other values are reserved.</p> <p><u>When UMTS is used, an MS not supporting any GSM band or a multiband GSM MS shall code this field as follows (see table):</u></p>																									
<p>Bits</p> <table border="1"> <thead> <tr> <th>3</th> <th>2</th> <th>1</th> <th></th> </tr> </thead> <tbody> <tr> <td>1</td> <td>1</td> <td>1</td> <td><u>RF Power capability is irrelevant in this information element</u></td> </tr> </tbody> </table> <p><u>All other values are reserved.</u></p>		3	2	1		1	1	1	<u>RF Power capability is irrelevant in this information element</u>																
3	2	1																							
1	1	1	<u>RF Power capability is irrelevant in this information element</u>																						
<p>PS capability (pseudo-synchronization capability) (octet 4)  <u>Required for MS supporting GSM</u>  <u>An MS not supporting GSM shall set this bit to '0'.</u>  <u>An MS supporting GSM shall indicate the associated GSM capability (see table):</u></p>																									
<p>Bit 7</p> <table border="1"> <tbody> <tr> <td>0</td> <td>PS capability not present</td> </tr> <tr> <td>1</td> <td>PS capability present</td> </tr> </tbody> </table>		0	PS capability not present	1	PS capability present																				
0	PS capability not present																								
1	PS capability present																								
<p>SS Screening Indicator (octet 4)  <u>Required for MS supporting GSM and UMTS</u></p>																									
<p>Bits</p> <table border="1"> <thead> <tr> <th>6</th> <th>5</th> <th></th> </tr> </thead> <tbody> <tr> <td>0</td> <td>0</td> <td>defined in 3GPP TS 24.080</td> </tr> <tr> <td>0</td> <td>1</td> <td>defined in 3GPP TS 24.080</td> </tr> <tr> <td>1</td> <td>0</td> <td>defined in 3GPP TS 24.080</td> </tr> <tr> <td>1</td> <td>1</td> <td>defined in 3GPP TS 24.080</td> </tr> </tbody> </table>		6	5		0	0	defined in 3GPP TS 24.080	0	1	defined in 3GPP TS 24.080	1	0	defined in 3GPP TS 24.080	1	1	defined in 3GPP TS 24.080									
6	5																								
0	0	defined in 3GPP TS 24.080																							
0	1	defined in 3GPP TS 24.080																							
1	0	defined in 3GPP TS 24.080																							
1	1	defined in 3GPP TS 24.080																							

**Table 10.5.6a/3GPP TS 24.008: Mobile Station Classmark 2 information element**

<p>SM capability (MT SMS pt to pt capability) (octet 4)                  Required for MS supporting GSM.  <b>Bit 4</b>                  0 Mobile station does not support mobile terminated point to point SMS                  1 Mobile station supports mobile terminated point to point SMS</p>
<p><del>Table 10.5.6a/3GPP TS 24.008: Mobile Station Classmark 2 information element</del></p>
<p>VBS notification reception (octet 4)                  Required for MS supporting GSM.  <u>An MS not supporting GSM shall set this bit to '0'.</u>  <u>An MS supporting GSM shall indicate the associated GSM capability (see table):</u></p> <p><b>Bit 3</b>                  0 no VBS capability or no notifications wanted                  1 VBS capability and notifications wanted</p>
<p>VGCS notification reception (octet 4)                  Required for MS supporting GSM.  <u>An MS not supporting GSM shall set this bit to '0'.</u>  <u>An MS supporting GSM shall indicate the associated GSM capability (see table):</u></p> <p><b>Bit 2</b>                  0 no VGCS capability or no notifications wanted                  1 VGCS capability and notifications wanted</p>
<p>FC Frequency Capability (octet 4)                  Required for MS supporting GSM.                  When <u>the GSM 400, or GSM 700, or GSM 850, or DCS 1800, or PCS 1900 band or UMTS band</u> is used (for exceptions see 3GPP TS 44.018, for definitions of frequency band see 3GPP TS 45.005), <u>this bit shall be sent with the value '0':</u></p> <p><b>Bit 1</b>                  0 Reserved for future use (for definition of frequency bands see 3GPP TS 05.05)</p> <p>Note: This bit conveys no information about support or non support of the E-GSM or R-GSM bands when transmitted on a <u>GSM 400, GSM 700, GSM 850, DCS 1800, PCS 1900 band or UMTS is used channel.</u></p> <p>When GSM 700 band is used (for exceptions see 3GPP TS 44.018):  <b>Bit 1</b>                  0 Reserved for future use (for definition of frequency bands see 3GPP TS 05.05)</p> <p>Note: This bit conveys no information about support or non support of the E-GSM or R-GSM band when transmitted on a GSM 700 channel.</p> <p>When GSM 850 band is used (for exceptions see 3GPP TS 44.018):  <b>Bit 1</b>                  0 Reserved for future use (for definition of frequency bands see 3GPP TS 05.05)</p> <p>Note: This bit conveys no information about support or non support of the E-GSM or R-GSM band when transmitted on a GSM 850 channel.</p>



**Table 10.5.6a/3GPP TS 24.008: Mobile Station Classmark 2 information element**

When a GSM 900 band is used (for exceptions see 3GPP TS 44.018):	
<b>Bit 1</b>	
0	The MS does not support the E-GSM or R-GSM band (For definition of frequency bands see 3GPP TS 05.05)
1	The MS does support the E-GSM or R-GSM (For definition of frequency bands see 3GPP TS 05.05)
Note:	For mobile station supporting the R-GSM band further information can be found in MS Classmark 3.
<del>When the DCS 1800 band is used (for exceptions see 3GPP TS 44.018):</del>	
<del><b>Bit 1</b></del>	
<del>0</del>	<del>Reserved for future use (for definition of frequency bands see 3GPP TS 05.05)</del>
<del>Note:</del>	<del>This bit conveys no information about support or non-support of the E-GSM or R-GSM band when transmitted on a DCS 1800 channel.</del>
<del>When the PCS 1900 band is used (for exceptions see 3GPP TS 44.018):</del>	
<del><b>Bit 1</b></del>	
<del>0</del>	<del>Reserved for future use (for definition of frequency bands see 3GPP TS 05.05)</del>
<del>Note:</del>	<del>This bit conveys no information about support or non-support of the E-GSM or R-GSM band when transmitted on a PCS 1900 channel.</del>
CM3 (octet 5, bit 8)	
<del>Required for MS supporting GSM.</del>	
0	The MS does not support any options that are indicated in CM3
1	Classmark 3 information is available
LCS VA capability (LCS value added location request notification capability) (octet 5, bit 6)	
<del>Required for MS supporting GSM and UMTS.</del>	
0	LCS value added location request notification capability not supported
1	LCS value added location request notification capability supported
UCS2 treatment (octet 5, bit 5)	
<del>Required for MS supporting UMTS.</del>	
This information field indicates the likely treatment by the mobile station of UCS2 encoded character strings. <u>For backward compatibility reasons, if this field is not included, the value 0 shall be assumed by the receiver.</u>	
0	the ME has a preference for the default alphabet (defined in 3GPP TS 03.38) over UCS2.
1	the ME has no preference between the use of the default alphabet and the use of UCS2.

**Table 10.5.6a/3GPP TS 24.008: Mobile Station Classmark 2 information element**

SoLSA (octet 5, bit 4) Required for MS supporting GSM. <u>An MS not supporting GSM shall set this bit to '0'.</u> <u>An MS supporting GSM shall indicate the associated GSM capability (see table):</u>	
0	The ME does not support SoLSA.
1	The ME supports SoLSA.
CMSP: CM Service Prompt (octet 5, bit 3) \$(CCBS)\$ Required for MS supporting GSM and UMTS.	
0	"Network initiated MO CM connection request" not supported.
1	"Network initiated MO CM connection request" supported for at least one CM protocol.
A5/3 algorithm supported (octet 5, bit 2) Required for MS supporting GSM. <u>An MS not supporting GSM shall set this bit to '0'.</u> <u>An MS supporting GSM shall indicate the associated GSM capability (see table):</u>	
0	encryption algorithm A5/3 not available
1	encryption algorithm A5/3 available
A5/2 algorithm supported (octet 5, bit 1) Required for MS supporting GSM. <u>An MS not supporting GSM shall set this bit to '0'.</u> <u>An MS supporting GSM shall indicate the associated GSM capability (see table):</u>	
0	encryption algorithm A5/2 not available
1	encryption algorithm A5/2 available

~~A MS supporting GSM shall always encode all fields relevant for GSM radio access technology, even when accessing UMTS radio access technology. A UMTS MS which does not support GSM shall encode fields relevant only for GSM radio access technology using any value which has been defined for this version of the protocol and is not reserved.~~

NOTE: Additional mobile station capability information might be obtained by invoking the classmark interrogation procedure when ~~GSM is used~~the mobile station is accessing the GSM radio access technology.

### 10.5.1.7 Mobile Station Classmark 3

The purpose of the *Mobile Station Classmark 3* information element is to provide the network with information concerning aspects of the mobile station. The contents might affect the manner in which the network handles the operation of the mobile station. The Mobile Station Classmark information indicates general mobile station characteristics and it shall therefore, except for fields explicitly indicated, be independent of the frequency band of the channel it is sent on.

The *MS Classmark 3* is a type 4 information element with a maximum of 14 octets length.

The value part of a *MS Classmark 3* information element is coded as shown in figure 10.5.7/3GPP TS 24.008 and table 10.5.7/3GPP TS 24.008.

NOTE: The 14 octet limit is so that the CLASSMARK CHANGE message will fit in one layer 2 frame.

SEMANTIC RULE : a multiband mobile station shall provide information about all frequency bands it can support. A single band mobile station shall not indicate the band it supports in the *Multiband Supported*, *GSM 400 Bands Supported*, *GSM 700 Associated Radio Capability*, *GSM 850 Associated Radio Capability* or *PCS 1900 Associated Radio Capability* fields in the MS Classmark 3. Due to shared radio frequency channel numbers between DCS 1800 and PCS 1900, the mobile should indicate support for either DCS 1800 band OR PCS 1900 band.

SEMANTIC RULE : a mobile station shall include the MS Measurement Capability field if the *Multi Slot Class* field contains a value of 19 or greater (see 3GPP TS 05.02).

Typically, the number of spare bits at the end is the minimum to reach an octet boundary. The receiver may add any number of bits set to "0" at the end of the received string if needed for correct decoding.

```

<Classmark 3 Value part> ::=
  < spare bit >
  { < Multiband supported : { 000 } >
    < A5 bits >
  | < Multiband supported : { 101 | 110 } >
    < A5 bits >
    < Associated Radio Capability 2 : bit(4) >
    < Associated Radio Capability 1 : bit(4) >
  | < Multiband supported : { 001 | 010 | 100 } >
    < A5 bits >
    < spare bit >(4)
    < Associated Radio Capability 1 : bit(4) > }
  { 0 | 1 < R Support > }
  { 0 | 1 < Multi Slot Capability > }
  < UCS2 treatment: bit >
  < Extended Measurement Capability : bit >
  { 0 | 1 < MS measurement capability > }
  { 0 | 1 < MS Positioning Method Capability > }
  { 0 | 1 < EDGE Multi Slot Capability > }
  { 0 | 1 < EDGE Struct > }
  { 0 | 1 < GSM 400 Bands Supported : { 01 | 10 | 11 } >
    < GSM 400 Associated Radio Capability: bit(4) > }

  { 0 | 1 <GSM 850 Associated Radio Capability : bit(4) > }
  { 0 | 1 <PCS 1900 Associated Radio Capability : bit(4) > }
  < UMTS FDD Radio Access Technology Capability : bit >
  < UMTS 3.84 Mcps TDD Radio Access Technology Capability : bit >
  < CDMA 2000 Radio Access Technology Capability : bit >

  { 0 | 1 < DTM GPRS Multi Slot Sub-Class : bit(2) >
    < MAC Mode Support : bit >
    { 0 | 1 < DTM EGPRS Multi Slot Sub-Class : bit(2) > } }
  { 0 | 1 < Single Band Support > } -- Release 4 starts here:
  { 0 | 1 <GSM 700 Associated Radio Capability : bit(4)>}

  < UMTS 1.28 Mcps TDD Radio Access Technology Capability : bit >
  < spare bit > ;

< A5 bits > ::=
  < A5/7 : bit > < A5/6 : bit > < A5/5 : bit > < A5/4 : bit > ;

<R Support>::=
  < R-GSM band Associated Radio Capability : bit(3) > ;

< Multi Slot Capability > ::=
  < Multi Slot Class : bit(5) > ;

< MS Measurement capability > ::=
  < SMS_VALUE : bit (4) >
  < SM_VALUE : bit (4) > ;

< MS Positioning Method Capability > ::=
  < MS Positioning Method : bit(5) > ;

< EDGE Multi Slot Capability > ::=
  < EDGE Multi Slot Class : bit(5) > ;

<EDGE Struct> : :=
  < Modulation Capability : bit >
  { 0 | 1 < EDGE RF Power Capability 1: bit(2) > }
  { 0 | 1 < EDGE RF Power Capability 2: bit(2) > }

< Single Band Support > ::=
  < GSM Band : bit (4) > ;

```

**Figure 10.5.7/3GPP TS 24.008 Mobile Station Classmark 3 information element**

**Table 10.5.7/3GPP TS 24.008: Mobile Station Classmark 3 information element**

Multiband Supported (3 bit field)	
Band 1 supported (third bit of the field)	
Bit	3
0	P-GSM not supported
1	P-GSM supported
Band 2 supported (second bit of the field)	
BIT	2
0	E-GSM or R-GSM not supported
1	E-GSM or R-GSM supported
Band 3 supported (first bit of the field)	
Bit	1
0	DCS 1800 not supported
1	DCS 1800 supported
The indication of support of P-GSM band or E-GSM or R-GSM band is mutually exclusive.	
When the 'Band 2 supported' bit indicates support of E-GSM or R-GSM, the presence of the <R Support> field, see below, indicates if the E-GSM or R-GSM band is supported.	
In this version of the protocol, the sender indicates in this field either none, one or two of these 3 bands supported. <del>If only one band is indicated, the receiver shall ignore the Associated Radio Capability 2.</del>	
<u>For single band mobile station or a mobile station supporting none of the GSM 900 bands(P-GSM, E-GSM and R-GSM) and DCS 1800 bands, all bits are set to 0.</u>	
A5/4	
Bit	1
0	Encryption algorithm A5/4 not available
1	Encryption algorithm A5/4 available
A5/5	
Bit	1
0	Encryption algorithm A5/5 not available
1	Encryption algorithm A5/5 available
A5/6	
Bit	1
0	Encryption algorithm A5/6 not available
1	Encryption algorithm A5/6 available
A5/7	
0	Encryption algorithm A5/7 not available
1	Encryption algorithm A5/7 available
Associated Radio capability 1 and 2 (4 bit fields)	
If either of P-GSM or E-GSM or R-GSM is supported, the radio capability 1 field indicates the radio capability for P-GSM, E-GSM or R-GSM, and the radio capability 2 field indicates the radio capability for DCS1800 if supported, and is spare otherwise.	
If none of P-GSM or E-GSM or R-GSM are supported, the radio capability 1 field indicates the radio capability for DCS1800, and the radio capability 2 field is spare.	
The radio capability contains the binary coding of the power class associated with the band indicated in multiband support bits (see GSM 05.05).	

(continued...)

**Table 10.5.1.7/3GPP TS 24.008 (continued): MS Classmark 3 information element**

**R Support**

In case where the R-GSM band is supported the R-GSM band associated radio capability field contains the binary coding of the power class associated (see GSM 045.005) (regardless of the number of GSM bands supported). A mobile station supporting the R-GSM band shall also when appropriate, (see 10.5.1.6) indicate its support in the 'FC' bit in the Mobile Station Classmark 2 information element.

Note: the coding of the power class for P-GSM, E-GSM, R-GSM and DCS 1800 in radio capability 1 and/or 2 is different to that used in the Mobile Station Classmark 1 and Mobile Station Classmark 2 information elements.

**Multi Slot Class (5 bit field)**

In case the MS supports the use of multiple timeslots then the Multi Slot Class field is coded as the binary representation of the multislots class defined in TS GSM 05.02.

**UCS2 treatment (1 bit field)**

This information field indicates the likely treatment by the mobile station of UCS2 encoded character strings. If not included, the value 0 shall be assumed by the receiver.

Bit 1  
 0 the ME has a preference for the default alphabet (defined in 3GPP TS 03.38) over UCS2.  
 1 the ME has no preference between the use of the default alphabet and the use of UCS2.

**Extended Measurement Capability (1 bit field)**

This bit indicates whether the mobile station supports 'Extended Measurements' or not

Bit 1  
 0 the MS does not support Extended Measurements  
 1 the MS supports Extended Measurements

**SMS\_VALUE (Switch-Measure-Switch) (4 bit field)**

The SMS field indicates the time needed for the mobile station to switch from one radio channel to another, perform a neighbour cell power measurement, and the switch from that radio channel to another radio channel.

Bits  
 4 3 2 1  
 0 0 0 0 1/4 timeslot (~144 microseconds)  
 0 0 0 1 2/4 timeslot (~288 microseconds)  
 0 0 1 0 3/4 timeslot (~433 microseconds)  
 ...  
 1 1 1 1 16/4 timeslot (~2307 microseconds)

**SM\_VALUE (Switch-Measure) (4 bit field)**

The SM field indicates the time needed for the mobile station to switch from one radio channel to another and perform a neighbour cell power measurement.

Bits  
 4 3 2 1  
 0 0 0 0 1/4 timeslot (~144 microseconds)  
 0 0 0 1 2/4 timeslot (~288 microseconds)  
 0 0 1 0 3/4 timeslot (~433 microseconds)  
 ...  
 1 1 1 1 16/4 timeslot (~2307 microseconds)

**MS Positioning Method Capability (1 bit field)**

This bit indicates whether the MS supports Positioning Method or not for the provision of Location Services.

**MS Positioning Method (5 bit field)**

This field indicates the Positioning Method(s) supported by the mobile station.

**MS assisted E-OTD**

Bit 5  
 0 MS assisted E-OTD not supported  
 1 MS assisted E-OTD supported

**Table 10.5.1.7/3GPP TS 24.008 (continued): MS Classmark 3 information element**

MS based E-OTD

Bit 4  
0 MS based E-OTD not supported  
1 MS based E-OTD supported

MS assisted GPS

Bit 3  
0 MS assisted GPS not supported  
1 MS assisted GPS supported

MS based GPS

Bit 2  
0 MS based GPS not supported  
1 MS based GPS supported

MS conventional GPS

Bit 1  
0 conventional GPS not supported  
1 conventional GPS supported

**EDGE Multi Slot class (5 bit field)**

In case the EDGE MS supports the use of multiple timeslots and the number of supported time slots is different from number of time slots supported for GMSK then the EDGE Multi Slot class field is included and is coded as the binary representation of the multislot class defined in TS GSM 05.02.

**Modulation Capability**

Modulation Capability field indicates the supported modulation scheme by MS in addition to GMSK

Bit 1  
0 8-PSK supported for downlink reception only  
1 8-PSK supported for uplink transmission and downlink reception

**EDGE RF Power Capability 1 (2 bit field)**

If 8-PSK is supported for both uplink and downlink, the **EDGE RF Power Capability 1** field indicates the radio capability for GSM700, GSM850 or GSM900.

The radio capability contains the binary coding of the EDGE power class(see GSM05.05).

**EDGE RF Power Capability 2 (2 bit field)**

If 8-PSK is supported for both uplink and downlink, the **EDGE RF Power Capability 2** field indicates the radio capability for DCS1800 or PCS1900 if supported, and is not included otherwise.

The radio capability contains the binary coding of the EDGE power class (see 3GPP TS 05.05).

**Table 10.5.1.7/3GPP TS 24.008 (continued): MS Classmark 3 information element**

**GSM 400 Bands Supported (2 bit field)**

See the semantic rule for the sending of this field.

Bits

2 1

0 1 GSM 480 supported, GSM 450 not supported

1 0 GSM 450 supported, GSM 480 not supported

1 1 GSM 450 supported, GSM 480 supported

**GSM 400 Associated Radio Capability (4 bit field)**

If either GSM 450 or GSM 480 or both is supported, the GSM 400 Associated Radio Capability field indicates the radio capability for GSM 450 and/or GSM 480.

The radio capability contains the binary coding of the power class associated with the band indicated in GSM 400 Bands Supported bits (see 3GPP TS 05.05).

Note: the coding of the power class for GSM 450 and GSM 480 in GSM 400 Associated Radio Capability is different to that used in the Mobile Station Classmark 1 and Mobile Station Classmark 2 information elements.

**GSM 850 Associated Radio Capability (4 bit field)**

See the semantic rule for the sending of this field.

This field indicates whether GSM 850 band is supported and its associated radio capability.

The radio capability contains the binary coding of the power class associated with the GSM 850 band (see 3GPP TS 05.05).

Note: the coding of the power class for GSM 850 in GSM 850 Associated Radio Capability is different to that used in the Mobile Station Classmark 1 and Mobile Station Classmark 2 information elements.

**PCS 1900 Associated Radio Capability (4 bit field)**

See the semantic rule for the sending of this field. This field indicates whether PCS 1900 band is supported and its associated radio capability.

The radio capability contains the binary coding of the power class associated with the PCS 1900 band (see 3GPP TS 05.05).

Note: the coding of the power class for PCS 1900 in PCS 1900 Associated Radio Capability is different to that used in the Mobile Station Classmark 1 and Mobile Station Classmark 2 information elements.



**Table 10.5.1.7/3GPP TS 24.008 (continued): MS Classmark 3 information element**

**UMTS FDD Radio Access Technology Capability (1 bit field)**

Bit 1  
 0 UMTS FDD not supported  
 1 UMTS FDD supported

**UMTS 3.84 Mcps TDD Radio Access Technology Capability (1 bit field)**

Bit 1  
 0 UMTS 3.84 Mcps TDD not supported  
 1 UMTS 3.84 Mcps TDD supported

**CDMA 2000 Radio Access Technology Capability (1 bit field)**

Bit 1  
 0 CDMA2000 not supported  
 1 CDMA2000 supported

**DTM GPRS Multi Slot Sub-Class (2 bit field)**

This field indicates the GPRS DTM capabilities of the MS. The GPRS DTM Multi Slot Sub-Class is independent from the Multi Slot Capabilities field. It is coded as follows:

Bit 2 1  
 0 0 Sub-Class 1 supported  
 0 1 Sub-Class 5 supported  
 1 0 Sub-Class 9 supported  
 1 1 Reserved for future extension. If received, the network shall interpret this as '00'

**DTM EGPRS Multi Slot Sub-Class (2 bit field)**

This field indicates the EGPRS DTM capabilities of the MS. The DTM EGPRS Multi Slot Sub-Class is independent from the Multi Slot Capabilities field. This field shall be included only if the mobile station supports EGPRS DTM. This field is coded as the DTM GPRS Multi Slot Sub-Class field.

**MAC Mode Support (1 bit field)**

This field indicates whether the MS supports Dynamic and Fixed Allocation or only supports Exclusive Allocation. It is coded as follows:

Bit 1  
 0 Dynamic and Fixed Allocation not supported  
 1 Dynamic and Fixed allocation supported

**Single Band Support**

This field shall be sent if the mobile station supports UMTS and one and only one GSM band with the exception of R-GSM; this field shall not be sent otherwise

**GSM Band (4 bit field)**

Bits  
4 3 2 1  
0 0 0 0 E-GSM is supported  
0 0 0 1 P-GSM is supported  
0 0 1 0 DCS 1800 is supported  
0 0 1 1 GSM 450 is supported  
0 1 0 0 GSM 480 is supported  
0 1 0 1 GSM 850 is supported  
0 1 1 0 PCS 1900 is supported  
0 1 1 1 GSM 700 is supported  
All other values are reserved for future use.

NOTE: When this field is received, the associated RF power capability is found in Classmark 1 or 2.

**GSM 700 Associated Radio Capability (4 bit field)**

See the semantic rule for the sending of this field.

This field indicates whether GSM 700 band is supported and its associated radio capability.

The radio capability contains the binary coding of the power class associated with the GSM 700 band (see 3GPP TS 05.05).

Note: the coding of the power class for GSM 700 in GSM 700 Associated Radio Capability is different to that used in the Mobile Station Classmark 1 and Mobile Station Classmark 2 information elements.

**UMTS 1.28 Mcps TDD Radio Access Technology Capability (1 bit field)**

- Bit 1
- 0 UMTS 1.28 Mcps TDD not supported
- 1 UMTS 1.28 Mcps TDD supported

\*\*\* Extract of TS 44.018 for information \*\*\*

### 9.1.11 Classmark change

This message is sent on the main DCCH by the mobile station to the network to indicate a classmark change or as a response to a classmark enquiry. See Table 9.1.11.1/3GPP TS 44.018.

Message type: CLASSMARK CHANGE

Significance: dual

Direction: mobile station to network

**Table 9.1.11.1/3GPP TS 04.18: CLASSMARK CHANGE message content**

IEI	Information element	Type / Reference	Presence	Format	length
	RR management Protocol Discriminator	Protocol Discriminator 10.2	M	V	1/2
	Skip Indicator	Skip Indicator 10.3.1	M	V	1/2
	Classmark Change Message Type	Message Type 10.4	M	V	1
	Mobile Station Classmark	Mobile Station Classmark 2 10.5.1.6	M	LV	4
20	Additional Mobile Station Classmark Information	Mobile Station Classmark 3 10.5.1.7	C	TLV	3-14

#### 9.1.11.1 Additional Mobile Station Classmark Information

This IE shall be included if and only if the CM3 bit in the *Mobile Station Classmark* IE is set to 1.

#### 9.1.11.2 Mobile Station Classmark

This IE shall include for multiband MS the Classmark 2 corresponding to the frequency band in use.

