

**TSG-RAN Meeting #13**  
**Beijing, China, 18 - 21 September 2001**

**RP-010554**

**Title:** Agreed CRs (Rel-4) to TS 25.331

**Source:** TSG-RAN WG2

**Agenda item:** 8.2.4

Doc-1st-	Status-	Spec	CR	Rev	Phase	Subject	Cat	Version	Versio	Workite
R2-011841	agreed	25.331	0933		Rel-4	Order of bits in bitstrings	F	4.1.0	4.2.0	LCRTD D-L23
R2-011852	agreed	25.331	0946		Rel-4	Selection of the RFC3095 CID transmission	F	4.1.0	4.2.0	RANimp -RABSE
R2-011870	agreed	25.331	0970		Rel-4	Correction of IPDL parameters for TDD enhancements in ASN.1 description	F	4.1.0	4.2.0	LCS1- UEpos- enh
R2-012148	agreed	25.331	0971	1	Rel-4	1.28 Mcps TDD PICH, Midamble and UL timing advance control corrections	F	4.1.0	4.2.0	LCRTD D-L23
R2-011872	agreed	25.331	0972		Rel-4	Introduction of 1.28 Mcps TDD Mode in clause 13.7	F	4.1.0	4.2.0	LCRTD D-L23
R2-011873	agreed	25.331	0973		Rel-4	Tadv in 1.28 Mcps TDD	F	4.1.0	4.2.0	LCRTD D-L23
R2-011874	agreed	25.331	0974		Rel-4	Correction and clarification to PRACH in 1.28 Mcps TDD	F	4.1.0	4.2.0	LCRTD D-L23

CR-Form-v4		
<b>CHANGE REQUEST</b>		
⌘	<b>25.331 CR 933</b>	⌘ ev <b>-</b> ⌘ Current version: <b>4.1.0</b> ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

**Proposed change affects:** ⌘ (U)SIM  ME/UE  Radio Access Network  Core Network

<b>Title:</b>	⌘ Order of bits in bitstrings		
<b>Source:</b>	⌘ TSG-RAN WG2		
<b>Work item code:</b>	⌘ LCRTDD-L23	<b>Date:</b>	⌘ 2001-08-23
<b>Category:</b>	⌘ <b>F</b>	<b>Release:</b>	⌘ REL-4
	<i>Use one of the following categories:</i> <b>F</b> (correction) <b>A</b> (corresponds to a correction in an earlier release) <b>B</b> (addition of feature), <b>C</b> (functional modification of feature) <b>D</b> (editorial modification) Detailed explanations of the above categories can be found in 3GPP <a href="#">TR 21.900</a> .		<i>Use one of the following releases:</i> <b>2</b> (GSM Phase 2) <b>R96</b> (Release 1996) <b>R97</b> (Release 1997) <b>R98</b> (Release 1998) <b>R99</b> (Release 1999) <b>REL-4</b> (Release 4) <b>REL-5</b> (Release 5)

<b>Reason for change:</b>	⌘ The order of bits in bitstrings has already been clarified for a number of IEs part of R99. Some IEs introduced in REL-4, related to the 1.28 Mcps TDD option, would need the same type of clarification.
<b>Summary of change:</b>	⌘ The meaning of each bit in the IE "SYNC UL codes bitmap" present in the IEs "SYNC_UL info" and "Uplink Timing Advance Control" is clarified.  The changes have isolated impact and were corrections to a function where the specification was ambiguous or not sufficiently explicit. They would not affect implementations behaving like indicated in the CR, would affect implementations supporting the corrected functionality otherwise.
<b>Consequences if not approved:</b>	⌘ Risk of interoperability problems if the meaning of the bits are interpreted differently by the UE and the network.

<b>Clauses affected:</b>	⌘ 10.3.6.78a, 10.3.6.96, 11.3		
<b>Other specs affected:</b>	⌘ <input type="checkbox"/>	Other core specifications	⌘
	<input type="checkbox"/>	Test specifications	
	<input type="checkbox"/>	O&M Specifications	
<b>Other comments:</b>	⌘		

**How to create CRs using this form:**

Comprehensive information and tips about how to create CRs can be found at: [http://www.3gpp.org/3G\\_Specs/CRs.htm](http://www.3gpp.org/3G_Specs/CRs.htm). Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/>. For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.

- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

10.3.6.78a SYNC\_UL info

NOTE: Only for 1.28 Mcps TDD.

Information Element/ Group name	Need	Multi	Type and reference	Semantics description	Version
SYNC_UL codes bitmap	MP		Bitstring(8)	<u>Each bit indicates availability of a SYNC_UL code, where the SYNC_UL codes are numbered "code 0" to "code 7".</u> <u>The value 1 of a bit indicates that the corresponding SYNC_UL code can be used.</u> <u>The value 0 of a bit indicates that the corresponding SYNC_UL code can not be used.</u> <u>00000001- indicates code 0 can be used,10000001- indicates that codes 0 and 7 can be used.</u>	REL-4
UL Target SIR	MP		Real(-11 .. 20 by step of 0.5)	In dB	REL-4
Power Ramping Step	MP		Integer(0,1,2,3)	In dB	REL-4
Max SYNC_UL Transmissions	MP		Integer(1,2,4,8)	Maximum numbers of SYNC_UL transmissions in a power ramping sequence.	REL-4
Mmax	MP		Integer(1..32)	Maximum number of synchronisation attempts.	REL-4

### 10.3.6.96 Uplink Timing Advance Control

NOTE: Only for TDD

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
CHOICE <i>Timing Advance</i>	MP				
>Disabled			Null	Indicates that no timing advance is applied	
>Enabled					
>>CHOICE <i>TDD option</i>	MP				REL-4
>>>3.84 Mcps TDD					REL-4
>>>>UL Timing Advance	MD		Uplink Timing Advance 10.3.6.95	Absolute timing advance value to be used to avoid large delay spread at the NodeB. Default value is the existing value for uplink timing advance.	
>>>>Activation Time	OP		Activation Time 10.3.3.1	Frame number timing advance is to be applied. This IE is required when a new UL Timing Advance adjustment is specified and Activation Time is not otherwise specified in the RRC message.	
>>>1.28 Mcps TDD				(no data)	REL-4
>>>>Uplink synchronisation parameters	MD			Default: Uplink synchronisation parameters is 1. Uplink synchronisation frequency is 1.	REL-4
>>>>>Uplink synchronisation step size	MP		Integer(1..8)	This parameter specifies the step size to be used for the adjustment of the uplink transmission timing	REL-4
>>>>>Uplink synchronisation frequency	MP		Integer(1..8)	This parameter specifies the frequency of the adjustment of the uplink transmission timing	REL-4
>>>>Synchronization parameters	OP				
>>>>>SYNC_UL codes bitmap	MD		Bitstring(8)	<a href="#">Each bit indicates availability of a SYNC_UL code, where the SYNC_UL codes are numbered "code 0" to "code 7". The value 1 of a bit indicates that the corresponding SYNC_UL code can be used. The value 0 of a bit indicates that the corresponding</a>	REL-4

				<p><u>SYNC_UL code can not be used.</u>  <del>00000001 indicates code 0 can be used,</del>  <del>10000001 indicates that codes 0 and 7 can be used.</del>                  Default: all SYNC_UL codes can be used</p>	
>>>>FPACH info	MP		FPACH info 10.3.6.?		REL-4
>>>>SYNC_UL procedure	MD			Default is: Max SYNC_UL Transmission is 2. Power Ramping Step is 2.	REL-4
>>>>>Max SYNC_UL Transmissions	MP		Integer(1,2,4,8)	Maximum numbers of SYNC_UL transmissions in a power ramping sequence.	REL-4
>>>>>Power Ramping Step	MP		Integer(0,1,2,3)	In dB	REL-4

## 11.3 Information element definitions

```
-- *****
--
--     PHYSICAL CHANNEL INFORMATION ELEMENTS (10.3.6)
--
-- *****
```

```
SynchronisationParameters-r4 ::= SEQUENCE {
    sync-UL-CodesBitmap          BIT STRING {
        code7(0),
        code6(1),
        code5(2),
        code4(3),
        code3(4),
        code2(5),
        code1(6),
        code0(7)
    } (SIZE (8))                                OPTIONAL,
    fpach-Info                  FPACH-Info-r4,
    sync-UL-Procedure           SYNC-UL-Procedure-r4    OPTIONAL
}
```

```
SYNC-UL-Info-r4 ::= SEQUENCE {
    sync-UL-Codes-Bitmap        BIT STRING {
        code7(0),
        code6(1),
        code5(2),
        code4(3),
        code3(4),
        code2(5),
        code1(6),
        code0(7)
    } ( SIZE (8)),
    ul-TargetSIR                UL-TargetSIR,
    powerRampingStep            INTEGER (0..3),
    max-SYNC-UL-Transmissions   ENUMERATED { tr1, tr2, tr4, tr8 } ,
    mmax                        INTEGER(1..32)
}
```



<small>CR-Form-v4</small>
<h2>CHANGE REQUEST</h2>
⌘ <b>25.331 CR 946</b> ⌘ ev <b>-</b> ⌘ Current version: <b>4.1.0</b> ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

Proposed change affects: ⌘ (U)SIM  ME/UE  Radio Access Network  Core Network

<b>Title:</b> ⌘ Selection of the RFC3095 CID transmission
<b>Source:</b> ⌘ TSG-RAN WG2
<b>Work item code:</b> ⌘ RANimp-RABSE <span style="float:right"><b>Date:</b> ⌘ 5.7.2001</span>
<b>Category:</b> ⌘ <b>F</b> <span style="float:right"><b>Release:</b> ⌘ REL-4</span>
<small>Use <u>one</u> of the following categories:</small>
<small><b>F</b> (correction) <b>A</b> (corresponds to a correction in an earlier release) <b>B</b> (addition of feature), <b>C</b> (functional modification of feature) <b>D</b> (editorial modification)</small>
<small>Detailed explanations of the above categories can be found in 3GPP <a href="#">TR 21.900</a>.</small>
<small>Use <u>one</u> of the following releases:</small>
<small>2 (GSM Phase 2) R96 (Release 1996) R97 (Release 1997) R98 (Release 1998) R99 (Release 1999) REL-4 (Release 4) REL-5 (Release 5)</small>

<b>Reason for change:</b> ⌘ Missing configuration parameter in RRC message. PDCP spec (25.323) refers that the selection of RFC3095 CID transmission is configured by upper layers, but there is no means to do this on RRC.
<b>Summary of change:</b> ⌘ Addition of field to carry the required selection information
<b>Consequences if not approved:</b> ⌘ -

<b>Clauses affected:</b> ⌘ 10.3.4.2, 11.3
<b>Other specs affected:</b> ⌘ <input checked="" type="checkbox"/> Other core specifications ⌘ 25.323, CR 026
<input type="checkbox"/> Test specifications
<input type="checkbox"/> O&M Specifications
<b>Other comments:</b> ⌘

**How to create CRs using this form:**

Comprehensive information and tips about how to create CRs can be found at: [http://www.3gpp.org/3G\\_Specs/CRs.htm](http://www.3gpp.org/3G_Specs/CRs.htm). Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

#### 10.3.4.2 PDCP info

The purpose of the PDCP info IE is to indicate which algorithms shall be established and to configure the parameters of each of the algorithms.

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
Support for lossless SRNS relocation	CV- <i>LosslessCriteria</i>		Boolean	TRUE means support	
Max PDCP SN window size	CV- <i>Lossless</i>		Enumerated( sn255, sn65535)	Maximum PDCP sequence number window size. The handling of sequence number when the Max PDCP SN window size is 255 is specified in [23].	
PDCP PDU header	MD		Enumerated (present, absent)	Whether a PDCP PDU header is existent or not. Default value is "present"	
Header compression information	OP	1 to <maxPDC PAlgoType >			
>CHOICE <i>algorithm type</i>	MP				
>>RFC 2507				Header compression according to IETF standard RFC 2507	
>>>F_MAX_PERIOD	MD		Integer (1..65535)	Largest number of compressed non-TCP headers that may be sent without sending a full header. Default value is 256.	
>>>F_MAX_TIME	MD		Integer (1..255)	Compressed headers may not be sent more than F_MAX_TIME seconds after sending last full header. Default value is 5.	
>>>MAX_HEADER	MD		Integer (60..65535)	The largest header size in octets that may be compressed. Default value is 168.	
>>>TCP_SPACE	MD		Integer (3..255)	Maximum CID value for TCP connections. Default value is 15.	
>>>NON_TCP_SPACE	MD		Integer (3..65535)	Maximum CID value for non-TCP connections. Default value is 15.	
>>>EXPECT_REORDERING	MD		Enumerated (reordering not expected, reordering expected)	Whether the algorithm shall reorder PDCP SDUs or not. Default value is "reordering not expected".	

>>RFC 3095				Header compression according to IETF standard RFC 3095	REL-4
>>> CID inclusion info	MP		Enumerated (PDCP header, RFC3095 packet format)	Configures which method shall be used to carry RFC3095 CID values.	REL-4
>>>Max_CID	MD		Integer (1..16383)	Highest context ID number to be used by the compressor. Default value is 15.	REL-4
>>>Profiles	MP	1 to <maxROHC-Profiles>		Profiles supported by the decompressor.	REL-4
>>>>Profile instance	MP		Integer(1 .. 3)	Supported profile types. At least four spare values.	REL-4
>>>MRRU	MD		Integer (0 .. 65535)	Maximum reconstructed reception unit. Default value is 0 (no segmentation).	REL-4
>>>Packet_Sizes_Allowed	OP	1 to <maxROHC-PacketSizes>		List of packet sizes that are allowed to be produced by RFC 3095.	REL-4
>>>>Packet size	MP		Integer (2 .. 1500)	Packet size as defined in RFC 3095.	REL-4
>>>>Reverse-Decompression_Depth	MD		Integer (0..65535)	Determines whether reverse decompression should be used or not and the maximum number of packets that can be reverse decompressed by the decompressor. Default value is 0 (reverse decompression shall not be used).	REL-4

Condition	Explanation
<i>LosslessCriteria</i>	This IE is present only if the IE "RLC mode" is "Acknowledged" and the IE "In-sequence delivery" is "True".
<i>Lossless</i>	This IE shall be present if the IE "Support for lossless SRNS relocation" is TRUE, otherwise it shall be absent.

## 11.3 Information element definitions

```
InformationElements DEFINITIONS AUTOMATIC TAGS ::=
```

```
-- *****
--
-- CORE NETWORK INFORMATION ELEMENTS (10.3.1)
--
-- *****
```

```
BEGIN
```

```
IMPORTS
```

```

    hiPDSCHidentities,
    hiPUSCHidentities,
    hiRM,
    maxAC,
    maxAdditionalMeas,
    maxASC,
    maxASCmap,
    maxASCpersist,
    maxCCTrCH,
    maxCellMeas,
    maxCellMeas-1,
    maxCNdomains,
    maxCPCHsets,
    maxDPCH-DLchan,
    maxDPCHcodesPerTS,
    maxDPDCH-UL,
    maxDRACclasses,
    maxFACHPCH,
    maxFreq,
    maxFreqBandsFDD,
    maxFreqBandsTDD,
    maxFreqBandsGSM,
    maxInterSysMessages,
    maxLoCHperRLC,
    maxMeasEvent,
    maxMeasIntervals,
    maxMeasParEvent,
    maxNumCDMA2000Freqs,
    maxNumFDDFreqs,
    maxNumGSMFreqRanges,
    maxNumTDDFreqs,
    maxOtherRAT,
    maxPage1,
    maxPCPCH-APsig,
    maxPCPCH-APsubCh,
    maxPCPCH-CDsig,
    maxPCPCH-CDsubCh,
    maxPCPCH-SF,
    maxPCPCHs,
    maxPDCPAlgoType,
    maxPDSCH,
    maxPDSCH-TFCIgroups,
    maxPRACH,
    maxPRACH-FPACH,
    maxPUSCH,
    maxRABsetup,
    maxRAT,
    maxRB,
    maxRBallRABs,
    maxRBMuxOptions,
    maxRBperRAB,
    maxReportedGSMCells,
    maxSRBsetup,
    maxRL,
    maxRL-1,
    maxROHC-PacketSizes-r4,
    maxROHC-Profile-r4,
    maxSCCPCH,
    maxSat,
    maxSIB,
    maxSIB-FACH,
```

```

maxSig,
maxSubCh,
maxSystemCapability,
maxTF,
maxTF-CPCH,
maxTFC,
maxTFCl-2-Combs,
maxTGPS,
maxTrCH,
maxTS,
maxTS-1,
maxTS-LCR,
maxTS-LCR-1,
maxURA
FROM Constant-definitions;

Ansi-41-IDNNS ::=                                BIT STRING (SIZE (14))

CN-DomainIdentity ::=                           ENUMERATED {
    cs-domain,
    ps-domain }

CN-DomainInformation ::=                        SEQUENCE {
    cn-DomainIdentity
    cn-DomainSpecificNAS-Info
}

CN-DomainInformationFull ::=                   SEQUENCE {
    cn-DomainIdentity
    cn-DomainSpecificNAS-Info
    cn-DRX-CycleLengthCoeff
}

CN-DomainInformationList ::=                   SEQUENCE (SIZE (1..maxCNdomains)) OF
    CN-DomainInformation

CN-DomainInformationListFull ::=               SEQUENCE (SIZE (1..maxCNdomains)) OF
    CN-DomainInformationFull

CN-DomainSysInfo ::=                           SEQUENCE {
    cn-DomainIdentity
    cn-Type
    gsm-MAP
    ansi-41
},
    cn-DRX-CycleLengthCoeff
}

CN-DomainSysInfoList ::=                       SEQUENCE (SIZE (1..maxCNdomains)) OF
    CN-DomainSysInfo

CN-InformationInfo ::=                         SEQUENCE {
    plmn-Identity
    cn-CommonGSM-MAP-NAS-SysInfo
    cn-DomainInformationList
}

CN-InformationInfoFull ::=                     SEQUENCE {
    plmn-Identity
    cn-CommonGSM-MAP-NAS-SysInfo
    cn-DomainInformationListFull
}

Digit ::=                                     INTEGER (0..9)

Gsm-map-IDNNS ::=                             SEQUENCE {
    routingbasis
    localPTMSI
    routingparameter
},
    tMSIofsamePLMN
    routingparameter
},
    tMSIofdifferntPLMN
    routingparameter
},
    iMSIresponsetopaging
    routingparameter
}

```

<pre>         },         IMSIUEinitiatedEvent             routingparameter     },     IMEI         routingparameter     },     spare1         routingparameter     },     spare2         routingparameter     } }, enteredparameter } </pre>	<pre> SEQUENCE {     RoutingParameter }  SEQUENCE {     RoutingParameter }  SEQUENCE {     RoutingParameter }  SEQUENCE {     RoutingParameter }  BOOLEAN </pre>
<pre> IMEI ::= </pre>	<pre> SEQUENCE (SIZE (15)) OF     IMEI-Digit </pre>
<pre> IMEI-Digit ::= </pre>	<pre> INTEGER (0..15) </pre>
<pre> IMSI-GSM-MAP ::= </pre>	<pre> SEQUENCE (SIZE (6..15)) OF     Digit </pre>
<pre> IntraDomainNasNodeSelector ::=     version         release99             cn-Type                 gsm-Map-IDNNS                 ansi-41-IDNNS             },         later             futurecoding     } } </pre>	<pre> SEQUENCE {     CHOICE {         SEQUENCE {             CHOICE {                 Gsm-map-IDNNS,                 Ansi-41-IDNNS             }         }     },     SEQUENCE {         BIT STRING (SIZE (15))     } } </pre>
<pre> LAI ::=     plmn-Identity     lac } </pre>	<pre> SEQUENCE {     PLMN-Identity,     BIT STRING (SIZE (16)) } </pre>
<pre> MCC ::= </pre>	<pre> SEQUENCE (SIZE (3)) OF     Digit </pre>
<pre> MNC ::= </pre>	<pre> SEQUENCE (SIZE (2..3)) OF     Digit </pre>
<pre> NAS-Message ::= </pre>	<pre> OCTET STRING (SIZE (1..4095)) </pre>
<pre> NAS-Synchronisation-Indicator ::= </pre>	<pre> BIT STRING(SIZE(4)) </pre>
<pre> NAS-SystemInformationGSM-MAP ::= </pre>	<pre> OCTET STRING (SIZE (1..8)) </pre>
<pre> P-TMSI-GSM-MAP ::= </pre>	<pre> BIT STRING (SIZE (32)) </pre>
<pre> PagingRecordTypeID ::= </pre>	<pre> ENUMERATED {     imsi-GSM-MAP,     tmsi-GSM-MAP-P-TMSI,     imsi-DS-41,     tmsi-DS-41 } </pre>
<pre> PLMN-Identity ::=     mcc     mnc } </pre>	<pre> SEQUENCE {     MCC,     MNC } </pre>
<pre> PLMN-Type ::=     gsm-MAP         plmn-Identity     },     ansi-41         p-REV         min-P-REV         sid         nid </pre>	<pre> CHOICE {     SEQUENCE {         PLMN-Identity     }     SEQUENCE {         P-REV,         Min-P-REV,         SID,         NID     } } </pre>

```

    },
    gsm-MAP-and-ANSI-41      SEQUENCE {
        plmn-Identity        PLMN-Identity,
        p-REV                 P-REV,
        min-P-REV            Min-P-REV,
        sid                   SID,
        nid                   NID
    }
}

RAB-Identity ::=
    gsm-MAP-RAB-Identity    CHOICE {
        ansi-4l-RAB-Identity BIT STRING (SIZE (8)),
    }

RAI ::=
    lai                      SEQUENCE {
        rac                   RoutingAreaCode
    }

RoutingAreaCode ::=
    BIT STRING (SIZE (8))

RoutingParameter ::=
    BIT STRING (SIZE (10))

TMSI-GSM-MAP ::=
    BIT STRING (SIZE (32))

-- *****
--
--     UTRAN MOBILITY INFORMATION ELEMENTS (10.3.2)
--
-- *****

AccessClassBarred ::=
    ENUMERATED {
        barred, notBarred }

AccessClassBarredList ::=
    SEQUENCE (SIZE (maxAC)) OF
        AccessClassBarred

AllowedIndicator ::=
    ENUMERATED {
        allowed, notAllowed }

CellAccessRestriction ::=
    cellBarred               SEQUENCE {
        cellReservedForOperatorUse ReservedIndicator,
        cellReservationExtension  ReservedIndicator,
        accessClassBarredList     AccessClassBarredList
    }
    OPTIONAL

CellBarred ::=
    barred                    CHOICE {
        intraFreqCellReselectionInd SEQUENCE {
            t-Barred                AllowedIndicator,
        },
        notBarred                  NULL
    }

CellIdentity ::=
    BIT STRING (SIZE (28))

CellSelectReselectInfoSIB-3-4 ::=
    mappingInfo              SEQUENCE {
        cellSelectQualityMeasure MappingInfo
    }
    OPTIONAL,
    cpich-Ec-N0              SEQUENCE {
        q-HYST-2-S              Q-Hyst-S
    }
    OPTIONAL,
    -- Default value for q-HYST-2-S is q-HYST-1-S
    },
    cpich-RSCP               NULL
    },
    modeSpecificInfo         CHOICE {
        fdd                   SEQUENCE {
            s-Intrasearch      S-SearchQual
            s-Intersearch      S-SearchQual
            s-SearchHCS        S-SearchRXLEV
            rat-List           RAT-FDD-InfoList
            q-QualMin          Q-QualMin,
            q-RxlevMin         Q-RxlevMin
        },
        tdd                   SEQUENCE {
            s-Intrasearch      S-SearchRXLEV
        }
    }
    OPTIONAL,

```



```

        s-Intersearch
        s-SearchHCS
        rat-List
        q-RxlevMin
    }
},
q-Hyst-l-S
t-Reselection-S
hcs-ServingCellInformation
maxAllowedUL-TX-Power
}

MappingFunctionParameterList ::=
    SEQUENCE {
        MappingFunctionParameterList
    }

MappingFunctionParameter ::=
    SEQUENCE {
        functionType
        mapParameter1
        mapParameter2
        upperLimit
        -- The parameter is conditional on the number of repetition
    }
    OPTIONAL,
    OPTIONAL

MappingFunctionParameterList ::=
    SEQUENCE (SIZE (1..maxMeasIntervals)) OF
        MappingFunctionParameter

MappingFunctionType ::=
    ENUMERATED {
        linear,
        functionType2,
        functionType3,
        functionType4 }

-- In this list, mapping for FDD and 3.84Mcps TDD is defined. For 1.28Mcps TDD, Mapping-LCR-r4
-- is used instead.
MappingInfo ::=
    SEQUENCE (SIZE (1..maxRAT)) OF
        Mapping

-- Actual value = IE value * 2
Q-Hyst-S ::=
    INTEGER (0..20)

RAT ::=
    ENUMERATED {
        ultra-FDD,
        ultra-TDD,
        gsm,
        cdma2000 }

RAT-FDD-Info ::=
    SEQUENCE {
        rat-Identifier
        s-SearchRAT
        s-HCS-RAT
        s-Limit-SearchRAT
    }
    OPTIONAL,

RAT-FDD-InfoList ::=
    SEQUENCE (SIZE (1..maxOtherRAT)) OF
        RAT-FDD-Info

RAT-Identifier ::=
    ENUMERATED {
        gsm, cdma2000 }

RAT-TDD-Info ::=
    SEQUENCE {
        rat-Identifier
        s-SearchRAT
        s-HCS-RAT
        s-Limit-SearchRAT
    }
    OPTIONAL,

RAT-TDD-InfoList ::=
    SEQUENCE (SIZE (1..maxOtherRAT)) OF
        RAT-TDD-Info

ReservedIndicator ::=
    ENUMERATED {

```

```

        reserved,
        notReserved }

-- Actual value = IE value * 2
S-SearchQual ::=                               INTEGER (-16..10)

-- Actual value = (IE value * 2) + 1
S-SearchRXLEV ::=                              INTEGER (-53..45)

T-Barred ::=                                  ENUMERATED {
        s10, s20, s40, s80,
        s160, s320, s640, s1280 }

T-Reselection-S ::=                           INTEGER (0..31)

-- The used range depends on the RAT used.
UpperLimit ::=                                INTEGER (1..91)

URA-Identity ::=                             BIT STRING (SIZE (16))

URA-IdentityList ::=                          SEQUENCE (SIZE (1..maxURA)) OF
        URA-Identity

-- *****
--
--     USER EQUIPMENT INFORMATION ELEMENTS (10.3.3)
--
-- *****

ActivationTime ::=                             INTEGER (0..255)
-- TABULAR : value 'now' always appear as default, and is encoded by absence of the field

BackoffControlParams ::=                       SEQUENCE {
        n-AP-RetransMax           N-AP-RetransMax,
        n-AccessFails            N-AccessFails,
        nf-BO-NoAICH             NF-BO-NoAICH,
        ns-BO-Busy               NS-BO-Busy,
        nf-BO-AllBusy            NF-BO-AllBusy,
        nf-BO-Mismatch           NF-BO-Mismatch,
        t-CPCH                   T-CPCH
}

C-RNTI ::=                                     BIT STRING (SIZE (16))

CapabilityUpdateRequirement ::=                SEQUENCE {
        ue-RadioCapabilityFDDUpdateRequirement-FDD    BOOLEAN,
-- The following is for 3.84Mcps TDD update requirement
        ue-RadioCapabilityTDDUpdateRequirement-TDD    BOOLEAN,
        systemSpecificCapUpdateReqList               SystemSpecificCapUpdateReqList    OPTIONAL
}

CapabilityUpdateRequirement-r4-ext ::=         SEQUENCE {
        ue-RadioCapabilityUpdateRequirement-TDD128    BOOLEAN
}

CapabilityUpdateRequirement-r4 ::=             SEQUENCE {
        ue-RadioCapabilityFDDUpdateRequirement-FDD    BOOLEAN,
        ue-RadioCapabilityTDDUpdateRequirement-TDD384    BOOLEAN,
        ue-RadioCapabilityTDDUpdateRequirement-TDD128    BOOLEAN,
        systemSpecificCapUpdateReqList               SystemSpecificCapUpdateReqList    OPTIONAL
}

CellUpdateCause ::=                           ENUMERATED {
        cellReselection,
        periodicalCellUpdate,
        uplinkDataTransmission,
        utran-pagingResponse,
        re-enteredServiceArea,
        radiolinkFailure,
        rlc-unrecoverableError,
        spare1 }

ChipRateCapability ::=                         ENUMERATED {
        mcps3-84, mcps1-28 }

CipheringAlgorithm ::=                         ENUMERATED {
        uea0, uea1 }

```

```

CipheringModeCommand ::= CHOICE {
    startRestart          CipheringAlgorithm,
    stopCiphering        NULL
}

CipheringModeInfo ::= SEQUENCE {
    cipheringModeCommand CipheringModeCommand,
    -- TABULAR: The ciphering algorithm is included in
    -- the CipheringModeCommand.
    activationTimeForDPCH ActivationTime OPTIONAL,
    rb-DL-CiphActivationTimeInfo RB-ActivationTimeInfoList OPTIONAL
}

CN-DRX-CycleLengthCoefficient ::= INTEGER (6..9)

CN-PagedUE-Identity ::= CHOICE {
    imsi-GSM-MAP          IMSI-GSM-MAP,
    tmsi-GSM-MAP          TMSI-GSM-MAP,
    p-TMSI-GSM-MAP        P-TMSI-GSM-MAP,
    imsi-DS-41            IMSI-DS-41,
    tmsi-DS-41            TMSI-DS-41
}

CompressedModeMeasCapability ::= SEQUENCE {
    fdd-Measurements      BOOLEAN,
    -- TABULAR: The IEs below are made optional since they are conditional based
    -- on another information element. Their absence corresponds to the case where
    -- the condition is not true.
    -- tdd-Measurements indicates need for compressed mode for 3.84Mcps TDD measurements
    tdd-Measurements      BOOLEAN OPTIONAL,
    gsm-Measurements      GSM-Measurements OPTIONAL,
    multiCarrierMeasurements BOOLEAN OPTIONAL
}

CompressedModeMeasCapability-LCR-r4 ::= SEQUENCE {
    tdd128-Measurements   BOOLEAN OPTIONAL
}

CompressedModeMeasCapabFDDList ::= SEQUENCE (SIZE (1..maxFreqBandsFDD)) OF
    CompressedModeMeasCapabFDD

CompressedModeMeasCapabFDD ::= SEQUENCE {
    radioFrequencyBandFDD RadioFrequencyBandFDD OPTIONAL,
    dl-MeasurementsFDD     BOOLEAN,
    ul-MeasurementsFDD     BOOLEAN
}

CompressedModeMeasCapabTDDList ::= SEQUENCE (SIZE (1..maxFreqBandsTDD)) OF
    CompressedModeMeasCapabTDD

CompressedModeMeasCapabTDD ::= SEQUENCE {
    radioFrequencyBandTDD RadioFrequencyBandTDD,
    dl-MeasurementsTDD     BOOLEAN,
    ul-MeasurementsTDD     BOOLEAN
}

CompressedModeMeasCapabGSMList ::= SEQUENCE (SIZE (1..maxFreqBandsGSM)) OF
    CompressedModeMeasCapabGSM

CompressedModeMeasCapabGSM ::= SEQUENCE {
    radioFrequencyBandGSM RadioFrequencyBandGSM,
    dl-MeasurementsGSM     BOOLEAN,
    ul-MeasurementsGSM     BOOLEAN
}

CompressedModeMeasCapabMC ::= SEQUENCE {
    dl-MeasurementsMC      BOOLEAN,
    ul-MeasurementsMC      BOOLEAN
}

CPCH-Parameters ::= SEQUENCE {
    initialPriorityDelayList InitialPriorityDelayList OPTIONAL,
    backoffControlParams     BackoffControlParams,
    powerControlAlgorithm     PowerControlAlgorithm,
    -- TABULAR: TPC step size nested inside PowerControlAlgorithm
    dl-DPCCH-BER             DL-DPCCH-BER
}

```

```

DL-DPCCH-BER ::= INTEGER (0..63)

DL-PhysChCapabilityFDD ::= SEQUENCE {
    maxNoDPCH-PDSCH-Codes          INTEGER (1..8),
    maxNoPhysChBitsReceived        MaxNoPhysChBitsReceived,
    supportForSF-512                BOOLEAN,
    supportOfPDSCH                  BOOLEAN,
    simultaneousSCCPCH-DPCH-Reception SimultaneousSCCPCH-DPCH-Reception
}

DL-PhysChCapabilityTDD ::= SEQUENCE {
    maxTS-PerFrame                 MaxTS-PerFrame,
    maxPhysChPerFrame              MaxPhysChPerFrame,
    minimumSF                       MinimumSF-DL,
    supportOfPDSCH                  BOOLEAN,
    maxPhysChPerTS                  MaxPhysChPerTS
}

DL-PhysChCapabilityTDD-LCR-r4 ::= SEQUENCE {
    maxTS-PerSubFrame              MaxTS-PerSubFrame-r4,
    maxPhysChPerSubFrame-r4        MaxPhysChPerSubFrame-r4,
    minimumSF                       MinimumSF-DL,
    supportOfPDSCH                  BOOLEAN,
    maxPhysChPerTS                  MaxPhysChPerTS,
    supportOf8PSK                   BOOLEAN
}

DL-TransChCapability ::= SEQUENCE {
    maxNoBitsReceived               MaxNoBits,
    maxConvCodeBitsReceived         MaxNoBits,
    turboDecodingSupport            TurboSupport,
    maxSimultaneousTransChs         MaxSimultaneousTransChsDL,
    maxSimultaneousCCTrCH-Count     MaxSimultaneousCCTrCH-Count,
    maxReceivedTransportBlocks      MaxTransportBlocksDL,
    maxNumberOfTFC-InTFCS           MaxNumberOfTFC-InTFCS-DL,
    maxNumberOfTF                    MaxNumberOfTF
}

DRAC-SysInfo ::= SEQUENCE {
    transmissionProbability          TransmissionProbability,
    maximumBitRate                   MaximumBitRate
}

DRAC-SysInfoList ::= SEQUENCE (SIZE (1..maxDRACclasses)) OF
    DRAC-SysInfo

ESN-DS-41 ::= BIT STRING (SIZE (32))

EstablishmentCause ::= ENUMERATED {
    originatingConversationalCall,
    originatingStreamingCall,
    originatingInteractiveCall,
    originatingBackgroundCall,
    originatingSubscribedTrafficCall,
    terminatingConversationalCall,
    terminatingStreamingCall,
    terminatingInteractiveCall,
    terminatingBackgroundCall,
    emergencyCall,
    interRAT-CellReselection,
    interRAT-CellChangeOrder,
    registration,
    detach,
    originatingHighPrioritySignalling,
    originatingLowPrioritySignalling,
    callRe-establishment,
    terminatingHighPrioritySignalling,
    terminatingLowPrioritySignalling,
    terminatingCauseUnknown,
    spare1 }

FailureCauseWithProtErr ::= CHOICE {
    configurationUnsupported         NULL,
    physicalChannelFailure           NULL,
    incompatibleSimultaneousReconfiguration
                                     NULL,
    compressedModeRuntimeError       TGPSI,
    protocolError                     ProtocolErrorInformation,
}

```

```

cellUpdateOccurred          NULL,
invalidConfiguration        NULL,
configurationIncomplete     NULL,
unsupportedMeasurement       NULL,
spare1                      NULL,
spare2                      NULL,
spare3                      NULL,
spare4                      NULL,
spare5                      NULL,
spare6                      NULL,
spare7                      NULL
}

FailureCauseWithProtErrTrId ::= SEQUENCE {
    rrc-TransactionIdentifier RRC-TransactionIdentifier,
    failureCause              FailureCauseWithProtErr
}

GSM-Measurements ::= SEQUENCE {
    gsm900                    BOOLEAN,
    dcs1800                   BOOLEAN,
    gsm1900                   BOOLEAN
}

-- If ICS-Version-r4 is included, the following IE shall be ignored.
ICS-Version ::= ENUMERATED {
    r99 }

ICS-Version-r4 ::= ENUMERATED {
    rel-4 }

IMSI-and-ESN-DS-41 ::= SEQUENCE {
    imsi-DS-41                IMSI-DS-41,
    esn-DS-41                 ESN-DS-41
}

IMSI-DS-41 ::= OCTET STRING (SIZE (5..7))

InitialPriorityDelayList ::= SEQUENCE (SIZE (1..maxASC)) OF
    NS-IP

InitialUE-Identity ::= CHOICE {
    imsi                      IMSI-GSM-MAP,
    tmsi-and-LAI              TMSI-and-LAI-GSM-MAP,
    p-TMSI-and-RAI           P-TMSI-and-RAI-GSM-MAP,
    imei                      IMEI,
    esn-DS-41                 ESN-DS-41,
    imsi-DS-41                IMSI-DS-41,
    imsi-and-ESN-DS-41        IMSI-and-ESN-DS-41,
    tmsi-DS-41                TMSI-DS-41
}

IntegrityCheckInfo ::= SEQUENCE {
    messageAuthenticationCode MessageAuthenticationCode,
    rrc-MessageSequenceNumber RRC-MessageSequenceNumber
}

IntegrityProtActivationInfo ::= SEQUENCE {
    rrc-MessageSequenceNumberList RRC-MessageSequenceNumberList
}

IntegrityProtectionAlgorithm ::= ENUMERATED {
    uial }

IntegrityProtectionModeCommand ::= CHOICE {
    startIntegrityProtection SEQUENCE {
        integrityProtInitNumber IntegrityProtInitNumber
    },
    modify                    SEQUENCE {
        dl-IntegrityProtActivationInfo IntegrityProtActivationInfo
    }
}

IntegrityProtectionModeInfo ::= SEQUENCE {
    integrityProtectionModeCommand IntegrityProtectionModeCommand,
    -- TABULAR: DL integrity protection activation info and Integrity

```

```

-- protection intialisation number have been nested inside
-- IntegrityProtectionModeCommand.
integrityProtectionAlgorithm IntegrityProtectionAlgorithm OPTIONAL
}

IntegrityProtInitNumber ::= BIT STRING (SIZE (32))

MaxHcContextSpace ::= ENUMERATED {
    by512, by1024, by2048, by4096,
    by8192 }

MaxROHC-ContextSessions-r4 ::= ENUMERATED {
    s2, s4, s8, s12, s16, s24, s32, s48,
    s64, s128, s256, s512, s1024, s16384 }

MaximumAM-EntityNumberRLC-Cap ::= ENUMERATED {
    am3, am4, am5, am6,
    am8, am16, am30 }

-- Actual value = IE value * 16
MaximumBitRate ::= INTEGER (0..32)

MaximumRLC-WindowSize ::= ENUMERATED { mws2047, mws4095 }

MaxNoDPDCH-BitsTransmitted ::= ENUMERATED {
    b600, b1200, b2400, b4800,
    b9600, b19200, b28800, b38400,
    b48000, b57600 }

MaxNoBits ::= ENUMERATED {
    b640, b1280, b2560, b3840, b5120,
    b6400, b7680, b8960, b10240,
    b20480, b40960, b81920, b163840 }

MaxNoPhysChBitsReceived ::= ENUMERATED {
    b600, b1200, b2400, b3600,
    b4800, b7200, b9600, b14400,
    b19200, b28800, b38400, b48000,
    b57600, b67200, b76800 }

MaxNoSCCPCH-RL ::= ENUMERATED {
    r11 }

MaxNumberOfTF ::= ENUMERATED {
    tf32, tf64, tf128, tf256,
    tf512, tf1024 }

MaxNumberOfTFC-InTFCS-DL ::= ENUMERATED {
    tfc16, tfc32, tfc48, tfc64, tfc96,
    tfc128, tfc256, tfc512, tfc1024 }

MaxNumberOfTFC-InTFCS-UL ::= ENUMERATED {
    tfc4, tfc8, tfc16, tfc32, tfc48, tfc64,
    tfc96, tfc128, tfc256, tfc512, tfc1024 }

MaxPhysChPerFrame ::= INTEGER (1..224)

MaxPhysChPerSubFrame-r4 ::= INTEGER (1..96)

MaxPhysChPerTimeslot ::= ENUMERATED {
    ts1, ts2 }

MaxPhysChPerTS ::= INTEGER (1..16)

MaxSimultaneousCCTrCH-Count ::= INTEGER (1..8)

MaxSimultaneousTransChsDL ::= ENUMERATED {
    e4, e8, e16, e32 }

MaxSimultaneousTransChsUL ::= ENUMERATED {
    e2, e4, e8, e16, e32 }

MaxTransportBlocksDL ::= ENUMERATED {
    tb4, tb8, tb16, tb32, tb48,
    tb64, tb96, tb128, tb256, tb512 }

MaxTransportBlocksUL ::= ENUMERATED {

```

```

        tb2, tb4, tb8, tb16, tb32, tb48,
        tb64, tb96, tb128, tb256, tb512 }

MaxTS-PerFrame ::=                INTEGER (1..14)

MaxTS-PerSubFrame-r4 ::=          INTEGER (1..6)

-- TABULAR: This IE contains dependencies to UE-MultiModeRAT-Capability,
-- the conditional fields have been left mandatory for now.
MeasurementCapability ::=          SEQUENCE {
    downlinkCompressedMode         CompressedModeMeasCapability,
    uplinkCompressedMode           CompressedModeMeasCapability
}

MeasurementCapability-v370 ::=     SEQUENCE{
    compressedModeMeasCapabFDDList CompressedModeMeasCapabFDDList,
    compressedModeMeasCapabTDDList CompressedModeMeasCapabTDDList OPTIONAL,
    compressedModeMeasCapabGSMList CompressedModeMeasCapabGSMList OPTIONAL,
    compressedModeMeasCapabMC      CompressedModeMeasCapabMC      OPTIONAL
}

MeasurementCapability-r4-ext ::=   SEQUENCE {
    downlinkCompressedMode-LCR     CompressedModeMeasCapability-LCR-r4,
    uplinkCompressedMode-LCR       CompressedModeMeasCapability-LCR-r4
}

MessageAuthenticationCode ::=     BIT STRING (SIZE (32))

MinimumSF-DL ::=                   ENUMERATED {
    sf1, sf16 }

MinimumSF-UL ::=                   ENUMERATED {
    sf1, sf2, sf4, sf8, sf16 }

MultiModeCapability ::=            ENUMERATED {
    tdd, fdd, fdd-tdd }

MultiRAT-Capability ::=           SEQUENCE {
    supportOfGSM                    BOOLEAN,
    supportOfMulticarrier           BOOLEAN
}

N-300 ::=                          INTEGER (0..7)
N-301 ::=                          INTEGER (0..7)
N-302 ::=                          INTEGER (0..7)
N-304 ::=                          INTEGER (0..7)
N-308 ::=                          INTEGER (1..8)
N-310 ::=                          INTEGER (0..7)
N-312 ::=                          ENUMERATED {
    s1, s50, s100, s200, s400,
    s600, s800, s1000 }
N-313 ::=                          ENUMERATED {
    s1, s2, s4, s10, s20,
    s50, s100, s200 }
N-315 ::=                          ENUMERATED {
    s1, s50, s100, s200, s400,
    s600, s800, s1000 }

N-AccessFails ::=                 INTEGER (1..64)

N-AP-RetransMax ::=               INTEGER (1..64)

NetworkAssistedGPS-Supported ::=  ENUMERATED {
    networkBased,
    ue-Based,
    bothNetworkAndUE-Based,
    noNetworkAssistedGPS }

NF-BO-AllBusy ::=                 INTEGER (0..31)

```

```

NF-BO-NoAICH ::= INTEGER (0..31)
NF-BO-Mismatch ::= INTEGER (0..127)
NS-BO-Busy ::= INTEGER (0..63)
NS-IP ::= INTEGER (0..28)
P-TMSI-and-RAI-GSM-MAP ::= SEQUENCE {
    p-TMSI P-TMSI-GSM-MAP,
    rai RAI
}
PagingCause ::= ENUMERATED {
    terminatingConversationalCall,
    terminatingStreamingCall,
    terminatingInteractiveCall,
    terminatingBackgroundCall,
    terminatingHighPrioritySignalling,
    terminatingLowPrioritySignalling,
    terminatingCauseUnknown
}
PagingRecord ::= CHOICE {
    cn-Identity SEQUENCE {
        pagingCause PagingCause,
        cn-DomainIdentity CN-DomainIdentity,
        cn-pagedUE-Identity CN-PagedUE-Identity
    },
    utran-Identity SEQUENCE {
        u-RNTI U-RNTI,
        cn-OriginatedPage-connectedMode-UE SEQUENCE {
            pagingCause PagingCause,
            cn-DomainIdentity CN-DomainIdentity,
            pagingRecordTypeID PagingRecordTypeID
        }
    }
} OPTIONAL
PagingRecordList ::= SEQUENCE (SIZE (1..maxPage1)) OF
    PagingRecord
PDCP-Capability ::= SEQUENCE {
    losslessSRNS-RelocationSupport BOOLEAN,
    supportForRfc2507 CHOICE {
        notSupported NULL,
        supported MaxHcContextSpace
    }
}
PDCP-Capability-r4-ext ::= SEQUENCE {
    supportForRfc3095 CHOICE {
        notSupported NULL,
        supported SEQUENCE {
            maxROHC-ContextSessions MaxROHC-ContextSessions-r4 DEFAULT s16,
            reverseCompressionDepth INTEGER (0..65535) DEFAULT 0
        }
    }
}
PhysicalChannelCapability ::= SEQUENCE {
    fddPhysChCapability SEQUENCE {
        downlinkPhysChCapability DL-PhysChCapabilityFDD,
        uplinkPhysChCapability UL-PhysChCapabilityFDD
    }
    OPTIONAL,
    -- The following describes the 3.84Mcps TDD physical channel capability
    tddPhysChCapability SEQUENCE {
        downlinkPhysChCapability DL-PhysChCapabilityTDD,
        uplinkPhysChCapability UL-PhysChCapabilityTDD
    }
    OPTIONAL
}
-- The following describes the 1.28Mcps TDD physical channel capability
PhysicalChannelCapability-LCR-r4 ::= SEQUENCE {
    tdd128-PhysChCapability SEQUENCE {
        downlinkPhysChCapability DL-PhysChCapabilityTDD-LCR-r4,
        uplinkPhysChCapability UL-PhysChCapabilityTDD-LCR-r4
    }
    OPTIONAL
}

```



```

}
PNBSCH-Allocation-r4 ::=          SEQUENCE {
    numberOfRepetitionsPerSFNPeriod  ENUMERATED {
        c2, c3, c4, c5, c6, c7, c8, c9, c10,
        c12, c14, c16, c18, c20, c24, c28, c32,
        c36, c40, c48, c56, c64, c72, c80 }
}

ProtocolErrorCause ::=          ENUMERATED {
    asn1-ViolationOrEncodingError,
    messageTypeNonexistent,
    messageNotCompatibleWithReceiverState,
    ie-ValueNotComprehended,
    conditionalInformationElementError,
    messageExtensionNotComprehended,
    spare1, spare2 }

ProtocolErrorIndicator ::=      ENUMERATED {
    noError, errorOccurred }

ProtocolErrorIndicatorWithMoreInfo ::=
    CHOICE {
        noError                NULL,
        errorOccurred          SEQUENCE {
            rrc-TransactionIdentifier  RRC-TransactionIdentifier,
            protocolErrorInformation   ProtocolErrorInformation
        }
    }

ProtocolErrorMoreInformation ::= SEQUENCE {
    diagnosticsType          CHOICE {
        type1                 CHOICE {
            asn1-ViolationOrEncodingError  NULL,
            messageTypeNonexistent         NULL,
            messageNotCompatibleWithReceiverState
                IdentificationOfReceivedMessage,
            ie-ValueNotComprehended        IdentificationOfReceivedMessage,
            conditionalInformationElementError
                IdentificationOfReceivedMessage,
            messageExtensionNotComprehended
                IdentificationOfReceivedMessage,
            spare1                     NULL,
            spare2                     NULL
        },
        spare                  NULL
    }
}

RadioFrequencyBandFDD ::=      ENUMERATED {
    fdd2100,
    fdd1900,
    spare1, spare2, spare3, spare4, spare5, spare6}

RadioFrequencyBandTDDList ::=  ENUMERATED {
    a, b, c, ab, ac, bc, abc }

RadioFrequencyBandTDD ::=      ENUMERATED {a, b, c, spare}

RadioFrequencyBandGSM ::=      ENUMERATED {
    gsm450,
    gsm480,
    gsm850,
    gsm900P,
    gsm900E,
    gsm1800,
    gsm1900,
    spare1, spare2, spare3, spare4, spare5,
    spare6, spare7, spare8, spare9}

Rb-timer-indicator ::=        SEQUENCE {
    t314-expired              BOOLEAN,
    t315-expired              BOOLEAN }

Re-EstablishmentTimer ::=     ENUMERATED {
    useT314, useT315
}

RedirectionInfo ::=          CHOICE {
    frequencyInfo            FrequencyInfo,

```

```

    interRATInfo
  }
InterRATInfo

RejectionCause ::=
ENUMERATED {
    congestion,
    unspecified }

ReleaseCause ::=
ENUMERATED {
    normalEvent,
    unspecified,
    pre-emptiveRelease,
    congestion,
    re-establishmentReject,
    directedsignallingconnectionre-establishment,
    userInactivity }

RF-Capability ::=
SEQUENCE {
    fddRF-Capability
        ue-PowerClass
        txRxFrequencySeparation
    }
    tddRF-Capability
        ue-PowerClass
        radioFrequencyBandTDDList
        chipRateCapability
    }
}

RF-Capability-r4-ext ::=
SEQUENCE {
    tddRF-Capability
        ue-PowerClass
        radioFrequencyBandTDDList
        chipRateCapability
    }
}

RLC-Capability ::=
SEQUENCE {
    totalRLC-AM-BufferSize
    maximumRLC-WindowSize
    maximumAM-EntityNumber
}

RRC-MessageSequenceNumber ::=
INTEGER (0..15)

RRC-MessageSequenceNumberList ::=
SEQUENCE (SIZE (4..5)) OF
    RRC-MessageSequenceNumber

RRC-StateIndicator ::=
ENUMERATED {
    cell-DCH, cell-FACH, cell-PCH, ura-PCH }

RRC-TransactionIdentifier ::=
INTEGER (0..3)

S-RNTI ::=
BIT STRING (SIZE (20))

S-RNTI-2 ::=
BIT STRING (SIZE (10))

SecurityCapability ::=
SEQUENCE {
    cipheringAlgorithmCap
        BIT STRING {
            spare15(0),
            spare14(1),
            spare13(2),
            spare12(3),
            spare11(4),
            spare10(5),
            spare9(6),
            spare8(7),
            spare7(8),
            spare6(9),
            spare5(10),
            spare4(11),
            spare3(12),
            spare2(13),
            ueal(14),
            uea0(15)
        } (SIZE (16)),
    integrityProtectionAlgorithmCap
        BIT STRING {

```

```

        spare15(0),
        spare14(1),
        spare13(2),
        spare12(3),
        spare11(4),
        spare10(5),
        spare9(6),
        spare8(7),
        spare7(8),
        spare6(9),
        spare5(10),
        spare4(11),
        spare3(12),
        spare2(13),
        uia1(14),
        spare0(15)
    } (SIZE (16))
}

SimultaneousSCCPCH-DPCH-Reception ::= CHOICE {
    notSupported          NULL,
    supported             SEQUENCE {
        maxNoSCCPCH-RL   MaxNoSCCPCH-RL,
        simultaneousSCCPCH-DPCH-DPDCH-Reception
            BOOLEAN
        -- The IE above is applicable only if IE Support of PDSCH = TRUE
    }
}

SRNC-Identity ::=          BIT STRING (SIZE (12))

START-Value ::=          BIT STRING (SIZE (20))

STARTList ::=          SEQUENCE (SIZE (1..maxCNdomains)) OF
                        STARTSingle

STARTSingle ::=          SEQUENCE {
    cn-DomainIdentity     CN-DomainIdentity,
    start-Value           START-Value
}

SystemSpecificCapUpdateReq ::=          ENUMERATED {
    gsm }

SystemSpecificCapUpdateReqList ::= SEQUENCE (SIZE (1..maxSystemCapability)) OF
    SystemSpecificCapUpdateReq

T-300 ::=          ENUMERATED {
    ms100, ms200, ms400, ms600, ms800,
    ms1000, ms1200, ms1400, ms1600,
    ms1800, ms2000, ms3000, ms4000,
    ms6000, ms8000 }

T-301 ::=          ENUMERATED {
    ms100, ms200, ms400, ms600, ms800,
    ms1000, ms1200, ms1400, ms1600,
    ms1800, ms2000, ms3000, ms4000,
    ms6000, ms8000 }

T-302 ::=          ENUMERATED {
    ms100, ms200, ms400, ms600, ms800,
    ms1000, ms1200, ms1400, ms1600,
    ms1800, ms2000, ms3000, ms4000,
    ms6000, ms8000 }

T-304 ::=          ENUMERATED {
    ms100, ms200, ms400,
    ms1000, ms2000, spare1, spare2, spare3 }

T-305 ::=          ENUMERATED {
    noUpdate, m5, m10, m30,
    m60, m120, m360, m720 }

T-307 ::=          ENUMERATED {
    s5, s10, s15, s20,
    s30, s40, s50 }

```

```

T-308 ::=
    ENUMERATED {
        ms40, ms80, ms160, ms320 }

T-309 ::=
    INTEGER (1..8)

T-310 ::=
    ENUMERATED {
        ms40, ms80, ms120, ms160,
        ms200, ms240, ms280, ms320 }

T-311 ::=
    ENUMERATED {
        ms250, ms500, ms750, ms1000,
        ms1250, ms1500, ms1750, ms2000 }

T-312 ::=
    INTEGER (0..15)

T-313 ::=
    INTEGER (0..15)

T-314 ::=
    ENUMERATED {
        s0, s2, s4, s6, s8,
        s12, s16, s20 }

T-315 ::=
    ENUMERATED {
        s0, s10, s30, s60, s180,
        s600, s1200, s1800 }

T-316 ::=
    ENUMERATED {
        s0, s10, s20, s30, s40,
        s50, s-inf }

T-317 ::=
    ENUMERATED {
        s0, s10, s30, s60, s180,
        s600, s1200, s1800 }

T-CPCH ::=
    ENUMERATED {
        ct0, ct1 }

TMSI-and-LAI-GSM-MAP ::=
    tmsi
    lai
    }

TMSI-DS-41 ::=
    OCTET STRING (SIZE (2..12))

TotalRLC-AM-BufferSize ::=
    ENUMERATED {
        kb2, kb10, kb50, kb100,
        kb150, kb500, kb1000 }

-- Actual value = IE value * 0.125
TransmissionProbability ::=
    INTEGER (1..8)

TransportChannelCapability ::=
    dl-TransChCapability
    ul-TransChCapability
    }

TurboSupport ::=
    notSupported
    supported
    }

TxRxFrequencySeparation ::=
    ENUMERATED {
        mhz190, mhz174-8-205-2,
        mhz134-8-245-2 }

U-RNTI ::=
    srcn-Identity
    s-RNTI
    }

U-RNTI-Short ::=
    srcn-Identity
    s-RNTI-2
    }

UE-ConnTimersAndConstants ::=
    SEQUENCE {
-- Optional is used also for parameters for which the default value is the last one read in SIB1
-- t-301 and n-301 should not be used by the UE in this release of the protocol

```

```

t-301          T-301          DEFAULT ms2000,
n-301          N-301          DEFAULT 2,
t-302          T-302          DEFAULT ms4000,
n-302          N-302          DEFAULT 3,
t-304          T-304          DEFAULT ms2000,
n-304          N-304          DEFAULT 2,
t-305          T-305          DEFAULT m30,
t-307          T-307          DEFAULT s30,
t-308          T-308          DEFAULT ms160,
t-309          T-309          DEFAULT 5,
t-310          T-310          DEFAULT ms160,
n-310          N-310          DEFAULT 4,
t-311          T-311          DEFAULT ms2000,
t-312          T-312          DEFAULT 1,
n-312          N-312          DEFAULT s1,
t-313          T-313          DEFAULT 3,
n-313          N-313          DEFAULT s20,
t-314          T-314          DEFAULT s12,
t-315          T-315          DEFAULT s180,
n-315          N-315          DEFAULT s1,
t-316          T-316          DEFAULT s30,
t-317          T-317          DEFAULT s180
}

UE-IdleTimersAndConstants ::= SEQUENCE {
    t-300          T-300,
    n-300          N-300,
    t-312          T-312,
    n-312          N-312
}

UE-MultiModeRAT-Capability ::= SEQUENCE {
    multiRAT-CapabilityList MultiRAT-Capability,
    multiModeCapability      MultiModeCapability
}

UE-PowerClass ::= INTEGER (1..4)

UE-PowerClass-v370 ::= ENUMERATED {class1, class2, class3, class4,
    spare1, spare2, spare3, spare4}

UE-RadioAccessCapability ::= SEQUENCE {
    ics-Version          ICS-Version,
    pdcp-Capability      PDCP-Capability,
    rlc-Capability        RLC-Capability,
    transportChannelCapability TransportChannelCapability,
    rf-Capability         RF-Capability,
    physicalChannelCapability PhysicalChannelCapability,
    ue-MultiModeRAT-Capability UE-MultiModeRAT-Capability,
    securityCapability    SecurityCapability,
    ue-positioning-Capability UE-Positioning-Capability,
    measurementCapability MeasurementCapability OPTIONAL
}

UE-RadioAccessCapability-v370ext ::= SEQUENCE {
    ue-RadioAccessCapabBandFDDList UE-RadioAccessCapabBandFDDList
}

UE-RadioAccessCapabBandFDDList ::= SEQUENCE (SIZE (1..maxFreqBandsFDD)) OF
    UE-RadioAccessCapabBandFDD

UE-RadioAccessCapabBandFDD ::= SEQUENCE{
    radioFrequencyBandFDD          RadioFrequencyBandFDD,
    fddRF-Capability                SEQUENCE {
        ue-PowerClass              UE-PowerClass-v370,
        txRxFrequencySeparation    TxRxFrequencySeparation
    }
    measurementCapability           MeasurementCapability-v370 OPTIONAL,
}

UE-RadioAccessCapability-r4-ext ::= SEQUENCE {
    pdcp-Capability-r4-ext          PDCP-Capability-r4-ext,
    ics-Version-r4                  ICS-Version-r4,
    rf-Capability                   RF-Capability-r4-ext,
    physicalChannelCapability-LCR    PhysicalChannelCapability-LCR-r4,
    measurementCapability-r4-ext     MeasurementCapability-r4-ext OPTIONAL
}

```

```

UL-PhysChCapabilityFDD ::= SEQUENCE {
    maxNoDPDCH-BitsTransmitted MaxNoDPDCH-BitsTransmitted,
    supportOfPCPCH BOOLEAN
}

UL-PhysChCapabilityTDD ::= SEQUENCE {
    maxTS-PerFrame MaxTS-PerFrame,
    maxPhysChPerTimeslot MaxPhysChPerTimeslot,
    minimumSF MinimumSF-UL,
    supportOfPUSCH BOOLEAN
}

UL-PhysChCapabilityTDD-LCR-r4 ::= SEQUENCE {
    maxTS-PerSubFrame MaxTS-PerSubFrame-r4,
    maxPhysChPerTimeslot MaxPhysChPerTimeslot,
    minimumSF MinimumSF-UL,
    supportOfPUSCH BOOLEAN,
    supportOf8PSK BOOLEAN
}

UL-TransChCapability ::= SEQUENCE {
    maxNoBitsTransmitted MaxNoBits,
    maxConvCodeBitsTransmitted MaxNoBits,
    turboDecodingSupport TurboSupport,
    maxSimultaneousTransChs MaxSimultaneousTransChsUL,
    modeSpecificInfo CHOICE {
        fdd NULL,
        tdd SEQUENCE {
            maxSimultaneousCCTrCH-Count MaxSimultaneousCCTrCH-Count
        }
    },
    maxTransmittedBlocks MaxTransportBlocksUL,
    maxNumberOfTFC-InTFCS MaxNumberOfTFC-InTFCS-UL,
    maxNumberOfTF MaxNumberOfTF
}

UE-Positioning-Capability ::= SEQUENCE {
    standaloneLocMethodsSupported BOOLEAN,
    ue-BasedOTDOA-Supported BOOLEAN,
    networkAssistedGPS-Supported NetworkAssistedGPS-Supported,
    gps-ReferenceTimeCapable BOOLEAN,
    supportForIPDL BOOLEAN
}

URA-UpdateCause ::= ENUMERATED {
    changeOfURA,
    periodicURAUpdate,
    re-enteredServiceArea,
    spare1 }

UTRAN-DRX-CycleLengthCoefficient ::= INTEGER (3..9)

WaitTime ::= INTEGER (0..15)

-- *****
--
-- RADIO BEARER INFORMATION ELEMENTS (10.3.4)
--
-- *****

AlgorithmSpecificInfo ::= CHOICE {
    rfc2507-Info RFC2507-Info
}

AlgorithmSpecificInfo-r4 ::= CHOICE {
    rfc2507-Info RFC2507-Info,
    rfc3095-Info RFC3095-Info-r4
}

CID-InclusionInfo-r4 ::= ENUMERATED {
    pdcp-Header,
    rfc3095-PacketFormat }

-- Upper limit is 2^32 - 1
COUNT-C ::= INTEGER (0..4294967295)

-- Upper limit is 2^25 - 1
COUNT-C-MSB ::= INTEGER (0..33554431)

```

```

DefaultConfigIdentity ::=          INTEGER (0..9)

DefaultConfigMode ::=             ENUMERATED {
                                   fdd,
                                   tdd }

DL-AM-RLC-Mode ::=               SEQUENCE {
    inSequenceDelivery             BOOLEAN,
    receivingWindowSize            ReceivingWindowSize,
    dl-RLC-StatusInfo             DL-RLC-StatusInfo
}

DL-CounterSynchronisationInfo ::= SEQUENCE {
    rB-WithPDCP-InfoList          RB-WithPDCP-InfoList    OPTIONAL
}

DL-LogicalChannelMapping ::=      SEQUENCE {
    -- TABULAR: DL-TransportChannelType contains TransportChannelIdentity as well.
    dl-TransportChannelType       DL-TransportChannelType,
    logicalChannelIdentity        LogicalChannelIdentity    OPTIONAL
}

DL-LogicalChannelMappingList ::=  SEQUENCE (SIZE (1..maxLoChperRLC)) OF
    DL-LogicalChannelMapping

DL-RLC-Mode ::=                  CHOICE {
    dl-AM-RLC-Mode               DL-AM-RLC-Mode,
    dl-UM-RLC-Mode               NULL,
    dl-TM-RLC-Mode               DL-TM-RLC-Mode
}

DL-RLC-StatusInfo ::=           SEQUENCE {
    timerStatusProhibit          TimerStatusProhibit    OPTIONAL,
    timerEPC                     TimerEPC                OPTIONAL,
    missingPDU-Indicator         BOOLEAN,
    timerStatusPeriodic          TimerStatusPeriodic      OPTIONAL
}

DL-TM-RLC-Mode ::=              SEQUENCE {
    segmentationIndication       BOOLEAN
}

DL-TransportChannelType ::=      CHOICE {
    dch                          TransportChannelIdentity,
    fach                          NULL,
    dsch                          TransportChannelIdentity,
    dch-and-dsch                  TransportChannelIdentityDCHandDSCH
}

ExpectReordering ::=             ENUMERATED {
    reorderingNotExpected,
    reorderingExpected }

ExplicitDiscard ::=              SEQUENCE {
    timerMRW                      TimerMRW,
    timerDiscard                  TimerDiscard,
    maxMRW                        MaxMRW
}

HeaderCompressionInfo ::=        SEQUENCE {
    algorithmSpecificInfo         AlgorithmSpecificInfo
}

HeaderCompressionInfoList ::=    SEQUENCE (SIZE (1..maxPDCPALgoType)) OF
    HeaderCompressionInfo

HeaderCompressionInfo-r4 ::=      SEQUENCE {
    algorithmSpecificInfo-r4      AlgorithmSpecificInfo-r4
}

HeaderCompressionInfoList-r4 ::= SEQUENCE (SIZE (1..maxPDCPALgoType)) OF
    HeaderCompressionInfo-r4

LogicalChannelIdentity ::=        INTEGER (1..15)

LosslessSRNS-RelocSupport ::=    CHOICE {
    supported                      MaxPDCP-SN-WindowSize,
}

```

```

    notSupported          NULL
}

MAC-LogicalChannelPriority ::=      INTEGER (1..8)

MaxDAT ::=                  ENUMERATED {
    dat1, dat2, dat3, dat4, dat5, dat6,
    dat7, dat8, dat9, dat10, dat15, dat20,
    dat25, dat30, dat35, dat40 }

MaxDAT-Retransmissions ::=        SEQUENCE {
    maxDAT          MaxDAT,
    timerMRW       TimerMRW,
    maxMRW         MaxMRW
}

MaxMRW ::=                  ENUMERATED {
    mm1, mm4, mm6, mm8, mm12, mm16,
    mm24, mm32 }

MaxPDCP-SN-WindowSize ::=        ENUMERATED {
    sn255, sn65535 }

MaxRST ::=                  ENUMERATED {
    rst1, rst4, rst6, rst8, rst12,
    rst16, rst24, rst32 }

NoExplicitDiscard ::=          ENUMERATED {
    dt10, dt20, dt30, dt40, dt50,
    dt60, dt70, dt80, dt90, dt100 }

PDCP-Info ::=                SEQUENCE {
    losslessSRNS-RelocSupport      LosslessSRNS-RelocSupport      OPTIONAL,
    pdcp-PDU-Header                PDCP-PDU-Header,
    -- TABULAR: The IE above is MD in the tabular format and it can be encoded
    -- in one bit, so the OPTIONAL is removed for compactness.
    headerCompressionInfoList      HeaderCompressionInfoList      OPTIONAL
}

PDCP-Info-r4 ::=              SEQUENCE {
    losslessSRNS-RelocSupport      LosslessSRNS-RelocSupport      OPTIONAL,
    pdcp-PDU-Header                PDCP-PDU-Header,
    -- TABULAR: The IE above is MD in the tabular format and it can be encoded
    -- in one bit, so the OPTIONAL is removed for compactness.
    headerCompressionInfoList      HeaderCompressionInfoList-r4      OPTIONAL
}

PDCP-InfoReconfig ::=         SEQUENCE {
    pdcp-Info                      PDCP-Info,
    -- dummy is not used in this version of the protocol
    dummy                          INTEGER (0..65535)
}

PDCP-InfoReconfig-r4 ::=      SEQUENCE {
    pdcp-Info                      PDCP-Info-r4,
    pdcp-SN-Info                   PDCP-SN-Info
}

PDCP-PDU-Header ::=           ENUMERATED {
    present, absent }

PDCP-SN-Info ::=              INTEGER (0..65535)

Poll-PDU ::=                  ENUMERATED {
    pdu1, pdu2, pdu4, pdu8, pdu16,
    pdu32, pdu64, pdu128 }

Poll-SDU ::=                  ENUMERATED {
    sdu1, sdu4, sdu16, sdu64 }

PollingInfo ::=               SEQUENCE {
    timerPollProhibit              TimerPollProhibit              OPTIONAL,
    timerPoll                      TimerPoll                      OPTIONAL,
    poll-PDU                       Poll-PDU                      OPTIONAL,
    poll-SDU                       Poll-SDU                      OPTIONAL,
    lastTransmissionPDU-Poll       BOOLEAN,
    lastRetransmissionPDU-Poll     BOOLEAN,
    pollWindow                     PollWindow                     OPTIONAL,
}

```



```

    timerPollPeriodic                TimerPollPeriodic                OPTIONAL
}

PollWindow ::=                       ENUMERATED {
    pw50, pw60, pw70, pw80, pw85,
    pw90, pw95, pw99 }

PredefinedConfigIdentity ::=         INTEGER (0..15)

PredefinedConfigValueTag ::=         INTEGER (0..15)

PredefinedRB-Configuration ::=       SEQUENCE {
    re-EstablishmentTimer             Re-EstablishmentTimer,
    srb-InformationList                SRB-InformationSetupList,
    rb-InformationList                 RB-InformationSetupList
}

PreDefRadioConfiguration ::=         SEQUENCE {
    -- Radio bearer IEs
    predefinedRB-Configuration         PredefinedRB-Configuration,
    -- Transport channel IEs
    preDefTransChConfiguration         PreDefTransChConfiguration,
    -- Physical channel IEs
    preDefPhyChConfiguration           PreDefPhyChConfiguration
}

RAB-Info ::=                          SEQUENCE {
    rab-Identity                       RAB-Identity,
    cn-DomainIdentity                  CN-DomainIdentity,
    nas-Synchronisation-Indicator      NAS-Synchronisation-Indicator OPTIONAL,
    re-EstablishmentTimer              Re-EstablishmentTimer
}

RAB-InformationList ::=                SEQUENCE (SIZE (1..maxRABsetup)) OF
    RAB-Info

RAB-InformationReconfigList ::=       SEQUENCE (SIZE (1.. maxRABsetup)) OF
    RAB-InformationReconfig

RAB-InformationReconfig ::=           SEQUENCE {
    rab-Identity                       RAB-Identity,
    cn-DomainIdentity                  CN-DomainIdentity,
    nas-Synchronisation-Indicator      NAS-Synchronisation-Indicator
}

RAB-Info-Post ::=                     SEQUENCE {
    rab-Identity                       RAB-Identity,
    cn-DomainIdentity                  CN-DomainIdentity,
    nas-Synchronisation-Indicator      NAS-Synchronisation-Indicator OPTIONAL
}

RAB-InformationSetup ::=              SEQUENCE {
    rab-Info                           RAB-Info,
    rb-InformationSetupList            RB-InformationSetupList
}

RAB-InformationSetup-r4 ::=           SEQUENCE {
    rab-Info                           RAB-Info,
    rb-InformationSetupList-r4         RB-InformationSetupList-r4
}

RAB-InformationSetupList ::=          SEQUENCE (SIZE (1..maxRABsetup)) OF
    RAB-InformationSetup

RAB-InformationSetupList-r4 ::=       SEQUENCE (SIZE (1..maxRABsetup)) OF
    RAB-InformationSetup-r4

RB-ActivationTimeInfo ::=             SEQUENCE {
    rb-Identity                        RB-Identity,
    rlc-SequenceNumber                 RLC-SequenceNumber
}

RB-ActivationTimeInfoList ::=         SEQUENCE (SIZE (1..maxRB)) OF
    RB-ActivationTimeInfo

RB-COUNT-C-Information ::=            SEQUENCE {
    rb-Identity                        RB-Identity,
    count-C-UL                         COUNT-C,
    count-C-DL                         COUNT-C
}

```

```

}

RB-COUNT-C-InformationList ::= SEQUENCE (SIZE (1..maxRBallRABs)) OF
                               RB-COUNT-C-Information

RB-COUNT-C-MSB-Information ::= SEQUENCE {
    rb-Identity                RB-Identity,
    count-C-MSB-UL             COUNT-C-MSB,
    count-C-MSB-DL             COUNT-C-MSB
}

RB-COUNT-C-MSB-InformationList ::= SEQUENCE (SIZE (1..maxRBallRABs)) OF
                                    RB-COUNT-C-MSB-Information

RB-Identity ::= INTEGER (1..32)

RB-IdentityList ::= SEQUENCE (SIZE (1..maxRB)) OF
                    RB-Identity

RB-InformationAffected ::= SEQUENCE {
    rb-Identity                RB-Identity,
    rb-MappingInfo             RB-MappingInfo
}

RB-InformationAffectedList ::= SEQUENCE (SIZE (1..maxRB)) OF
                                RB-InformationAffected

RB-InformationReconfig ::= SEQUENCE {
    rb-Identity                RB-Identity,
    pdcp-Info                  PDCP-InfoReconfig           OPTIONAL,
    pdcp-SN-Info               PDCP-SN-Info             OPTIONAL,
    rlc-Info                    RLC-Info                 OPTIONAL,
    rb-MappingInfo              RB-MappingInfo           OPTIONAL,
    rb-StopContinue             RB-StopContinue         OPTIONAL
}

RB-InformationReconfig-r4 ::= SEQUENCE {
    rb-Identity                RB-Identity,
    pdcp-Info                  PDCP-InfoReconfig-r4     OPTIONAL,
    rlc-Info                    RLC-Info                 OPTIONAL,
    rb-MappingInfo              RB-MappingInfo           OPTIONAL,
    rb-StopContinue             RB-StopContinue         OPTIONAL
}

RB-InformationReconfigList ::= SEQUENCE (SIZE (1..maxRB)) OF
                                RB-InformationReconfig

RB-InformationReconfigList-r4 ::= SEQUENCE (SIZE (1..maxRB)) OF
                                    RB-InformationReconfig-r4

RB-InformationReleaseList ::= SEQUENCE (SIZE (1..maxRB)) OF
                                RB-Identity

RB-InformationSetup ::= SEQUENCE {
    rb-Identity                RB-Identity,
    pdcp-Info                  PDCP-Info                 OPTIONAL,
    rlc-InfoChoice              RLC-InfoChoice            OPTIONAL,
    rb-MappingInfo              RB-MappingInfo
}

RB-InformationSetup-r4 ::= SEQUENCE {
    rb-Identity                RB-Identity,
    pdcp-Info                  PDCP-Info-r4              OPTIONAL,
    rlc-Info                    RLC-Info,
    rb-MappingInfo              RB-MappingInfo
}

RB-InformationSetupList ::= SEQUENCE (SIZE (1..maxRBperRAB)) OF
                                RB-InformationSetup

RB-InformationSetupList-r4 ::= SEQUENCE (SIZE (1..maxRBperRAB)) OF
                                    RB-InformationSetup-r4

RB-MappingInfo ::= SEQUENCE (SIZE (1..maxRBMuxOptions)) OF
                    RB-MappingOption

RB-MappingOption ::= SEQUENCE {
    ul-LogicalChannelMappings UL-LogicalChannelMappings OPTIONAL,

```

```

    dl-LogicalChannelMappingList          DL-LogicalChannelMappingList          OPTIONAL
}

RB-StopContinue ::=                      ENUMERATED {
                                        stopRB, continueRB }

RB-WithPDCP-Info ::=                     SEQUENCE {
    rb-Identity                          RB-Identity,
    pdcp-SN-Info                          PDCP-SN-Info
}

RB-WithPDCP-InfoList ::=                 SEQUENCE (SIZE (1..maxRBallRABs)) OF
                                        RB-WithPDCP-Info

ReceivingWindowSize ::=                  ENUMERATED {
    rw1, rw8, rw16, rw32, rw64, rw128, rw256,
    rw512, rw768, rw1024, rw1536, rw2047,
    rw2560, rw3072, rw3584, rw4095 }

RFC2507-Info ::=                         SEQUENCE {
    f-MAX-PERIOD                          INTEGER (1..65535)                DEFAULT 256,
    f-MAX-TIME                             INTEGER (1..255)                  DEFAULT 5,
    max-HEADER                             INTEGER (60..65535)              DEFAULT 168,
    tcp-SPACE                              INTEGER (3..255)                 DEFAULT 15,
    non-TCP-SPACE                          INTEGER (3..65535)              DEFAULT 15,
    expectReordering                       ExpectReordering
    -- TABULAR: The IE above has only two possible values, so using Optional or Default
    -- would be wasteful
}

RFC3095-Info-r4 ::=                       SEQUENCE {
    cid-InclusionInfo                       CID-InclusionInfo-r4,
    max-CID                                INTEGER (1..16383)                DEFAULT 15,
    rohcProfileList                        ROHC-ProfileList-r4,
    mrru                                   INTEGER (0..65535)              DEFAULT 0,
    rohcPacketSizeList                    ROHC-PacketSizeList-r4,
    reverseDecompressionDepth              INTEGER (0..65535)              DEFAULT 0
}

RLC-Info ::=                              SEQUENCE {
    ul-RLC-Mode                            UL-RLC-Mode                      OPTIONAL,
    dl-RLC-Mode                            DL-RLC-Mode                      OPTIONAL
}

RLC-InfoChoice ::=                        CHOICE {
    rlc-Info                               RLC-Info,
    same-as-RB                             RB-Identity
}

RLC-SequenceNumber ::=                   INTEGER (0..4095)

RLC-SizeInfo ::=                          SEQUENCE {
    rlc-SizeIndex                          INTEGER (1..maxTF)
}

RLC-SizeExplicitList ::=                  SEQUENCE (SIZE (1..maxTF)) OF
                                        RLC-SizeInfo

ROHC-Profile-r4 ::=                       INTEGER (1..3)

ROHC-ProfileList-r4 ::=                   SEQUENCE (SIZE (1..maxROHC-Profile-r4)) OF
                                        ROHC-Profile-r4

ROHC-PacketSize-r4 ::=                    INTEGER (2..1500)

ROHC-PacketSizeList-r4 ::=                SEQUENCE (SIZE (1..maxROHC-PacketSizes-r4)) OF
                                        ROHC-PacketSize-r4

SRB-InformationSetup ::=                  SEQUENCE {
    rb-Identity                            RB-Identity                      OPTIONAL,
    -- The default value for the IE above is the smallest value not used yet.
    rlc-InfoChoice                          RLC-InfoChoice,
    rb-MappingInfo                          RB-MappingInfo
}

SRB-InformationSetupList ::=              SEQUENCE (SIZE (1..maxSRBsetup)) OF
                                        SRB-InformationSetup

```

```

SRB-InformationSetupList2 ::= SEQUENCE (SIZE (3..4)) OF
                               SRB-InformationSetup

TimerDiscard ::= ENUMERATED {
                   td0-1, td0-25, td0-5, td0-75,
                   td1, td1-25, td1-5, td1-75,
                   td2, td2-5, td3, td3-5, td4,
                   td4-5, td5, td7-5 }

TimerEPC ::= ENUMERATED {
              te50, te60, te70, te80, te90,
              te100, te120, te140, te160, te180,
              te200, te300, te400, te500, te700,
              te900 }

TimerMRW ::= ENUMERATED {
              te50, te60, te70, te80, te90, te100,
              te120, te140, te160, te180, te200,
              te300, te400, te500, te700, te900 }

TimerPoll ::= ENUMERATED {
               tp10, tp20, tp30, tp40, tp50,
               tp60, tp70, tp80, tp90, tp100,
               tp110, tp120, tp130, tp140, tp150,
               tp160, tp170, tp180, tp190, tp200,
               tp210, tp220, tp230, tp240, tp250,
               tp260, tp270, tp280, tp290, tp300,
               tp310, tp320, tp330, tp340, tp350,
               tp360, tp370, tp380, tp390, tp400,
               tp410, tp420, tp430, tp440, tp450,
               tp460, tp470, tp480, tp490, tp500,
               tp510, tp520, tp530, tp540, tp550,
               tp600, tp650, tp700, tp750, tp800,
               tp850, tp900, tp950, tp1000 }

TimerPollPeriodic ::= ENUMERATED {
                       tper100, tper200, tper300, tper400,
                       tper500, tper750, tper1000, tper2000 }

TimerPollProhibit ::= ENUMERATED {
                       tpp10, tpp20, tpp30, tpp40, tpp50,
                       tpp60, tpp70, tpp80, tpp90, tpp100,
                       tpp110, tpp120, tpp130, tpp140, tpp150,
                       tpp160, tpp170, tpp180, tpp190, tpp200,
                       tpp210, tpp220, tpp230, tpp240, tpp250,
                       tpp260, tpp270, tpp280, tpp290, tpp300,
                       tpp310, tpp320, tpp330, tpp340, tpp350,
                       tpp360, tpp370, tpp380, tpp390, tpp400,
                       tpp410, tpp420, tpp430, tpp440, tpp450,
                       tpp460, tpp470, tpp480, tpp490, tpp500,
                       tpp510, tpp520, tpp530, tpp540, tpp550,
                       tpp600, tpp650, tpp700, tpp750, tpp800,
                       tpp850, tpp900, tpp950, tpp1000 }

TimerRST ::= ENUMERATED {
              tr50, tr100, tr150, tr200, tr250, tr300,
              tr350, tr400, tr450, tr500, tr550,
              tr600, tr700, tr800, tr900, tr1000 }

TimerStatusPeriodic ::= ENUMERATED {
                       tsp100, tsp200, tsp300, tsp400, tsp500,
                       tsp750, tsp1000, tsp2000 }

TimerStatusProhibit ::= ENUMERATED {
                       tsp10, tsp20, tsp30, tsp40, tsp50,
                       tsp60, tsp70, tsp80, tsp90, tsp100,
                       tsp110, tsp120, tsp130, tsp140, tsp150,
                       tsp160, tsp170, tsp180, tsp190, tsp200,
                       tsp210, tsp220, tsp230, tsp240, tsp250,
                       tsp260, tsp270, tsp280, tsp290, tsp300,
                       tsp310, tsp320, tsp330, tsp340, tsp350,
                       tsp360, tsp370, tsp380, tsp390, tsp400,
                       tsp410, tsp420, tsp430, tsp440, tsp450,
                       tsp460, tsp470, tsp480, tsp490, tsp500,
                       tsp510, tsp520, tsp530, tsp540, tsp550,
                       tsp600, tsp650, tsp700, tsp750, tsp800,
                       tsp850, tsp900, tsp950, tsp1000 }

```

```

TransmissionRLC-Discard ::=          CHOICE {
    timerBasedExplicit                ExplicitDiscard,
    timerBasedNoExplicit              NoExplicitDiscard,
    maxDAT-Retransmissions           MaxDAT-Retransmissions,
    noDiscard                         MaxDAT
}

TransmissionWindowSize ::=          ENUMERATED {
    tw1, tw8, tw16, tw32, tw64, tw128, tw256,
    tw512, tw768, tw1024, tw1536, tw2047,
    tw2560, tw3072, tw3584, tw4095 }

UL-AM-RLC-Mode ::=                 SEQUENCE {
    transmissionRLC-Discard           TransmissionRLC-Discard,
    transmissionWindowSize            TransmissionWindowSize,
    timerRST                          TimerRST,
    max-RST                           MaxRST,
    pollingInfo                       PollingInfo                               OPTIONAL
}

UL-CounterSynchronisationInfo ::=  SEQUENCE {
    rB-WithPDCP-InfoList             RB-WithPDCP-InfoList    OPTIONAL,
    startList                         STARTList
}

UL-LogicalChannelMapping ::=        SEQUENCE {
    -- TABULAR: UL-TransportChannelType contains TransportChannelIdentity as well.
    ul-TransportChannelType          UL-TransportChannelType,
    logicalChannelIdentity            LogicalChannelIdentity    OPTIONAL,
    rlc-SizeList                     CHOICE {
        allSizes                     NULL,
        configured                   NULL,
        explicitList                 RLC-SizeExplicitList
    },
    mac-LogicalChannelPriority        MAC-LogicalChannelPriority
}

UL-LogicalChannelMappingList ::=    SEQUENCE {
    rlc-LogicalChannelMappingIndicator  BOOLEAN,    -- NOTE: This parameter shall be set to TRUE in
this release
    ul-LogicalChannelMapping          SEQUENCE (SIZE (maxLoCHperRLC)) OF
UL-LogicalChannelMapping
}

UL-LogicalChannelMappings ::=       CHOICE {
    oneLogicalChannel                 UL-LogicalChannelMapping,
    twoLogicalChannels                UL-LogicalChannelMappingList
}

UL-RLC-Mode ::=                    CHOICE {
    ul-AM-RLC-Mode                   UL-AM-RLC-Mode,
    ul-UM-RLC-Mode                   UL-UM-RLC-Mode,
    ul-TM-RLC-Mode                   UL-TM-RLC-Mode,
    spare                             NULL
}

UL-TM-RLC-Mode ::=                 SEQUENCE {
    transmissionRLC-Discard           TransmissionRLC-Discard    OPTIONAL,
    segmentationIndication           BOOLEAN
}

UL-UM-RLC-Mode ::=                 SEQUENCE {
    transmissionRLC-Discard           TransmissionRLC-Discard    OPTIONAL
}

UL-TransportChannelType ::=         CHOICE {
    dch                               TransportChannelIdentity,
    rach                              NULL,
    cpch                              NULL,
    usch                              TransportChannelIdentity
}

-- *****
--
--     TRANSPORT CHANNEL INFORMATION ELEMENTS (10.3.5)
--
-- *****

```

```

AllowedTFC-List ::=                               SEQUENCE (SIZE (1..maxTFC)) OF
                                                  TFC-Value

AllowedTFI-List ::=                               SEQUENCE (SIZE (1..maxTF)) OF
                                                  INTEGER (0..31)

BitModeRLC-SizeInfo ::=                          CHOICE {
  sizeType1                                       INTEGER (0..127),
  sizeType2                                       SEQUENCE {
    part1                                         INTEGER (0..15),
    part2                                         INTEGER (1..7)                                     OPTIONAL
    -- Actual size = (part1 * 8) + 128 + part2
  },
  sizeType3                                       SEQUENCE {
    part1                                         INTEGER (0..47),
    part2                                         INTEGER (1..15)                                 OPTIONAL
    -- Actual size = (part1 * 16) + 256 + part2
  },
  sizeType4                                       SEQUENCE {
    part1                                         INTEGER (0..62),
    part2                                         INTEGER (1..63)                                 OPTIONAL
    -- Actual size = (part1 * 64) + 1024 + part2
  }
}
-- Actual value = IE value * 0.1
BLER-QualityValue ::=                            INTEGER (-63..0)

ChannelCodingType ::=                            CHOICE {
  noCoding                                         NULL,
  convolutional                                    CodingRate,
  turbo                                            NULL
}

CodingRate ::=                                   ENUMERATED {
  half,
  third }

CommonDynamicTF-Info ::=                         SEQUENCE {
  rlc-Size                                         CHOICE {
    fdd                                           SEQUENCE {
      octetModeRLC-SizeInfoType2                 OctetModeRLC-SizeInfoType2
    },
    tdd                                           SEQUENCE {
      commonTDD-Choice                           CHOICE {
        bitModeRLC-SizeInfo                     BitModeRLC-SizeInfo,
        octetModeRLC-SizeInfoType1              OctetModeRLC-SizeInfoType1
      }
    }
  },
  numberOfTbSizeList                               SEQUENCE (SIZE (1..maxTF)) OF
                                                  NumberOfTransportBlocks,
  logicalChannelList                               LogicalChannelList
}

CommonDynamicTF-Info-DynamicTTI ::= SEQUENCE {
  commonTDD-Choice                                CHOICE {
    bitModeRLC-SizeInfo                          BitModeRLC-SizeInfo,
    octetModeRLC-SizeInfoType1                  OctetModeRLC-SizeInfoType1
  },
  numberOfTbSizeAndTTIList                       NumberOfTbSizeAndTTIList,
  logicalChannelList                             LogicalChannelList
}

CommonDynamicTF-InfoList ::=                     SEQUENCE (SIZE (1..maxTF)) OF
                                                  CommonDynamicTF-Info

CommonDynamicTF-InfoList-DynamicTTI ::= SEQUENCE (SIZE (1..maxTF)) OF
                                                  CommonDynamicTF-Info-DynamicTTI

CommonTransChTFS ::=                             SEQUENCE {
  tti                                             CHOICE {
    tti10                                         CommonDynamicTF-InfoList,
    tti20                                         CommonDynamicTF-InfoList,
    tti40                                         CommonDynamicTF-InfoList,
    tti80                                         CommonDynamicTF-InfoList,
    dynamic                                       CommonDynamicTF-InfoList-DynamicTTI
  },
}

```

```

    semistaticTF-Information          SemistaticTF-Information
}

CommonTransChTFS-LCR ::=
    tti
        tti5
        tti10
        tti20
        tti40
        tti80
        dynamic
    },
    semistaticTF-Information          SemistaticTF-Information
}

CPCH-SetID ::=
    INTEGER (1..maxCPCHsets)

CRC-Size ::=
    ENUMERATED {
        crc0, crc8, crc12, crc16, crc24 }

DedicatedDynamicTF-Info ::=
    rlc-Size
        bitMode
        octetModeType1
    },
    numberOfTbSizeList
    NumberOfTransportBlocks,
    logicalChannelList
}

DedicatedDynamicTF-Info-DynamicTTI ::= SEQUENCE {
    rlc-Size
        bitMode
        octetModeType1
    },
    numberOfTbSizeAndTTIList
    logicalChannelList
}

DedicatedDynamicTF-InfoList ::= SEQUENCE (SIZE (1..maxTF)) OF
    DedicatedDynamicTF-Info

DedicatedDynamicTF-InfoList-DynamicTTI ::= SEQUENCE (SIZE (1..maxTF)) OF
    DedicatedDynamicTF-Info-DynamicTTI

DedicatedTransChTFS ::=
    tti
        tti10
        tti20
        tti40
        tti80
        dynamic
    },
    semistaticTF-Information          SemistaticTF-Information
}

DL-AddReconfTransChInfo2List ::= SEQUENCE (SIZE (1..maxTrCH)) OF
    DL-AddReconfTransChInformation2

DL-AddReconfTransChInfoList ::= SEQUENCE (SIZE (1..maxTrCH)) OF
    DL-AddReconfTransChInformation

-- ASN.1 for IE "Added or Reconfigured DL TrCH information"
-- in case of messages other than: Radio Bearer Release message and
-- Radio Bearer Reconfiguration message
DL-AddReconfTransChInformation ::= SEQUENCE {
    dl-TransportChannelType          DL-TrCH-Type,
    dl-transportChannelIdentity      TransportChannelIdentity,
    tfs-SignallingMode
        explicit
        sameAsULTrCH
    },
    dch-QualityTarget                QualityTarget
    tm-SignallingInfo                TM-SignallingInfo
}

-- ASN.1 for IE "Added or Reconfigured DL TrCH information"
-- in case of Radio Bearer Release message and

```

```

-- Radio Bearer Reconfiguration message
DL-AddReconfTransChInformation2 ::= SEQUENCE {
    dl-TransportChannelType      DL-TrCH-Type,
    transportChannelIdentity     TransportChannelIdentity,
    tfs-SignallingMode          CHOICE {
        explicit                 TransportFormatSet,
        sameAsULTrCH            UL-TransportChannelIdentity
    },
    qualityTarget                QualityTarget
}

DL-CommonTransChInfo ::= SEQUENCE {
    sccpch-TFCS                  TFCS
    modeSpecificInfo             CHOICE {
        fdd                      SEQUENCE {
            dl-Parameters        CHOICE {
                dl-DCH-TFCS      TFCS,
                sameAsUL         NULL
            }
        },
        tdd                      SEQUENCE {
            individualDL-CCTrCH-InfoList IndividualDL-CCTrCH-InfoList
        }
    }
}
-- NOTE: CHOICE modeSpecificInfo should be optional. A new version of this IE
-- should be defined to be used in later versions of messages using this IE

DL-CommonTransChInfo-r4 ::= SEQUENCE {
    sccpch-TFCS                  TFCS
    modeSpecificInfo             CHOICE {
        fdd                      SEQUENCE {
            dl-Parameters        CHOICE {
                dl-DCH-TFCS      TFCS
                tfs               TFCS
            },
            sameAsUL              NULL
        },
        tdd                      SEQUENCE {
            individualDL-CCTrCH-InfoList IndividualDL-CCTrCH-InfoList
        }
    }
}

DL-DeletedTransChInfoList ::= SEQUENCE (SIZE (1..maxTrCH)) OF
    DL-TransportChannelIdentity

DL-TransportChannelIdentity ::= SEQUENCE {
    dl-TransportChannelType     DL-TrCH-Type,
    dl-TransportChannelIdentity TransportChannelIdentity
}

DL-TrCH-Type ::= ENUMERATED {dch, dsch}

DRAC-ClassIdentity ::= INTEGER (1..maxDRACclasses)

DRAC-StaticInformation ::= SEQUENCE {
    transmissionTimeValidity    TransmissionTimeValidity,
    timeDurationBeforeRetry     TimeDurationBeforeRetry,
    drac-ClassIdentity          DRAC-ClassIdentity
}

DRAC-StaticInformationList ::= SEQUENCE (SIZE (1..maxTrCH)) OF
    DRAC-StaticInformation

ExplicitTFCS-Configuration ::= CHOICE {
    complete                    TFCS-ReconfAdd,
    addition                    TFCS-ReconfAdd,
    removal                     TFCS-RemovalList,
    replacement                 SEQUENCE {
        tfsRemoval              TFCS-RemovalList,
        tfsAdd                  TFCS-ReconfAdd
    }
}

```



```

GainFactor ::=                               INTEGER (0..15)

GainFactorInformation ::=                    CHOICE {
    signalledGainFactors                     SignalledGainFactors,
    computedGainFactors                      ReferenceTFC-ID
}

IndividualDL-CCTrCH-Info ::=                 SEQUENCE {
    dl-TFCS-Identity                         TFCS-Identity,
    tfcs-SignallingMode                     CHOICE {
        explicit                             TFCS,
        sameAsUL                             TFCS-Identity
    }
}

IndividualDL-CCTrCH-InfoList ::=             SEQUENCE (SIZE (1..maxCCTrCH)) OF
    IndividualDL-CCTrCH-Info

IndividualUL-CCTrCH-Info ::=                 SEQUENCE {
    ul-TFCS-Identity                         TFCS-Identity,
    ul-TFCS                                  TFCS ,
    tfc-Subset                               TFC-Subset
}

IndividualUL-CCTrCH-InfoList ::=             SEQUENCE (SIZE (1..maxCCTrCH)) OF
    IndividualUL-CCTrCH-Info

LogicalChannelByRB ::=                       SEQUENCE {
    rb-Identity                              RB-Identity,
    logChOfRb                                INTEGER (0..1)
}
OPTIONAL

LogicalChannelList ::=                       CHOICE {
    allSizes                                 NULL,
    configured                              NULL,
    explicitList                            SEQUENCE (SIZE (1..15)) OF
        LogicalChannelByRB
}

NumberOfTbSizeAndTTIList ::=                 SEQUENCE (SIZE (1..maxTF)) OF SEQUENCE {
    numberOfTransportBlocks                 NumberOfTransportBlocks,
    transmissionTimeInterval                TransmissionTimeInterval
}

MessType ::=                                 ENUMERATED {
    transportFormatCombinationControl }

Non-allowedTFC-List ::=                     SEQUENCE (SIZE (1..maxTFC)) OF
    TFC-Value

NumberOfTransportBlocks ::=                  CHOICE {
    zero                                    NULL,
    one                                     NULL,
    small                                  INTEGER (2..17),
    large                                  INTEGER (18..512)
}

OctetModeRLC-SizeInfoType1 ::=              CHOICE {
    sizeType1                               INTEGER (0..31),
    -- Actual size = (8 * sizeType1) + 16
    sizeType2                               SEQUENCE {
        part1                               INTEGER (0..23),
        part2                               INTEGER (1..3)
    },
    -- Actual size = (32 * part1) + 272 + (part2 * 8)
    sizeType3                               SEQUENCE {
        part1                               INTEGER (0..61),
        part2                               INTEGER (1..7)
    },
    -- Actual size = (64 * part1) + 1040 + (part2 * 8)
}
OPTIONAL
OPTIONAL

OctetModeRLC-SizeInfoType2 ::=              CHOICE {
    sizeType1                               INTEGER (0..31),
    -- Actual size = (sizeType1 * 8) + 48
    sizeType2                               INTEGER (0..63),
    -- Actual size = (sizeType2 * 16) + 312
    sizeType3                               INTEGER (0..56)
}

```

```

-- Actual size = (sizeType3 *64) + 1384
}

PowerOffsetInformation ::=          SEQUENCE {
    gainFactorInformation            GainFactorInformation,
    -- PowerOffsetPp-m is always absent in TDD
    powerOffsetPp-m                 PowerOffsetPp-m           OPTIONAL
}

PowerOffsetPp-m ::=                INTEGER (-5..10)

PreDefTransChConfiguration ::=    SEQUENCE {
    ul-CommonTransChInfo            UL-CommonTransChInfo,
    ul-AddReconfTrChInfoList        UL-AddReconfTransChInfoList,
    dl-CommonTransChInfo            DL-CommonTransChInfo,
    dl-TrChInfoList                 DL-AddReconfTransChInfoList
}

QualityTarget ::=                  SEQUENCE {
    bler-QualityValue               BLER-QualityValue
}

RateMatchingAttribute ::=          INTEGER (1..hIRM)

ReferenceTFC-ID ::=                INTEGER (0..3)

RestrictedTrChInfo ::=              SEQUENCE {
    ul-TransportChannelType          UL-TrCH-Type,
    restrictedTrChIdentity            TransportChannelIdentity,
    allowedTFI-List                  AllowedTFI-List           OPTIONAL
}

RestrictedTrChInfoList ::=          SEQUENCE (SIZE (1..maxTrCH)) OF
    RestrictedTrChInfo

SemistaticTF-Information ::=        SEQUENCE {
    -- TABULAR: Transmission time interval has been included in the IE CommonTransChTFS.
    channelCodingType                ChannelCodingType,
    rateMatchingAttribute             RateMatchingAttribute,
    crc-Size                          CRC-Size
}

SignalledGainFactors ::=            SEQUENCE {
    modeSpecificInfo                 CHOICE {
        fdd                           SEQUENCE {
            gainFactorBetaC            GainFactor
        },
        tdd                             NULL
    },
    gainFactorBetaD                   GainFactor,
    referenceTFC-ID                   ReferenceTFC-ID           OPTIONAL
}

SplitTFCI-Signalling ::=            SEQUENCE {
    splitType                         SplitType                OPTIONAL,
    tfci-Field2-Length                INTEGER (1..10)           OPTIONAL,
    tfci-Field1-Information            ExplicitTFCS-Configuration OPTIONAL,
    tfci-Field2-Information            TFCI-Field2-Information  OPTIONAL
}

SplitType ::=                       ENUMERATED {
    hardSplit, logicalSplit }

TFC-Subset ::=                       CHOICE {
    minimumAllowedTFC-Number          TFC-Value,
    allowedTFC-List                    AllowedTFC-List,
    non-allowedTFC-List                Non-allowedTFC-List,
    restrictedTrChInfoList              RestrictedTrChInfoList,
    fullTFCS                            NULL
}

TFC-Value ::=                       INTEGER (0..1023)

TFCI-Field2-Information ::=          CHOICE {
    tfci-Range                         TFCI-RangeList,
    explicit                            ExplicitTFCS-Configuration
}

```

```

TFCI-Range ::=
    maxTFCIField2Value
    tfcs-InfoForDSCH
}

TFCI-RangeList ::=
    SEQUENCE (SIZE (1..maxPDSCH-TFCIgroups)) OF
        TFCI-Range

TFCs ::=
    normalTFCI-Signalling
    splitTFCI-Signalling
}

TFCs-Identity ::=
    tfcs-ID
    sharedChannelIndicator
}

TFCs-IdentityPlain ::=
    INTEGER (1..8)

TFCs-InfoForDSCH ::=
    ctfc2bit
    ctfc4bit
    ctfc6bit
    ctfc8bit
    ctfc12bit
    ctfc16bit
    ctfc24bit
}

TFCs-ReconfAdd ::=
    SEQUENCE{
        ctfcSize
        ctfc2Bit
            ctfc2
            powerOffsetInformation
        },
        ctfc4Bit
            ctfc4
            powerOffsetInformation
        },
        ctfc6Bit
            ctfc6
            powerOffsetInformation
        },
        ctfc8Bit
            ctfc8
            powerOffsetInformation
        },
        ctfc12Bit
            ctfc12
            powerOffsetInformation
        },
        ctfc16Bit
            ctfc16
            powerOffsetInformation
        },
        ctfc24Bit
            ctfc24
            powerOffsetInformation
        }
    }

TFCs-Removal ::=
    SEQUENCE {
        tfci
            INTEGER (0..1023)
    }

TFCs-RemovalList ::=
    SEQUENCE (SIZE (1..maxTFC)) OF
        TFCs-Removal

TimeDurationBeforeRetry ::=
    INTEGER (1..256)

TM-SignallingInfo ::=
    messtype
    tm-SignallingMode
        model
        mode2
}
SEQUENCE {
    INTEGER (1..1023),
    TFCs-InfoForDSCH
}
SEQUENCE (SIZE (1..maxPDSCH-TFCIgroups)) OF
    TFCI-Range
CHOICE {
    ExplicitTFCs-Configuration,
    SplitTFCI-Signalling
}
SEQUENCE {
    TFCs-IdentityPlain
    BOOLEAN
    DEFAULT 1,
}
CHOICE {
    INTEGER (0..3),
    INTEGER (0..15),
    INTEGER (0..63),
    INTEGER (0..255),
    INTEGER (0..4095),
    INTEGER (0..65535),
    INTEGER (0..16777215)
}
SEQUENCE{
    CHOICE{
        SEQUENCE (SIZE (1..maxTFC)) OF SEQUENCE {
            INTEGER (0..3),
            PowerOffsetInformation
            OPTIONAL
        },
        SEQUENCE (SIZE (1..maxTFC)) OF SEQUENCE {
            INTEGER (0..15),
            PowerOffsetInformation
            OPTIONAL
        },
        SEQUENCE (SIZE (1..maxTFC)) OF SEQUENCE {
            INTEGER (0..63),
            PowerOffsetInformation
            OPTIONAL
        },
        SEQUENCE (SIZE (1..maxTFC)) OF SEQUENCE {
            INTEGER (0..255),
            PowerOffsetInformation
            OPTIONAL
        },
        SEQUENCE (SIZE(1..maxTFC)) OF SEQUENCE {
            INTEGER (0..4095),
            PowerOffsetInformation
            OPTIONAL
        },
        SEQUENCE (SIZE (1..maxTFC)) OF SEQUENCE {
            INTEGER(0..65535),
            PowerOffsetInformation
            OPTIONAL
        },
        SEQUENCE (SIZE (1..maxTFC)) OF SEQUENCE {
            INTEGER(0..16777215),
            PowerOffsetInformation
            OPTIONAL
        }
    }
}
SEQUENCE {
    INTEGER (0..1023)
}
SEQUENCE (SIZE (1..maxTFC)) OF
    TFCs-Removal
INTEGER (1..256)
SEQUENCE {
    Messtype,
    CHOICE {
        NULL,
        SEQUENCE {

```

```

        --TrCH-Type is always DCH
        ul-controlledTrChList
    }
}

TransmissionTimeInterval ::=          ENUMERATED {
                                        tti10, tti20, tti40, tti80 }

TransmissionTimeValidity ::=          INTEGER (1..256)

TransportChannelIdentity ::=          INTEGER (1..32)

TransportChannelIdentityDCHandDSCH ::= SEQUENCE {
    dch-transport-ch-id                TransportChannelIdentity,
    dsch-transport-ch-id                TransportChannelIdentity
}

TransportFormatSet ::=                 CHOICE {
    dedicatedTransChTFS                 DedicatedTransChTFS,
    commonTransChTFS                    CommonTransChTFS
}

TransportFormatSet-LCR ::=             CHOICE {
    dedicatedTransChTFS                 DedicatedTransChTFS,
    commonTransChTFS-LCR                CommonTransChTFS-LCR
}

UL-AddReconfTransChInfoList ::=       SEQUENCE (SIZE (1..maxTrCH)) OF
                                        UL-AddReconfTransChInformation

UL-AddReconfTransChInformation ::=     SEQUENCE {
    ul-TransportChannelType              UL-TrCH-Type,
    transportChannelIdentity             TransportChannelIdentity,
    transportFormatSet                   TransportFormatSet
}

UL-CommonTransChInfo ::=              SEQUENCE {
    -- TABULAR: this tfc-subset IE is applicable to FDD only, TDD specifies tfc-subset in individual
    -- CTRCH Info.
    tfc-Subset                           TFC-Subset                OPTIONAL,
    prach-TFCS                            TFCS                      OPTIONAL,
    modeSpecificInfo                       CHOICE {
        fdd                                SEQUENCE {
            ul-TFCS                          TFCS
        },
        tdd                                SEQUENCE {
            individualUL-CCTrCH-InfoList      IndividualUL-CCTrCH-InfoList
                                                OPTIONAL
        }
    }
}

-- TrCH-Type is always DCH
UL-ControlledTrChList ::=              SEQUENCE (SIZE (1..maxTrCH)) OF
                                        TransportChannelIdentity

UL-DeletedTransChInfoList ::=          SEQUENCE (SIZE (1..maxTrCH)) OF
                                        UL-TransportChannelIdentity

UL-TransportChannelIdentity ::=        SEQUENCE {
    ul-TransportChannelType              UL-TrCH-Type,
    ul-transportChannelIdentity           TransportChannelIdentity
}

UL-TrCH-Type ::= ENUMERATED {dch, usch}

-- *****
--
--     PHYSICAL CHANNEL INFORMATION ELEMENTS (10.3.6)
--
-- *****

AC-To-ASC-Mapping ::=                 INTEGER (0..7)

AC-To-ASC-MappingTable ::=            SEQUENCE (SIZE (maxASCmap)) OF
                                        AC-To-ASC-Mapping

```

```

AccessServiceClass-FDD ::= SEQUENCE {
    availableSignatureStartIndex    INTEGER (0..15),
    availableSignatureEndIndex      INTEGER (0..15),

    assignedSubChannelNumber        BIT STRING {
                                        b3(0),
                                        b2(1),
                                        b1(2),
                                        b0(3)
                                    } (SIZE(4))
}

AccessServiceClass-TDD ::= SEQUENCE {
    channelisationCodeIndices        BIT STRING {
                                        chCodeIndex0(0),
                                        chCodeIndex1(1),
                                        chCodeIndex2(2),
                                        chCodeIndex3(3),
                                        chCodeIndex4(4),
                                        chCodeIndex5(5),
                                        chCodeIndex6(6),
                                        chCodeIndex7(7)
                                    } (SIZE(8)) OPTIONAL,

    subchannelSize                    CHOICE {
        size1                          NULL,
        size2                          SEQUENCE {
            -- in size2, subch0 means bitstring '01' in the tabular, subch1 means bitsring '10'.
            subchannels                  ENUMERATED { subch0, subch1 } OPTIONAL
        },
        size4                          SEQUENCE {
            subchannels                  BIT STRING {
                subCh3(0),
                subCh2(1),
                subCh1(2),
                subCh0(3)
            } (SIZE(4)) OPTIONAL
        },
        size8                          SEQUENCE {
            subchannels                  BIT STRING {
                subCh7(0),
                subCh6(1),
                subCh5(2),
                subCh4(3),
                subCh3(4),
                subCh2(5),
                subCh1(6),
                subCh0(7)
            } (SIZE(8)) OPTIONAL
        }
    }
}

AccessServiceClass-TDD-LCR-r4 ::= SEQUENCE {
    availableSYNC-ULCodesIndices      BIT STRING {
                                        sulCodeIndex0(0),
                                        sulCodeIndex1(1),
                                        sulCodeIndex2(2),
                                        sulCodeIndex3(3),
                                        sulCodeIndex4(4),
                                        sulCodeIndex5(5),
                                        sulCodeIndex6(6),
                                        sulCodeIndex7(7)
                                    } (SIZE(8)) OPTIONAL,

    subchannelSize                    CHOICE {
        size1                          NULL,
        size2                          SEQUENCE {
            -- in size2, subch0 means bitstring '01' in the tabular, subch1 means bitsring '10'.
            subchannels                  ENUMERATED { subch0, subch1 } OPTIONAL
        },
        size4                          SEQUENCE {
            subchannels                  BIT STRING {
                subCh3(0),
                subCh2(1),
                subCh1(2),
                subCh0(3)
            } (SIZE(4)) OPTIONAL
        },
    }
}

```

```

size8
subchannels
}
}

AICH-Info ::=
channelisationCode256
sttd-Indicator
aich-TransmissionTiming
}

AICH-PowerOffset ::=
INTEGER (-22..5)

AICH-TransmissionTiming ::=
ENUMERATED {
e0, e1 }

AllocationPeriodInfo ::=
allocationActivationTime
allocationDuration
}
-- Actual value = IE value * 0.125
Alpha ::=
INTEGER (0..8)

AP-AICH-ChannelisationCode ::=
INTEGER (0..255)

AP-PreambleScramblingCode ::=
INTEGER (0..79)

AP-Signature ::=
INTEGER (0..15)

AP-Signature-VCAM ::=
ap-Signature
availableAP-SubchannelList
}

AP-Subchannel ::=
INTEGER (0..11)

ASCSetting-FDD ::=
-- TABULAR: This is MD in tabular description
-- Default value is previous ASC
-- If this is the first ASC, the default value is all available signature and sub-channels
accessServiceClass-FDD
}

ASCSetting-TDD ::=
-- TABULAR: This is MD in tabular description
-- Default value is previous ASC
-- If this is the first ASC, the default value is all available channelisation codes and
-- all available sub-channels with subchannelSize=size1.
accessServiceClass-TDD
}

ASCSetting-TDD-LCR-r4 ::=
-- TABULAR: This is MD in tabular description
-- Default value is previous ASC
-- If this is the first ASC, the default value is all available SYNC_UL codes and
-- all available sub-channels with subchannelSize=size1.
accessServiceClass-TDD-LCR
}

AvailableAP-Signature-VCAMList ::=
SEQUENCE (SIZE (1..maxPCPCH-APsig)) OF
AP-Signature-VCAM

AvailableAP-SignatureList ::=
SEQUENCE (SIZE (1..maxPCPCH-APsig)) OF
AP-Signature

AvailableAP-SubchannelList ::=
SEQUENCE (SIZE (1..maxPCPCH-APsubCh)) OF
AP-Subchannel

```

```

AvailableMinimumSF-ListVCAM ::= SEQUENCE (SIZE (1..maxPCPCH-SF)) OF
    AvailableMinimumSF-VCAM

AvailableMinimumSF-VCAM ::= SEQUENCE {
    minimumSpreadingFactor MinimumSpreadingFactor,
    nf-Max NF-Max,
    maxAvailablePCPCH-Number MaxAvailablePCPCH-Number,
    availableAP-Signature-VCAMList AvailableAP-Signature-VCAMList
}

AvailableSignatures ::= BIT STRING {
    signature15(0),
    signature14(1),
    signature13(2),
    signature12(3),
    signature11(4),
    signature10(5),
    signature9(6),
    signature8(7),
    signature7(8),
    signature6(9),
    signature5(10),
    signature4(11),
    signature3(12),
    signature2(13),
    signature1(14),
    signature0(15)
} (SIZE(16))

AvailableSubChannelNumbers ::= BIT STRING {
    subCh11(0),
    subCh10(1),
    subCh9(2),
    subCh8(3),
    subCh7(4),
    subCh6(5),
    subCh5(6),
    subCh4(7),
    subCh3(8),
    subCh2(9),
    subCh1(10),
    subCh0(11)
} (SIZE(12))

BurstType ::= ENUMERATED {
    short1, long2 }

CCTrCH-PowerControlInfo ::= SEQUENCE {
    tfcs-Identity TFCS-Identity OPTIONAL,
    ul-DPCH-PowerControlInfo UL-DPCH-PowerControlInfo
}

CCTrCH-PowerControlInfo-r4 ::= SEQUENCE {
    tfcs-Identity TFCS-Identity OPTIONAL,
    ul-DPCH-PowerControlInfo-r4 UL-DPCH-PowerControlInfo-r4
}

CD-AccessSlotSubchannel ::= INTEGER (0..11)

CD-AccessSlotSubchannelList ::= SEQUENCE (SIZE (1..maxPCPCH-CDsubCh)) OF
    CD-AccessSlotSubchannel

CD-CA-ICH-ChannelisationCode ::= INTEGER (0..255)

CD-PreambleScramblingCode ::= INTEGER (0..79)

CD-SignatureCode ::= INTEGER (0..15)

CD-SignatureCodeList ::= SEQUENCE (SIZE (1..maxPCPCH-CDsig)) OF
    CD-SignatureCode

CellAndChannelIdentity ::= SEQUENCE {
    burstType BurstType,
    midambleShift MidambleShiftLong,
    timeslot TimeslotNumber,
    cellParametersID CellParametersID
}

```

```

CellParametersID ::= INTEGER (0..127)

Cfntargetsfnframeoffset ::= INTEGER(0..255)

ChannelAssignmentActive ::= CHOICE {
    notActive
    isActive
}

ChannelisationCode256 ::= INTEGER (0..255)

ChannelReqParamsForUCSM ::= SEQUENCE {
    availableAP-SignatureList AvailableAP-SignatureList,
    availableAP-SubchannelList AvailableAP-SubchannelList OPTIONAL
}

ClosedLoopTimingAdjMode ::= ENUMERATED {
    slot1, slot2 }

CodeNumberDSCH ::= INTEGER (0..255)

CodeRange ::= SEQUENCE {
    pdsch-CodeMapList PDSCH-CodeMapList
}

CodeWordSet ::= ENUMERATED {
    longCWS,
    mediumCWS,
    shortCWS,
    ssdtOff }

CommonTimeslotInfo ::= SEQUENCE {
    -- TABULAR: The IE below is MD, but since it can be encoded in a single
    -- bit it is not defined as OPTIONAL.
    secondInterleavingMode SecondInterleavingMode,
    tfci-Coding TFCI-Coding OPTIONAL,
    puncturingLimit PuncturingLimit,
    repetitionPeriodAndLength RepetitionPeriodAndLength OPTIONAL
}

CommonTimeslotInfoSCCPCH ::= SEQUENCE {
    -- TABULAR: The IE below is MD, but since it can be encoded in a single
    -- bit it is not defined as OPTIONAL.
    secondInterleavingMode SecondInterleavingMode,
    tfci-Coding TFCI-Coding OPTIONAL,
    puncturingLimit PuncturingLimit,
    repetitionPeriodLengthAndOffset RepetitionPeriodLengthAndOffset OPTIONAL
}

ConstantValue ::= INTEGER (-35..-10)

CPCH-PersistenceLevels ::= SEQUENCE {
    cpch-SetID CPCH-SetID,
    dynamicPersistenceLevelTF-List DynamicPersistenceLevelTF-List
}

CPCH-PersistenceLevelsList ::= SEQUENCE (SIZE (1..maxCPCHsets)) OF
    CPCH-PersistenceLevels

CPCH-SetInfo ::= SEQUENCE {
    cpch-SetID CPCH-SetID,
    transportFormatSet TransportFormatSet,
    tfcs TFCS,
    ap-PreambleScramblingCode AP-PreambleScramblingCode,
    ap-AICH-ChannelisationCode AP-AICH-ChannelisationCode,
    cd-PreambleScramblingCode CD-PreambleScramblingCode,
    cd-CA-ICH-ChannelisationCode CD-CA-ICH-ChannelisationCode,
    cd-AccessSlotSubchannelList CD-AccessSlotSubchannelList OPTIONAL,
    cd-SignatureCodeList CD-SignatureCodeList OPTIONAL,
    deltaPp-m DeltaPp-m,
    ul-DPCCH-SlotFormat UL-DPCCH-SlotFormat,
    n-StartMessage N-StartMessage,
    n-EOT N-EOT,
    channelAssignmentActive ChannelAssignmentActive,
    -- TABULAR: VCAM info has been nested inside ChannelAssignmentActive,
    -- which in turn is mandatory since it's only a binary choice.
    cpch-StatusIndicationMode CPCH-StatusIndicationMode,
}

```



```

    pcpch-ChannelInfoList          PCPCH-ChannelInfoList
}

CPCH-SetInfoList ::=              SEQUENCE (SIZE (1..maxCPCHsets)) OF
                                  CPCH-SetInfo

CPCH-StatusIndicationMode ::=    ENUMERATED {
                                  pa-mode,
                                  pamsf-mode }

CSICH-PowerOffset ::=            INTEGER (-10..5)

-- DefaultDPCH-OffsetValueFDD and DefaultDPCH-OffsetValueTDD corresponds to
-- IE "Default DPCH Offset Value" depending on the mode.
-- Actual value = IE value * 512
DefaultDPCH-OffsetValueFDD ::=    INTEGER (0..599)

DefaultDPCH-OffsetValueTDD ::=    INTEGER (0..7)

DeltaPp-m ::=                    INTEGER (-10..10)

-- Actual value = IE value * 0.1
DeltaSIR ::=                      INTEGER (0..30)

DL-CCTrCh ::=                    SEQUENCE {
    tfcs-ID                        TFCS-IdentityPlain          DEFAULT 1,
    timeInfo                       TimeInfo,
    dl-CCTrCH-TimeslotsCodes       DownlinkTimeslotsCodes     OPTIONAL,
    ul-CCTrChTPCList              UL-CCTrChTPCList            OPTIONAL
}

DL-CCTrCh-r4 ::=                 SEQUENCE {
    tfcs-ID                        TFCS-IdentityPlain          DEFAULT 1,
    timeInfo                       TimeInfo,
    tddOption                      CHOICE {
        tdd384                     SEQUENCE {
            dl-CCTrCH-TimeslotsCodes DownlinkTimeslotsCodes OPTIONAL
        },
        tdd128                     SEQUENCE {
            dl-CCTrCH-TimeslotsCodes DownlinkTimeslotsCodes-LCR-r4 OPTIONAL
        }
    },
    ul-CCTrChTPCList              UL-CCTrChTPCList            OPTIONAL
}

DL-CCTrChList ::=               SEQUENCE (SIZE (1..maxCCTrCH)) OF
                                  DL-CCTrCh

DL-CCTrChList-r4 ::=            SEQUENCE (SIZE (1..maxCCTrCH)) OF
                                  DL-CCTrCh-r4

DL-CCTrChTPCList ::=            SEQUENCE (SIZE (0..maxCCTrCH)) OF
                                  TFCS-Identity

DL-ChannelisationCode ::=        SEQUENCE {
    secondaryScramblingCode        SecondaryScramblingCode     OPTIONAL,
    sf-AndCodeNumber              SF512-AndCodeNumber,
    scramblingCodeChange          ScramblingCodeChange           OPTIONAL
}

DL-ChannelisationCodeList ::=    SEQUENCE (SIZE (1..maxDPCH-DLchan)) OF
                                  DL-ChannelisationCode

DL-CommonInformation ::=         SEQUENCE {
    dl-DPCH-InfoCommon            DL-DPCH-InfoCommon          OPTIONAL,
    modeSpecificInfo              CHOICE {
        fdd                        SEQUENCE {
            defaultDPCH-OffsetValue DefaultDPCH-OffsetValueFDD OPTIONAL,
            dpch-CompressedModeInfo DPCH-CompressedModeInfo   OPTIONAL,
            tx-DiversityMode        TX-DiversityMode           OPTIONAL,
            ssdt-Information        SSDT-Information            OPTIONAL
        },
        tdd                        SEQUENCE {
            defaultDPCH-OffsetValue DefaultDPCH-OffsetValueTDD OPTIONAL
        }
    }
}

```

```

DL-CommonInformation-r4 ::= SEQUENCE {
  dl-DPCH-InfoCommon          DL-DPCH-InfoCommon          OPTIONAL,
  modeSpecificInfo            CHOICE {
    fdd                        SEQUENCE {
      defaultDPCH-OffsetValue DefaultDPCH-OffsetValueFDD OPTIONAL,
      dpch-CompressedModeInfo DPCH-CompressedModeInfo   OPTIONAL,
      tx-DiversityMode         TX-DiversityMode             OPTIONAL,
      ssdt-Information         SSDT-Information-r4          OPTIONAL
    },
    tdd                        SEQUENCE {
      tddOption                CHOICE {
        tdd384                  NULL,
        tddl28                  SEQUENCE {
          tstd-Indicator        BOOLEAN
        }
      }
    },
    defaultDPCH-OffsetValue    DefaultDPCH-OffsetValueTDD OPTIONAL
  }
}

DL-CommonInformationPost ::= SEQUENCE {
  dl-DPCH-InfoCommon          DL-DPCH-InfoCommonPost
}

DL-CommonInformationPredef ::= SEQUENCE {
  dl-DPCH-InfoCommon          DL-DPCH-InfoCommonPredef  OPTIONAL
}

DL-CompressedModeMethod ::= ENUMERATED {
  puncturing, sf-2,
  higherLayerScheduling }

DL-DPCH-InfoCommon ::= SEQUENCE {
  cfnHandling                 CHOICE {
    maintain                   NULL,
    initialise                  SEQUENCE {
      cfntargetsfnsframeoffset Cfntargetsfnsframeoffset  OPTIONAL
    }
  },
  modeSpecificInfo            CHOICE {
    fdd                        SEQUENCE {
      dl-DPCH-PowerControlInfo DL-DPCH-PowerControlInfo   OPTIONAL,
      powerOffsetPilot-pdpch   PowerOffsetPilot-pdpch,
      dl-rate-matching-restriction Dl-rate-matching-restriction  OPTIONAL,
      spreadingFactorAndPilot   SF512-AndPilot,
      -- TABULAR: The number of pilot bits is nested inside the spreading factor.
      positionFixedOrFlexible   PositionFixedOrFlexible,
      tfci-Existence            BOOLEAN
    },
    tdd                        SEQUENCE {
      dl-DPCH-PowerControlInfo DL-DPCH-PowerControlInfo   OPTIONAL,
      commonTimeslotInfo        CommonTimeslotInfo          OPTIONAL
    }
  }
}

DL-DPCH-InfoCommonPost ::= SEQUENCE {
  dl-DPCH-PowerControlInfo    DL-DPCH-PowerControlInfo    OPTIONAL
}

DL-DPCH-InfoCommonPredef ::= SEQUENCE {
  modeSpecificInfo            CHOICE {
    fdd                        SEQUENCE {
      spreadingFactorAndPilot   SF512-AndPilot,
      -- TABULAR: The number of pilot bits is nested inside the spreading factor.
      positionFixedOrFlexible   PositionFixedOrFlexible,
      tfci-Existence            BOOLEAN
    },
    tdd                        SEQUENCE {
      commonTimeslotInfo        CommonTimeslotInfo
    }
  }
}

DL-DPCH-InfoPerRL ::= CHOICE {
  fdd                          SEQUENCE {
    pCPICH-UsageForChannelEst   PCPICH-UsageForChannelEst,

```

```

        dpch-FrameOffset          DPCH-FrameOffset,
        secondaryCPICH-Info       SecondaryCPICH-Info          OPTIONAL,
        dl-ChannelisationCodeList DL-ChannelisationCodeList,
        tpc-CombinationIndex      TPC-CombinationIndex,
        ssdt-CellIdentity         SSDT-CellIdentity          OPTIONAL,
        closedLoopTimingAdjMode   ClosedLoopTimingAdjMode        OPTIONAL
    },
    tdd                            DL-CCTrChList
}

DL-DPCH-InfoPerRL-r4 ::=
    fdd                            CHOICE {
        pCPICH-UsageForChannelEst PCPICH-UsageForChannelEst,
        dpch-FrameOffset          DPCH-FrameOffset,
        secondaryCPICH-Info       SecondaryCPICH-Info          OPTIONAL,
        dl-ChannelisationCodeList DL-ChannelisationCodeList,
        tpc-CombinationIndex      TPC-CombinationIndex,
        ssdt-CellIdentity         SSDT-CellIdentity          OPTIONAL,
        closedLoopTimingAdjMode   ClosedLoopTimingAdjMode        OPTIONAL
    },
    tdd                            DL-CCTrChList-r4
}

DL-DPCH-InfoPerRL-PostFDD ::=
    pCPICH-UsageForChannelEst     PCPICH-UsageForChannelEst,
    dl-ChannelisationCode         DL-ChannelisationCode,
    tpc-CombinationIndex          TPC-CombinationIndex
}

DL-DPCH-InfoPerRL-PostTDD ::=
    dl-DPCH-TimeslotsCodes        DownlinkTimeslotsCodes
}

DL-DPCH-InfoPerRL-PostTDD-LCR-r4 ::=
    dl-CCTrCH-TimeslotsCodes      DownlinkTimeslotsCodes-LCR-r4
}

DL-DPCH-PowerControlInfo ::=
    modeSpecificInfo              SEQUENCE {
        fdd                        CHOICE {
            dpc-Mode               DPC-Mode
        },
        tdd                        SEQUENCE {
            tpc-StepSizeTDD        TPC-StepSizeTDD          OPTIONAL
        }
    }
}

DL-FrameType ::=
    ENUMERATED {
        dl-FrameTypeA, dl-FrameTypeB }

DL-InformationPerRL ::=
    modeSpecificInfo              SEQUENCE {
        fdd                        CHOICE {
            primaryCPICH-Info      PrimaryCPICH-Info,
            pdsch-SHO-DCH-Info     PDSCH-SHO-DCH-Info          OPTIONAL,
            pdsch-CodeMapping      PDSCH-CodeMapping          OPTIONAL
        },
        tdd                        PrimaryCCPCH-Info
    },
    dl-DPCH-InfoPerRL            DL-DPCH-InfoPerRL          OPTIONAL,
    sccpch-InfoForFACH           SCCPCH-InfoForFACH          OPTIONAL
}

DL-InformationPerRL-r4 ::=
    modeSpecificInfo              SEQUENCE {
        fdd                        CHOICE {
            primaryCPICH-Info      PrimaryCPICH-Info,
            pdsch-SHO-DCH-Info     PDSCH-SHO-DCH-Info          OPTIONAL,
            pdsch-CodeMapping      PDSCH-CodeMapping          OPTIONAL
        },
        tdd                        PrimaryCCPCH-Info-r4
    },
    dl-DPCH-InfoPerRL            DL-DPCH-InfoPerRL-r4          OPTIONAL,
    secondaryCCPCH-Info          SecondaryCCPCH-Info-r4          OPTIONAL
}

DL-InformationPerRL-List ::=
    SEQUENCE (SIZE (1..maxRL)) OF

```

```

DL-InformationPerRL
DL-InformationPerRL-List-r4 ::= SEQUENCE (SIZE (1..maxRL)) OF
    DL-InformationPerRL-r4
DL-InformationPerRL-ListPostFDD ::= SEQUENCE (SIZE (1..maxRL)) OF
    DL-InformationPerRL-PostFDD
DL-InformationPerRL-PostFDD ::= SEQUENCE {
    primaryCPICH-Info          PrimaryCPICH-Info,
    dl-DPCH-InfoPerRL         DL-DPCH-InfoPerRL-PostFDD
}
DL-InformationPerRL-PostTDD ::= SEQUENCE {
    primaryCCPCH-Info          PrimaryCCPCH-InfoPost,
    dl-DPCH-InfoPerRL         DL-DPCH-InfoPerRL-PostTDD
}
DL-InformationPerRL-PostTDD-LCR-r4 ::= SEQUENCE {
    primaryCCPCH-Info          PrimaryCCPCH-InfoPostTDD-LCR-r4,
    dl-DPCH-InfoPerRL         DL-DPCH-InfoPerRL-PostTDD-LCR-r4
}
DL-PDSCH-Information ::= SEQUENCE {
    pdsch-SHO-DCH-Info        PDSCH-SHO-DCH-Info          OPTIONAL,
    pdsch-CodeMapping         PDSCH-CodeMapping          OPTIONAL
}
Dl-rate-matching-restriction ::= SEQUENCE {
    restrictedTrCH-InfoList    RestrictedTrCH-InfoList    OPTIONAL
}
DL-TS-ChannelisationCode ::= ENUMERATED {
    cc16-1, cc16-2, cc16-3, cc16-4,
    cc16-5, cc16-6, cc16-7, cc16-8,
    cc16-9, cc16-10, cc16-11, cc16-12,
    cc16-13, cc16-14, cc16-15, cc16-16 }
DL-TS-ChannelisationCodesShort ::= SEQUENCE {
    codesRepresentation        CHOICE {
        consecutive            SEQUENCE {
            firstChannelisationCode    DL-TS-ChannelisationCode,
            lastChannelisationCode     DL-TS-ChannelisationCode
        },
        bitmap                 BIT STRING {
            chCode16-SF16(0),
            chCode15-SF16(1),
            chCode14-SF16(2),
            chCode13-SF16(3),
            chCode12-SF16(4),
            chCode11-SF16(5),
            chCode10-SF16(6),
            chCode9-SF16(7),
            chCode8-SF16(8),
            chCode7-SF16(9),
            chCode6-SF16(10),
            chCode5-SF16(11),
            chCode4-SF16(12),
            chCode3-SF16(13),
            chCode2-SF16(14),
            chCode1-SF16(15)
        } (SIZE (16))
    }
}
DownlinkAdditionalTimeslots ::= SEQUENCE {
    parameters                CHOICE {
        sameAsLast            SEQUENCE {
            timeslotNumber    TimeslotNumber
        },
        newParameters         SEQUENCE {
            individualTimeslotInfo    IndividualTimeslotInfo,
            dl-TS-ChannelisationCodesShort    DL-TS-ChannelisationCodesShort
        }
    }
}
DownlinkAdditionalTimeslots-LCR-r4 ::= SEQUENCE {

```

```

parameters                               CHOICE {
  sameAsLast                               SEQUENCE {
    timeslotNumber                         TimeslotNumber-LCR-r4
  },
  newParameters                             SEQUENCE {
    individualTimeslotInfo                 IndividualTimeslotInfo-LCR-r4,
    dl-TS-ChannelisationCodesShort        DL-TS-ChannelisationCodesShort
  }
}

DownlinkTimeslotsCodes ::= SEQUENCE {
  firstIndividualTimeslotInfo              IndividualTimeslotInfo,
  dl-TS-ChannelisationCodesShort          DL-TS-ChannelisationCodesShort,
  moreTimeslots                           CHOICE {
    noMore                                 NULL,
    additionalTimeslots                   CHOICE {
      consecutive                          INTEGER (1..maxTS-1),
      timeslotList                         SEQUENCE (SIZE (1..maxTS-1)) OF
                                          DownlinkAdditionalTimeslots
    }
  }
}

DownlinkTimeslotsCodes-LCR-r4 ::= SEQUENCE {
  firstIndividualTimeslotInfo              IndividualTimeslotInfo-LCR-r4,
  dl-TS-ChannelisationCodesShort          DL-TS-ChannelisationCodesShort,
  moreTimeslots                           CHOICE {
    noMore                                 NULL,
    additionalTimeslots                   CHOICE {
      consecutive                          INTEGER (1..maxTS-LCR-1),
      timeslotList                         SEQUENCE (SIZE (1..maxTS-LCR-1)) OF
                                          DownlinkAdditionalTimeslots-LCR-r4
    }
  }
}

DPC-Mode ::= ENUMERATED {
  singleTPC,
  tpcTripletInSoft }

-- The actual value of DPCCH power offset is the value of this IE * 2.
DPCCH-PowerOffset ::= INTEGER (-82..-3)

-- The actual value of DPCCH power offset is the value of this (2 + IE * 4).
DPCCH-PowerOffset2 ::= INTEGER (-28..-13)

DPCH-CompressedModeInfo ::= SEQUENCE {
  tgp-SequenceList                        TGP-SequenceList
}

DPCH-CompressedModeStatusInfo ::= SEQUENCE {
  tgps-Reconfiguration-CFN                TGPS-Reconfiguration-CFN,
  tgp-SequenceShortList                   SEQUENCE (SIZE (1..maxTGPS)) OF
                                          TGP-SequenceShort
}

-- TABULAR: Actual value = IE value * 256
DPCH-FrameOffset ::= INTEGER (0..149)

DSCH-Mapping ::= SEQUENCE {
  maxTFICI-Field2Value                    MaxTFICI-Field2Value,
  spreadingFactor                          SF-PDSCH,
  codeNumber                               CodeNumberDSCH,
  multiCodeInfo                            MultiCodeInfo
}

DSCH-MappingList ::= SEQUENCE (SIZE (1..maxPDSCH-TFCIgroups)) OF
  DSCH-Mapping

DSCH-RadioLinkIdentifier ::= INTEGER (0..511)

DurationTimeInfo ::= INTEGER (1..4096)

-- TABULAR : value [Duration = infinite] is the value by default,
-- and is encoded by absence of the full sequence. If the sequence is present,
-- thefield is absent, the default is respectivelyinfinite. Presence of the

```

```

-- field absent should not be used, but shall be understood as if the
-- sequence was absent.

DynamicPersistenceLevel ::=          INTEGER (1..8)

DynamicPersistenceLevelList ::=      SEQUENCE (SIZE (1..maxPRACH)) OF
                                      DynamicPersistenceLevel

DynamicPersistenceLevelTF-List ::=   SEQUENCE (SIZE (1..maxTF-CPCH)) OF
                                      DynamicPersistenceLevel

FACH-PCH-Information ::=            SEQUENCE {
    transportFormatSet              TransportFormatSet,
    transportChannelIdentity        TransportChannelIdentity,
    ctch-Indicator                   BOOLEAN
}

FACH-PCH-InformationList ::=        SEQUENCE (SIZE (1..maxFACHPCH)) OF
                                      FACH-PCH-Information

FPACH-Info-r4 ::=                   SEQUENCE {
    timeslot                         TimeslotNumber-PRACH-LCR-r4,
    channelisationCode               TDD-FPACH-CCode16-r4,
    midambleShiftAndBurstType        MidambleShiftAndBurstType-LCR-r4,
    wi                                Wi-LCR
}

FrequencyInfo ::=                   SEQUENCE {
    modeSpecificInfo                 CHOICE {
        fdd                          FrequencyInfoFDD,
        tdd                          FrequencyInfoTDD    }
}

FrequencyInfoFDD ::=                SEQUENCE {
    uarfcn-UL                        UARFCN                OPTIONAL,
    uarfcn-DL                        UARFCN
}

FrequencyInfoTDD ::=                SEQUENCE {
    uarfcn-Nt                        UARFCN
}

IndividualTimeslotInfo ::=           SEQUENCE {
    timeslotNumber                   TimeslotNumber,
    tfci-Existence                   BOOLEAN,
    midambleShiftAndBurstType        MidambleShiftAndBurstType
}

IndividualTimeslotInfo-LCR-r4 ::=    SEQUENCE {
    timeslotNumber                   TimeslotNumber-LCR-r4,
    tfci-Existence                   BOOLEAN,
    midambleShiftAndBurstType        MidambleShiftAndBurstType-LCR-r4,
    modulation                       ENUMERATED { mod-QPSK, mod-8PSK },
    ss-TPC-Symbols                   ENUMERATED { zero, one, sixteenOverSF }
}

IndividualTimeslotInfo-LCR-r4-ext ::= SEQUENCE {
-- timeslotNumber and tfci-Existence is taken from IndividualTimeslotInfo.
-- midambleShiftAndBurstType in IndividualTimeslotInfo shall be ignored.
    midambleShiftAndBurstType        MidambleShiftAndBurstType-LCR-r4,
    modulation                       ENUMERATED { mod-QPSK, mod-8PSK },
    ss-TPC-Symbols                   ENUMERATED { zero, one, sixteenOverSF }
}

IndividualTS-Interference ::=        SEQUENCE {
    timeslot                         TimeslotNumber,
    ul-TimeslotInterference          UL-Interference
}

IndividualTS-Interference-LCR-r4 ::= SEQUENCE {
    timeslot                         TimeslotNumber-LCR-r4,
    ul-TimeslotInterference          UL-Interference
}

IndividualTS-InterferenceList ::=    SEQUENCE (SIZE (1..maxTS)) OF
                                      IndividualTS-Interference

IndividualTS-InterferenceList-r4 ::= CHOICE {

```

```

tdd384                SEQUENCE (SIZE (1..maxTS)) OF
                        IndividualTS-Interference,
tdd128                SEQUENCE (SIZE (1..maxTS-LCR)) OF
                        IndividualTS-Interference-LCR-r4
}

ITP ::=                ENUMERATED {
                        mode0, mode1 }

NidentifyAbort ::=    INTEGER (1..128)

MaxAllowedUL-TX-Power ::=    INTEGER (-50..33)

MaxAvailablePCPCH-Number ::=    INTEGER (1..64)

MaxPowerIncrease-r4 ::=    INTEGER (0..3)

MaxTFCI-Field2Value ::=    INTEGER (1..1023)

MidambleConfigurationBurstTypeand3 ::=    ENUMERATED {ms4, ms8, ms16}

MidambleConfigurationBurstType2 ::=    ENUMERATED {ms3, ms6}

MidambleShiftAndBurstType ::=    SEQUENCE {
    burstType          CHOICE {
        type1          SEQUENCE {
            midambleConfigurationBurstTypeand3 MidambleConfigurationBurstTypeand3,
            midambleAllocationMode             CHOICE {
                defaultMidamble             NULL,
                commonMidamble              NULL,
                ueSpecificMidamble          SEQUENCE {
                    midambleShift             MidambleShiftLong
                }
            }
        },
        type2          SEQUENCE {
            midambleConfigurationBurstType2 MidambleConfigurationBurstType2,
            midambleAllocationMode             CHOICE {
                defaultMidamble             NULL,
                commonMidamble              NULL,
                ueSpecificMidamble          SEQUENCE {
                    midambleShift             MidambleShiftShort
                }
            }
        },
        type3          SEQUENCE {
            midambleConfigurationBurstTypeand3 MidambleConfigurationBurstTypeand3,
            midambleAllocationMode             CHOICE {
                defaultMidamble             NULL,
                ueSpecificMidamble          SEQUENCE {
                    midambleShift             MidambleShiftLong
                }
            }
        }
    }
}

MidambleShiftAndBurstType-LCR-r4 ::=    SEQUENCE {
    midambleAllocationMode CHOICE {
        defaultMidamble             NULL,
        ueSpecificMidamble          SEQUENCE {
            midambleShift             INTEGER (0..15)
        }
    },
    midambleConfiguration    INTEGER (1..8)    -- Actual value = IE value * 2
}

MidambleShiftLong ::=    INTEGER (0..15)

MidambleShiftShort ::=    INTEGER (0..5)

MinimumSpreadingFactor ::=    ENUMERATED {
    sf4, sf8, sf16, sf32,
    sf64, sf128, sf256 }

MultiCodeInfo ::=    INTEGER (1..16)

```

```

N-EOT ::= INTEGER (0..7)
N-GAP ::= ENUMERATED {
    f2, f4, f8 }
N-PCH ::= INTEGER (1..8)
N-StartMessage ::= INTEGER (1..8)
NB01 ::= INTEGER (0..50)
NF-Max ::= INTEGER (1..64)
NumberOfDPDCH ::= INTEGER (1..maxDPDCH-UL)
NumberOfFBI-Bits ::= INTEGER (1..2)
OpenLoopPowerControl-TDD ::= SEQUENCE {
    primaryCCPCH-TX-Power PrimaryCCPCH-TX-Power,
    -- The following IEs shall be ignored in 1.28Mcps TDD mode.
    alpha Alpha OPTIONAL,
    prach-ConstantValue ConstantValue,
    dpch-ConstantValue ConstantValue,
    pusch-ConstantValue ConstantValue OPTIONAL
}
OpenLoopPowerControl-IPDL-TDD-r4 ::= SEQUENCE {
    ipdl-alpha Alpha,
    maxPowerIncrease MaxPowerIncrease-r4
}
PagingIndicatorLength ::= ENUMERATED {
    pi4, pi8, pi16 }
PC-Preamble ::= INTEGER (0..7)
PCP-Length ::= ENUMERATED {
    as0, as8 }
PCPCH-ChannelInfo ::= SEQUENCE {
    pcpch-UL-ScramblingCode INTEGER (0..79),
    pcpch-DL-ChannelisationCode INTEGER (0..511),
    pcpch-DL-ScramblingCode SecondaryScramblingCode OPTIONAL,
    pcp-Length PCP-Length,
    ucsM-Info UCSM-Info OPTIONAL
}
PCPCH-ChannelInfoList ::= SEQUENCE (SIZE (1..maxPCPCHs)) OF
    PCPCH-ChannelInfo
PCPICH-UsageForChannelEst ::= ENUMERATED {
    maybeUsed,
    shallNotBeUsed }
PDSCH-CapacityAllocationInfo ::= SEQUENCE {
    pdsch-PowerControlInfo PDSCH-PowerControlInfo OPTIONAL,
    -- pdsch-PowerControlInfo is conditional on new-configuration branch below, if this
    -- selected the IE is OPTIONAL otherwise it should not be sent
    pdsch-AllocationPeriodInfo AllocationPeriodInfo,
    tfcs-ID TFCS-IdentityPlain DEFAULT 1,
    configuration CHOICE {
        old-Configuration SEQUENCE {
            pdsch-Identity PDSCH-Identity
        },
        new-Configuration SEQUENCE {
            pdsch-Info PDSCH-Info,
            pdsch-Identity PDSCH-Identity OPTIONAL
        }
    }
}
PDSCH-CapacityAllocationInfo-r4 ::= SEQUENCE {
    pdsch-PowerControlInfo PDSCH-PowerControlInfo OPTIONAL,
    -- pdsch-PowerControlInfo is conditional on new-configuration branch below, if this
    -- selected the IE is OPTIONAL otherwise it should not be sent
    pdsch-AllocationPeriodInfo AllocationPeriodInfo,
    tfcs-ID TFCS-IdentityPlain DEFAULT 1,

```



```

configuration
  old-Configuration
    pdsch-Identity
  },
  new-Configuration
    pdsch-Info
    pdsch-Identity
}
}

PDSCH-CodeInfo ::=
  spreadingFactor
  codeNumber
  multiCodeInfo
}

PDSCH-CodeInfoList ::=
  SEQUENCE (SIZE (1..maxTFPI-2-Combs)) OF
  PDSCH-CodeInfo

PDSCH-CodeMap ::=
  spreadingFactor
  multiCodeInfo
  codeNumberStart
  codeNumberStop
}

PDSCH-CodeMapList ::=
  SEQUENCE (SIZE (1..maxPDSCH-TFCIgroups)) OF
  PDSCH-CodeMap

PDSCH-CodeMapping ::=
  dl-ScramblingCode
  signallingMethod
  codeRange
  tfci-Range
  explicit
  replace
}

PDSCH-Identity ::=
  INTEGER (1..hiPDSCHidentities)

PDSCH-Info ::=
  tfcs-ID
  commonTimeslotInfo
  pdsch-TimeslotsCodes
}

PDSCH-Info-r4 ::=
  tfcs-ID
  commonTimeslotInfo
  tddOption
  tdd384
    pdsch-TimeslotsCodes
  },
  tdd128
    pdsch-TimeslotsCodes
}

PDSCH-Info-LCR-r4 ::=
  tfcs-ID
  commonTimeslotInfo
  pdsch-TimeslotsCodes
}

PDSCH-PowerControlInfo ::=
  tpc-StepSizeTDD
  ul-CCTrChTPCList
}

PDSCH-SHO-DCH-Info ::=
  dsch-RadioLinkIdentifier
  rl-IdentifierList
}

CHOICE {
  SEQUENCE {
    PDSCH-Identity
  },
  SEQUENCE {
    PDSCH-Info-r4,
    PDSCH-Identity
  }
} OPTIONAL

SEQUENCE {
  SF-PDSCH,
  CodeNumberDSCH,
  MultiCodeInfo
}

SEQUENCE (SIZE (1..maxTFPI-2-Combs)) OF
  PDSCH-CodeInfo

SEQUENCE {
  SF-PDSCH,
  MultiCodeInfo,
  CodeNumberDSCH,
  CodeNumberDSCH
}

SEQUENCE (SIZE (1..maxPDSCH-TFCIgroups)) OF
  PDSCH-CodeMap

SEQUENCE {
  SecondaryScramblingCode
  CHOICE {
    CodeRange,
    DSCH-MappingList,
    PDSCH-CodeInfoList,
    ReplacedPDSCH-CodeInfoList
  }
} OPTIONAL,

INTEGER (1..hiPDSCHidentities)

SEQUENCE {
  TFCS-IdentityPlain
  CommonTimeslotInfo
  DownlinkTimeslotsCodes
}
DEFAULT 1,
OPTIONAL,
OPTIONAL

SEQUENCE {
  TFCS-IdentityPlain
  CommonTimeslotInfo
  CHOICE {
    SEQUENCE {
      DownlinkTimeslotsCodes
    }
    SEQUENCE {
      DownlinkTimeslotsCodes-LCR-r4
    }
  }
}
DEFAULT 1,
OPTIONAL,
OPTIONAL

SEQUENCE {
  TFCS-IdentityPlain
  CommonTimeslotInfo
  DownlinkTimeslotsCodes-LCR-r4
}
DEFAULT 1,
OPTIONAL,
OPTIONAL

SEQUENCE {
  TPC-StepSizeTDD
  UL-CCTrChTPCList
}
OPTIONAL,
OPTIONAL

SEQUENCE {
  DSCH-RadioLinkIdentifier,
  RL-IdentifierList
}
OPTIONAL

```

```

PDSCH-SysInfo ::=
    pdsch-Identity
    pdsch-Info
    dsch-TFS
    dsch-TFCS
}
SEQUENCE {
    PDSCH-Identity,
    PDSCH-Info,
    TransportFormatSet
    TFCS
OPTIONAL,
OPTIONAL
}

PDSCH-SysInfo-LCR-r4 ::=
    pdsch-Identity
    pdsch-Info
    dsch-TFS
    dsch-TFCS
}
SEQUENCE {
    PDSCH-Identity,
    PDSCH-Info-LCR-r4,
    TransportFormatSet
    TFCS
OPTIONAL,
OPTIONAL
}

PDSCH-SysInfoList ::=
SEQUENCE (SIZE (1..maxPDSCH)) OF
PDSCH-SysInfo

PDSCH-SysInfoList-LCR-r4 ::=
SEQUENCE (SIZE (1..maxPDSCH)) OF
PDSCH-SysInfo-LCR-r4

PDSCH-SysInfoList-SFN ::=
SEQUENCE (SIZE (1..maxPDSCH)) OF
SEQUENCE {
    pdsch-SysInfo
    sfm-TimeInfo
}
OPTIONAL

PDSCH-SysInfoList-SFN-LCR-r4 ::=
SEQUENCE (SIZE (1..maxPDSCH)) OF
SEQUENCE {
    pdsch-SysInfo
    sfm-TimeInfo
}
OPTIONAL

PersistenceScalingFactor ::=
ENUMERATED {
    psf0-9, psf0-8, psf0-7, psf0-6,
    psf0-5, psf0-4, psf0-3, psf0-2 }

PersistenceScalingFactorList ::=
SEQUENCE (SIZE (1..maxASCPersist)) OF
PersistenceScalingFactor

PI-CountPerFrame ::=
ENUMERATED {
    e18, e36, e72, e144 }

PICH-Info ::=
    fdd
        channelisationCode256
        pi-CountPerFrame
        sttd-Indicator
    },
    tdd
        channelisationCode
        timeslot
        burstType
            type-1
            type-2
        }
        repetitionPeriodLengthOffset
        pagingIndicatorLength
        n-GAP
        n-PCH
}
CHOICE {
    SEQUENCE {
        ChannelisationCode256,
        PI-CountPerFrame,
        BOOLEAN
    }
    SEQUENCE {
        TDD-PICH-CCode
        TimeslotNumber
        CHOICE {
            MidambleShiftLong,
            MidambleShiftShort
        }
        RepPerLengthOffset-PICH
        PagingIndicatorLength
        N-GAP
        N-PCH
}
OPTIONAL,
OPTIONAL,
OPTIONAL,
OPTIONAL,
DEFAULT pi4,
DEFAULT f4,
DEFAULT 2
}

PICH-Info-LCR-r4 ::=
    timeslot
    midambleShiftAndBurstType
    repetitionPeriodLengthOffset
    pagingIndicatorLength
    n-GAP
    n-PCH
}
SEQUENCE {
    TimeslotNumber-LCR-r4
    MidambleShiftAndBurstType-LCR-r4,
    RepPerLengthOffset-PICH
    PagingIndicatorLength
    N-GAP
    N-PCH
OPTIONAL,
OPTIONAL,
OPTIONAL,
DEFAULT pi4,
DEFAULT f4,
DEFAULT 2
}

PICH-PowerOffset ::=
INTEGER (-10..5)

PilotBits128 ::=
ENUMERATED {
    pb4, pb8 }

PilotBits256 ::=
ENUMERATED {
    pb2, pb4, pb8 }

```

```

PositionFixedOrFlexible ::=          ENUMERATED {
                                        fixed,
                                        flexible }

PowerControlAlgorithm ::=            CHOICE {
    algorithm1                       TPC-StepSizeFDD,
    algorithm2                       NULL
}

PowerOffsetPilot-pdpdch ::=         INTEGER (0..24)

PowerRampStep ::=                   INTEGER (1..8)

PRACH-ChanCodes-LCR-r4 ::=          SEQUENCE (SIZE (1..4)) OF
                                        TDD-PRACH-CCode-LCR-r4

PRACH-Definition-LCR-r4 ::=          SEQUENCE {
    timeslot                          TimeslotNumber-PRACH-LCR-r4,
    prach-ChanCodes-LCR               PRACH-ChanCodes-LCR-r4,
    midambleShiftAndBurstType         MidambleShiftAndBurstType-LCR-r4,
    fpach-Info                        FPACH-Info-r4
}

PRACH-Midamble ::=                  ENUMERATED {
                                        direct,
                                        direct-Inverted }

PRACH-Partitioning ::=              CHOICE {
    fdd                                SEQUENCE (SIZE (1..maxASC)) OF
                                        ASCSetting-FDD,
    tdd                                SEQUENCE (SIZE (1..maxASC)) OF
                                        ASCSetting-TDD
}

PRACH-Partitioning-LCR-r4 ::=        SEQUENCE (SIZE (1..maxASC)) OF
                                        ASCSetting-TDD-LCR-r4

PRACH-PowerOffset ::=               SEQUENCE {
    powerRampStep                     PowerRampStep,
    preambleRetransMax                PreambleRetransMax
}

PRACH-RACH-Info ::=                 SEQUENCE {
    modeSpecificInfo                  CHOICE {
        fdd                            SEQUENCE {
            availableSignatures         AvailableSignatures,
            availableSF                 SF-PRACH,
            preambleScramblingCodeWordNumber PreambleScramblingCodeWordNumber,
            puncturingLimit             PuncturingLimit,
            availableSubChannelNumbers  AvailableSubChannelNumbers
        },
        tdd                            SEQUENCE {
            timeslot                    TimeslotNumber,
            channelisationCodeList     TDD-PRACH-CCodeList,
            prach-Midamble              PRACH-Midamble
        }
    }
}

PRACH-RACH-Info-LCR-r4 ::=           SEQUENCE {
    sync-UL-Info                      SYNC-UL-Info-r4,
    prach-DefinitionList              SEQUENCE (SIZE (1..maxPRACH-FPACH)) OF
                                        PRACH-Definition-LCR-r4
}

PRACH-SystemInformation ::=          SEQUENCE {
    prach-RACH-Info                   PRACH-RACH-Info,
    transportChannelIdentity           TransportChannelIdentity,
    rach-TransportFormatSet            TransportFormatSet                                OPTIONAL,
    rach-TFCS                          TFCS                                                    OPTIONAL,
    prach-Partitioning                 PRACH-Partitioning                                OPTIONAL,
    persistenceScalingFactorList       PersistenceScalingFactorList                            OPTIONAL,
    ac-To-ASC-MappingTable             AC-To-ASC-MappingTable                                OPTIONAL,
    modeSpecificInfo                   CHOICE {
        fdd                            SEQUENCE {
            primaryCPICH-TX-Power       PrimaryCPICH-TX-Power                                OPTIONAL,
            constantValue                ConstantValue                                        OPTIONAL,

```

```

        prach-PowerOffset          PRACH-PowerOffset          OPTIONAL,
        rach-TransmissionParameters RACH-TransmissionParameters OPTIONAL,
        aich-Info                  AICH-Info                  OPTIONAL
    },
    tdd                            NULL
}
}
}

PRACH-SystemInformationList ::= SEQUENCE (SIZE (1..maxPRACH)) OF
                                PRACH-SystemInformation

PreambleRetransMax ::= INTEGER (1..64)

PreambleScramblingCodeWordNumber ::= INTEGER (0..15)

PreDefPhyChConfiguration ::= SEQUENCE {
    ul-DPCH-InfoPredef          UL-DPCH-InfoPredef,
    dl-CommonInformationPredef  DL-CommonInformationPredef OPTIONAL
}

PrimaryCCPCH-Info ::= CHOICE {
    fdd                         SEQUENCE {
        tx-DiversityIndicator   BOOLEAN
    },
    tdd                         SEQUENCE {
        -- syncCase should be absent for 1.28Mcps TDD mode
        syncCase                CHOICE {
            syncCase1           SEQUENCE {
                timeslot        TimeslotNumber
            },
            syncCase2           SEQUENCE {
                timeslotSync2   TimeslotSync2
            }
        }
        cellParametersID       CellParametersID          OPTIONAL,
        blockSTTD-Indicator    BOOLEAN                  OPTIONAL,
    }
}

PrimaryCCPCH-Info-r4 ::= CHOICE {
    fdd                         SEQUENCE {
        tx-DiversityIndicator   BOOLEAN
    },
    tdd                         SEQUENCE {
        tddOption              CHOICE {
            tdd384             SEQUENCE {
                syncCase       CHOICE {
                    syncCase1  SEQUENCE {
                        timeslot TimeslotNumber
                    },
                    syncCase2  SEQUENCE {
                        timeslotSync2 TimeslotSync2
                    }
                }
            }
        },
        tdd128                 SEQUENCE {
            tstd-Indicator     BOOLEAN
        }
    },
    cellParametersID         CellParametersID          OPTIONAL,
    blockSTTD-Indicator     BOOLEAN
}

PrimaryCCPCH-Info-LCR-r4 ::= SEQUENCE {
    tstd-Indicator          BOOLEAN,
    cellParametersID      CellParametersID          OPTIONAL,
    blockSTTD-Indicator    BOOLEAN
}

-- For 1.28Mcps TDD, the following IE includes elements for the PCCPCH Info additional to those
-- in PrimaryCCPCH-Info
PrimaryCCPCH-Info-LCR-r4-ext ::= SEQUENCE {
    tstd-Indicator          BOOLEAN
}

PrimaryCCPCH-InfoPost ::= SEQUENCE {
    syncCase                CHOICE {

```

```

        syncCase1                SEQUENCE {
            timeslot                TimeslotNumber
        },
        syncCase2                SEQUENCE {
            timeslotSync2            TimeslotSync2
        }
    },
    cellParametersID            CellParametersID,
    blockSTTD-Indicator          BOOLEAN
}

PrimaryCCPCH-InfoPostTDD-LCR-r4 ::= SEQUENCE {
    tstd-Indicator                BOOLEAN,
    cellParametersID            CellParametersID,
    blockSTTD-Indicator          BOOLEAN
}

PrimaryCCPCH-TX-Power ::=          INTEGER (6..43)

PrimaryCPICH-Info ::=            SEQUENCE {
    primaryScramblingCode        PrimaryScramblingCode
}

PrimaryCPICH-TX-Power ::=        INTEGER (-10..50)

PrimaryScramblingCode ::=        INTEGER (0..511)

PuncturingLimit ::=             ENUMERATED {
    p10-40, p10-44, p10-48, p10-52, p10-56,
    p10-60, p10-64, p10-68, p10-72, p10-76,
    p10-80, p10-84, p10-88, p10-92, p10-96, p11 }

PUSCH-CapacityAllocationInfo ::= SEQUENCE {
    pusch-Allocation              CHOICE {
        pusch-AllocationPending    NULL,
        pusch-AllocationAssignment SEQUENCE {
            pdsch-AllocationPeriodInfo AllocationPeriodInfo,
            pusch-PowerControlInfo     UL-TargetSIR                OPTIONAL,
            tfcs-ID                    TFCS-IdentityPlain          DEFAULT 1,
            configuration                CHOICE {
                old-Configuration        SEQUENCE {
                    pusch-Identity        PUSCH-Identity
                },
                new-Configuration        SEQUENCE {
                    pusch-Info            PUSCH-Info,
                    pusch-Identity        PUSCH-Identity          OPTIONAL
                }
            }
        }
    }
}

PUSCH-CapacityAllocationInfo-r4 ::= SEQUENCE {
    pusch-Allocation              CHOICE {
        pusch-AllocationPending    NULL,
        pusch-AllocationAssignment SEQUENCE {
            pdsch-AllocationPeriodInfo AllocationPeriodInfo,
            pusch-PowerControlInfo     PUSCH-PowerControlInfo-r4  OPTIONAL,
            tfcs-Identity              TFCS-IdentityPlain          OPTIONAL,
            configuration                CHOICE {
                old-Configuration        SEQUENCE {
                    pusch-Identity        PUSCH-Identity
                },
                new-Configuration        SEQUENCE {
                    pusch-Info-r4        PUSCH-Info-r4,
                    pusch-Identity        PUSCH-Identity          OPTIONAL
                }
            }
        }
    }
}

PUSCH-Identity ::=              INTEGER (1..hiPUSCHidentities)

PUSCH-Info ::=                  SEQUENCE {
    tfcs-ID                      TFCS-IdentityPlain          DEFAULT 1,
    commonTimeslotInfo            CommonTimeslotInfo              OPTIONAL,
    pusch-TimeslotsCodes          UplinkTimeslotsCodes              OPTIONAL
}

```

```

}

PUSCH-Info-r4 ::=
    tfcs-ID
    commonTimeslotInfo
    tddOption
        tdd384
            pusch-TimeslotsCodes
        },
        tdd128
            pusch-TimeslotsCodes
    }
}

PUSCH-Info-LCR-r4 ::=
    tfcs-ID

    commonTimeslotInfo
    pusch-TimeslotsCodes
}

PUSCH-PowerControlInfo-r4 ::=
    ul-TargetSIR
    tddOption
        tdd384
            tpc-StepSize
            dl-CCTrChTPCList
        },
        tdd128
            tpc-StepSize
            dl-CCTrChTPCList
    }
}

PUSCH-SysInfo ::=
    pusch-Identity
    pusch-Info
    usch-TFS
    usch-TFCS
}

PUSCH-SysInfo-LCR-r4 ::=
    pusch-Identity
    pusch-Info
    usch-TFS
    usch-TFCS
}

PUSCH-SysInfoList ::=
    SEQUENCE (SIZE (1..maxPUSCH)) OF
        PUSCH-SysInfo

PUSCH-SysInfoList-LCR-r4 ::=
    SEQUENCE (SIZE (1..maxPUSCH)) OF
        PUSCH-SysInfo-LCR-r4

PUSCH-SysInfoList-SFN ::=
    SEQUENCE (SIZE (1..maxPUSCH)) OF
        SEQUENCE {
            pusch-SysInfo
            sfm-TimeInfo
        }
        PUSCH-SysInfo,
        SFN-TimeInfo
    OPTIONAL

PUSCH-SysInfoList-SFN-LCR-r4 ::=
    SEQUENCE (SIZE (1..maxPDSCH)) OF
        SEQUENCE {
            pusch-SysInfo
            sfm-TimeInfo
        }
        PUSCH-SysInfo-LCR-r4,
        SFN-TimeInfo
    OPTIONAL

RACH-TransmissionParameters ::=
    SEQUENCE {
        mmax
            INTEGER (1..32),
        nb01Min
            NB01,
        nb01Max
            NB01
    }

ReducedScramblingCodeNumber ::=
    INTEGER (0..8191)

RepetitionPeriodAndLength ::=
    CHOICE {
        repetitionPeriod1
            NULL,
        repetitionPeriod2
            INTEGER (1..1),
        -- repetitionPeriod2 could just as well be NULL also.
        repetitionPeriod4
            INTEGER (1..3),
    }

```

```

    repetitionPeriod8          INTEGER (1..7),
    repetitionPeriod16         INTEGER (1..15),
    repetitionPeriod32         INTEGER (1..31),
    repetitionPeriod64         INTEGER (1..63)
}

RepetitionPeriodLengthAndOffset ::= CHOICE {
    repetitionPeriod1          NULL,
    repetitionPeriod2          SEQUENCE {
        length                  NULL,
        offset                  INTEGER (0..1)
    },
    repetitionPeriod4          SEQUENCE {
        length                  INTEGER (1..3),
        offset                  INTEGER (0..3)
    },
    repetitionPeriod8          SEQUENCE {
        length                  INTEGER (1..7),
        offset                  INTEGER (0..7)
    },
    repetitionPeriod16         SEQUENCE {
        length                  INTEGER (1..15),
        offset                  INTEGER (0..15)
    },
    repetitionPeriod32         SEQUENCE {
        length                  INTEGER (1..31),
        offset                  INTEGER (0..31)
    },
    repetitionPeriod64         SEQUENCE {
        length                  INTEGER (1..63),
        offset                  INTEGER (0..63)
    }
}

ReplacedPDSCH-CodeInfo ::= SEQUENCE {
    tfci-Field2                MaxTFCI-Field2Value,
    spreadingFactor            SF-PDSCH,
    codeNumber                  CodeNumberDsch,
    multiCodeInfo              MultiCodeInfo
}

ReplacedPDSCH-CodeInfoList ::= SEQUENCE (SIZE (1..maxTFCI-2-Combs)) OF
    ReplacedPDSCH-CodeInfo

RepPerLengthOffset-PICH ::= CHOICE {
    rpp4-2                     INTEGER (0..3),
    rpp8-2                     INTEGER (0..7),
    rpp8-4                     INTEGER (0..7),
    rpp16-2                    INTEGER (0..15),
    rpp16-4                    INTEGER (0..15),
    rpp32-2                    INTEGER (0..31),
    rpp32-4                    INTEGER (0..31),
    rpp64-2                    INTEGER (0..63),
    rpp64-4                    INTEGER (0..63)
}

RestrictedTrCH ::= SEQUENCE {
    dl-restrictedTrCh-Type     DL-TrCH-Type,
    restrictedDL-TrCH-Identity TransportChannelIdentity,
    allowedTFIList             AllowedTFI-List
}

RestrictedTrCH-InfoList ::= SEQUENCE (SIZE(1..maxTrCH)) OF
    RestrictedTrCH

RL-AdditionInformation ::= SEQUENCE {
    primaryCPICH-Info          PrimaryCPICH-Info,
    dl-DPCH-InfoPerRL          DL-DPCH-InfoPerRL,
    tfci-CombiningIndicator     BOOLEAN,
    sccpch-InfoForFACH          SCCPCH-InfoForFACH
}

RL-AdditionInformationList ::= SEQUENCE (SIZE (1..maxRL-1)) OF
    RL-AdditionInformation

RL-IdentifierList ::= SEQUENCE (SIZE (1..maxRL)) OF
    PrimaryCPICH-Info

```

```

RL-RemovalInformationList ::= SEQUENCE (SIZE (1..maxRL)) OF
    PrimaryCPICH-Info

RPP ::= ENUMERATED {
    mode0, mode1 }

S-Field ::= ENUMERATED {
    elbit, e2bits }

SCCPCH-ChannelisationCode ::= ENUMERATED {
    cc16-1, cc16-2, cc16-3, cc16-4,
    cc16-5, cc16-6, cc16-7, cc16-8,
    cc16-9, cc16-10, cc16-11, cc16-12,
    cc16-13, cc16-14, cc16-15, cc16-16 }

SCCPCH-ChannelisationCodeList ::= SEQUENCE (SIZE (1..16)) OF
    SCCPCH-ChannelisationCode

SCCPCH-InfoForFACH ::= SEQUENCE {
    secondaryCCPCH-Info SecondaryCCPCH-Info,
    tfcs TFCS,
    modeSpecificInfo CHOICE {
        fdd SEQUENCE {
            fach-PCH-InformationList FACH-PCH-InformationList,
            sib-ReferenceListFACH SIB-ReferenceListFACH
        },
        tdd NULL
    }
}

SCCPCH-SystemInformation ::= SEQUENCE {
    secondaryCCPCH-Info SecondaryCCPCH-Info,
    tfcs TFCS OPTIONAL,
    fach-PCH-InformationList FACH-PCH-InformationList OPTIONAL,
    pich-Info PICH-Info OPTIONAL
}

SCCPCH-SystemInformation-LCR-r4-ext ::= SEQUENCE {
    secondaryCCPCH-LCR-Extensions SecondaryCCPCH-Info-LCR-r4-ext,
    -- pich-Info in the SCCPCH-SystemInformation IE shall be absent, and instead the following used.
    pich-Info PICH-Info-LCR-r4 OPTIONAL
}

SCCPCH-SystemInformationList ::= SEQUENCE (SIZE (1..maxSCCPCH)) OF
    SCCPCH-SystemInformation

-- The following list includes elements additional to those in
-- SCCPCH-SystemInformationList for the 1.28Mcps TDD. The order of the IEs
-- indicates which SCCPCH-SystemInformation-LCR-r4-ext IE extends which
-- SCCPCH-SystemInformation IE.
SCCPCH-SystemInformationList-LCR-r4-ext ::= SEQUENCE (SIZE (1..maxSCCPCH)) OF
    SCCPCH-SystemInformation-LCR-r4-ext

ScramblingCodeChange ::= ENUMERATED {
    codeChange, noCodeChange }

ScramblingCodeType ::= ENUMERATED {
    shortSC,
    longSC }

SecondaryCCPCH-Info ::= SEQUENCE {
    modeSpecificInfo CHOICE {
        fdd SEQUENCE {
            pCPICH-UsageForChannelEst PCPICH-UsageForChannelEst,
            secondaryCPICH-Info SecondaryCPICH-Info OPTIONAL,
            secondaryScramblingCode SecondaryScramblingCode OPTIONAL,
            sttd-Indicator BOOLEAN,
            sf-AndCodeNumber SF256-AndCodeNumber,
            pilotSymbolExistence BOOLEAN,
            tfci-Existence BOOLEAN,
            positionFixedOrFlexible PositionFixedOrFlexible,
            timingOffset TimingOffset DEFAULT 0
        },
        tdd SEQUENCE {
            -- TABULAR: the offset is included in CommonTimeslotInfoSCCPCH
            commonTimeslotInfo CommonTimeslotInfoSCCPCH,
            individualTimeslotInfo IndividualTimeslotInfo,
            channelisationCode SCCPCH-ChannelisationCodeList
        }
    }
}

```



```

    }
  }
}

SecondaryCCPCH-Info-r4 ::= SEQUENCE {
  modeSpecificInfo CHOICE {
    fdd SEQUENCE {
      pCPICH-UsageForChannelEst PCPICH-UsageForChannelEst,
      secondaryCPICH-Info SecondaryCPICH-Info OPTIONAL,
      secondaryScramblingCode SecondaryScramblingCode OPTIONAL,
      sttG-Indicator BOOLEAN,
      sf-AndCodeNumber SF256-AndCodeNumber,
      pilotSymbolExistence BOOLEAN,
      tfci-Existence BOOLEAN,
      positionFixedOrFlexible PositionFixedOrFlexible,
      timingOffset TimingOffset DEFAULT 0
    },
    tdd SEQUENCE {
      -- TABULAR: the offset is included in CommonTimeslotInfoSCCPCH
      commonTimeslotInfo CommonTimeslotInfoSCCPCH,
      tddOption CHOICE {
        tdd384 SEQUENCE {
          individualTimeslotInfo IndividualTimeslotInfo
        },
        tdd128 SEQUENCE {
          individualTimeslotInfo IndividualTimeslotInfo-LCR-r4
        }
      },
      channelisationCode SCCPCH-ChannelisationCodeList
    }
  }
}

SecondaryCCPCH-Info-LCR-r4-ext ::= SEQUENCE {
  individualTimeslotLCR-Ext IndividualTimeslotInfo-LCR-r4-ext
}

SecondaryCPICH-Info ::= SEQUENCE {
  secondaryDL-ScramblingCode SecondaryScramblingCode OPTIONAL,
  channelisationCode ChannelisationCode256
}

SecondaryScramblingCode ::= INTEGER (1..15)

SecondInterleavingMode ::= ENUMERATED {
  frameRelated, timeslotRelated }

-- SF256-AndCodeNumber encodes both "Spreading factor" and "Code Number"
SF256-AndCodeNumber ::= CHOICE {
  sf4 INTEGER (0..3),
  sf8 INTEGER (0..7),
  sf16 INTEGER (0..15),
  sf32 INTEGER (0..31),
  sf64 INTEGER (0..63),
  sf128 INTEGER (0..127),
  sf256 INTEGER (0..255)
}

-- SF512-AndCodeNumber encodes both "Spreading factor" and "Code Number"
SF512-AndCodeNumber ::= CHOICE {
  sf4 INTEGER (0..3),
  sf8 INTEGER (0..7),
  sf16 INTEGER (0..15),
  sf32 INTEGER (0..31),
  sf64 INTEGER (0..63),
  sf128 INTEGER (0..127),
  sf256 INTEGER (0..255),
  sf512 INTEGER (0..511)
}

-- SF512-AndPilot encodes both "Spreading factor" and "Number of bits for Pilot bits"
SF512-AndPilot ::= CHOICE {
  sfd4 NULL,
  sfd8 NULL,
  sfd16 NULL,
  sfd32 NULL,
  sfd64 NULL,
  sfd128 PilotBits128,
}

```

```

    sfd256                PilotBits256,
    sfd512                NULL
}
SF-PDSCH ::=             ENUMERATED {
                           sfp4, sfp8, sfp16, sfp32,
                           sfp64, sfp128, sfp256 }

SF-PRACH ::=             ENUMERATED {
                           sfpr32, sfpr64, sfpr128, sfpr256 }

SFN-TimeInfo ::=        SEQUENCE {
    activationTimeSFN     INTEGER (0..4095),
    physChDuration        DurationTimeInfo
}

SpecialBurstScheduling ::= INTEGER (0..7)

SpreadingFactor ::=     ENUMERATED {
                           sf4, sf8, sf16, sf32,
                           sf64, sf128, sf256 }

SRB-delay ::=           INTEGER (0..7)

SSDT-CellIdentity ::=  ENUMERATED {
                           ssdt-id-a, ssdt-id-b, ssdt-id-c,
                           ssdt-id-d, ssdt-id-e, ssdt-id-f,
                           ssdt-id-g, ssdt-id-h }

SSDT-Information ::=    SEQUENCE {
    s-Field                S-Field,
    codeWordSet            CodeWordSet
}

SSDT-Information-r4 ::= SEQUENCE {
    s-Field                S-Field,
    codeWordSet            CodeWordSet,
    ssdt-UL                SSDT-UL-r4
}
                                                                    OPTIONAL

-- The following information element is used to extend the
-- SSDT-Information IE from Release 4 onwards.
SSDT-UL-r4 ::=          ENUMERATED {
                           ul, ul-AndDL }

SynchronisationParameters-r4 ::= SEQUENCE {
    sync-UL-CodesBitmap    BIT STRING (SIZE (8))
                                                                    OPTIONAL,
    fpach-Info             FPACH-Info-r4,
    sync-UL-Procedure      SYNC-UL-Procedure-r4
                                                                    OPTIONAL
}

SYNC-UL-Procedure-r4 ::= SEQUENCE {
    max-SYNC-UL-Transmissions
                                                                    ENUMERATED { tr1, tr2, tr4, tr8 },
    powerRampingStep       INTEGER (0..3)
}

SYNC-UL-Info-r4 ::=     SEQUENCE {
    sync-UL-Codes-Bitmap   BIT STRING ( SIZE (8)),
    ul-TargetSIR           UL-TargetSIR,
    powerRampingStep       INTEGER (0..3),
    max-SYNC-UL-Transmissions
                                                                    ENUMERATED { tr1, tr2, tr4, tr8 } ,
    mmax                   INTEGER(1..32)
}

TDD-FPACH-CCode16-r4 ::= ENUMERATED {
                           cc16-1, cc16-2, cc16-3, cc16-4,
                           cc16-5, cc16-6, cc16-7, cc16-8,
                           cc16-9, cc16-10, cc16-11, cc16-12,
                           cc16-13, cc16-14, cc16-15, cc16-16 }

TDD-PICH-CCode ::=     ENUMERATED {
                           cc16-1, cc16-2, cc16-3, cc16-4,
                           cc16-5, cc16-6, cc16-7, cc16-8,
                           cc16-9, cc16-10, cc16-11, cc16-12,
                           cc16-13, cc16-14, cc16-15, cc16-16 }

TDD-PRACH-CCode8 ::=   ENUMERATED {
                           cc8-1, cc8-2, cc8-3, cc8-4,
                           cc8-5, cc8-6, cc8-7, cc8-8 }

```

```

TDD-PRACH-CCode16 ::=          ENUMERATED {
                                cc16-1, cc16-2, cc16-3, cc16-4,
                                cc16-5, cc16-6, cc16-7, cc16-8,
                                cc16-9, cc16-10, cc16-11, cc16-12,
                                cc16-13, cc16-14, cc16-15, cc16-16 }

TDD-PRACH-CCode-LCR-r4 ::=     ENUMERATED {
                                cc4-1, cc4-2, cc4-3, cc4-4,
                                cc8-1, cc8-2, cc8-3, cc8-4,
                                cc8-5, cc8-6, cc8-7, cc8-8,
                                cc16-1, cc16-2, cc16-3, cc16-4,
                                cc16-5, cc16-6, cc16-7, cc16-8,
                                cc16-9, cc16-10, cc16-11, cc16-12,
                                cc16-13, cc16-14, cc16-15, cc16-16 }

TDD-PRACH-CCodeList ::=       CHOICE {
                                sf8
                                SEQUENCE (SIZE (1..8)) OF
                                    TDD-PRACH-CCode8,
                                sf16
                                SEQUENCE (SIZE (1..8)) OF
                                    TDD-PRACH-CCode16
                                }

TFC-ControlDuration ::=       ENUMERATED {
                                tfc-cd1, tfc-cd2, tfc-cd4, tfc-cd8,
                                tfc-cd16, tfc-cd24, tfc-cd32,
                                tfc-cd48, tfc-cd64, tfc-cd128,
                                tfc-cd192, tfc-cd256, tfc-cd512 }

TFCI-Coding ::=               ENUMERATED {
                                tfci-bits-4, tfci-bits-8,
                                tfci-bits-16, tfci-bits-32 }

TGCFN ::=                     INTEGER (0..255)

-- The value 270 represents "undefined" in the tabular description.
TGD ::=                       INTEGER (15..270)

TGL ::=                       INTEGER (1..14)

TGMP ::=                     ENUMERATED {
                                tdd-Measurement, fdd-Measurement,
                                gsm-CarrierRSSIMeasurement,
                                gsm-initialBSICIdentification, gsmBSICReconfirmation,
                                multi-carrier }

TGP-Sequence ::=              SEQUENCE {
                                tgpsi
                                TGPSI,
                                tgps-Status
                                CHOICE {
                                    activate
                                    SEQUENCE {
                                        tgcfm
                                        TGCFN
                                    },
                                    deactivate
                                    NULL
                                },
                                tgps-ConfigurationParams
                                TGPS-ConfigurationParams
                                OPTIONAL
                                }

TGPS-Reconfiguration-CFN ::=   INTEGER (0..255)

TGP-SequenceList ::=          SEQUENCE (SIZE (1..maxTGPS)) OF
                                TGP-Sequence

TGP-SequenceShort ::=         SEQUENCE {
                                tgpsi
                                TGPSI,
                                tgps-Status
                                CHOICE {
                                    activate
                                    SEQUENCE {
                                        tgcfm
                                        TGCFN
                                    },
                                    deactivate
                                    NULL
                                }
                                }

TGPL ::=                     INTEGER (1..144)

-- TABULAR: The value 0 represents "infinity" in the tabular description.
TGPRC ::=                     INTEGER (0..511)

TGPS-ConfigurationParams ::=   SEQUENCE {

```

```

    tgmprc          TGMPRC,
    tgsn            TGSN,
    tgl1            TGL,
    tgl2            TGL                                OPTIONAL,
    tgd             TGD,
    tgpl1           TGPL,
    tgpl2           TGPL                                OPTIONAL,
    rpp             RPP,
    itp             ITP,
    ul-DL-Mode      UL-DL-Mode,
    -- TABULAR: Compressed mode method is nested inside UL-DL-Mode
    dl-FrameType    DL-FrameType,
    deltaSIR1       DeltaSIR,
    deltaSIRAfter1  DeltaSIR,
    deltaSIR2       DeltaSIR                                OPTIONAL,
    deltaSIRAfter2  DeltaSIR                                OPTIONAL,
    nidentifyAbort  NidentifyAbort                        OPTIONAL,
    treconfirmAbort TreconfirmAbort                      OPTIONAL
}

TGPSI ::=          INTEGER (1..maxTGPS)

TGSN ::=           INTEGER (0..14)

TimeInfo ::=       SEQUENCE {
    activationTime  ActivationTime                        OPTIONAL,
    durationTimeInfo DurationTimeInfo                    OPTIONAL
}

TimeslotList ::=   SEQUENCE (SIZE (1..maxTS)) OF
    TimeslotNumber

TimeslotList-r4 ::= CHOICE {
    tdd384          SEQUENCE (SIZE (1..maxTS)) OF
        TimeslotNumber,
    tdd128          SEQUENCE (SIZE (1..maxTS-LCR)) OF
        TimeslotNumber-LCR-r4
}

-- If TimeslotNumber is included for a 1.28Mcps TDD description, it shall take values from 0..6
TimeslotNumber ::= INTEGER (0..14)

TimeslotNumber-LCR-r4 ::= INTEGER (0..6)

TimeslotNumber-PRACH-LCR-r4 ::= INTEGER (1..6)

TimeslotSync2 ::=  INTEGER (0..6)

-- Actual value = IE value * 256
TimingOffset ::=   INTEGER (0..149)

TPC-CombinationIndex ::= INTEGER (0..5)

TPC-StepSizeFDD ::= INTEGER (0..1)

TPC-StepSizeTDD ::= INTEGER (1..3)

-- Actual value = IE value * 0.5 seconds
TreconfirmAbort ::= INTEGER (1..20)

TX-DiversityMode ::= ENUMERATED {
    noDiversity,
    sttd,
    closedLoopMode1,
    closedLoopMode2 }

UARFCN ::=         INTEGER (0..16383)

UCSM-Info ::=      SEQUENCE {
    minimumSpreadingFactor MinimumSpreadingFactor,
    nf-Max              NF-Max,
    channelReqParamsForUCSM ChannelReqParamsForUCSM
}

UL-CCTrCH ::=      SEQUENCE {
    tfcs-ID             TFCS-IdentityPlain                DEFAULT 1,
    timeInfo            TimeInfo,

```

```

    commonTimeslotInfo          CommonTimeslotInfo          OPTIONAL,
    ul-CCTrCH-TimeslotsCodes    UplinkTimeslotsCodes      OPTIONAL
}

UL-CCTrCH-r4 ::=
    tfcs-ID                      TFCS-IdentityPlain          DEFAULT 1,
    timeInfo                      TimeInfo,
    commonTimeslotInfo            CommonTimeslotInfo          OPTIONAL,
    tddOption                     CHOICE {
        tdd384                    SEQUENCE {
            ul-CCTrCH-TimeslotsCodes    UplinkTimeslotsCodes      OPTIONAL
        },
        tdd128                    SEQUENCE {
            ul-CCTrCH-TimeslotsCodes    UplinkTimeslotsCodes-LCR-r4 OPTIONAL
        }
    }
}

UL-CCTrCHList ::=
    SEQUENCE (SIZE (1..maxCCTrCH)) OF
    UL-CCTrCH

UL-CCTrCHList-r4 ::=
    SEQUENCE (SIZE (1..maxCCTrCH)) OF
    UL-CCTrCH-r4

UL-CCTrChTPCList ::=
    SEQUENCE (SIZE (0..maxCCTrCH)) OF
    TFCS-Identity

UL-ChannelRequirement ::=
    CHOICE {
        ul-DPCH-Info              UL-DPCH-Info,
        cpch-SetInfo              CPCH-SetInfo
    }

UL-ChannelRequirement-r4 ::=
    CHOICE {
        ul-DPCH-Info              UL-DPCH-Info-r4,
        cpch-SetInfo              CPCH-SetInfo
    }

UL-ChannelRequirementWithCPCH-SetID ::= CHOICE {
    ul-DPCH-Info                  UL-DPCH-Info,
    cpch-SetInfo                  CPCH-SetInfo,
    cpch-SetID                    CPCH-SetID
}

UL-ChannelRequirementWithCPCH-SetID-r4 ::= CHOICE {
    ul-DPCH-Info                  UL-DPCH-Info-r4,
    cpch-SetInfo                  CPCH-SetInfo,
    cpch-SetID                    CPCH-SetID
}

UL-CompressedModeMethod ::=
    ENUMERATED {
        sf-2,
        higherLayerScheduling }

UL-DL-Mode ::=
    CHOICE {
        ul                          UL-CompressedModeMethod,
        dl                          DL-CompressedModeMethod,
        ul-and-dl                    SEQUENCE {
            ul                        UL-CompressedModeMethod,
            dl                        DL-CompressedModeMethod
        }
    }

UL-DPCCH-SlotFormat ::=
    ENUMERATED {
        slf0, slf1, slf2 }

UL-DPCH-Info ::=
    SEQUENCE {
        ul-DPCH-PowerControlInfo    UL-DPCH-PowerControlInfo    OPTIONAL,
        modeSpecificInfo            CHOICE {
            fdd                      SEQUENCE {
                scramblingCodeType    ScramblingCodeType,
                scramblingCode         UL-ScramblingCode,
                numberOfDPDCH          NumberOfDPDCH              DEFAULT 1,
                spreadingFactor        SpreadingFactor,
                tfci-Existence         BOOLEAN,
                numberOfFBI-Bits       NumberOfFBI-Bits          OPTIONAL,
                -- The IE above is conditional based on history
                puncturingLimit        PuncturingLimit
            },
            tdd                      SEQUENCE {

```

```

        ul-TimingAdvance
        ul-CCTrCHList
    }
}

UL-DPCH-Info-r4 ::=
    ul-DPCH-PowerControlInfo
    modeSpecificInfo
        fdd
            scramblingCodeType
            scramblingCode
            numberOfDPDCH
            spreadingFactor
            tfci-Existence
            numberOfFBI-Bits
            -- The IE above is conditional based on history
            puncturingLimit
        },
        tdd
            ul-TimingAdvance
            ul-CCTrCHList
    }
}

UL-DPCH-InfoPostFDD ::=
    ul-DPCH-PowerControlInfo
        scramblingCodeType
        reducedScramblingCodeNumber
        spreadingFactor
    }

UL-DPCH-InfoPostTDD ::=
    ul-DPCH-PowerControlInfo
    ul-TimingAdvance
    ul-CCTrCH-TimeslotsCodes
}

UL-DPCH-InfoPostTDD-LCR-r4 ::=
    ul-DPCH-PowerControlInfo
    ul-TimingAdvance
    ul-CCTrCH-TimeslotsCodes
}

UL-DPCH-InfoPredef ::=
    ul-DPCH-PowerControlInfo
    modeSpecificInfo
        fdd
            tfci-Existence
            puncturingLimit
        },
        tdd
            commonTimeslotInfo
    }
}

UL-DPCH-PowerControlInfo ::=
    fdd
        dpch-PowerOffset
        pc-Preamble
        sRB-delay
        powerControlAlgorithm
        -- TABULAR: TPC step size nested inside PowerControlAlgorithm
    },
    tdd
        ul-TargetSIR
        ul-OL-PC-Signalling
        broadcast-UL-OL-PC-info
        handoverGroup
            individualTS-InterferenceList
            dpch-ConstantValue
            primaryCCPCH-TX-Power
        }
    }
}

```

```

}

UL-DPCH-PowerControlInfo-r4 ::= CHOICE {
  fdd SEQUENCE {
    dpcch-PowerOffset DPCCH-PowerOffset,
    pc-Preamble PC-Preamble,
    powerControlAlgorithm PowerControlAlgorithm
    -- TABULAR: TPC step size nested inside PowerControlAlgorithm
  },
  tdd SEQUENCE {
    ul-TargetSIR UL-TargetSIR,
    ul-OL-PC-Signalling CHOICE {
      broadcast-UL-OL-PC-info NULL,
      handoverGroup SEQUENCE {
        tddOption CHOICE {
          tdd384 SEQUENCE {
            individualTS-InterferenceList IndividualTS-InterferenceList,
            dpch-ConstantValue ConstantValue
          },
          tdd128 SEQUENCE {
            tpc-StepSize TPC-StepSizeTDD
          }
        }
      },
      primaryCCPCH-TX-Power PrimaryCCPCH-TX-Power
    }
  }
}

UL-DPCH-PowerControlInfoPostFDD ::= SEQUENCE {
  dpcch-PowerOffset DPCCH-PowerOffset2, -- smaller range to save bits
  pc-Preamble PC-Preamble,
  SRB-delay SRB-delay
}

UL-DPCH-PowerControlInfoPostTDD ::= SEQUENCE {
  ul-TargetSIR UL-TargetSIR,
  ul-TimeslotInterference UL-Interference
}

UL-DPCH-PowerControlInfoPostTDD-LCR-r4 ::= SEQUENCE {
  ul-TargetSIR UL-TargetSIR
}

UL-DPCH-PowerControlInfoPredef ::= CHOICE {
  fdd SEQUENCE {
    powerControlAlgorithm PowerControlAlgorithm
    -- TABULAR: TPC step size nested inside PowerControlAlgorithm
  },
  tdd SEQUENCE {
    -- The following IE shall be ignored if in 1.28Mcps TDD mode.
    dpch-ConstantValue ConstantValue
  }
}

UL-Interference ::= INTEGER (-110..-70)

UL-ScramblingCode ::= INTEGER (0..16777215)

UL-SynchronisationParameters-r4 ::= SEQUENCE {
  stepSize INTEGER (1..8),
  frequency INTEGER (1..8)
}

-- Actual value = (IE value * 0.5) - 11
UL-TargetSIR ::= INTEGER (0..62)

UL-TimingAdvance ::= INTEGER (0..63)

UL-TimingAdvanceControl ::= CHOICE {
  disabled NULL,
  enabled SEQUENCE {
    ul-TimingAdvance UL-TimingAdvance OPTIONAL,
    activationTime ActivationTime OPTIONAL
  }
}

```

```

UL-TimingAdvanceControl-r4 ::= CHOICE {
    disabled          NULL,
    enabled           SEQUENCE {
        tddOption     CHOICE {
            tdd384    SEQUENCE {
                ul-TimingAdvance          UL-TimingAdvance          OPTIONAL,
                activationTime            ActivationTime            OPTIONAL
            },
            tdd128    SEQUENCE {
                ul-SynchronisationParameters  UL-SynchronisationParameters-r4 OPTIONAL,
                synchronisationParameters      SynchronisationParameters-r4 OPTIONAL
            }
        }
    }
}

UL-TimingAdvanceControl-LCR-r4 ::= CHOICE {
    disabled          NULL,
    enabled           SEQUENCE {
        ul-SynchronisationParameters  UL-SynchronisationParameters-r4 OPTIONAL,
        synchronisationParameters      SynchronisationParameters-r4   OPTIONAL
    }
}

UL-TS-ChannelisationCode ::= ENUMERATED {
    cc1-1, cc2-1, cc2-2,
    cc4-1, cc4-2, cc4-3, cc4-4,
    cc8-1, cc8-2, cc8-3, cc8-4,
    cc8-5, cc8-6, cc8-7, cc8-8,
    cc16-1, cc16-2, cc16-3, cc16-4,
    cc16-5, cc16-6, cc16-7, cc16-8,
    cc16-9, cc16-10, cc16-11, cc16-12,
    cc16-13, cc16-14, cc16-15, cc16-16 }

UL-TS-ChannelisationCodeList ::= SEQUENCE (SIZE (1..2)) OF
    UL-TS-ChannelisationCode

UplinkAdditionalTimeslots ::= SEQUENCE {
    parameters          CHOICE {
        sameAsLast      SEQUENCE {
            timeslotNumber      TimeslotNumber
        },
        newParameters    SEQUENCE {
            individualTimeslotInfo  IndividualTimeslotInfo,
            ul-TS-ChannelisationCodeList  UL-TS-ChannelisationCodeList
        }
    }
}

UplinkAdditionalTimeslots-LCR-r4 ::= SEQUENCE {
    parameters          CHOICE {
        sameAsLast      SEQUENCE {
            timeslotNumber      TimeslotNumber
        },
        newParameters    SEQUENCE {
            individualTimeslotInfo  IndividualTimeslotInfo-LCR-r4,
            ul-TS-ChannelisationCodeList  UL-TS-ChannelisationCodeList
        }
    }
}

UplinkTimeslotsCodes ::= SEQUENCE {
    dynamicSFusage      BOOLEAN,
    firstIndividualTimeslotInfo  IndividualTimeslotInfo,
    ul-TS-ChannelisationCodeList  UL-TS-ChannelisationCodeList,
    moreTimeslots       CHOICE {
        noMore          NULL,
        additionalTimeslots  CHOICE {
            consecutive    SEQUENCE {
                numAdditionalTimeslots  INTEGER (1..maxTS-1)
            },
            timeslotList    SEQUENCE (SIZE (1..maxTS-1)) OF
                UplinkAdditionalTimeslots
        }
    }
}

UplinkTimeslotsCodes-LCR-r4 ::= SEQUENCE {

```



```

dynamicSFusage          BOOLEAN,
firstIndividualTimeslotInfo IndividualTimeslotInfo-LCR-r4,
ul-TS-ChannelisationCodeList UL-TS-ChannelisationCodeList,
moreTimeslots          CHOICE {
  noMore                NULL,
  additionalTimeslots   CHOICE {
    consecutive         SEQUENCE {
      numAdditionalTimeslots INTEGER (1..maxTS-LCR-1)
    },
    timeslotList        SEQUENCE (SIZE (1..maxTS-LCR-1)) OF
                        UplinkAdditionalTimeslots-LCR-r4
  }
}
}

Wi-LCR ::=                                                       INTEGER(1..4)

-- *****
--
-- MEASUREMENT INFORMATION ELEMENTS (10.3.7)
--
-- *****

AcquisitionSatInfo ::=          SEQUENCE {
  satID                          SatID,
  -- Actual value = IE value * 2.5
  doppler0thOrder                INTEGER (-2048..2047),
  extraDopplerInfo                ExtraDopplerInfo                OPTIONAL,
  codePhase                       INTEGER (0..1022),
  integerCodePhase                INTEGER (0..19),
  gps-BitNumber                   INTEGER (0..3),
  codePhaseSearchWindow           CodePhaseSearchWindow,
  azimuthAndElevation             AzimuthAndElevation             OPTIONAL
}

AcquisitionSatInfoList ::=      SEQUENCE (SIZE (1..maxSat)) OF
                                AcquisitionSatInfo

AdditionalMeasurementID-List ::= SEQUENCE (SIZE (1..maxAdditionalMeas)) OF
                                MeasurementIdentity

AlmanacSatInfo ::=              SEQUENCE {
  dataID                          INTEGER (0..3),
  satID                            SatID,
  e                                BIT STRING (SIZE (16)),
  t-oa                             BIT STRING (SIZE (8)),
  deltaI                            BIT STRING (SIZE (16)),
  omegaDot                          BIT STRING (SIZE (16)),
  satHealth                         BIT STRING (SIZE (8)),
  a-Sqrt                            BIT STRING (SIZE (24)),
  omega0                            BIT STRING (SIZE (24)),
  m0                                BIT STRING (SIZE (24)),
  omega                             BIT STRING (SIZE (24)),
  af0                               BIT STRING (SIZE (11)),
  af1                               BIT STRING (SIZE (11))
}

AlmanacSatInfoList ::=          SEQUENCE (SIZE (1..maxSat)) OF
                                AlmanacSatInfo

AverageRLC-BufferPayload ::=    ENUMERATED {
  pla0, pla4, pla8, pla16, pla32,
  pla64, pla128, pla256, pla512,
  pla1024, pla2k, pla4k, pla8k, pla16k,
  pla32k, pla64k, pla128k, pla256k,
  pla512k, pla1024k }

AzimuthAndElevation ::=        SEQUENCE {
  -- Actual value = IE value * 11.25
  azimuth                          INTEGER (0..31),
  -- Actual value = IE value * 11.25
  elevation                         INTEGER (0..7)
}

BadSatList ::=                  SEQUENCE (SIZE (1..maxSat)) OF
                                INTEGER (0..63)

```

```

Frequency-Band ::=
    ENUMERATED {
        dcs1800BandUsed, pcs1900BandUsed }

BCCH-ARFCN ::=
    INTEGER (0..1023)

BLER-MeasurementResults ::=
    SEQUENCE {
        transportChannelIdentity
            TransportChannelIdentity,
        dl-TransportChannelBLER
            DL-TransportChannelBLER
    }
    OPTIONAL

BLER-MeasurementResultsList ::=
    SEQUENCE (SIZE (1..maxTrCH)) OF
        BLER-MeasurementResults

BLER-TransChIdList ::=
    SEQUENCE (SIZE (1..maxTrCH)) OF
        TransportChannelIdentity

BSIC-VerificationRequired ::=
    ENUMERATED {
        required, notRequired }

BSICReported ::=
    CHOICE {
        -- Value maxCellMeas is not allowed for verifiedBSIC
        verifiedBSIC
            INTEGER (0..maxCellMeas),
        nonVerifiedBSIC
            BCCH-ARFCN
    }

BurstModeParameters ::=
    SEQUENCE {
        burstStart
            INTEGER (0..15),
        burstLength
            INTEGER (10..25),
        burstFreq
            INTEGER (1..16)
    }

CellDCH-ReportCriteria ::=
    CHOICE {
        intraFreqReportingCriteria
            IntraFreqReportingCriteria,
        periodicalReportingCriteria
            PeriodicalReportingCriteria
    }

CellDCH-ReportCriteria-LCR-r4 ::=
    CHOICE {
        intraFreqReportingCriteria
            IntraFreqReportingCriteria-LCR-r4,
        periodicalReportingCriteria
            PeriodicalReportingCriteria
    }

-- Actual value = IE value * 0.5
CellIndividualOffset ::=
    INTEGER (-20..20)

CellInfo ::=
    SEQUENCE {
        cellIndividualOffset
            CellIndividualOffset
            DEFAULT 0,
        referenceTimeDifferenceToCell
            ReferenceTimeDifferenceToCell
            OPTIONAL,
        modeSpecificInfo
            CHOICE {
                fdd
                    SEQUENCE {
                        primaryCPICH-Info
                            PrimaryCPICH-Info
                            OPTIONAL,
                        primaryCPICH-TX-Power
                            PrimaryCPICH-TX-Power
                            OPTIONAL,
                        readSFN-Indicator
                            BOOLEAN,
                        tx-DiversityIndicator
                            BOOLEAN
                    },
                tdd
                    SEQUENCE {
                        primaryCCPCH-Info
                            PrimaryCCPCH-Info,
                        primaryCCPCH-TX-Power
                            PrimaryCCPCH-TX-Power
                            OPTIONAL,
                        timeslotInfoList
                            TimeslotInfoList
                            OPTIONAL,
                        readSFN-Indicator
                            BOOLEAN
                    }
            }
    }

CellInfo-r4 ::=
    SEQUENCE {
        cellIndividualOffset
            CellIndividualOffset
            DEFAULT 0,
        referenceTimeDifferenceToCell
            ReferenceTimeDifferenceToCell
            OPTIONAL,
        modeSpecificInfo
            CHOICE {
                fdd
                    SEQUENCE {
                        primaryCPICH-Info
                            PrimaryCPICH-Info
                            OPTIONAL,
                        primaryCPICH-TX-Power
                            PrimaryCPICH-TX-Power
                            OPTIONAL,
                        readSFN-Indicator
                            BOOLEAN,
                        tx-DiversityIndicator
                            BOOLEAN
                    },
                tdd
                    SEQUENCE {
                        primaryCCPCH-Info
                            PrimaryCCPCH-Info-r4,
                        primaryCCPCH-TX-Power
                            PrimaryCCPCH-TX-Power
                            OPTIONAL,
                        timeslotInfoList
                            TimeslotInfoList-r4
                            OPTIONAL
                    }
            }
    }

```

```

    }
  }
}

CellInfoSI-RSCP ::=
  cellIndividualOffset
  referenceTimeDifferenceToCell
  modeSpecificInfo
  fdd
    primaryCPICH-Info
    primaryCPICH-TX-Power
    readSFN-Indicator
    tx-DiversityIndicator
  },
  tdd
    primaryCCPCH-Info
    primaryCCPCH-TX-Power
    timeslotInfoList
    readSFN-Indicator
  },
  cellSelectionReselectionInfo
}

SEQUENCE {
  CellIndividualOffset           DEFAULT 0,
  ReferenceTimeDifferenceToCell  OPTIONAL,
  CHOICE {
    SEQUENCE {
      PrimaryCPICH-Info          OPTIONAL,
      PrimaryCPICH-TX-Power      OPTIONAL,
      BOOLEAN,
      BOOLEAN
    }
    SEQUENCE {
      PrimaryCCPCH-Info,
      PrimaryCCPCH-TX-Power      OPTIONAL,
      TimeslotInfoList           OPTIONAL,
      BOOLEAN
    }
  }
  CellSelectReselectInfoSIB-11-12-RSCP  OPTIONAL
}

CellInfoSI-RSCP-LCR-r4 ::=
  cellIndividualOffset
  referenceTimeDifferenceToCell
  primaryCCPCH-Info
  primaryCCPCH-TX-Power
  timeslotInfoList
  cellSelectionReselectionInfo
}

SEQUENCE {
  CellIndividualOffset           DEFAULT 0,
  ReferenceTimeDifferenceToCell  OPTIONAL,
  PrimaryCCPCH-Info-LCR-r4,
  PrimaryCCPCH-TX-Power          OPTIONAL,
  TimeslotInfoList-LCR-r4       OPTIONAL,
  CellSelectReselectInfoSIB-11-12-RSCP  OPTIONAL
}

CellInfoSI-ECN0 ::=
  cellIndividualOffset
  referenceTimeDifferenceToCell
  modeSpecificInfo
  fdd
    primaryCPICH-Info
    primaryCPICH-TX-Power
    readSFN-Indicator
    tx-DiversityIndicator
  },
  tdd
    primaryCCPCH-Info
    primaryCCPCH-TX-Power
    timeslotInfoList
    readSFN-Indicator
  },
  cellSelectionReselectionInfo
}

SEQUENCE {
  CellIndividualOffset           DEFAULT 0,
  ReferenceTimeDifferenceToCell  OPTIONAL,
  CHOICE {
    SEQUENCE {
      PrimaryCPICH-Info          OPTIONAL,
      PrimaryCPICH-TX-Power      OPTIONAL,
      BOOLEAN,
      BOOLEAN
    }
    SEQUENCE {
      PrimaryCCPCH-Info,
      PrimaryCCPCH-TX-Power      OPTIONAL,
      TimeslotInfoList           OPTIONAL,
      BOOLEAN
    }
  }
  CellSelectReselectInfoSIB-11-12-ECN0  OPTIONAL
}

CellInfoSI-ECN0-LCR-r4 ::=
  cellIndividualOffset
  referenceTimeDifferenceToCell
  primaryCCPCH-Info
  primaryCCPCH-TX-Power
  timeslotInfoList
  cellSelectionReselectionInfo
}

SEQUENCE {
  CellIndividualOffset           DEFAULT 0,
  ReferenceTimeDifferenceToCell  OPTIONAL,
  PrimaryCCPCH-Info-LCR-r4,
  PrimaryCCPCH-TX-Power          OPTIONAL,
  TimeslotInfoList-LCR-r4       OPTIONAL,
  CellSelectReselectInfoSIB-11-12-ECN0  OPTIONAL
}

CellInfoSI-HCS-RSCP ::=
  cellIndividualOffset
  referenceTimeDifferenceToCell
  modeSpecificInfo
  fdd
    primaryCPICH-Info
    primaryCPICH-TX-Power
    readSFN-Indicator
    tx-DiversityIndicator
  },
  tdd
    primaryCCPCH-Info
    primaryCCPCH-TX-Power
    timeslotInfoList
    readSFN-Indicator
  }

SEQUENCE {
  CellIndividualOffset           DEFAULT 0,
  ReferenceTimeDifferenceToCell  OPTIONAL,
  CHOICE {
    SEQUENCE {
      PrimaryCPICH-Info          OPTIONAL,
      PrimaryCPICH-TX-Power      OPTIONAL,
      BOOLEAN,
      BOOLEAN
    }
    SEQUENCE {
      PrimaryCCPCH-Info,
      PrimaryCCPCH-TX-Power      OPTIONAL,
      TimeslotInfoList           OPTIONAL,
      BOOLEAN
    }
  }
}

```

```

    },
    cellSelectionReselectionInfo          CellSelectReselectInfoSIB-11-12-HCS-RSCP    OPTIONAL
}

CellInfoSI-HCS-RSCP-LCR-r4 ::=          SEQUENCE {
    cellIndividualOffset                  CellIndividualOffset                DEFAULT 0,
    referenceTimeDifferenceToCell         ReferenceTimeDifferenceToCell        OPTIONAL,
    primaryCCPCH-Info                     PrimaryCCPCH-Info-LCR-r4,
    primaryCCPCH-TX-Power                  PrimaryCCPCH-TX-Power                OPTIONAL,
    timeslotInfoList                      TimeslotInfoList-LCR-r4             OPTIONAL,
    cellSelectionReselectionInfo          CellSelectReselectInfoSIB-11-12-HCS-RSCP    OPTIONAL
}

CellInfoSI-HCS-ECN0 ::=                 SEQUENCE {
    cellIndividualOffset                  CellIndividualOffset                DEFAULT 0,
    referenceTimeDifferenceToCell         ReferenceTimeDifferenceToCell        OPTIONAL,
    modeSpecificInfo                      CHOICE {
        fdd                               SEQUENCE {
            primaryCPICH-Info              PrimaryCPICH-Info                  OPTIONAL,
            primaryCPICH-TX-Power           PrimaryCPICH-TX-Power              OPTIONAL,
            readSFN-Indicator               BOOLEAN,
            tx-DiversityIndicator           BOOLEAN
        },
        tdd                               SEQUENCE {
            primaryCCPCH-Info              PrimaryCCPCH-Info,
            primaryCCPCH-TX-Power           PrimaryCCPCH-TX-Power              OPTIONAL,
            timeslotInfoList                TimeslotInfoList                   OPTIONAL,
            readSFN-Indicator               BOOLEAN
        }
    },
    cellSelectionReselectionInfo          CellSelectReselectInfoSIB-11-12-HCS-ECN0    OPTIONAL
}

CellInfoSI-HCS-ECN0-LCR-r4 ::=          SEQUENCE {
    cellIndividualOffset                  CellIndividualOffset                DEFAULT 0,
    referenceTimeDifferenceToCell         ReferenceTimeDifferenceToCell        OPTIONAL,
    primaryCCPCH-Info                     PrimaryCCPCH-Info-LCR-r4,
    primaryCCPCH-TX-Power                  PrimaryCCPCH-TX-Power                OPTIONAL,
    timeslotInfoList                      TimeslotInfoList-LCR-r4             OPTIONAL,
    cellSelectionReselectionInfo          CellSelectReselectInfoSIB-11-12-HCS-ECN0    OPTIONAL
}

CellMeasuredResults ::=                  SEQUENCE {
    cellIdentity                           CellIdentity                        OPTIONAL,
    sfm-SFN-ObsTimeDifference              SFN-SFN-ObsTimeDifference           OPTIONAL,
    cellSynchronisationInfo                CellSynchronisationInfo              OPTIONAL,
    modeSpecificInfo                       CHOICE {
        fdd                               SEQUENCE {
            primaryCPICH-Info              PrimaryCPICH-Info,
            cpich-Ec-N0                     CPICH-Ec-N0                        OPTIONAL,
            cpich-RSCP                       CPICH-RSCP                          OPTIONAL,
            pathloss                          Pathloss                             OPTIONAL
        },
        tdd                               SEQUENCE {
            cellParametersID                CellParametersID,
            proposedTGSN                     TGSN                                OPTIONAL,
            primaryCCPCH-RSCP                PrimaryCCPCH-RSCP                    OPTIONAL,
            pathloss                          Pathloss                             OPTIONAL,
            timeslotISCP-List                TimeslotISCP-List                    OPTIONAL
        }
    }
}

CellMeasurementEventResults ::=          CHOICE {
    fdd                                     SEQUENCE (SIZE (1..maxCellMeas)) OF
        PrimaryCPICH-Info,
    tdd                                     SEQUENCE (SIZE (1..maxCellMeas)) OF
        PrimaryCCPCH-Info
}

CellMeasurementEventResults-LCR-r4 ::=   SEQUENCE (SIZE (1..maxCellMeas)) OF
    PrimaryCCPCH-Info-LCR-r4

CellPosition ::=                          SEQUENCE {
    relativeNorth                          INTEGER (-32767..32767),
    relativeEast                            INTEGER (-32767..32767),
    relativeAltitude                        INTEGER (-4095..4095)
}

```

```

CellReportingQuantities ::= SEQUENCE {
    sfn-SFN-OTD-Type SFN-SFN-OTD-Type,
    cellIdentity-reportingIndicator BOOLEAN,
    cellSynchronisationInfoReportingIndicator BOOLEAN,
    modeSpecificInfo CHOICE {
        fdd SEQUENCE {
            cpich-Ec-N0-reportingIndicator BOOLEAN,
            cpich-RSCP-reportingIndicator BOOLEAN,
            pathloss-reportingIndicator BOOLEAN
        },
        tdd SEQUENCE {
            timeslotISCP-reportingIndicator BOOLEAN,
            proposedTGSN-ReportingRequired BOOLEAN,
            primaryCCPCH-RSCP-reportingIndicator BOOLEAN,
            pathloss-reportingIndicator BOOLEAN
        }
    }
}

CellSelectReselectInfoSIB-11-12 ::= SEQUENCE {
    q-Offset1S-N Q-OffsetS-N DEFAULT 0,
    q-Offset2S-N Q-OffsetS-N OPTIONAL,
    maxAllowedUL-TX-Power MaxAllowedUL-TX-Power OPTIONAL,
    hcs-NeighbouringCellInformation-RSCP HCS-NeighbouringCellInformation-RSCP
    OPTIONAL,
    modeSpecificInfo CHOICE {
        fdd SEQUENCE {
            q-QualMin Q-QualMin OPTIONAL,
            q-RxlevMin Q-RxlevMin OPTIONAL
        },
        tdd SEQUENCE {
            q-RxlevMin Q-RxlevMin OPTIONAL
        },
        gsm SEQUENCE {
            q-RxlevMin Q-RxlevMin OPTIONAL
        }
    }
}

CellSelectReselectInfoSIB-11-12-RSCP ::= SEQUENCE {
    q-OffsetS-N Q-OffsetS-N DEFAULT 0,
    maxAllowedUL-TX-Power MaxAllowedUL-TX-Power OPTIONAL,
    modeSpecificInfo CHOICE {
        fdd SEQUENCE {
            q-QualMin Q-QualMin OPTIONAL,
            q-RxlevMin Q-RxlevMin OPTIONAL
        },
        tdd SEQUENCE {
            q-RxlevMin Q-RxlevMin OPTIONAL
        },
        gsm SEQUENCE {
            q-RxlevMin Q-RxlevMin OPTIONAL
        }
    }
}

CellSelectReselectInfoSIB-11-12-ECNO ::= SEQUENCE {
    q-Offset1S-N Q-OffsetS-N DEFAULT 0,
    q-Offset2S-N Q-OffsetS-N DEFAULT 0,
    maxAllowedUL-TX-Power MaxAllowedUL-TX-Power OPTIONAL,
    modeSpecificInfo CHOICE {
        fdd SEQUENCE {
            q-QualMin Q-QualMin OPTIONAL,
            q-RxlevMin Q-RxlevMin OPTIONAL
        },
        tdd SEQUENCE {
            q-RxlevMin Q-RxlevMin OPTIONAL
        },
        gsm SEQUENCE {
            q-RxlevMin Q-RxlevMin OPTIONAL
        }
    }
}

CellSelectReselectInfoSIB-11-12-HCS-RSCP ::= SEQUENCE {
    q-OffsetS-N Q-OffsetS-N DEFAULT 0,
    maxAllowedUL-TX-Power MaxAllowedUL-TX-Power OPTIONAL,
}

```

```

hcs-NeighbouringCellInformation-RSCP      HCS-NeighbouringCellInformation-RSCP
OPTIONAL,
modeSpecificInfo
  fdd
    q-QualMin
    q-RxlevMin
  },
  tdd
    q-RxlevMin
  },
  gsm
    q-RxlevMin
  }
}

CellSelectReselectInfoSIB-11-12-HCS-ECNO ::= SEQUENCE {
  q-Offset1S-N          Q-OffsetS-N          DEFAULT 0,
  q-Offset2S-N          Q-OffsetS-N          DEFAULT 0,
  maxAllowedUL-TX-Power MaxAllowedUL-TX-Power OPTIONAL,
  hcs-NeighbouringCellInformation-ECNO      HCS-NeighbouringCellInformation-ECNO
OPTIONAL,
modeSpecificInfo
  fdd
    q-QualMin
    q-RxlevMin
  },
  tdd
    q-RxlevMin
  },
  gsm
    q-RxlevMin
  }
}

CellsForInterFreqMeasList ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
  InterFreqCellID
CellsForInterRATMeasList ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
  InterRATCellID
CellsForIntraFreqMeasList ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
  IntraFreqCellID

CellSynchronisationInfo ::= SEQUENCE {
  modeSpecificInfo
    fdd
      countC-SFN-Frame-difference CountC-SFN-Frame-difference OPTIONAL,
      tm                          INTEGER(0..38399)
    },
    tdd
      countC-SFN-Frame-difference CountC-SFN-Frame-difference OPTIONAL
  }
}

CellToMeasure ::= SEQUENCE {
  sfn-sfn-Drift          INTEGER (0..30)          OPTIONAL,
  primaryCPICH-Info     PrimaryCPICH-Info,
  frequencyInfo         FrequencyInfo          OPTIONAL,
  sfn-SFN-ObservedTimeDifference SFN-SFN-ObsTimeDifference1,
  fineSFN-SFN          FineSFN-SFN,
  cellPosition         CellPosition          OPTIONAL
}

CellToMeasureInfoList ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
  CellToMeasure

CellToReport ::= SEQUENCE {
  bsicReported
}

CellToReportList ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
  CellToReport

CodePhaseSearchWindow ::= ENUMERATED {
  w1023, w1, w2, w3, w4, w6, w8,
  w12, w16, w24, w32, w48, w64,
  w96, w128, w192 }

```

```

CountC-SFN-Frame-difference ::= SEQUENCE {
    countC-SFN-High    INTEGER(0..15),      -- Actual value = IE value * 256
    off                INTEGER(0..255)
}

CPICH-Ec-N0 ::=          INTEGER (0..50)

CPICH-RSCP ::=          INTEGER (0..91)

DeltaPRC ::=           INTEGER (-127..127)

-- Actual value = IE value * 0.032
DeltaRRC ::=          INTEGER (-7..7)

DGPS-CorrectionSatInfo ::= SEQUENCE {
    satID              SatID,
    iode               IODE,
    udre               UDRE,
    prc                PRC,
    rrc                RRC,
    deltaPRC2          DeltaPRC,
    deltaRRC2          DeltaRRC,
    deltaPRC3          DeltaPRC              OPTIONAL,
    deltaRRC3          DeltaRRC              OPTIONAL
}

DGPS-CorrectionSatInfoList ::= SEQUENCE (SIZE (1..maxSat)) OF
    DGPS-CorrectionSatInfo

DiffCorrectionStatus ::= ENUMERATED {
    udre-1-0, udre-0-75, udre-0-5, udre-0-3,
    udre-0-2, udre-0-1, noData, invalidData }

-- Actual value = IE value * 0.02
DL-PhysicalChannelBER ::= INTEGER (0..255)

DL-TransportChannelBLER ::= INTEGER (0..63)

DopplerUncertainty ::= ENUMERATED {
    hz12-5, hz25, hz50, hz100, hz200 }

EllipsoidPoint ::= SEQUENCE {
    latitudeSign      ENUMERATED { north, south },
    latitude          INTEGER (0..8388607),
    longitude         INTEGER (-8388608..8388607)
}

EllipsoidPointAltitude ::= SEQUENCE {
    latitudeSign      ENUMERATED { north, south },
    latitude          INTEGER (0..8388607),
    longitude         INTEGER (-8388608..8388607),
    altitudeDirection ENUMERATED {height, depth},
    altitude          INTEGER (0..32767)
}

EllipsoidPointAltitudeEllipsoide ::= SEQUENCE {
    latitudeSign      ENUMERATED { north, south },
    latitude          INTEGER (0..8388607),
    longitude         INTEGER (-8388608..8388607),
    altitudeDirection ENUMERATED {height, depth},
    altitude          INTEGER (0..32767),
    uncertaintySemiMajor    INTEGER (0..127),
    uncertaintySemiMinor    INTEGER (0..127),
    orientationMajorAxis    INTEGER (0..89),
    uncertaintyAltitude     INTEGER (0..127),
    confidence              INTEGER (0..100)
}

EllipsoidPointUncertCircle ::= SEQUENCE {
    latitudeSign      ENUMERATED { north, south },
    latitude          INTEGER (0..8388607),
    longitude         INTEGER (-8388608..8388607),
    uncertaintyCode    INTEGER (0..127)
}

```

```

}

EllipsoidPointUncertEllipse ::= SEQUENCE {
    latitudeSign      ENUMERATED { north, south },
    latitude          INTEGER (0..8388607),
    longitude         INTEGER (-8388608..8388607),
    uncertaintySemiMajor  INTEGER (0..127),
    uncertaintySemiMinor  INTEGER (0..127),
    orientationMajorAxis  INTEGER (0..89),
    confidence         INTEGER (0..100)
}

EnvironmentCharacterisation ::= ENUMERATED {
    possibleHeavyMultipathNLOS,
    lightMultipathLOS,
    notDefined }

Event1a ::= SEQUENCE {
    triggeringCondition  TriggeringCondition2,
    reportingRange      ReportingRange,
    forbiddenAffectCellList  ForbiddenAffectCellList      OPTIONAL,
    w                   W,
    reportDeactivationThreshold  ReportDeactivationThreshold,
    reportingAmount      ReportingAmount,
    reportingInterval    ReportingInterval
}

Event1a-r4 ::= SEQUENCE {
    triggeringCondition  TriggeringCondition2,
    reportingRange      ReportingRange,
    forbiddenAffectCellList  ForbiddenAffectCellList-r4      OPTIONAL,
    w                   W,
    reportDeactivationThreshold  ReportDeactivationThreshold,
    reportingAmount      ReportingAmount,
    reportingInterval    ReportingInterval
}

Event1a-LCR-r4 ::= SEQUENCE {
    triggeringCondition  TriggeringCondition2,
    reportingRange      ReportingRange,
    forbiddenAffectCellList  ForbiddenAffectCellList-LCR-r4      OPTIONAL,
    w                   W,
    reportDeactivationThreshold  ReportDeactivationThreshold,
    reportingAmount      ReportingAmount,
    reportingInterval    ReportingInterval
}

Event1b ::= SEQUENCE {
    triggeringCondition  TriggeringCondition1,
    reportingRange      ReportingRange,
    forbiddenAffectCellList  ForbiddenAffectCellList      OPTIONAL,
    w                   W
}

Event1b-r4 ::= SEQUENCE {
    triggeringCondition  TriggeringCondition1,
    reportingRange      ReportingRange,
    forbiddenAffectCellList  ForbiddenAffectCellList-r4      OPTIONAL,
    w                   W
}

Event1b-LCR-r4 ::= SEQUENCE {
    triggeringCondition  TriggeringCondition1,
    reportingRange      ReportingRange,
    forbiddenAffectCellList  ForbiddenAffectCellList-LCR-r4      OPTIONAL,
    w                   W
}

Event1c ::= SEQUENCE {
    replacementActivationThreshold  ReplacementActivationThreshold,
    reportingAmount      ReportingAmount,
    reportingInterval    ReportingInterval
}

Event1e ::= SEQUENCE {
    triggeringCondition  TriggeringCondition2,

```



```

    thresholdUsedFrequency          ThresholdUsedFrequency
}

Event1f ::=
    triggeringCondition              TriggeringCondition1,
    thresholdUsedFrequency          ThresholdUsedFrequency
}

Event2a ::=
    usedFreqThreshold               Threshold,
    usedFreqW                       W,
    hysteresis                      HysteresisInterFreq,
    timeToTrigger                   TimeToTrigger,
    reportingCellStatus             ReportingCellStatus          OPTIONAL,
    nonUsedFreqParameterList       NonUsedFreqParameterList    OPTIONAL
}

Event2b ::=
    usedFreqThreshold               Threshold,
    usedFreqW                       W,
    hysteresis                      HysteresisInterFreq,
    timeToTrigger                   TimeToTrigger,
    reportingCellStatus             ReportingCellStatus          OPTIONAL,
    nonUsedFreqParameterList       NonUsedFreqParameterList    OPTIONAL
}

Event2c ::=
    hysteresis                      HysteresisInterFreq,
    timeToTrigger                   TimeToTrigger,
    reportingCellStatus             ReportingCellStatus          OPTIONAL,
    nonUsedFreqParameterList       NonUsedFreqParameterList    OPTIONAL
}

Event2d ::=
    usedFreqThreshold               Threshold,
    usedFreqW                       W,
    hysteresis                      HysteresisInterFreq,
    timeToTrigger                   TimeToTrigger,
    reportingCellStatus             ReportingCellStatus          OPTIONAL
}

Event2e ::=
    hysteresis                      HysteresisInterFreq,
    timeToTrigger                   TimeToTrigger,
    reportingCellStatus             ReportingCellStatus          OPTIONAL,
    nonUsedFreqParameterList       NonUsedFreqParameterList    OPTIONAL
}

Event2f ::=
    usedFreqThreshold               Threshold,
    usedFreqW                       W,
    hysteresis                      HysteresisInterFreq,
    timeToTrigger                   TimeToTrigger,
    reportingCellStatus             ReportingCellStatus          OPTIONAL
}

Event3a ::=
    thresholdOwnSystem              Threshold,
    w                                W,
    thresholdOtherSystem            Threshold,
    hysteresis                      Hysteresis,
    timeToTrigger                   TimeToTrigger,
    reportingCellStatus             ReportingCellStatus          OPTIONAL
}

Event3b ::=
    thresholdOtherSystem            Threshold,
    hysteresis                      Hysteresis,
    timeToTrigger                   TimeToTrigger,
    reportingCellStatus             ReportingCellStatus          OPTIONAL
}

Event3c ::=
    thresholdOtherSystem            Threshold,
    hysteresis                      Hysteresis,
    timeToTrigger                   TimeToTrigger,
    reportingCellStatus             ReportingCellStatus          OPTIONAL
}

```

```

}

Event3d ::=
    hysteresis
    timeToTrigger
    reportingCellStatus
}

SEQUENCE {
    Hysteresis,
    TimeToTrigger,
    ReportingCellStatus
} OPTIONAL

EventIDInterFreq ::=
    ENUMERATED {
        e2a, e2b, e2c, e2d, e2e, e2f
    }

EventIDInterRAT ::=
    ENUMERATED {
        e3a, e3b, e3c, e3d
    }

EventIDIntraFreq ::=
    ENUMERATED {
        e1a, e1b, e1c, e1d, e1e,
        e1f, e1g, e1h, e1i
    }

EventResults ::=
    intraFreqEventResults
    interFreqEventResults
    interRATEventResults
    trafficVolumeEventResults
    qualityEventResults
    ue-InternalEventResults
    ue-positioning-MeasurementEventResults
}

CHOICE {
    IntraFreqEventResults,
    InterFreqEventResults,
    InterRATEventResults,
    TrafficVolumeEventResults,
    QualityEventResults,
    UE-InternalEventResults,
    UE-Positioning-MeasurementEventResults
}

ExtraDopplerInfo ::=
    SEQUENCE {
        -- Actual value = IE value * 0.023
        doppler1stOrder
        dopplerUncertainty
    }

INTEGER (-42..21),
DopplerUncertainty

FACH-MeasurementOccasionInfo ::=
    SEQUENCE {
        fACH-meas-occasion-coeff
        inter-freq-FDD-meas-ind
        -- The following IE is for 3.84Mcps TDD. For 1.28Mcps TDD, the IE in
        -- FACH-MeasurementOccasionInfo-LCR-r4-ext is used.
        inter-freq-TDD-meas-ind
        inter-RAT-meas-ind
    }

INTEGER (1..12)
BOOLEAN,
SEQUENCE (SIZE (1..maxOtherRAT)) OF
RAT-Type
OPTIONAL

FACH-MeasurementOccasionInfo-LCR-r4-ext ::= SEQUENCE {
    inter-freq-TDD128-meas-ind
}

BOOLEAN

FilterCoefficient ::=
    ENUMERATED {
        fc0, fc1, fc2, fc3, fc4, fc5,
        fc6, fc7, fc8, fc9, fc11, fc13,
        fc15, fc17, fc19, spare1
    }

-- Actual value = IE value * 0.0625
FineSFN-SFN ::=
    INTEGER (0..15)

ForbiddenAffectCell ::=
    CHOICE {
        fdd
        tdd
    }

PrimaryCPICH-Info,
PrimaryCCPCH-Info

ForbiddenAffectCell-r4 ::=
    CHOICE {
        fdd
        tdd
    }

PrimaryCPICH-Info,
PrimaryCCPCH-Info-r4

ForbiddenAffectCell-LCR-r4 ::=
    SEQUENCE {
        tdd
    }

PrimaryCCPCH-Info-LCR-r4

ForbiddenAffectCellList ::=
    SEQUENCE (SIZE (1..maxCellMeas)) OF
    ForbiddenAffectCell

ForbiddenAffectCellList-r4 ::=
    SEQUENCE (SIZE (1..maxCellMeas)) OF
    ForbiddenAffectCell-r4

ForbiddenAffectCellList-LCR-r4 ::=
    SEQUENCE (SIZE (1..maxCellMeas)) OF
    ForbiddenAffectCell-LCR-r4

```

```

FreqQualityEstimateQuantity-FDD ::= ENUMERATED {
    cpich-Ec-N0,
    cpich-RSCP }

FreqQualityEstimateQuantity-TDD ::= ENUMERATED {
    primaryCCPCH-RSCP }

GPS-MeasurementParam ::= SEQUENCE {
    satelliteID          INTEGER (0..63),
    c-N0                 INTEGER (0..63),
    doppler              INTEGER (-32768..32768),
    wholeGPS-Chips       INTEGER (0..1023),
    fractionalGPS-Chips  INTEGER (0..1023),
    multipathIndicator    MultipathIndicator,
    pseudorangeRMS-Error INTEGER (0..63)
}

GPS-MeasurementParamList ::= SEQUENCE (SIZE (1..maxSat)) OF
    GPS-MeasurementParam

GSM-CarrierRSSI ::= BIT STRING (SIZE (6))

GSM-MeasuredResults ::= SEQUENCE {
    gsm-CarrierRSSI      GSM-CarrierRSSI          OPTIONAL,
    pathloss              Pathloss                OPTIONAL,
    bsicReported          BSICReported            OPTIONAL,
    observedTimeDifferenceToGSM
    ObservedTimeDifferenceToGSM  OPTIONAL
}

GSM-MeasuredResultsList ::= SEQUENCE (SIZE (1..maxReportedGSMCells)) OF
    GSM-MeasuredResults

GPS-TOW-1msec ::= INTEGER (0..604799999)

GPS-TOW-Assist ::= SEQUENCE {
    satID                SatID,
    tlm-Message          BIT STRING (SIZE (14)),
    tlm-Reserved         BIT STRING (SIZE (2)),
    alert                BOOLEAN,
    antiSpoof            BOOLEAN
}

GPS-TOW-AssistList ::= SEQUENCE (SIZE (1..maxSat)) OF
    GPS-TOW-Assist

GPS-TOW-rem-usec ::= INTEGER (0..999)

HCS-CellReselectInformation-RSCP ::= SEQUENCE {
    penaltyTime          PenaltyTime-RSCP
    -- TABULAR: The default value is "notUsed", temporary offset is nested inside PenaltyTime
}

HCS-CellReselectInformation-ECNO ::= SEQUENCE {
    penaltyTime          PenaltyTime-ECNO
    -- TABULAR: The default value is "notUsed", temporary offset is nested inside PenaltyTime
}

HCS-NeighbouringCellInformation-RSCP ::= SEQUENCE {
    hcs-PRIO            HCS-PRIO          DEFAULT 0,
    q-HCS               Q-HCS            DEFAULT 0,
    hcs-CellReselectInformation
    HCS-CellReselectInformation-RSCP
}

HCS-NeighbouringCellInformation-ECNO ::= SEQUENCE {
    hcs-PRIO            HCS-PRIO          DEFAULT 0,
    q-HCS               Q-HCS            DEFAULT 0,
    hcs-CellReselectInformation
    HCS-CellReselectInformation-ECNO
}

HCS-PRIO ::= INTEGER (0..7)

HCS-ServingCellInformation ::= SEQUENCE {
    hcs-PRIO            HCS-PRIO          DEFAULT 0,
    q-HCS               Q-HCS            DEFAULT 0,
    t-CR-Max           T-CRMax           OPTIONAL
}

```

```

-- Actual value = IE value * 0.5
Hysteresis ::= INTEGER (0..15)

-- Actual value = IE value * 0.5
HysteresisInterFreq ::= INTEGER (0..29)

InterFreqCell ::= SEQUENCE {
    frequencyInfo          FrequencyInfo,
    nonFreqRelatedEventResults CellMeasurementEventResults
}

InterFreqCell-LCR-r4 ::= SEQUENCE {
    frequencyInfo          FrequencyInfo,
    nonFreqRelatedEventResults CellMeasurementEventResults-LCR-r4
}

InterFreqCellID ::= INTEGER (0..maxCellMeas-1)

InterFreqCellInfoList ::= SEQUENCE {
    removedInterFreqCellList    RemovedInterFreqCellList    OPTIONAL,
    newInterFreqCellList        NewInterFreqCellList        OPTIONAL,
    cellsForInterFreqMeasList    CellsForInterFreqMeasList    OPTIONAL
}

InterFreqCellInfoList-r4 ::= SEQUENCE {
    removedInterFreqCellList    RemovedInterFreqCellList    OPTIONAL,
    newInterFreqCellList        NewInterFreqCellList-r4        OPTIONAL
}

InterFreqCellInfoSI-List-RSCP ::= SEQUENCE {
    removedInterFreqCellList    RemovedInterFreqCellList    OPTIONAL,
    newInterFreqCellList        NewInterFreqCellSI-List-RSCP    OPTIONAL
}

InterFreqCellInfoSI-List-ECN0 ::= SEQUENCE {
    removedInterFreqCellList    RemovedInterFreqCellList    OPTIONAL,
    newInterFreqCellList        NewInterFreqCellSI-List-ECN0    OPTIONAL
}

InterFreqCellInfoSI-List-HCS-RSCP ::= SEQUENCE {
    removedInterFreqCellList    RemovedInterFreqCellList    OPTIONAL,
    newInterFreqCellList        NewInterFreqCellSI-List-HCS-RSCP    OPTIONAL
}

InterFreqCellInfoSI-List-HCS-ECN0 ::= SEQUENCE {
    removedInterFreqCellList    RemovedInterFreqCellList    OPTIONAL,
    newInterFreqCellList        NewInterFreqCellSI-List-HCS-ECN0    OPTIONAL
}

InterFreqCellInfoSI-List-RSCP-LCR ::= SEQUENCE {
    removedInterFreqCellList    RemovedInterFreqCellList    OPTIONAL,
    newInterFreqCellList        NewInterFreqCellSI-List-RSCP-LCR-r4    OPTIONAL
}

InterFreqCellInfoSI-List-ECN0-LCR ::= SEQUENCE {
    removedInterFreqCellList    RemovedInterFreqCellList    OPTIONAL,
    newInterFreqCellList        NewInterFreqCellSI-List-ECN0-LCR-r4    OPTIONAL
}

InterFreqCellInfoSI-List-HCS-RSCP-LCR ::= SEQUENCE {
    removedInterFreqCellList    RemovedInterFreqCellList    OPTIONAL,
    newInterFreqCellList        NewInterFreqCellSI-List-HCS-RSCP-LCR-r4    OPTIONAL
}

InterFreqCellInfoSI-List-HCS-ECN0-LCR ::= SEQUENCE {
    removedInterFreqCellList    RemovedInterFreqCellList    OPTIONAL,
    newInterFreqCellList        NewInterFreqCellSI-List-HCS-ECN0-LCR-r4    OPTIONAL
}

InterFreqCellList ::= SEQUENCE (SIZE (1..maxFreq)) OF
    InterFreqCell

InterFreqCellList-LCR-r4-ext ::= SEQUENCE (SIZE (1..maxFreq)) OF
    InterFreqCell-LCR-r4

InterFreqCellMeasuredResultsList ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    CellMeasuredResults

InterFreqEvent ::= CHOICE {

```

```

event2a          Event2a,
event2b          Event2b,
event2c          Event2c,
event2d          Event2d,
event2e          Event2e,
event2f          Event2f
}

InterFreqEventList ::=          SEQUENCE (SIZE (1..maxMeasEvent)) OF
                                InterFreqEvent

InterFreqEventResults ::=      SEQUENCE {
    eventID          EventIDInterFreq,
    interFreqCellList InterFreqCellList          OPTIONAL
}

InterFreqEventResults-LCR-r4-ext ::= SEQUENCE {
    eventID          EventIDInterFreq,
    interFreqCellList InterFreqCellList-LCR-r4-ext  OPTIONAL
}

InterFreqMeasQuantity ::=      SEQUENCE {
    reportingCriteria CHOICE {
        intraFreqReportingCriteria SEQUENCE {
            intraFreqMeasQuantity IntraFreqMeasQuantity
        },
        interFreqReportingCriteria SEQUENCE {
            filterCoefficient FilterCoefficient          DEFAULT fc0,
            modeSpecificInfo CHOICE {
                fdd SEQUENCE {
                    freqQualityEstimateQuantity-FDD FreqQualityEstimateQuantity-FDD
                },
                tdd SEQUENCE {
                    freqQualityEstimateQuantity-TDD FreqQualityEstimateQuantity-TDD
                }
            }
        }
    }
}

InterFreqMeasuredResults ::=    SEQUENCE {
    frequencyInfo      FrequencyInfo          OPTIONAL,
    ultra-CarrierRSSI  UTRA-CarrierRSSI        OPTIONAL,
    interFreqCellMeasuredResultsList InterFreqCellMeasuredResultsList  OPTIONAL
}

InterFreqMeasuredResultsList ::= SEQUENCE (SIZE (1..maxFreq)) OF
                                InterFreqMeasuredResults

InterFreqMeasurementSysInfo-RSCP ::= SEQUENCE {
    interFreqCellInfoSI-List InterFreqCellInfoSI-List-RSCP  OPTIONAL
}

InterFreqMeasurementSysInfo-ECN0 ::= SEQUENCE {
    interFreqCellInfoSI-List InterFreqCellInfoSI-List-ECN0  OPTIONAL
}

InterFreqMeasurementSysInfo-HCS-RSCP ::= SEQUENCE {
    interFreqCellInfoSI-List InterFreqCellInfoSI-List-HCS-RSCP  OPTIONAL
}

InterFreqMeasurementSysInfo-HCS-ECN0 ::= SEQUENCE {
    interFreqCellInfoSI-List InterFreqCellInfoSI-List-HCS-ECN0  OPTIONAL
}

InterFreqMeasurementSysInfo-RSCP-LCR-r4 ::= SEQUENCE {
    interFreqCellInfoSI-List InterFreqCellInfoSI-List-RSCP-LCR  OPTIONAL
}

InterFreqMeasurementSysInfo-ECN0-LCR-r4 ::= SEQUENCE {
    interFreqCellInfoSI-List InterFreqCellInfoSI-List-ECN0-LCR  OPTIONAL
}

InterFreqMeasurementSysInfo-HCS-RSCP-LCR-r4 ::= SEQUENCE {
    interFreqCellInfoSI-List InterFreqCellInfoSI-List-HCS-RSCP-LCR  OPTIONAL
}

```

```

InterFreqMeasurementSysInfo-HCS-ECNO-LCR-r4 ::= SEQUENCE {
    interFreqCellInfoSI-List          InterFreqCellInfoSI-List-HCS-ECNO-LCR  OPTIONAL
}

InterFreqReportCriteria ::= CHOICE {
    intraFreqReportingCriteria      IntraFreqReportingCriteria,
    interFreqReportingCriteria      InterFreqReportingCriteria,
    periodicalReportingCriteria     PeriodicalWithReportingCellStatus,
    noReporting                     ReportingCellStatusOpt
}

InterFreqReportCriteria-r4 ::= CHOICE {
    intraFreqReportingCriteria      IntraFreqReportingCriteria-r4,
    interFreqReportingCriteria      InterFreqReportingCriteria,
    periodicalReportingCriteria     PeriodicalWithReportingCellStatus,
    noReporting                     ReportingCellStatusOpt
}

InterFreqReportingCriteria ::= SEQUENCE {
    interFreqEventList              InterFreqEventList          OPTIONAL
}

InterFreqReportingQuantity ::= SEQUENCE {
    ultra-Carrier-RSSI              BOOLEAN,
    frequencyQualityEstimate        BOOLEAN,
    nonFreqRelatedQuantities        CellReportingQuantities
}

InterFrequencyMeasurement ::= SEQUENCE {
    interFreqCellInfoList           InterFreqCellInfoList,
    interFreqMeasQuantity           InterFreqMeasQuantity          OPTIONAL,
    interFreqReportingQuantity      InterFreqReportingQuantity     OPTIONAL,
    measurementValidity             MeasurementValidity           OPTIONAL,
    interFreqSetUpDate              UE-AutonomousUpdateMode      OPTIONAL,
    reportCriteria                  InterFreqReportCriteria
}

InterFrequencyMeasurement-r4 ::= SEQUENCE {
    interFreqCellInfoList-r4        InterFreqCellInfoList-r4,
    interFreqMeasQuantity           InterFreqMeasQuantity          OPTIONAL,
    interFreqReportingQuantity      InterFreqReportingQuantity     OPTIONAL,
    measurementValidity             MeasurementValidity           OPTIONAL,
    interFreqSetUpDate              UE-AutonomousUpdateMode      OPTIONAL,
    reportCriteria                  InterFreqReportCriteria-r4
}

InterRAT-TargetCellDescription ::= SEQUENCE {
    technologySpecificInfo          CHOICE {
        gsm                         SEQUENCE {
            bsic                     BSIC,
            frequency-band           Frequency-Band,
            bcch-ARFCN              BCCH-ARFCN,
            ncMode                   NC-Mode          OPTIONAL
        },
        is-2000                     NULL,
        spare                        NULL
    }
}

InterRATCellID ::= INTEGER (0..maxCellMeas-1)

InterRATCellInfoList ::= SEQUENCE {
    removedInterRATCellList        RemovedInterRATCellList,
    newInterRATCellList            NewInterRATCellList,
    cellsForInterRATMeasList       CellsForInterRATMeasList     OPTIONAL
}

InterRATCellInfoList-B ::= SEQUENCE {
    removedInterRATCellList        RemovedInterRATCellList,
    newInterRATCellList            NewInterRATCellList-B
}

InterRATCellIndividualOffset ::= INTEGER (-50..50)

InterRATEvent ::= CHOICE {
    event3a                         Event3a,
    event3b                         Event3b,
}

```

```

    event3c          Event3c,
    event3d          Event3d
}

InterRATEEventList ::=          SEQUENCE (SIZE (1..maxMeasEvent)) OF
                                InterRATEEvent

InterRATEEventResults ::=      SEQUENCE {
    eventID          EventIDInterRAT,
    cellToReportList CellToReportList
}

InterRATInfo ::=              ENUMERATED {
    gsm }

InterRATMeasQuantity ::=      SEQUENCE {
    measQuantityUTRAN-QualityEstimate IntraFreqMeasQuantity          OPTIONAL,
    ratSpecificInfo CHOICE {
        gsm SEQUENCE {
            measurementQuantity MeasurementQuantityGSM,
            filterCoefficient FilterCoefficient          DEFAULT fc0,
            bsic-VerificationRequired BSIC-VerificationRequired
        },
        is-2000 SEQUENCE {
            tadd-EcIo          INTEGER (0..63),
            tcomp-EcIo        INTEGER (0..15),
            softSlope          INTEGER (0..63)          OPTIONAL,
            addIntercept      INTEGER (0..63)          OPTIONAL
        }
    }
}

InterRATMeasuredResults ::=    CHOICE {
    gsm              GSM-MeasuredResultsList,
    spare           NULL
}

InterRATMeasuredResultsList ::= SEQUENCE (SIZE (1..maxOtherRAT)) OF
                                InterRATMeasuredResults

InterRATMeasurement ::=      SEQUENCE {
    interRATCellInfoList InterRATCellInfoList          OPTIONAL,
    interRATMeasQuantity InterRATMeasQuantity          OPTIONAL,
    interRATReportingQuantity InterRATReportingQuantity OPTIONAL,
    reportCriteria      InterRATReportCriteria
}

InterRATMeasurementSysInfo ::= SEQUENCE {
    interRATCellInfoList InterRATCellInfoList          OPTIONAL
}

InterRATMeasurementSysInfo-B ::= SEQUENCE {
    interRATCellInfoList InterRATCellInfoList-B        OPTIONAL
}

InterRATReportCriteria ::=    CHOICE {
    interRATReportingCriteria InterRATReportingCriteria,
    periodicalReportingCriteria PeriodicalWithReportingCellStatus,
    noReporting              ReportingCellStatusOpt
}

InterRATReportingCriteria ::= SEQUENCE {
    interRATEEventList InterRATEEventList          OPTIONAL
}

InterRATReportingQuantity ::= SEQUENCE {
    utran-EstimatedQuality BOOLEAN,
    ratSpecificInfo CHOICE {
        gsm SEQUENCE {
            pathloss          BOOLEAN,
            observedTimeDifferenceGSM BOOLEAN,
            gsm-Carrier-RSSI  BOOLEAN
        }
    }
}

IntraFreqCellID ::=          INTEGER (0..maxCellMeas-1)

```

```

IntraFreqCellInfoList ::=          SEQUENCE {
    removedIntraFreqCellList        RemovedIntraFreqCellList        OPTIONAL,
    newIntraFreqCellList             NewIntraFreqCellList           OPTIONAL,
    cellsForIntraFreqMeasList        CellsForIntraFreqMeasList      OPTIONAL
}

IntraFreqCellInfoList-r4 ::=       SEQUENCE {
    removedIntraFreqCellList        RemovedIntraFreqCellList        OPTIONAL,
    newIntraFreqCellList-r4         NewIntraFreqCellList-r4        OPTIONAL
}

IntraFreqCellInfoSI-List-RSCP ::=  SEQUENCE {
    removedIntraFreqCellList        RemovedIntraFreqCellList        OPTIONAL,
    newIntraFreqCellList            NewIntraFreqCellSI-List-RSCP
}

IntraFreqCellInfoSI-List-ECNO ::=  SEQUENCE {
    removedIntraFreqCellList        RemovedIntraFreqCellList        OPTIONAL,
    newIntraFreqCellList            NewIntraFreqCellSI-List-ECNO
}

IntraFreqCellInfoSI-List-HCS-RSCP ::= SEQUENCE {
    removedIntraFreqCellList        RemovedIntraFreqCellList        OPTIONAL,
    newIntraFreqCellList            NewIntraFreqCellSI-List-HCS-RSCP
}

IntraFreqCellInfoSI-List-HCS-ECNO ::= SEQUENCE {
    removedIntraFreqCellList        RemovedIntraFreqCellList        OPTIONAL,
    newIntraFreqCellList            NewIntraFreqCellSI-List-HCS-ECNO
}

IntraFreqCellInfoSI-List-RSCP-LCR-r4 ::= SEQUENCE {
    removedIntraFreqCellList        RemovedIntraFreqCellList        OPTIONAL,
    newIntraFreqCellList            NewIntraFreqCellSI-List-RSCP-LCR-r4
}

IntraFreqCellInfoSI-List-ECNO-LCR-r4 ::= SEQUENCE {
    removedIntraFreqCellList        RemovedIntraFreqCellList        OPTIONAL,
    newIntraFreqCellList            NewIntraFreqCellSI-List-ECNO-LCR-r4
}

IntraFreqCellInfoSI-List-HCS-RSCP-LCR-r4 ::= SEQUENCE {
    removedIntraFreqCellList        RemovedIntraFreqCellList        OPTIONAL,
    newIntraFreqCellList            NewIntraFreqCellSI-List-HCS-RSCP-LCR-r4
}

IntraFreqCellInfoSI-List-HCS-ECNO-LCR-r4 ::= SEQUENCE {
    removedIntraFreqCellList        RemovedIntraFreqCellList        OPTIONAL,
    newIntraFreqCellList            NewIntraFreqCellSI-List-HCS-ECNO-LCR-r4
}

IntraFreqEvent ::=                CHOICE {
    e1a                               Event1a,
    e1b                               Event1b,
    e1c                               Event1c,
    e1d                               NULL,
    e1e                               Event1e,
    e1f                               Event1f,
    e1g                               NULL,
    e1h                               ThresholdUsedFrequency,
    e1i                               ThresholdUsedFrequency
}

IntraFreqEvent-r4 ::=             CHOICE {
    e1a                               Event1a-r4,
    e1b                               Event1b-r4,
    e1c                               Event1c,
    e1d                               NULL,
    e1e                               Event1e,
    e1f                               Event1f,
    e1g                               NULL,
    e1h                               ThresholdUsedFrequency,
    e1i                               ThresholdUsedFrequency
}

IntraFreqEvent-LCR-r4 ::=         CHOICE {
    e1a                               Event1a-LCR-r4,
    e1b                               Event1b-LCR-r4,

```



```

    e1c          Event1c,
    e1d          NULL,
    e1e          Event1e,
    e1f          Event1f,
    e1g          NULL,
    e1h          ThresholdUsedFrequency,
    e1i          ThresholdUsedFrequency
}

IntraFreqEventCriteria ::= SEQUENCE {
    event          IntraFreqEvent,
    hysteresis     Hysteresis,
    timeToTrigger TimeToTrigger,
    reportingCellStatus ReportingCellStatus           OPTIONAL
}

IntraFreqEventCriteria-r4 ::= SEQUENCE {
    event          IntraFreqEvent-r4,
    hysteresis     Hysteresis,
    timeToTrigger TimeToTrigger,
    reportingCellStatus ReportingCellStatus           OPTIONAL
}

IntraFreqEventCriteria-LCR-r4 ::= SEQUENCE {
    event          IntraFreqEvent-LCR-r4,
    hysteresis     Hysteresis,
    timeToTrigger TimeToTrigger,
    reportingCellStatus ReportingCellStatus           OPTIONAL
}

IntraFreqEventCriteriaList ::= SEQUENCE (SIZE (1..maxMeasEvent)) OF
    IntraFreqEventCriteria

IntraFreqEventCriteriaList-r4 ::= SEQUENCE (SIZE (1..maxMeasEvent)) OF
    IntraFreqEventCriteria-r4

IntraFreqEventCriteriaList-LCR-r4 ::= SEQUENCE (SIZE (1..maxMeasEvent)) OF
    IntraFreqEventCriteria-LCR-r4

IntraFreqEventResults ::= SEQUENCE {
    eventID        EventIDIntraFreq,
    cellMeasurementEventResults CellMeasurementEventResults
}

IntraFreqMeasQuantity ::= SEQUENCE {
    filterCoefficient FilterCoefficient           DEFAULT fc0,
    modeSpecificInfo   CHOICE {
        fdd            SEQUENCE {
            intraFreqMeasQuantity-FDD IntraFreqMeasQuantity-FDD
        },
        tdd            SEQUENCE {
            intraFreqMeasQuantity-TDDList IntraFreqMeasQuantity-TDDList
        }
    }
}

IntraFreqMeasQuantity-FDD ::= ENUMERATED {
    cpich-EC-N0,
    cpich-RSCP,
    pathloss,
    ultra-CarrierRSSI }

IntraFreqMeasQuantity-TDD ::= ENUMERATED {
    primaryCCPCH-RSCP,
    pathloss,
    timeslotISCP,
    ultra-CarrierRSSI }

IntraFreqMeasQuantity-TDDList ::= SEQUENCE (SIZE (1..4)) OF
    IntraFreqMeasQuantity-TDD

IntraFreqMeasuredResultsList ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    CellMeasuredResults

IntraFreqMeasurementSysInfo-RSCP ::= SEQUENCE {
    intraFreqMeasurementID MeasurementIdentity           DEFAULT 1,
    intraFreqCellInfoSI-List IntraFreqCellInfoSI-List-RSCP       OPTIONAL,
    intraFreqMeasQuantity   IntraFreqMeasQuantity                 OPTIONAL,
}

```

```

    intraFreqReportingQuantityForRACH IntraFreqReportingQuantityForRACH OPTIONAL,
    maxReportedCellsOnRACH           MaxReportedCellsOnRACH           OPTIONAL,
    reportingInfoForCellDCH           ReportingInfoForCellDCH           OPTIONAL
}

IntraFreqMeasurementSysInfo-ECN0 ::= SEQUENCE {
    intraFreqMeasurementID           MeasurementIdentity           DEFAULT 1,
    intraFreqCellInfoSI-List         IntraFreqCellInfoSI-List-ECN0 OPTIONAL,
    intraFreqMeasQuantity            IntraFreqMeasQuantity       OPTIONAL,
    intraFreqReportingQuantityForRACH IntraFreqReportingQuantityForRACH OPTIONAL,
    maxReportedCellsOnRACH           MaxReportedCellsOnRACH       OPTIONAL,
    reportingInfoForCellDCH           ReportingInfoForCellDCH       OPTIONAL
}

IntraFreqMeasurementSysInfo-HCS-RSCP ::= SEQUENCE {
    intraFreqMeasurementID           MeasurementIdentity           DEFAULT 1,
    intraFreqCellInfoSI-List         IntraFreqCellInfoSI-List-HCS-RSCP OPTIONAL,
    intraFreqMeasQuantity            IntraFreqMeasQuantity       OPTIONAL,
    intraFreqReportingQuantityForRACH IntraFreqReportingQuantityForRACH OPTIONAL,
    maxReportedCellsOnRACH           MaxReportedCellsOnRACH       OPTIONAL,
    reportingInfoForCellDCH           ReportingInfoForCellDCH       OPTIONAL
}

IntraFreqMeasurementSysInfo-HCS-ECN0 ::= SEQUENCE {
    intraFreqMeasurementID           MeasurementIdentity           DEFAULT 1,
    intraFreqCellInfoSI-List         IntraFreqCellInfoSI-List-HCS-ECN0 OPTIONAL,
    intraFreqMeasQuantity            IntraFreqMeasQuantity       OPTIONAL,
    intraFreqReportingQuantityForRACH IntraFreqReportingQuantityForRACH OPTIONAL,
    maxReportedCellsOnRACH           MaxReportedCellsOnRACH       OPTIONAL,
    reportingInfoForCellDCH           ReportingInfoForCellDCH       OPTIONAL
}

IntraFreqMeasurementSysInfo-RSCP-LCR-r4 ::= SEQUENCE {
    intraFreqMeasurementID           MeasurementIdentity           DEFAULT 1,
    intraFreqCellInfoSI-List         IntraFreqCellInfoSI-List-RSCP-LCR-r4 OPTIONAL,
    intraFreqMeasQuantity            IntraFreqMeasQuantity       OPTIONAL,
    intraFreqReportingQuantityForRACH IntraFreqReportingQuantityForRACH OPTIONAL,
    maxReportedCellsOnRACH           MaxReportedCellsOnRACH       OPTIONAL,
    reportingInfoForCellDCH           ReportingInfoForCellDCH-LCR-r4 OPTIONAL
}

IntraFreqMeasurementSysInfo-ECN0-LCR-r4 ::= SEQUENCE {
    intraFreqMeasurementID           MeasurementIdentity           DEFAULT 1,
    intraFreqCellInfoSI-List         IntraFreqCellInfoSI-List-ECN0-LCR-r4 OPTIONAL,
    intraFreqMeasQuantity            IntraFreqMeasQuantity       OPTIONAL,
    intraFreqReportingQuantityForRACH IntraFreqReportingQuantityForRACH OPTIONAL,
    maxReportedCellsOnRACH           MaxReportedCellsOnRACH       OPTIONAL,
    reportingInfoForCellDCH           ReportingInfoForCellDCH-LCR-r4 OPTIONAL
}

IntraFreqMeasurementSysInfo-HCS-RSCP-LCR-r4 ::= SEQUENCE {
    intraFreqMeasurementID           MeasurementIdentity           DEFAULT 1,
    intraFreqCellInfoSI-List         IntraFreqCellInfoSI-List-HCS-RSCP-LCR-r4 OPTIONAL,
    intraFreqMeasQuantity            IntraFreqMeasQuantity       OPTIONAL,
    intraFreqReportingQuantityForRACH IntraFreqReportingQuantityForRACH OPTIONAL,
    maxReportedCellsOnRACH           MaxReportedCellsOnRACH       OPTIONAL,
    reportingInfoForCellDCH           ReportingInfoForCellDCH-LCR-r4 OPTIONAL
}

IntraFreqMeasurementSysInfo-HCS-ECN0-LCR-r4 ::= SEQUENCE {
    intraFreqMeasurementID           MeasurementIdentity           DEFAULT 1,
    intraFreqCellInfoSI-List         IntraFreqCellInfoSI-List-HCS-ECN0-LCR-r4 OPTIONAL,
    intraFreqMeasQuantity            IntraFreqMeasQuantity       OPTIONAL,
    intraFreqReportingQuantityForRACH IntraFreqReportingQuantityForRACH OPTIONAL,
    maxReportedCellsOnRACH           MaxReportedCellsOnRACH       OPTIONAL,
    reportingInfoForCellDCH           ReportingInfoForCellDCH-LCR-r4 OPTIONAL
}

IntraFreqReportCriteria ::= CHOICE {
    intraFreqReportingCriteria        IntraFreqReportingCriteria,
    periodicalReportingCriteria        PeriodicalWithReportingCellStatus,
    noReporting                        ReportingCellStatusOpt
}

IntraFreqReportCriteria-r4 ::= CHOICE {
    intraFreqReportingCriteria-r4     IntraFreqReportingCriteria-r4,
    periodicalReportingCriteria        PeriodicalWithReportingCellStatus,
    noReporting                        ReportingCellStatusOpt
}

```

```

}

IntraFreqReportingCriteria ::= SEQUENCE {
    eventCriteriaList          IntraFreqEventCriteriaList          OPTIONAL
}

IntraFreqReportingCriteria-r4 ::= SEQUENCE {
    eventCriteriaList          IntraFreqEventCriteriaList-r4      OPTIONAL
}

IntraFreqReportingCriteria-LCR-r4 ::= SEQUENCE {
    eventCriteriaList          IntraFreqEventCriteriaList-LCR-r4  OPTIONAL
}

IntraFreqReportingQuantity ::= SEQUENCE {
    activeSetReportingQuantities CellReportingQuantities,
    monitoredSetReportingQuantities CellReportingQuantities,
    detectedSetReportingQuantities CellReportingQuantities          OPTIONAL
}

IntraFreqReportingQuantityForRACH ::= SEQUENCE {
    sfn-SFN-OTD-Type          SFN-SFN-OTD-Type,
    modeSpecificInfo          CHOICE {
        fdd                    SEQUENCE {
            intraFreqRepQuantityRACH-FDD      IntraFreqRepQuantityRACH-FDD
        },
        tdd                    SEQUENCE {
            intraFreqRepQuantityRACH-TDDList   IntraFreqRepQuantityRACH-TDDList
        }
    }
}

IntraFreqRepQuantityRACH-FDD ::= ENUMERATED {
    cpich-EcN0, cpich-RSCP,
    pathloss, noReport }

IntraFreqRepQuantityRACH-TDD ::= ENUMERATED {
    timeslotISCP,
    primaryCCPCH-RSCP,
    noReport }

IntraFreqRepQuantityRACH-TDDList ::= SEQUENCE (SIZE (1..2)) OF
    IntraFreqRepQuantityRACH-TDD

IntraFrequencyMeasurement ::= SEQUENCE {
    intraFreqCellInfoList      IntraFreqCellInfoList          OPTIONAL,
    intraFreqMeasQuantity      IntraFreqMeasQuantity          OPTIONAL,
    intraFreqReportingQuantity IntraFreqReportingQuantity          OPTIONAL,
    measurementValidity        MeasurementValidity          OPTIONAL,
    reportCriteria              IntraFreqReportCriteria          OPTIONAL
}

IntraFrequencyMeasurement-r4 ::= SEQUENCE {
    intraFreqCellInfoList-r4   IntraFreqCellInfoList-r4      OPTIONAL,
    intraFreqMeasQuantity-r4   IntraFreqMeasQuantity-r4      OPTIONAL,
    intraFreqReportingQuantity-r4 IntraFreqReportingQuantity-r4 OPTIONAL,
    measurementValidity-r4     MeasurementValidity-r4          OPTIONAL,
    reportCriteria-r4          IntraFreqReportCriteria-r4          OPTIONAL
}

IODE ::= INTEGER (0..255)

IP-Length ::= ENUMERATED {
    ip15, ip110 }

IP-PCCPCH-r4 ::= BOOLEAN

IP-Spacing ::= ENUMERATED {
    e5, e7, e10, e15, e20,
    e30, e40, e50 }

IP-Spacing-TDD ::= ENUMERATED {
    e30, e40, e50, e70, e100}

IS-2000SpecificMeasInfo ::= ENUMERATED {
    frequency, timeslot, colourcode,
    outputpower, pn-Offset }

```

```

MaxNumberOfReportingCellsType1 ::= ENUMERATED {
    e1, e2, e3, e4, e5, e6}

MaxNumberOfReportingCellsType2 ::= ENUMERATED {
    e1, e2, e3, e4, e5, e6, e7, e8, e9, e10, e11, e12}

MaxNumberOfReportingCellsType3 ::= ENUMERATED {
    viactCellsPlus1,
    viactCellsPlus2,
    viactCellsPlus3,
    viactCellsPlus4,
    viactCellsPlus5,
    viactCellsPlus6 }

MaxReportedCellsOnRACH ::= ENUMERATED {
    noReport,
    currentCell,
    currentAnd-1-BestNeighbour,
    currentAnd-2-BestNeighbour,
    currentAnd-3-BestNeighbour,
    currentAnd-4-BestNeighbour,
    currentAnd-5-BestNeighbour,
    currentAnd-6-BestNeighbour }

MeasuredResults ::= CHOICE {
    intraFreqMeasuredResultsList      IntraFreqMeasuredResultsList,
    interFreqMeasuredResultsList      InterFreqMeasuredResultsList,
    interRATMeasuredResultsList      InterRATMeasuredResultsList,
    trafficVolumeMeasuredResultsList  TrafficVolumeMeasuredResultsList,
    qualityMeasuredResults            QualityMeasuredResults,
    ue-InternalMeasuredResults        UE-InternalMeasuredResults,
    ue-positioning-MeasuredResults    UE-Positioning-MeasuredResults
}

MeasuredResults-LCR-r4 ::= CHOICE {
    intraFreqMeasuredResultsList      IntraFreqMeasuredResultsList,
    interFreqMeasuredResultsList      InterFreqMeasuredResultsList,
    interRATMeasuredResultsList      InterRATMeasuredResultsList,
    trafficVolumeMeasuredResultsList  TrafficVolumeMeasuredResultsList,
    qualityMeasuredResults            QualityMeasuredResults,
    ue-InternalMeasuredResults        UE-InternalMeasuredResults-LCR-r4,
    ue-positioning-MeasuredResults    UE-Positioning-MeasuredResults
}

MeasuredResultsList ::= SEQUENCE (SIZE (1..maxAdditionalMeas)) OF
    MeasuredResults

MeasuredResultsList-LCR-r4-ext ::= SEQUENCE (SIZE (1..maxAdditionalMeas)) OF
    MeasuredResults-LCR-r4

MeasuredResultsOnRACH ::= SEQUENCE {
    currentCell          SEQUENCE {
        modeSpecificInfo CHOICE {
            fdd           SEQUENCE {
                measurementQuantity CHOICE {
                    cpich-Ec-N0    CPICH-Ec-N0,
                    cpich-RSCP     CPICH-RSCP,
                    pathloss       Pathloss
                }
            },
            tdd           SEQUENCE {
                timeslotISCP      TimeslotISCP-List      OPTIONAL,
                primaryCCPCH-RSCP PrimaryCCPCH-RSCP    OPTIONAL
            }
        },
        monitoredCells          MonitoredCellRACH-List      OPTIONAL
    }

MeasurementCommand ::= CHOICE {
    setup      MeasurementType,
    modify     SEQUENCE {
        measurementType      MeasurementType      OPTIONAL
    },
    release    NULL
}

MeasurementCommand-r4 ::= CHOICE {

```

```

    setup          MeasurementType-r4,
    modify         SEQUENCE {
        measurementType MeasurementType-r4          OPTIONAL
    },
    release        NULL
}

MeasurementControlSysInfo ::= SEQUENCE {
    use-of-HCS      CHOICE {
        hcs-not-used SEQUENCE {
            cellSelectQualityMeasure CHOICE {
                cpich-RSCP SEQUENCE {
                    intraFreqMeasurementSysInfo IntraFreqMeasurementSysInfo-RSCP
                }
            },
            interFreqMeasurementSysInfo InterFreqMeasurementSysInfo-RSCP OPTIONAL
        },
        cpich-Ec-N0 SEQUENCE {
            intraFreqMeasurementSysInfo IntraFreqMeasurementSysInfo-ECN0
        }
        OPTIONAL,
            interFreqMeasurementSysInfo InterFreqMeasurementSysInfo-ECN0 OPTIONAL
        }
    },
    interRATMeasurementSysInfo InterRATMeasurementSysInfo-B OPTIONAL
},
    hcs-used        SEQUENCE {
        cellSelectQualityMeasure CHOICE {
            cpich-RSCP SEQUENCE {
                intraFreqMeasurementSysInfo IntraFreqMeasurementSysInfo-HCS-RSCP
            }
        }
        OPTIONAL,
            interFreqMeasurementSysInfo InterFreqMeasurementSysInfo-HCS-RSCP
        }
        OPTIONAL
    },
        cpich-Ec-N0 SEQUENCE {
            intraFreqMeasurementSysInfo IntraFreqMeasurementSysInfo-HCS-ECN0
        }
        OPTIONAL,
            interFreqMeasurementSysInfo InterFreqMeasurementSysInfo-HCS-ECN0
        }
        OPTIONAL
    },
    interRATMeasurementSysInfo InterRATMeasurementSysInfo OPTIONAL
},
}

trafficVolumeMeasSysInfo TrafficVolumeMeasSysInfo OPTIONAL,
ue-InternalMeasurementSysInfo UE-InternalMeasurementSysInfo OPTIONAL
}

MeasurementControlSysInfo-LCR-r4-ext ::= SEQUENCE {
-- The following CHOICE shall have the same value as the use-of-HCS in MeasurementControlSysInfo
    use-of-HCS      CHOICE {
        hcs-not-used SEQUENCE {
-- The following CHOICE shall have the same value as the cellSelectQualityMeasure in
-- MeasurementControlSysInfo
            cellSelectQualityMeasure CHOICE {
                cpich-RSCP SEQUENCE {
                    intraFreqMeasurementSysInfo IntraFreqMeasurementSysInfo-RSCP-LCR-r4 OPTIONAL,
                    interFreqMeasurementSysInfo InterFreqMeasurementSysInfo-RSCP-LCR-r4 OPTIONAL
                },
                cpich-Ec-N0 SEQUENCE {
                    intraFreqMeasurementSysInfo IntraFreqMeasurementSysInfo-ECN0-LCR-r4 OPTIONAL,
                    interFreqMeasurementSysInfo InterFreqMeasurementSysInfo-ECN0-LCR-r4 OPTIONAL
                }
            }
        }
    },
    hcs-used        SEQUENCE {
-- The following CHOICE shall have the same value as the cellSelectQualityMeasure in
-- MeasurementControlSysInfo
        cellSelectQualityMeasure CHOICE {
            cpich-RSCP SEQUENCE {
                intraFreqMeasurementSysInfo IntraFreqMeasurementSysInfo-HCS-RSCP-LCR-r4
            }
        }
        OPTIONAL,
            interFreqMeasurementSysInfo InterFreqMeasurementSysInfo-HCS-RSCP-LCR-r4 OPTIONAL
        },
        cpich-Ec-N0 SEQUENCE {
            intraFreqMeasurementSysInfo IntraFreqMeasurementSysInfo-HCS-ECN0-LCR-r4
        }
        OPTIONAL,
            interFreqMeasurementSysInfo InterFreqMeasurementSysInfo-HCS-ECN0-LCR-r4 OPTIONAL
        }
    }
}

```

```

    }
  }
}

MeasurementIdentity ::=      INTEGER (1..16)

MeasurementQuantityGSM ::=   ENUMERATED {
                                gsm-CarrierRSSI,
                                pathloss }

MeasurementReportingMode ::= SEQUENCE {
    measurementReportTransferMode TransferMode,
    periodicalOrEventTrigger      PeriodicalOrEventTrigger
}

MeasurementType ::=          CHOICE {
    intraFrequencyMeasurement      IntraFrequencyMeasurement,
    interFrequencyMeasurement      InterFrequencyMeasurement,
    interRATMeasurement            InterRATMeasurement,
    ue-positioning-Measurement      UE-Positioning-Measurement,
    trafficVolumeMeasurement        TrafficVolumeMeasurement,
    qualityMeasurement              QualityMeasurement,
    ue-InternalMeasurement          UE-InternalMeasurement
}

MeasurementType-r4 ::=       CHOICE {
    intraFrequencyMeasurement-r4    IntraFrequencyMeasurement-r4,
    interFrequencyMeasurement-r4    InterFrequencyMeasurement-r4,
    interRATMeasurement              InterRATMeasurement,
    up-Measurement                    UE-Positioning-Measurement-r4,
    trafficVolumeMeasurement          TrafficVolumeMeasurement,
    qualityMeasurement                QualityMeasurement,
    ue-InternalMeasurement-r4        UE-InternalMeasurement-r4
}

MeasurementValidity ::=      SEQUENCE {
    ue-State                          ENUMERATED {
                                        cell-DCH, all-But-Cell-DCH, all-States }
}

MonitoredCellRACH-List ::=   SEQUENCE (SIZE (1..7)) OF
                                MonitoredCellRACH-Result

MonitoredCellRACH-Result ::= SEQUENCE {
    sfn-SFN-ObsTimeDifference          SFN-SFN-ObsTimeDifference          OPTIONAL,
    modeSpecificInfo                   CHOICE {
        fdd                             SEQUENCE {
            primaryCPICH-Info            PrimaryCPICH-Info,
            measurementQuantity           CHOICE {
                cpich-Ec-NO,
                cpich-RSCP,
                pathloss
            }
        },
        tdd                             SEQUENCE {
            cellParametersID              CellParametersID,
            primaryCCPCH-RSCP
        }
    }
}

MultipathIndicator ::=        ENUMERATED {
                                nm,
                                low,
                                medium,
                                high }

N-CR-T-CRMaxHyst ::=          SEQUENCE {
    n-CR                                INTEGER (1..16)          DEFAULT 8,
    t-CRMaxHyst                          T-CRMaxHyst
}

NavigationModelSatInfo ::=    SEQUENCE {
    satID                                SatID,
    satelliteStatus                       SatelliteStatus,
    ephemerisParameter                    EphemerisParameter          OPTIONAL
}

```

```

NavigationModelSatInfoList ::=          SEQUENCE (SIZE (1..maxSat)) OF
                                         NavigationModelSatInfo

EphemerisParameter ::=                SEQUENCE {
    codeOnL2                            BIT STRING (SIZE (2)),
    uraIndex                             BIT STRING (SIZE (4)),
    satHealth                            BIT STRING (SIZE (6)),
    iodc                                 BIT STRING (SIZE (10)),
    l2Pflag                              BIT STRING (SIZE (1)),
    sflRevd                             SubFrame1Reserved,
    t-GD                                 BIT STRING (SIZE (8)),
    t-oc                                 BIT STRING (SIZE (16)),
    af2                                  BIT STRING (SIZE (8)),
    af1                                  BIT STRING (SIZE (16)),
    af0                                  BIT STRING (SIZE (22)),
    c-rs                                 BIT STRING (SIZE (16)),
    delta-n                              BIT STRING (SIZE (16)),
    m0                                   BIT STRING (SIZE (32)),
    c-uc                                 BIT STRING (SIZE (16)),
    e                                    BIT STRING (SIZE (32)),
    c-us                                 BIT STRING (SIZE (16)),
    a-Sqrt                              BIT STRING (SIZE (32)),
    t-oe                                 BIT STRING (SIZE (16)),
    fitInterval                          BIT STRING (SIZE (1)),
    aodo                                 BIT STRING (SIZE (5)),
    c-ic                                 BIT STRING (SIZE (16)),
    omega0                              BIT STRING (SIZE (32)),
    c-is                                 BIT STRING (SIZE (16)),
    i0                                   BIT STRING (SIZE (32)),
    c-rc                                 BIT STRING (SIZE (16)),
    omega                               BIT STRING (SIZE (32)),
    omegaDot                            BIT STRING (SIZE (24)),
    iDot                                BIT STRING (SIZE (14))
}
NC-Mode ::=                            BIT STRING (SIZE (3))

Neighbour ::=                          SEQUENCE {
    modeSpecificInfo                    CHOICE {
        fdd                             SEQUENCE {
            neighbourIdentity            PrimaryCPICH-Info                OPTIONAL,
            ue-RX-TX-TimeDifferenceType2 UE-RX-TX-TimeDifferenceType2    OPTIONAL
        },
        tdd                             SEQUENCE {
            neighbourAndChannelIdentity  CellAndChannelIdentity        OPTIONAL
        }
    },
    neighbourQuality                    NeighbourQuality,
    sfn-SFN-ObsTimeDifference2          SFN-SFN-ObsTimeDifference2}

NeighbourList ::=                      SEQUENCE (SIZE (1..maxCellMeas)) OF
                                         Neighbour

NeighbourQuality ::=                  SEQUENCE {
    ue-Positioning-OTDOA-Quality        UE-Positioning-OTDOA-Quality
}

NewInterFreqCell ::=                  SEQUENCE {
    interFreqCellID                    InterFreqCellID                OPTIONAL,
    frequencyInfo                      FrequencyInfo                  OPTIONAL,
    cellInfo                           CellInfo
}

NewInterFreqCell-r4 ::=                SEQUENCE {
    interFreqCellID                    InterFreqCellID                OPTIONAL,
    frequencyInfo                      FrequencyInfo                  OPTIONAL,
    cellInfo                           CellInfo-r4
}

NewInterFreqCellList ::=              SEQUENCE (SIZE (1..maxCellMeas)) OF
                                         NewInterFreqCell

NewInterFreqCellList-r4 ::=            SEQUENCE (SIZE (1..maxCellMeas)) OF
                                         NewInterFreqCell-r4

NewInterFreqCellSI-RSCP ::=            SEQUENCE {
    interFreqCellID                    InterFreqCellID                OPTIONAL,
    frequencyInfo                      FrequencyInfo                  OPTIONAL,
    cellInfo                           CellInfoSI-RSCP
}

```

```

}

NewInterFreqCellSI-ECNO ::=
    interFreqCellID
    frequencyInfo
    cellInfo
}

NewInterFreqCellSI-HCS-RSCP ::=
    interFreqCellID
    frequencyInfo
    cellInfo
}

NewInterFreqCellSI-HCS-ECNO ::=
    interFreqCellID
    frequencyInfo
    cellInfo
}

NewInterFreqCellSI-RSCP-LCR-r4 ::=
    interFreqCellID
    frequencyInfo
    cellInfo
}

NewInterFreqCellSI-ECNO-LCR-r4 ::=
    interFreqCellID
    frequencyInfo
    cellInfo
}

NewInterFreqCellSI-HCS-RSCP-LCR-r4 ::=
    interFreqCellID
    frequencyInfo
    cellInfo
}

NewInterFreqCellSI-HCS-ECNO-LCR-r4 ::=
    interFreqCellID
    frequencyInfo
    cellInfo
}

NewInterFreqCellSI-List-ECNO ::=
    SEQUENCE (SIZE (1..maxCellMeas)) OF
    NewInterFreqCellSI-ECNO

NewInterFreqCellSI-List-HCS-RSCP ::=
    SEQUENCE (SIZE (1..maxCellMeas)) OF
    NewInterFreqCellSI-HCS-RSCP

NewInterFreqCellSI-List-HCS-ECNO ::=
    SEQUENCE (SIZE (1..maxCellMeas)) OF
    NewInterFreqCellSI-HCS-ECNO

NewInterFreqCellSI-List-RSCP ::=
    SEQUENCE (SIZE (1..maxCellMeas)) OF
    NewInterFreqCellSI-RSCP

NewInterFreqCellSI-List-ECNO-LCR-r4 ::=
    SEQUENCE (SIZE (1..maxCellMeas)) OF
    NewInterFreqCellSI-ECNO-LCR-r4

NewInterFreqCellSI-List-HCS-RSCP-LCR-r4 ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    NewInterFreqCellSI-HCS-RSCP-LCR-r4

NewInterFreqCellSI-List-HCS-ECNO-LCR-r4 ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    NewInterFreqCellSI-HCS-ECNO-LCR-r4

NewInterFreqCellSI-List-RSCP-LCR-r4 ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    NewInterFreqCellSI-RSCP-LCR-r4

NewInterRATCell ::=
    interRATCellID
    technologySpecificInfo
    gsm
        cellSelectionReselectionInfo
        interRATCellIndividualOffset
        bsic
        frequency-band
        bcch-ARFCN
        dummy
}

SEQUENCE {
    InterRATCellID
    CHOICE {
        SEQUENCE {
            CellSelectReselectInfoSIB-11-12
            InterRATCellIndividualOffset,
            BSIC,
            Frequency-Band,
            BCCH-ARFCN,
            NULL
        }
    }
}
OPTIONAL,
OPTIONAL,
OPTIONAL,
OPTIONAL,
OPTIONAL

```



```

    },
    is-2000
        is-2000SpecificMeasInfo
    },
    spare1
    spare2
}
}

NewInterRATCell-B ::=
    interRATCellID
    technologySpecificInfo
        gsm
            cellSelectionReselectionInfo
            interRATCellIndividualOffset
            bsic
            frequency-band
            bcch-ARFCN
            dummy
        },
        is-2000
            is-2000SpecificMeasInfo
        },
        spare1
        spare2
    }
}

NewInterRATCellList ::=
    SEQUENCE (SIZE (1..maxCellMeas)) OF
        NewInterRATCell

NewInterRATCellList-B ::=
    SEQUENCE (SIZE (1..maxCellMeas)) OF
        NewInterRATCell-B

NewIntraFreqCell ::=
    intraFreqCellID
    cellInfo
}

NewIntraFreqCell-r4 ::=
    intraFreqCellID
    cellInfo
}

NewIntraFreqCellList ::=
    SEQUENCE (SIZE (1..maxCellMeas)) OF
        NewIntraFreqCell

NewIntraFreqCellList-r4 ::=
    SEQUENCE (SIZE (1..maxCellMeas)) OF
        NewIntraFreqCell-r4

NewIntraFreqCellSI-RSCP ::=
    intraFreqCellID
    cellInfo
}

NewIntraFreqCellSI-ECN0 ::=
    intraFreqCellID
    cellInfo
}

NewIntraFreqCellSI-HCS-RSCP ::=
    intraFreqCellID
    cellInfo
}

NewIntraFreqCellSI-HCS-ECN0 ::=
    intraFreqCellID
    cellInfo
}

NewIntraFreqCellSI-RSCP-LCR-r4 ::=
    intraFreqCellID
    cellInfo
}

NewIntraFreqCellSI-ECN0-LCR-r4 ::=
    intraFreqCellID
    cellInfo
}

```

```

NewIntraFreqCellSI-HCS-RSCP-LCR-r4 ::= SEQUENCE {
    intraFreqCellID          IntraFreqCellID          OPTIONAL,
    cellInfo                  CellInfoSI-HCS-RSCP-LCR-r4
}

NewIntraFreqCellSI-HCS-ECN0-LCR-r4 ::= SEQUENCE {
    intraFreqCellID          IntraFreqCellID          OPTIONAL,
    cellInfo                  CellInfoSI-HCS-ECN0-LCR-r4
}

NewIntraFreqCellSI-List-RSCP ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    NewIntraFreqCellSI-RSCP

NewIntraFreqCellSI-List-ECN0 ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    NewIntraFreqCellSI-ECN0

NewIntraFreqCellSI-List-HCS-RSCP ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    NewIntraFreqCellSI-HCS-RSCP

NewIntraFreqCellSI-List-HCS-ECN0 ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    NewIntraFreqCellSI-HCS-ECN0

NewIntraFreqCellSI-List-RSCP-LCR-r4 ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    NewIntraFreqCellSI-RSCP-LCR-r4

NewIntraFreqCellSI-List-ECN0-LCR-r4 ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    NewIntraFreqCellSI-ECN0-LCR-r4

NewIntraFreqCellSI-List-HCS-RSCP-LCR-r4 ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    NewIntraFreqCellSI-HCS-RSCP-LCR-r4

NewIntraFreqCellSI-List-HCS-ECN0-LCR-r4 ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    NewIntraFreqCellSI-HCS-ECN0-LCR-r4

-- Actual value = IE value * 0.0125 - 0.09375
NodeB-ClockDrift ::= INTEGER (0..15)

NonUsedFreqParameter ::= SEQUENCE {
    nonUsedFreqThreshold    Threshold,
    nonUsedFreqW            W
}

NonUsedFreqParameterList ::= SEQUENCE (SIZE (1..maxFreq)) OF
    NonUsedFreqParameter

ObservedTimeDifferenceToGSM ::= INTEGER (0..4095)

OTDOA-SearchWindowSize ::= ENUMERATED {
    c20, c40, c80, c160, c320,
    c640, c1280, moreThan1280 }

Pathloss ::= INTEGER (46..158)

PenaltyTime-RSCP ::= CHOICE {
    notUsed          NULL,
    pt10             TemporaryOffset,
    pt20             TemporaryOffset,
    pt30             TemporaryOffset,
    pt40             TemporaryOffset,
    pt50             TemporaryOffset,
    pt60             TemporaryOffset
}

PenaltyTime-ECN0 ::= CHOICE {
    notUsed          NULL,
    pt10             TemporaryOffsetList,
    pt20             TemporaryOffsetList,
    pt30             TemporaryOffsetList,
    pt40             TemporaryOffsetList,
    pt50             TemporaryOffsetList,
    pt60             TemporaryOffsetList
}

PendingTimeAfterTrigger ::= ENUMERATED {
    ptat0-25, ptat0-5, ptat1,
    ptat2, ptat4, ptat8, ptat16 }

PeriodicalOrEventTrigger ::= ENUMERATED {

```

```

                                periodical,
                                eventTrigger }

PeriodicalReportingCriteria ::= SEQUENCE {
    reportingAmount              ReportingAmount              DEFAULT ra-Infinity,
    reportingInterval            ReportingIntervalLong
}

PeriodicalWithReportingCellStatus ::= SEQUENCE {
    periodicalReportingCriteria  PeriodicalReportingCriteria,
    reportingCellStatus          ReportingCellStatus          OPTIONAL
}

PLMNIdentitiesOfNeighbourCells ::= SEQUENCE {
    plmnsOfIntraFreqCellsList   PLMNsOfIntraFreqCellsList   OPTIONAL,
    plmnsOfInterFreqCellsList   PLMNsOfInterFreqCellsList   OPTIONAL,
    plmnsOfInterRATCellsList    PLMNsOfInterRATCellsList    OPTIONAL
}

PLMNsOfInterFreqCellsList ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    SEQUENCE {
        plmn-Identity            PLMN-Identity            OPTIONAL
    }

PLMNsOfIntraFreqCellsList ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    SEQUENCE {
        plmn-Identity            PLMN-Identity            OPTIONAL
    }

PLMNsOfInterRATCellsList ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    SEQUENCE {
        plmn-Identity            PLMN-Identity            OPTIONAL
    }

PositionEstimate ::= CHOICE {
    ellipsoidPoint                EllipsoidPoint,
    ellipsoidPointUncertCircle    EllipsoidPointUncertCircle,
    ellipsoidPointUncertEllipse  EllipsoidPointUncertEllipse,
    ellipsoidPointAltitude        EllipsoidPointAltitude,
    ellipsoidPointAltitudeEllipse EllipsoidPointAltitudeEllipsoide
}

PositioningMethod ::= ENUMERATED {
    otdoa,
    gps,
    otdoaOrGPS }

-- Actual value = IE value * 0.32
PRC ::= INTEGER (-2047..2047)

PrimaryCCPCH-RSCP ::= INTEGER (0..91)

Q-HCS ::= INTEGER (0..99)

Q-OffsetS-N ::= INTEGER (-50..50)

Q-QualMin ::= INTEGER (-24..0)

-- Actual value = (IE value * 2) + 1
Q-RxlevMin ::= INTEGER (-58..-13)

QualityEventResults ::= SEQUENCE (SIZE (1..maxTrCH)) OF
    TransportChannelIdentity

QualityMeasuredResults ::= SEQUENCE {
    blerMeasurementResultsList   BLER-MeasurementResultsList   OPTIONAL,
    modeSpecificInfo             CHOICE {
        fdd                       NULL,
        tdd                       SEQUENCE {
            sir-MeasurementResults SIR-MeasurementList           OPTIONAL
        }
    }
}

QualityMeasurement ::= SEQUENCE {
    qualityReportingQuantity      QualityReportingQuantity      OPTIONAL,
    reportCriteria                QualityReportCriteria
}

```

```

}

QualityReportCriteria ::=          CHOICE {
    qualityReportingCriteria      QualityReportingCriteria,
    periodicalReportingCriteria   PeriodicalReportingCriteria,
    noReporting                   NULL
}

QualityReportingCriteria ::=       SEQUENCE (SIZE (1..maxTrCH)) OF
    QualityReportingCriteriaSingle

QualityReportingCriteriaSingle ::= SEQUENCE {
    transportChannelIdentity      TransportChannelIdentity,
    totalCRC                      INTEGER (1..512),
    badCRC                       INTEGER (1..512),
    pendingAfterTrigger          INTEGER (1..512)
}

QualityReportingQuantity ::=       SEQUENCE {
    dl-TransChBLER               BOOLEAN,
    bler-dl-TransChIdList        BLER-TransChIdList           OPTIONAL,
    modeSpecificInfo             CHOICE {
        fdd                     NULL,
        tdd                     SEQUENCE {
            sir-TFCS-List       SIR-TFCS-List           OPTIONAL
        }
    }
}

QualityType ::=                   ENUMERATED {
    std-10, std-50, cpich-Ec-N0 }

RAT-Type ::=                      ENUMERATED {
    gsm, is2000 }

ReferenceCellPosition ::=         CHOICE {
    ellipsoidPoint               EllipsoidPoint,
    ellipsoidPointWithAltitude   EllipsoidPointAltitude
}

-- As defined in 23.032
ReferenceLocation ::=             SEQUENCE {
    ellipsoidPointAltitudeEllipsoide EllipsoidPointAltitudeEllipsoide
}

ReferenceSFN ::=                 INTEGER (0..4095)

ReferenceTimeDifferenceToCell ::= CHOICE {
    -- Actual value = IE value * 40
    accuracy40                   INTEGER (0..960),
    -- Actual value = IE value * 256
    accuracy256                  INTEGER (0..150),
    -- Actual value = IE value * 2560
    accuracy2560                 INTEGER (0..15)
}

RemovedInterFreqCellList ::=     CHOICE {
    removeAllInterFreqCells      NULL,
    removeSomeInterFreqCells     SEQUENCE (SIZE (1..maxCellMeas)) OF
        InterFreqCellID,
    removeNoInterFreqCells       NULL
}

RemovedInterRATCellList ::=      CHOICE {
    removeAllInterRATCells        NULL,
    removeSomeInterRATCells       SEQUENCE (SIZE (1..maxCellMeas)) OF
        InterRATCellID,
    removeNoInterRATCells        NULL
}

RemovedIntraFreqCellList ::=     CHOICE {
    removeAllIntraFreqCells       NULL,
    removeSomeIntraFreqCells      SEQUENCE (SIZE (1..maxCellMeas)) OF
        IntraFreqCellID,
    removeNoIntraFreqCells       NULL
}

ReplacementActivationThreshold ::= ENUMERATED {

```

```

notApplicable, t1, t2,
t3, t4, t5, t6, t7 }

ReportDeactivationThreshold ::=      ENUMERATED {
notApplicable, t1, t2,
t3, t4, t5, t6, t7 }

ReportingAmount ::=                  ENUMERATED {
ra1, ra2, ra4, ra8, ra16, ra32,
ra64, ra-Infinity }

ReportingCellStatus ::=              CHOICE{
  withinActiveSet                    MaxNumberOfReportingCellsType1,
  withinMonitoredSetUsedFreq          MaxNumberOfReportingCellsType1,
  withinActiveAndOrMonitoredUsedFreq  MaxNumberOfReportingCellsType1,
  withinDetectedSetUsedFreq           MaxNumberOfReportingCellsType1,
  withinMonitoredAndOrDetectedUsedFreq MaxNumberOfReportingCellsType1,
  allActiveplusMonitoredSet           MaxNumberOfReportingCellsType3,
  allActivePlusDetectedSet            MaxNumberOfReportingCellsType3,
  allActivePlusMonitoredAndOrDetectedSet MaxNumberOfReportingCellsType3,
  withinVirtualActSet                 MaxNumberOfReportingCellsType1,
  withinMonitoredSetNonUsedFreq        MaxNumberOfReportingCellsType1,
  withinMonitoredAndOrActiveSetNonUsedFreq MaxNumberOfReportingCellsType1,
  allVirtualActSetplusMonitoredSetNonUsedFreq MaxNumberOfReportingCellsType3,
  withinActSetOrVirtualActSet          MaxNumberOfReportingCellsType2,
  withinActSetAndOrMonitoredUsedFreqOrMonitoredNonUsedFreq MaxNumberOfReportingCellsType2
}

ReportingCellStatusOpt ::=           SEQUENCE {
  reportingCellStatus                 ReportingCellStatus           OPTIONAL
}

ReportingInfoForCellDCH ::=          SEQUENCE {
  intraFreqReportingQuantity          IntraFreqReportingQuantity,
  measurementReportingMode             MeasurementReportingMode,
  reportCriteria                       CellDCH-ReportCriteria
}

ReportingInfoForCellDCH-LCR-r4 ::=  SEQUENCE {
  intraFreqReportingQuantity          IntraFreqReportingQuantity,
  measurementReportingMode             MeasurementReportingMode,
  reportCriteria                       CellDCH-ReportCriteria-LCR-r4
}

ReportingInterval ::=                ENUMERATED {
noPeriodicalreporting, ri0-25,
ri0-5, ril, ri2, ri4, ri8, ril6 }

ReportingIntervalLong ::=            ENUMERATED {
ril0, ril0-25, ril0-5, ril1,
ril2, ril3, ril4, ril6, ril8,
ril12, ril16, ril20, ril24,
ril28, ril32, ril64 }

-- Actual value = IE value * 0.5
ReportingRange ::=                   INTEGER (0..29)

RL-AdditionInfoList ::=              SEQUENCE (SIZE (1..maxRL)) OF
PrimaryCPICH-Info

RL-InformationLists ::=              SEQUENCE {
  rl-AdditionInfoList                 RL-AdditionInfoList           OPTIONAL,
  rl-RemovalInfoList                  RL-RemovalInfoList           OPTIONAL
}

RL-RemovalInfoList ::=               SEQUENCE (SIZE (1..maxRL)) OF
PrimaryCPICH-Info

RLC-BuffersPayload ::=               ENUMERATED {
p10, p14, p18, p116, p132, p164, p1128,
p1256, p1512, p11024, p12k, p14k,
p18k, p116k, p132k, p164k, p1128k,

```

```

        p1256k, p1512k, p11024k }

-- Actual value = IE value * 0.032
RRC ::=
    INTEGER (-127..127)

SatData ::=
    SEQUENCE {
        satID
        iode
    }

SatDataList ::=
    SEQUENCE (SIZE (0..maxSat)) OF
        SatData

SatelliteStatus ::=
    ENUMERATED {
        ns-NN-U,
        es-SN,
        es-NN-U,
        rev2,
        rev }

SatID ::=
    INTEGER (0..63)

SFN-SFN-Drift ::=
    ENUMERATED {no-drift, sfnsfndrift0-33, sfnsfndrift0-66,
        sfnsfndrift1, sfnsfndrift1-33, sfnsfndrift1-66,
        sfnsfndrift2, sfnsfndrift2-5, sfnsfndrift3,
        sfnsfndrift4, sfnsfndrift5, sfnsfndrift7,
        sfnsfndrift9, sfnsfndrift11, sfnsfndrift13,
        sfnsfndrift15, sfnsfndrift-0-33, sfnsfndrift-0-66,
        sfnsfndrift-1, sfnsfndrift-1-33, sfnsfndrift-1-66,
        sfnsfndrift-2, sfnsfndrift-2-5, sfnsfndrift-3,
        sfnsfndrift-4, sfnsfndrift-5, sfnsfndrift-7,
        sfnsfndrift-9, sfnsfndrift-11, sfnsfndrift-13,
        sfnsfndrift-15}

SFN-SFN-ObsTimeDifference ::=
    CHOICE {
        type1
        type2
    }

SFN-SFN-ObsTimeDifference1 ::=
    INTEGER (0..9830399)

SFN-SFN-ObsTimeDifference2 ::=
    INTEGER (0..40961)

SFN-SFN-OTD-Type ::=
    ENUMERATED {
        noReport,
        type1,
        type2 }

SFN-SFN-RelTimeDifference1 ::=
    SEQUENCE {
        sfn-Offset
        sfn-sfn-Reltimedifference
    }

SFN-TOW-Uncertainty ::=
    ENUMERATED {
        lessThan10,
        moreThan10 }

SIR ::=
    INTEGER (0..63)

SIR-MeasurementList ::=
    SEQUENCE (SIZE (1..maxCCTrCH)) OF
        SIR-MeasurementResults

SIR-MeasurementResults ::=
    SEQUENCE {
        tfcs-ID
        sir-TimeslotList
    }

SIR-TFCS ::=
    TFCS-IdentityPlain

SIR-TFCS-List ::=
    SEQUENCE (SIZE (1..maxCCTrCH)) OF
        SIR-TFCS

SIR-TimeslotList ::=
    SEQUENCE (SIZE (1..maxTS)) OF
        SIR

```

```

-- Reserved bits in subframe 1 of the GPS navigation message
SubFrame1Reserved ::=
    SEQUENCE {
        reserved1      BIT STRING (SIZE (23)),
        reserved2      BIT STRING (SIZE (24)),
        reserved3      BIT STRING (SIZE (24)),
        reserved4      BIT STRING (SIZE (16))
    }

T-CRMax ::=
    CHOICE {
        notUsed        NULL,
        t30             N-CR-T-CRMaxHyst,
        t60             N-CR-T-CRMaxHyst,
        t120            N-CR-T-CRMaxHyst,
        t180            N-CR-T-CRMaxHyst,
        t240            N-CR-T-CRMaxHyst
    }

T-CRMaxHyst ::=
    ENUMERATED {
        notUsed, t10, t20, t30,
        t40, t50, t60, t70 }

TemporaryOffset ::=
    ENUMERATED {
        to10, to20, to30, to40, to50,
        to60, to70, infinite }

TemporaryOffsetList ::=
    SEQUENCE {
        temporaryOffset1
        temporaryOffset2
    }

Threshold ::=
    INTEGER (-115..0)

ThresholdPositionChange ::=
    ENUMERATED {
        pc10, pc20, pc30, pc40, pc50,
        pc100, pc200, pc300, pc500,
        pc1000, pc2000, pc5000, pc10000,
        pc20000, pc50000, pc100000 }

ThresholdSFN-GPS-TOW ::=
    ENUMERATED {
        ms1, ms2, ms3, ms5, ms10,
        ms20, ms50, ms100 }

ThresholdSFN-SFN-Change ::=
    ENUMERATED {
        c0-25, c0-5, c1, c2, c3, c4, c5,
        c10, c20, c50, c100, c200, c500,
        c1000, c2000, c5000 }

ThresholdUsedFrequency ::=
    INTEGER (-115..165)

-- Actual value = IE value * 20.
TimeInterval ::=
    INTEGER (1..13)

TimeslotInfo ::=
    SEQUENCE {
        timeslotNumber
        burstType
    }

TimeslotInfo-LCR-r4 ::=
    SEQUENCE {
        timeslotNumber-LCR-r4,
        burstType
    }

TimeslotInfoList ::=
    SEQUENCE (SIZE (1..maxTS)) OF
        TimeslotInfo

TimeslotInfoList-LCR-r4 ::=
    SEQUENCE (SIZE (1..maxTS-LCR)) OF
        TimeslotInfo-LCR-r4

TimeslotInfoList-r4 ::=
    CHOICE {
        tdd384
            SEQUENCE (SIZE (1..maxTS)) OF
                TimeslotInfo,
        tdd128
            SEQUENCE (SIZE (1..maxTS-LCR)) OF
                TimeslotInfo-LCR-r4
    }

TimeslotISCP ::=
    INTEGER (0..91)

```

```

-- The following list shall not include more than 6 elements in 1.28Mcps TDD mode.
TimeslotISCP-List ::= SEQUENCE (SIZE (1..maxTS)) OF
    TimeslotISCP

TimeslotListWithISCP ::= SEQUENCE (SIZE (1..maxTS)) OF
    TimeslotWithISCP

TimeslotWithISCP ::= SEQUENCE {
    timeslot TimeslotNumber,
    timeslotISCP TimeslotISCP
}

TimeToTrigger ::= ENUMERATED {
    ttt0, ttt10, ttt20, ttt40, ttt60,
    ttt80, ttt100, ttt120, ttt160,
    ttt200, ttt240, ttt320, ttt640,
    ttt1280, ttt2560, ttt5000 }

TrafficVolumeEventParam ::= SEQUENCE {
    eventID TrafficVolumeEventType,
    reportingThreshold TrafficVolumeThreshold,
    timeToTrigger TimeToTrigger OPTIONAL,
    pendingTimeAfterTrigger PendingTimeAfterTrigger OPTIONAL,
    tx-InterruptionAfterTrigger TX-InterruptionAfterTrigger OPTIONAL
}

TrafficVolumeEventResults ::= SEQUENCE {
    ul-transportChannelCausingEvent UL-TrCH-Identity,
    trafficVolumeEventIdentity TrafficVolumeEventType
}

TrafficVolumeEventType ::= ENUMERATED {
    e4a,
    e4b }

TrafficVolumeMeasQuantity ::= CHOICE {
    rlc-BufferPayload NULL,
    averageRLC-BufferPayload TimeInterval,
    varianceOfRLC-BufferPayload TimeInterval
}

TrafficVolumeMeasSysInfo ::= SEQUENCE {
    trafficVolumeMeasurementID MeasurementIdentity DEFAULT 4,
    trafficVolumeMeasurementObjectList TrafficVolumeMeasurementObjectList OPTIONAL,
    trafficVolumeMeasQuantity TrafficVolumeMeasQuantity OPTIONAL,
    trafficVolumeReportingQuantity TrafficVolumeReportingQuantity OPTIONAL,
    trafficVolumeMeasRepCriteria TrafficVolumeReportingCriteria OPTIONAL,
    measurementValidity MeasurementValidity OPTIONAL,
    measurementReportingMode MeasurementReportingMode,
    reportCriteriaSysInf TrafficVolumeReportCriteriaSysInfo
}

TrafficVolumeMeasuredResults ::= SEQUENCE {
    rb-Identity RB-Identity,
    rlc-BuffersPayload RLC-BuffersPayload OPTIONAL,
    averageRLC-BufferPayload AverageRLC-BufferPayload OPTIONAL,
    varianceOfRLC-BufferPayload VarianceOfRLC-BufferPayload OPTIONAL
}

TrafficVolumeMeasuredResultsList ::= SEQUENCE (SIZE (1..maxRB)) OF
    TrafficVolumeMeasuredResults

TrafficVolumeMeasurement ::= SEQUENCE {
    trafficVolumeMeasurementObjectList TrafficVolumeMeasurementObjectList OPTIONAL,
    trafficVolumeMeasQuantity TrafficVolumeMeasQuantity OPTIONAL,
    trafficVolumeReportingQuantity TrafficVolumeReportingQuantity OPTIONAL,
    measurementValidity MeasurementValidity OPTIONAL,
    reportCriteria TrafficVolumeReportCriteria
}

TrafficVolumeMeasurementObjectList ::= SEQUENCE (SIZE (1..maxTrCH)) OF
    UL-TrCH-Identity

TrafficVolumeReportCriteria ::= CHOICE {
    trafficVolumeReportingCriteria TrafficVolumeReportingCriteria,

```



```

    periodicalReportingCriteria      PeriodicalReportingCriteria,
    noReporting                      NULL
}

TrafficVolumeReportCriteriaSysInfo ::= CHOICE {
    trafficVolumeReportingCriteria  TrafficVolumeReportingCriteria,
    periodicalReportingCriteria     PeriodicalReportingCriteria
}

TrafficVolumeReportingCriteria ::= SEQUENCE {
    transChCriteriaList             TransChCriteriaList                OPTIONAL
}

TrafficVolumeReportingQuantity ::= SEQUENCE {
    rlc-RB-BufferPayload            BOOLEAN,
    rlc-RB-BufferPayloadAverage     BOOLEAN,
    rlc-RB-BufferPayloadVariance    BOOLEAN
}

TrafficVolumeThreshold ::=
    ENUMERATED {
        th8, th16, th32, th64, th128,
        th256, th512, th1024, th2k, th3k,
        th4k, th6k, th8k, th12k, th16k,
        th24k, th32k, th48k, th64k, th96k,
        th128k, th192k, th256k, th384k,
        th512k, th768k }

TransChCriteria ::=
    SEQUENCE {
        ul-transportChannelID        UL-TrCH-Identity                OPTIONAL,
        eventSpecificParameters      SEQUENCE (SIZE (1..maxMeasParEvent)) OF
                                     TrafficVolumeEventParam            OPTIONAL
    }

TransChCriteriaList ::=
    SEQUENCE (SIZE (1..maxTrCH)) OF
    TransChCriteria

TransferMode ::=
    ENUMERATED {
        acknowledgedModeRLC,
        unacknowledgedModeRLC }

TransmittedPowerThreshold ::=
    INTEGER (-50..33)

TriggeringCondition1 ::=
    ENUMERATED {
        activeSetCellsOnly,
        monitoredSetCellsOnly,
        activeSetAndMonitoredSetCells }

TriggeringCondition2 ::=
    ENUMERATED {
        activeSetCellsOnly,
        monitoredSetCellsOnly,
        activeSetAndMonitoredSetCells,
        detectedSetCellsOnly,
        detectedSetAndMonitoredSetCells }

TX-InterruptionAfterTrigger ::=
    ENUMERATED {
        txiat0-25, txiat0-5, txiat1,
        txiat2, txiat4, txiat8, txiat16 }

UDRE ::=
    ENUMERATED {
        lessThan1,
        between1-and-4,
        between4-and-8,
        over8 }

UE-6AB-Event ::=
    SEQUENCE {
        timeToTrigger                TimeToTrigger,
        transmittedPowerThreshold    TransmittedPowerThreshold
    }

UE-6FG-Event ::=
    SEQUENCE {
        timeToTrigger                TimeToTrigger,
        ue-RX-TX-TimeDifferenceThreshold UE-RX-TX-TimeDifferenceThreshold
    }

UE-AutonomousUpdateMode ::=
    CHOICE {
        on                            NULL,
        onWithNoReporting             NULL,
        off                           RL-InformationLists
    }

```

```

}

UE-InternalEventParam ::=          CHOICE {
    event6a                        UE-6AB-Event,
    event6b                        UE-6AB-Event,
    event6c                        TimeToTrigger,
    event6d                        TimeToTrigger,
    event6e                        TimeToTrigger,
    event6f                        UE-6FG-Event,
    event6g                        UE-6FG-Event
}

UE-InternalEventParamList ::=      SEQUENCE (SIZE (1..maxMeasEvent)) OF
    UE-InternalEventParam

UE-InternalEventResults ::=        CHOICE {
    event6a                        NULL,
    event6b                        NULL,
    event6c                        NULL,
    event6d                        NULL,
    event6e                        NULL,
    event6f                        PrimaryCPICH-Info,
    event6g                        PrimaryCPICH-Info
}

UE-InternalMeasQuantity ::=        SEQUENCE {
    measurementQuantity            UE-MeasurementQuantity,
    filterCoefficient              FilterCoefficient              DEFAULT fc0
}

UE-InternalMeasuredResults ::=      SEQUENCE {
    modeSpecificInfo              CHOICE {
        fdd                       SEQUENCE {
            ue-TransmittedPowerFDD UE-TransmittedPower      OPTIONAL,
            ue-RX-TX-ReportEntryList UE-RX-TX-ReportEntryList  OPTIONAL
        },
        tdd                       SEQUENCE {
            ue-TransmittedPowerTDD-List UE-TransmittedPowerTDD-List  OPTIONAL,
            appliedTA              UL-TimingAdvance          OPTIONAL
        }
    }
}

UE-InternalMeasuredResults-LCR-r4 ::= SEQUENCE {
    ue-TransmittedPowerTDD-List    UE-TransmittedPowerTDD-List    OPTIONAL,
    upPCH-ADV                      INTEGER (0..352)                OPTIONAL
}

UE-InternalMeasurement ::=         SEQUENCE {
    ue-InternalMeasQuantity        UE-InternalMeasQuantity        OPTIONAL,
    ue-InternalReportingQuantity   UE-InternalReportingQuantity   OPTIONAL,
    reportCriteria                 UE-InternalReportCriteria
}

UE-InternalMeasurement-r4 ::=      SEQUENCE {
    ue-InternalMeasQuantity        UE-InternalMeasQuantity        OPTIONAL,
    ue-InternalReportingQuantity   UE-InternalReportingQuantity-r4  OPTIONAL,
    reportCriteria                 UE-InternalReportCriteria
}

UE-InternalMeasurementSysInfo ::=  SEQUENCE {
    ue-InternalMeasurementID       MeasurementIdentity            DEFAULT 5,
    ue-InternalMeasQuantity        UE-InternalMeasQuantity
}

UE-InternalReportCriteria ::=      CHOICE {
    ue-InternalReportingCriteria   UE-InternalReportingCriteria,
    periodicalReportingCriteria    PeriodicalReportingCriteria,
    noReporting                    NULL
}

UE-InternalReportingCriteria ::=    SEQUENCE {
    ue-InternalEventParamList      UE-InternalEventParamList      OPTIONAL
}

UE-InternalReportingQuantity ::=    SEQUENCE {
    ue-TransmittedPower            BOOLEAN,
    modeSpecificInfo              CHOICE {

```

```

        fdd                SEQUENCE {
            ue-RX-TX-TimeDifference    BOOLEAN
        },
        tdd                SEQUENCE {
            appliedTA                BOOLEAN
        }
    }
}

UE-InternalReportingQuantity-r4 ::= SEQUENCE {
    ue-TransmittedPower            BOOLEAN,
    modeSpecificInfo                CHOICE {
        fdd                SEQUENCE {
            ue-RX-TX-TimeDifference    BOOLEAN
        },
        tdd                SEQUENCE {
            tddOption        CHOICE {
                tdd384        SEQUENCE {
                    appliedTA    BOOLEAN
                },
                tdd128        SEQUENCE {
                    upPTS-ADV    BOOLEAN
                }
            }
        }
    }
}

-- TABULAR: For TDD only the first two values are used.
UE-MeasurementQuantity ::= ENUMERATED {
    ue-TransmittedPower,
    ultra-Carrier-RSSI,
    ue-RX-TX-TimeDifference }

UE-RX-TX-ReportEntry ::= SEQUENCE {
    primaryCPICH-Info        PrimaryCPICH-Info,
    ue-RX-TX-TimeDifferenceType1    UE-RX-TX-TimeDifferenceType1
}

UE-RX-TX-ReportEntryList ::= SEQUENCE (SIZE (1..maxRL)) OF
    UE-RX-TX-ReportEntry

UE-RX-TX-TimeDifferenceType1 ::= INTEGER (768..1280)

-- Actual value = IE value * 0.0625 + 768
UE-RX-TX-TimeDifferenceType2 ::= INTEGER (0..8191)

UE-RX-TX-TimeDifferenceThreshold ::= INTEGER (768..1280)

UE-TransmittedPower ::= INTEGER (0..104)

UE-TransmittedPowerTDD-List ::= SEQUENCE (SIZE (1..maxTS)) OF
    UE-TransmittedPower

UL-TrCH-Identity ::= CHOICE{
    dch                TransportChannelIdentity,
    rach                NULL,
    usch                TransportChannelIdentity
}

UE-Positioning-Accuracy ::= BIT STRING (SIZE (7))

UE-Positioning-CipherParameters ::= SEQUENCE {
    cipheringKeyFlag        BIT STRING (SIZE (1)),
    cipheringSerialNumber    INTEGER (0..65535)
}

UE-Positioning-Error ::= SEQUENCE {
    errorReason            UE-Positioning-ErrorCause,
    ue-positioning-GPS-additionalAssistanceDataRequest    UE-Positioning-GPS-
AdditionalAssistanceDataRequest OPTIONAL
}

UE-Positioning-ErrorCause ::= ENUMERATED {
    notEnoughOTDOA-Cells,
    notEnoughGPS-Satellites,
    assistanceDataMissing,
}

```

```

methodNotSupported,
undefinedError,
requestDeniedByUser,
notProcessedAndTimeout ,
referenceCellNotServingCell }

UE-Positioning-EventID ::=
    ENUMERATED {
    e7a, e7b, e7c }

UE-Positioning-EventParam ::=
    SEQUENCE {
    reportingAmount
    reportFirstFix
    measurementInterval
    eventSpecificInfo
    }

UE-Positioning-EventParamList ::=
    SEQUENCE (SIZE (1..maxMeasEvent)) OF
    UE-Positioning-EventParam

UE-Positioning-EventSpecificInfo ::=
    CHOICE {
    e7a
    e7b
    e7c
    }

UE-Positioning-GPS-AcquisitionAssistance ::=
    SEQUENCE {
    referenceTime
        CHOICE {
        utran-ReferenceTime
            UTRAN-ReferenceTime,
        gps-ReferenceTimeOnly
            INTEGER (0..604799999)
        },
    satelliteInformationList
        AcquisitionSatInfoList
    }

UE-Positioning-GPS-AdditionalAssistanceDataRequest ::=
    SEQUENCE {
    almanacRequest
        BOOLEAN,
    utcModelRequest
        BOOLEAN,
    ionosphericModelRequest
        BOOLEAN,
    navigationModelRequest
        BOOLEAN,
    dgpsCorrectionsRequest
        BOOLEAN,
    referenceLocationRequest
        BOOLEAN,
    referenceTimeRequest
        BOOLEAN,
    aquisitionAssistanceRequest
        BOOLEAN,
    realTimeIntegrityRequest
        BOOLEAN,
    navModelAddDataRequest
        UE-Positioning-GPS-NavModelAddDataReq OPTIONAL
    }

UE-Positioning-GPS-Almanac ::=
    SEQUENCE {
    wn-a
        BIT STRING (SIZE (8)),
    almanacSatInfoList
        AlmanacSatInfoList,
    sv-GlobalHealth
        BIT STRING (SIZE (364)) OPTIONAL
    }

UE-Positioning-GPS-AssistanceData ::=
    SEQUENCE {
    ue-positioning-GPS-ReferenceTime
        UE-Positioning-GPS-ReferenceTime
    OPTIONAL,
    ue-positioning-GPS-ReferenceLocation
        ReferenceLocation OPTIONAL,
    ue-positioning-GPS-DGPS-Corrections
        UE-Positioning-GPS-DGPS-Corrections
    OPTIONAL,
    ue-positioning-GPS-NavigationModel
        UE-Positioning-GPS-NavigationModel
    OPTIONAL,
    ue-positioning-GPS-IonosphericModel
        UE-Positioning-GPS-IonosphericModel
    OPTIONAL,
    ue-positioning-GPS-UTC-Model
        UE-Positioning-GPS-UTC-Model
    OPTIONAL,
    ue-positioning-GPS-Almanac
        UE-Positioning-GPS-Almanac
    OPTIONAL,
    ue-positioning-GPS-AcquisitionAssistance
        UE-Positioning-GPS-AcquisitionAssistance
    OPTIONAL,
    ue-positioning-GPS-Real-timeIntegrity
        BadSatList OPTIONAL
    }

UE-Positioning-GPS-DGPS-Corrections ::=
    SEQUENCE {
    gps-TOW
        INTEGER (0..604799),
    statusHealth
        DiffCorrectionStatus,
    dgps-CorrectionSatInfoList
        DGPS-CorrectionSatInfoList
    }

UE-Positioning-GPS-IonosphericModel ::=
    SEQUENCE {

```

```

    alfa0          BIT STRING (SIZE (8)),
    alfa1          BIT STRING (SIZE (8)),
    alfa2          BIT STRING (SIZE (8)),
    alfa3          BIT STRING (SIZE (8)),
    beta0          BIT STRING (SIZE (8)),
    beta1          BIT STRING (SIZE (8)),
    beta2          BIT STRING (SIZE (8)),
    beta3          BIT STRING (SIZE (8))
}

UE-Positioning-GPS-MeasurementResults ::= SEQUENCE {
    modeSpecificInfo CHOICE {
        fdd SEQUENCE {
            referenceIdentity PrimaryCPICH-Info OPTIONAL
        },
        tdd SEQUENCE {
            referenceIdentity CellParametersID OPTIONAL
        }
    },
    referenceSFN ReferenceSFN OPTIONAL,
    gps-TOW-lmsec GPS-TOW-lmsec,
    gps-TOW-rem-usec GPS-TOW-rem-usec OPTIONAL,
    gps-MeasurementParamList GPS-MeasurementParamList
}

UE-Positioning-GPS-NavModelAddDataReq ::= SEQUENCE {
    navigationModelSatInfoList NavigationModelSatInfoList
}

UE-Positioning-GPS-NavModelAddDataReq ::= SEQUENCE {
    gps-Week INTEGER (0..1023),
    gps-Toe INTEGER (0..167),
    tToeLimit INTEGER (0..10),
    satDataList SatDataList
}

UE-Positioning-GPS-ReferenceTime ::= SEQUENCE {
    gps-Week INTEGER (0..1023),
    gps-tow-lmsec GPS-TOW-lmsec,
    gps-tow-rem-usec GPS-TOW-rem-usec OPTIONAL,
    modeSpecificInfo CHOICE {
        fdd SEQUENCE {
            referenceIdentity PrimaryCPICH-Info OPTIONAL
        },
        tdd SEQUENCE {
            referenceIdentity CellParametersID OPTIONAL
        }
    },
    sfn INTEGER (0..4095) OPTIONAL,
    sfn-tow-Uncertainty SFN-TOW-Uncertainty OPTIONAL,
    nodeBClockDrift NodeB-ClockDrift OPTIONAL,
    gps-TOW-AssistList GPS-TOW-AssistList OPTIONAL
}

UE-Positioning-GPS-UTC-Model ::= SEQUENCE {
    a1 BIT STRING (SIZE (24)),
    a0 BIT STRING (SIZE (32)),
    t-ot BIT STRING (SIZE (8)),
    wn-t BIT STRING (SIZE (8)),
    delta-t-LS BIT STRING (SIZE (8)),
    wn-lsf BIT STRING (SIZE (8)),
    dn BIT STRING (SIZE (8)),
    delta-t-LSF BIT STRING (SIZE (8))
}

UE-Positioning-IPDL-Parameters ::= SEQUENCE {
    ip-Spacing IP-Spacing,
    ip-Length IP-Length,
    ip-Offset INTEGER (0..9),
    seed INTEGER (0..63),
    burstModeParameters BurstModeParameters OPTIONAL
}

UE-Positioning-IPDL-Parameters-r4 ::= SEQUENCE {
    modeSpecificInfo CHOICE {
        fdd SEQUENCE {
            ip-Spacing IP-Spacing,
            ip-Length IP-Length,

```

```

        ip-Offset                INTEGER (0..9),
        seed                     INTEGER (0..63)
    },
    tdd                          SEQUENCE {
        ip-Spacing-TDD           IP-Spacing-TDD,
        ip-slot                  INTEGER (0..14),
        ip-Start                 INTEGER (0..4095),
        ip-PCCPCG                IP-PCCPCH-r4          OPTIONAL
    }
},
burstModeParameters            BurstModeParameters
}

UP-IPDL-Parameters-TDD-r4-ext ::= SEQUENCE {
    ip-Spacing                   IP-Spacing-TDD,
    ip-slot                      INTEGER (0..14),
    ip-Start                     INTEGER (0..4095),
    ip-PCCPCG                    IP-PCCPCH-r4          OPTIONAL,
    burstModeParameters          BurstModeParameters
}

UE-Positioning-MeasuredResults ::= SEQUENCE {
    ue-positioning-OTDOA-Measurement    UE-Positioning-OTDOA-Measurement
    OPTIONAL,
    ue-positioning-PositionEstimateInfo UE-Positioning-PositionEstimateInfo
    OPTIONAL,
    ue-positioning-GPS-Measurement      UE-Positioning-GPS-MeasurementResults
    OPTIONAL,
    ue-positioning-Error                UE-Positioning-Error
    OPTIONAL
}

UE-Positioning-Measurement ::= SEQUENCE {
    ue-positioning-ReportingQuantity    UE-Positioning-ReportingQuantity,
    reportCriteria                      UE-Positioning-ReportCriteria,
    ue-positioning-OTDOA-AssistanceData UE-Positioning-OTDOA-AssistanceData
    OPTIONAL,
    ue-positioning-GPS-AssistanceData   UE-Positioning-GPS-AssistanceData
    OPTIONAL
}

UE-Positioning-Measurement-r4 ::= SEQUENCE {
    ue-positioning-ReportingQuantity    UE-Positioning-ReportingQuantity,
    reportCriteria                      UE-Positioning-ReportCriteria,
    ue-positioning-OTDOA-AssistanceData UE-Positioning-OTDOA-AssistanceData-r4
    OPTIONAL,
    ue-positioning-GPS-AssistanceData   UE-Positioning-GPS-AssistanceData
    OPTIONAL
}

UE-Positioning-MeasurementEventResults ::= CHOICE {
    event7a    UE-Positioning-PositionEstimateInfo,
    event7b    UE-Positioning-OTDOA-Measurement,
    event7c    UE-Positioning-GPS-MeasurementResults
}

UE-Positioning-MeasurementInterval ::= ENUMERATED {
    e5, e15, e60, e300,
    e900, e1800, e3600, e7200 }

UE-Positioning-MethodType ::= ENUMERATED {
    ue-Assisted,
    ue-Based,
    ue-BasedPreferred,
    ue-AssistedPreferred }

UE-Positioning-OTDOA-AssistanceData ::= SEQUENCE {
    ue-positioning-OTDOA-ReferenceCellInfo    UE-Positioning-OTDOA-ReferenceCellInfo
    OPTIONAL,
    ue-positioning-OTDOA-NeighbourCellList    UE-Positioning-OTDOA-NeighbourCellList
    OPTIONAL
}

UE-Positioning-OTDOA-AssistanceData-r4 ::= SEQUENCE {
    ue-positioning-OTDOA-ReferenceCellInfo-r4    UE-Positioning-OTDOA-ReferenceCellInfo-r4
    OPTIONAL,
    ue-positioning-OTDOA-NeighbourCellList-r4    UE-Positioning-OTDOA-NeighbourCellList-r4
    OPTIONAL
}

```

```

}
UE-Positioning-OTDOA-Measurement ::= SEQUENCE {
  sfn INTEGER (0..4095),
  modeSpecificInfo CHOICE {
    fdd SEQUENCE {
      referenceCellIdentity PrimaryCPICH-Info,
      ue-RX-TX-TimeDifferenceType2 UE-RX-TX-TimeDifferenceType2
    },
    tdd SEQUENCE {
      referenceCellIdentity CellParametersID
    }
  },
  neighbourList NeighbourList OPTIONAL
}
UE-Positioning-OTDOA-NeighbourCellInfo ::= SEQUENCE {
  modeSpecificInfo CHOICE {
    fdd SEQUENCE {
      primaryCPICH-Info PrimaryCPICH-Info
    },
    tdd SEQUENCE {
      cellAndChannelIdentity CellAndChannelIdentity
    }
  },
  frequencyInfo FrequencyInfo OPTIONAL,
  ue-positioning-IPDL-Parameters UE-Positioning-IPDL-Parameters OPTIONAL,
  sfn-SFN-RelTimeDifference SFN-SFN-RelTimeDifference1,
  sfn-SFN-Drift SFN-SFN-Drift OPTIONAL,
  searchWindowSize OTDOA-SearchWindowSize,
  positioningMode CHOICE {
    ueBased SEQUENCE {
      relativeNorth INTEGER (-20000..20000) OPTIONAL,
      relativeEast INTEGER (-20000..20000) OPTIONAL,
      relativeAltitude INTEGER (-4000..4000) OPTIONAL,
      fineSFN-SFN FineSFN-SFN,
      -- actual value = (IE value * 0.0625) + 876
      roundTripTime INTEGER (0.. 32766) OPTIONAL
    },
    ueAssisted SEQUENCE {}
  }
}
UE-Positioning-OTDOA-NeighbourCellInfo-r4 ::= SEQUENCE {
  modeSpecificInfo CHOICE {
    fdd SEQUENCE {
      primaryCPICH-Info PrimaryCPICH-Info
    },
    tdd SEQUENCE {
      cellAndChannelIdentity CellAndChannelIdentity
    }
  },
  frequencyInfo FrequencyInfo OPTIONAL,
  ue-positioning-IPDL-Parameters UE-Positioning-IPDL-Parameters-r4 OPTIONAL,
  sfn-SFN-RelTimeDifference SFN-SFN-RelTimeDifference1,
  sfn-SFN-Drift INTEGER (0..30),
  searchWindowSize OTDOA-SearchWindowSize,
  positioningMode CHOICE {
    ueBased SEQUENCE {
      relativeNorth INTEGER (-20000..20000) OPTIONAL,
      relativeEast INTEGER (-20000..20000) OPTIONAL,
      relativeAltitude INTEGER (-4000..4000) OPTIONAL,
      fineSFN-SFN FineSFN-SFN OPTIONAL,
      -- actual value = (IE value * 0.0625) + 876
      roundTripTime INTEGER (0.. 32766) OPTIONAL
    },
    ueAssisted SEQUENCE {}
  }
}
UE-Positioning-OTDOA-NeighbourCellList ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
  UE-Positioning-OTDOA-NeighbourCellInfo
UE-Positioning-OTDOA-NeighbourCellList-r4 ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
  UE-Positioning-OTDOA-NeighbourCellInfo-r4

```

```

UE-Positioning-OTDOA-Quality ::=
    stdResolution                BIT STRING (SIZE (2)),
    numberOfOTDOA-Measurements   BIT STRING (SIZE (3)),
    stdOfOTDOA-Measurements      BIT STRING (SIZE (5))
}

UE-Positioning-OTDOA-ReferenceCellInfo ::=
    sfm                          INTEGER (0..4095)
    OPTIONAL,
    modeSpecificInfo CHOICE {
        fdd                      SEQUENCE {
            primaryCPICH-Info    PrimaryCPICH-Info
        },
        tdd                      SEQUENCE {
            cellAndChannelIdentity CellAndChannelIdentity
        }
    },
    frequencyInfo                FrequencyInfo OPTIONAL,
    positioningMode CHOICE {
        ueBased                  SEQUENCE {
            cellPosition          ReferenceCellPosition OPTIONAL,
            -- actual value = (IE value * 0.0625) + 876
            roundTripTime        INTEGER (0..32766) OPTIONAL
        },
        ueAssisted              SEQUENCE {}
    },
    ue-positioning-IPDL-Parameters UE-Positioning-IPDL-Parameters OPTIONAL
}

UE-Positioning-OTDOA-ReferenceCellInfo-r4 ::=
    sfm                          INTEGER (0..4095)
    OPTIONAL,
    modeSpecificInfo CHOICE {
        fdd                      SEQUENCE {
            primaryCPICH-Info    PrimaryCPICH-Info
        },
        tdd                      SEQUENCE {
            cellAndChannelIdentity CellAndChannelIdentity
        }
    },
    frequencyInfo                FrequencyInfo OPTIONAL,
    positioningMode CHOICE {
        ueBased                  SEQUENCE {
            cellPosition          ReferenceCellPosition OPTIONAL,
            -- actual value = (IE value * 0.0625) + 876
            roundTripTime        INTEGER (0..32766) OPTIONAL
        },
        ueAssisted              SEQUENCE {}
    },
    ue-positioning-IPDL-Parameters UE-Positioning-IPDL-Parameters-r4 OPTIONAL
}

UE-Positioning-PositionEstimateInfo ::=
    modeSpecificInfo            CHOICE {
        fdd                      SEQUENCE {
            referenceIdentity     PrimaryCPICH-Info OPTIONAL
        },
        tdd                      SEQUENCE {
            referenceIdentity     CellParametersID OPTIONAL
        }
    },
    referenceSFN                ReferenceSFN,
    gps-tow-lmsec               GPS-TOW-lmsec OPTIONAL,
    gps-tow-rem-usec            GPS-TOW-rem-usec OPTIONAL,
    positionEstimate            PositionEstimate
}

UE-Positioning-ReportCriteria ::=
    ue-positioning-ReportingCriteria UE-Positioning-EventParamList,
    periodicalReportingCriteria    PeriodicalReportingCriteria,
    noReporting                    NULL
}

UE-Positioning-ReportingQuantity ::=
    methodType                  UE-Positioning-MethodType,
    positioningMethod            PositioningMethod,
    responseTime                 UE-Positioning-ResponseTime,
    accuracy                     UE-Positioning-Accuracy OPTIONAL,

```



```

    gps-TimingOfCellWanted          BOOLEAN,
    multipleSets                    BOOLEAN,
    additionalAssistanceDataReq     BOOLEAN,
    environmentCharacterisation     EnvironmentCharacterisation    OPTIONAL
}

UE-Positioning-ResponseTime ::=
    ENUMERATED {
        s1, s2, s4, s8, s16,
        s32, s64, s128 }

UTRA-CarrierRSSI ::=
    INTEGER (0..76)

UTRAN-ReferenceTime ::=
    SEQUENCE {
        gps-tow-lmsec              GPS-TOW-lmsec,
        gps-tow-rem-usec           GPS-TOW-rem-usec,
        modeSpecificInfo          CHOICE {
            fdd                    SEQUENCE {
                referenceIdentity   PrimaryCPICH-Info    OPTIONAL
            },
            tdd                    SEQUENCE {
                referenceIdentity   CellParametersID    OPTIONAL
            }
        },
        sfn                        INTEGER (0..4095)
    }

VarianceOfRLC-BufferPayload ::=
    ENUMERATED {
        plv0, plv4, plv8, plv16, plv32, plv64,
        plv128, plv256, plv512, plv1024,
        plv2k, plv4k, plv8k, plv16k }

-- Actual value = IE value * 0.1
W ::=
    INTEGER (0..20)

-- *****
--
--     OTHER INFORMATION ELEMENTS (10.3.8)
--
-- *****

BCC ::=
    INTEGER (0..7)

BCCH-ModificationInfo ::=
    SEQUENCE {
        mib-ValueTag              MIB-ValueTag,
        bcch-ModificationTime     BCCH-ModificationTime    OPTIONAL
    }

-- Actual value = IE value * 8
BCCH-ModificationTime ::=
    INTEGER (0..511)

BSIC ::=
    SEQUENCE {
        ncc                        NCC,
        bcc                        BCC
    }

CBS-DRX-Level1Information ::=
    SEQUENCE {
        ctch-AllocationPeriod     INTEGER (1..256),
        cbs-FrameOffset          INTEGER (0..255)
    }

CDMA2000-Message ::=
    SEQUENCE {
        msg-Type                  BIT STRING (SIZE (8)),
        payload                   BIT STRING (SIZE (1..512))
    }

CDMA2000-MessageList ::=
    SEQUENCE (SIZE (1..maxInterSysMessages)) OF
        CDMA2000-Message

CDMA2000-UMTS-Frequency-List ::=
    SEQUENCE (SIZE (1..maxNumCDMA2000Freqs)) OF
        FrequencyInfoCDMA2000

CellValueTag ::=
    INTEGER (1..4)

--Actual value = 2^(IE value)
ExpirationTimeFactor ::=
    INTEGER (1..8)

FDD-UMTS-Frequency-List ::=
    SEQUENCE (SIZE (1..maxNumFDDFreqs)) OF

```

```

FrequencyInfoFDD
FrequencyInfoCDMA2000 ::= SEQUENCE {
    band-Class      BIT STRING (SIZE (5)),
    cdma-Freq       BIT STRING (SIZE(11))
}
GSM-BA-Range ::= SEQUENCE {
    gsmLowRangeUARFCN    UARFCN,
    gsmUpRangeUARFCN    UARFCN
}
GSM-BA-Range-List ::= SEQUENCE (SIZE (1..maxNumGSMFreqRanges)) OF
    GSM-BA-Range
GSM-Classmark2 ::= OCTET STRING (SIZE (5))
GSM-Classmark3 ::= OCTET STRING (SIZE (1..32))
GSM-MessageList ::= SEQUENCE (SIZE (1..maxInterSysMessages)) OF
    BIT STRING (SIZE (1..512))
GsmSecurityCapability ::= BIT STRING {
    a5-7(0),
    a5-6(1),
    a5-5(2),
    a5-4(3),
    a5-3(4),
    a5-2(5),
    a5-1(6)
} (SIZE (7))
IdentificationOfReceivedMessage ::= SEQUENCE {
    rrc-TransactionIdentifier    RRC-TransactionIdentifier,
    receivedMessageType          ReceivedMessageType
}
InterRAT-ChangeFailureCause ::= CHOICE {
    configurationUnacceptable    NULL,
    physicalChannelFailure      NULL,
    protocolError                ProtocolErrorInformation,
    unspecified                  NULL,
    spare1                       NULL,
    spare2                       NULL,
    spare3                       NULL
}
InterRAT-UE-RadioAccessCapability ::= CHOICE {
    gsm                           SEQUENCE {
        gsm-Classmark2          GSM-Classmark2,
        gsm-Classmark3          GSM-Classmark3
    },
    cdma2000                      SEQUENCE {
        cdma2000-MessageList    CDMA2000-MessageList
    }
}
InterRAT-UE-RadioAccessCapabilityList ::= SEQUENCE (SIZE(1..maxInterSysMessages)) OF
    InterRAT-UE-RadioAccessCapability
InterRAT-UE-SecurityCapability ::= CHOICE {
    gsm                           SEQUENCE {
        gsmSecurityCapability    GsmSecurityCapability
    }
}
InterRAT-UE-SecurityCapList ::= SEQUENCE (SIZE(1..maxInterSysMessages)) OF
    InterRAT-UE-SecurityCapability
InterRAT-HO-FailureCause ::= CHOICE {
    configurationUnacceptable    NULL,
    physicalChannelFailure      NULL,
    protocolError                ProtocolErrorInformation,
    interRAT-ProtocolError      NULL,
    unspecified                  NULL,
    spare1                       NULL,
    spare2                       NULL,
    spare3                       NULL,
}

```

```

    spare4                                NULL
}

InterRATMessage ::=                       CHOICE {
    gsm                                    SEQUENCE {
        gsm-MessageList                    GSM-MessageList
    },
    cdma2000                               SEQUENCE {
        cdma2000-MessageList                CDMA2000-MessageList
    }
}

MasterInformationBlock ::=                 SEQUENCE {
    mib-ValueTag                            MIB-ValueTag,
    plmn-Type                                PLMN-Type,
    -- TABULAR: The PLMN identity and ANSI-41 core network information
    -- are included in PLMN-Type.
    sibSb-ReferenceList                      SIBSb-ReferenceList,
    -- Extension mechanism for non- release99 information
    nonCriticalExtensions                     SEQUENCE {}                                OPTIONAL
}

MIB-ValueTag ::=                          INTEGER (1..8)

NCC ::=                                    INTEGER (0..7)

PLMN-ValueTag ::=                          INTEGER (1..256)

PredefinedConfigIdentityAndValueTag ::= SEQUENCE {
    predefinedConfigIdentity                  PredefinedConfigIdentity,
    predefinedConfigValueTag                  PredefinedConfigValueTag
}

ProtocolErrorInformation ::=                SEQUENCE {
    diagnosticsType                           CHOICE {
        type1                                SEQUENCE {
            protocolErrorCause                ProtocolErrorCause
        },
        spare                                NULL
    }
}

ReceivedMessageType ::=                     ENUMERATED {
    activeSetUpdate,
    cellChangeOrderFromUTRAN,
    cellUpdateConfirm,
    counterCheck,
    downlinkDirectTransfer,
    interRATHandoverCommand,
    measurementControl,
    pagingType2,
    physicalChannelReconfiguration,
    physicalSharedChannelAllocation,
    radioBearerReconfiguration,
    radioBearerRelease,
    radioBearerSetup,
    rrcConnectionRelease,
    rrcConnectionReject,
    rrcConnectionSetup,
    securityModeCommand,
    signallingConnectionRelease,
    transportChannelReconfiguration,
    transportFormatCombinationControl,
    ueCapabilityEnquiry,
    ueCapabilityInformationConfirm,
    uplinkPhysicalChannelControl,
    uraUpdateConfirm,
    utranMobilityInformation,
    assistanceDataDelivery,
    spare1, spare2, spare3, spare4,
    spare5
}

Rplmn-Information ::=                       SEQUENCE {
    gsm-BA-Range-List                         GSM-BA-Range-List    OPTIONAL,
    fdd-UMTS-Frequency-List                   FDD-UMTS-Frequency-List
OPTIONAL,

```

```

OPTIONAL,
List OPTIONAL
}

Rplmn-Information-r4 ::= SEQUENCE {
    gsm-BA-Range-List GSM-BA-Range-List OPTIONAL,
    fdd-UMTS-Frequency-List FDD-UMTS-Frequency-List OPTIONAL,
    tdd384-UMTS-Frequency-List TDD-UMTS-Frequency-List OPTIONAL,
    tdd128-UMTS-Frequency-List TDD-UMTS-Frequency-List OPTIONAL,
    cdma2000-UMTS-Frequency-List CDMA2000-UMTS-Frequency-List OPTIONAL
}

SchedulingInformation ::= SEQUENCE {
    scheduling SEQUENCE {
        segCount SegCount DEFAULT 1,
        sib-Pos CHOICE {
            -- The element name indicates the repetition period and the value
            -- (multiplied by two) indicates the position of the first segment.
            rep4 INTEGER (0..1),
            rep8 INTEGER (0..3),
            rep16 INTEGER (0..7),
            rep32 INTEGER (0..15),
            rep64 INTEGER (0..31),
            rep128 INTEGER (0..63),
            rep256 INTEGER (0..127),
            rep512 INTEGER (0..255),
            rep1024 INTEGER (0..511),
            rep2048 INTEGER (0..1023),
            rep4096 INTEGER (0..2047)
        },
        sib-PosOffsetInfo SibOFF-List OPTIONAL
    }
}

SchedulingInformationSIB ::= SEQUENCE {
    sib-Type SIB-TypeAndTag,
    scheduling SchedulingInformation
}

SchedulingInformationSIBSb ::= SEQUENCE {
    sibSb-Type SIBSb-TypeAndTag,
    scheduling SchedulingInformation
}

SegCount ::= INTEGER (1..16)

SegmentIndex ::= INTEGER (1..15)

-- Actual value = 2 * IE value
SFN-Prime ::= INTEGER (0..2047)

SIB-Data-fixed ::= BIT STRING (SIZE (222))

SIB-Data-variable ::= BIT STRING (SIZE (1..214))

SIBOccurIdentity ::= INTEGER (0..15)

SIBOccurrenceIdentityAndValueTag ::= SEQUENCE {
    sibOccurIdentity SIBOccurIdentity,
    sibOccurValueTag SIBOccurValueTag
}

SIBOccurValueTag ::= INTEGER (0..15)

SIB-ReferenceList ::= SEQUENCE (SIZE (1..maxSIB)) OF SchedulingInformationSIB

SIBSb-ReferenceList ::= SEQUENCE (SIZE (1..maxSIB)) OF SchedulingInformationSIBSb

SIB-ReferenceListFACH ::= SEQUENCE (SIZE (1..maxSIB-FACH)) OF SchedulingInformationSIB

SIB-Type ::= ENUMERATED {

```

```

masterInformationBlock,
systemInformationBlockType1,
systemInformationBlockType2,
systemInformationBlockType3,
systemInformationBlockType4,
systemInformationBlockType5,
systemInformationBlockType6,
systemInformationBlockType7,
systemInformationBlockType8,
systemInformationBlockType9,
systemInformationBlockType10,
systemInformationBlockType11,
systemInformationBlockType12,
systemInformationBlockType13,
systemInformationBlockType13-1,
systemInformationBlockType13-2,
systemInformationBlockType13-3,
systemInformationBlockType13-4,
systemInformationBlockType14,
systemInformationBlockType15,
systemInformationBlockType15-1,
systemInformationBlockType15-2,
systemInformationBlockType15-3,
systemInformationBlockType16,
systemInformationBlockType17,
systemInformationBlockType15-4,
systemInformationBlockType18,
schedulingBlock1,
schedulingBlock2,
spare1, spare2, spare3 }

SIB-TypeAndTag ::=
sysInfoType1
sysInfoType2
sysInfoType3
sysInfoType4
sysInfoType5
sysInfoType6
sysInfoType7
sysInfoType8
sysInfoType9
sysInfoType10
sysInfoType11
sysInfoType12
sysInfoType13
sysInfoType13-1
sysInfoType13-2
sysInfoType13-3
sysInfoType13-4
sysInfoType14
sysInfoType15
sysInfoType16
sysInfoType17
sysInfoType15-1
sysInfoType15-2
sysInfoType15-3
sysInfoType15-4
sysInfoType18
}

CHOICE {
PLMN-ValueTag,
CellValueTag,
CellValueTag,
CellValueTag,
CellValueTag,
CellValueTag,
NULL,
CellValueTag,
NULL,
NULL,
CellValueTag,
CellValueTag,
CellValueTag,
CellValueTag,
CellValueTag,
CellValueTag,
NULL,
CellValueTag,
PredefinedConfigIdentityAndValueTag,
NULL,
CellValueTag,
SIBOccurrenceIdentityAndValueTag,
SIBOccurrenceIdentityAndValueTag,
CellValueTag,
CellValueTag
}

SIBSb-TypeAndTag ::=
sysInfoType1
sysInfoType2
sysInfoType3
sysInfoType4
sysInfoType5
sysInfoType6
sysInfoType7
sysInfoType8
sysInfoType9
sysInfoType10
sysInfoType11
sysInfoType12
sysInfoType13
sysInfoType13-1
sysInfoType13-2
sysInfoType13-3
sysInfoType13-4
}

CHOICE {
PLMN-ValueTag,
CellValueTag,
CellValueTag,
CellValueTag,
CellValueTag,
CellValueTag,
NULL,
CellValueTag,
NULL,
NULL,
CellValueTag,
CellValueTag,
CellValueTag,
CellValueTag,
CellValueTag,
CellValueTag,
CellValueTag,
CellValueTag,
CellValueTag,
CellValueTag,
CellValueTag,
CellValueTag
}

```

```

sysInfoType14          NULL,
sysInfoType15          CellValueTag,
sysInfoType16          PredefinedConfigIdentityAndValueTag,
sysInfoType17          NULL,
sysInfoTypeSB1         CellValueTag,
sysInfoTypeSB2         CellValueTag,
sysInfoType15-1        CellValueTag,
sysInfoType15-2        SIBOccurrenceIdentityAndValueTag,
sysInfoType15-3        SIBOccurrenceIdentityAndValueTag,
sysInfoType15-4        CellValueTag,
sysInfoType18          CellValueTag
}

SibOFF ::=              ENUMERATED {
                        so2, so4, so6, so8, so10,
                        so12, so14, so16, so18,
                        so20, so22, so24, so26,
                        so28, so30, so32 }

SibOFF-List ::=        SEQUENCE (SIZE (1..15)) OF
                        SibOFF

SysInfoType1 ::=       SEQUENCE {
-- Core network IEs
  cn-CommonGSM-MAP-NAS-SysInfo  NAS-SystemInformationGSM-MAP,
  cn-DomainSysInfoList          CN-DomainSysInfoList,
-- User equipment IEs
  ue-ConnTimersAndConstants      UE-ConnTimersAndConstants      OPTIONAL,
  ue-IdleTimersAndConstants      UE-IdleTimersAndConstants      OPTIONAL,
-- Extension mechanism for non- release99 information
  nonCriticalExtensions          SEQUENCE {}                      OPTIONAL
}

SysInfoType2 ::=       SEQUENCE {
-- UTRAN mobility IEs
  ura-IdentityList              URA-IdentityList,
-- Extension mechanism for non- release99 information
  nonCriticalExtensions          SEQUENCE {}                      OPTIONAL
}

SysInfoType3 ::=       SEQUENCE {
  sib4indicator                 BOOLEAN,
-- UTRAN mobility IEs
  cellIdentity                  CellIdentity,
  cellSelectReselectInfo        CellSelectReselectInfoSIB-3-4,
  cellAccessRestriction         CellAccessRestriction,
-- Extension mechanism for non- release99 information
  nonCriticalExtensions          SEQUENCE {
    sysInfoType3-r3-r4-ext      SysInfoType3-r3-r4-ext-IEs,
    nonCriticalExtensions        SEQUENCE {}
  }
}
OPTIONAL

SysInfoType3-r3-r4-ext-IEs ::= SEQUENCE {
  mapping-LCR                   Mapping-LCR-r4
}
OPTIONAL

SysInfoType4 ::=       SEQUENCE {
-- UTRAN mobility IEs
  cellIdentity                  CellIdentity,
  cellSelectReselectInfo        CellSelectReselectInfoSIB-3-4,
  cellAccessRestriction         CellAccessRestriction,
-- Extension mechanism for non- release99 information
  nonCriticalExtensions          SEQUENCE {
    sysInfoType4-r3-r4-ext      SysInfoType4-r3-r4-ext-IEs,
    nonCriticalExtensions        SEQUENCE {}
  }
}
OPTIONAL

SysInfoType4-r3-r4-ext-IEs ::= SEQUENCE {
  mapping-LCR                   Mapping-LCR-r4
}
OPTIONAL

SysInfoType5 ::=       SEQUENCE {
  sib6indicator                 BOOLEAN,
-- Physical channel IEs
  pich-PowerOffset              PICH-PowerOffset,
  modeSpecificInfo              CHOICE {

```

```

        fdd                SEQUENCE {
            aich-PowerOffset    AICH-PowerOffset
        },
        tdd                SEQUENCE {
-- If PDSCH/PUSCH is configured for 1.28Mcps TDD, the following IEs should be absent
-- and the info included in the tdd128SpecificInfo instead.
            pusch-SysInfoList-SFN    PUSCH-SysInfoList-SFN        OPTIONAL,
            pdsch-SysInfoList-SFN    PDSCH-SysInfoList-SFN        OPTIONAL,
            openLoopPowerControl-TDD    OpenLoopPowerControl-TDD
        }
    },
    primaryCCPCH-Info            PrimaryCCPCH-Info                OPTIONAL,
    prach-SystemInformationList    PRACH-SystemInformationList,
    sCCPCH-SystemInformationList    SCCPCH-SystemInformationList,
    cbs-DRX-Level1Information        CBS-DRX-Level1Information        OPTIONAL,
-- Conditional on any of the CTCH indicator IEs in
-- sCCPCH-SystemInformationList
-- Extension mechanism for non- release99 information
    nonCriticalExtensions        SEQUENCE {
        sysInfoType5-r3-r4-ext        SysInfoType5-r3-r4-ext-IEs,
-- Extension mechanism for non- rel-4 information
        nonCriticalExtensions        SEQUENCE {}                OPTIONAL
    }
}

SysInfoType5-r3-r4-ext-IEs ::= SEQUENCE {
    pNBSCCH-Allocation-r4            PNBSCCH-Allocation-r4            OPTIONAL,
-- In case of TDD, the following IE is included instead of the
-- IE up-IPDL-Parameter in up-OTDOA-AssistanceData.
    openLoopPowerControl-IPDL-TDD    OpenLoopPowerControl-IPDL-TDD-r4    OPTIONAL,
-- If SysInfoType5 is sent to describe a 1.28Mcps TDD cell, the IE PRACH-RACH-Info included in
-- PRACH-SystemInformationList shall be ignored, and the following IE shall describe
-- the PRACH-RACH-Information.
    prach-RACH-Info-LCR                PRACH-RACH-Info-LCR-r4            OPTIONAL,
-- If SysInfoType5 is sent to describe a 1.28Mcps TDD cell, the IE PRACH-Partitioning in
-- PRACH-SystemInformationList shall be absent, and the following IE shall describe
-- the PRACH-Partitioning.
    prach-Partitioning-LCR            PRACH-Partitioning-LCR-r4        OPTIONAL,
-- If SysInfoType5 is sent to describe a 1.28Mcps TDD cell, the IE rach-TransportFormatSet in
-- PRACH-SystemInformationList shall be absent, and the following IE shall describe
-- the rach-TransportFormatSet.
    rach-TransportFormatSet-LCR        TransportFormatSet-LCR            OPTIONAL,
    tdd128SpecificInfo                SEQUENCE {
        pusch-SysInfoList-SFN        PUSCH-SysInfoList-SFN-LCR-r4    OPTIONAL,
        pdsch-SysInfoList-SFN        PDSCH-SysInfoList-SFN-LCR-r4    OPTIONAL,
        pCCPCH-LCR-Extensions        PrimaryCCPCH-Info-LCR-r4-ext    OPTIONAL,
        sCCPCH-LCR-ExtensionsList    SCCPCH-SystemInformationList-LCR-r4-ext
    }
}

SysInfoType6 ::= SEQUENCE {
-- Physical channel IEs
    pich-PowerOffset                PICH-PowerOffset,
    modeSpecificInfo                CHOICE {
        fdd                SEQUENCE {
            aich-PowerOffset        AICH-PowerOffset,
            dummy                CSICH-PowerOffset        OPTIONAL
-- This parameter dummy is not to be sent in the current version of the specification.
        },
        tdd                SEQUENCE {
-- If PDSCH/PUSCH is configured for 1.28Mcps TDD, the following IEs should be absent
-- and the info included in the tdd128SpecificInfo instead.
            pusch-SysInfoList-SFN    PUSCH-SysInfoList-SFN        OPTIONAL,
            pdsch-SysInfoList-SFN    PDSCH-SysInfoList-SFN        OPTIONAL,
            openLoopPowerControl-TDD    OpenLoopPowerControl-TDD
        }
    },
    primaryCCPCH-Info            PrimaryCCPCH-Info                OPTIONAL,
    prach-SystemInformationList    PRACH-SystemInformationList        OPTIONAL,
    sCCPCH-SystemInformationList    SCCPCH-SystemInformationList        OPTIONAL,
    cbs-DRX-Level1Information        CBS-DRX-Level1Information        OPTIONAL,
-- Conditional on any of the CTCH indicator IEs in
-- sCCPCH-SystemInformationList
-- Extension mechanism for non- release99 information
    nonCriticalExtensions        SEQUENCE {
        sysInfoType6-r3-r4-ext        SysInfoType6-r3-r4-ext-IEs,
-- Extension mechanism for non- rel-4 information
        nonCriticalExtensions        SEQUENCE {}                OPTIONAL
    }
}

```

```

    }
}

SysInfoType6-r3-r4-ext-IEs ::= SEQUENCE {
    -- This IE is present only if IPDLs are applied for TDD
    openLoopPowerControl-IPDL-TDD    OpenLoopPowerControl-IPDL-TDD-r4    OPTIONAL,
    -- If SysInfoType6 is sent to describe a 1.28Mcps TDD cell, the IE PRACH-RACH-Info included in
    -- PRACH-SystemInformationList shall be ignored, and the following IE shall describe
    -- the PRACH-RACH-Information.
    prach-RACH-Info-LCR                PRACH-RACH-Info-LCR-r4                OPTIONAL,
    -- If SysInfoType6 is sent to describe a 1.28Mcps TDD cell, the IE PRACH-Partitioning in
    -- PRACH-SystemInformationList shall be absent, and the following IE shall describe
    -- the PRACH-Partitioning.
    prach-Partitioning-LCR            PRACH-Partitioning-LCR-r4            OPTIONAL,
    -- If SysInfoType6 is sent to describe a 1.28Mcps TDD cell, the IE rach-TransportFormatSet in
    -- PRACH-SystemInformationList shall be absent, and the following IE shall describe
    -- the rach-TransportFormatSet.
    rach-TransportFormatSet-LCR        TransportFormatSet-LCR        OPTIONAL,
    tddl28SpecificInfo                SEQUENCE {
        pusch-SysInfoList-SFN          PUSCH-SysInfoList-SFN-LCR-r4    OPTIONAL,
        pdsch-SysInfoList-SFN          PDSCH-SysInfoList-SFN-LCR-r4    OPTIONAL,
        pCCPCH-LCR-Extensions          PrimaryCCPCH-Info-LCR-r4-ext    OPTIONAL,
        sCCPCH-LCR-ExtensionsList      SCCPCH-SystemInformationList-LCR-r4-ext OPTIONAL
    }
}

SysInfoType7 ::= SEQUENCE {
    -- Physical channel IEs
    modeSpecificInfo                  CHOICE {
        fdd                            SEQUENCE {
            ul-Interference            UL-Interference
        },
        tdd                            NULL
    },
    prach-Information-SIB5-List        DynamicPersistenceLevelList,
    prach-Information-SIB6-List        DynamicPersistenceLevelList    OPTIONAL,
    expirationTimeFactor              ExpirationTimeFactor            OPTIONAL,
    -- Extension mechanism for non- release99 information
    nonCriticalExtensions              SEQUENCE {}                    OPTIONAL
}

SysInfoType8 ::= SEQUENCE {
    -- User equipment IEs
    cpch-Parameters                    CPCH-Parameters,
    -- Physical channel IEs
    cpch-SetInfoList                   CPCH-SetInfoList,
    csich-PowerOffset                  CSICH-PowerOffset,
    -- Extension mechanism for non- release99 information
    nonCriticalExtensions              SEQUENCE {}                    OPTIONAL
}

SysInfoType9 ::= SEQUENCE {
    -- Physical channel IEs
    cpch-PersistenceLevelsList         CPCH-PersistenceLevelsList,
    -- Extension mechanism for non- release99 information
    nonCriticalExtensions              SEQUENCE {}                    OPTIONAL
}

SysInfoType10 ::= SEQUENCE {
    -- User equipment IEs
    drac-SysInfoList                   DRAC-SysInfoList,
    -- Extension mechanism for non- release99 information
    nonCriticalExtensions              SEQUENCE {}                    OPTIONAL
}

SysInfoType11 ::= SEQUENCE {
    sib12indicator                     BOOLEAN,
    -- Measurement IEs
    fach-MeasurementOccasionInfo       FACH-MeasurementOccasionInfo    OPTIONAL,
    measurementControlSysInfo          MeasurementControlSysInfo,
    -- Extension mechanism for non- release99 information
    nonCriticalExtensions              SEQUENCE {
        sysInfoType11-r3-r4-ext        SysInfoType11-r3-r4-ext-IEs,
        nonCriticalExtensions          SEQUENCE {}                    OPTIONAL
    }
}

SysInfoType11-r3-r4-ext-IEs ::= SEQUENCE {

```



```

    fach-MeasurementOccasionInfo-LCR-Ext    FACH-MeasurementOccasionInfo-LCR-r4-ext OPTIONAL,
    measurementControlSysInfo-LCR          MeasurementControlSysInfo-LCR-r4-ext
}

SysInfoType12 ::=                               SEQUENCE {
-- Measurement IEs
    fach-MeasurementOccasionInfo    FACH-MeasurementOccasionInfo    OPTIONAL,
    measurementControlSysInfo        MeasurementControlSysInfo,
-- Extension mechanism for non- release99 information
    nonCriticalExtensions            SEQUENCE {
        sysInfoType12-r3-r4-ext    SysInfoType12-r3-r4-ext-IEs,
        nonCriticalExtensions        SEQUENCE {}                    OPTIONAL
    }
}

SysInfoType12-r3-r4-ext-IEs ::= SEQUENCE {
    fach-MeasurementOccasionInfo-LCR-Ext    FACH-MeasurementOccasionInfo-LCR-r4-ext OPTIONAL,
    measurementControlSysInfo-LCR          MeasurementControlSysInfo-LCR-r4-ext
}

SysInfoType13 ::=                               SEQUENCE {
-- Core network IEs
    cn-DomainSysInfoList            CN-DomainSysInfoList,
-- User equipment IEs
    ue-IdleTimersAndConstants        UE-IdleTimersAndConstants    OPTIONAL,
    capabilityUpdateRequirement      CapabilityUpdateRequirement    OPTIONAL,
-- Extension mechanism for non- release99 information
    nonCriticalExtensions            SEQUENCE {
        sysInfoType13-r3-r4-ext    SysInfoType13-r3-r4-ext-IEs,
-- Extension mechanism for non- release99 information
        nonCriticalExtensions        SEQUENCE {}                    OPTIONAL
    }
}

SysInfoType13-r3-r4-ext-IEs ::= SEQUENCE {
    capabilityUpdateRequirement-r4Ext    CapabilityUpdateRequirement-r4-ext    OPTIONAL
}

SysInfoType13-1 ::=                               SEQUENCE {
-- ANSI-41 IEs
    ansi-41-RAND-Information          ANSI-41-RAND-Information,
-- Extension mechanism for non- release99 information
    nonCriticalExtensions            SEQUENCE {}                    OPTIONAL
}

SysInfoType13-2 ::=                               SEQUENCE {
-- ANSI-41 IEs
    ansi-41-UserZoneID-Information    ANSI-41-UserZoneID-Information,
-- Extension mechanism for non- release99 information
    nonCriticalExtensions            SEQUENCE {}                    OPTIONAL
}

SysInfoType13-3 ::=                               SEQUENCE {
-- ANSI-41 IEs
    ansi-41-PrivateNeighbourListInfo  ANSI-41-PrivateNeighbourListInfo,
-- Extension mechanism for non- release99 information
    nonCriticalExtensions            SEQUENCE {}                    OPTIONAL
}

SysInfoType13-4 ::=                               SEQUENCE {
-- ANSI-41 IEs
    ansi-41-GlobalServiceRedirectInfo  ANSI-41-GlobalServiceRedirectInfo,
-- Extension mechanism for non- release99 information
    nonCriticalExtensions            SEQUENCE {}                    OPTIONAL
}

SysInfoType14 ::=                               SEQUENCE {
-- Physical channel IEs
    individualTS-InterferenceList      IndividualTS-InterferenceList,
    expirationTimeFactor                ExpirationTimeFactor    OPTIONAL,
-- Extension mechanism for non- release99 information
    nonCriticalExtensions            SEQUENCE {}                    OPTIONAL
}

SysInfoType15 ::=                               SEQUENCE {
-- Measurement IEs

```

```

    ue-positioning-GPS-CipherParameters      UE-Positioning-CipherParameters      OPTIONAL,
    ue-positioning-GPS-ReferenceLocation     ReferenceLocation,
    ue-positioning-GPS-ReferenceTime         UE-Positioning-GPS-ReferenceTime,

    ue-positioning-GPS-Real-timeIntegrity   BadSatList                            OPTIONAL,
-- Extension mechanism for non- release99 information
    nonCriticalExtensions                    SEQUENCE {
        sysInfoType15-r3-r4-ext             SysInfoType15-r3-r4-ext-IEs,
-- Extension mechanism for non- release4 information
        nonCriticalExtensions                SEQUENCE {}                OPTIONAL
    }
}

SysInfoType15-r3-r4-ext-IEs ::= SEQUENCE {
    up-IPDL-Parameters-TDD                   UP-IPDL-Parameters-TDD-r4-ext        OPTIONAL
}

SysInfoType15-1 ::= SEQUENCE {
-- DGPS corrections
    ue-positioning-GPS-DGPS-Corrections     UE-Positioning-GPS-DGPS-Corrections,

-- Extension mechanism for non- release99 information
    nonCriticalExtensions                    SEQUENCE {}                OPTIONAL
}

SysInfoType15-2 ::= SEQUENCE {
-- Ephemeris and clock corrections
    transmissionTOW                          INTEGER (0..604799),
    satID                                     SatID,
    ephemerisParameter                       EphemerisParameter,

-- Extension mechanism for non- release99 information
    nonCriticalExtensions                    SEQUENCE {}                OPTIONAL
}

SysInfoType15-3 ::= SEQUENCE {
-- Almanac and other data
    transmissionTOW                          INTEGER (0.. 604799),
    ue-positioning-GPS-Almanac                UE-Positioning-GPS-Almanac
OPTIONAL,
    ue-positioning-GPS-IonosphericModel      UE-Positioning-GPS-IonosphericModel
OPTIONAL,
    ue-positioning-GPS-UTC-Model             UE-Positioning-GPS-UTC-Model
OPTIONAL,
    satMask                                  BIT STRING (SIZE (1..32))          OPTIONAL,
    lsbTOW                                   BIT STRING (SIZE (8))              OPTIONAL,
-- Extension mechanism for non- release99 information
    nonCriticalExtensions                    SEQUENCE {}                OPTIONAL
}

SysInfoType15-4 ::= SEQUENCE {
-- Measurement IEs
    ue-positioning-OTDOA-CipherParameters    UE-Positioning-CipherParameters    OPTIONAL,
    ue-positioning-OTDOA-AssistanceData      UE-Positioning-OTDOA-AssistanceData,
-- Extension mechanism for non- release99 information
    nonCriticalExtensions                    SEQUENCE {}                OPTIONAL
}

SysInfoType16 ::= SEQUENCE {
-- Radio bearer IEs
    preDefinedRadioConfiguration            PreDefRadioConfiguration,
-- Extension mechanism for non- release99 information
    nonCriticalExtensions                    SEQUENCE {}                OPTIONAL
}

SysInfoType17 ::= SEQUENCE {
-- Physical channel IEs
-- If PDSCH/PUSCH is configured for 1.28Mcps TDD, the following IEs should be absent
-- and the info included in the tdd128SpecificInfo instead.
    pusch-SysInfoList                       PUSCH-SysInfoList                  OPTIONAL,
    pdsch-SysInfoList                       PDSCH-SysInfoList                  OPTIONAL,
-- Extension mechanism for non- release99 information
    nonCriticalExtensions                    SEQUENCE {
        sysInfoType17-r3-r4-ext             SysInfoType17-r3-r4-ext-IEs,
        nonCriticalExtensions                SEQUENCE {}                OPTIONAL
    }
}

```

```

SysInfoType17-r3-r4-ext-IEs ::= SEQUENCE {
    tdd128SpecificInfo          SEQUENCE {
        pusch-SysInfoList      PUSCH-SysInfoList-LCR-r4      OPTIONAL,
        pdsch-SysInfoList      PDSCH-SysInfoList-LCR-r4      OPTIONAL,
    }
}

SysInfoType18 ::=
    SEQUENCE {
        idleModePLMNIdentities  PLMNIdentitiesOfNeighbourCells  OPTIONAL,
        connectedModePLMNIdentities PLMNIdentitiesOfNeighbourCells  OPTIONAL,
        -- Extension mechanism for non- release99 information
        nonCriticalExtensions    SEQUENCE {}      OPTIONAL
    }

SysInfoTypeSB1 ::=
    SEQUENCE {
        -- Other IEs
        sib-ReferenceList        SIB-ReferenceList,
        -- Extension mechanism for non- release99 information
        nonCriticalExtensions    SEQUENCE {}      OPTIONAL
    }

SysInfoTypeSB2 ::=
    SEQUENCE {
        -- Other IEs
        sib-ReferenceList        SIB-ReferenceList,
        -- Extension mechanism for non- release99 information
        nonCriticalExtensions    SEQUENCE {}      OPTIONAL
    }

TDD-UMTS-Frequency-List ::=
    SEQUENCE (SIZE (1..maxNumTDDFreqs)) OF
        FrequencyInfoTDD

-- *****
--
--     ANSI-41 INFORMATION ELEMENTS (10.3.9)
--
-- *****

ANSI-41-GlobalServiceRedirectInfo ::= ANSI-41-NAS-Parameter
ANSI-41-PrivateNeighbourListInfo ::= ANSI-41-NAS-Parameter
ANSI-41-RAND-Information ::= ANSI-41-NAS-Parameter
ANSI-41-UserZoneID-Information ::= ANSI-41-NAS-Parameter
ANSI-41-NAS-Parameter ::= BIT STRING (SIZE (1..2048))

Min-P-REV ::= BIT STRING (SIZE (8))

NAS-SystemInformationANSI-41 ::= ANSI-41-NAS-Parameter
NID ::= BIT STRING (SIZE (16))

P-REV ::= BIT STRING (SIZE (8))

SID ::= BIT STRING (SIZE (15))

END

```

## CHANGE REQUEST

⌘ **25.331 CR 970** ⌘ ev **-** ⌘ Current version: **4.1.0** ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

**Proposed change affects:** ⌘ (U)SIM  ME/UE  Radio Access Network  Core Network

<b>Title:</b>	⌘ Correction of IPDL parameters for TDD enhancements in ASN.1 description		
<b>Source:</b>	⌘ TSG-RAN WG2		
<b>Work item code:</b>	⌘ LCS1-UEpos-enh	<b>Date:</b>	⌘ 25.06.01
<b>Category:</b>	⌘ <b>F</b>	<b>Release:</b>	⌘ R99
	Use <u>one</u> of the following categories:		Use <u>one</u> of the following releases:
	<b>F</b> (correction)	<b>R96</b> (Release 1996)	<b>2</b> (GSM Phase 2)
	<b>A</b> (corresponds to a correction in an earlier release)	<b>R97</b> (Release 1997)	
	<b>B</b> (addition of feature),	<b>R98</b> (Release 1998)	
	<b>C</b> (functional modification of feature)	<b>R99</b> (Release 1999)	
	<b>D</b> (editorial modification)	<b>REL-4</b> (Release 4)	
	Detailed explanations of the above categories can be found in 3GPP <a href="http://www.3gpp.org/Specs/CRs.htm">TR 21.900</a> .	<b>REL-5</b> (Release 5)	

<b>Reason for change:</b>	⌘ When sending IPDL parameters for TDD in release 4 in the non-critical extensions of ASSISTANCE DATA DELIVERY, MEASUREMENT CONTROL messages or System Information, the parameters could only be sent once for the reference cell.  In order to enable UTRAN to sent IPDL configuration of neighbour cells the non-critical extension has to be changed.
<b>Summary of change:</b>	⌘ Changes of the ASN.1 regarding IPDLs for TDD
<b>Consequences if not approved:</b>	⌘ IPDL configuration for TDD could only be sent to the UE for the reference cell, but not for neighbour cells.

<b>Clauses affected:</b>	⌘ 11.2; 11.3	
<b>Other specs affected:</b>	⌘ <input type="checkbox"/> Other core specifications	⌘ <input type="checkbox"/>
	<input type="checkbox"/> Test specifications	
	<input type="checkbox"/> O&M Specifications	
<b>Other comments:</b>	⌘	

### How to create CRs using this form:

Comprehensive information and tips about how to create CRs can be found at: [http://www.3gpp.org/3G\\_Specs/CRs.htm](http://www.3gpp.org/3G_Specs/CRs.htm). Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be

downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.

- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

```

-- *****
--
-- Assistance Data Delivery
--
-- *****

AssistanceDataDelivery ::= CHOICE {
    r3 SEQUENCE {
        assistanceDataDelivery-r3 AssistanceDataDelivery-r3-IEs,
        nonCriticalExtensions SEQUENCE {
            assistanceDataDelivery-r3-r4-ext
            nonCriticalExtensions SEQUENCE {} OPTIONAL
        } OPTIONAL
    },
    later-than-r3 SEQUENCE {
        rrc-TransactionIdentifier RRC-TransactionIdentifier,
        criticalExtensions SEQUENCE {}
    }
}

AssistanceDataDelivery-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier RRC-TransactionIdentifier,
    -- Measurement Information Elements
    ue-positioning-GPS-AssistanceData UE-Positioning-GPS-AssistanceData OPTIONAL,
    ue-positioning-OTDOA-AssistanceData UE-Positioning-OTDOA-AssistanceData
}

AssistanceDataDelivery-r3-r4-ext-IEs ::= SEQUENCE {

    -- In case of TDD, the following IE is included instead of the IE
    up-IPDL-Parameters-in-up-OTDOA-AssistanceData
    ue-Positioning-OTDOA-AssistanceData-r4ext UE-Positioning-OTDOA-AssistanceData-r4ext
    OPTIONAL
    up-IpdL-Parameters-TDD UP-IPDL-Parameters-TDD-r4-ext OPTIONAL

}

-- *****
--
-- MEASUREMENT CONTROL
--
-- *****

MeasurementControl ::= CHOICE {
    r3 SEQUENCE {
        measurementControl-r3 MeasurementControl-r3-IEs,
        nonCriticalExtensions SEQUENCE {
            measurementControl-r3-r4-ext MeasurementControl-r3-r4-ext-IEs,
            nonCriticalExtensions SEQUENCE {} OPTIONAL
        } OPTIONAL
    },
    criticalExtensions CHOICE {
        r4 SEQUENCE {
            measurementControl-r4 MeasurementControl-r4-IEs,
            nonCriticalExtensions SEQUENCE {} OPTIONAL
        },
        criticalExtensions SEQUENCE {}
    }
}

MeasurementControl-r3-IEs ::= SEQUENCE {
    -- User equipment IEs
    rrc-TransactionIdentifier RRC-TransactionIdentifier,
    -- Measurement IEs
    measurementIdentity MeasurementIdentity,
    measurementCommand MeasurementCommand,
    -- TABULAR: The measurement type is included in MeasurementCommand.
    measurementReportingMode MeasurementReportingMode OPTIONAL,
    additionalMeasurementList AdditionalMeasurementID-List OPTIONAL,
}

```

```

-- Physical channel IEs
    dpch-CompressedModeStatusInfo    DPCH-CompressedModeStatusInfo    OPTIONAL
}

MeasurementControl-r3-r4-ext-IEs ::= SEQUENCE {
    In case of TDD, the following IE is included instead of the IE
    up IPDL Parameters in up OTDOA AssistanceData
    up IpdL Parameters TDD
    ue-Positioning-OTDOA-AssistanceData-r4ext
    UP-IPDL-Parameters-TDD-r4-ext    OPTIONAL
    UE-Positioning-OTDOA-AssistanceData-r4ext    OPTIONAL
}

```

```

MeasurementControl-r4-IEs ::= SEQUENCE {
-- User equipment IEs
    rrc-TransactionIdentifier    RRC-TransactionIdentifier,
-- Measurement IEs
    measurementIdentity    MeasurementIdentity,
    measurementCommand    MeasurementCommand-r4,
    -- TABULAR: The measurement type is included in MeasurementCommand.
    measurementReportingMode    MeasurementReportingMode    OPTIONAL,
    additionalMeasurementList    AdditionalMeasurementID-List    OPTIONAL,
-- Physical channel IEs
    dpch-CompressedModeStatusInfo    DPCH-CompressedModeStatusInfo    OPTIONAL
}

```

```

-- *****
--
-- MEASUREMENT INFORMATION ELEMENTS (10.3.7)
--
-- *****

```

```

UE-Positioning-IPDL-Parameters-r4 ::= SEQUENCE {
    modeSpecificInfo    CHOICE {
        fdd    SEQUENCE {
            ip-Spacing    IP-Spacing,
            ip-Length    IP-Length,
            ip-Offset    INTEGER (0..9),
            seed    INTEGER (0..63)
        },
        tdd    SEQUENCE {
            ip-Spacing-TDD    IP-Spacing-TDD,
            ip-slot    INTEGER (0..14),
            ip-Start    INTEGER (0..4095),
            ip-PCCPCH    IP-PCCPCH-r4    OPTIONAL
        }
    },
    burstModeParameters    BurstModeParameters
}

```

```

UE-Positioning-IPDL-Parameters-TDD-r4-ext ::= SEQUENCE {
    ip-Spacing    IP-Spacing-TDD,
    ip-slot    INTEGER (0..14),
    ip-Start    INTEGER (0..4095),
    ip-PCCPCH    IP-PCCPCH-r4    OPTIONAL,
    burstModeParameters    BurstModeParameters
}

```

```

UE-Positioning-OTDOA-AssistanceData-r4ext ::= SEQUENCE {
    -- In case of TDD these IPDL parameters shall be used for the reference cell instead of
    -- IPDL Parameters in IE UE-Positioning-OTDOA-ReferenceCellInfo
    ue-Positioning-IPDL-Parameters-TDD-r4-ext    UE-Positioning-IPDL-Parameters-TDD-r4-ext    OPTIONAL
    -- These IPDL parameters shall be used for the neighbour cells in case of TDD instead of
    -- IPDL Parameters in IE UE-Positioning-OTDOA-NeighbourCellInfoList. The cells shall be
    -- listed in the same order as in IE UE-Positioning-OTDOA-NeighbourCellInfoList
    ue-Positioning-IPDL-Parameters-TDDList-r4-ext    UE-Positioning-IPDL-Parameters-TDDList-r4-
    ext    OPTIONAL
}

```

```

UE-Positioning-IPDL-Parameters-TDDList-r4-ext ::= SEQUENCE (SIZE (1..maxCellMeas)) OF
    UE-Positioning-IPDL-Parameters-TDD-r4-ext

```

```

-- *****
--
-- OTHER INFORMATION ELEMENTS (10.3.8)

```

```

--
-- *****

SysInfoType15-4 ::=                               SEQUENCE {
  -- Measurement IEs
  ue-positioning-OTDOA-CipherParameters    UE-Positioning-CipherParameters
OPTIONAL,
  ue-positioning-OTDOA-AssistanceData      UE-Positioning-OTDOA-AssistanceData,
  -- Extension mechanism for non- release99 information
  nonCriticalExtensions                    SEQUENCE {
    sysInfoType15-4-r4ext                  SysInfoType15-4-r4ext          OPTIONAL,
    nonCriticalExtensions                  SEQUENCE {}
  }
}
OPTIONAL

SysInfoType15-4-r4ext ::= SEQUENCE {
  ue-Positioning-OTDOA-AssistanceData-r4ext  UE-Positioning-OTDOA-AssistanceData-r4ext
OPTIONAL
}

```



## CHANGE REQUEST

⌘ **25.331 CR 971** ⌘ ev **r1** ⌘ Current version: **4.1.0** ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

**Proposed change affects:** ⌘ (U)SIM  ME/UE  Radio Access Network  Core Network

<b>Title:</b>	⌘ 1.28 Mcps TDD PICH, Midamble and UL timing advance control corrections		
<b>Source:</b>	⌘ TSG-RAN WG2		
<b>Work item code:</b>	⌘ LCRTDD-L23	<b>Date:</b>	⌘ 30.7.2001
<b>Category:</b>	⌘ <b>F</b>	<b>Release:</b>	⌘ REL-4
	<i>Use <u>one</u> of the following categories:</i> <b>F</b> (correction) <b>A</b> (corresponds to a correction in an earlier release) <b>B</b> (addition of feature), <b>C</b> (functional modification of feature) <b>D</b> (editorial modification) Detailed explanations of the above categories can be found in 3GPP <a href="http://www.3gpp.org/21.900">TR 21.900</a> .		<i>Use <u>one</u> of the following releases:</i> <b>2</b> (GSM Phase 2) <b>R96</b> (Release 1996) <b>R97</b> (Release 1997) <b>R98</b> (Release 1998) <b>R99</b> (Release 1999) <b>REL-4</b> (Release 4) <b>REL-5</b> (Release 5)

<b>Reason for change:</b>	⌘ 1) Procedure description on reception of UL Timing Advance Control in 1.28 Mcps TDD missing.  2) Option of "Common Midamble" is erroneously missing in Midamble Shift and burst type for 1.28 Mcps TDD. This inconsistency with WG1 is corrected. Information on channelisation codes is erroneously missing for 1.28 Mcps TDD.
<b>Summary of change:</b>	⌘ 1) Missing description added by distinguishing between 3.84 Mcps and 1.28 Mcps TDD and adding references to 25.225. 2) Common Midamble added in IE "Midamble Shift and burst type"  3) Information about channelisation codes are erroneously missing for 1.28 Mcps TDD
<b>Consequences if not approved:</b>	⌘ Procedure description on reception of IE "UL Timing Advance Control" missing in 1.28 Mcps TDD. Inconsistency with WG1 regarding Midamble Shift and burst type

<b>Clauses affected:</b>	⌘ 8.6.6.26, 10.3.6.41, 10.3.6.49, 11.3		
<b>Other specs affected:</b>	⌘ <input type="checkbox"/> Other core specifications	⌘	
	<input type="checkbox"/> Test specifications		
	<input type="checkbox"/> O&M Specifications		
<b>Other comments:</b>	⌘		

**How to create CRs using this form:**

Comprehensive information and tips about how to create CRs can be found at: [http://www.3gpp.org/3G\\_Specs/CRs.htm](http://www.3gpp.org/3G_Specs/CRs.htm). Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

### 8.6.6.26 UL Timing Advance Control (TDD only)

If the IE "UL Timing Advance Control" is present, the UE shall:

- if IE "Uplink Timing Advance Control" has the value "disabled":
  - reset timing advance to 0;
  - disable calculated timing advance following handover;
  - in case of handover:
    - start uplink transmissions in the target cell without applying timing advance;
- if IE "Uplink Timing Advance Control" has the value "enabled":
  - in case of no cell change:
    - in 3.84 Mcps TDD evaluate and apply the timing advance value for uplink transmission as indicated in IE "Uplink Timing Advance" at the CFN indicated in the IE "Activation Time";
    - in 1.28 Mcps TDD continue to use the current uplink timing
  - in case of cell change:
    - in 3.84 Mcps TDD
      - use the IE "Uplink Timing Advance" as  $TA_{old}$  and apply  $TA_{new}$  for uplink transmission in the target cell at the CFN indicated in the IE "Activation Time" as specified in [33];
      - include the value of the applied timing advance in the IE "Timing Advance" in the COMPLETE message.
    - in 1.28 Mcps TDD
      - if the IE "Synchronization parameters" is included the UE shall initiate SYNC\_UL code transmissions as specified in [33] using the parameters as indicated in IE "Synchronization parameters"
      - if the IE "Synchronization parameters" is not included the UE shall evaluate the timing for uplink transmissions as specified in [33]

### 10.3.6.41 Midamble shift and burst type

NOTE: Only for TDD.

This information element indicates burst type and midamble allocation. Three different midamble allocation schemes exist:

- Default midamble: the midamble shift is selected by layer 1 depending on the associated channelisation code (DL and UL)
- Common midamble: the midamble shift is chosen by layer 1 depending on the number of channelisation codes (possible in DL only)
- UE specific midamble: a UE specific midamble is explicitly assigned (DL and UL).

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
CHOICE <i>TDD option</i>	MP				REL-4
>3.84 Mcps TDD					REL-4
>>CHOICE <i>Burst Type</i>	MP				
>>>Type 1					
>>>>Midamble Allocation Mode	MP		Enumerated (Default midamble, Common midamble, UE specific midamble)		
>>>>Midamble configuration burst type 1 and 3	MP		Integer(4, 8, 16)	As defined in [30]	
>>>>Midamble Shift	CV-UE		Integer(0..15)		
>>>>Type 2					
>>>>Midamble Allocation Mode	MP		Enumerated (Default midamble, Common midamble, UE specific midamble)		
>>>>Midamble configuration burst type 2	MP		Integer(3, 6)	As defined in [30]	
>>>>Midamble Shift	CV-UE		Integer(0..5)		
>>>>Type 3					
>>>>Midamble Allocation Mode	MP		Enumerated (Default midamble, UE specific midamble)		
>>>>Midamble configuration burst type 1 and 3	MP		Integer(4, 8, 16)	As defined in [30]	
>>>>Midamble Shift	CV-UE		Integer (0..15)	NOTE: Burst Type 3 is only used in uplink.	
>1.28 Mcps TDD					REL-4
>>Midamble Allocation Mode	MP		Enumerated (Default midamble, <a href="#">Common midamble</a> , UE specific midamble)		REL-4
>>Midamble configuration	MP		Integer(2, 4, 6, 8, 10, 12, 14, 16)	As defined in [30]	REL-4
>>Midamble Shift	CV-UE		Integer (0..15)		REL-4

Condition	Explanation
UE	This information element is only sent when the value of the "Midamble Allocation Mode" IE is "UE-specific midamble".

### 10.3.6.49 PICH Info

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
CHOICE <i>mode</i>	MP				
>FDD					
>>Channelisation code	MP		Integer(0..255)	SF is fixed and equal to 256	
>>Number of PI per frame	MP		Integer (18, 36, 72, 144)		
>>STTD indicator	MP		STTD Indicator 10.3.6.78		
>TDD					
>>Timeslot number	MD		Timeslot number 10.3.6.84	Default value is the timeslot used by the SCCPCH carrying the associated PCH.	
>>>>CHOICE <i>TDD option</i>	MP				REL-4
>>>>>3.84 Mcps TDD					REL-4
>>>>>>Channelisation code	MD		Enumerated ( (16/1)...(16/16) )	Default value is the channelisation code used by the SCCPCH carrying the associated PCH.	
>>>1.28 Mcps TDD					REL-4
>>>>>Codes list	<a href="#">MP</a>	<a href="#">1..2</a>			<a href="#">REL-4</a>
>>>>>>Channelisation code	<a href="#">MP</a>		<a href="#">Enumerated ( (16/1)...(16/16) )</a>		<a href="#">REL-4</a>
>>>>>>Midamble shift and burst type	MP		Midamble shift and burst type 10.3.6.41		REL-4
>>Repetition period/length	MD		Enumerated( (4/2),(8/2), (8/4),(16/2), (16/4), (32/2),(32/4), (64/2),(64/4) )	Default value is "(64/2)".	
>>Offset	MP		Integer (0...Repetition period -1)	SFN mod Repetitionperiod = Offset.	
>>Paging indicator length	MD		Integer (4, 8, 16)	Indicates the length of one paging indicator in Bits. Default value is 4.	
>>N <sub>GAP</sub>	MD		Integer(2, 4, 8)	Number of frames between the last frame carrying PICH for this Paging Occasion and the first frame carrying paging messages for this Paging Occasion. Default value is 4.	
>>N <sub>PCH</sub>	MD		Integer(1 .. 8)	Number of paging groups. Default value is 2.	

## 11.3 Information element definitions

```

MidambleShiftAndBurstType ::=          SEQUENCE {
  burstType                            CHOICE {
    type1                               SEQUENCE {
      midambleConfigurationBurstTypeand3 MidambleConfigurationBurstTypeand3,
      midambleAllocationMode             CHOICE {
        defaultMidamble                 NULL,
        commonMidamble                  NULL,
        ueSpecificMidamble              SEQUENCE {
          midambleShift                  MidambleShiftLong
        }
      }
    },
    type2                               SEQUENCE {
      midambleConfigurationBurstType2    MidambleConfigurationBurstType2,
      midambleAllocationMode             CHOICE {
        defaultMidamble                 NULL,
        commonMidamble                  NULL,
        ueSpecificMidamble              SEQUENCE {
          midambleShift                  MidambleShiftShort
        }
      }
    },
    type3                               SEQUENCE {
      midambleConfigurationBurstTypeand3 MidambleConfigurationBurstTypeand3,
      midambleAllocationMode             CHOICE {
        defaultMidamble                 NULL,
        ueSpecificMidamble              SEQUENCE {
          midambleShift                  MidambleShiftLong
        }
      }
    }
  }
}

MidambleShiftAndBurstType-LCR-r4 ::=  SEQUENCE {
  midambleAllocationMode                CHOICE {
    defaultMidamble                     NULL,
    commonMidamble                  NULL,
    ueSpecificMidamble                  SEQUENCE {
      midambleShift                      INTEGER (0..15)
    }
  },
  midambleConfiguration                  INTEGER (1..8)  -- Actual value = IE value * 2
}

...

PichChannelisationCodeList-LCR-r4 ::= SEQUENCE (SIZE (1..2)) OF
                                       DL-TS-ChannelisationCode

PICH-Info ::=                          CHOICE {
  fdd                                    SEQUENCE {
    channelisationCode256                ChannelisationCode256,
    pi-CountPerFrame                     PI-CountPerFrame,
    sttd-Indicator                        BOOLEAN
  },
  tdd                                    SEQUENCE {
    channelisationCode                    TDD-PICH-CCode                OPTIONAL,
    timeslot                              TimeslotNumber            OPTIONAL,
    burstType                             CHOICE {
      type-1                              MidambleShiftLong,
      type-2                              MidambleShiftShort
    }
    repetitionPeriodLengthOffset          RepPerLengthOffset-PICH    OPTIONAL,
    pagingIndicatorLength                  PagingIndicatorLength     DEFAULT pi4,
    n-GAP                                  N-GAP                     DEFAULT f4,
    n-PCH                                  N-PCH                     DEFAULT 2
  }
}

PICH-Info-LCR-r4 ::=                    SEQUENCE {
  timeslot                                TimeslotNumber-LCR-r4      OPTIONAL,

```

<u>pichChannelisationCodeList-<i>LCR-r4</i></u>	<u>PichChannelisationCodeList-<i>LCR-r4</i></u>
midambleShiftAndBurstType	MidambleShiftAndBurstType- <i>LCR-r4</i> ,
repetitionPeriodLengthOffset	RepPerLengthOffset- <i>PICH</i> OPTIONAL,
pagingIndicatorLength	PagingIndicatorLength DEFAULT <i>pi4</i> ,
n-GAP	N-GAP DEFAULT <i>f4</i> ,
n-PCH	N-PCH DEFAULT <i>2</i>
}	

CR-Form-v4

## CHANGE REQUEST

⌘ **25.331 CR 972** ⌘ ev **-** ⌘ Current version: **4.1.0** ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

**Proposed change affects:** ⌘ (U)SIM  ME/UE  Radio Access Network  Core Network

<b>Title:</b>	⌘ Introduction of 1.28Mcps TDD Mode in clause 13.7		
<b>Source:</b>	⌘ TSG-RAN WG2		
<b>Work item code:</b>	⌘ LCRTDD-L23	<b>Date:</b>	⌘ 14.08.2001
<b>Category:</b>	⌘ <b>F</b>	<b>Release:</b>	⌘ REL-4
	<i>Use one of the following categories:</i> <b>F</b> (correction) <b>A</b> (corresponds to a correction in an earlier release) <b>B</b> (addition of feature), <b>C</b> (functional modification of feature) <b>D</b> (editorial modification) Detailed explanations of the above categories can be found in 3GPP <a href="#">TR 21.900</a> .		<i>Use one of the following releases:</i> <b>2</b> (GSM Phase 2) <b>R96</b> (Release 1996) <b>R97</b> (Release 1997) <b>R98</b> (Release 1998) <b>R99</b> (Release 1999) <b>REL-4</b> (Release 4) <b>REL-5</b> (Release 5)

<b>Reason for change:</b>	⌘ Introduction of Information Elements and parameter values for default radio configurations for 1.28 Mcps TDD		
<b>Summary of change:</b>	⌘ • Introduction of IE "PhyCH Information 1.28Mcps TDD" into the default radio configurations in the chapter 13.7.		
<b>Consequences if not approved:</b>	⌘ Missing parameter values for default radio configuration for 1.28 Mcps TDD		

<b>Clauses affected:</b>	⌘ 13.7		
<b>Other specs affected:</b>	⌘ <input type="checkbox"/> Other core specifications ⌘ <input type="checkbox"/> Test specifications ⌘ <input type="checkbox"/> O&M Specifications		
<b>Other comments:</b>	⌘		

### How to create CRs using this form:

Comprehensive information and tips about how to create CRs can be found at: [http://www.3gpp.org/3G\\_Specs/CRs.htm](http://www.3gpp.org/3G_Specs/CRs.htm). Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/>. For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.



## 13.7 Parameter values for default radio configurations

The UE shall support the use of the default radio configurations that are specified in the following.

NOTE 1: These configurations are based on [41] and cover a number of RAB and signalling connection configurations.

In the table that is used to specify the parameter values for these default configurations, the following principles are used:

- Optional IEs that are not used are omitted;
- In case no parameter value is specified in a column, this means the value given the previous (left side) column applies.

NOTE 2: If needed, signalling radio bearer RB4 is established after the completion of handover.

NOTE 3: For each default configuration, the value of ~~both FDD, and 3.84 Mcps TDD~~ and 1.28 Mcps TDD parameters are specified. All parameters apply to ~~both FDD, and 3.84 Mcps TDD~~ and 1.28 Mcps TDD modes, unless explicitly stated otherwise. It should be noted that in this respect default configurations differ from pre-defined configurations, which only include parameter values for one mode.

NOTE 4: The transport format sizes, indicated in the following table, concern the RLC PDU size, since all configurations concern dedicated channels. The transport block sizes indicated in TS 34.108 are different since these include the size of the MAC header.

Configuration	3.4 kbps signalling	13.6 kbps signalling	7.95 kbps speech + 3.4 kbps signalling	12.2 kbps speech + 3.4 kbps signalling
Ref 34.108	2	3	6	4
Default configuration identity	0	1	2	3
<b>RB INFORMATION</b>				
rb-Identity	RB1: 1, RB2: 2, RB3: 3	RB1: 1, RB2: 2, RB3: 3	RB1: 1, RB2: 2, RB3: 3, RB5: 5, RB6: 6	RB1: 1, RB2: 2, RB3: 3, RB5: 5, RB6: 6, RB7: 7
rlc-InfoChoice	Rlc-info	Rlc-info	Rlc-info	Rlc-info
>ul-RLC-Mode	RB1: UM RB2- RB3: AM	RB1: UM RB2- RB3: AM	RB1: UM RB2- RB3: AM RB5- RB6: TM	RB1: UM RB2- RB3: AM RB5- RB7: TM
>>transmissionRLC-DiscardMode	RB1: N/A RB2- RB3: NoDiscard	RB1: N/A RB2- RB3: NoDiscard	RB1: N/A RB2- RB3: NoDiscard RB5- RB6: N/A	RB1: N/A RB2- RB3: NoDiscard RB5- RB7: N/A
>>>maxDat	RB1: N/A RB2- RB3: 15	RB1: N/A RB2- RB3: 15	RB1: N/A RB2- RB3: 15 RB5- RB6: N/A	RB1: N/A RB2- RB3: 15 RB5- RB7: N/A
>>transmissionWindowSize	RB1: N/A RB2- RB3: 128	RB1: N/A RB2- RB3: 128	RB1: N/A RB2- RB3: 128 RB5- RB6: N/A	RB1: N/A RB2- RB3: 128 RB5- RB7: N/A
>>timerRST	RB1: N/A RB2- RB3: 300	RB1: N/A RB2- RB3: 300	RB1: N/A RB2- RB3: 300 RB5- RB6: N/A	RB1: N/A RB2- RB3: 300 RB5- RB7: N/A
>>max-RST	RB1: N/A RB2- RB3: 1	RB1: N/A RB2- RB3: 1	RB1: N/A RB2- RB3: 1 RB5- RB6: N/A	RB1: N/A RB2- RB3: 1 RB5- RB7: N/A
>>pollingInfo	RB1: N/A RB2- RB3: as below	RB1: N/A RB2- RB3: as below	RB1: N/A RB2- RB3: as below RB5- RB6: N/A	RB1: N/A RB2- RB3: as below RB5- RB7: N/A
>>>lastTransmissionPUPoll	RB2- RB3: FALSE	RB2- RB3: FALSE	RB2- RB3: FALSE	RB2- RB3: FALSE
>>>lastRetransmissionPUPoll	RB2- RB3: FALSE	RB2- RB3: FALSE	RB2- RB3: FALSE	RB2- RB3: FALSE
>>>timerPollPeriodic	RB2- RB3: 100	RB2- RB3: 100	RB2- RB3: 100	RB2- RB3: 100
>>segmentationIndication	RB1- RB3: N/A	RB1- RB3: N/A	RB1- RB3: N/A RB5- RB6: FALSE	RB1- RB3: N/A RB5- RB7: FALSE
>dl-RLC-Mode	RB1: UM RB2- RB3: AM	RB1: UM RB2- RB3: AM	RB1: UM RB2- RB3: AM RB5- RB6: TM	RB1: UM RB2- RB3: AM RB5- RB7: TM
>>inSequenceDelivery	RB1: N/A RB2- RB3: TRUE	RB1: N/A RB2- RB3: TRUE	RB1: N/A RB2- RB3: TRUE RB5- RB6: N/A	RB1: N/A RB2- RB3: TRUE RB5- RB7: N/A
>>receivingWindowSize	RB1: N/A RB2- RB3: 128	RB1: N/A RB2- RB3: 128	RB1: N/A RB2- RB3: 128 RB5- RB6: N/A	RB1: N/A RB2- RB3: 128 RB5- RB7: N/A
>>dl-RLC-StatusInfo	RB1: N/A RB2- RB3: as below	RB1: N/A RB2- RB3: as below	RB1: N/A RB2- RB3: as below RB5- RB6: N/A	RB1: N/A RB2- RB3: as below RB5- RB7: N/A
>>>timerStatusProhibit	RB2- RB3: 100	RB2- RB3: 100	RB2- RB3: 100	RB2- RB3: 100
>>>missingPUIndicator	RB2- RB3: FALSE	RB2- RB3: FALSE	RB2- RB3: FALSE	RB2- RB3: FALSE
>>>timerStatusPeriodic	RB2- RB3: 100	RB2- RB3: 100	RB2- RB3: 100	RB2- RB3: 100
>>segmentationIndication	RB1- RB3: N/A	RB1- RB3: N/A	RB1- RB3: N/A RB5- RB6: FALSE	RB1- RB3: N/A RB5- RB7: FALSE
rb-MappingInfo				
>UL-LogicalChannelMappings	OneLogicalChannel	OneLogicalChannel	OneLogicalChannel	OneLogicalChannel
>>ul-TransportChannelType	Dch	Dch	Dch	Dch
>>>transportChannelIdentity	RB1- RB3: 1	RB1- RB3: 1	RB1- RB3: 3 RB5: 1, RB6: 2	RB1- RB3: 4 RB5: 1, RB6: 2, RB7: 3

>>logicalChannelIdentity	RB1: 1, RB2: 2, RB3: 3	RB1: 1, RB2: 2, RB3: 3	RB1: 1, RB2: 2, RB3: 3 RB5- RB6: N/A	RB1: 1, RB2: 2, RB3: 3 RB5- RB7: N/A
>>rlc-SizeList	RB1- RB3: all	RB1- RB3: all	RB1- RB3: all RB5- RB6: N/A	RB1- RB3: all RB5- RB7: N/A
>>mac-LogicalChannelPriority	RB1: 1, RB2: 2, RB3: 3	RB1: 1, RB2: 2, RB3: 3	RB1: 1, RB2: 2, RB3: 3 RB5- RB6: 5	RB1: 1, RB2: 2, RB3: 3 RB5- RB7: 5
>DL-logicalChannelMappingList				
>>Mapping option 1	One mapping option	One mapping option	One mapping option	One mapping option
>>>dl-TransportChannelType	Dch	Dch	Dch	Dch
>>>>transportChannelIdentity	RB1- RB3: 1	RB1- RB3: 1	RB1- RB3: 3 RB5: 1, RB6: 2	RB1- RB3: 4 RB5: 1, RB6: 2, RB7: 3
>>>>logicalChannelIdentity	RB1: 1, RB2: 2, RB3: 3	RB1: 1, RB2: 2, RB3: 3	RB1: 1, RB2: 2, RB3: 3 RB5- RB6: N/A	RB1: 1, RB2: 2, RB3: 3 RB5- RB7: N/A
TrCH INFORMATION PER TrCH				
UL-AddReconfTransChInfoList				
>transportChannelIdentity	TrCH1: 1	TrCH1: 1	TrCH1: 1, TrCH2: 2, TrCH3: 3	TrCH1: 1, TrCH2: 2, TrCH3: 3, TrCH4: 4
>transportFormatSet	DedicatedTransChTFS	DedicatedTransChTFS	DedicatedTransChTFS	DedicatedTransChTFS
>>dynamicTF-information				
>>>tf0/ tf0,1	TrCH1: (0x144, 1x144)	TrCH1: (0x144, 1x144)	TrCH1: (0x75) TrCH2: (0x 84 1x84) TrCH3: (0x144, 1x144)	TrCH1: (0x81) TrCH2: (0x 103, 1x103) TrCH3: (0x 60, 1x60) TrCH4: (0x144, 1x144)
>>>>rlcSize	BitMode	BitMode	BitMode	BitMode
>>>>>sizeType	TrCH1: type 2, part1= 2, part2= 0 (144)	TrCH1: type 2, part1= 2, part2= 0 (144)	TrCH1: type 1: 75 TrCH2: type 1: 84 TrCH3: 2: type 2, part1= 2, part2= 0 (144)	TrCH1: type 1: 81 TrCH2: type 1: 103 TrCH3: type 1: 60 TrCH4: 2: type 2, part1= 2, part2= 0 (144)
>>>>>numberOfTbSizeList	TrCH1: Zero, one	TrCH1: Zero, one	TrCH1: Zero TrCH2-3: Zero, one	TrCH1: Zero TrCH2-4: Zero, one
>>>>>logicalChannelList	All	All	All	All
>>>>tf 1	N/A	N/A	TrCH1: (1x39) TrCH2- TrCH4: N/A	TrCH1: (1x39) TrCH2- TrCH4: N/A
>>>>>numberOfTransportBlocks			TrCH1: One	TrCH1: One
>>>>>rlc-Size			TrCH1: BitMode	TrCH1: BitMode
>>>>>>sizeType			TrCH1: 1: 39	TrCH1: 1: 39
>>>>>>numberOfTbSizeList			TrCH1: One	TrCH1: One
>>>>>>logicalChannelList			TrCH1: all	TrCH1: all
>>>>>tf 2	N/A	N/A	TrCH1: (1x75) TrCH2- TrCH3: N/A	TrCH1: (1x81) TrCH2- TrCH4: N/A
>>>>>>numberOfTransportBlocks			TrCH1: Zero	TrCH1: Zero
>>>>>>rlc-Size			TrCH1: BitMode	TrCH1: BitMode
>>>>>>>sizeType			TrCH1: type 1: 75	TrCH1: type 1: 81
>>>>>>>numberOfTbSizeList			TrCH1: One	TrCH1: One
>>>>>>>logicalChannelList			TrCH1: all	TrCH1: all
>>>>tti	TrCH1: 40	TrCH1: 10	TrCH1- TrCH2: 20 TrCH3: 40	TrCH1- TrCH3: 20 TrCH4: 40
>>>>channelCodingType	Convolutional	Convolutional	Convolutional	Convolutional

>>>>codingRate	TrCH1: Third	TrCH1: Third	TrCH1- TrCH2: Third TrCH3: Third	TrCH1- TrCH2: Third TrCH3: Half TrCH4: Third
>>>rateMatchingAttribute	TrCH1: 160	TrCH1: 160	TrCH1: 200 TrCH2: 190 TrCH3: 160	TrCH1: 200 TrCH2: 190 TrCH3: 235 TrCH4: 160
>>>crc-Size	TrCH1: 16	TrCH1: 16	TrCH1: 12 TrCH2: 0 TrCH3: 16	TrCH1: 12 TrCH2- TrCH3: 0 TrCH4: 16
DL- AddReconfTransChInfoList				
>dl- TransportChannelIdentity (should be as for UL)	TrCH1: 1	TrCH1: 1	TrCH1: 1, TrCH2: 2, TrCH3: 3	TrCH1: 1, TrCH2: 2, TrCH3: 3, TrCH4: 4
>tfs-SignallingMode	SameAsUL	SameAsUL	Independent <Only tf0 on TrCH1 is different and shown below>	Independent <Only tf0 on TrCH1 is different and shown below>
>>transportFormatSet			DedicatedTransChT FS	DedicatedTransChT FS
>>>dynamicTF-information				
>>>>tf0/ tf0,1			TrCH1: (1x0)	TrCH1: (1x0)
>>>>rlcSize			BitMode	bitMode
>>>>>sizeType			TrCH1: type 1: 0	TrCH1: type 1: 0
>>>>numberOfTbSizeList			TrCH1: One	TrCH1: One
>>>>logicalChannelList			All	All
>>ULTrCH-Id	TrCH1: 1	TrCH1: 1	TrCH1: 1, TrCH2: 2, TrCH3: 3	TrCH1: 1, TrCH2: 2, TrCH3: 3, TrCH4: 4
>dch-QualityTarget				
>>bler-QualityValue	TrCH1: $5 \times 10^{-2}$	TrCH1: $5 \times 10^{-2}$	TrCH1: $7 \times 10^{-3}$ TrCH2- TrCH3: Absent	TrCH1: $7 \times 10^{-3}$ TrCH2- TrCH4: Absent
TrCH INFORMATION, COMMON				
ul-CommonTransChInfo				
>tfs-ID (TDD only)	1	1	1	1
>sharedChannelIndicator (TDD only)	FALSE	FALSE	FALSE	FALSE
>tfc-Subset	Absent, not required	Absent, not required	Absent, not required	Absent, not required
>ul-TFCS	Normal TFCI signalling	Normal TFCI signalling	Normal TFCI signalling	Normal TFCI signalling
>>explicitTFCS- ConfigurationMode	Complete	Complete	Complete	Complete
>>>ctfcSize	Ctfc2Bit	Ctfc2Bit	Ctfc4Bit	Ctfc6Bit
>>>>TFCS representation	Addition	Addition	Addition	Addition
>>>>>TFCS list				
>>>>>>TFCS 1	(TF0)	(TF0)	(TF0, TF0, TF0)	(TF0, TF0, TF0, TF0)
>>>>>>>ctfc	0	0	0	0
>>>>>>>gainFactorInform ation	Computed	Computed	Computed	Computed
>>>>>>>>referenceTFClId	0	0	0	0
>>>>>>>TFCS 2	(TF1)	(TF1)	(TF1, TF0, TF0)	(TF1, TF0, TF0, TF0)
>>>>>>>ctfc	1	1	1	1
>>>>>>>gainFactorInform ation	Signalled	Signalled	Computed	Computed
>>>>>>>> $\beta$ c (FDD only)	11	11	N/A	N/A
>>>>>>>> $\beta$ d	15	15	N/A	N/A
>>>>>>>>>referenceTFClId	N/A	N/A	0	0
>>>>>>>TFCS 3			(TF2, TF1, TF0)	(TF2, TF1, TF1, TF0)
>>>>>>>>ctfc			5	11

>>>>>>gainFactorInformation			Computed	Computed
>>>>>>referenceTFCIId			0	0
>>>>>>TFCS 4			(TF0, TF0, TF1)	(TF0, TF0, TF0, TF1)
>>>>>>ctfc			6	12
>>>>>>gainFactorInformation			Computed	Computed
>>>>>> $\beta$ c (FDD only)			N/A	N/A
>>>>>> $\beta$ d			N/A	N/A
>>>>>>referenceTFCIId			0	0
>>>>>>TFCS 5			(TF1, TF0, TF1)	(TF1, TF0, TF0, TF1)
>>>>>>ctfc			7	13
>>>>>>gainFactorInformation			Computed	Computed
>>>>>>referenceTFCIId			0	0
>>>>>>TFCS 6			(TF2, TF1, TF1)	(TF2, TF1, TF1, TF1)
>>>>>>ctfc			11	23
>>>>>>gainFactorInformation			Signalled	Signalled
>>>>>> $\beta$ c (FDD only)			11	11
>>>>>> $\beta$ d			15	15
>>>>>>referenceTFCIId			0	0
dl-CommonTransChInfo				
>tfcs-SignallingMode	Same as UL	Same as UL	Same as UL	Same as UL
PhyCH INFORMATION FDD				
UL-DPCH-InfoPredef				
>ul-DPCH-PowerControllInfo				
>>powerControlAlgorithm	Algorithm 1	Algorithm 1	Algorithm 1	Algorithm 1
>>>tpcStepSize	1	1	1	1
>tfci-Existence	TRUE	TRUE	TRUE	TRUE
>puncturingLimit	1	1	1	0.88
DL-CommonInformationPredef				
>dl-DPCH-InfoCommon				
>>spreadingFactor	256	128	128	128
>>pilotBits	4	4	4	4
>>positionFixed	N/A	N/A	Fixed	Fixed
PhyCH INFORMATION <a href="#">3.84 Mcps_TDD</a>				
UL-DPCH-InfoPredef				
>ul-DPCH-PowerControllInfo				
>>dpch-ConstantValue	-20	-20	-20	-20
>commonTimeslotInfo				
>>secondInterleavingMode	frameRelated	frameRelated	frameRelated	frameRelated
>>>tfci-Coding	4	4	16	16
>>puncturingLimit	0.80	0.80	0.80	0.80
>>repetitionPeriodAndLength	repetitionPeriod1	repetitionPeriod1	repetitionPeriod1	repetitionPeriod1
DL-CommonInformationPredef				
>dl-DPCH-InfoCommon				
>>commonTimeslotInfo				
>>>secondInterleavingMode	frameRelated	frameRelated	frameRelated	frameRelated
>>>tfci-Coding	4	4	16	16
>>>puncturingLimit	0.74	0.74	0.80	0.80
>>>repetitionPeriodAndLength	repetitionPeriod1	repetitionPeriod1	repetitionPeriod1	repetitionPeriod1

<a href="#">PhyCH INFORMATION</a> <a href="#">1.28Mcps TDD</a>				
<a href="#">UL-DPCH-InfoPredef</a>				
<a href="#">&gt;commonTimeslotInfo</a>				
<a href="#">&gt;&gt;secondInterleavingMode</a>	<a href="#">frameRelated</a>	<a href="#">frameRelated</a>	<a href="#">frameRelated</a>	<a href="#">frameRelated</a>
<a href="#">&gt;&gt;tfc-Coding</a>	<a href="#">4</a>	<a href="#">4</a>	<a href="#">16</a>	<a href="#">16</a>
<a href="#">&gt;&gt;puncturingLimit</a>	<a href="#">1</a>	<a href="#">0.64</a>	<a href="#">0.80</a>	<a href="#">0.60</a>
<a href="#">&gt;&gt;repetitionPeriodAndLength</a>	<a href="#">repetitionPeriod1</a>	<a href="#">repetitionPeriod1</a>	<a href="#">repetitionPeriod1</a>	<a href="#">repetitionPeriod1</a>
<a href="#">DL-CommonInformationPredef</a>				
<a href="#">&gt;dl-DPCH-InfoCommon</a>				
<a href="#">&gt;&gt;commonTimeslotInfo</a>				
<a href="#">&gt;&gt;&gt;secondInterleavingMode</a>	<a href="#">frameRelated</a>	<a href="#">frameRelated</a>	<a href="#">frameRelated</a>	<a href="#">frameRelated</a>
<a href="#">&gt;&gt;&gt;tfc-Coding</a>	<a href="#">4</a>	<a href="#">4</a>	<a href="#">16</a>	<a href="#">16</a>
<a href="#">&gt;&gt;&gt;puncturingLimit</a>	<a href="#">1</a>	<a href="#">0.64</a>	<a href="#">0.80</a>	<a href="#">0.60</a>
<a href="#">&gt;&gt;&gt;repetitionPeriodAndLength</a>	<a href="#">repetitionPeriod1</a>	<a href="#">repetitionPeriod1</a>	<a href="#">repetitionPeriod1</a>	<a href="#">repetitionPeriod1</a>

<b>Configuration</b>	<b>28.8 kbps conv. CS- data + 3.4 kbps signalling</b>	<b>32 kbps conv. CS- data + 3.4 kbps signalling</b>	<b>64kbps conv. CS- data + 3.4 kbps signalling</b>	<b>14.4 kbps streaming CS- data + 3.4 kbps signalling</b>
Ref 34.108	12	14	13	15
Default configuration identity	4	5	6	7
<b>RB INFORMATION</b>				
rb-Identity	RB1: 1, RB2: 2, RB3: 3, RB5: 5	RB1: 1, RB2: 2, RB3: 3, RB5: 5	RB1: 1, RB2: 2, RB3: 3, RB5: 5	RB1: 1, RB2: 2, RB3: 3, RB5: 5
rlc-InfoChoice	Rlc-info	Rlc-info	Rlc-info	Rlc-info
>ul-RLC-Mode	RB1: UM RB2- RB3: AM RB5: TM	RB1: UM RB2- RB3: AM RB5: TM	RB1: UM RB2- RB3: AM RB5: TM	RB1: UM RB2- RB3: AM RB5: TM
>>transmissionRLC-DiscardMode	RB1: N/A RB2- RB3: NoDiscard RB5: N/A	RB1: N/A RB2- RB3: NoDiscard RB5: N/A	RB1: N/A RB2- RB3: NoDiscard RB5: N/A	RB1: N/A RB2- RB3: NoDiscard RB5: N/A
>>>maxDat	RB1: N/A RB2- RB3: 15 RB5: N/A	RB1: N/A RB2- RB3: 15 RB5: N/A	RB1: N/A RB2- RB3: 15 RB5: N/A	RB1: N/A RB2- RB3: 15 RB5: N/A
>>transmissionWindowSize	RB1: N/A RB2- RB3: 128 RB5: N/A	RB1: N/A RB2- RB3: 128 RB5: N/A	RB1: N/A RB2- RB3: 128 RB5: N/A	RB1: N/A RB2- RB3: 128 RB5: N/A
>>timerRST	RB1: N/A RB2- RB3: 300 RB5: N/A	RB1: N/A RB2- RB3: 300 RB5: N/A	RB1: N/A RB2- RB3: 300 RB5: N/A	RB1: N/A RB2- RB3: 300 RB5: N/A
>>max-RST	RB1: N/A RB2- RB3: 1 RB5: N/A	RB1: N/A RB2- RB3: 1 RB5: N/A	RB1: N/A RB2- RB3: 1 RB5: N/A	RB1: N/A RB2- RB3: 1 RB5: N/A
>>pollingInfo	RB1: N/A RB2- RB3: as below RB5: N/A	RB1: N/A RB2- RB3: as below RB5: N/A	RB1: N/A RB2- RB3: as below RB5: N/A	RB1: N/A RB2- RB3: as below RB5: N/A
>>>lastTransmissionPUPoll	RB2- RB3: FALSE	RB2- RB3: FALSE	RB2- RB3: FALSE	RB2- RB3: FALSE
>>>lastRetransmissionPUPoll	RB2- RB3: FALSE	RB2- RB3: FALSE	RB2- RB3: FALSE	RB2- RB3: FALSE
>>>timerPollPeriodic	RB2- RB3: 100	RB2- RB3: 100	RB2- RB3: 100	RB2- RB3: 100
>>segmentationIndication	RB1- RB3: N/A RB5: FALSE	RB1- RB3: N/A RB5: FALSE	RB1- RB3: N/A RB5: FALSE	RB1- RB3: N/A RB5: FALSE
>dl-RLC-Mode	RB1: UM RB2- RB3: AM RB5: TM	RB1: UM RB2- RB3: AM RB5: TM	RB1: UM RB2- RB3: AM RB5: TM	RB1: UM RB2- RB3: AM RB5: TM
>>inSequenceDelivery	RB1: N/A RB2- RB3: TRUE RB5: N/A	RB1: N/A RB2- RB3: TRUE RB5: N/A	RB1: N/A RB2- RB3: TRUE RB5: N/A	RB1: N/A RB2- RB3: TRUE RB5: N/A
>>receivingWindowSize	RB1: N/A RB2- RB3: 128 RB5: N/A	RB1: N/A RB2- RB3: 128 RB5: N/A	RB1: N/A RB2- RB3: 128 RB5: N/A	RB1: N/A RB2- RB3: 128 RB5: N/A
>>dl-RLC-StatusInfo	RB1: N/A RB2- RB3: as below RB5: N/A	RB1: N/A RB2- RB3: as below RB5: N/A	RB1: N/A RB2- RB3: as below RB5: N/A	RB1: N/A RB2- RB3: as below RB5: N/A
>>>timerStatusProhibit	RB2- RB3: 100	RB2- RB3: 100	RB2- RB3: 100	RB2- RB3: 100
>>>missingPUIndicator	RB2- RB3: FALSE	RB2- RB3: FALSE	RB2- RB3: FALSE	RB2- RB3: FALSE
>>>timerStatusPeriodic	RB2- RB3: 100	RB2- RB3: 100	RB2- RB3: 100	RB2- RB3: 100
>>segmentationIndication	RB1- RB3: N/A RB5: FALSE	RB1- RB3: N/A RB5: FALSE	RB1- RB3: N/A RB5: FALSE	RB1- RB3: N/A RB5: FALSE
<b>rb-MappingInfo</b>				
>UL-LogicalChannelMappings	OneLogicalChannel	OneLogicalChannel	OneLogicalChannel	OneLogicalChannel
>>ul-TransportChannelType	Dch	Dch	Dch	Dch
>>>transportChannelIdentity	RB1- RB3: 2 RB5: 1	RB1- RB3: 2 RB5: 1	RB1- RB3: 2 RB5: 1	RB1- RB3: 2 RB5: 1

>>logicalChannelIdentity	RB1: 1, RB2: 2, RB3: 3 RB5: N/A	RB1: 1, RB2: 2, RB3: 3 RB5: N/A	RB1: 1, RB2: 2, RB3: 3 RB5: N/A	RB1: 1, RB2: 2, RB3: 3 RB5: N/A
>>rlc-SizeList	RB1- RB3: all RB5: N/A	RB1- RB3: all RB5: N/A	RB1- RB3: all RB5: N/A	RB1- RB3: all RB5: N/A
>>mac-LogicalChannelPriority	RB1: 1, RB2: 2, RB3: 3 RB5: 5	RB1: 1, RB2: 2, RB3: 3 RB5: 5	RB1: 1, RB2: 2, RB3: 3 RB5: 5	RB1: 1, RB2: 2, RB3: 3 RB5: 5
>DL-logicalChannelMappingList				
>>Mapping option 1	One mapping option	One mapping option	One mapping option	One mapping option
>>>dl-TransportChannelType	Dch	Dch	Dch	Dch
>>>>transportChannelIdentity	RB1- RB3: 2 RB5: 1	RB1- RB3: 2 RB5: 1	RB1- RB3: 2 RB5: 1	RB1- RB3: 2 RB5: 1
>>>>logicalChannelIdentity	RB1: 1, RB2: 2, RB3: 3 RB5: N/A	RB1: 1, RB2: 2, RB3: 3 RB5: N/A	RB1: 1, RB2: 2, RB3: 3 RB5: N/A	RB1: 1, RB2: 2, RB3: 3 RB5: N/A
TrCH INFORMATION PER TrCH				
UL-AddReconfTransChInfoList				
>transportChannelIdentity	TrCH1: 1, TrCH2: 2	TrCH1: 1, TrCH2: 2	TrCH1: 1, TrCH2: 2	TrCH1: 1, TrCH2: 2
>transportFormatSet	DedicatedTransChTFS	DedicatedTransChTFS	DedicatedTransChTFS	DedicatedTransChTFS
>>dynamicTF-information				
>>>>tf0/ tf0,1	TrCH1: (0x576, 1x576, 2x576) TrCH2: (0x144, 1x144)	TrCH1: (0x640, 1x640) TrCH2: (0x144, 1x144)	TrCH1: (0x640, 2x640) TrCH2: (0x144, 1x144)	TrCH1: (0x576, 1x576) TrCH2: (0x144, 1x144)
>>>>rlcSize	TrCH1: OctetMode TrCH2:BitMode	TrCH1: OctetMode TrCH2:BitMode	TrCH1: OctetMode TrCH2:BitMode	TrCH1: OctetMode TrCH2:BitMode
>>>>>sizeType	TrCH1: type 2, part1= 11, part2= 2 (576) TrCH2: type 2, part1= 2, part2= 0 (144)	TrCH1: type 2, part1= 11, part2= 2 (640) TrCH2: type 2, part1= 2, part2= 0 (144)	TrCH1: type 2, part1= 11, part2= 2 (640) TrCH2: type 2, part1= 2, part2= 0 (144)	TrCH1: type 2, part1= 9, part2= 2 (576) TrCH2: type 2, part1= 2, part2= 0 (144)
>>>>>numberOfTbSizeList	TrCH1: Zero,1, 2 (4) TrCH2: Zero, one	TrCH1: Zero, one TrCH2: Zero, one	TrCH1: Zero, 2 (4) TrCH2: Zero, one	TrCH1: Zero, one, TrCH2: Zero, one
>>>>>logicalChannelList	All	All	All	All
>>semiStaticTF-Information				
>>>>tti	TrCH1: 40 TrCH2: 40	TrCH1: 20 TrCH2: 40	TrCH1: 20 TrCH2: 40	TrCH1: 40 TrCH2: 40
>>>>channelCodingType	TrCH1: Turbo TrCH2: Convolutional	TrCH1: Turbo TrCH2: Convolutional	TrCH1: Turbo TrCH2: Convolutional	TrCH1: Turbo TrCH2: Convolutional
>>>>>codingRate	TrCH1: N/A TrCH2: Third	TrCH1: N/A TrCH2: Third	TrCH1: N/A TrCH2: Third	TrCH1: N/A TrCH2: Third
>>>>>rateMatchingAttribute	TrCH1: 180 TrCH2: 160	TrCH1: 185 TrCH2: 160	TrCH1: 170 TrCH2: 160	TrCH1: 165 TrCH2: 160
>>>>>crc-Size	TrCH1: 16 TrCH2: 16	TrCH1: 16 TrCH2: 16	TrCH1: 16 TrCH2: 16	TrCH1: 16 TrCH2: 16
DL-AddReconfTransChInfoList				
>dl-TransportChannelIdentity (should be as for UL)	TrCH1: 1, TrCH2: 2	TrCH1: 1, TrCH2: 2	TrCH1: 1, TrCH2: 2	TrCH1: 1, TrCH2: 2
>tfs-SignallingMode	SameAsUL	SameAsUL	SameAsUL	SameAsUL
>>transportFormatSet				
>>>>dynamicTF-information				
>>>>>tf0/ tf0,1				
>>>>>rlcSize				



>>>>sizeType				
>>>>numberOfTbSizeList				
>>>>logicalChannelList				
>>ULTrCH-Id	TrCH1: 1, TrCH2: 2	TrCH1: 1, TrCH2: 2	TrCH1: 1, TrCH2: 2	TrCH1: 1, TrCH2: 2
>dch-QualityTarget				
>>bler-QualityValue	TrCH1: $2 \times 10^{-3}$ TrCH2: Absent	TrCH1: $2 \times 10^{-3}$ TrCH2: Absent	TrCH1: $2 \times 10^{-3}$ TrCH2: Absent	TrCH1: $1 \times 10^{-2}$ TrCH2: Absent
TrCH INFORMATION, COMMON				
ul-CommonTransChInfo				
>tfc-ID (TDD only)	1	1	1	1
>sharedChannelIndicator (TDD only)	FALSE	FALSE	FALSE	FALSE
>tfc-Subset	Absent, not required	Absent, not required	Absent, not required	Absent, not required
>ul-TFCS	Normal TFCI signalling	Normal TFCI signalling	Normal TFCI signalling	Normal TFCI signalling
>>explicitTFCS- ConfigurationMode	Complete	Complete	Complete	Complete
>>>ctfcSize	Ctfc2Bit	Ctfc2Bit	Ctfc2Bit	Ctfc4Bit
>>>>TFCS representation	Addition	Addition	Addition	Addition
>>>>>TFCS list				
>>>>>>TFCS 1	(TF0, TF0)	(TF0, TF0)	(TF0, TF0)	(TF0, TF0)
>>>>>>>ctfc	0	0	0	0
>>>>>>>>gainFactorInform ation	Computed	Computed	Computed	Computed
>>>>>>>>referenceTFCl d	0	0	0	0
>>>>>>>>TFCS 2	(TF1, TF0)	(TF1, TF0)	(TF1, TF0)	(TF1, TF0)
>>>>>>>>ctfc	1	1	1	1
>>>>>>>>>gainFactorInform ation	Computed	Computed	Computed	Computed
>>>>>>>>>>βc (FDD only)	N/A	N/A	N/A	N/A
>>>>>>>>>>βd	N/A	N/A	N/A	N/A
>>>>>>>>>>>referenceTFCl d	0	0	0	0
>>>>>>>>>>>TFCS 3	(TF2, TF0)	(TF0, TF1)	(TF0, TF1)	(TF0, TF1)
>>>>>>>>>>>ctfc	2	2	2	2
>>>>>>>>>>>>gainFactorInform ation	Computed	Computed	Computed	Computed
>>>>>>>>>>>>>referenceTFCl d	0	0	0	0
>>>>>>>>>>>>>TFCS 4	(TF0, TF1)	(TF1, TF1)	(TF1, TF1)	(TF1, TF1)
>>>>>>>>>>>>>ctfc	3	3	3	3
>>>>>>>>>>>>>>gainFactorInform ation	Computed	Signalled	Signalled	Signalled
>>>>>>>>>>>>>>>βc (FDD only)	N/A	8	8	11
>>>>>>>>>>>>>>>βd	N/A	15	15	15
>>>>>>>>>>>>>>>>referenceTFCl d	N/A	N/A	N/A	N/A
>>>>>>>>>>>>>>>>>TFCS 5	(TF1, TF1)	N/A	N/A	
>>>>>>>>>>>>>>>>>ctfc	4			
>>>>>>>>>>>>>>>>>>gainFactorInform ation	Computed			
>>>>>>>>>>>>>>>>>>>referenceTFCl d	8			
>>>>>>>>>>>>>>>>>>>>TFCS 6	(TF2, TF1)	N/A	N/A	
>>>>>>>>>>>>>>>>>>>>ctfc	5			
>>>>>>>>>>>>>>>>>>>>>gainFactorInform ation	Signalled			
>>>>>>>>>>>>>>>>>>>>>>βc (FDD only)	8			
>>>>>>>>>>>>>>>>>>>>>>βd	15			
>>>>>>>>>>>>>>>>>>>>>>>referenceTFCl d	N/A			
>>>>>>>>>>>>>>>>>>>>>>>>TFCS 7				
>>>>>>>>>>>>>>>>>>>>>>>>ctfc				
>>>>>>>>>>>>>>>>>>>>>>>>>gainFactorInform ation				
>>>>>>>>>>>>>>>>>>>>>>>>>>referenceTFCl d				
>>>>>>>>>>>>>>>>>>>>>>>>>>>TFCS 8				

>>>>>>ctfc				
>>>>>>gainFactorInformation				
>>>>>>referenceTFCId				
>>>>>>TFCS 9				
>>>>>>ctfc				
>>>>>>gainFactorInformation				
>>>>>>referenceTFCId				
>>>>>>TFCS 10				
>>>>>>ctfc				
>>>>>>gainFactorInformation				
>>>>>> $\beta_c$ (FDD only)				
>>>>>> $\beta_d$				
>>>>>>referenceTFCId				
dl-CommonTransChInfo				
>tfc-SignallingMode	Same as UL	Same as UL	Same as UL	Same as UL
PhyCH INFORMATION FDD				
UL-DPCH-InfoPredef				
>ul-DPCH-PowerControlInfo				
>>powerControlAlgorithm	Algorithm 1	Algorithm 1	Algorithm 1	Algorithm 1
>>>tpcStepSize	1	1	1	1
>tfc-Existence	TRUE	TRUE	TRUE	TRUE
>puncturingLimit	0.92	0.8	0.92	1
DL-CommonInformationPredef				
>dl-DPCH-InfoCommon				
>>spreadingFactor	64	64	32	128
>>pilotBits	8	8	8	8
>>positionFixed	Flexible	Flexible	Flexible	Flexible
PhyCH INFORMATION - 3.84Mcps TDD				
UL-DPCH-InfoPredef				
>ul-DPCH-PowerControlInfo				
>>dpch-ConstantValue	-20	-20	-20	-20
>commonTimeslotInfo				
>>secondInterleavingMode	frameRelated	frameRelated	frameRelated	frameRelated
>>tfc-Coding	8	8	8	16
>>puncturingLimit	0.56	0.8	0.56	1
>>repetitionPeriodAndLength	repetitionPeriod1	repetitionPeriod1	repetitionPeriod1	repetitionPeriod1
DL-CommonInformationPredef				
>dl-DPCH-InfoCommon				
>>commonTimeslotInfo				
>>>secondInterleavingMode	frameRelated	frameRelated	frameRelated	frameRelated
>>>tfc-Coding	8	8	8	16
>>>puncturingLimit	0.52	0.52	0.52	0.46
>>>repetitionPeriodAndLength	repetitionPeriod1	repetitionPeriod1	repetitionPeriod1	repetitionPeriod1
PhyCH INFORMATION 1.28Mcps TDD				
UL-DPCH-InfoPredef				
>commonTimeslotInfo				
>>secondInterleavingMode	frameRelated	frameRelated	frameRelated	frameRelated

>>tfci-Coding	16	8	8	8
>>puncturingLimit	0.64	0.60	0.64	1
>>repetitionPeriodAndLength	repetitionPeriod1	repetitionPeriod1	repetitionPeriod1	repetitionPeriod1
DL-CommonInformationPredef				
>dl-DPCH-InfoCommon				
>>commonTimeslotInfo				
>>>secondInterleavingMode	frameRelated	frameRelated	frameRelated	frameRelated
>>>tfci-Coding	16	8	8	8
>>>puncturingLimit	0.64	0.60	0.64	0.88
>>>repetitionPeriodAndLength	repetitionPeriod1	repetitionPeriod1	repetitionPeriod1	repetitionPeriod1

<b>Configuration</b>	<b>28.8 kbps streaming CS- data + 3.4 kbps signalling</b>	<b>57.6 kbps streaming CS- data + 3.4 kbps signalling</b>
Ref 34.108	16	17
Default configuration identity	8	9
<b>RB INFORMATION</b>		
rb-Identity	RB1: 1, RB2: 2, RB3: 3, RB5: 5	RB1: 1, RB2: 2, RB3: 3, RB5: 5
rlc-InfoChoice	Rlc-info	Rlc-info
>ul-RLC-Mode	RB1: UM RB2- RB3: AM RB5: TM	RB1: UM RB2- RB3: AM RB5: TM
>>transmissionRLC-DiscardMode	RB1: N/A RB2- RB3: NoDiscard RB5: N/A	RB1: N/A RB2- RB3: NoDiscard RB5: N/A
>>>maxDat	RB1: N/A RB2- RB3: 15 RB5: N/A	RB1: N/A RB2- RB3: 15 RB5: N/A
>>transmissionWindowSize	RB1: N/A RB2- RB3: 128 RB5: N/A	RB1: N/A RB2- RB3: 128 RB5: N/A
>>timerRST	RB1: N/A RB2- RB3: 300 RB5: N/A	RB1: N/A RB2- RB3: 300 RB5: N/A
>>max-RST	RB1: N/A RB2- RB3: 1 RB5: N/A	RB1: N/A RB2- RB3: 1 RB5: N/A
>>pollingInfo	RB1: N/A RB2- RB3: as below RB5: N/A	RB1: N/A RB2- RB3: as below RB5: N/A
>>>lastTransmissionPUPoll	RB2- RB3: FALSE	RB2- RB3: FALSE
>>>lastRetransmissionPUPoll	RB2- RB3: FALSE	RB2- RB3: FALSE
>>>timerPollPeriodic	RB2- RB3: 100	RB2- RB3: 100
>>segmentationIndication	RB1- RB3: N/A RB5: FALSE	RB1- RB3: N/A RB5: FALSE
>dl-RLC-Mode	RB1: UM RB2- RB3: AM RB5: TM	RB1: UM RB2- RB3: AM RB5: TM
>>inSequenceDelivery	RB1: N/A RB2- RB3: TRUE RB5: N/A	RB1: N/A RB2- RB3: TRUE RB5: N/A
>>receivingWindowSize	RB1: N/A RB2- RB3: 128 RB5: N/A	RB1: N/A RB2- RB3: 128 RB5: N/A
>>dl-RLC-StatusInfo	RB1: N/A RB2- RB3: as below RB5: N/A	RB1: N/A RB2- RB3: as below RB5: N/A
>>>timerStatusProhibit	RB2- RB3: 100	RB2- RB3: 100
>>>missingPUIndicator	RB2- RB3: FALSE	RB2- RB3: FALSE
>>>timerStatusPeriodic	RB2- RB3: 100	RB2- RB3: 100
>>segmentationIndication	RB1- RB3: N/A RB5: FALSE	RB1- RB3: N/A RB5: FALSE
rb-MappingInfo		
>UL-LogicalChannelMappings	OneLogicalChannel	OneLogicalChannel
>>ul-TransportChannelType	Dch	Dch
>>>transportChannelIdentity	RB1- RB3: 2 RB5: 1	RB1- RB3: 2 RB5: 1

>>logicalChannelIdentity	RB1: 1, RB2: 2, RB3: 3 RB5: N/A	RB1: 1, RB2: 2, RB3: 3 RB5: N/A
>>rlc-SizeList	RB1- RB3: all RB5: N/A	RB1- RB3: all RB5: N/A
>>mac-LogicalChannelPriority	RB1: 1, RB2: 2, RB3: 3 RB5: 5	RB1: 1, RB2: 2, RB3: 3 RB5: 5
>DL-logicalChannelMappingList		
>>Mapping option 1	One mapping option	One mapping option
>>>dl-TransportChannelType	Dch	Dch
>>>>transportChannelIdentity	RB1- RB3: 2 RB5: 1	RB1- RB3: 2 RB5: 1
>>>>logicalChannelIdentity	RB1: 1, RB2: 2, RB3: 3 RB5: N/A	RB1: 1, RB2: 2, RB3: 3 RB5: N/A
TrCH INFORMATION PER TrCH		
UL-AddReconfTransChInfoList		
>transportChannelIdentity	TrCH1: 1, TrCH2: 2	TrCH1: 1, TrCH2: 2
>transportFormatSet	DedicatedTransChTFS	DedicatedTransChTFS
>>dynamicTF-information		
>>>>tf0/ tf0,1	TrCH1: (0x576, 1x576, 2x576) TrCH2: (0x144, 1x144)	TrCH1: (0x576, 1x576, 2x576, 3x576, 4x576) TrCH2: (0x144, 1x144)
>>>>>rlcSize	TrCH1: OctetMode TrCH2:BitMode	TrCH1: OctetMode TrCH2:BitMode
>>>>>>sizeType	TrCH1: type 2, part1= 9, part2= 2 (576) TrCH2: type 2, part1= 2, part2= 0 (144)	TrCH1: type 2, part1= 9, part2= 2 (576) TrCH2: type 2, part1= 2, part2= 0 (144)
>>>>>numberOfTbSizeList	TrCH1: Zero, one, 2 TrCH2: Zero, one	TrCH1: Zero, one, 2, 3, 4 TrCH2: Zero, one
>>>>>logicalChannelList	All	All
>>semiStaticTF-Information		
>>>tti	TrCH1: 40 TrCH2: 40	TrCH1: 40 TrCH2: 40
>>>>channelCodingType	TrCH1: Turbo TrCH2: Convolutional	TrCH1: Turbo TrCH2: Convolutional
>>>>>codingRate	TrCH1: N/A TrCH2: Third	TrCH1: N/A TrCH2: Third
>>>>rateMatchingAttribute	TrCH1: 155 TrCH2: 160	TrCH1: 145 TrCH2: 160
>>>>crc-Size	TrCH1: 16 TrCH2: 16	TrCH1: 16 TrCH2: 16
DL-AddReconfTransChInfoList		
>dl-TransportChannelIdentity (should be as for UL)	TrCH1: 1, TrCH2: 2	TrCH1: 1, TrCH2: 2
>dfs-SignallingMode	SameAsUL	SameAsUL
>>transportFormatSet		
>>>dynamicTF-information		

>>>>tf0/ tf0,1		
>>>>rlcSize		
>>>>>sizeType		
>>>>>numberOfTbSizeList		
>>>>>logicalChannelList		
>>ULTrCH-Id	TrCH1: 1, TrCH2: 2	TrCH1: 1, TrCH2: 2
>dch-QualityTarget		
>>bler-QualityValue	TrCH1: $1 \times 10^{-2}$ TrCH2: Absent	TrCH1: $1 \times 10^{-2}$ TrCH2: Absent
TrCH INFORMATION, COMMON		
ul-CommonTransChInfo		
>tfcs-ID (TDD only)	1	1
>sharedChannelIndicator (TDD only)	FALSE	FALSE
>tfcs-Subset	Absent, not required	Absent, not required
>ul-TFCS	Normal TFCS signalling	Normal TFCS signalling
>>explicitTFCS- ConfigurationMode	Complete	Complete
>>>ctfcSize	Ctfc4Bit	Ctfc4Bit
>>>>TFCS representation	Addition	Addition
>>>>>TFCS list		
>>>>>>TFCS 1	(TF0, TF0)	(TF0, TF0)
>>>>>>>ctfc	0	0
>>>>>>>>gainFactorInform ation	Computed	Computed
>>>>>>>>referenceTFCSId	0	0
>>>>>>TFCS 2	(TF1, TF0)	(TF1, TF0)
>>>>>>>ctfc	1	1
>>>>>>>>gainFactorInform ation	Computed	Computed
>>>>>>>>> $\beta$ c (FDD only)	N/A	N/A
>>>>>>>>> $\beta$ d	N/A	N/A
>>>>>>>>>referenceTFCSId	0	0
>>>>>>TFCS 3	(TF2, TF0)	(TF2, TF0)
>>>>>>>ctfc	2	2
>>>>>>>>gainFactorInform ation	Computed	Computed
>>>>>>>>>referenceTFCSId	0	0
>>>>>>TFCS 4	(TF0, TF1)	(TF3, TF0)
>>>>>>>ctfc	3	3
>>>>>>>>gainFactorInform ation	Computed	Computed
>>>>>>>>> $\beta$ c (FDD only)	N/A	N/A
>>>>>>>>> $\beta$ d	N/A	N/A
>>>>>>>>>referenceTFCSId	0	0
>>>>>>TFCS 5	(TF1, TF1)	(TF4, TF0)
>>>>>>>ctfc	4	4
>>>>>>>>gainFactorInform ation	Computed	Computed
>>>>>>>>>referenceTFCSId	0	0
>>>>>>TFCS 6	(TF2, TF1)	(TF0, TF1)
>>>>>>>ctfc	5	5
>>>>>>>>gainFactorInform ation	Signalled	Computed
>>>>>>>>> $\beta$ c (FDD only)	8	N/A
>>>>>>>>> $\beta$ d	15	N/A
>>>>>>>>>referenceTFCSId	N/A	0
>>>>>>TFCS 7		(TF1, TF1)
>>>>>>>ctfc		6
>>>>>>>>gainFactorInform ation		Computed

>>>>>>referenceTFClId		0
>>>>>TFCS 8		(TF2, TF1)
>>>>>ctfc		7
>>>>>>gainFactorInformation		Computed
>>>>>>referenceTFClId		0
>>>>>TFCS 9		(TF3, TF1)
>>>>>ctfc		8
>>>>>>gainFactorInformation		Computed
>>>>>>referenceTFClId		0
>>>>>TFCS 10		(TF4, TF1)
>>>>>ctfc		9
>>>>>>gainFactorInformation		Signalled
>>>>>>>βc (FDD only)		8
>>>>>>>βd		15
>>>>>>>referenceTFClId		0
dl-CommonTransChInfo		
>tfcs-SignallingMode	Same as UL	Same as UL
PhyCH INFORMATION FDD		
UL-DPCH-InfoPredef		
>ul-DPCH-PowerControlInfo		
>>powerControlAlgorithm	Algorithm 1	Algorithm 1
>>>tpcStepSize	1	1
>tfci-Existence	TRUE	TRUE
>puncturingLimit	1	1
DL-CommonInformationPredef		
>dl-DPCH-InfoCommon		
>>spreadingFactor	64	32
>>pilotBits	8	8
>>positionFixed	Flexible	Flexible
PhyCH INFORMATION <u>3.84Mcps TDD</u>		
UL-DPCH-InfoPredef		
>ul-DPCH-PowerControlInfo		
>>dpch-ConstantValue	-20	-20
>commonTimeslotInfo		
>>secondInterleavingMode	frameRelated	frameRelated
>>>tfci-Coding	16	16
>>>puncturingLimit	0.50	0.50
>>>repetitionPeriodAndLength	repetitionPeriod1	repetitionPeriod1
DL-CommonInformationPredef		
>dl-DPCH-InfoCommon		
>>commonTimeslotInfo		
>>>secondInterleavingMode	frameRelated	frameRelated
>>>>tfci-Coding	16	16
>>>>puncturingLimit	0.46	0.46
>>>>repetitionPeriodAndLength	repetitionPeriod1	repetitionPeriod1
<a href="#">PhyCH INFORMATION</a> <a href="#">1.28Mcps TDD</a>		
<a href="#">UL-DPCH-InfoPredef</a>		
<a href="#">&gt;commonTimeslotInfo</a>		

>>secondInterleavingMode	frameRelated	frameRelated
>>tfc-Coding	16	16
>>puncturingLimit	0.64	0.72
>>repetitionPeriodAndLength	repetitionPeriod1	repetitionPeriod1
DL-CommonInformationPredefined		
>dl-DPCH-InfoCommon		
>>commonTimeslotInfo		
>>>secondInterleavingMode	frameRelated	frameRelated
>>>tfc-Coding	16	16
>>>puncturingLimit	0.64	0.72
>>>repetitionPeriodAndLength	repetitionPeriod1	repetitionPeriod1



## CHANGE REQUEST

⌘ **25.331 CR 973** ⌘ ev **-** ⌘ Current version: **4.1.0** ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

**Proposed change affects:** ⌘ (U)SIM  ME/UE  Radio Access Network  Core Network

<b>Title:</b>	⌘ Tadv in 1.28 Mcps TDD		
<b>Source:</b>	⌘ TSG-RAN WG2		
<b>Work item code:</b>	⌘ TEI	<b>Date:</b>	⌘ 30.7.2001
<b>Category:</b>	⌘ <b>F</b>	<b>Release:</b>	⌘ REL-4
	Use <u>one</u> of the following categories:		Use <u>one</u> of the following releases:
	<b>F</b> (correction)	<b>2</b> (GSM Phase 2)	
	<b>A</b> (corresponds to a correction in an earlier release)	<b>R96</b> (Release 1996)	
	<b>B</b> (addition of feature),	<b>R97</b> (Release 1997)	
	<b>C</b> (functional modification of feature)	<b>R98</b> (Release 1998)	
	<b>D</b> (editorial modification)	<b>R99</b> (Release 1999)	
	Detailed explanations of the above categories can be found in 3GPP <a href="#">TR 21.900</a> .	<b>REL-4</b> (Release 4)	
		<b>REL-5</b> (Release 5)	

<b>Reason for change:</b>	⌘ Inconsistency with 25.225 and 25.302		
<b>Summary of change:</b>	⌘ Reporting of Tadv enabled by replacing the parameter with UpPCHAdv which was erroneously included; 25.302 suggests that the measurement should be event triggered or periodic. Therefore an event is included. The event is triggered if changes greater than a threshold occur. A time stamp is included in order to relate the measurement to a corresponding measurement in the UTRAN.		
<b>Consequences if not approved:</b>	⌘ Tadv measurement reporting not possible.		

<b>Clauses affected:</b>	⌘ 10.3.7.76, 10.3.7.79, 10.3.7.80, 10.3.7.82, 10.3.7.112, 11.3, 14.6.1, 14.6.2.6, 14.6.2.6a (new)		
<b>Other specs affected:</b>	⌘ <input type="checkbox"/> Other core specifications	⌘ <input type="checkbox"/>	
	<input type="checkbox"/> Test specifications	<input type="checkbox"/>	
	<input type="checkbox"/> O&M Specifications	<input type="checkbox"/>	
<b>Other comments:</b>	⌘		

### How to create CRs using this form:

Comprehensive information and tips about how to create CRs can be found at: [http://www.3gpp.org/3G\\_Specs/CRs.htm](http://www.3gpp.org/3G_Specs/CRs.htm). Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.

- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

### 10.3.7.76 UE internal measured results

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
CHOICE <i>mode</i>	MP				
>FDD					
>>UE Transmitted Power	OP		UE Transmitted Power info 10.3.7.85		
>>>UE Rx-Tx report entries	OP	1 to <maxRL>			
>>>>Primary CPICH info	MP		Primary CPICH info 10.3.6.60	Primary CPICH info for each cell included in the active set	
>>>>UE Rx-Tx time difference type 1	MP		UE Rx-Tx time difference type 1 10.3.7.83	UE Rx-Tx time difference in chip for each RL included in the active set	
>TDD					
>>UE Transmitted Power list	OP	1 to <maxTS>		UE Transmitted Power for each used uplink timeslot in ascending timeslot number order	
>>>UE Transmitted Power	MP		UE Transmitted Power info 10.3.7.85		
>>CHOICE <i>TDD option</i>	MP				REL-4
>>>3.84 Mcps TDD					REL-4
>>>>Applied TA	OP		Uplink Timing Advance 10.3.6.95	Uplink timing advance applied by the UE	
>>>>1.28 Mcps TDD					REL-4
>>>> <a href="#">UpPCH<sub>ADV</sub>T<sub>ADV</sub></a>	OP		<a href="#">UpPCH<sub>ADV</sub>T<sub>ADV</sub></a> 10.3.7.112		REL-4

### 10.3.7.79 UE internal measurement quantity

The quantity the UE shall measure in case of UE internal measurement.

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
CHOICE <i>mode</i>	MP				
>FDD					
>>Measurement quantity	MP		Enumerated(UE Transmitted Power, UTRA Carrier RSSI, UE Rx-Tx time difference)		
>TDD					
>>Measurement quantity	MP		Enumerated(UE Transmitted Power, UTRA Carrier RSSI, <u>T<sub>ADV</sub></u> )	<a href="#">Measurement on Timing Advance is for 1.28Mcps TDD</a>	<a href="#">REL-4</a>
Filter coefficient	MP		Filter coefficient 10.3.7.9		

### 10.3.7.80 UE internal measurement reporting criteria

The triggering of the event-triggered reporting for a UE internal measurement. All events concerning UE internal measurements are labelled 6x where x is a, b, c.... In TDD, the events 6a - 6d are measured and reported on timeslot basis.

Event 6a: The UE Transmitted Power becomes larger than an absolute threshold

Event 6b: The UE Transmitted Power becomes less than an absolute threshold

Event 6c: The UE Transmitted Power reaches its minimum value

Event 6d: The UE Transmitted Power reaches its maximum value

Event 6e: The UE RSSI reaches the UEs dynamic receiver range

Event 6f (FDD): The UE Rx-Tx time difference for a RL included in the active set becomes larger than an absolute threshold

Event 6f (1.28 Mcps TDD): The time difference indicated by T<sub>ADV</sub> becomes larger than an absolute threshold

Event 6g: The UE Rx-Tx time difference for a RL included in the active set becomes less than an absolute threshold

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
Parameters sent for each UE internal measurement event	OP	1 to <maxMeas Event>			
>UE internal event identity	MP		UE internal event identity 10.3.7.75		
>Time-to-trigger	MP		Integer(0, 10, 20, 40, 60, 80, 100, 120, 160, 200, 240, 320, 640, 1280, 2560, 5000)	Time in ms. Indicates the period of time between the timing of event detection and the timing of sending Measurement Report.	
>UE Transmitted Power Tx power threshold	CV-clause 1		Integer(-50..33)	Power in dBm. In event 6a, 6b.	
>UE Rx-Tx time difference threshold	CV-clause 2		Integer(768..1280)	Time difference in chip. In event 6f, 6g.	
<u>&gt;T<sub>ADV</sub> threshold</u>	<u>CV-clause 3</u>		<u>Real (0..63 step 0.125)</u>	<u>Time difference in chip. In event 6f</u>	<u>REL-4</u>

Condition	Explanation
<i>Clause 1</i>	The IE is mandatory if "UE internal event identity" is set to "6a" or "6b", otherwise the IE is not needed
<i>Clause 2</i>	<u>In FDD</u> the IE is mandatory if "UE internal event identity" is set to "6f" or "6g", otherwise the IE is not needed
<u>Clause 3</u>	<u>In 1.28 Mcps TDD the IE is mandatory if "UE internal event identity" is set to "6f", otherwise the IE is not needed</u>

### 10.3.7.82 UE Internal reporting quantity

For all boolean types TRUE means inclusion in the report is requested.

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
UE Transmitted Power	MP		Boolean		
CHOICE <i>mode</i>	MP				
>FDD					
>>UE Rx-Tx time difference	MP		Boolean		
>TDD					
>>CHOICE <i>TDD option</i>					REL-4
>>>3.84 Mcps TDD				(no data)	REL-4
>>Applied TA	MP		Boolean		
>>>1.28 Mcps TDD					REL-4
>>>> <a href="#">UpPCH<sub>ADV</sub>T<sub>ADV</sub>_info</a>	MP		Boolean		REL-4

### 10.3.7.112 [UpPCH<sub>T</sub><sub>ADV</sub>\\_info](#)

NOTE: Only for 1.28Mcps TDD.

[UpPCH<sub>ADV</sub>T<sub>ADV</sub>](#) indicates the difference between the Rx timing and ~~initial~~-Tx timing of a UE.

Information Element/group name	Need	Multi	Type and reference	Semantics description	Version
<a href="#">UpPCH<sub>ADV</sub>T<sub>ADV</sub></a>	MP		Integer (0..3522047)	<del>In chips</del> As defined in [20]	REL-4
<a href="#">SFN</a>	<a href="#">MP</a>		<a href="#">Integer(0..4095)</a>	SFN during which the <a href="#">T<sub>ADV</sub></a> measurement was performed.	<a href="#">REL-4</a>

## 11.3 Information element definitions

```

T-ADVInfo ::= SEQUENCE {
    t-ADV INTEGER(0..2047),
    sfn INTEGER(0..4095)
}

UE-6FG-Event ::= SEQUENCE {
    timeToTrigger TimeToTrigger,
    -- in 1.28 Mcps TDD ue-RX-TX-TimeDifferenceThreshold corresponds to TADV Threshold
    ue-RX-TX-TimeDifferenceThreshold UE-RX-TX-TimeDifferenceThreshold
}

UE-InternalEventParam ::= CHOICE {
    event6a UE-6AB-Event,
    event6b UE-6AB-Event,
    event6c TimeToTrigger,
    event6d TimeToTrigger,
    event6e TimeToTrigger,
    event6f UE-6FG-Event,
    event6g UE-6FG-Event
}

UE-InternalMeasuredResults-LCR-r4 ::= SEQUENCE {
    ue-TransmittedPowerTDD-List UE-TransmittedPowerTDD-List OPTIONAL,
    upPCHt-ADVInfo INTEGER(0..352)T-ADVInfo OPTIONAL
}

....

UE-InternalReportCriteria ::= CHOICE {
    ue-InternalReportingCriteria UE-InternalReportingCriteria,
    periodicalReportingCriteria PeriodicalReportingCriteria,
    noReporting NULL
}

UE-InternalReportingCriteria ::= SEQUENCE {
    ue-InternalEventParamList UE-InternalEventParamList OPTIONAL
}

UE-InternalReportingQuantity ::= SEQUENCE {
    ue-TransmittedPower BOOLEAN,
    modeSpecificInfo CHOICE {
        fdd SEQUENCE {
            ue-RX-TX-TimeDifference BOOLEAN
        },
        tdd SEQUENCE {
            appliedTA BOOLEAN
        }
    }
}

UE-InternalReportingQuantity-r4 ::= SEQUENCE {
    ue-TransmittedPower BOOLEAN,
    modeSpecificInfo CHOICE {
        fdd SEQUENCE {
            ue-RX-TX-TimeDifference BOOLEAN
        },
        tdd SEQUENCE {
            tddOption CHOICE {
                tdd384 SEQUENCE {
                    appliedTA BOOLEAN
                },
                tdd128 SEQUENCE {
                    upPTSt-ADVInfo BOOLEAN
                }
            }
        }
    }
}

```

```
-- TABULAR: For 3.84 Mcps TDD only the first two values are used.
-- for 1.28 Mcps TDD ue-RX-TX-TimeDifference corresponds to TADV in the tabular
UE-MeasurementQuantity ::= ENUMERATED {
    ue-TransmittedPower,
    ue-Carrier-RSSI,
    ue-RX-TX-TimeDifference }
--in 1.28 Mcps TDD actual value for TADV Threshold = (UE-RX-TX-TimeDifferenceThreshold - 768) * 0.125
UE-RX-TX-TimeDifferenceThreshold ::= INTEGER (768..1280)
```



## 14.6 UE internal measurements

### 14.6.1 UE internal measurement quantities

For UE internal measurements the following measurement quantities exist:

1. UE transmission (Tx) power, for TDD measured on a timeslot basis.
2. UE received signal strength power (RSSI).
3. UE Rx-Tx time difference ([FDD only](#)).
4. [T<sub>ADV</sub> \(1.28 Mcps TDD\)](#)

#### 14.6.2.6 Reporting event 6F (FDD): The UE Rx-Tx time difference for a RL included in the active set becomes larger than an absolute threshold

When this event is ordered by UTRAN in a MEASUREMENT CONTROL message, the UE shall send a MEASUREMENT REPORT message when the UE Rx-Tx time difference becomes larger than the threshold defined by the IE "UE Rx-Tx time difference threshold".

#### 14.6.2.6a Reporting event 6F (1.28 Mcps TDD): Event 6f (1.28 Mcps TDD): The time difference indicated by $T_{ADV}$ becomes larger than an absolute threshold

When this event is ordered by UTRAN in a MEASUREMENT CONTROL message, the UE shall send a MEASUREMENT REPORT message when the  $T_{Adv}$  changes compared to the last reported value more than a predefined threshold as configured with IE "  $T_{ADV}$  Threshold".

The UE shall set the IE " $T_{ADV}$ " to the measured value and the IE "SFN" to the SFN during which the measurement was performed in the IE " $T_{ADV}$  Info".

## CHANGE REQUEST

⌘ **25.331 CR 974** ⌘ ev **-** ⌘ Current version: **4.1.0** ⌘

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the ⌘ symbols.

**Proposed change affects:** ⌘ (U)SIM  ME/UE  Radio Access Network  Core Network

<b>Title:</b>	⌘ Correction and clarification to PRACH in 1.28 Mcps TDD		
<b>Source:</b>	⌘ TSG-RAN WG2		
<b>Work item code:</b>	⌘ TEI	<b>Date:</b>	⌘ 2.7.2001
<b>Category:</b>	⌘ <b>F</b>	<b>Release:</b>	⌘ REL-4
	<i>Use <u>one</u> of the following categories:</i> <b>F</b> (correction) <b>A</b> (corresponds to a correction in an earlier release) <b>B</b> (addition of feature), <b>C</b> (functional modification of feature) <b>D</b> (editorial modification) Detailed explanations of the above categories can be found in 3GPP <a href="#">TR 21.900</a> .		<i>Use <u>one</u> of the following releases:</i> <b>2</b> (GSM Phase 2) <b>R96</b> (Release 1996) <b>R97</b> (Release 1997) <b>R98</b> (Release 1998) <b>R99</b> (Release 1999) <b>REL-4</b> (Release 4) <b>REL-5</b> (Release 5)

<b>Reason for change:</b>	⌘ Corrections and clarifications to PRACH handling in 1.28 Mcps TDD		
<b>Summary of change:</b>	⌘ Editorial improvement in power control related section and clarification of parameter by improved naming of elements. Alignment of RACH selection algorithm with FDD and 3.84 Mcps TDD descriptions Clarification on ASC setting in 1.28 Mcps TDD by providing similar example as for FDD and 3.84 Mcps TDD Clarification of transport formats for 1.28 Mcps TDD.		
<b>Consequences if not approved:</b>	⌘ Ambiguity in RACH handling in 1.28 Mcps TDD		

<b>Clauses affected:</b>	⌘ 8.5.7, 8.5.17, 8.5.18.2, 8.6.4.8, 8.6.6.29, 8.6.6.30, 10.3.6.78a, 10.3.6.96, 11		
<b>Other specs affected:</b>	⌘ <input type="checkbox"/> Other core specifications <input type="checkbox"/> Test specifications <input type="checkbox"/> O&M Specifications	⌘	
<b>Other comments:</b>	⌘		

### How to create CRs using this form:

Comprehensive information and tips about how to create CRs can be found at: [http://www.3gpp.org/3G\\_Specs/CRs.htm](http://www.3gpp.org/3G_Specs/CRs.htm). Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/>. For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.

- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

## 8.5.7 Open loop power control

For FDD and prior to PRACH or PCPCH transmission the UE shall:

- read the IEs "Primary CPICH DL TX power", "UL interference" and "Constant value" in System Information Block type 6 (or System Information Block type 5, if system information block type 6 is not being broadcast) and System Information Block type 7;
- measure the value for the CPICH\_RSCP;
- calculate the power for the first preamble as:

$$\text{Preamble\_Initial\_Power} = \text{Primary CPICH DL TX power} - \text{CPICH\_RSCP} + \text{UL interference} + \text{Constant Value}$$

Where,

Primary CPICH DL TX power shall have the value of IE "Primary CPICH DL TX power",

UL interference shall have the value of IE "UL interference"; and

Constant Value shall have the value of IE "Constant Value".

- as long as the physical layer is configured for PRACH or PCPCH transmission:
  - continuously recalculate the Preamble\_Initial\_Power when any of the broadcast parameters used in the above formula changes; and
  - resubmit to the physical layer the new calculated Preamble\_Initial\_Power.

For 3.84 Mcps TDD the UE shall:

- if in the IE "Uplink DPCH Power Control" the "CHOICE UL OL PC info" has the value "Broadcast UL OL PC info":
  - acquire Reference Power, Constant Values from System Information Block type 6 (or System Information Block type 5, according to 8.1.1.6.5), and  $I_{\text{BTS}}$  for all active UL timeslots from System Information Block type 14 on the BCH;
- otherwise:
  - acquire Reference Power, Constant Values and  $I_{\text{BTS}}$  for all active UL timeslots from the IE "Uplink DPCH Power Control".
- for PUSCH and PRACH power control:
  - acquire Reference Power, Constant Values and  $I_{\text{BTS}}$  for all active UL timeslots from System Information Block type 6 (or System Information Block type 5, according to 8.1.1.6.5) and System Information Block type 14 on the BCH,

calculate the UL transmit power according to the following formula for the PRACH continuously while the physical channel is active:

$$P_{\text{PRACH}} = L_{\text{PCCPCH}} + I_{\text{BTS}} + \text{RACH Constant value},$$

- 3dB shall be added to RACH Constant Value in the above equation for the case where RACH Spreading Factor = 8
- calculate the UL transmit power according to the following formula for the DPCH continuously while the physical channel is active:

$$P_{\text{DPCH}} = \alpha L_{\text{PCCPCH}} + (1-\alpha)L_0 + I_{\text{BTS}} + \text{SIR}_{\text{TARGET}} + \text{DPCH Constant value}$$

- calculate the UL transmit power according to the following formula for the PUSCH continuously while the physical channel is active:

$$P_{\text{USCH}} = \alpha L_{\text{PCCPCH}} + (1-\alpha)L_0 + I_{\text{BTS}} + \text{SIR}_{\text{TARGET}} + \text{USCH Constant value}$$

Where, for all the above equations for TDD the following apply:

- $P_{\text{PRACH}}$ ,  $P_{\text{DPCH}}$ , &  $P_{\text{USCH}}$ : Transmitter power level in dBm;
- Pathloss values:
  - $L_{\text{PCCPCH}}$ : Measurement representing path loss in dB based on beacon channels (the reference transmit power is signalled as the value of the IE "Primary CCPCH Tx Power" on BCH in System Information Block type 6 (or System Information Block type 5, according to 8.1.1.6.5), or individually signalled in the IE "Uplink DPCH Power Control").
  - $L_0$ : Long term average of path loss in dB;
  - If the midamble is used in the evaluation of  $L_{\text{PCCPCH}}$  and  $L_0$ , and the Tx diversity scheme used for the P-CCPCH involves the transmission of different midambles from the diversity antennas, the received power of the different midambles from the different antennas shall be combined prior to evaluation of the variables.
- $I_{\text{BTS}}$ : Interference signal power level at cell's receiver in dBm.  $I_{\text{BTS}}$  shall have the value of the IE "UL Timeslot Interference" (IE "UL Timeslot Interference" is broadcast on BCH in System Information Block type 14 or individually signalled to each UE in the IE "Uplink DPCH Power Control" for each active uplink timeslot).
- $\alpha$ :  $\alpha$  is a weighting parameter, which represents the quality of path loss measurements.  $\alpha$  may be a function of the time delay between the uplink time slot and the most recent down link PCCPCH time slot.  $\alpha$  is calculated at the UE.  $\alpha$  shall be smaller or equal to the value of the IE "Alpha". If the IE "Alpha" is not explicitly signalled to the UE  $\alpha$  shall be set to 1. If UE is capable of estimating its position by using the OTDOA IPDL method, the UE shall use the IPDL- $\alpha$  parameter.
- $\text{SIR}_{\text{TARGET}}$ : Target SNR in dB. This value is individually signalled to UEs in IE "UL target SIR" in IE "UL DPCH Power Control Info" or in IE "PUSCH Power Control Info" respectively.
- RACH Constant value: RACH Constant value shall have the value of the IE "RACH Constant value".
- DPCH Constant value: DPCH Constant value shall have the value of the IE "DPCH Constant value".
- USCH Constant Value: USCH Constant value shall have the value of the IE "USCH Constant value".
- Values received by dedicated signalling shall take precedence over broadcast values.
- If IPDLs are applied, the UE may increase UL Tx power by the value given in the IE "Max power increase". This power increase is only allowed in the slots between an idle slot and the next beacon slot.

For 1.28 Mcps TDD the UE shall:

- calculate the UL transmit power according to the following formula for each UpPCH code transmission:

$$P_{\text{UpPCH}} = L_{\text{PCCPCH}} + \text{PRX}_{\text{UpPCHdes}} + i * P_{\text{Wramp}}$$

- calculate the UL transmit power according to the following formula for each PRACH transmission:

$$P_{\text{PRACH}} = L_{\text{PCCPCH}} + \text{PRX}_{\text{PRACHdes}} + i * P_{\text{Wramp}}$$

- calculate the initial UL transmit power according to the following formula for the PUSCH. Once the UE receives TPC bits relating to the PUSCH then it transitions to closed loop power control. If successive PUSCH resource allocations are contiguous then no return is made to open loop power control at the beginning of the succeeding resource allocation.

$$P_{\text{USCH}} = \text{SIR}_{\text{TARGET}} + L_{\text{PCCPCH}} + \text{SIR}_{\text{TARGET}} + L_{\text{PCCPCH}}$$

- calculate the initial UL transmit power according to the following formula for the DPCH. Once the UE receives TPC bits relating to the uplink DPCH then it transitions to closed loop power control.

$$P_{\text{DPCH}} = \text{SIR}_{\text{TARGET}} + L_{\text{PCCPCH}} + \text{SIR}_{\text{TARGET}} + L_{\text{PCCPCH}}$$

Where:

- $P_{\text{UpPCH}}$ ,  $P_{\text{PRACH}}$ ,  $P_{\text{DPCH}}$ , &  $P_{\text{USCH}}$ : Transmitter power level in dBm,
- $L_{\text{PCCPCH}}$ : Measurement representing path loss in dB (reference transmit power "Primary CCPCH Tx Power" is broadcast on BCH in System Information Block type 5 and System Information Block type 6, or individually signalled to each UE in the IE "Uplink DPCH Power Control").
- $\text{SIR}_{\text{TARGET}}$ : Target SIR in dB. This value is individually signalled to UEs in IEs "UL DPCH Power Control Info" and "PUSCH Power Control Info".
- $i$  is the number of transmission attempts on UpPCH
- $\text{PRX}_{\text{PRACHdes}}$ : Desired PRACH RX power at the cell's receiver in dBm signalled to the UE by the network in the FPACH response to the UE's successful SYNC\_UL transmission.
- $\text{PRX}_{\text{UpPCHdes}}$ : Desired UpPCH RX power at the cell's receiver in dBm. The value is broadcast [in "PRX<sub>UpPCHdes</sub>" in IE "SYNC\\_UL info"](#) on BCH and shall be read on System Information Block type 5 and System Information Block type 6. It can also be signalled directly to the UE in a protocol message triggering a hard handover.
- $P_{\text{wramp}}$ : The UE shall increase its transmission power by the value of the IE "Power Ramping step" by every UpPCH transmission.

## 8.5.17 PRACH selection

For this version of the specification, when a UE selects a cell, the uplink frequency to be used for the initial PRACH transmission shall have a default duplex frequency spacing offset from the downlink frequency that the cell was selected on. The default duplex frequency separation to be used by the UE is specified in [35] (for FDD only).

The UE shall select a "PRACH system information" according to the following rule. The UE shall:

- select a default "PRACH system information" from the ones indicated in the IE "PRACH system information list" in System Information Block type 5 (applicable in Idle Mode and Connected Mode) or System Information Block type 6 (applicable in Connected Mode only), as follows:
  - [in FDD](#) if both RACH with 10 ms and 20 ms TTI are indicated in System Information Block type 5 or System Information Block type 6:
    - select the appropriate TTI based on power requirements, as specified in subclause 8.5.18.1;
  - [in 1.28 Mcps TDD both RACH with 5 ms, 10 ms and 20 ms TTI are indicated in System Information Block type 5 or System Information Block Type 6:](#)
    - [select the TTI according to 8.5.18.2](#)
- select a "PRACH system information" randomly from the ones listed in System Information Block type 5 or System Information Block type 6 as follows:

$$\text{"Index of selected PRACH"} = \text{floor}(\text{rand} * K)$$

where K is equal to the number of listed PRACH system informations that carry a RACH with the above selected TTI, "rand" is a random number uniformly distributed in the range 0,...,1, and "floor" refers to rounding down to nearest integer. PRACH system informations carrying RACHs with 10 and 20 ms TTI shall be counted separately. These PRACH system informations shall be indexed from 0 to K-1 in the order of their occurrence in System Information Block type 5 or System Information Block type 6. The random number generator is left to implementation. The scheme shall be implemented such that one of the available PRACH system informations is randomly selected with uniform probability. At start-up of the random number generator in the UE the seed shall be dependent on the IMSI of the UE or time, thereby avoiding that all UEs select the same RACH;

- in Connected mode:
  - select the PRACH according to the following preference:
    - if System Information Block type 6 is defined and PRACH info is included:
      - select PRACH from the PRACHs listed in System Information Block type 6;
    - if System Information Block type 6 is defined and no PRACH info is included:
      - select PRACH from the PRACHs listed in System Information Block type 5;
    - if no System Information Block type 6 is defined:
      - select PRACH from the PRACHs listed in System Information Block type 5.
  - reselect the default PRACH system information when a new cell is selected. RACH reselection may also be performed after each transmission of a Transport Block Set on RACH;
- for emergency call, the UE is allowed to select any of the available PRACH system informations.

After selecting a PRACH system information, the RRC in the UE shall configure the MAC and the physical layer for the RACH access according to the parameters included in the selected "PRACH system information" IE.

### 8.5.18.2 1.28Mcps TDD

In 1.28Mcps TDD, a RACH may be assigned a 5, 10 or 20 ms TTI. If, in one cell, more than one RACH is defined a UE shall select the RACH that is to be used for each transmission according to the following rule:



- if only one RACH is assigned a transport format that is suitable for the transmission of the transport block set:
  - select this RACH and the RACH's TTI;
- if more than one RACH is assigned a transport format that is suitable for the transmission of the transport block set:
  - select that which has the largest TTI;
- if two or more RACH having the same TTI fulfil this criteria:
  - select randomly between them as follows:

$$\text{"Index of selected PRACH"} = \text{floor}(\text{rand} * K)$$

— where K is equal to the number of listed PRACH system informations that carry an RACH with the above selected TTI and criteria, "rand" is a random number uniformly distributed in the range 0,...,1, and "floor" refers to rounding down to nearest integer. PRACH system informations carrying RACHs with 5, 10 and 20 ms TTI shall be counted separately. These PRACH system informations shall be indexed from 0 to K-1 in the order of their occurrence in SIB 5 or SIB 6. The random number generator is left to implementation. The scheme shall be implemented such that one of the available PRACH system informations is randomly selected with uniform probability. At start-up of the random number generator in the UE the seed shall be dependent on the IMSI of the UE or time, thereby avoiding that all UEs select the same RACH.

#### 8.6.4.8 RB mapping info

If the IE "RB mapping info" is included, the UE shall, for each multiplexing option of that RB:

- if the value of the IE "RLC size list" is set to "Explicit list":
  - if a "Transport format set" for that transport channel is included in the same message, and the value (index) of any IE "RLC size index" in the IE "RLC size index list" does not correspond to an "RLC size" in the IE transport format set of that transport channel given in the message; or
  - if a "Transport format set" for that transport channel is not included in the same message, and the value (index) of any IE "RLC size index" in the IE "RLC size index list" does not correspond to an "RLC size" in the stored transport format set of that transport channel; or
  - if a "Transport format set" for that transport channel is included in the same message, and the value of any IE "Logical channel list" in the transport format set is not set to "Configured"; or
  - if a "Transport format set" for that transport channel is included in the same message, and the value of any IE "Logical channel list" in the stored transport format set of that transport channel is not set to "Configured":
    - set the variable INVALID\_CONFIGURATION to TRUE;
- if the value of the IE "RLC size list" is set to "All":
  - if a "Transport format set" for that transport channel is included in the same message, and the value of any IE "Logical channel list" in the transport format set is not set to "Configured"; or
  - if a "Transport format set" for that transport channel is included in the same message, and the value of any IE "Logical channel list" in the stored transport format set of that transport channel is not set to "Configured":
    - set the variable INVALID\_CONFIGURATION to TRUE;
- if the value of the IE "RLC size list" is set to "Configured":
  - if a "Transport format set" for that transport channel is included in the same message, and the IE "Logical channel list" in the transport format set indicates that no "RLC size" is applicable for that RB; or
  - if a "Transport format set" for that transport channel is included in the same message, and the IE "Logical channel list" in the stored transport format set of that transport channel indicates that no "RLC size" is applicable for that RB:

- set the variable INVALID\_CONFIGURATION to TRUE;
- if that RB is using TM and the IE "Segmentation indication" is set to TRUE and, based on the multiplexing configuration resulting from this message, it is mapped onto the same transport channel as another RB:
  - set the variable INVALID\_CONFIGURATION to true;
- else:
  - delete all previously stored multiplexing options for that radio bearer;
  - store each new multiplexing option for that radio bearer;
  - select and configure the multiplexing options applicable for the transport channels to be used;
  - if the IE "Uplink transport channel type" is set to the value "RACH":
    - [in FDD](#) refer the IE "RLC size index" to the RACH Transport Format Set of the first PRACH received in the IE "PRACH system information list" received in SIB5 or SIB6;
    - [in TDD use the first Transport Format of the PRACH of the IE "PRACH system information list" at the position equal to the value in the IE "RLC size index"](#)
  - determine the sets of RLC sizes that apply to the logical channels used by that RB, based on the "RLC size list" and/or the "Logical Channel List" included in the applicable "Transport format set" (either the one received in the same message or the one stored if none were received);
  - if that RB is using AM and the set of RLC sizes applicable to the logical channel transferring data PDUs has more than one element:
    - set the variable INVALID\_CONFIGURATION to true;
  - if that RB is using AM and the RLC size applicable to the logical channel transporting data PDUs is different from the one derived from the previously stored configuration:
    - re-establish the corresponding RLC entity;
    - configure the corresponding RLC entity with the new RLC size;
  - if the variable CIPHERING\_STATUS is set to "Started":
    - if this IE was included in system information:
      - set the HFN values for the corresponding RLC entity equal to the value of the IE "START" for the CN domain stored in the variable LATEST\_CONFIGURED\_CN\_DOMAIN that will be included in the CELL UPDATE message that will be sent before the next transmission;
    - if this IE was included in CELL UPDATE CONFIRM:
      - set the HFN values for the corresponding RLC entity equal to the value of the IE "START" included in the latest transmitted CELL UPDATE message for the CN domain stored in the variable LATEST\_CONFIGURED\_CN\_DOMAIN;
    - if this IE was included in a reconfiguration message:
      - set the HFN values for the corresponding RLC entity equal to the value of the IE "START" that will be included in the reconfiguration complete message for the CN domain stored in the variable LATEST\_CONFIGURED\_CN\_DOMAIN;
  - if that RB is using UM, indicate the largest applicable RLC size to the corresponding RLC entity;
  - configure MAC multiplexing according to the selected multiplexing option;
  - configure the MAC with the logical channel priorities according to selected multiplexing option;
  - configure the MAC with the set of applicable RLC Sizes for each of the logical channels used for that RB;
  - if a transport channel that would not exist as a result of the message is referred to:

- set the variable INVALID\_CONFIGURATION to TRUE;
- if a multiplexing option that maps a logical channel corresponding to a TM-RLC entity onto RACH, CPCH, FACH or DSCH is included:
  - set the variable INVALID\_CONFIGURATION to TRUE;
- if a multiplexing option is included that realises the radio bearer on the uplink (resp. on the downlink) using two logical channels with different values of the IE "Uplink transport channel type" (resp. of the IE "Downlink transport channel type"):
  - set the variable INVALID\_CONFIGURATION to TRUE;
- if there is no multiplexing option applicable for the transport channels to be used:
  - set the variable INVALID\_CONFIGURATION to TRUE;
- if there is more than one multiplexing option applicable for the transport channels to be used:
  - set the variable INVALID\_CONFIGURATION to TRUE.

In case IE "RB mapping info" includes IE "Downlink RLC logical channel info" but IE "Number of downlink RLC logical channels" is absent, the parameter values are exactly the same as for the corresponding UL logical channels. In case two multiplexing options are specified for the UL, the first options shall be used as default for the DL. As regards the IE "Channel type", the following rule should be applied to derive the DL channel type from the UL channel included in the IE:

Channel used in UL	DL channel type implied by "same as"
DCH	DCH
RACH	FACH
CPCH	FACH
USCH	DSCH

### 8.6.6.29 ASC setting

If the IE "ASC setting" is included, the UE shall:

- establish the available signatures for this ASC as specified in the following:
  - renumber the list of available signatures specified in the IE "Available signature" included in the IE "PRACH info" from signature index 0 to signature index N-1, where N is the number of available signatures, starting with the lowest available signature number and continuing in sequence, in the order of increasing signature numbers;
  - consider as available signatures for this ASC the signatures included in this renumbered list from the index specified by the IE "Available signature Start Index" to the index specified by the IE "Available signature End Index";
- establish the available access slot sub-channels for this ASC as specified in the following:
  - if the IE "AICH transmission timing" included in the IE "AICH Info" is set to '0':
    - ignore the leftmost (most significant) bit (bit b3) of the bitstring specified by the IE "Assigned Sub-Channel Number";
    - repeat 4 times the 3 rightmost (least significant) bits (bits b2-b0) of the bitstring specified by the IE "Assigned Sub-Channel Number" to form a resulting bitstring 'b2 b1 b0 b2 b1 b0 b2 b1 b0 b2 b1 b0' of length 12 bits, where the leftmost bit is the most significant;
  - if the IE "AICH transmission timing" included in the IE "AICH Info" is set to '1':
    - repeat 3 times the bitstring (bits b3-b0) specified by the IE "Assigned Sub-Channel Number" to form a bitstring 'b3 b2 b1 b0 b3 b2 b1 b0 b3 b2 b1 b0' of length 12 bits, where the leftmost bit is the most significant;

- perform in both cases, for the resulting bitstring (that includes the repetitions) bit-wise logical AND operation with the IE "Available Sub Channel number" included in IE "PRACH info (for RACH)";
- consider as available sub-channels for this ASC the available sub-channels indicated in the resulting bitstring, after logical AND operation i.e. each bit set to 1 or 0 indicates availability or non-availability, respectively, of sub-channel number  $x$ , with  $x$  from 0 to 11, for the respective ASC.

NOTE 1: In FDD, the list of available signatures is renumbered from signature index 0 to signature index N-1, where N is the number of available signatures, starting with the lowest available signature number and continuing in sequence, in the order of increasing signature numbers.

- List of available signatures: 16 or fewer signatures are available.
- Example: only signatures 0, 5, 10 and 15 are available, then :
  - Signature 0 is: available signature index 0
  - Signature 5 is: available signature index 1
  - Signature 10 is: available signature index 2
  - Signature 15 is: available signature index 3

NOTE 2: In 3.84 Mcps TDD, the list of available channelisation codes (defined in PRACH info) is renumbered from channelisation code index 0 to channelisation code index N-1, where N is the number of available channelisation codes, starting with the lowest available channelisation code number and continuing in sequence, in the order of increasing channelisation code numbers

List of available channelisation codes : 8 or less channelisation codes are available.

The  $i$ -th bit of the bitmap defined in the IE "Available Channelisation Code indices" defines whether the channelisation code with the available channelisation code index  $i$  is to be used for this ASC (bit set means used, bit unset means not used). Only the low N bits shall be used in the bitmap, where N is the number of available channelisation codes defined in PRACH info.

Ex : spreading factor 16, channelisation codes 16/1, 16/2, 16/5, 16/10 are available :

- Channelisation code 16/1 is: available channelisation code index 0
- Channelisation code 16/2 is: available channelisation code index 1
- Channelisation code 16/5 is: available channelisation code index 2
- Channelisation code 16/10 is: available channelisation code index 3

Available Channelisation Code indices has the value '1100' means: Channelisation Codes 16/5 and 16/10 are available for this ASC.

NOTE 3: In 1.28 Mcps TDD, the list of available SYNC\_UL codes (defined in PRACH info) is numbered from SYNC\_UL code index 0 to SYNC\_UL code index N-1, where N is the number of available SYNC\_UL codes, starting with the lowest available SYNC\_UL code number and continuing in sequence, in the order of increasing SYNC\_UL code numbers

The  $i$ -th bit of the bitmap defined in the IE "Available SYNC\_UL codes indices" defines whether the SYNC\_UL code with the available SYNC\_UL code index  $i$  is to be used for this ASC (bit set means used, bit unset means not used). Only the low N bits shall be used in the bitmap, where N is the number of available SYNC\_UL codes defined in PRACH info.

- List of available SYNC\_UL codes: 8 or fewer SYNC\_UL codes are available.

Example: only signatures 0, 5, 6 and 7 are available, then :

- SYNC\_UL codes 0 is: available SYNC\_UL codes index 0
- SYNC\_UL codes 5 is: available SYNC\_UL codes index 1
- SYNC\_UL codes 6 is: available SYNC\_UL codes index 2
- SYNC\_UL codes 7 is: available SYNC\_UL codes index 3

Available SYNC\_UL codes indices has the value '1100' means: SYNC\_UL codes 6 and 7 are available for this ASC.

NOTE 43: In TDD, the subchannel description is found in [33].

### 8.6.6.30 SRB delay, PC preamble (FDD only)

When the IE "SRB delay" and IE "PC preamble" is received in a message that results in a configuration of uplink DPCH, the UE shall:

- after the establishment of the uplink physical channel, send DPCH and no DPDCH according to [26] during the number of frames indicated in the IE "PC preamble"; and
- then not send any data on signalling radio bearers RB0 to RB4 during the number of frames indicated in the IE "SRB delay".

### 10.3.6.78a SYNC\_UL info

NOTE: Only for 1.28 Mcps TDD.

Information Element/ Group name	Need	Multi	Type and reference	Semantics description	Version
SYNC_UL codes bitmap	MP		Bitstring(8)	00000001 indicates code 0 can be used, 10000001 indicates that codes 0 and 7 can be used.	REL-4
<u>PRX<sub>Up</sub>PCHdes<sub>UL</sub>TargetSIR</u>	MP		Real(-11 .. 20 by step of 0.5)	In dB	REL-4
Power Ramping Step	MP		Integer(0,1,2,3)	In dB	REL-4
Max SYNC_UL Transmissions	MP		Integer(1,2,4,8)	Maximum numbers of SYNC_UL transmissions in a power ramping sequence.	REL-4
Mmax	MP		Integer(1..32)	Maximum number of synchronisation attempts.	REL-4

### 10.3.6.96 Uplink Timing Advance Control

NOTE: Only for TDD

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
CHOICE <i>Timing Advance</i>	MP				
>Disabled			Null	Indicates that no timing advance is applied	
>Enabled					
>>CHOICE <i>TDD option</i>	MP				REL-4
>>>3.84 Mcps TDD					REL-4
>>>>UL Timing Advance	MD		Uplink Timing Advance 10.3.6.95	Absolute timing advance value to be used to avoid large delay spread at the NodeB. Default value is the existing value for uplink timing advance.	
>>>>Activation Time	OP		Activation Time 10.3.3.1	Frame number timing advance is to be applied. This IE is required when a new UL Timing Advance adjustment is specified and Activation Time is not otherwise specified in the RRC message.	
>>>1.28 Mcps TDD				(no data)	REL-4
>>>>Uplink synchronisation parameters	MD			Default: Uplink synchronisation <a href="#">parametersstep size</a> is 1. Uplink synchronisation frequency is 1.	REL-4
>>>>Uplink synchronisation step size	MP		Integer(1..8)	This parameter specifies the step size to be used for the adjustment of the uplink transmission timing	REL-4
>>>>Uplink synchronisation frequency	MP		Integer(1..8)	This parameter specifies the frequency of the adjustment of the uplink transmission timing	REL-4
>>>>Synchronization parameters	OP				
>>>>>SYNC_UL codes bitmap	MD		Bitstring(8)	00000001 indicates code 0 can be used, 10000001 indicates that codes 0 and 7 can be used. Default: all SYNC_UL codes can be used	REL-4
>>>>>FPACH info	MP		FPACH info 10.3.6. <a href="#">35a?</a>		REL-4
>>>>>SYNC_UL procedure	MD			Default is: Max SYNC_UL Transmission is 2.	REL-4

				Power Ramping Step is 2.	
>>>>>Max SYNC_UL Transmissions	MP		Integer(1,2,4,8)	Maximum numbers of SYNC_UL transmissions in a power ramping sequence.	REL-4
>>>>>Power Ramping Step	MP		Integer(0,1,2,3)	In dB	REL-4

```
SYNC-UL-Info-r4 ::=                               SEQUENCE {
    sync-UL-Codes-Bitmap                          BIT STRING ( SIZE (8)),
    prxUpPCHdesul-TargetSIR                    INTEGER (0..62),
    -- Actual value = (IE value * 0.5) - 11
    UL-TargetSIR,
    powerRampingStep                              INTEGER (0..3),
    max-SYNC-UL-Transmissions                     ENUMERATED { tr1, tr2, tr4, tr8 } ,
    mmax                                           INTEGER(1..32)
}
```