

TSG-RAN Meeting #28
Quebec, Canada, 01-03 June 2005

RP-050310
agenda item 7.7.4

Source: TSG-RAN WG2.

Title: CRs (Rel-5 & Rel-6) to WG2 specifications for the removal of dedicated pilot as sole phase reference

The following CRs are in RP-050310:

Spec	CR	Rev	Phase	Subject	Cat	Version-Current	Version-New	Doc-2nd-Level	Workitem
25.306	0114	-	Rel-5	Feature Clean Up: Removal of dedicated pilot as sole phase reference	C	5.10.0	5.11.0	R2-051628	TEI5
25.306	0115	-	Rel-6	Feature Clean Up: Removal of dedicated pilot as sole phase reference	C	6.4.1	6.5.0	R2-051629	TEI5
25.331	2590	-	Rel-5	Feature Clean Up: Removal of dedicated pilot as sole phase reference	C	5.12.1	5.13.0	R2-051630	TEI5
25.331	2591	-	Rel-6	Feature Clean Up: Removal of dedicated pilot as sole phase reference	C	6.5.0	6.6.0	R2-051631	TEI5

CHANGE REQUEST

25.306 CR 0114 # rev - # Current version: 5.10.0

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the # symbols.

Proposed change affects: UICC apps ME Radio Access Network Core Network

Title:	# Feature Clean Up: Removal of dedicated pilot as sole phase reference		
Source:	# RAN WG2		
Work item code:	# TEI5	Date:	# 20/04/2005
Category:	# C	Release:	# Rel-5
	<i>Use <u>one</u> of the following categories:</i> F (correction) A (corresponds to a correction in an earlier release) B (addition of feature), C (functional modification of feature) D (editorial modification) Detailed explanations of the above categories can be found in 3GPP TR 21.900 .		<i>Use <u>one</u> of the following releases:</i> Ph2 (GSM Phase 2) R96 (Release 1996) R97 (Release 1997) R98 (Release 1998) R99 (Release 1999) Rel-4 (Release 4) Rel-5 (Release 5) Rel-6 (Release 6) Rel-7 (Release 7)

Reason for change:	# At RAN#27 it was agreed to remove the support for dedicated pilots as sole phase reference from the specifications as part of a feature cleanup process.
Summary of change:	# The support for dedicated pilots as sole phase reference is removed from the specification.
Consequences if not approved:	# If the CR is not approved then decision taken in RAN#23 will not be applied to the specs. The redundant support for dedicated pilots as sole phase reference feature will remain in the specifications.

Clauses affected:	# 4.5.3, 5.1, 5.2.2										
Other specs affected:	<table border="1" style="display: inline-table; border-collapse: collapse;"> <tr> <td style="width: 20px; text-align: center;">Y</td> <td style="width: 20px; text-align: center;">N</td> </tr> <tr> <td style="text-align: center;">X</td> <td style="text-align: center;"></td> </tr> <tr> <td style="text-align: center;"></td> <td style="text-align: center;">X</td> </tr> <tr> <td style="text-align: center;"></td> <td style="text-align: center;">X</td> </tr> </table> Other core specifications	Y	N	X			X		X	#	25.331, 25.306, 25.211, 25.214, 25.101
Y	N										
X											
	X										
	X										
Other comments:	#										

How to create CRs using this form:

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>. Below is a brief summary:

- 1) Fill out the above form. The symbols above marked # contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be

downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.

- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

4.5.3 FDD Physical channel parameters in downlink

Maximum number of DPCH/PDSCH codes to be simultaneously received

Defines the number of codes the UE is capable of receiving in parallel. For DPCH in soft/softer handover, each DPCH is only calculated once in this capability. The capability does not include codes used for S-CCPCH.

Maximum number of physical channel bits received in any 10 ms interval (DPCH, PDSCH, S-CCPCH)

Defines the number of physical channel bits the UE is capable of receiving. For DPCH in soft/softer handover, each DPCH is only calculated once in this capability.

The number of DPCH channel bits indicates the capability of the UE when operating in non-compressed mode.

The parameter also indicates the capability of the UE to support compressed mode by spreading factor reduction as follows. The UE shall:

- for parameter values up to and including 9600 bits:
 - support compressed mode by spreading factor reduction when operating at any value up to the reported capability.
- for parameter values greater than 9600 bits:
 - support compressed mode by spreading factor reduction when operating at any value up to the greater of:
 - half the reported capability; or
 - 9600bits.

NOTE: Compressed mode by spreading factor reduction is not applicable when operating at spreading factor 4.

Support for SF 512

Defines whether the UE supports spreading factor 512 in downlink or not.

Support of PDSCH

Defines whether the UE supports PDSCH or not.

Support of HS-PDSCH

Defines whether the UE supports HS-PDSCH or not.

Simultaneous reception of SCCPCH and DPCH

Defines whether the UE supports simultaneous reception of SCCPCH and DPCH or not.

NOTE: Simultaneous reception of SCCPCH and DPCH, i.e. simultaneous reception of FACH and DCH is required for e.g. DRAC procedure

Simultaneous reception of SCCPCH, DPCH and PDSCH

Defines whether the UE supports simultaneous reception of SCCPCH, DPCH and PDSCH or not. The PDSCH part of this capability is only relevant if the UE supports PDSCH, as covered by the capability "Support of PDSCH".

NOTE: Simultaneous reception of SCCPCH, DPCH and PDSCH, i.e. simultaneous reception of FACH, DCH and DSCH is required for e.g. simultaneous use of DSCH and the DRAC procedure.

Simultaneous reception of SCCPCH, DPCH and HS-PDSCH

Defines whether the UE supports simultaneous reception of SCCPCH, DPCH and HS-PDSCH or not. The HS-PDSCH part of this capability is only relevant if the UE supports HS-PDSCH, as covered by the capability "Support of HS-PDSCH".

NOTE: Simultaneous reception of SCCPCH, DPCH and HS-PDSCH, i.e. simultaneous reception of FACH, DCH and HS-PDSCH is required for e.g. simultaneous use of HS-PDSCH and the DRAC procedure.

Maximum number of simultaneous S-CCPCH radio links

Defines the maximum number of radio links on which the UE is capable of receiving S-CCPCH simultaneously.

~~Support of dedicated pilots for channel estimation~~

~~Defines whether the UE supports dedicated pilots for channel estimation or not.~~

~~Support of dedicated pilots for channel estimation of HS-DSCH~~

~~Defines whether the UE supports dedicated pilots for channel estimation of HS-PDSCH and HS-SCCH or not.~~

Maximum number of HS-DSCH codes received

Defines the maximum number of HS-DSCH codes the UE is capable of receiving.

Total number of soft channel bits in HS-DSCH

Defines the maximum number of soft channel bits over all HARQ processes. When explicit signalling is used, UTRAN configures Process Memory Size for each HARQ process so that the following criterion must be fulfilled in the configuration:

Total number of soft channel bits in HS-DSCH \geq sum of Process Memory Size of all the HARQ processes.

Minimum inter-TTI interval in HS-DSCH

Defines the distance from the beginning of a TTI to the beginning of the next TTI that can be assigned to the UE.

5 Possible UE radio access capability parameter settings

5.1 Value ranges

Table 5.1: UE radio access capability parameter value ranges

		UE radio access capability parameter	Value range
PDCP parameters		Support for RFC 2507	Yes/No
		Support for RFC 3095	Yes/No
		Support for RFC 3095 context relocation	Yes/No
		Support for loss-less SRNS relocation	Yes/No
		Maximum header compression context space	1024, 2048, 4096, 8192, 16384, 32768, 65536, 131072 bytes
		Maximum number of ROHC context sessions	2, 4, 8, 12, 16, 24, 32, 48, 64, 128, 256, 512, 1024, 16384
		Support for Reverse Decompression	Not supported, 1..65535
RLC and MAC-hs parameters		Total RLC AM and MAC-hs buffer size	2, 10, 50, 100, 150, 200, 300, 400, 500, 750, 1000 kBytes
		Maximum number of AM entities	3, 4, 5, 6, 8, 16, 30
		Maximum RLC AM window size	2047, 4095
PHY parameters	Transport channel parameters in downlink	Maximum sum of number of bits of all transport blocks being received at an arbitrary time instant	640, 1280, 2560, 3840, 5120, 6400, 7680, 8960, 10240, 20480, 40960, 81920, 163840
		Maximum sum of number of bits of all convolutionally coded transport blocks being received at an arbitrary time instant	640, 1280, 2560, 3840, 5120, 6400, 7680, 8960, 10240, 20480, 40960, 81920, 163840
		Maximum sum of number of bits of all turbo coded transport blocks being received at an arbitrary time instant	640, 1280, 2560, 3840, 5120, 6400, 7680, 8960, 10240, 20480, 40960, 81920, 163840
		Maximum number of simultaneous transport channels	4, 8, 16, 32
		Maximum number of simultaneous CCTrCH	1, 2, 3, 4, 5, 6, 7, 8
		Maximum total number of transport blocks received within TTIs that end within the same 10 ms interval	4, 8, 16, 32, 48, 64, 96, 128, 256, 512
		Maximum number of TFC	16, 32, 48, 64, 96, 128, 256, 512, 1024
		Maximum number of TF	32, 64, 128, 256, 512, 1024
		Support for turbo decoding	Yes/No
	Transport channel parameters in uplink	Maximum sum of number of bits of all transport blocks being transmitted at an arbitrary time instant	640, 1280, 2560, 3840, 5120, 6400, 7680, 8960, 10240, 20480, 40960, 81920, 163840
		Maximum sum of number of bits of all convolutionally coded transport blocks being transmitted at an arbitrary time instant	640, 1280, 2560, 3840, 5120, 6400, 7680, 8960, 10240, 20480, 40960, 81920, 163840
		Maximum sum of number of bits of all turbo coded transport blocks being transmitted at an arbitrary time instant	640, 1280, 2560, 3840, 5120, 6400, 7680, 8960, 10240, 20480, 40960, 81920, 163840
		Maximum number of simultaneous transport channels	2, 4, 8, 16, 32
		Maximum number of simultaneous CCTrCH of DCH type (TDD only)	1, 2, 3, 4, 5, 6, 7, 8

		UE radio access capability parameter	Value range		
		Maximum total number of transport blocks transmitted within TTIs that start at the same time	2, 4, 8, 16, 32, 48, 64, 96, 128, 256, 512		
		Maximum number of TFC	4, 8, 16, 32, 48, 64, 96, 128, 256, 512, 1024		
		Maximum number of TF	32, 64, 128, 256, 512, 1024		
		Support for turbo encoding	Yes/No		
FDD Physical channel parameters in downlink		Maximum number of DPCH/PDSCH codes to be simultaneously received	1, 2, 3, 4, 5, 6, 7, 8		
		Maximum number of physical channel bits received in any 10 ms interval (DPCH, PDSCH, S-CCPCH)	600, 1200, 2400, 3600, 4800, 7200, 9600, 14400, 19200, 28800, 38400, 48000, 57600, 67200, 76800		
		Support for SF 512	Yes/No		
		Support of PDSCH	Yes/No		
		Support of HS-PDSCH	Yes/No		
		Simultaneous reception of SCCPCH and DPCH	Yes/No		
		Simultaneous reception of SCCPCH, DPCH and PDSCH	Yes/No		
		Simultaneous reception of SCCPCH, DPCH and HS-PDSCH	Yes/No		
		Maximum number of simultaneous S-CCPCH radio links	1 NOTE: Only the value 1 is part of this release of the specification		
		Support of dedicated pilots for channel estimation	Yes		
		Support of dedicated pilots for channel estimation of HS-DSCH	Yes/No		
		FDD Physical channel parameters in uplink		Maximum number of DPDCH bits transmitted per 10 ms	600, 1200, 2400, 4800, 9600, 19200, 28800, 38400, 48000, 57600
				Support of PCPCH	Yes/No
TDD 3.84 Mcps physical channel parameters in downlink		Maximum number of timeslots per frame	1..14		
		Maximum number of physical channels per frame	1, 2, 3..224		
		Minimum SF	16, 1		
		Support of PDSCH	Yes/No		
		Support of HS-PDSCH	Yes/No		
		Maximum number of physical channels per timeslot	1..16		
TDD 3.84 Mcps physical channel parameters in uplink		Maximum Number of timeslots per frame	1..14		
		Maximum number of physical channels per timeslot	1, 2		
		Minimum SF	16, 8, 4, 2, 1		
		Support of PUSCH	Yes/No		
TDD 1.28 Mcps physical channel parameters in downlink		Maximum number of timeslots per subframe	1..6		
		Maximum number of physical channels per subframe	1, 2, 3, ..., 96		
		Minimum SF	16, 1		
		Support of PDSCH	Yes/No		
		Support of HS-PDSCH	Yes/No		
		Maximum number of physical channels per timeslot	1..16		
TDD 1.28 Mcps physical channel parameters in uplink		Support 8PSK	Yes/No		
		Maximum number of timeslots per subframe	1..6		
		Maximum number of physical channels per timeslot	1, 2		
		Minimum SF	16, 8, 4, 2, 1		
		Support of 8PSK	Yes/No		
TDD 1.28 Mcps physical channel parameters in uplink		Support of PUSCH	Yes/No		

		UE radio access capability parameter	Value range
RF parameters	FDD RF parameters	UE power class	3, 4 NOTE: Only power classes 3 and 4 are part of this release of the specification
		Tx/Rx frequency separation	190 Mhz 174.8 MHz to 205.2 MHz 134.8 MHz to 245.2 MHz
RF parameters	TDD 3.84 Mcps RF parameters	UE power class	2, 3 NOTE: Only power classes 2 and 3 are part of this release of the specification
		Radio frequency bands	a), b), c), a+b), a+c), b+c), a+b+c)
	TDD 1.28 Mcps RF parameters	UE power class	2, 3
		Radio frequency bands	a), b), c), a+b), a+c), b+c), a+b+c)
Multi-mode related parameters		Support of UTRA FDD	Yes/No
		Support of UTRA TDD 3.84 Mcps	Yes/No
		Support of UTRA TDD 1.28 Mcps	Yes/No
Multi-RAT related parameters		Support of GSM	Yes/No (per GSM frequency band)
		Support of multi-carrier	Yes/No
		Support of UTRAN to GERAN Network Assisted Cell Change	Yes/No
Security parameters		Support of ciphering algorithm UEA0	Yes
		Support of ciphering algorithm UEA1	Yes
		Support of integrity protection algorithm UIA1	Yes
UE positioning related parameters		Standalone location method(s) supported	Yes/No
		Network assisted GPS support	Network based / UE based / Both/ None
		GPS reference time capable	Yes/No
		Support for IPDL	Yes/No
		Support for OTDOA UE based method	Yes/No
		Support for Rx-Tx time difference type 2 measurement	Yes/No
		Support for UE Positioning assisted GPS measurement validity in CELL_PCH and URA_PCH RRC states	Yes
Measurement related capabilities		Need for downlink compressed mode	Yes/No (per frequency band, UTRA mode and RAT)
		Need for uplink compressed mode	Yes/No (per frequency band, UTRA mode and RAT)
General capabilities		Access Stratum release indicator	R99, REL-4, REL-5
DL capabilities with simultaneous HS-DSCH		DL capability with simultaneous HS-DSCH configuration	32 kbps, 64 kbps, 128 kbps, 384 kbps

Table 5.1a: FDD HS-DSCH physical layer categories

HS-DSCH category	Maximum number of HS-DSCH codes received	Minimum inter-TTI interval	Maximum number of bits of an HS-DSCH transport block received within an HS-DSCH TTI	Total number of soft channel bits
Category 1	5	3	7298	19200
Category 2	5	3	7298	28800
Category 3	5	2	7298	28800
Category 4	5	2	7298	38400
Category 5	5	1	7298	57600
Category 6	5	1	7298	67200

HS-DSCH category	Maximum number of HS-DSCH codes received	Minimum inter-TTI interval	Maximum number of bits of an HS-DSCH transport block received within an HS-DSCH TTI	Total number of soft channel bits
Category 7	10	1	14411	115200
Category 8	10	1	14411	134400
Category 9	15	1	20251	172800
Category 10	15	1	27952	172800
Category 11	5	2	3630	14400
Category 12	5	1	3630	28800

UEs of Categories 11 and 12 support QPSK only.

Table 5.1b: RLC and MAC-hs parameters for FDD HS-DSCH physical layer categories

HS-DSCH category	Maximum number of AM RLC entities	Minimum total RLC AM and MAC-hs buffer size [kBytes]
Category 1	6	50
Category 2	6	50
Category 3	6	50
Category 4	6	50
Category 5	6	50
Category 6	6	50
Category 7	8	100
Category 8	8	100
Category 9	8	150
Category 10	8	150
Category 11	6	50
Category 12	6	50

Table 5.1c: 1.28 Mcps TDD HS-DSCH physical layer categories

HS-DSCH category	Maximum number of HS-DSCH codes per timeslot	Maximum number of HS-DSCH timeslots per TTI	Maximum number of HS-DSCH transport channel bits that can be received within an HS-DSCH TTI	Total number of soft channel bits
Category 1	12	5	7016	28160
Category 2	12	5	7016	56320
Category 3	12	5	7016	84480
Category 4	16	5	7016	28160
Category 5	16	5	7016	56320
Category 6	16	5	7016	84480
Category 7	12	5	10204	40912
Category 8	12	5	10204	81824
Category 9	12	5	10204	122736
Category 10	16	5	10204	40912
Category 11	16	5	10204	81824
Category 12	16	5	10204	122736
Category 13	16	5	14056	56320
Category 14	16	5	14056	112640
Category 15	16	5	14056	168960

Table 5.1d: RLC and MAC-hs parameters for 1.28 Mcps TDD HS-DSCH physical layer categories

HS-DSCH category	Maximum number of AM RLC entities	Minimum total RLC AM and MAC-hs buffer size [kBytes]
------------------	-----------------------------------	--

HS-DSCH category	Maximum number of AM RLC entities	Minimum total RLC AM and MAC-hs buffer size [kBytes]
Category 1	6	50
Category 2	6	50
Category 3	6	50
Category 4	6	50
Category 5	6	50
Category 6	6	50
Category 7	6	50
Category 8	6	50
Category 9	6	50
Category 10	6	50
Category 11	6	50
Category 12	6	50
Category 13	6	100
Category 14	6	100
Category 15	6	100

Table 5.1e: 3.84 Mcps TDD HS-DSCH physical layer categories

HS-DSCH category	Maximum number of HS-DSCH codes per timeslot	Maximum number of HS-DSCH timeslots per TTI	Maximum number of HS-DSCH transport channel bits that can be received within an HS-DSCH TTI	Total number of soft channel bits
Category 1	16	2	12000	52992
Category 2	16	12	12000	52992
Category 3	16	4	24000	105984
Category 4	16	12	24000	105984
Category 5	16	6	36000	158976
Category 6	16	12	36000	158976
Category 7	16	12	53000	211968
Category 8	16	12	73000	264960
Category 9	16	12	102000	317952

Table 5.1f: RLC and MAC-hs parameters for 3.84 Mcps TDD HS-DSCH physical layer categories

HS-DSCH category	Maximum number of AM RLC entities	Minimum total RLC AM and MAC-hs buffer size [kBytes]
Category 1	6	50
Category 2	6	50
Category 3	6	50
Category 4	6	50
Category 5	6	100
Category 6	6	100
Category 7	6	150
Category 8	8	150
Category 9	8	200

5.2.2 Combinations of UE Radio Access Parameters for DL

Table 5.2.2.1: UE radio access capability parameter combinations, DL parameters

Reference combination of UE Radio Access capability parameters in DL	12 kbps class	32 kbps class	64 kbps class	128 kbps class	384 kbps class	768 kbps class	2048 kbps class
Transport channel parameters							
Maximum sum of number of bits of all transport blocks being received at an arbitrary time instant	640 (FDD) 1280(TDD)	1280	3840	3840	6400	10240	20480
Maximum sum of number of bits of all convolutionally coded transport blocks being received at an arbitrary time instant	640	640	640	640	640	640	640
Maximum sum of number of bits of all turbo coded transport blocks being received at an arbitrary time instant	NA (FDD) 1280(TDD)	1280	3840	3840	6400	10240	20480(1) 10240(2) NOTE 5
Maximum number of simultaneous transport channels	4	8 NOTE 4	8 NOTE 4	8 NOTE 4	8 NOTE 4	8 NOTE 4	16 NOTE 4
Maximum number of simultaneous CCTrCH (FDD)	1	1 NOTE 3	2/1 NOTE 2 NOTE 3	2/1 NOTE 2 NOTE 3	2 NOTE 3	2 NOTE 3	2 NOTE 3
Maximum number of simultaneous CCTrCH (TDD)	1 NOTE 3	2 NOTE 3	3 NOTE 3	3 NOTE 3	3 NOTE 3	4 NOTE 3	4 NOTE 3
Maximum total number of transport blocks received within TTIs that end at the same time	4	8	8	16	32	64	96
Maximum number of TFC	16	32	48	96	128	256	1024
Maximum number of TF	32	32	64	64	64	128	256
Support for turbo decoding	No (FDD) Yes (TDD)	Yes	Yes	Yes	Yes	Yes	Yes
Physical channel parameters (FDD)							
Maximum number of DPCH/PDSCH codes to be simultaneously received	1	1	2/1 NOTE 2	2/1 NOTE 2	3	3	3
Maximum number of physical channel bits received in any 10 ms interval (DPCH, PDSCH, S-CCPCH).	1200	1200	3600/2400 NOTE2	7200/4800 NOTE2	19200	28800	57600
Support for SF 512 for DPCH NOTE 6	No	No	No	No	No	No	No
Support of PDSCH	No	No	Yes/No NOTE 1	Yes/No NOTE 1	Yes	Yes	Yes
Support of HS-PDSCH	No	No	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1
Maximum number of simultaneous S-CCPCH radio links	1	1	1	1	1	1	1
Support of dedicated pilots for channel estimation	Yes NOTE 1 NOTE 7	Yes NOTE 1 NOTE 7	Yes NOTE 1 NOTE 7	Yes NOTE 1 NOTE 7	Yes NOTE 1 NOTE 7	Yes NOTE 1 NOTE 7	Yes NOTE 1 NOTE 7
Support of dedicated pilots for channel estimation of HS-DSCH	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1
Physical channel parameters (TDD 3.84 Mcps)							
Maximum number of timeslots per frame	1	1	2	4	5	10	12
Maximum number of physical channels per frame	5	8	9	14	28	64	136
Minimum SF	16	16	16	16	1/16 NOTE 1	1/16 NOTE 1	1/16 NOTE 1
Support of PDSCH	No	Yes/No NOTE 1	Yes	Yes	Yes	Yes	Yes

Reference combination of UE Radio Access capability parameters in DL	12 kbps class	32 kbps class	64 kbps class	128 kbps class	384 kbps class	768 kbps class	2048 kbps class
Support of HS-PDSCH	No	No	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1
Maximum number of physical channels per timeslot	5	8	9	9	9	9	13
Physical channel parameters (TDD 1.28 Mcps)							
Maximum number of timeslots per subframe	1	1	2	3	4	6	6
Maximum number of physical channels per subframe	5	8	12	18	43	77	77
Minimum SF	16	16	16	16	1/16 NOTE 1	1/16 NOTE 1	1
Support of PDSCH	No	Yes/No NOTE 1	Yes	Yes	Yes	Yes	Yes
Support of HS-PDSCH	No	No	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1
Maximum number of physical channels per timeslot	5	8	11	14	14	14	14
Support of 8PSK	No	No	No	No	No	No	Yes

NOTE 1: Options represent different combinations that should be supported with conformance tests.

NOTE 2: Options depend on the support of PDSCH. The highest value is required if PDSCH is supported.

NOTE 3: The given number does not contain the BCH CCTrCH of the current cell nor of the neighbour cells.

NOTE 4: The given number does not contain the BCH of the neighbour cell.

NOTE 5: (1) For FDD and 3.84 Mcps TDD (2) For 1.28 Mcps TDD.

NOTE 6: This UE capability does not relate to the support of CPCH in the uplink for which SF 512 is needed

~~NOTE 7: A UE conforming to this release of the specification shall set the support of channel estimation based on dedicated pilot bits to TRUE.~~

The reference combinations for HS-DSCH capabilities are shown in tables 5.2.2.2, 5.2.2.3 and 5.2.2.4. These tables are subject to further discussions in TSG-RAN WG1 and TSG-RAN WG2.

Table 5.2.2.2: FDD UE radio access capability parameter combinations, DL HS-DSCH parameters

Reference combination	1.2 Mbps class	3.6 Mbps class	7 Mbps class	10 Mbps class
FDD HS-DSCH category	Category 1	Category 5	Category 7	Category 9

Table 5.2.2.3: 1.28 Mcps TDD UE radio access capability parameter combinations, DL HS-DSCH parameters

Reference combination	1.4 Mbps class	2.0 Mbps class	2.8 Mbps class
1.28 Mcps TDD HS-DSCH Category	Category 1	Category 7	Category 13

Table 5.2.2.4: 3.84 Mcps TDD UE radio access capability parameter combinations, DL HS-DSCH parameters

Reference combination	1.2 Mbps class	2.4 Mbps class	3.6 Mbps class	7.3 Mbps class	10.2 Mbps class
3.84 Mcps TDD HS-DSCH category	Category 1	Category 3	Category 5	Category 8	Category 9

CHANGE REQUEST

25.306 CR 0115 # rev - # Current version: 6.4.1

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the # symbols.

Proposed change affects: UICC apps ME Radio Access Network Core Network

Title:	# Feature Clean Up: Removal of dedicated pilot as sole phase reference		
Source:	# RAN WG2		
Work item code:	# TEI5	Date:	# 20/04/2005
Category:	# C	Release:	# Rel-6
	Use <u>one</u> of the following categories: F (correction) A (corresponds to a correction in an earlier release) B (addition of feature), C (functional modification of feature) D (editorial modification) Detailed explanations of the above categories can be found in 3GPP TR 21.900 .		Use <u>one</u> of the following releases: Ph2 (GSM Phase 2) R96 (Release 1996) R97 (Release 1997) R98 (Release 1998) R99 (Release 1999) Rel-4 (Release 4) Rel-5 (Release 5) Rel-6 (Release 6) Rel-7 (Release 7)

Reason for change:	# At RAN#27 it was agreed to remove the support for dedicated pilots as sole phase reference from the specifications as part of a feature cleanup process.
Summary of change:	# The support for dedicated pilots as sole phase reference is removed from the specification.
Consequences if not approved:	# If the CR is not approved then decision taken in RAN#23 will not be applied to the specs. The redundant support for dedicated pilots as sole phase reference feature will remain in the specifications.

Clauses affected:	# 4.5.3, 5.1, 5.2.2										
Other specs affected:	<table border="1" style="display: inline-table; border-collapse: collapse;"> <tr> <td style="width: 20px; text-align: center;">Y</td> <td style="width: 20px; text-align: center;">N</td> </tr> <tr> <td style="text-align: center;">X</td> <td></td> </tr> <tr> <td></td> <td style="text-align: center;">X</td> </tr> <tr> <td></td> <td style="text-align: center;">X</td> </tr> </table> Other core specifications	Y	N	X			X		X	#	25.331, 25.306, 25.211, 25.214, 25.101
Y	N										
X											
	X										
	X										
	Test specifications										
	O&M Specifications										
Other comments:	#										

How to create CRs using this form:

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>. Below is a brief summary:

- 1) Fill out the above form. The symbols above marked # contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be

downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.

- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

4.5.3 FDD Physical channel parameters in downlink

Maximum number of DPCH/PDSCH codes to be simultaneously received

Defines the number of codes the UE is capable of receiving in parallel. For DPCH in soft/softer handover, each DPCH is only calculated once in this capability. The capability does not include codes used for S-CCPCH.

Maximum number of physical channel bits received in any 10 ms interval (DPCH, PDSCH, S-CCPCH)

Defines the number of physical channel bits the UE is capable of receiving. For DPCH in soft/softer handover, each DPCH is only calculated once in this capability.

The number of DPCH channel bits indicates the capability of the UE when operating in non-compressed mode.

The parameter also indicates the capability of the UE to support compressed mode by spreading factor reduction as follows. The UE shall:

- for parameter values up to and including 9600 bits:
 - support compressed mode by spreading factor reduction when operating at any value up to the reported capability.
- for parameter values greater than 9600 bits:
 - support compressed mode by spreading factor reduction when operating at any value up to the greater of:
 - half the reported capability; or
 - 9600bits.

NOTE: Compressed mode by spreading factor reduction is not applicable when operating at spreading factor 4.

Support for SF 512

Defines whether the UE supports spreading factor 512 in downlink or not.

Support of PDSCH

Defines whether the UE supports PDSCH or not.

Support of HS-PDSCH

Defines whether the UE supports HS-PDSCH or not.

Simultaneous reception of SCCPCH and DPCH

Defines whether the UE supports simultaneous reception of SCCPCH and DPCH or not.

NOTE: Simultaneous reception of SCCPCH and DPCH, i.e. simultaneous reception of FACH and DCH is required for e.g. DRAC procedure

Simultaneous reception of SCCPCH, DPCH and PDSCH

Defines whether the UE supports simultaneous reception of SCCPCH, DPCH and PDSCH or not. The PDSCH part of this capability is only relevant if the UE supports PDSCH, as covered by the capability "Support of PDSCH".

NOTE: Simultaneous reception of SCCPCH, DPCH and PDSCH, i.e. simultaneous reception of FACH, DCH and DSCH is required for e.g. simultaneous use of DSCH and the DRAC procedure.

Simultaneous reception of SCCPCH, DPCH and HS-PDSCH

Defines whether the UE supports simultaneous reception of SCCPCH, DPCH and HS-PDSCH or not. The HS-PDSCH part of this capability is only relevant if the UE supports HS-PDSCH, as covered by the capability "Support of HS-PDSCH".

NOTE: Simultaneous reception of SCCPCH, DPCH and HS-PDSCH, i.e. simultaneous reception of FACH, DCH and HS-PDSCH is required for e.g. simultaneous use of HS-PDSCH and the DRAC procedure.

Maximum number of simultaneous S-CCPCH radio links

Defines the maximum number of radio links on which the UE is capable of receiving S-CCPCH simultaneously.

~~Support of dedicated pilots for channel estimation~~

~~Defines whether the UE supports dedicated pilots for channel estimation or not.~~

~~Support of dedicated pilots for channel estimation of HS-DSCH~~

~~Defines whether the UE supports dedicated pilots for channel estimation of HS-PDSCH and HS-SCCH or not.~~

Maximum number of HS-DSCH codes received

Defines the maximum number of HS-DSCH codes the UE is capable of receiving.

Total number of soft channel bits in HS-DSCH

Defines the maximum number of soft channel bits over all HARQ processes. When explicit signalling is used, UTRAN configures Process Memory Size for each HARQ process so that the following criterion must be fulfilled in the configuration:

Total number of soft channel bits in HS-DSCH \geq sum of Process Memory Size of all the HARQ processes.

Minimum inter-TTI interval in HS-DSCH

Defines the distance from the beginning of a TTI to the beginning of the next TTI that can be assigned to the UE.

5 Possible UE radio access capability parameter settings

5.1 Value ranges

Table 5.1: UE radio access capability parameter value ranges

		UE radio access capability parameter	Value range
PDCP parameters	Support for RFC 2507		Yes/No
	Support for RFC 3095		Yes/No
	Support for RFC 3095 context relocation		Yes/No
	Support for loss-less SRNS relocation		Yes/No
	Support for loss-less DL RLC PDU size change		Yes/No
	Maximum header compression context space		1024, 2048, 4096, 8192, 16384, 32768, 65536, 131072 bytes
	Maximum number of ROHC context sessions		2, 4, 8, 12, 16, 24, 32, 48, 64, 128, 256, 512, 1024, 16384
	Support for Reverse Decompression		Not supported, 1..65535
RLC and MAC-hs parameters	Total RLC AM and MAC-hs buffer size		2, 10, 50, 100, 150, 200, 300, 400, 500, 750, 1000 kBytes
	Maximum number of AM entities		3, 4, 5, 6, 8, 16, 30
	Maximum RLC AM window size		2047, 4095
PHY parameters	Transport channel parameters in downlink	Maximum sum of number of bits of all transport blocks being received at an arbitrary time instant	640, 1280, 2560, 3840, 5120, 6400, 7680, 8960, 10240, 20480, 40960, 81920, 163840
		Maximum sum of number of bits of all convolutionally coded transport blocks being received at an arbitrary time instant	640, 1280, 2560, 3840, 5120, 6400, 7680, 8960, 10240, 20480, 40960, 81920, 163840
		Maximum sum of number of bits of all turbo coded transport blocks being received at an arbitrary time instant	640, 1280, 2560, 3840, 5120, 6400, 7680, 8960, 10240, 20480, 40960, 81920, 163840
		Maximum number of simultaneous transport channels	4, 8, 16, 32
		Maximum number of simultaneous CCTrCH	1, 2, 3, 4, 5, 6, 7, 8
		Maximum total number of transport blocks received within TTIs that end within the same 10 ms interval	4, 8, 16, 32, 48, 64, 96, 128, 256, 512
		Maximum number of TFC	16, 32, 48, 64, 96, 128, 256, 512, 1024
		Maximum number of TF	32, 64, 128, 256, 512, 1024
		Support for turbo decoding	Yes/No
	Transport channel parameters in uplink	Maximum sum of number of bits of all transport blocks being transmitted at an arbitrary time instant	640, 1280, 2560, 3840, 5120, 6400, 7680, 8960, 10240, 20480, 40960, 81920, 163840
		Maximum sum of number of bits of all convolutionally coded transport blocks being transmitted at an arbitrary time instant	640, 1280, 2560, 3840, 5120, 6400, 7680, 8960, 10240, 20480, 40960, 81920, 163840
		Maximum sum of number of bits of all turbo coded transport blocks being transmitted at an arbitrary time instant	640, 1280, 2560, 3840, 5120, 6400, 7680, 8960, 10240, 20480, 40960, 81920, 163840
		Maximum number of simultaneous transport channels	2, 4, 8, 16, 32
		Maximum number of simultaneous CCTrCH of DCH type (TDD only)	1, 2, 3, 4, 5, 6, 7, 8

		UE radio access capability parameter	Value range
		Maximum total number of transport blocks transmitted within TTIs that start at the same time	2, 4, 8, 16, 32, 48, 64, 96, 128, 256, 512
		Maximum number of TFC	4, 8, 16, 32, 48, 64, 96, 128, 256, 512, 1024
		Maximum number of TF	32, 64, 128, 256, 512, 1024
		Support for turbo encoding	Yes/No
FDD Physical channel parameters in downlink		Maximum number of DPCH/PDSCH codes to be simultaneously received	1, 2, 3, 4, 5, 6, 7, 8
		Maximum number of physical channel bits received in any 10 ms interval (DPCH, PDSCH, S-CCPCH)	600, 1200, 2400, 3600, 4800, 7200, 9600, 14400, 19200, 28800, 38400, 48000, 57600, 67200, 76800
		Support for SF 512	Yes/No
		Support of PDSCH	Yes/No
		Support of HS-PDSCH	Yes/No
		Simultaneous reception of SCCPCH and DPCH	Yes/No
		Simultaneous reception of SCCPCH, DPCH and PDSCH	Yes/No
		Simultaneous reception of SCCPCH, DPCH and HS-PDSCH	Yes/No
		Maximum number of simultaneous S-CCPCH radio links	1 NOTE: Only the value 1 is part of this release of the specification
		Support of dedicated pilots for channel estimation	Yes
		Support of dedicated pilots for channel estimation of HS-DSCH	Yes/No
FDD Physical channel parameters in uplink		Maximum number of DPDCH bits transmitted per 10 ms	600, 1200, 2400, 4800, 9600, 19200, 28800, 38400, 48000, 57600
		Support of PCPCH	Yes/No
		Support of E-DPDCH	Yes/No
TDD 3.84 Mcps physical channel parameters in downlink		Maximum number of timeslots per frame	1..14
		Maximum number of physical channels per frame	1, 2, 3..224
		Minimum SF	16, 1
		Support of PDSCH	Yes/No
		Support of HS-PDSCH	Yes/No
		Maximum number of physical channels per timeslot	1..16
TDD 3.84 Mcps physical channel parameters in uplink		Maximum Number of timeslots per frame	1..14
		Maximum number of physical channels per timeslot	1, 2
		Minimum SF	16, 8, 4, 2, 1
		Support of PUSCH	Yes/No
TDD 1.28 Mcps physical channel parameters in downlink		Maximum number of timeslots per subframe	1..6
		Maximum number of physical channels per subframe	1, 2, 3, ..., 96
		Minimum SF	16, 1
		Support of PDSCH	Yes/No
		Support of HS-PDSCH	Yes/No
		Maximum number of physical channels per timeslot	1..16
TDD 1.28 Mcps physical channel parameters in uplink		Support 8PSK	Yes/No
		Maximum number of timeslots per subframe	1..6
		Maximum number of physical channels per timeslot	1, 2
		Minimum SF	16, 8, 4, 2, 1
		Support of 8PSK	Yes/No
		Support of PUSCH	Yes/No

		UE radio access capability parameter	Value range
RF parameters	FDD RF parameters	UE power class	3, 4 NOTE: Only power classes 3 and 4 are part of this release of the specification
		Tx/Rx frequency separation	190 Mhz 174.8 MHz to 205.2 MHz 134.8 MHz to 245.2 MHz
RF parameters	TDD 3.84 Mcps RF parameters	UE power class	2, 3 NOTE: Only power classes 2 and 3 are part of this release of the specification
		Radio frequency bands	a), b), c), a+b), a+c), b+c), a+b+c)
	TDD 1.28 Mcps RF parameters	UE power class	2, 3
		Radio frequency bands	a), b), c), a+b), a+c), b+c), a+b+c)
Multi-mode related parameters		Support of UTRA FDD	Yes/No
		Support of UTRA TDD 3.84 Mcps	Yes/No
		Support of UTRA TDD 1.28 Mcps	Yes/No
Multi-RAT related parameters		Support of GSM	Yes/No (per GSM frequency band)
		Support of multi-carrier	Yes/No
		Support of UTRAN to GERAN Network Assisted Cell Change	Yes/No
Security parameters		Support of ciphering algorithm UEA0	Yes
		Support of ciphering algorithm UEA1	Yes
		Support of integrity protection algorithm UIA1	Yes
UE positioning related parameters		Standalone location method(s) supported	Yes/No
		Network assisted GPS support	Network based / UE based / Both/ None
		GPS reference time capable	Yes/No
		Support for IPDL	Yes/No
		Support for OTDOA UE based method	Yes/No
		Support for Rx-Tx time difference type 2 measurement	Yes/No
		Support for UE Positioning assisted GPS measurement validity in CELL_PCH and URA_PCH RRC states	Yes
		Support for SFN-SFN observed time difference type 2 measurement	Yes/No
Measurement related capabilities		Need for downlink compressed mode	Yes/No (per frequency band, UTRA mode and RAT)
		Need for uplink compressed mode	Yes/No (per frequency band, UTRA mode and RAT)
General capabilities		Access Stratum release indicator	R99, REL-4, REL-5
DL capabilities with simultaneous HS-DSCH		DL capability with simultaneous HS-DSCH configuration	32 kbps, 64 kbps, 128 kbps, 384 kbps
UL capabilities with simultaneous E-DCH		UL capabilities with simultaneous E-DCH	64 kbps

Table 5.1a: FDD HS-DSCH physical layer categories

HS-DSCH category	Maximum number of HS-DSCH codes received	Minimum inter-TTI interval	Maximum number of bits of an HS-DSCH transport block received within an HS-DSCH TTI	Total number of soft channel bits
Category 1	5	3	7298	19200
Category 2	5	3	7298	28800
Category 3	5	2	7298	28800
Category 4	5	2	7298	38400
Category 5	5	1	7298	57600

HS-DSCH category	Maximum number of HS-DSCH codes received	Minimum inter-TTI interval	Maximum number of bits of an HS-DSCH transport block received within an HS-DSCH TTI	Total number of soft channel bits
Category 6	5	1	7298	67200
Category 7	10	1	14411	115200
Category 8	10	1	14411	134400
Category 9	15	1	20251	172800
Category 10	15	1	27952	172800
Category 11	5	2	3630	14400
Category 12	5	1	3630	28800

UEs of Categories 11 and 12 support QPSK only.

Table 5.1b: RLC and MAC-hs parameters for FDD HS-DSCH physical layer categories

HS-DSCH category	Maximum number of AM RLC entities	Minimum total RLC AM and MAC-hs buffer size [kBytes]
Category 1	6	50
Category 2	6	50
Category 3	6	50
Category 4	6	50
Category 5	6	50
Category 6	6	50
Category 7	8	100
Category 8	8	100
Category 9	8	150
Category 10	8	150
Category 11	6	50
Category 12	6	50

Table 5.1c: 1.28 Mcps TDD HS-DSCH physical layer categories

HS-DSCH category	Maximum number of HS-DSCH codes per timeslot	Maximum number of HS-DSCH timeslots per TTI	Maximum number of HS-DSCH transport channel bits that can be received within an HS-DSCH TTI	Total number of soft channel bits
Category 1	12	5	7016	28160
Category 2	12	5	7016	56320
Category 3	12	5	7016	84480
Category 4	16	5	7016	28160
Category 5	16	5	7016	56320
Category 6	16	5	7016	84480
Category 7	12	5	10204	40912
Category 8	12	5	10204	81824
Category 9	12	5	10204	122736
Category 10	16	5	10204	40912
Category 11	16	5	10204	81824
Category 12	16	5	10204	122736
Category 13	16	5	14056	56320
Category 14	16	5	14056	112640
Category 15	16	5	14056	168960

Table 5.1d: RLC and MAC-hs parameters for 1.28 Mcps TDD HS-DSCH physical layer categories

HS-DSCH category	Maximum number of AM RLC entities	Minimum total RLC AM and MAC-hs buffer size [kBytes]
Category 1	6	50
Category 2	6	50
Category 3	6	50
Category 4	6	50
Category 5	6	50
Category 6	6	50
Category 7	6	50
Category 8	6	50
Category 9	6	50
Category 10	6	50
Category 11	6	50
Category 12	6	50
Category 13	6	100
Category 14	6	100
Category 15	6	100

Table 5.1e: 3.84 Mcps TDD HS-DSCH physical layer categories

HS-DSCH category	Maximum number of HS-DSCH codes per timeslot	Maximum number of HS-DSCH timeslots per TTI	Maximum number of HS-DSCH transport channel bits that can be received within an HS-DSCH TTI	Total number of soft channel bits
Category 1	16	2	12000	52992
Category 2	16	12	12000	52992
Category 3	16	4	24000	105984
Category 4	16	12	24000	105984
Category 5	16	6	36000	158976
Category 6	16	12	36000	158976
Category 7	16	12	53000	211968
Category 8	16	12	73000	264960
Category 9	16	12	102000	317952

Table 5.1f: RLC and MAC-hs parameters for 3.84 Mcps TDD HS-DSCH physical layer categories

HS-DSCH category	Maximum number of AM RLC entities	Minimum total RLC AM and MAC-hs buffer size [kBytes]
Category 1	6	50
Category 2	6	50
Category 3	6	50
Category 4	6	50
Category 5	6	100
Category 6	6	100
Category 7	6	150
Category 8	8	150
Category 9	8	200

Table 5.1g: FDD E-DCH physical layer categories

E-DCH category	Maximum number of E-DCH codes transmitted	Minimum spreading factor	Support for 10 and 2 ms TTI EDCH	Maximum number of bits of an E-DCH transport block transmitted within a 10 ms E-DCH TTI	Maximum number of bits of an E-DCH transport block transmitted within a 2 ms E-DCH TTI
Category 1	1	SF4	10 ms TTI only	7296	-
Category 2	2	SF4	10 ms and 2 ms TTI	14592	2919
Category 3	2	SF4	10 ms TTI only	14592	-
Category 4	2	SF2	10 ms and 2 ms TTI	20000	5837
Category 5	2	SF2	10 ms TTI only	20000	-
Category 6	4	SF2	10 ms and 2 ms TTI	20000	11520
NOTE: When 4 codes are transmitted in parallel, two codes shall be transmitted with SF2 and two with SF4					

5.2.2 Combinations of UE Radio Access Parameters for DL

Table 5.2.2.1: UE radio access capability parameter combinations, DL parameters

Reference combination of UE Radio Access capability parameters in DL	12 kbps class	32 kbps class	64 kbps class	128 kbps class	384 kbps class	768 kbps class	2048 kbps class
Transport channel parameters							
Maximum sum of number of bits of all transport blocks being received at an arbitrary time instant	640 (FDD) 1280(TDD)	1280	3840	3840	6400	10240	20480
Maximum sum of number of bits of all convolutionally coded transport blocks being received at an arbitrary time instant	640	640	640	640	640	640	640
Maximum sum of number of bits of all turbo coded transport blocks being received at an arbitrary time instant	NA (FDD) 1280(TDD)	1280	3840	3840	6400	10240	20480(1) 10240(2) NOTE 5
Maximum number of simultaneous transport channels	4	8 NOTE 4	8 NOTE 4	8 NOTE 4	8 NOTE 4	8 NOTE 4	16 NOTE 4
Maximum number of simultaneous CCTrCH (FDD)	1	1 NOTE 3	2/1 NOTE 2 NOTE 3	2/1 NOTE 2 NOTE 3	2/1 NOTE 2 NOTE 3	2/1 NOTE 2 NOTE 3	2/1 NOTE 2 NOTE 3
Maximum number of simultaneous CCTrCH (TDD)	1 NOTE 3	2 NOTE 3	3 NOTE 3	3 NOTE 3	3 NOTE 3	4 NOTE 3	4 NOTE 3
Maximum total number of transport blocks received within TTIs that end at the same time	4	8	8	16	32	64	96
Maximum number of TFC	16	32	48	96	128	256	1024
Maximum number of TF	32	32	64	64	64	128	256
Support for turbo decoding	No (FDD) Yes (TDD)	Yes	Yes	Yes	Yes	Yes	Yes
Support for loss-less DL RLC PDU size change	No	No	Yes/No	Yes/No	Yes/No	Yes/No	Yes/No
Physical channel parameters (FDD)							
Maximum number of DPCH/PDSCH codes to be simultaneously received	1	1	2/1 NOTE 2	2/1 NOTE 2	3	3	3
Maximum number of physical channel bits received in any 10 ms interval (DPCH, PDSCH, S-CCPCH).	1200	1200	3600/2400 NOTE2	7200/4800 NOTE2	19200	28800	57600
Support for SF 512 for DPCH NOTE 6	No	No	No	No	No	No	No
Support of PDSCH	No	No	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1
Support of HS-PDSCH	No	No	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1
Maximum number of simultaneous S-CCPCH radio links	1	1	1	1	1	1	1
Support of dedicated pilots for channel estimation	Yes NOTE 1 NOTE 7	Yes NOTE 1 NOTE 7	Yes NOTE 1 NOTE 7	Yes NOTE 1 NOTE 7	Yes NOTE 1 NOTE 7	Yes NOTE 1 NOTE 7	Yes NOTE 1 NOTE 7
Support of dedicated pilots for channel estimation of HS-DSCH	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1
Physical channel parameters (TDD 3.84 Mcps)							
Maximum number of timeslots per frame	1	1	2	4	5	10	12
Maximum number of physical channels per frame	5	8	9	14	28	64	136
Minimum SF	16	16	16	16	1/16 NOTE 1	1/16 NOTE 1	1/16 NOTE 1
Support of PDSCH	No	Yes/No	Yes	Yes	Yes	Yes	Yes

Reference combination of UE Radio Access capability parameters in DL	12 kbps class	32 kbps class	64 kbps class	128 kbps class	384 kbps class	768 kbps class	2048 kbps class
		NOTE 1					
Support of HS-PDSCH	No	No	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1
Maximum number of physical channels per timeslot	5	8	9	9	9	9	13
Physical channel parameters (TDD 1.28 Mcps)							
Maximum number of timeslots per subframe	1	1	2	3	4	6	6
Maximum number of physical channels per subframe	5	8	12	18	43	77	77
Minimum SF	16	16	16	16	1/16 NOTE 1	1/16 NOTE 1	1
Support of PDSCH	No	Yes/No NOTE 1	Yes	Yes	Yes	Yes	Yes
Support of HS-PDSCH	No	No	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1	Yes/No NOTE 1
Maximum number of physical channels per timeslot	5	8	11	14	14	14	14
Support of 8PSK	No	No	No	No	No	No	Yes

NOTE 1: Options represent different combinations that should be supported with conformance tests.

NOTE 2: Options depend on the support of PDSCH. The highest value is required if PDSCH is supported.

NOTE 3: The given number does not contain the BCH CCTrCH of the current cell nor of the neighbour cells.

NOTE 4: The given number does not contain the BCH of the neighbour cell.

NOTE 5: (1) For FDD and 3.84 Mcps TDD (2) For 1.28 Mcps TDD.

NOTE 6: This UE capability does not relate to the support of CPCH in the uplink for which SF 512 is needed

~~NOTE 7: A UE conforming to this release of the specification shall set the support of channel estimation based on dedicated pilot bits to TRUE.~~

The reference combinations for HS-DSCH capabilities are shown in tables 5.2.2.2, 5.2.2.3 and 5.2.2.4. These tables are subject to further discussions in TSG-RAN WG1 and TSG-RAN WG2.

Table 5.2.2.2: FDD UE radio access capability parameter combinations, DL HS-DSCH parameters

Reference combination	1.2 Mbps class	3.6 Mbps class	7 Mbps class	10 Mbps class
FDD HS-DSCH category	Category 1	Category 5	Category 7	Category 9

Table 5.2.2.3: 1.28 Mcps TDD UE radio access capability parameter combinations, DL HS-DSCH parameters

Reference combination	1.4 Mbps class	2.0 Mbps class	2.8 Mbps class
1.28 Mcps TDD HS-DSCH Category	Category 1	Category 7	Category 13

Table 5.2.2.4: 3.84 Mcps TDD UE radio access capability parameter combinations, DL HS-DSCH parameters

Reference combination	1.2 Mbps class	2.4 Mbps class	3.6 Mbps class	7.3 Mbps class	10.2 Mbps class
3.84Mcps TDD HS-DSCH category	Category 1	Category 3	Category 5	Category 8	Category 9

CHANGE REQUEST

25.331 CR 2590 # rev **-** # Current version: **5.12.1**

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the # symbols.

Proposed change affects: UICC apps ME Radio Access Network Core Network

Title:	# Feature Clean Up: Removal of dedicated pilot as sole phase reference		
Source:	# RAN WG2		
Work item code:	# TEI5	Date:	# 20/04/2005
Category:	# C	Release:	# Rel-5
	Use <u>one</u> of the following categories:		Use <u>one</u> of the following releases:
	F (correction)		Ph2 (GSM Phase 2)
	A (corresponds to a correction in an earlier release)		R96 (Release 1996)
	B (addition of feature),		R97 (Release 1997)
	C (functional modification of feature)		R98 (Release 1998)
	D (editorial modification)		R99 (Release 1999)
	Detailed explanations of the above categories can be found in 3GPP TR 21.900 .		Rel-4 (Release 4)
			Rel-5 (Release 5)
			Rel-6 (Release 6)
			Rel-7 (Release 7)

Reason for change:	# At RAN#27 it was agreed to remove the support for dedicated pilots as sole phase reference from the specifications as part of a feature cleanup process.
Summary of change:	# The support for dedicated pilots as sole phase reference is removed from the specification. <i>Implementation of this CR by a Release 99/4 UE will not cause compatibility issues</i>
Consequences if not approved:	# If the CR is not approved then decision taken in RAN#23 will not be applied to the specs. The redundant support for dedicated pilots as sole phase reference feature will remain in the specifications.

Clauses affected:	# 8.6.6.13, 10.3.3.25, 11.3, 11.5										
Other specs affected:	<table border="1" style="display: inline-table; border-collapse: collapse; text-align: center;"> <tr> <td style="width: 20px;">Y</td> <td style="width: 20px;">N</td> </tr> <tr> <td>X</td> <td></td> </tr> <tr> <td></td> <td>X</td> </tr> <tr> <td></td> <td>X</td> </tr> </table>	Y	N	X			X		X	Other core specifications	# 25.331, 25.306, 25.211, 25.214, 25.101
Y	N										
X											
	X										
	X										
		Test specifications									
		O&M Specifications									
Other comments:	#										

How to create CRs using this form:

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>. Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

8.6.6.12 Secondary CPICH info

If the IE Secondary CPICH info is included, the UE may:

- 1> use the channelisation code according to IE "channelisation code", with scrambling code according to IE "DL scrambling code" in the IE "Secondary CPICH info", for channel estimation of that radio link;
- 1> use the pilot bits on DPCCH for channel estimation.

If the IE Secondary CPICH info is not included, the UE shall:

- 1> not use any previously stored configuration corresponding to the usage of the Secondary CPICH info.

8.6.6.13 Primary CPICH usage for channel estimation

If the IE "Primary CPICH usage for channel estimation" is included and has the value "Primary CPICH may be used" the UE:

- 1> may use the Primary CPICH for channel estimation;
- 1> may use the pilot bits on DPCCH for channel estimation.

If the IE "Primary CPICH usage for channel estimation" is included and has the value "Primary CPICH shall not be used" the UE:

- 1> shall not use the Primary CPICH for channel estimation;
- 1> may use the Secondary CPICH for channel estimation;
- 1> may use the pilot bits on DPCCH for channel estimation.

NOTE: If the IE "Primary CPICH usage for channel estimation" has the value "Primary CPICH shall not be used" and the IE "Secondary CPICH info" is not included for that radio link then the UE behaviour is not specified.

10.3.3.25 Physical channel capability

Information Element/Group name	Need	Multi	Type and Reference	Semantics description	Version
Downlink physical channel capability information elements					
FDD downlink physical channel capability	CH- fdd_req_su p				
>Max no DPCH/PDSCH codes	MP		Integer (1..8)	Maximum number of DPCH/PDSCH codes to be simultaneously received	
>Max no physical channel bits received	MP		Integer (1200, 2400, 3600, 4800, 7200, 9600, 14400, 19200, 28800, 38400, 48000, 57600, 67200, 76800)	Maximum number of physical channel bits received in any 10 ms interval (DPCH, PDSCH, S-CCPCH)	
>Support for SF 512	MP		Boolean	TRUE means supported	
>Support of PDSCH	MP		Boolean	TRUE means supported	
>CHOICE Support of HS-PDSCH	CV- not_iRAT_ HoInfo				REL-5
>>Supported					REL-5
>>>HS-DSCH physical layer category	MP		Integer (1..64)		REL-5
>>>Support of dedicated pilots for channel estimation of HS-DSCH	MP		Boolean	TRUE means supported	REL-5
>>>Simultaneous reception of SCCPCH, DPCH and HS-PDSCH	MP		Boolean	TRUE means supported. This IE shall only be set to TRUE in the case the IE "Simultaneous reception of SCCPCH and DPCH" is set to TRUE	REL-5
>>Unsupported				(no data)	REL-5
>Simultaneous reception of SCCPCH and DPCH	MP		Boolean	TRUE means supported	
>Simultaneous reception of SCCPCH, DPCH and PDSCH	CV- if_sim_rec_ pdsch_ sup		Boolean	TRUE means supported	
>Max no of S-CCPCH RL	CV- if_sim_rec		Integer(1)	Maximum number of simultaneous S-CCPCH radio links	
>Support of dedicated pilots for channel estimation	MD		Enumerated (true)	Presence of this element means supported and absence not supported. This IE shall be set to TRUE in this	

Information Element/Group name	Need	Multi	Type and Reference	Semantics description	Version
				version of the protocol	
3.84 Mcps TDD downlink physical channel capability	CH-3.84_Mcps_tdd_req_s up				Name changed in REL-4
>Maximum number of timeslots per frame	MP		Integer (1..14)		
>Maximum number of physical channels per frame	MP		Integer (5..224)		
>Minimum SF	MP		Integer (1, 16)		
>Support of PDSCH	MP		Boolean	TRUE means supported	
>CHOICE <i>Support of HS-PDSCH</i>	CV-not_iRAT_HoInfo				REL-5
>>Supported					REL-5
>>>HS-DSCH physical layer category	MP		Integer (1..64)		REL-5
>>Unsupported				(no data)	REL-5
>Maximum number of physical channels per timeslot	MP		Integer (5..16)		
1.28 Mcps TDD downlink physical channel capability	CH-1.28_Mcps_tdd_req_s up				REL-4
>Maximum number of timeslots per subframe	MP		Integer (1..6)		REL-4
>Maximum number of physical channels per subframe	MP		Integer (1..96)		REL-4
>Minimum SF	MP		Integer (1, 16)		REL-4
>Support of PDSCH	MP		Boolean	TRUE means supported	REL-4
>CHOICE <i>Support of HS-PDSCH</i>	CV-not_iRAT_HoInfo				REL-5
>>Supported					REL-5
>>>HS-DSCH physical layer category	MP		Integer (1..64)		REL-5
>>Unsupported				(no data)	REL-5
>Maximum number of physical channels per timeslot	MP		Integer (1..16)		REL-4
>Support of 8PSK	MP		Boolean	TRUE means supported	REL-4
Uplink physical channel capability information elements					
FDD uplink physical channel capability	CH-fdd_req_s up				
>Maximum number of DPDCH bits transmitted per 10 ms	MP		Integer (600, 1200, 2400, 4800, 9600, 19200, 28800, 38400, 48000, 57600)		
>Support of PCPCH	MP		Boolean	TRUE means supported	
3.84 Mcps TDD uplink physical channel capability	CH-3.84_Mcps				Name changed

Information Element/Group name	Need	Multi	Type and Reference	Semantics description	Version
	<i>_tdd_req_sup</i>				in REL-4
>Maximum Number of timeslots per frame	MP		Integer (1..14)		
>Maximum number of physical channels per timeslot	MP		Integer (1, 2)		
>Minimum SF	MP		Integer (1, 2, 4, 8)		
>Support of PUSCH	MP		Boolean	TRUE means supported	
1.28 Mcps TDD uplink physical channel capability	CH- <i>1.28_Mcps_tdd_req_sup</i>				REL-4
>Maximum Number of timeslots per subframe	MP		Integer (1..6)		REL-4
>Maximum number of physical channels per timeslot	MP		Integer (1, 2)		REL-4
>Minimum SF	MP		Integer (1, 2, 4, 8, 16)		REL-4
>Support of PUSCH	MP		Boolean	TRUE means supported	REL-4
>Support of 8PSK	MP		Boolean	TRUE means supported	REL-4

Condition	Explanation
<i>if_sim_rec_pdsch_sup</i>	The IE is mandatory present if the IE "Simultaneous reception of SCCPCH and DPCH" = True and IE Support of PDSCH = True. Otherwise this field is not needed in the message.
<i>if_sim_rec</i>	The IE is mandatory present if the IE "capability Simultaneous reception of SCCPCH and DPCH" = True. Otherwise this field is not needed in the message.
<i>3.84_Mcps_tdd_req_sup</i>	The IE is mandatory present if the IE "TDD RF capability" is present with the IE "Chip rate capability" set to "3.84 Mcps" and a 3.84 Mcps TDD capability update has been requested in a previous message. Otherwise this field is not needed in the message.
<i>1.28_Mcps_tdd_req_sup</i>	The IE is mandatory present if the IE "TDD RF capability" is present with the IE "Chip rate capability" set to "1.28 Mcps" and a 1.28 Mcps TDD capability update has been requested in a previous message. Otherwise this field is not needed in the message.
<i>fdd_req_sup</i>	The IE is mandatory present if the IE "Multi-mode capability" has the value "FDD" or "FDD/TDD" and a FDD capability update has been requested in a previous message. Otherwise this field is not needed in the message.
<i>not_iRAT_HoInfo</i>	The CHOICE <i>Support of HS-PDSCH</i> is not needed in the INTER RAT HANDOVER INFO message. Otherwise, it is mandatory present.

10.3.6.21 Downlink DPCH info for each RL

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
CHOICE <i>mode</i>	MP				
>FDD					
>>Primary CPICH usage for channel estimation	MP		Primary CPICH usage for channel estimation 10.3.6.62		
>>DPCH frame offset	MP		Integer(0..38144 by step of 256)	Offset (in number of chips) between the beginning of the P-CCPCH frame and the beginning of the DPCH frame This is called $\tau_{DPCH,n}$ in [26]	
>>>Secondary CPICH info	OP		Secondary CPICH info 10.3.6.73		
>>>DL channelisation code	MP	1 to <maxDPCH-DLchan >		For the purpose of physical channel mapping [27] the DPCHs are numbered, starting from DPCH number 1, according to the order that they are contained in this IE.	
>>>>Secondary scrambling code	MD		Secondary scrambling code 10.3.6.74	Default is the same scrambling code as for the Primary CPICH	
>>>>Spreading factor	MP		Integer(4, 8, 16, 32, 64, 128, 256, 512)	Defined in CHOICE SF512-AndCodenumbers with "code number" in ASN.1	
>>>>Code number	MP		Integer(0..Spreading factor - 1)		
>>>>Scrambling code change	CH-SF/2		Enumerated (code change, no code change)	Indicates whether the alternative scrambling code is used for compressed mode method 'SF/2'.	
>>>TPC combination index	MP		TPC combination index 10.3.6.85		
>>>Power offset $P_{TPC-DPDCH}$	OP		Integer (0..24)	Power offset equals $P_{TPC} - P_{DPDCH}$, range 0..6 dB, in steps of 0.25 dB	REL-5
>>>SSDT Cell Identity	OP		SSDT Cell Identity 10.3.6.76		
>>>Closed loop timing adjustment mode	CH-TxDiversity Mode		Integer(1, 2)	It is present if Tx Diversity is used in the radio link.	
>TDD					
>>>DL CCTrCh List	OP	1..<max CCTrCH		DL physical channels to establish or reconfigure	

Information Element/Group name	Need	Multi	Type and reference	Semantics description	Version
		>		list.	
>>>TFCS ID	MD		Integer(1..8)	Identity of this CCTrCh. Default value is 1	
>>>Time info	MP		Time Info 10.3.6.83		
>>>Common timeslot info	MD		Common Timeslot Info 10.3.6.10	Default is the current Common timeslot info	
>>>Downlink DPCH timeslots and codes	MD		Downlink Timeslots and Codes 10.3.6.32	Default is to use the old timeslots and codes.	
>>>UL CCTrCH TPC List	MD	0..<max CCTrCH >		UL CCTrCH identities for TPC commands associated with this DL CCTrCH. Default is previous list or all defined UL CCTrCHs. This list is not required for 1.28 Mcps TDD and is to be ignored by the UE.	
>>>>UL TPC TFCS Identity	MP		Transport Format Combination Set Identity 10.3.5.21		
>>DL CCTrCH List to Remove	OP	1..<max CCTrCH >		DL physical channels to remove list.	
>>>TFCS ID	MP		Integer(1..8)		

Condition	Explanation
<i>SF/2</i>	The information element is mandatory present if the UE has a compressed mode pattern sequence configured in variable TGPS_IDENTITY or included in the message including IE "Downlink DPCH info for each RL", which is using compressed mode method "SF/2". Otherwise the IE is not needed.
<i>TxDiversity Mode</i>	This IE is mandatory present if any TX Diversity Mode is used on the radio link, i.e. if STTD, "closed loop mode 1" or "closed loop mode 2" is used on the radio link. Otherwise the IE is not needed.

11.3 Information element definitions

```

InformationElements DEFINITIONS AUTOMATIC TAGS ::=

-- *****
--
-- CORE NETWORK INFORMATION ELEMENTS (10.3.1)
--
-- *****

DL-PhysChCapabilityFDD-v380ext ::= SEQUENCE {
    -- dummy is not used in this version of the specification, it should
    -- not be sent and if received it should be ignored.
    supportOfDedicatedPilotsForChEstimationdummy SupportOfDedicatedPilotsForChEstimation
    OPTIONAL
}

SupportOfDedicatedPilotsForChEstimation ::= ENUMERATED { true }

-- PhysicalChannelCapability-hspdsch-r5 describes the HS-PDSCH physical channel capability
PhysicalChannelCapability-hspdsch-r5 ::= SEQUENCE {
    fdd-hspdsch CHOICE {
        supported SEQUENCE {
            hsdSCH-physical-layer-category HSDSCH-physical-layer-category,
            -- dummy is not used in this version of the specification and
            -- it should be ignored by the receiver.
            supportOfDedicatedPilotsForChannelEstimationOfHSDSCHdummy BOOLEAN,
            -- simultaneousSCCPCH-DPCH-HSDSCH-Reception shall be true only if the
            -- IE SimultaneousSCCPCH-DPCH-Reception indicates support of simultaneous
            -- reception of S-CCPCH and DPCH
            simultaneousSCCPCH-DPCH-HSDSCH-Reception BOOLEAN
        },
        unsupported NULL
    },
    tdd384-hspdsch CHOICE {
        supported HSDSCH-physical-layer-category,
        unsupported NULL
    },
    tdd128-hspdsch CHOICE {
        supported HSDSCH-physical-layer-category,
        unsupported NULL
    }
}

```

11.5 RRC information between network nodes

```

DL-PhysChCapabilityFDD-r4 ::=          SEQUENCE {
    maxNoDPCH-PDSCH-Codes              INTEGER (1..8),
    maxNoPhysChBitsReceived            MaxNoPhysChBitsReceived,
    supportForSF-512                   BOOLEAN,
    supportOfPDSCH                     BOOLEAN,
    simultaneousSCCPCH-DPCH-Reception   SimultaneousSCCPCH-DPCH-Reception,
    supportOfDedicatedPilotsForChEstimation dummy SupportOfDedicatedPilotsForChEstimation
    OPTIONAL
}

DL-PhysChCapabilityFDD-r5 ::=          SEQUENCE {
    maxNoDPCH-PDSCH-Codes              INTEGER (1..8),
    maxNoPhysChBitsReceived            MaxNoPhysChBitsReceived,
    supportForSF-512                   BOOLEAN,
    supportOfPDSCH                     BOOLEAN,
    simultaneousSCCPCH-DPCH-Reception   SimultaneousSCCPCH-DPCH-Reception,
    supportOfDedicatedPilotsForChEstimation SupportOfDedicatedPilotsForChEstimation OPTIONAL,
    fdd-hspdsch                       CHOICE {
        supported                      SEQUENCE {
            hsdSCH-physical-layer-category HSDSCH-physical-layer-category,
            supportOfDedicatedPilotsForChannelEstimationOfHSDSCH dummy BOOLEAN,
            -- simultaneousSCCPCH-DPCH-HSDSCH-Reception shall be true only if the
            -- IE SimultaneousSCCPCH-DPCH-Reception indicates support of simultaneous
            -- reception of S-CCPCH and DPCH
            simultaneousSCCPCH-DPCH-HSDSCH-Reception BOOLEAN
        },
        unsupported                     NULL
    }
}

```

CHANGE REQUEST

25.331 CR 2591 # rev - # Current version: 6.5.0

For **HELP** on using this form, see bottom of this page or look at the pop-up text over the # symbols.

Proposed change affects: UICC apps ME Radio Access Network Core Network

Title:	# Feature Clean Up: Removal of dedicated pilot as sole phase reference		
Source:	# RAN WG2		
Work item code:	# TEI5	Date:	# 20/04/2005
Category:	# C	Release:	# Rel-6
	Use <u>one</u> of the following categories: F (correction) A (corresponds to a correction in an earlier release) B (addition of feature), C (functional modification of feature) D (editorial modification) Detailed explanations of the above categories can be found in 3GPP TR 21.900 .		Use <u>one</u> of the following releases: Ph2 (GSM Phase 2) R96 (Release 1996) R97 (Release 1997) R98 (Release 1998) R99 (Release 1999) Rel-4 (Release 4) Rel-5 (Release 5) Rel-6 (Release 6) Rel-7 (Release 7)

Reason for change:	# At RAN#27 it was agreed to remove the support for dedicated pilots as sole phase reference from the specifications as part of a feature cleanup process.
Summary of change:	# The support for dedicated pilots as sole phase reference is removed from the specification. Implementation of this CR by a Release 99/4 UE will not cause compatibility issues
Consequences if not approved:	# If the CR is not approved then decision taken in RAN#23 will not be applied to the specs. The redundant support for dedicated pilots as sole phase reference feature will remain in the specifications.

Clauses affected:	# 8.6.6.13, 10.3.3.25, 11.3, 11.5										
Other specs affected:	<table border="1" style="display: inline-table; border-collapse: collapse;"> <tr> <td style="width: 20px; text-align: center;">Y</td> <td style="width: 20px; text-align: center;">N</td> </tr> <tr> <td style="text-align: center;">X</td> <td style="text-align: center;"></td> </tr> <tr> <td style="text-align: center;"></td> <td style="text-align: center;">X</td> </tr> <tr> <td style="text-align: center;"></td> <td style="text-align: center;">X</td> </tr> </table> Other core specifications	Y	N	X			X		X	#	25.331, 25.306, 25.211, 25.214, 25.101
Y	N										
X											
	X										
	X										
	Test specifications										
	O&M Specifications										
Other comments:	#										

How to create CRs using this form:

Comprehensive information and tips about how to create CRs can be found at <http://www.3gpp.org/specs/CR.htm>. Below is a brief summary:

- 1) Fill out the above form. The symbols above marked ⌘ contain pop-up help information about the field that they are closest to.
- 2) Obtain the latest version for the release of the specification to which the change is proposed. Use the MS Word "revision marks" feature (also known as "track changes") when making the changes. All 3GPP specifications can be downloaded from the 3GPP server under <ftp://ftp.3gpp.org/specs/> For the latest version, look for the directory name with the latest date e.g. 2001-03 contains the specifications resulting from the March 2001 TSG meetings.
- 3) With "track changes" disabled, paste the entire CR form (use CTRL-A to select it) into the specification just in front of the clause containing the first piece of changed text. Delete those parts of the specification which are not relevant to the change request.

8.6.6.13 Primary CPICH usage for channel estimation

If the IE "Primary CPICH usage for channel estimation" is included and has the value "Primary CPICH may be used" the UE:

- 1> may use the Primary CPICH for channel estimation;
- 1> may use the pilot bits on DPCCH for channel estimation.

If the IE "Primary CPICH usage for channel estimation" is included and has the value "Primary CPICH shall not be used" the UE:

- 1> shall not use the Primary CPICH for channel estimation;
- 1> may use the Secondary CPICH for channel estimation;
- 1> may use the pilot bits on DPCCH for channel estimation.

NOTE: If the IE "Primary CPICH usage for channel estimation" has the value "Primary CPICH shall not be used" and the IE "Secondary CPICH info" is not included for that radio link then the UE behaviour is not specified.

10.3.3.25 Physical channel capability

Information Element/Group name	Need	Multi	Type and Reference	Semantics description	Version
Downlink physical channel capability information elements					
FDD downlink physical channel capability	CH- fdd_req_su p				
>Max no DPCH/PDSCH codes	MP		Integer (1..8)	Maximum number of DPCH/PDSCH codes to be simultaneously received	
>Max no physical channel bits received	MP		Integer (1200, 2400, 3600, 4800, 7200, 9600, 14400, 19200, 28800, 38400, 48000, 57600, 67200, 76800)	Maximum number of physical channel bits received in any 10 ms interval (DPCH, PDSCH, S-CCPCH)	
>Support for SF 512	MP		Boolean	TRUE means supported	
>Support of PDSCH	MP		Boolean	TRUE means supported	
>CHOICE Support of HS-PDSCH	CV- not_iRAT_ HoInfo				REL-5
>>Supported					REL-5
>>>HS-DSCH physical layer category	MP		Integer (1..64)		REL-5
>>>Support of dedicated pilots for channel estimation of HS-DSCH	MP		Boolean	TRUE means supported	REL-5
>>>Simultaneous reception of SCCPCH, DPCH and HS-PDSCH	MP		Boolean	TRUE means supported. This IE shall only be set to TRUE in the case the IE "Simultaneous reception of SCCPCH and DPCH" is set to TRUE	REL-5
>>Unsupported				(no data)	REL-5
>Simultaneous reception of SCCPCH and DPCH	MP		Boolean	TRUE means supported	
>Simultaneous reception of SCCPCH, DPCH and PDSCH	CV- if_sim_rec_ pdsch_ sup		Boolean	TRUE means supported	
>Max no of S-CCPCH RL	CV- if_sim_rec		Integer(1)	Maximum number of simultaneous S-CCPCH radio links	
>Support of dedicated pilots for channel estimation	MD		Enumerated- (true)	Presence of this element means supported and absence not supported. This IE shall be set to TRUE in this	

Information Element/Group name	Need	Multi	Type and Reference	Semantics description	Version
				version of the protocol	
3.84 Mcps TDD downlink physical channel capability	CH-3.84_Mcps_tdd_req_s up				Name changed in REL-4
>Maximum number of timeslots per frame	MP		Integer (1..14)		
>Maximum number of physical channels per frame	MP		Integer (5..224)		
>Minimum SF	MP		Integer (1, 16)		
>Support of PDSCH	MP		Boolean	TRUE means supported	
>CHOICE <i>Support of HS-PDSCH</i>	CV-not_iRAT_HoInfo				REL-5
>>Supported					REL-5
>>>HS-DSCH physical layer category	MP		Integer (1..64)		REL-5
>>Unsupported				(no data)	REL-5
>Maximum number of physical channels per timeslot	MP		Integer (5..16)		
1.28 Mcps TDD downlink physical channel capability	CH-1.28_Mcps_tdd_req_s up				REL-4
>Maximum number of timeslots per subframe	MP		Integer (1..6)		REL-4
>Maximum number of physical channels per subframe	MP		Integer (1..96)		REL-4
>Minimum SF	MP		Integer (1, 16)		REL-4
>Support of PDSCH	MP		Boolean	TRUE means supported	REL-4
>CHOICE <i>Support of HS-PDSCH</i>	CV-not_iRAT_HoInfo				REL-5
>>Supported					REL-5
>>>HS-DSCH physical layer category	MP		Integer (1..64)		REL-5
>>Unsupported				(no data)	REL-5
>Maximum number of physical channels per timeslot	MP		Integer (1..16)		REL-4
>Support of 8PSK	MP		Boolean	TRUE means supported	REL-4
Uplink physical channel capability information elements					
FDD uplink physical channel capability	CH-fdd_req_s up				
>Maximum number of DPDCH bits transmitted per 10 ms	MP		Integer (600, 1200, 2400, 4800, 9600, 19200, 28800, 38400, 48000, 57600)		
>Support of PCPCH	MP		Boolean	TRUE means supported	
3.84 Mcps TDD uplink physical channel capability	CH-3.84_Mcps				Name changed

Information Element/Group name	Need	Multi	Type and Reference	Semantics description	Version
	<i>_tdd_req_sup</i>				in REL-4
>Maximum Number of timeslots per frame	MP		Integer (1..14)		
>Maximum number of physical channels per timeslot	MP		Integer (1, 2)		
>Minimum SF	MP		Integer (1, 2, 4, 8)		
>Support of PUSCH	MP		Boolean	TRUE means supported	
1.28 Mcps TDD uplink physical channel capability	CH- <i>1.28_Mcps_tdd_req_sup</i>				REL-4
>Maximum Number of timeslots per subframe	MP		Integer (1..6)		REL-4
>Maximum number of physical channels per timeslot	MP		Integer (1, 2)		REL-4
>Minimum SF	MP		Integer (1, 2, 4, 8, 16)		REL-4
>Support of PUSCH	MP		Boolean	TRUE means supported	REL-4
>Support of 8PSK	MP		Boolean	TRUE means supported	REL-4

Condition	Explanation
<i>if_sim_rec_pdsch_sup</i>	The IE is mandatory present if the IE "Simultaneous reception of SCCPCH and DPCH" = True and IE Support of PDSCH = True. Otherwise this field is not needed in the message.
<i>if_sim_rec</i>	The IE is mandatory present if the IE "capability Simultaneous reception of SCCPCH and DPCH" = True. Otherwise this field is not needed in the message.
<i>3.84_Mcps_tdd_req_sup</i>	The IE is mandatory present if the IE "TDD RF capability" is present with the IE "Chip rate capability" set to "3.84 Mcps" and a 3.84 Mcps TDD capability update has been requested in a previous message. Otherwise this field is not needed in the message.
<i>1.28_Mcps_tdd_req_sup</i>	The IE is mandatory present if the IE "TDD RF capability" is present with the IE "Chip rate capability" set to "1.28 Mcps" and a 1.28 Mcps TDD capability update has been requested in a previous message. Otherwise this field is not needed in the message.
<i>fdd_req_sup</i>	The IE is mandatory present if the IE "Multi-mode capability" has the value "FDD" or "FDD/TDD" and a FDD capability update has been requested in a previous message. Otherwise this field is not needed in the message.
<i>not_iRAT_HoInfo</i>	The CHOICE <i>Support of HS-PDSCH</i> is not needed in the INTER RAT HANDOVER INFO message. Otherwise, it is mandatory present.

11.3 Information element definitions

```

InformationElements DEFINITIONS AUTOMATIC TAGS ::=

-- *****
--
-- CORE NETWORK INFORMATION ELEMENTS (10.3.1)
--
-- *****

DL-PhysChCapabilityFDD-v380ext ::= SEQUENCE {
    -- dummy is not used in this version of the specification, it should
    -- not be sent and if received it should be ignored.
    supportOfDedicatedPilotsForChEstimationdummy SupportOfDedicatedPilotsForChEstimation
    OPTIONAL
}

SupportOfDedicatedPilotsForChEstimation ::= ENUMERATED { true }

-- PhysicalChannelCapability-hspdsch-r5 describes the HS-PDSCH physical channel capability
PhysicalChannelCapability-hspdsch-r5 ::= SEQUENCE {
    fdd-hspdsch CHOICE {
        supported SEQUENCE {
            hsdSCH-physical-layer-category HSDSCH-physical-layer-category,
            -- dummy is not used in this version of the specification and
            -- it should be ignored by the receiver.
            supportOfDedicatedPilotsForChannelEstimationOfHSDSCHdummy BOOLEAN,
            -- simultaneousSCCPCH-DPCH-HSDSCH-Reception shall be true only if the
            -- IE SimultaneousSCCPCH-DPCH-Reception indicates support of simultaneous
            -- reception of S-CCPCH and DPCH
            simultaneousSCCPCH-DPCH-HSDSCH-Reception BOOLEAN
        },
        unsupported NULL
    },
    tdd384-hspdsch CHOICE {
        supported HSDSCH-physical-layer-category,
        unsupported NULL
    },
    tdd128-hspdsch CHOICE {
        supported HSDSCH-physical-layer-category,
        unsupported NULL
    }
}
    
```

11.5 RRC information between network nodes

```

DL-PhysChCapabilityFDD-r4 ::=          SEQUENCE {
    maxNoDPCH-PDSCH-Codes              INTEGER (1..8),
    maxNoPhysChBitsReceived            MaxNoPhysChBitsReceived,
    supportForSF-512                   BOOLEAN,
    supportOfPDSCH                     BOOLEAN,
    simultaneousSCCPCH-DPCH-Reception  SimultaneousSCCPCH-DPCH-Reception,
    supportOfDedicatedPilotsForChEstimation dummy SupportOfDedicatedPilotsForChEstimation
    OPTIONAL
}

DL-PhysChCapabilityFDD-r5 ::=          SEQUENCE {
    maxNoDPCH-PDSCH-Codes              INTEGER (1..8),
    maxNoPhysChBitsReceived            MaxNoPhysChBitsReceived,
    supportForSF-512                   BOOLEAN,
    supportOfPDSCH                     BOOLEAN,
    simultaneousSCCPCH-DPCH-Reception  SimultaneousSCCPCH-DPCH-Reception,
    supportOfDedicatedPilotsForChEstimation SupportOfDedicatedPilotsForChEstimation OPTIONAL,
    fdd-hspdsch                        CHOICE {
        supported                       SEQUENCE {
            hsdSCH-physical-layer-category HSDSCH-physical-layer-category,
            supportOfDedicatedPilotsForChannelEstimationOfHSDSCH dummy BOOLEAN,
            -- simultaneousSCCPCH-DPCH-HSDSCH-Reception shall be true only if the
            -- IE SimultaneousSCCPCH-DPCH-Reception indicates support of simultaneous
            -- reception of S-CCPCH and DPCH
            simultaneousSCCPCH-DPCH-HSDSCH-Reception BOOLEAN
        },
        unsupported                      NULL
    }
}

```