

TSG-RAN Working Group 1 meeting #9
Dresden, Germany
November 30 – December 3, 1999

TSGR1#9(99)k81

Agenda item: AH 16

Source: Ericsson

Title: CR 25.215-005r01: Physical channel BER on DPCCH

Document for: Decision

This is a revised version of R1-99i71. It was updated according to a measurement drafting setting during WG1#9.

The aim of this document is to incorporate one new measurement, Physical channel BER on DPCCH for UTRAN in TS 25.215.

During the WG1#8 meeting in New York document “R1-99g80 Physical channel BER on DPCCH in UTRA/FDD” was presented, proposing to introduce the Physical channel BER measured on DPCCH for UTRAN.

At the New York meeting support was given for the proposal. However, some concerns and questions on the measurement were also raised. These concerns and questions have now been addressed in offline discussions, so hopefully the measurement can be agreed at this meeting.

<h2 style="margin: 0;">CHANGE REQUEST</h2>		<i>Please see embedded help file at the bottom of this page for instructions on how to fill in this form correctly.</i>
25.215	CR 005r01	Current Version: 3.0.0
GSM (AA.BB) or 3G (AA.BBB) specification number ↑	↑ CR number as allocated by MCC support team	
For submission to: TSG-RAN #6 <i>list expected approval meeting # here ↑</i>	for approval <input checked="" type="checkbox"/> for information <input type="checkbox"/>	strategic <input type="checkbox"/> non-strategic <input type="checkbox"/> <small>(for SMG use only)</small>

Form: CR cover sheet, version 2 for 3GPP and SMG The latest version of this form is available from: <ftp://ftp.3gpp.org/Information/CR-Form-v2.doc>

Proposed change affects: (U)SIM ME UTRAN / Radio Core Network
(at least one should be marked with an X)

Source: Ericsson **Date:** 1999-12-03

Subject: Physical channel BER on DPCCH

Work item: _____

Category:	F Correction <input type="checkbox"/> A Corresponds to a correction in an earlier release <input type="checkbox"/> B Addition of feature <input checked="" type="checkbox"/> C Functional modification of feature <input type="checkbox"/> D Editorial modification <input type="checkbox"/>	Release:	Phase 2 <input type="checkbox"/> Release 96 <input type="checkbox"/> Release 97 <input type="checkbox"/> Release 98 <input type="checkbox"/> Release 99 <input checked="" type="checkbox"/> Release 00 <input type="checkbox"/>
------------------	--	-----------------	--

(only one category shall be marked with an X)

Reason for change: When no uplink data is sent on the uplink (uplink DTX) there will be periods where no physical channel BER on DPDCH or CRC for BLER calculation is available for the outer loop power control to adjust the SIR target. During DTX the control channel (DPCCH) is transmitted and it is possible to estimate the physical channel BER on the DPCCH. Since the DPDCH BER and DPCCH BER are correlated it will be possible to adjust the SIR target during DTX. This CR proposes the possibility to measure physical channel BER on DPCCH.

Clauses affected: 5.2.6 Physical channel BER

Other specs affected:	Other 3G core specifications <input type="checkbox"/> Other GSM core specifications <input type="checkbox"/> MS test specifications <input type="checkbox"/> BSS test specifications <input type="checkbox"/> O&M specifications <input type="checkbox"/>	→ List of CRs: → List of CRs: → List of CRs: → List of CRs: → List of CRs:
------------------------------	---	--

Other comments: _____



<----- double-click here for help and instructions on how to create a CR.

Column field	Comment
Definition	Contains the definition of the measurement.
Range/mapping	Gives the range and mapping to bits for the measurements quantity.

5.2.1 RSSI

Definition	Received Signal Strength Indicator, the wide-band received power within the UTRAN uplink carrier channel bandwidth in an UTRAN access point. The reference point for the RSSI measurements shall be the antenna connector.
Range/mapping	

5.2.2 SIR

Definition	Signal to Interference Ratio, is defined as the RSCP divided by the ISCP. Measurement shall be performed on the DPCCH after RL combination in Node B. The reference point for the SIR measurements shall be the antenna connector.
Range/mapping	

5.2.3 Transmitted carrier power

Definition	Transmitted carrier power, is the total transmitted power on one carrier from one UTRAN access point. Measurement shall be possible on any carrier transmitted from the UTRAN access point. The reference point for the total transmitted power measurement shall be the antenna connector. In case of Tx diversity the total transmitted power for each branch shall be measured.
Range/mapping	

5.2.4 Transmitted code power

Definition	Transmitted code power, is the transmitted power on one carrier, one scrambling code and one channelisation code. Measurement shall be possible on any channelisation code transmitted from the UTRAN access point. The reference point for the transmitted code power measurement shall be the antenna connector. In case of Tx diversity the transmitted code power for each branch shall be measured.
Range/mapping	

5.2.5 Transport channel BLER

Definition	Estimation of the transport channel block error rate (BLER). The BLER estimation shall be based on evaluating the CRC on each transport block. Measurement shall be possible to perform on any transport channel after RL combination in Node B. BLER estimation is only required for transport channels containing CRC.
Range/mapping	

5.2.6 Physical channel BER

Definition	<p>Type 1: Measured on the DPDCH: The physical channel BER is an estimation of the average bit error rate (BER) before channel decoding of the DPDCH data after RL combination in Node B.</p> <p>Type 2: Measured on the DPCCH: The Physical channel BER is an estimation of the average bit error rate (BER) on the DPCCH after RL combination in Node B.</p> <p>It shall be possible to report a physical channel BER estimate of type 1 or of type 2 or of both types at the end of each TTI for the transferred TrCh's, e.g. for TrCh's with a TTI of x ms a x ms averaged physical channel BER shall be possible to report every x ms.</p>
Range/mapping	