

CHANGE REQUEST				<small>Please see embedded help file at the bottom of this page for instructions on how to fill in this form correctly.</small>	
25.223		CR		Current Version: 3.3.0	
<small>GSM (AA.BB) or 3G (AA.BBB) specification number ↑</small>		xxx		<small>↑ CR number as allocated by MCC support team</small>	
For submission to:	RAN#10	for approval	<input checked="" type="checkbox"/>	strategic	<input type="checkbox"/>
<small>list expected approval meeting # here</small>	↑	for information	<input type="checkbox"/>	non-strategic	<input type="checkbox"/>
				<small>(for SMG use only)</small>	

Form: CR cover sheet, version 2 for 3GPP and SMG The latest version of this form is available from: <ftp://ftp.3gpp.org/Information/CR-Form-v2.doc>

Proposed change affects: (U)SIM ME UTRAN / Radio Core Network
(at least one should be marked with an X)

Source: CWTS **Date:** _____

Subject: CR for TS25.223 regarding 1.28 Mcps TDD

Work item: Low Chip Rate TDD option, Physical Layer

Category: <small>(only one category shall be marked with an X)</small>	F Correction	<input type="checkbox"/>	Release:	Phase 2	<input type="checkbox"/>
	A Corresponds to a correction in an earlier release	<input type="checkbox"/>		Release 96	<input type="checkbox"/>
	B Addition of feature	<input checked="" type="checkbox"/>		Release 97	<input type="checkbox"/>
	C Functional modification of feature	<input type="checkbox"/>		Release 98	<input type="checkbox"/>
	D Editorial modification	<input type="checkbox"/>		Release 99	<input type="checkbox"/>
				Release 00	<input checked="" type="checkbox"/>

Reason for change: This CR collects the principally agreed wording of the changes necessary for introducing the feature 'Low Chip Rate TDD option' in the TS25.223. In its last revision it should be editorially changed to reflect the correct changes needed for the latest approved version of this specification.

Clauses affected: _____

Other specs affected:	Other 3G core specifications	<input type="checkbox"/>	→ List of CRs:	_____
	Other GSM core specifications	<input type="checkbox"/>	→ List of CRs:	_____
	MS test specifications	<input type="checkbox"/>	→ List of CRs:	_____
	BSS test specifications	<input type="checkbox"/>	→ List of CRs:	_____
	O&M specifications	<input type="checkbox"/>	→ List of CRs:	_____

Other comments: In this first version, a proposed structure has been included in this CR. The structure was copied from TS25.223 vers. 3.3.0. In addition to that the proposals that were agreed in principle from WG1#14 to WG1#15 were included in this CR.



<----- double-click here for help and instructions on how to create a CR.

2 References

<For clarity, this chapter will currently collect only the references that are needed in addition to the already existing abbreviations. In its last version this chapter has to be modified, so that it includes the revisions with respect to the latest versions of TS25.223.>

3 Symbols and abbreviations

<For clarity, this chapter will currently collect only the symbols and abbreviations that are needed in addition to the already existing ones. In its last version this chapter has to be modified, so that it includes the revisions with respect to the latest versions of TS25.223.>

3.1 Symbols

3.2 Abbreviations

MIB Master Information Block

4 General

In the following, a separation between the data modulation and the spreading modulation has been made. The data modulation for 3.84Mcps TDD is defined in clause 5 'Data modulation for the 3.84 Mcps option', the data modulation for 1.28Mcps TDD is defined in clause 6 'Data modulation for the 1.28 Mcps option' and the spreading modulation in clause 67 'Spreading modulation'.

Table 1: Basic modulation parameters

Chip rate	same as FDD basic chiprate: 3.84 Mchip/s	Low chiprate: 1.28 Mchip/s
Data modulation	QPSK	QPSK, <u>8PSK</u>
Spreading characteristics	Orthogonal Q chips/symbol, where $Q = 2^p$, $0 \leq p \leq 4$	Orthogonal Q chips/symbol, where $Q = 2^p$, $0 \leq p \leq 4$

5 Data modulation for the 3.84 Mcps option

<No changes will be made in this chapter in this CR, only the title has to be changed. >

6 Data modulation for the 1.28 Mcps option

6.1 Symbol rate

The symbol duration T_S depends on the spreading factor Q and the chip duration T_C : $T_S = Q \times T_C$, where $T_C = \frac{1}{\text{chiprate}}$.

6.2 Mapping of bits onto signal point constellation

6.2.1 QPSK modulation

The mapping of bits onto the signal point constellation for QPSK modulation is the same like in the 3.84Mcps TDD cf. [5.2.1 Mapping for burst type 1 and 2].

6.2.2 8PSK modulation

The data modulation is performed to the bits from the output of the physical channel mapping procedure. In case of 8PSK modulation 3 consecutive binary bits are represented by one complex valued data symbol. Each user burst has two data carrying parts, termed data blocks:

$$\underline{d}^{(k,i)} = (d_1^{(k,i)}, d_2^{(k,i)}, \dots, d_{N_k}^{(k,i)})^T \quad i = 1, 2; k = 1, \dots, K. \quad (1)$$

N_k is the number of symbols per data field for the user k . This number is linked to the spreading factor Q_k .

Data block $\underline{d}^{(k,1)}$ is transmitted before the midamble and data block $\underline{d}^{(k,2)}$ after the midamble. Each of the N_k data symbols $d_n^{(k,i)}$; $i = 1, 2$; $k = 1, \dots, K$; $n = 1, \dots, N_k$; of equation 1 has the symbol duration $T_s^{(k)} = Q_k \cdot T_c$ as already given.

The data modulation is 8PSK, thus the data symbols $d_n^{(k,i)}$ are generated from 3 consecutive data bits from the output of the physical channel mapping procedure:

using the following mapping to complex symbols:

Consecutive binary bit pattern	complex symbol
$b_{1n}^{(k,i)} \quad b_{2n}^{(k,i)} \quad b_{3n}^{(k,i)}$	$d_n^{(k,i)}$
000	$\cos(11\pi/8) + j\sin(11\pi/8)$
001	$\cos(9\pi/8) + j\sin(9\pi/8)$
010	$\cos(5\pi/8) + j\sin(5\pi/8)$
011	$\cos(7\pi/8) + j\sin(7\pi/8)$
100	$\cos(13\pi/8) + j\sin(13\pi/8)$
101	$\cos(15\pi/8) + j\sin(15\pi/8)$
110	$\cos(3\pi/8) + j\sin(3\pi/8)$
111	$\cos(\pi/8) + j\sin(\pi/8)$

The mapping corresponds to a 8PSK modulation of the interleaved and encoded data bits $b_{l,n}^{(k,i)}$ of the table above and $d_n^{(k,i)}$ of equation 1.

67 Spreading modulation

<The numbering has to be changed. >

7.5 Modulation for the 3.84 Mcps option

<No changes will be made in this chapter in this CR, only the title and numbering have to be changed. >

7.6 Modulation for the 1.28 Mcps option

7.6.1 Combination of physical channels in uplink

7.6.2 Combination of physical channels in downlink

78 Synchronisation codes for the 3.84 Mcps option

<No changes will be made in this chapter in this CR, only the title and numbering have to be changed. >

9 Synchronisation codes for the 1.28 Mcps option

9.1 The downlink pilot timeslot (DwPTS)

The burst structure shown below is used in the DwPTS. It is composed of SYNC-DL codes of length 64 chips and a guard period of length 32 chips as shown in Figure below. The SYNC-DL code is not scrambled




Figure: The burst structure in DwPTS

There should be 32 different basic SYNC-DL codes for the whole system.

For the generation of the complex valued SYNC-DL codes of length 64, the basic binary SYNC-DL codes

$\mathbf{s} = (s_1, s_2, \dots, s_{64})$ of length 64 shown in Table A are used. The relation between the elements \underline{s} and \mathbf{s} is given by:

$$\underline{s}_i = (j)^i \cdot s_i \quad s_i \in \{1, -1\} \quad i=1, \dots, 64 \quad (1)$$

Hence, the elements \underline{s}_i of the complex SYNC-DL code $\underline{\mathbf{s}}$ are alternating real and imaginary.

The burst in the DwPTS is QPSK modulated and the phase of the SYNC-DL is used to signal the position of the MIB of the BCH in P-CCPCH in multi-frame.

9.2 The uplink pilot timeslot (UpPTS)

The burst in the UpPTS is composed of SYNC-UL codes of length 128 chips and a GP of length 32 chips as shown in Figure . The SYNC-UL code is not scrambled.




Figure Burst structure in UpPTS

There should be 256 different basic SYNC-UL codes (see Table B) for the whole system.

For the generation of the complex valued SYNC-UL codes of length 128, the basic binary SYNC-UL codes

$\mathbf{s} = (s_1, s_2, \dots, s_{128})$ of length 128 shown in Table B are used. The relation between the elements \underline{s} and \mathbf{s} is given by:

$$\underline{s}_i = (j)^i \cdot s_i \quad s_i \in \{1, -1\} \quad i=1, \dots, 128 \quad (2)$$

Hence, the elements \underline{s}_i of the complex SYNC-UL code \underline{s} are alternating real and imaginary.

9.3 Code Allocation

Relationship between the SYNC-DL and SYNC-UL sequences, the scrambling codes and the midamble codes

Code Group	Associated Codes			
	SYNC-DLID	SYNC-UL ID (coding criteria)	Scrambling Code ID (coding criteria)	Basic Midamble Code ID (coding criteria)
Group 1	0	0~7 (000~111)	0	0
			1	1
			2	2
			3	3
Group 2	1	8~15 (000~111)	4	4
			5	5
			6	6
			7	7

△ △ △				
<u>Group</u> <u>32</u>	<u>31</u>	<u>248~255</u> <u>(000~111)</u>	<u>124</u>	<u>124</u>
			<u>125</u>	<u>125</u>
			<u>126</u>	<u>126</u>
			<u>127</u>	<u>127</u>

Annex B (Normative) Synchronisation sequence

B.1 Basic SYNC-DL sequence

Table A Basic SYNC-DL Codes

<u>Code ID</u>	<u>SYNC-DL Codes of length 64</u>
<u>0</u>	<u>B3A7CC05A98688E4</u>
<u>1</u>	<u>9D559BD290606791</u>
<u>2</u>	<u>2CE7BA12A017C3A2</u>
<u>3</u>	<u>34511D20672F4712</u>
<u>4</u>	<u>9A772841474603F2</u>
<u>5</u>	<u>9109B1A5CE01F228</u>
<u>6</u>	<u>8FD429B3594501C0</u>
<u>7</u>	<u>25251354AA3F8C19</u>
<u>8</u>	<u>C9A3B8E0C043EA56</u>
<u>9</u>	<u>BA04B888E5BC1802</u>
<u>10</u>	<u>A735354299370207</u>
<u>11</u>	<u>74C3C8DA4415AE51</u>
<u>12</u>	<u>F4FD0458A0124663</u>
<u>13</u>	<u>A011D4E16C3D6064</u>
<u>14</u>	<u>BDA0661B0CAA8C68</u>
<u>15</u>	<u>8E31123F28928698</u>
<u>16</u>	<u>F095C1632E2906AB</u>
<u>17</u>	<u>B60B4A8A664071CF</u>
<u>18</u>	<u>AA094DCCE91E041A</u>
<u>19</u>	<u>C0C31CDA8A256807</u>
<u>20</u>	<u>D516964FB18C1890</u>
<u>21</u>	<u>30DE01834F4AACCE</u>
<u>22</u>	<u>8F700323BA5CAD34</u>
<u>23</u>	<u>1B50F4DEE0C1380C</u>
<u>24</u>	<u>443382164F56F2D1</u>
<u>25</u>	<u>E1E4005D49B846B4</u>

<u>26</u>	<u>040A97165330BFAA</u>
<u>27</u>	<u>C48E26881693AD78</u>
<u>28</u>	<u>D4354B2FE02361CC</u>
<u>29</u>	<u>5383AB6C8A10CE84</u>
<u>30</u>	<u>D417A730F2F12244</u>
<u>31</u>	<u>ABF0A0D905A939C4</u>

B.2 Basic SYNC-UL Codes

Table B Basic SYNC-UL Codes

<u>Code ID</u>	<u>SYNC-UL Codes of length 128</u>
<u>0</u>	<u>C11C20F0D1807DB8859175B798EC094A</u>
<u>1</u>	<u>91278068081EC8E74543DBC1C9AD4235</u>
<u>2</u>	<u>38F5AEE2E513DB12A663BA04160103E5</u>
<u>3</u>	<u>7AA8A0A210F12A1E4332F2EDD33011FC</u>
<u>4</u>	<u>C180EA3B9BA1774EB9611BD249C4A508</u>
<u>5</u>	<u>B072A2C839489D496B98CE9D0132FBC9</u>
<u>6</u>	<u>B2723EAC6EB01667F2B33961C8074234</u>
<u>7</u>	<u>C4144AD060F0EC095E227B92CF7C8280</u>
<u>8</u>	<u>653036A10D3054146FCF815986C63A14</u>
<u>9</u>	<u>F899CA61435D64DC07FDF04C4A0C053A</u>
<u>10</u>	<u>B56F2D6893A8051407F4C341D88DC7DC</u>
<u>11</u>	<u>DC0BE838242142EDE6413A72C88D74AA</u>
<u>12</u>	<u>22A2FD86E4086C70A4860B13C76E579F</u>
<u>13</u>	<u>A3CBC21322C97D2A02728E7875F39588</u>
<u>14</u>	<u>D4EC4F694A082CB38E3B1558A0FCC89F</u>
<u>15</u>	<u>CC891141C4E216D235C15CF5D3F9B002</u>
<u>16</u>	<u>A1993114C50B77CB0C0725D1E22FD016</u>
<u>17</u>	<u>24F73A979DE52F82E8800CCB93842A59</u>
<u>18</u>	<u>8F878FA04659842E294D8DEAB20BA2FD</u>
<u>19</u>	<u>AC90B0442D70662B028CF76A6BECDF09</u>
<u>20</u>	<u>D94A284DF64D7B0102F0E084C29C88C8</u>
<u>21</u>	<u>8603200C7596F24E865FD3815693358D</u>

<u>22</u>	<u>B466B12CF433642BD8B08F1F452E0550</u>
<u>23</u>	<u>86A3A1772C1C99FCA7DBBA0C312E34A0</u>
<u>24</u>	<u>622A1889F72A9A2C042D46F08EFEE1AC</u>
<u>25</u>	<u>BF220A362BC0D3B0D7CE400954C6CFAE</u>
<u>26</u>	<u>D28D73C52E89CF57905C502244F63616</u>
<u>27</u>	<u>AD4E1C2103697D64D8B9D4C035D90548</u>
<u>28</u>	<u>8F081A9BA12B6C6BD024531AA984D21C</u>
<u>29</u>	<u>E4092429BE82988E1E3585BF6A6AE550</u>
<u>30</u>	<u>08BD36E0A9C061782CB38B35B335CA56</u>
<u>31</u>	<u>1CDFF3CC2685D1C44F4A1059AB03F40A</u>
<u>32</u>	<u>506ED4E88FB1CECE3243F2A27A0221A4</u>
<u>33</u>	<u>846CF58A7AB613C83A24130B5778C0E2</u>
<u>34</u>	<u>A2711A99E26A0C75AC026F4CFAECE893</u>
<u>35</u>	<u>D846EEEBA2432AC05A01043C62579DCF</u>
<u>36</u>	<u>6B16B4E851CAF2121FC4CF88820C89E7</u>
<u>37</u>	<u>AA4889A78207674A74E10C6F2BE11D48</u>
<u>38</u>	<u>8534CF8145BC991052814ED5C72709EE</u>
<u>39</u>	<u>01AEF15D2290A84A607425746D9963C7</u>
<u>40</u>	<u>999188F758245D5164FE16D852942C71</u>
<u>41</u>	<u>CF71C008599287E446E30745BD56E2D2</u>
<u>42</u>	<u>248414BA0DF8CDC4711FE7C8707ED0AD</u>
<u>43</u>	<u>EB2E263EC016191C81AB714BFE4D2B30</u>
<u>44</u>	<u>862082A7482FAC1C499793A0D8CED670</u>
<u>45</u>	<u>DE2C22B2783AB75A7342608DE413840A</u>
<u>46</u>	<u>E31AA60B727F2CA2A78DAAC10665011D</u>
<u>47</u>	<u>CEF6CD06509870AC9E0177ACD550921D</u>
<u>48</u>	<u>E52C84D499FFCDC287581691471540F2</u>
<u>49</u>	<u>B33BF6551A4322504BEE0930BCA1EC68</u>
<u>50</u>	<u>555BE6886D0FC43D72315E6C6D384148</u>
<u>51</u>	<u>8444F67451EE23CE1240C90F0B52A492</u>
<u>52</u>	<u>5C290D28E84060E69D09788A261B10FF</u>
<u>53</u>	<u>337E0C35E83CD38CCC5D45804241F952</u>
<u>54</u>	<u>A7879F0D31A8982A01EE6AC4952984DC</u>

<u>55</u>	<u>A37F506508928C70A83D69A2373781B9</u>
<u>56</u>	<u>42F55208EE12909803A7CBEB19B5419E</u>
<u>57</u>	<u>57E5E268A328FCC9ED04B9E5420AC702</u>
<u>58</u>	<u>EB033AD1222F84D8642C4E3FAAD28206</u>
<u>59</u>	<u>98EE1415F026AC0E862C520451697DD0</u>
<u>60</u>	<u>6A0528AEA4B7CD6702660D81F8821E19</u>
<u>61</u>	<u>763D626A87C603BCB09E1A4C800A378F</u>
<u>62</u>	<u>EEA61897879289340C23F669D6A03762</u>
<u>63</u>	<u>A6571B3CC2D0E04F017ACC808B92DCE7</u>
<u>64</u>	<u>DDF88B52EA1831D293A803CF23C8C471</u>
<u>65</u>	<u>6CA4D333A2684140475DAB491F61C17A</u>
<u>66</u>	<u>A7D2AD23043989A13289F7C3E135580A</u>
<u>67</u>	<u>B1C752FA66B41C81904EDE27EA000E2E</u>
<u>68</u>	<u>8694BE3CC1CB36BE2A095F89CC619080</u>
<u>69</u>	<u>9C20334E1BBC596B25E151180BF99940</u>
<u>70</u>	<u>484256214F81070DD9C49A2B05A43DCE</u>
<u>71</u>	<u>401A20BCBE29B7438A7AEE44635A9E23</u>
<u>72</u>	<u>8858585C3239CBF628033FA0DF189378</u>
<u>73</u>	<u>EFA36404C1BA5118CC5F9052FD28D9C3</u>
<u>74</u>	<u>155609873D8A042D496E6477B747C4F8</u>
<u>75</u>	<u>8446077883A6D7D2549CC9742E3FD023</u>
<u>76</u>	<u>E630142B189AA209371A6F0FFDBC30A7</u>
<u>77</u>	<u>C46060535AC6DBB2095F1D7826D0CD5C</u>
<u>78</u>	<u>E00D19E48797148B28DEDA9D429362E2</u>
<u>79</u>	<u>645DE447E938485489416CAFCC1C571F</u>
<u>80</u>	<u>DA10AFBF2AE61C593A1D88584DE30598</u>
<u>81</u>	<u>BB248AEA5FD3FE210CD48FC401E1A686</u>
<u>82</u>	<u>A89F146BD9191F445301C081CB6F5625</u>
<u>83</u>	<u>15BBF04F247C59150208949EB6B9CC58</u>
<u>84</u>	<u>08F48BFA7804B5B2CC2E96510232E062</u>
<u>85</u>	<u>9AA2BE74005A3679C626B209580B8D03</u>
<u>86</u>	<u>9D40664A2C808F2F293E255398B37E6A</u>
<u>87</u>	<u>6869C98A8AAD81CAE41A23C83FF9EEA0</u>

88	576E8948E61BD0927C4140C3C04C4CF3
89	0F942C67A1137B6EAA058C2A74872C73
90	9D058E27ED546C10632684BBC84E5BC1
91	79D4B840E20148B134F90B51164BCBD0
92	0E35E1D8D1214C05FAC790B69B239150
93	FFA1BB0232CD71480BE5CA1C2A269F89
94	B2956F5F4E270446F9211584792628DB
95	F56CCA23421C8EC8F8A41F7DA4A41EA2
96	0B5ECA04F1789A7148C80C39D57D05F6
97	A10B538E8A8CFC8F8925C485F2A88660
98	9925C2C715001D9FC78ACCC51DA1AF34
99	0DAC9CFDEA40429A8B12C7D320D60F70
100	377FC9A097017958440914E83118E39D
101	8421096FA8B47E4E943B6473671955CC
102	574086183477C4F68540CB7E858263B1
103	895B6A8980C6703C779F49F40C5CFC19
104	D0D253E157BC19262150CEA668679E71
105	B8889C60EBA812BD7F0B6498823296D2
106	A13FB9F3A08528E44B13C12CF0D461AA
107	8D4DCFBE43D6E2024B1F8470224AA330
108	536D159E119E0893838657B12A074E64
109	DCFD49C504AD3A2F049A0CB70238EC8A
110	D363DB4C46C11757FA8FB18139789102
111	424A1E8A1D4DA256E4CA3BC8C2201BE3
112	417B619ED30FEB0A847CC3A191A20398
113	843FBBC95453C61786D1332612B45B4D
114	F26CACCC0732CF8ED0C5BC1462B1620B4
115	88E0FE440C70E9249A92A7AF94638880
116	99A52B7D8C950308057E0661D7459960
117	A5C28218BF5D16E63E42698A0A6B0896
118	B2763BEEC784A12E8C50778536921806
119	987B2B6A3A77A059B30A082457AB84E0
120	820DB500F1B206358D7A7F210AB85AA8

121	97760A5CFC5E03EB439C914590045938
122	896A720E8857C8708A59F8C94DE0841E
123	2D101F0CF95263843412577340DEBB11
124	E8E5214B4DCF5D11A245B0149D49C87C
125	51224EAA10099ACDE384834A5ADF03D8
126	64E51253554A230C186FDE4E8781BC09
127	A499E391E69ED08890AC1A82A6115BEC
128	EE54C6E1834210D3EC1B07A456B92AA8
129	949DB5CA82420B54C1E0BCC111E704D9
130	9439EE9A9E4C447D1AA350926495047F
131	AD095CC0E7438AECE38D60980B3F2D00
132	83089C254C5EE9788072BC3D9282F798
133	A27DC1A457BC5A56563D8A9B11203615
134	713053A9C0B1B08B14705FF5A7244DB4
135	D36D4B9F4007354E0EC1B0CA8C8C7124
136	82E7C990612114F1CCE1BD9509FD4386
137	C8D83FF0B48B14830D2015D53F8C0672
138	08AF223C869A36B169148FDDABB7D120
139	B6C284C600AD0A99F86C449F8F4C53A6
140	DC741B320C07682AF92AC4DBDE0C28C2
141	89B8D84FA902265850C0FA6FF0EB2C4F
142	A69445B3A52201DB984BC03D1956D7F3
143	0FE0F7224B7AD72E4D4530D0223F590C
144	1B8C06F051434048EB925133AD3BD3F9
145	E133D4C3C942726A351300C37E55D0DF
146	9E09481D1881A66F562D8B453BC83AB2
147	2397B04B60A3C5700907BDBBA4E818C8
148	8F81F7A08CC6C8DA3D692AD34F50C012
149	9AB325352981BCCFA072F8FDE3009221
150	4FA88B7F1F8A620C31B0D486C52AC2F6
151	097AF0ADD16D7D39851049F0130EE444
152	A5027732DACFF11C388D5820A4A9BA49
153	1CD981EA2EDB46218A407C7E20D4BE84

<u>154</u>	<u>D0FD94279FA67EC61A3904C0AD8ACA04</u>
<u>155</u>	<u>EA73A9415EC2004D49E9D0F645961C75</u>
<u>156</u>	<u>005AF0614A7552041194DEECBF8DD016</u>
<u>157</u>	<u>B514481533DA0A731705B93CF634E40D</u>
<u>158</u>	<u>983054521841A6E4FF34B2C07B5684FE</u>
<u>159</u>	<u>C46D927D0FD2B2F509550025677C6871</u>
<u>160</u>	<u>2AD85C08127487C87ECE014D65169102</u>
<u>161</u>	<u>0F617852FA3930AA7EE74B400B2CC831</u>
<u>162</u>	<u>AE9D395004C6E27540C378625D36E0D6</u>
<u>163</u>	<u>DC4FA55750F10B0636248F12C212FFE4</u>
<u>164</u>	<u>D3602B8D6CBF1809C88B827185631ECF</u>
<u>165</u>	<u>A94825850708E7723EA8F22C44BF78B2</u>
<u>166</u>	<u>A62D231C16AEFEF0B0026B306662945A</u>
<u>167</u>	<u>9C7BE810A86465A50551F89125D93B12</u>
<u>168</u>	<u>9712D9338B9CC60485C10172F50F121F</u>
<u>169</u>	<u>A3902CE0E0B9912591FF28C695728257</u>
<u>170</u>	<u>4167057891AB29473A9E0F67F3658921</u>
<u>171</u>	<u>B3368B91EC12A284BC414C8F0D7F8D20</u>
<u>172</u>	<u>EE21888101ABF06C1175828CB58B598D</u>
<u>173</u>	<u>E43923A00ECC32CCC2D162A4A44BD7F4</u>
<u>174</u>	<u>CC9E30B8538AD51703EEB6F70801AB22</u>
<u>175</u>	<u>B908AD2F1501DA1C156811736CD798CD</u>
<u>176</u>	<u>2B46302ACCC2F808797FC648A614326D</u>
<u>177</u>	<u>8A54494F1BE27235B8764023AA0FBCFA</u>
<u>178</u>	<u>BC1041E6F636421E89277DC154439103</u>
<u>179</u>	<u>275B39A63029B974E3561AE0A8FC8032</u>
<u>180</u>	<u>9283F6FE819B80492A22B85CE5CE5DC4</u>
<u>181</u>	<u>4CCB52C0CE058A78022C22DF5788CBCC</u>
<u>182</u>	<u>B0DF9608DE549A6F6C581516919A81E6</u>
<u>183</u>	<u>2CA185163CC36060D1E85BB0A7FBB988</u>
<u>184</u>	<u>66101D2846155CAC986FC790D2124EFC</u>
<u>185</u>	<u>8016E3904644D2093579B83BD7AB5071</u>
<u>186</u>	<u>531CAB7085BEC14257439658023647CF</u>

187	DF2910165AA5051E41F6EB198E4D491C
188	BA32052042B0FB2188DE7857DA1B6788
189	9E6D075AFF0EA4153615E140BF380666
190	9ACC5A037902534642A3BE391AA40F9B
191	4D741A3B4499843010D7E5FA8988DC80
192	FA1421C96EDC6092726154560B1C2FC8
193	882946076223CAE0B0BFE3EDA59826D5
194	CEBB288C28B7472A0D3917012276C034
195	BD35A6E00C9528DB38289CF823C34F30
196	E2C93618B6B2800D51171A5F85746A55
197	B43EF39A1A64F0E220AF740F9494291B
198	AC537817C2612744A58132A8AFBC44A3
199	98A321249A821DDBF81C38235A371A14
200	AE1D46069090D81BB6B08FED9E687285
201	7EAE2415DC2CD60AE083249A33B56E05
202	3D942AAA9BC9F27289421CE0B301FB98
203	1548BA6D08530727AC6D059C005C6C42
204	FF47C21142C65B502DA70647BAE831D1
205	C83AA7FEAC5E51A08091E10DB0C233D9
206	E86EDD2EC2DAA3104229EDC43471A16A
207	22FAFB9C184B78B56EE91B6602C03244
208	E45631DC509B1290C08D2C1A1F15DBFE
209	D203C51207092B56568FDAD9E2D44473
210	2AA87F31A7D1AB1C90024F936006C4A5
211	913136153593DEABC7305BF0C5A62180
212	D8DA5FE401F2758642A082C53A6A5CB8
213	23C2295213147F324DE8EC1C103BAE88
214	883AF097FCDE82B366A1844245E0D727
215	79E5E9F8C933159ACADC22A06F900A70
216	FE40502B44A9E44B2C336250D47538CC
217	670452E19172C843176F1278FE41D584
218	B7EAA436078E6886A3024F593AD57580
219	1044D4CDD7230E7B1953AD1232DF07E2

220	4D821ECAC3D845A2E1011695624576FF
221	96622ED2FBD44D1B859D70601999F438
222	CCC31C3D6D5B41B8D82FF4522A4C0146
223	4A84F7CD62E0C712980E6A0C89BF394F
224	10E56751F000927284DBE174E68ECC4C
225	A3DE70921356F026E084CFE302A210A9
226	B12DA0621B343A8C3FE941A32EA5D571
227	D653135DE825A74B743E275C19020C71
228	5CAD301BF846B2EE921D33A3D4BB1220
229	1292445ACBB548C668FC3853578474E6
230	B94B4B89C0654688C9E007D9061DF5FE
231	75A2C91E76061A8680884E8BFD14A64A
232	83726F3070B47ECE21504A5065D74A36
233	964A471444A270840919F7FE07382D14
234	A582701EBFCA899B8497088C3560F300
235	64FCB63E21CAC63002D1E09FD1543274
236	B1E1C83F689ADF422C865F98D288838A
237	A06A0D822165D3F3416B47419ECCB547
238	1D2068039A32B7EF728914ECE07CB416
239	64C0CF81F78E8823ECC8661A5295422A
240	902A7243F593F2180E5A306A8438E6A9
241	A4CCED356D56BF1B41C28E1504301FE8
242	82AE90E2F76B3055A2E3A966025CC01A
243	8B90D5A62364E18574145C5895CEFF60
244	43F7EA1AB0D19032551AD9DE21307353
245	DD5D8424AC60360B1C14E65815C9B15E
246	C632A67382ECB2681DFB8525140E2878
247	3A6ACF212B6F8B9C53FF224C2E00C16C
248	86A90C267B1171093F362FE5CB14E3A0
249	EA262EC36E6589C3BB005426AF2590F4
250	200F03126C5B0D7B901128E7757C5F70
251	68FC090C2221AA98BF0D24E85066EFC2
252	9E26CEC67832FC42A87E92FA1015212E

253	ACD889634F79506F2582EA03240F2A07
254	AA65407E1F4A33BF9A62860A3D6A4CC0
255	B1B950AC76A608AA32D04B03C7FF24D3